

Revision 5.1 [July, 2014]

Acknowledgements

The material contained herein is not a license, either expressly or impliedly, to any intellectual property owned or controlled by any of the authors or developers of this material or to any contribution thereto. The material contained herein is provided on an "AS IS" basis and, to the maximum extent permitted by applicable law, this information is provided AS IS AND WITH ALL FAULTS, and the authors and developers of this material hereby disclaim all other warranties and conditions, either express, implied or statutory, including, but not limited to, any (if any) implied warranties, duties or conditions of merchantability, of fitness for a particular purpose, of accuracy or completeness of responses, of results, of workmanlike effort, of lack of viruses and of lack of negligence, all with regard to this material and any contribution thereto. Designers must not rely on the absence or characteristics of any features or instructions marked "reserved" or "undefined." The Unified EFI Forum, Inc. reserves any features or instructions so marked for future definition and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to them. ALSO, THERE IS NO WARRANTY OR CONDITION OF TITLE, QUIET ENJOYMENT, QUIET POSSESSION, CORRESPONDENCE TO DESCRIPTION OR NON-INFRINGEMENT WITH REGARD TO THE SPECIFICATION AND ANY CONTRIBUTION THERETO.

IN NO EVENT WILL ANY AUTHOR OR DEVELOPER OF THIS MATERIAL OR ANY CONTRIBUTION THERETO BE LIABLE TO ANY OTHER PARTY FOR THE COST OF PROCURING SUBSTITUTE GOODS OR SERVICES, LOST PROFITS, LOSS OF USE, LOSS OF DATA, OR ANY INCIDENTAL, CONSEQUENTIAL, DIRECT, INDIRECT, OR SPECIAL DAMAGES WHETHER UNDER CONTRACT, TORT, WARRANTY, OR OTHERWISE, ARISING IN ANY WAY OUT OF THIS OR ANY OTHER AGREEMENT RELATING TO THIS DOCUMENT, WHETHER OR NOT SUCH PARTY HAD ADVANCE NOTICE OF THE POSSIBILITY OF SUCH DAMAGES.

Copyright 2014 Unified EFI, Inc. All Rights Reserved.

Revision History

Revision	Change Description	Affected Sections
	Unless otherwise noted the initial numbers in this column are Mantis ticket numbers	
5.1	1181 MADT GICC table definition is wrong	Table 5-61; 5.2.12.14
5.1	1180 FADT minor version byte length is wrong	5-34
5.1	1179 Errors in GTDT Section of 5.1 draft	5.2.24, 5.2.24.1;Table s 5-115, 5- 118, 5-121, 5- 122
5.1	1175 Bad section reference in ACPI 5.1	19.2.3
5.1	1164 Modifications to UEFI Forum ownership of PNP ID and ACPI ID Registry	6.1.5
5.1	1161 Misc typos in draft documents	5.2.1.6; 5.2.16.4;5.2.2 4;5.2.12.14; 5.2.24.1.1; Table 5- 74;Table 5- 115-116;Table 5-118-119; Table 5-61; 5- 61 8.4.5.1, 8.4.5.1.2.3 Table 6-162, Table 8-229; RM duplicates from 1123/ 1130:8.4.5.1.3 1.1
5.1	1160 ACPI 5.1 draft corrections related to _DSD (SEE 1126 BELOW)	6.2.5;Was Table 5-133 & 6-142 now >5-148 & 6- 157
5.1	1157 Reserve ACPI Low Power Idle Table Signature "LPIT"	Table 5-31
5.1	1155 Updates to M1133 MADT	Table 5-63, 5-64

Revision	Change Description	Affected Sections
5.1	1151 Bug in ASL example code	PRT3 code example following Figure 9-49
5.1	1149 GTDT changes for new GT Configurations	5.2.24, 5.24.1x
5.1	1136 Add a Notification Type for System Resource Affinity Change Event	Table 5-119 Device Object Notifications, new 17.2.2
5.1	1134 FADT changes for PSCI Support on ARM platforms	Table 5-34, 5- 36, New table 5-37
5.1	1135 PCC Doorbell Protocol for HW-Reduced Platforms	14.1.1, 14.1.2- 4, 14.2.1-2, 14.3-4
5.1	1133 MADT Updates for new GICs	5.2.12.15-17, Table 5-43, 5.2.12 table 5- 45, 5-60, 5-61, 5-63, 5-66
5.1	1131 Per-device Cache-coherency Attribute	6.2, 6.2.16; Was Table 6- 142>Table 6- 153
5.1	1126 Add _DSD Predefined Object "DeviceSpecific Data" properties	Was Table 5- 133 & 6-142 now>5-148 & 6-157
5.1	1123 CPPC Performance Feedback Counter Change 1130 CPPC2 [overlapping/duplicate tickets]	Tables 5-126, 8.4.5, 8.4.5.1x 8.4.5.1, 8.4.5.1.3.1-4; Was Table 8- 218>8-229
5.1	1116 Add x2APIC and GIC structure for _MAT method	6.2.10
5.0 B	1145 Support GICs in proximity domain	5.2.16 5.2. new section 16.4 new tables, 6.2.13 Table 5-65
5.0 B	1144 Fix the gap for Notify value description	5.6.6, new tables: Table 5-132, 5-133

Revision	Change Description	Affected Sections
5.0 B	1142 Error Source Notifications	18.3.2.6.2, 18.4, Table 18-290
5.0 B	1117 Move http://acpi.info/links.htm content to UEFI Forum Website	1.10, 5.2.4, 5.2.22.3, 5.2.24, 5.6.7,9.8.3.2, 13, 13.2.2 A.2.4, A.2.5; Tables 5-31, 5-60, 5-133
5.0 B	1113 Typos in ACPI 5.0a	Table 6-184
5.0 B	1148 Inconsistent BIX object description/example	Was Table 10- 234>10-250
5.0 B	1143 Typos in ACPI 5.0a	6.1.8, 8.4.1
5.0 B	1102 Clarify Use of GPE Block Devices in Hardware-Reduced ACPI	3.11.1, 4.1, 9.10
5.0 B	Mantis 1114 Lack of description on Bit 4 of _STA	6.3.7
5.0 A	Jira 51 incorrect type information	Table 19-322
5.0 A	Jira 50 Misspelling of "management"	3.10
5.0 A	Jira 49 Updated description of DerefOf to specify behavior when attempt is made to de-reference a reference (via Index) to a NULL (empty) package element.	19.5.29
5.0 A	Jira 48 Text changes to change PM Timer from required to optional	4.8.1.4, 4.8.2.1, 4.8.3.3, 5.2.9
5.0 A	Jira 46 Figure 5-29 is a printer killer	Fig 5-29
5.0 A	Jira 45 Typos in Figure 5-30	Fig 5-30
5.0 A	Jira 44 Link issues in table 5-133	Table 5-133
5.0 A	Jira 43 Invalid AddressSpaced keywords in example ASL code, orphan _REG	6.5.4
5.0 A	Jira 42 Serious bug in ASL example code for _OSC	6.2.10.4
5.0 A	Jira 41 Fix problems with PCC address space description	14.5
5.0 A	Jira 40 Issues with _GRT and _SRT Buffer description	9.18.3, 9.18.4
5.0 A	Jira 39 Clarification needed for _CST	Table 8-206
5.0 A	Jira 38 Incorrect field name in "Generic Register Descriptor".	6.4.3.7
5.0 A	Jira 37 Clarifications for _CPC method	8.4.5.1.2.1-2
5.0 A	Jira 36 Restore legality of module-level executable AML code.	19.1.3
5.0 A	Jira 35 ASL grammar: "UserTerm" is confusing	19.1
5.0 A	Jira 34 Description of _GTM has a bad line with very large font	9.8.2.1.1
5.0 A	Jira 33 Missing information in _CPC description	8.4.5.1
5.0 A	Jira3 2 Error in description of _REG method	6.5.4

Revision	Change Description	Affected Sections
5.0 A	Jira 31 Clarify length field for Serial resource descriptor	6.4.3.8.2 Table 6-190
5.0 A	Jira 30 Argument descriptions in incorrect order for resource descriptors	19.5.41,19.5.1 01
5.0 A	Jira 29 Issues with memory descriptors (grammar and macros)	19.1, 19.5
5.0 A	Jira 28 Problems with ASL grammar entry for DWordMemory	19.1.8
5.0 A	Jira 27 Problems with Unicode description for _MLS method	6.1.7
5.0 A	Jira 26 Incorrect grammar for "32-bits" and "64-bits"	throughout
5.0 A	Jira 25 Incorrect table reference in 19.2.5.4	19.2.5.4
5.0 A	Jira 24 Resource Descriptor tables formatting issues	6.4
5.0 A	Jira 23 Interrupt Descriptors: Wake bit should be split from Share bit	6.4
5.0 A	Jira 22 ASL grammar for ObjectType operator is incorrect	19.1.6
5.0 A	Jira 21 ASL grammar is missing description of type 6 opcodes	19.1.5
5.0 A	Jira 20 Problems with table 5-31 (reserved ACPI table signatures)	Table 5-31
5.0 A	Jira 19 Clarify description of _BQC method	B.5.4
5.0 A	Jira 18 Fix for EC OpRegion availability example	5.2.15
5.0 A	Jira 17 Clarify meaning of BGRT status field	Table 5-97
5.0 A	Jira 16 Correction to _DSM example	9.14.1
5.0 A	Jira 15 Clarify _DSM backward compatibility requirement and example	9.15.1
5.0 A	Jira 14 Description of _CPC is missing definition of unsupported optional registers	8.4.5.1
5.0 A	Jira 13 Incorrect _PLD name expansion	Table 5-133, 6.1.8
5.0 A	Jira 12 PLD description needs clarification	6.1.8
5.0 A	Jira 11 Errata forwarded from HP	5.2.24,5.6.5.3
5.0 A	Jira 10 More issues with ACPI table 5-133	Table 5-133
5.0 A	Jira 7 Error in QWordIO, ExtendedIO descriptions	19.5.41,19.5.1 01
5.0 A	Jira 6 Appendix A is now misnamed in ACPI 5.0	Appendix A
5.0 A	Jira 5 PARTIALNeed group agreementMethod _GTS and _BFS are unused, should be removed from ACPI spec.	7.3, 7.3.3, 16.1, 16.1.6-7, fig. 7-204
5.0 A	Jira 4 Table 5-133 - issues with _Sx methods	Table 5-133
5.0 A	Jira 3 Issues with predefined names table (table 5-133)	Table 5-133
5.0 A	Jira 2 Description of new sleep control register incorrect	Table 4-24
5.0 A	Jira 1 SystemCMOS keyword inconsistencies	Table 5-114, 5.5.2.4.1, 6.5.4 19.,5.96, 9.15.1 - 2, 19.5.96, 20.2.5.2

Revision	Change Description	Affected Sections
5.0 Dec. 2, 2011	Ptec-002	5.2.6
5.0	MSFT-020 Enumeration Power Controls	7.2.7, 7.2.12,
5.0	MSFT-019 GTDT table	5.2.24
5.0	MSFT_0018 Locking Targets from AML	5.7.5
5.0	MSFT-0017 PLD clarification for handhelf form factors	5.1.8
5.0	MSFT-0016 Extended GPIO-signaled Event Numbers	5.6.5.3
5.0	MSFT-0015 (0.1) D3 Cold Errata	7.2.1, 7.2.18 through 7.2.22
5.0	MSFT-0014	5.2.23
5.0	MSFT-0013_ADR for SIO	6.2
5.0	MSFT-0012 ROM (Get ROM Data)	5.6.6, 9.16
	MSFT-010 Reserved Table Signatures	5.2.6
5.0	MSFT-0009 (0.4)TimeAndAlarmDevice Modification	9.18
5.0	MSFT-0008 Collaborative Processor Performance Control	8.4.5
5.0	MSFT-0007 Platform Communications Channel added (new ch. 14)	Ch 14 (new)
5.0	MSFT-0007-0008 -Platform_Communication_Channel_and_CPPC_changes	(new) 14
5.0	MSFT-0006 SPB Abstraction	3.11.3, 5.5.2.4.5.x, 6.4.3.8.2, 6.5.8,18.1.3, 18.1.6, 18.1.7, 18.5.44, 18.5x,19.2.5.2
5.0	MSFT-0005 GPIO Abstraction	5.5.2.4.x,5.6, 5.6.5.x, 6.4.3, 6.3.8.x, 18.5.51, 18.5.52, 18.5.89
5.0	MSFT-0004 (0.2) Fixed DMA Descriptor	6.4.2.9, 18.5.50
5.0	MSFT-0003 Device identification	6.1, 6.1.3, 6.1.5, 6.1.6, 6.1.9
5.0	MSFT-0002 Interrupt Descriptors for Generic Interrupt Controller	5.2.11, 5.2.14-15

Revision	Change Description	Affected
		Sections
5.0	MSFT-0001 HW-reduced ACPI	3.11.x, 4,
		4.1.x, 4.3.7,
		5.2.9, 5.2.9.1,
		6.4.2.1,
		6.4.3.6, 7.2.11,
		7.3.4, 9.6, 12, 12.1, 12.6,
		12.11, 12.01,
		15, 15.1.x,
		15.3, 15.3.1.x,
		18.5.55,
		18.5.57
5.0	INTC-0014 Remove a line (reference) not needed	A.2.3
5.0	INTC-0013	
5.0	INTC-0012 fix AML opcode table	19.3
5.0	INTC-0011 fix table offsets	18.6.x (tables)
5.0	INTC-0010 Update Constant Descriptions	18.5.88,
		18.5.89,18.5.1
		04,18.5.136
5.0	INTC0009 RASF	5.2.20.x
5.0	INTC-008	5.2.6
5.0	INTC-006 Fixed Example	6.2.10.4
5.0	INTC-005 Update Package Description	18.5.92
5.0	INTC-004 Table Definition Language	20, 21.x
5.0	INTC-003 MPST	6.1, 6.1.3,
		6.1.5,6.1.6,
		6.1.9
5.0	INTC-002 EINJ	17.6.1, 17.6.3,
		17.6.5
5.0	INTC-001 (0.8) Firmware Performance Data Table (FPDT)	5.2.20.4,
		5.2.20.6
5.0	INTC-001 Firmware Performance Data Table (FPDT) (0.4)	5.2.19-
5.0	LID 0000 Additional Headonana For N. C. T.	5.2.20.6
5.0	HP-0002 Additional Hardware Error Notification Types	18.3.2.7
5.0	HP-0001 (0.2) BMC Requested Graceful Shutdown	5.6.5, 6.3.5
5.0	ACPI4.0 _DSM function 0 clarification	9.14.1
5.0	AMD-002 0.3 ROM (Get ROM Data)	B.3.3

Revision	Change Description	Affected
		Sections
4.0a	Errata corrected and clarifications added.	
Apr. 2010	Removed text concerning government requirement of mechanical off	2.2
	Clarified URL update document, Corrected section references for APIC,	5.2.6
	SLIT, SRAT in Table 5-5, Update URLs and reformated Table 5-6	
	Corrected reference to Interrupt Source Override Structure	5.2.12.4
	Corrected name for CPEP table	5.2.18
	Corrected reference to SMBus, should be IPMI	5.5.2.4.3.1
	Clarified BusCheck and DeviceCheck notifications in Table 5-53	5.6.5
	Added link to non-ACPI Plug and Play ID reference document	5.6.6
	Added missing _ATT and _GAI names, Corrected page/section references in Table 5-67	5.6.7
	Corrected EndTag name value. Was 0x78, correct value is 0x79 Table 6-33	6.4.2.8
	Consumer/Producer bit is ignored (Restored 2.0C change that had been lost)	6.4.3.5.1,2,3
	Clarified use of _GLK (Global Lock) object	6.5.7
	Corrected definition of _TSD object	8.4.3.4
	Corrected definition of _PSD object	8.4.4.5
	Corrected table name (CPEP)	8.4.5
	Corrected "maximum positive adjustment" value. Was 500%, correct value is	9.2.5
	50%, Updated description of example – 300 to 400 lux, Eliminated hardcoded	
	package lengths in examples, Changed "brightness" to "highest ambient light value"	
	Corrected reference to _IDE, should be _GTM. Corrected table reference	9.8.2.1.1
	Clarified GPE Block Device Description	9.10
	Corrected _PLD object examples	9.13
	Repaired diagram that would not display properly Figure 10-2	10.1.3.1
	Added missing _BCT method to Table 10-3	10.2.2
	Clarified that OEM Information field should contain NULL string if not supported in Table 10-4 &Table 10-5	10.2.1.1-2
	Corrected description of _BTM arguments and return value	10.2.2.8
	Clarified description of _BCT return value	10.2.2.9
	Corrected HID for Power Source device. Was ACPI0003, correct value is ACPI0004	10.3
	Corrected _PIF example. First package element was a Buffer, should be Integer, Clarified that OEM Information field should contain NULL string if not supported Table 10-10	10.3.3
	Corrected description of _SHL method Table 10-11	10.4
	Clarified _PRL return value, a list of References	10.3.4
	Corrected _PMC example. First package element was a Buffer, should be Integer	10.4.1
	Clarified that OEM Information field should contain NULL string if not supported Table 10-12	

Revision	Change Description	Affected Sections
	Removed "TODO" note. Updated example Repaired diagram that would not display properly Figure 15-1 Corrected error conditions from "fatal" to "corrected Corrected several incorrect section references, Clarified number of Generic Error Data Entry structures is >=1 (not Zero)	10.4.1 10.5 15.1 17.1
	Clarified number of Generic Error Data Entry structures is >=1 (not Zero) Added new section clarifying SCI notification for generic error sources Added new section describing Firmware First error handling Clarified purpose of the codes Table 17-17 Added reference to table of COMMAND_STATUS codes Table 17-23 Clarified purpose of the command status codes in Table 17-27 and the error type definitions in Table 17-28 Added _ATT resource descriptor field name Clarified rules for Buffer vs. Integer return types from a field unit Corrected section/page reference	17.1 17.3.1 17.3.2.6.1 17.3.2.6.2 17.4 17.5.1.1 17.6.1 17.6.3 18.1.8 18.5.44,89 18.5.101
4.0 June 2009	Major specification revision. Clock Domains, x2APIC Support, Logical Processor Idling, Corrected Platform Error Polling Table, Maximum System Characteristics Table, Power Metering and Budgeting, IPMI Operation Region, USB3 Support in _PLD, Re-evaluation of _PPC acknowledgement via _OST, Thermal Model Enhancements, _OSC at _SB, Wake Alarm Device, Battery Related Extensions, Memory Bandwidth Monitoring and Reporting, ACPI Hardware Error Interfaces, D3hot.	
3.0b Oct. 2006	Errata corrected and clarifications added.	
3.0a Dec. 2005	Errata corrected and clarifications added.	
3.0 Sept. 2004	Major specification revision. General configuration enhancements. Inter- Processor power, performance, and throttling state dependency support added. Support for > 256 processors added. NUMA Distancing support added. PCI Express support added. SATA support added. Ambient Light Sensor and User Presence device support added. Thermal model extended beyond processor-centric support.	
2.0c Aug. 2003	Errata corrected and clarifications added.	
2.0b Oct. 2002	Errata corrected and clarifications added.	
2.0a Mar. 2002	Errata corrected and clarifications added. ACPI 2.0 Errata Document Revision 1.0 through 1.5 integrated.	
ACPI 2.0 Errata Doc. Rev. 1.5	Errata corrected and clarifications added.	

Revision	Change Description	Affected Sections
ACPI 2.0 Errata Doc. Rev. 1.4	Errata corrected and clarifications added.	
ACPI 2.0 Errata Doc. Rev. 1.3	Errata corrected and clarifications added.	
ACPI 2.0 Errata Doc. Rev. 1.2	Errata corrected and clarifications added.	
ACPI 2.0 Errata Doc. Rev. 1.1	Errata corrected and clarifications added.	
ACPI 2.0 Errata Doc. Rev. 1.0	Errata corrected and clarifications added.	
2.0 Aug. 2000	Major specification revision. 64-bit addressing support added. Processor and device performance state support added. Numerous multiprocessor workstation and server-related enhancements. Consistency and readability enhancements throughout.	
1.0b Feb. 1999	Errata corrected and clarifications added. New interfaces added.	
1.0a Jul. 1998	Errata corrected and clarifications added. New interfaces added.	
1.0 Dec. 1996	Original Release.	

Contents

1		
	Introduction	1
	1.1 Principal Goals	1
	1.2 Power Management Rationale	
	1.3 Legacy Support	
	1.4 OEM Implementation Strategy	
	1.5 Power and Sleep Buttons	
	1.6 ACPI Specification and the Structure Of ACPI	
	1.7 OS and Platform Compliance	
	1.7.1 Platform Implementations of ACPI-defined Interfaces	
	1.7.2 OSPM Implementations	
	1.7.3 OS Requirements	
	1.8 Target Audience	
	1.9 Document Organization	
	1.9.1 ACPI Introduction and Overview	
	1.9.2 Programming Models	
	1.9.3 Implementation Details	
	1.9.4 Technical Reference	
	1.10 Related Documents	
_		
2	Definition of Torms	47
	Definition of Terms	
	2.1 General ACPI Terminology	
	2.2 Global System State Definitions	
	2.3 Device Power State Definitions	
	2.4 Sleeping State Definitions	
	2.5 Processor Power State Definitions	
	2.6 Device and Processor Performance State Definitions	29
3		
	ACPI Overview	31
	3.1 System Power Management	
	3.2 Power States	33
	3.2.1 Power Button	
	3.2.2 Platform Power Management Characteristics	
	3.3 Device Power Management	
	3.3.1 Power Management Standards	
	3.3.2 Device Power States	
	3.3.3 Device Power State Definitions	
	3.4 Controlling Device Power	
	3.4.1 Getting Device Power Capabilities	
	3.4.2 Setting Device Power States	
	3.4.3 Getting Device Power Status	

	3.4.4 Waking the Computer	39
	3.4.5 Example: Modem Device Power Management	39
	3.5 Processor Power Management	
	3.6 Device and Processor Performance States	43
	3.7 Configuration and "Plug and Play"	43
	3.7.1 Device Configuration Example: Configuring the Modem	44
	3.7.2 NUMA Nodes	
	3.8 System Events	44
	3.9 Battery Management	45
	3.9.1 Battery Communications	
	3.9.2 Battery Capacity	46
	3.9.3 Battery Gas Gauge	46
	3.9.4 Low Battery Levels	
	3.9.5 Battery Calibration	
	3.10 Thermal Management	
	3.10.1 Active and Passive Cooling Modes	
	3.10.2 Performance vs. Energy Conservation	
	3.10.3 Acoustics (Noise)	
	3.10.4 Multiple Thermal Zones	
	3.11 Flexible Platform Architecture Support	
	3.11.1 Hardware-reduced ACPI	
	3.11.2 Low-Power Idle	
	3.11.3 Connection Resources	
4	ACDI Handwara Chasification	
	ACPI Hardware Specification	
	4.1 Hardware-Reduced ACPI	
	4.1.1 Hardware-Reduced Events	
	4.2 Fixed Hardware Programming Model	
	4.3 Generic Hardware Programming Model	
	4.4 Diagram Legends	
	4.5 Register Bit Notation	
	4.6 The ACPI Hardware Model	
	4.6.1 Hardware Reserved Bits	
	4.6.2 Hardware Ignored Bits	
	4.6.3 Hardware Write-Only Bits	
	4.6.4 Cross Device Dependencies	
	4.7 ACPI Hardware Features	
	4.8 ACPI Register Model	
	4.8.1 ACPI Register Summary	
	4.8.2 Fixed Hardware Features	
	4.8.3 Fixed Hardware Registers	
	4.8.4 Generic Hardware Registers	91
5		
	ACPI Software Programming Model	99
	ACPI Software Programming Model 5.1 Overview of the System Description Table Architecture	
	ACPI Software Programming Model 5.1 Overview of the System Description Table Architecture	99

5.2 ACPI System Description Tables	102
5.2.1 Reserved Bits and Fields	103
5.2.2 Compatability	104
5.2.3 Address Format	104
5.2.4 Universal Uniform Identifiers (UUID)	
5.2.5 Root System Description Pointer (RSDP)	
5.2.6 System Description Table Header	
5.2.7 Root System Description Table (RSDT)	112
5.2.8 Extended System Description Table (XSDT)	
5.2.9 Fixed ACPI Description Table (FADT)	
5.2.10 Firmware ACPI Control Structure (FACS)	
5.2.11 Definition Blocks	
5.2.12 Multiple APIC Description Table (MADT)	
5.2.13 Global System Interrupts	
5.2.14 Smart Battery Table (SBST)	
5.2.15 Embedded Controller Boot Resources Table (ECDT)	
5.2.16 System Resource Affinity Table (SRAT)	
5.2.17 System Locality Distance Information Table (SLIT)	159
5.2.18 Corrected Platform Error Polling Table (CPEP)	160
5.2.19 Maximum System Characteristics Table (MSCT)	
5.2.20 ACPI RAS FeatureTable (RASF)	
5.2.21 Memory Power StateTable (MPST)	
5.2.22 Boot Graphics Resource Table (BGRT)	
5.2.23 Firmware Performance Data Table (FPDT)	
5.2.24 Generic Timer Description Table (GTDT)	
5.3 ACPI Namespace	
5.3.1 Predefined Root Namespaces	199
5.3.2 Objects	200
5.4 Definition Block Encoding	
5.5 Using the ACPI Control Method Source Language	202
5.5.1 ASL Statements	
5.5.2 Control Method Execution	204
5.6 ACPI Event Programming Model	226
5.6.1 ACPI Event Programming Model Components	226
5.6.2 Types of ACPI Events	227
5.6.3 Fixed Event Handling	
5.6.4 General-Purpose Event Handling	228
5.6.5 GPIO-signaled ACPI Events	
5.6.6 Device Object Notifications	235
5.6.7 Device Class-Specific Objects	240
5.6.8 Predefined ACPI Names for Objects, Methods, and Resources	242
5.7 Predefined Objects	
5.7.1 _GL (Global Lock Mutex)	
5.7.2 _OSI (Operating System Interfaces)	254
5.7.3 _OS (OS Name Object)	
5.7.4 _REV (Revision Data Object)	257
5.7.5 _DLM (DeviceLock Mutex)	258

	5.8 System Configuration Objects	259
	5.8.1 _PIC Method	259
6		
	Device Configuration	261
	6.1 Device Identification Objects	
	6.1.1 _ADR (Address)	
	6.1.2 CID (Compatible ID)	263
	6.1.3 CLS (Class Code)	
	6.1.4 DDN (DOS Device Name)	
	6.1.5 _HID (Hardware ID)	265
	6.1.6 _HRV (Hardware Revision)	265
	6.1.7 _MLS (Multiple Language String)	266
	6.1.8 PLD (Physical Location of Device)	267
	6.1.9 _SUB	274
	6.1.10 _STR (String)	275
	6.1.11 _SUN (Slot User Number)	275
	6.1.12 _UID (Unique ID)	
	6.2 Device Configuration Objects	276
	6.2.1 _CDM (Clock Domain)	
	6.2.2 _CRS (Current Resource Settings)	
	6.2.3 _DIS (Disable)	
	6.2.4 _DMA (Direct Memory Access)	
	6.2.5 _DSD (Device Specific Data)	
	6.2.6 _FIX (Fixed Register Resource Provider)	
	6.2.7 _GSB (Global System Interrupt Base)	
	6.2.8 _HPP (Hot Plug Parameters)	
	6.2.9 _HPX (Hot Plug Parameter Extensions)	
	6.2.10 _MAT (Multiple APIC Table Entry)	
	6.2.11 _OSC (Operating System Capabilities)	
	6.2.12 PRS (Possible Resource Settings)	
	6.2.13 _PRT (PCI Routing Table)	
	6.2.14 _PXM (Proximity)	
	6.2.15 _SLI (System Locality Information)	
	6.2.16 _SRS (Set Resource Settings)	
	6.2.17 _CCA (Cache Coherency Attribute)	
	6.3 Device Insertion, Removal, and Status Objects	
	6.3.1 _EDL (Eject Device List)	
	6.3.2 _EJD (Ejection Dependent Device)	
	6.3.3 _EJx (Eject)	
	6.3.4 _LCK (Lock)	
	6.3.5 _OST (OSPM Status Indication)	
	6.3.6 _RMV (Remove)	
	6.3.7 _STA (Status)	
	6.4 Resource Data Types for ACPI	
	6.4.1 ASL Macros for Resource Descriptors	
	6.4.2 Small Resource Data Type	

	6.4.3 Large Resource Data Type	331
	6.5 Other Objects and Control Methods	363
	6.5.1 _INI (Init)	363
	6.5.2 DCK (Dock)	
	6.5.3 BDN (BIOS Dock Name)	
	6.5.4 _REG (Region)	
	6.5.5 BBN (Base Bus Number)	
	6.5.6 _SEG (Segment)	
	6.5.7 GLK (Global Lock)	
	6.5.8 _DEP (Operation Region Dependencies)	
_	· · · · · · · · · · · · · · · · · · ·	
7		274
	Power and Performance Management	
	7.1 Declaring a Power Resource Object	
	7.1.1 Defined Child Objects for a Power Resource	
	7.1.2 _OFF	
	7.1.3 _ON	
	7.1.4 _STA (Status)	
	7.2 Device Power Management Objects	
	7.2.1 _DSW (Device Sleep Wake)	
	7.2.2 _PS0 (Power State 0)	
	7.2.3 _PS1 (Power State 1)	
	7.2.4 _PS2 (Power State 2)	
	7.2.5 _PS3 (Power State 3)	
	7.2.6 _PSC (Power State Current)	
	7.2.7 _PSE (Power State for Enumeration)	
	7.2.8 PR0 (Power Resources for D0)	
	7.2.9 PR1 (Power Resources for D1)	
	7.2.10 PR2 (Power Resources for D2)	
	7.2.11 PR3 (Power Resources for D3hot)	
	7.2.12 PRE (Power Resources for Enumeration)	
	7.2.13 PRW (Power Resources for Wake)	
	7.2.14 _PSW (Power State Wake)	
	7.2.15 _IRC (In Rush Current)	
	7.2.16 _S1D (S1 Device State)	
	7.2.17 _S2D (S2 Device State)	
	7.2.18 _S3D (S3 Device State)	383
	7.2.19 _S4D (S4 Device State)	
	7.2.20 _S0W (S0 Device Wake State)	385
	7.2.21 _S1W (S1 Device Wake State)	385
	7.2.22 _S2W (S2 Device Wake State)	
	7.2.23 _S3W (S3 Device Wake State)	386
	7.2.24 _S4W (S4 Device Wake State)	
	7.3 OEM-Supplied System-Level Control Methods	386
	7.3.1 _PTS (Prepare To Sleep)	
	7.3.2 System _Sx states	
	7.3.3 _SWS (System Wake Source)	

	7.3.4 _TTS (Transition To State)	394
	7.3.5 _WAK (System Wake)	394
	7.4 OSPM usage of _PTS, _TTS, and _WAK	395
8		
U	Processor Configuration and Control	397
	8.1 Processor Power States	
	8.1.1 Processor Power State Co	
	8.1.2 Processor Power State C1	
	8.1.3 Processor Power State C2	
	8.1.4 Processor Power State C3	
	8.1.5 Additional Processor Power States	
	8.2 Flushing Caches	
	8.3 Power, Performance, and Throttling State Dependencies	
	8.4 Declaring Processors	
	8.4.1 _PDC (Processor Driver Capabilities)	
	8.4.2 Processor Power State Control	
	8.4.3 Processor Throttling Controls	
	8.4.4 Processor Performance Control	
	8.4.5 Collaborative Processor Performance Control	
	8.4.6 _PPE (Polling for Platform Errors)	
	8.5 Processor Aggregator Device	
	8.5.1 Logical Processor Idling	
	8.5.2 OSPM _OST Evaluation	445
	-	_
9		_
9		
9	ACPI-Defined Devices and Device-Specific Objects	447
9	ACPI-Defined Devices and Device-Specific Objects	447 447
9	ACPI-Defined Devices and Device-Specific Objects	447 447 447
9	ACPI-Defined Devices and Device-Specific Objects	447 447 447
9	ACPI-Defined Devices and Device-Specific Objects	447 447 447 448
9	ACPI-Defined Devices and Device-Specific Objects	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 _SI System Indicators 9.1.1 _SST (System Status) 9.1.2 _MSG (Message) 9.1.3 _BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 \ SST (System Status) 9.1.2 \ MSG (Message) 9.1.3 \ BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \ ALI (Ambient Light Illuminance)	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 \ SST (System Status) 9.1.2 \ MSG (Message) 9.1.3 \ BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \ ALI (Ambient Light Illuminance) 9.2.3 \ ALT (Ambient Light Temperature)	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 \ SST (System Status) 9.1.2 \ MSG (Message) 9.1.3 \ BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \ ALI (Ambient Light Illuminance) 9.2.3 \ ALT (Ambient Light Temperature) 9.2.4 \ ALC (Ambient Light Color Chromaticity)	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 \ SST (System Status) 9.1.2 \ MSG (Message) 9.1.3 \ BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \ ALI (Ambient Light Illuminance) 9.2.3 \ ALT (Ambient Light Temperature) 9.2.4 \ ALC (Ambient Light Color Chromaticity) 9.2.5 \ ALR (Ambient Light Response)	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 \ SST (System Status) 9.1.2 \ MSG (Message) 9.1.3 \ BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \ ALI (Ambient Light Illuminance) 9.2.3 \ ALT (Ambient Light Temperature) 9.2.4 \ ALC (Ambient Light Color Chromaticity) 9.2.5 \ ALR (Ambient Light Response) 9.2.6 \ ALP (Ambient Light Polling)	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 \ SST (System Status) 9.1.2 \ MSG (Message) 9.1.3 \ BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \ ALI (Ambient Light Illuminance) 9.2.3 \ ALT (Ambient Light Temperature) 9.2.4 \ ALC (Ambient Light Color Chromaticity) 9.2.5 \ ALR (Ambient Light Response) 9.2.6 \ ALP (Ambient Light Polling) 9.2.7 Ambient Light Sensor Events	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 _SST (System Status) 9.1.2 _MSG (Message) 9.1.3 _BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 _ALI (Ambient Light Illuminance) 9.2.3 _ALT (Ambient Light Temperature) 9.2.4 _ALC (Ambient Light Color Chromaticity) 9.2.5 _ALR (Ambient Light Response) 9.2.6 _ALP (Ambient Light Polling) 9.2.7 Ambient Light Sensor Events 9.2.8 Relationship to Backlight Control Methods	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \subseteq SI System Indicators 9.1.1 _SST (System Status) 9.1.2 _MSG (Message) 9.1.3 _BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 _ALI (Ambient Light Illuminance) 9.2.3 _ALT (Ambient Light Temperature) 9.2.4 _ALC (Ambient Light Color Chromaticity) 9.2.5 _ALR (Ambient Light Response) 9.2.6 _ALP (Ambient Light Polling) 9.2.7 Ambient Light Sensor Events 9.2.8 Relationship to Backlight Control Methods 9.3 Battery Device	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \subseteq Stystem Indicators 9.1.1 \subseteq SST (System Status) 9.1.2 \subseteq MSG (Message) 9.1.3 \subseteq BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \subseteq ALI (Ambient Light Illuminance) 9.2.3 \subseteq ALT (Ambient Light Temperature) 9.2.4 \subseteq ALC (Ambient Light Color Chromaticity) 9.2.5 \subseteq ALR (Ambient Light Response) 9.2.6 \subseteq ALP (Ambient Light Polling) 9.2.7 Ambient Light Sensor Events 9.2.8 Relationship to Backlight Control Methods 9.3 Battery Device 9.4 Control Method Lid Device	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \subseteq System Indicators 9.1.1 \subseteq SST (System Status). 9.1.2 \subseteq MSG (Message). 9.1.3 \subseteq BLT (Battery Level Threshold). 9.2 Ambient Light Sensor Device. 9.2.1 Overview. 9.2.2 \subseteq ALI (Ambient Light Illuminance). 9.2.3 \subseteq ALT (Ambient Light Temperature). 9.2.4 \subseteq ALC (Ambient Light Color Chromaticity). 9.2.5 \subseteq ALR (Ambient Light Response). 9.2.6 \subseteq ALP (Ambient Light Polling). 9.2.7 Ambient Light Sensor Events. 9.2.8 Relationship to Backlight Control Methods. 9.3 Battery Device. 9.4 Control Method Lid Device. 9.4.1 \subseteq LID.	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 \ SST (System Status) 9.1.2 \ MSG (Message) 9.1.3 \ BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \ ALI (Ambient Light Illuminance) 9.2.3 \ ALT (Ambient Light Temperature) 9.2.4 \ ALC (Ambient Light Color Chromaticity) 9.2.5 \ ALR (Ambient Light Response) 9.2.6 \ ALP (Ambient Light Polling) 9.2.7 Ambient Light Sensor Events 9.2.8 Relationship to Backlight Control Methods 9.3 Battery Device 9.4 Control Method Lid Device 9.4.1 \ LID. 9.5 Control Method Power and Sleep Button Devices	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 \ SST (System Status) 9.1.2 \ MSG (Message) 9.1.3 \ BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \ ALI (Ambient Light Illuminance) 9.2.3 \ ALT (Ambient Light Temperature) 9.2.4 \ ALC (Ambient Light Color Chromaticity) 9.2.5 \ ALR (Ambient Light Response) 9.2.6 \ ALP (Ambient Light Polling) 9.2.7 Ambient Light Sensor Events 9.2.8 Relationship to Backlight Control Methods 9.3 Battery Device 9.4 Control Method Lid Device 9.4.1 \ LID 9.5 Control Method Power and Sleep Button Devices 9.6 Embedded Controller Device	
9	ACPI-Defined Devices and Device-Specific Objects. 9.1 \ SI System Indicators	
9	ACPI-Defined Devices and Device-Specific Objects 9.1 \ SI System Indicators 9.1.1 \ SST (System Status) 9.1.2 \ MSG (Message) 9.1.3 \ BLT (Battery Level Threshold) 9.2 Ambient Light Sensor Device 9.2.1 Overview 9.2.2 \ ALI (Ambient Light Illuminance) 9.2.3 \ ALT (Ambient Light Temperature) 9.2.4 \ ALC (Ambient Light Color Chromaticity) 9.2.5 \ ALR (Ambient Light Response) 9.2.6 \ ALP (Ambient Light Polling) 9.2.7 Ambient Light Sensor Events 9.2.8 Relationship to Backlight Control Methods 9.3 Battery Device 9.4 Control Method Lid Device 9.4.1 \ LID 9.5 Control Method Power and Sleep Button Devices 9.6 Embedded Controller Device	

	9.8.2 IDE Controller Device	459
	9.8.3 Serial ATA (SATA) Controller Device	462
	9.9 Floppy Controller Device Objects	464
	9.9.1 _FDE (Floppy Disk Enumerate)	464
	9.9.2 _FDI (Floppy Disk Information)	465
	9.9.3 _FDM (Floppy Disk Drive Mode)	466
	9.10 GPE Block Device	466
	9.10.1 Matching Control Methods for Events in a GPE Block Device	467
	9.11 Module Device	468
	9.12 Memory Devices	
	9.12.1 Address Decoding	
	9.12.2 Memory Bandwidth Monitoring and Reporting	
	9.12.3 _OSC Definition for Memory Device	
	9.12.4 Example: Memory Device	
	9.13 _UPC (USB Port Capabilities)	
	9.13.1 USB 2.0 Host Controllers and _UPC and _PLD	
	9.14 Device Object Name Collision	
	9.14.1 _DSM (Device Specific Method)	
	9.15 PC/AT RTC/CMOS Devices	
	9.15.1 PC/AT-compatible RTC/CMOS Devices (PNP0B00)	
	9.15.3 Dallas Semiconductor-compatible RTC/CMOS Devices (PNP0B02)	485
	9.16 User Presence Detection Device	
	9.16.1 _UPD (User Presence Detect)	
	9.16.2 _UPP (User Presence Polling)	
	9.16.3 User Presence Sensor Events	
	9.17 I/O APIC Device	
	9.18 Time and Alarm Device	
	9.18.2 _GCP (Get Capability)	
	9.18.3 _GRT (Get Real Time)	
	9.18.4 _SRT (Set Real Time)	
	9.18.5 _GWS (Get Wake alarm status)	
	9.18.6 _CWS (Clear Wake alarm status)	
	9.18.7 _STP (Set Expired Timer Wake Policy)	
	9.18.8 _STV (Set Timer Value)	
	9.18.9 _TIP (Expired Timer Wake Policy)	
	9.18.10 _TIV (Timer Values)	
	9.18.11 ACPI Wakeup Alarm Events	
	9.18.12 Relationship to Real Time Clock Alarm	
	9.18.13 Time and Alarm device as a replacement to the RTC	
	9.18.14 Relationship to UEFI time source	
	9.18.15 Example ASL code	497
10		
-	Power Source and Power Meter Devices	503
	10.1 Smart Battery Subsystems	
	10.1.1 ACPI Smart Battery Status Change Notification Requirements	
	10.1.2 Smart Battery Objects	

	10.1.3 _SBS (Smart Battery Subsystem)	508
	10.2 Control Method Batteries	
	10.2.1 Battery Events	511
	10.2.2 Battery Control Methods	511
	10.3 AC Adapters and Power Source Objects	524
	10.3.1 PSR (Power Source)	
	10.3.2 PCL (Power Consumer List)	525
	10.3.3 PIF (Power Source Information)	
	10.3.4 PRL (Power Source Redundancy List)	
	10.4 Power Meters	
	10.4.1 _PMC (Power Meter Capabilities)	527
	10.4.2 _PTP (Power Trip Points)	528
	10.4.3 _PMM (Power Meter Measurement)	529
	10.4.4 PAI (Power Averaging Interval)	
	10.4.5 _GAI (Get Averaging Interval)	530
	10.4.6 _SHL (Set Hardware Limit)	530
	10.4.7 _GHL (Get Hardware Limit)	531
	10.4.8 _PMD (Power Metered Devices)	
	10.5 Example: Power Source and Power Meter Namespace	531
11		
11	Thermal Management	522
	11.1 Thermal Control	
	11.1.1 Active, Passive, and Critical Policies	
	11.1.2 Dynamically Changing Cooling Temperature Trip Points	
	11.1.3 Detecting Temperature Changes	
	11.1.4 Active Cooling	
	11.1.5 Passive Cooling	
	11.1.6 Critical Shutdown	
	11.2 Cooling Preferences	
	11.2.1 Evaluating Thermal Device Lists	
	11.2.2 Evaluating Device Thermal Relationship Information	
	11.3 Fan Device	
	11.3.1 Fan Objects	
	11.4 Thermal Objects	
	11.4.1 _ACx (Active Cooling)	
	11.4.2 _ALx (Active List)	
	11.4.3 _ART (Active Cooling Relationship Table)	
	11.4.4 _CRT (Critical Temperature)	
	11.4.5 _DTI (Device Temperature Indication)	
	11.4.6 _HOT (Hot Temperature)	
	11.4.7 _NTT (Notification Temperature Threshold)	
	11.4.8 _PSL (Passive List)	
	11.4.9 _PSV (Passive)	
	11.4.10 _RTV (Relative Temperature Values)	
	11.4.11 _SCP (Set Cooling Policy)	
	11.4.12 _TC1 (Thermal Constant 1)	
	· · · · · · · · · · · · · · · · · ·	

	11.4.13 _TC2 (Thermal Constant 2)	557
	11.4.14 _TMP (Temperature)	558
	11.4.15 _TPT (Trip Point Temperature)	558
	11.4.16 _TRT (Thermal Relationship Table)	558
	11.4.17 _TSP (Thermal Sampling Period)	559
	11.4.18 _TST (Temperature Sensor Threshold)	559
	11.4.19 _TZD (Thermal Zone Devices)	560
	11.4.20 _TZM (Thermal Zone Member)	560
	11.4.21 _TZP (Thermal Zone Polling)	560
	11.5 Native OS Device Driver Thermal Interfaces	561
	11.6 Thermal Zone Interface Requirements	562
	11.7 Thermal Zone Examples	562
	11.7.1 Example: The Basic Thermal Zone	562
	11.7.2 Example: Multiple-Speed Fans	564
	11.7.3 Example: Thermal Zone with Multiple Devices	566
12		
1 4	ACPI Embedded Controller Interface Specification	573
	12.1 Embedded Controller Interface Description	
	12.2 Embedded Controller Register Descriptions	
	12.2.1 Embedded Controller Status, EC_SC (R)	
	12.2.2 Embedded Controller Command, EC_SC (W)	
	12.2.3 Embedded Controller Data, EC_DATA (R/W)	
	12.3 Embedded Controller Command Set	
	12.3.1 Read Embedded Controller, RD_EC (0x80)	
	12.3.2 Write Embedded Controller, WR_EC (0x81)	
	12.3.3 Burst Enable Embedded Controller, BE_EC (0x82)	
	12.3.4 Burst Disable Embedded Controller, BD_EC (0x83)	
	12.3.5 Query Embedded Controller, QR_EC (0x84)	
	12.4 SMBus Host Controller Notification Header (Optional), OS_SMB_EVT	
	12.5 Embedded Controller Firmware	
	12.6 Interrupt Model	
	12.6.1 Event Interrupt Model	
	12.6.2 Command Interrupt Model	
	12.7 Embedded Controller Interfacing Algorithms	
	12.8 Embedded Controller Description Information	
	12.9 SMBus Host Controller Interface via Embedded Controller	
	12.9.1 Register Description	584
	12.9.2 Protocol Description	
	12.10 SMBus Devices	
	12.10.1 SMBus Device Access Restrictions	
	12.10.2 SMBus Device Command Access Restriction	
	12.11 Defining an Embedded Controller Device in ACPI Namespace	
	12.11.1 Example: EC Definition ASL Code	
	12.12 Defining an EC SMBus Host Controller in ACPI Namespace	596
	12.12.1 Example: EC SMBus Host Controller ASL-Code	

13		EOC
	ACPI System Management Bus Interface Specification	
	13.1.1 SMBus Slave Addresses	
	13.1.2 SMBus Protocols	
	13.1.3 SMBus Status Codes	
	13.1.4 SMBus Command Values	
	13.2 Accessing the SMBus from ASL Code	
	13.2.1 Declaring SMBus Host Controller Objects	
	13.2.2 Declaring SMBus Devices	
	13.2.3 Declaring SMBus Operation Regions	
	13.2.4 Declaring SMBus Fields	604
	13.2.5 Declaring and Using an SMBus Data Buffer	
	13.3 Using the SMBus Protocols	
	13.3.1 Read/Write Quick (SMBQuick)	
	13.3.2 Send/Receive Byte (SMBSendReceive)	
	13.3.3 Read/Write Byte (SMBByte)	
	13.3.4 Read/Write Word (SMBWord)	
	13.3.5 Read/Write Block (SMBBlock)	
	13.3.6 Word Process Call (SMBProcessCall)	
	13.3.7 Block Process Call (SMBBlockProcessCall)	
14		
	Platform Communications Channel (PCC)	613
	14.1 Platform Communications Channel Table	
	14.1.1 Platform Communications Channel Global Flags	
	14.1.2 Platform Communications Channel Subspace Structures	
	14.1.3 Generic Communications Subspace Structure (type 0)	
	14.1.4 HW-Reduced Communications Subspace Structure (type 1)	
	14.2 Generic Communications Channel Shared Memory Region	
	14.2.1 Generic Communications Channel Command Field	
	14.2.2 Generic Communications Channel Status Field	617
	14.3 Doorbell Protocol	617
	14.4 Platform Notification	618
	14.5 Referencing the PCC address space	618
15		
	System Address Map Interfaces	621
	15.1 INT 15H, E820H - Query System Address Map	
	15.2 E820 Assumptions and Limitations	
	15.3 UEFI GetMemoryMap() Boot Services Function	
	15.4 UEFI Assumptions and Limitations	
	15.5 Example Address Map	
	15.6 Example: Operating System Usage	
16		
. •	Waking and Sleeping	629
	16.1 Sleeping States	
	. •	

	16.1.1 S1 Sleeping State	633
	16.1.2 S2 Sleeping State	634
	16.1.3 S3 Sleeping State	
	16.1.4 S4 Sleeping State	
	16.1.5 S5 Soft Off State	
	16.1.6 Transitioning from the Working to the Sleeping State	
	16.1.7 Transitioning from the Working to the Soft Off State	
	16.2 Flushing Caches	
	16.3 Initialization	
	16.3.1 Placing the System in ACPI Mode	
	16.3.2 BIOS Initialization of Memory	
	16.3.3 OS Loading	
	16.3.4 Exiting ACPI Mode	
. –	5	
17		647
	Non-Uniform Memory Access (NUMA) Architecture Platforms	
	17.1 NUMA Node	
	17.2 System Locality	
	17.2.1 System Resource Affinity Table Definition	
	17.2.2 System Resource Affinity Update	
	17.3 System Locality Distance Information	
	17.3.1 Online Hot Plug	
	17.3.2 Impact to Existing Localities	649
18		
	ACPI Platform Error Interfaces (APEI)	054
	/\cdr \cdr \cdr \cdr \cdr \cdr \cdr \cdr	651
	18.2 Relationship between OSPM and System Firmware	
		652
	18.2 Relationship between OSPM and System Firmware	652 652
	18.2 Relationship between OSPM and System Firmware	652 652 652
	18.2 Relationship between OSPM and System Firmware	652 652 652 654
	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.3.2 ACPI Error Source 18.4 Firmware First Error Handling	652 652 652 654
	18.2 Relationship between OSPM and System Firmware	652 652 654 667
	18.2 Relationship between OSPM and System Firmware	652 652 654 667 668
	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.3.2 ACPI Error Source 18.4 Firmware First Error Handling 18.4.1 Example: Firmware First Handling Using NMI Notification 18.5 Error Serialization 18.5.1 Serialization Action Table	652 652 654 667 668 668
	18.2 Relationship between OSPM and System Firmware	652 652 654 667 668 669 675
	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.3.2 ACPI Error Source 18.4 Firmware First Error Handling 18.4.1 Example: Firmware First Handling Using NMI Notification 18.5 Error Serialization 18.5.1 Serialization Action Table	652 652 654 667 668 669 679
	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.3.2 ACPI Error Source 18.4 Firmware First Error Handling 18.4.1 Example: Firmware First Handling Using NMI Notification 18.5 Error Serialization 18.5.1 Serialization Action Table 18.5.2 Operations 18.6 Error Injection	
	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.3.2 ACPI Error Source 18.4 Firmware First Error Handling 18.4.1 Example: Firmware First Handling Using NMI Notification 18.5 Error Serialization 18.5.1 Serialization Action Table 18.5.2 Operations. 18.6 Error Injection 18.6.1 Error Injection Table (EINJ).	
	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.3.2 ACPI Error Source 18.4 Firmware First Error Handling 18.4.1 Example: Firmware First Handling Using NMI Notification 18.5 Error Serialization 18.5.1 Serialization Action Table 18.5.2 Operations 18.6 Error Injection 18.6.1 Error Injection Table (EINJ) 18.6.2 Injection Instruction Entries	
	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.4 Firmware First Error Handling 18.4.1 Example: Firmware First Handling Using NMI Notification 18.5 Error Serialization 18.5.1 Serialization Action Table 18.6.2 Operations. 18.6.1 Error Injection Table (EINJ) 18.6.2 Injection Instruction Entries 18.6.3 Injection Instructions 18.6.4 Trigger Action Table.	
19	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.3.2 ACPI Error Source 18.4 Firmware First Error Handling 18.4.1 Example: Firmware First Handling Using NMI Notification 18.5 Error Serialization 18.5.1 Serialization Action Table 18.5.2 Operations 18.6 Error Injection 18.6.1 Error Injection Table (EINJ) 18.6.2 Injection Instruction Entries 18.6.3 Injection Instructions 18.6.4 Trigger Action Table	
19	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.3.2 ACPI Error Source 18.4 Firmware First Error Handling 18.4.1 Example: Firmware First Handling Using NMI Notification 18.5 Error Serialization 18.5.1 Serialization Action Table 18.5.2 Operations. 18.6 Error Injection 18.6.1 Error Injection Table (EINJ) 18.6.2 Injection Instruction Entries 18.6.3 Injection Instructions 18.6.4 Trigger Action Table. ACPI Source Language (ASL)Reference	652652654667668669679679683683
19	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery 18.3.1 Boot Error Source 18.3.2 ACPI Error Source 18.4 Firmware First Error Handling 18.4.1 Example: Firmware First Handling Using NMI Notification 18.5 Error Serialization 18.5.1 Serialization Action Table 18.5.2 Operations. 18.6 Error Injection 18.6.1 Error Injection Table (EINJ) 18.6.2 Injection Instruction Entries 18.6.3 Injection Instructions 18.6.4 Trigger Action Table. ACPI Source Language (ASL)Reference 19.1 ASL Language Grammar	652652654667668669679679683685
19	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery	652652654667668669679682683685
19	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery	652652654667668669679683685689689
19	18.2 Relationship between OSPM and System Firmware 18.3 Error Source Discovery	652652654667668669679679683683685689691

19.1.5 ASL Opcode Terms	695
19.1.6 ASL Primary (Terminal) Terms	696
19.1.7 ASL Parameter Keyword Terms	707
19.1.8 ASL Resource Template Terms	709
19.2 ASL Concepts	716
19.2.1 ASL Names	
19.2.2 ASL Literal Constants	716
19.2.3 ASL Resource Templates	718
19.2.4 ASL Macros	
19.2.5 ASL Data Types	720
19.3 ASL Operator Summary	
19.4 ASL Operator Summary By Type	
19.5 ASL Operator Reference	
19.5.1 AccessAs (Change Field Unit Access)	
19.5.2 Acquire (Acquire a Mutex)	
19.5.3 Add (Integer Add)	
19.5.4 Alias (Declare Name Alias)	
19.5.5 And (Integer Bitwise And)	
19.5.6 Argx (Method Argument Data Objects)	
19.5.7 BankField (Declare Bank/Data Field)	
19.5.8 Break (Break from While)	
19.5.9 BreakPoint (Execution Break Point)	
19.5.10 Buffer (Declare Buffer Object)	
19.5.11 Case (Expression for Conditional Execution)	
19.5.12 Concatenate (Concatenate Data)	
19.5.13 ConcatenateResTemplate (Concatenate Resource Templates)	
19.5.14 CondRefOf (Create Object Reference Conditionally)	
19.5.15 Connection (Declare Field Connection Attributes)	
19.5.16 Continue (Continue Innermost Enclosing While)	
19.5.17 CopyObject (Copy and Store Object)	
19.5.18 CreateBitField (Create 1-Bit Buffer Field)	
19.5.19 CreateByteField (Create 8-Bit Buffer Field)	
19.5.20 CreateDWordField (Create 32-Bit Buffer Field)	
19.5.21 CreateField (Create Arbitrary Length Buffer Field)	
19.5.22 CreateQWordField (Create 64-Bit Buffer Field)	
19.5.23 CreateWordField (Create 16-Bit Buffer Field)	
19.5.24 DataTableRegion (Create Data Table Operation Region)	
19.5.25 Debug (Debugger Output)	
19.5.26 Decrement (Integer Decrement)	
19.5.27 Default (Default Execution Path in Switch)	751
19.5.28 DefinitionBlock (Declare Definition Block)	
19.5.29 DerefOf (Dereference an Object Reference)	
19.5.30 Device (Declare Bus/Device Package)	
19.5.31 Divide (Înteger Divide)	
19.5.32 DMA (DMA Resource Descriptor Macro)	
19.5.33 DWordIO (DWord IO Resource Descriptor Macro)	
19.5.34 DWordMemory (DWord Memory Resource Descriptor Macro)	

19.5.35 DWordSpace (DWord Space Resource Descriptor Macro)	. 758
19.5.36 EISAID (EISA ID String To Integer Conversion Macro)	. 759
19.5.37 Else (Alternate Execution)	. 760
19.5.38 Elself (Alternate/Conditional Execution)	
19.5.39 EndDependentFn (End Dependent Function Resource Descriptor Macro)	. 761
19.5.40 Event (Declare Event Synchronization Object)	
19.5.41 ExtendedIO (Extended IO Resource Descriptor Macro)	. 762
19.5.42 ExtendedMemory (Extended Memory Resource Descriptor Macro)	
19.5.43 ExtendedSpace (Extended Address Space Resource Descriptor Macro)	. 765
19.5.44 External (Declare External Objects)	. 767
19.5.45 Fatal (Fatal Error Check)	
19.5.46 Field (Declare Field Objects)	
19.5.47 FindSetLeftBit (Find First Set Left Bit)	
19.5.48 FindSetRightBit (Find First Set Right Bit)	
19.5.49 FixedDMA (DMA Resource Descriptor Macro)	
19.5.50 FixedIO (Fixed IO Resource Descriptor Macro)	
19.5.51 FromBCD (Convert BCD To Integer)	
19.5.52 Function (Declare Control Method)	
19.5.53 GpioInt (GPIO Interrupt Connection Resource Descriptor Macro)	
19.5.54 Gpiolo (GPIO Connection IO Resource Descriptor Macro)	
19.5.55 I2CSerialBus (I2C Serial Bus Connection Resource Descriptor Macro)	
19.5.56 If (Conditional Execution)	
19.5.57 Include (Include Additional ASL File)	
19.5.58 Increment (Integer Increment)	
19.5.59 Index (Indexed Reference To Member Object)	
19.5.60 IndexField (Declare Index/Data Fields)	
19.5.61 Interrupt (Interrupt Resource Descriptor Macro)	
19.5.62 IO (IO Resource Descriptor Macro)	
19.5.63 IRQ (Interrupt Resource Descriptor Macro)	
19.5.64 IRQNoFlags (Interrupt Resource Descriptor Macro)	. 784
19.5.65 LAnd (Logical And)	
19.5.66 LEqual (Logical Equal)	
19.5.67 LGreater (Logical Greater)	
19.5.68 LGreaterEqual (Logical Greater Than Or Equal)	
	. 785
19.5.70 LLessEqual (Logical Less Than Or Equal)	
19.5.71 LNot (Logical Not)	. 786
19.5.72 LNotEqual (Logical Not Equal))	
19.5.73 Load (Load Definition Block)	
19.5.74 LoadTable (Load Definition Block From XSDT)	
19.5.75 Localx (Method Local Data Objects)	
19.5.76 LOr (Logical Or)	. 789
19.5.77 Match (Find Object Match)	700
19.5.78 Memory24 (Memory Resource Descriptor Macro)	
19.5.79 Memory32 (Memory Resource Descriptor Macro)	
19.5.80 Memory32Fixed (Memory Resource Descriptor Macro)	
19.5.81 Method (Declare Control Method)	. 192

19.5.82 Mid (Extract Portion of Buffer or String)	. 794
19.5.83 Mod (Integer Modulo)	
19.5.84 Multiply (Integer Multiply)	
19.5.85 Mutex (Declare Synchronization/Mutex Object)	. 795
19.5.86 Name (Declare Named Object)	
19.5.87 NAnd (Integer Bitwise Nand)	. 796
19.5.88 NoOp Code (No Operation)	. 796
19.5.89 NOr (Integer Bitwise Nor)	. 797
19.5.90 Not (Integer Bitwise Not)	
19.5.91 Notify (Notify Object of Event)	
19.5.92 Offset (Change Current Field Unit Offset)	
19.5.93 ObjectType (Get Object Type)	
19.5.94 One (Constant One Integer)	
19.5.95 Ones (Constant Ones Integer)	
19.5.96 OperationRegion (Declare Operation Region)	
19.5.97 Or (Integer Bitwise Or)	
19.5.98 Package (Declare Package Object)	
19.5.99 PowerResource (Declare Power Resource)	
19.5.100 Processor (Declare Processor)	
19.5.101 QWordIO (QWord IO Resource Descriptor Macro)	
19.5.102 QWordMemory (QWord Memory Resource Descriptor Macro)	
19.5.103 QWordSpace (QWord Space Resource Descriptor Macro)	
19.5.104 RawDataBuffer	
19.5.105 RefOf (Create Object Reference)	
19.5.106 Register (Generic Register Resource Descriptor Macro)	
19.5.107 Release (Release a Mutex Synchronization Object)	
19.5.108 Reset (Reset an Event Synchronization Object)	
19.5.109 ResourceTemplate (Resource To Buffer Conversion Macro)	
19.5.110 Return (Return from Method Execution)	
19.5.111 Revision (Constant Revision Integer)	
19.5.112 Scope (Open Named Scope)	
19.5.113 ShiftLeft (Integer Shift Left)	
19.5.114 ShiftRight (Integer Shift Right)	
19.5.115 Signal (Signal a Synchronization Event)	
19.5.116 SizeOf (Get Data Object Size)	
19.5.117 Sleep (Milliseconds Sleep)	
19.5.118 SPISerialBus (SPI Serial Bus Connection Resource Descriptor Macro)	
19.5.119 Stall (Stall for a Short Time)	. 816
19.5.120 StartDependentFn (Start Dependent Function Resource Descriptor Macro	ວ)
816 10.5.121 Start Dependent En No Pri (Start Dependent Function Resource Descriptor	
19.5.121 StartDependentFnNoPri (Start Dependent Function Resource Descriptor	
Macro)	
19.5.122 Store (Store an Object)	/O۱ . مهو
19.5.123 Subtract (Integer Subtract)	
19.5.124 Switch (Select Code To Execute Based On Expression)	
19.5.125 ThermalZone (Declare Thermal Zone)	. o∠U
19.5.126 Timer (Get 64-Bit Timer Value)	. o∠∪

	19.5.127 ToBCD (Convert Integer to BCD)	821
	19.5.128 ToBuffer (Convert Data to Buffer)	
	19.5.129 ToDecimalString (Convert Data to Decimal String)	
	19.5.130 ToHexString (Convert Data to Hexadecimal String)	822
	19.5.131 ToInteger (Convert Data to Integer)	822
	19.5.132 ToString (Convert Buffer To String)	823
	19.5.133 ToUUID (Convert String to UUID Macro)	
	19.5.134 UARTSerialBus (UART Serial Bus Connection Resource Descriptor N 824	lacro)
	19.5.135 Unicode (String To Unicode Conversion Macro)	
	19.5.136 Unload (Unload Definition Block)	
	19.5.137 VendorLong (Long Vendor Resource Descriptor)	
	19.5.138 VendorShort (Short Vendor Resource Descriptor)	
	19.5.139 Wait (Wait for a Synchronization Event)	
	19.5.140 While (Conditional Loop)	
	19.5.141 WordBusNumber (Word Bus Number Resource Descriptor Macro)	
	19.5.142 WordIO (Word IO Resource Descriptor Macro)	
	19.5.143 WordSpace (Word Space Resource Descriptor Macro))	
	19.5.144 XOr (Integer Bitwise Xor)	
	19.5.145 Zero (Constant Zero Integer)	832
20		
	ACPI Machine Language (AML) Specification	835
	20.1 Notation Conventions	
	20.2 AML Grammar Definition	836
	20.2.1 Table and Table Header Encoding	836
	20.2.2 Name Objects Encoding	837
	20.2.3 Data Objects Encoding	838
	20.2.4 Package Length Encoding	838
	20.2.5 Term Objects Encoding	839
	20.2.6 Miscellaneous Objects Encoding	846
	20.3 AML Byte Stream Byte Values	
	20.4 AML Encoding of Names in the Namespace	852
21		
~ I	ACPI Data Tables and Table Definition Language	855
	21.1 Types of ACPI Data Tables	
	21.2 ACPI Table Definition Language Specification	
	21.2.1 Overview of the Table Definition Language (TDL)	
	21.2.2 TDL Grammar Specification	
	21.2.3 Data Types	
	21.2.4 Fields Set Automatically by the Compiler	
	21.2.5 Special Fields	
	21.2.6 TDL Generic Data Types	
	21.2.7 Defining a Known ACPI Table in TDL	
	21.2.8 Defining an Unknown or New ACPI table in TDL	
	21.2.9 Table Definition Language Examples	
	21.2.10 Minimal ECDT Definition	

Appendix A Device Class Specifications	869
A.1 Overview	
A.2 Device Power States	
A.2.1 Bus Power Management	
A.2.2 Display Power Management	
A.2.3 PCMCIA/PCCARD/CardBus Power Management	
A.2.4 PCI Power Management	
A.2.5 USB Power Management	
A.2.6 Device Classes	
A.3 Default Device Class	
A.3.1 Default Power Management Policy	
A.3.2 Default Wake Events	
A.3.3 Minimum Power Capabilities	
A.4 Audio Device Class	
A.4.1 Power State Definitions	
A.4.2 Power Management Policy	
A.4.3 Wake Events	
A.4.4 Minimum Power Capabilities	
A.5 COM Port Device Class	
A.5.1 Power State Definitions	
A.5.2 Power Management Policy	
A.5.3 Wake Events	
A.5.4 Minimum Power Capabilities	
A.6 Display Device Class	
A.6.1 Power State Definitions	
A.6.2 Power Management Policy for the Display Class	
A.6.3 Wake Events	
A.6.4 Minimum Power Capabilities	
A.6.5 Performance States for Display Class Devices	
A.7 Input Device Class	
A.7.1 Power State Definitions	
A.7.2 Power Management Policy	
A.7.3 Wake Events	
A.7.4 Minimum Power Capabilities	
A.8 Modem Device Class	
A.8.1 Technology Overview	
A.8.2 Power State Definitions	
A.8.3 Power Management Policy	
A.8.4 Wake Events	
A.8.5 Minimum Power Capabilities	
A.9 Network Device Class	
A.9.1 Power State Definitions	
A.9.2 Power Management Policy	
A.9.3 Wake Events	
A.9.4 Minimum Power Capabilities	
A.10 PC Card Controller Device Class	

A.10.1 Power State Definitions	889
A.10.2 Power Management Policy	889
A.10.3 Wake Events	890
A.10.4 Minimum Power Capabilities	890
A.11 Storage Device Class	
A.11.1 Power State Definitions	
A.11.2 Power Management Policy	892
A.11.3 Wake Events	
A.11.4 Minimum Power Capabilities	892
Appendix B	
Video Extensions	895
B.1 ACPI Extensions for Display Adapters: Introduction	895
B.2 Definitions	896
B.3 ACPI Namespace	
B.3.1 _DOS (Enable/Disable Output Switching)	
B.3.2 _DOD (Enumerate All Devices Attached to the Display Adapter)	
B.3.3 _ROM (Get ROM Data)	
B.3.4 _GPD (Get POST Device)	
B.3.5 _SPD (Set POST Device)	
B.3.6 _VPO (Video POST Options)	
B.4 Notifications for Display Devices	
B.5 Output Device-specific Methods	
B.5.1 _ADR (Return the Unique ID for this Device)	
B.5.2 _BCL (Query List of Brightness Control Levels Supported)	
B.5.3 _BCM (Set the Brightness Level)	
B.5.4 _BQC (Brightness Query Current level)	
B.5.5 _DDC (Return the EDID for this Device)	
B.5.6 _DCS (Return the Status of Output Device)	
B.5.7 _DGS (Query Graphics State)	
B.5.8 _DSS (Device Set State)	
B.6 Notifications Specific to Output Devices	
B.7 Notes on State Changes	910

Tables

Table 1-1 Hardware Type vs. OS Type Interaction	3
Table 2-2 Summary of Global Power States	
Table 2-3 Summary of Device Power States	27
Table 3-4 Low Battery Levels	47
Table 3-5 Implementable Platform Types	53
Table 4-6 Feature/Programming Model Summary	
Table 4-7 PM1 Event Registers	
Table 4-8 PM1 Control Registers	70
Table 4-9 PM2 Control Register	71
Table 4-10 PM Timer Register	71
Table 4-11 Processor Control Registers	71
Table 4-12 General-Purpose Event Registers	71
Table 4-13 Power Button Support	74
Table 4-14 Sleep Button Support	77
Table 4-15 Alarm Field Decodings within the FADT	81
Table 4-16 PM1 Status Registers Fixed Hardware Feature Status Bits	84
Table 4-17 PM1 Enable Registers Fixed Hardware Feature Enable Bits	86
Table 4-18 PM1 Control Registers Fixed Hardware Feature Control Bits	87
Table 4-19 PM Timer Bits	88
Table 4-20 PM2 Control Register Bits	88
Table 4-21 Processor Control Register Bits	
Table 4-22 Processor LVL2 Register Bits	
Table 4-23 Processor LVL3 Register Bits	
Table 4-24 Sleep Control Register	91
Table 4-25 Sleep Status Register	
Table 5-26 Generic Address Structure (GAS)	
Table 5-27 Address Space Format	
Table 5-28 Root System Description Pointer Structure	
Table 5-29 DESCRIPTION_HEADER Fields	
Table 5-30 DESCRIPTION_HEADER Signatures for tables defined by ACPI	
Table 5-31 DESCRIPTION_HEADER Signatures for tables reserved by ACPI	
Table 5-32 Root System Description Table Fields (RSDT)	
Table 5-33 Extended System Description Table Fields (XSDT)	
Table 5-34 Fixed ACPI Description Table (FADT) Format	114
Table 5-35 Fixed ACPI Description Table Fixed Feature Flags	
Table 5-36 Fixed ACPI Description Table Boot IA-PC Boot Architecture Flags	
Table 5-37 Fixed ACPI Description Table ARM Boot Architecture Flags	
Table 5-38 Firmware ACPI Control Structure (FACS)	
Table 5-39 Firmware Control Structure Feature Flags	
Table 5-40 OSPM Enabled Firmware Control Structure Feature Flags	
Table 5-41 Global Lock Structure within the FACS	
Table 5-42 Differentiated System Description Table Fields (DSDT)	
Table 5-43 Secondary System Description Table Fields (SSDT)	135

Table 5-44 Multiple APIC Description Table (MADT) Format	
Table 5-45 Multiple APIC Flags	
Table 5-46 Interrupt Controller Structure Types	137
Table 5-47 Processor Local APIC Structure	
Table 5-48 Local APIC Flags	138
Table 5-49 I/O APIC Structure	
Table 5-50 Interrupt Source Override Structure	140
Table 5-51 MPS INTI Flags	
Table 5-52 Non-maskable Source Structure	
Table 5-53 Local APIC NMI Structure	
Table 5-54 Local APIC Address Override Structure	
Table 5-55 I/O SAPIC Structure	
Table 5-56 Processor Local SAPIC Structure	
Table 5-57 Platform Interrupt Sources Structure	
Table 5-58 Platform Interrupt Source Flags	
Table 5-59 Processor Local x2APIC Structure	
Table 5-60 Local x2APIC NMI Structure	
Table 5-61 GICC Structure Format	
Table 5-62 GICC CPU Interface Flags	
Table 5-63 GIC Distributor Structure	
Table 5-64 GIC MSI Structure	
Table 5-65 GIC MSI Frame Flags	
Table 5-66 GIC Redistributor Structure	
Table 5-67 Smart Battery Description Table (SBST) Format	
Table 5-68 Embedded Controller Boot Resources Table Format	
Table 5-69 Static Resource Affinity Table Format	
Table 5-70 Processor Local APIC/SAPIC Affinity Structure	
Table 5-71 Flags – Processor Local APIC/SAPIC Affinity Structure	
Table 5-72 Memory Affinity Structure	
Table 5-73 Flags – Memory Affinity Structure	
Table 5-74 Processor Local x2APIC Affinity Structure	
Table 5-75 GICC Affinity Structure	
Table 5-76 Flags – GICC Affinity Structure	
Table 5-77 SLIT Format	
Table 5-78 Corrected Platform Error Polling Table Format	
Table 5-79 Corrected Platform Error Polling Processor Structure	
Table 5-80 Maximum System Characteristics Table (MSCT) Format	
Table 5-81 Maximum Proximity Domain Information Structure	
Table 5-82 RASF Table format	
Table 5-83 RASF Platform Communication Channel Shared Memory Region	
Table 5-84 PCC Command Codes used by RASF Platform Communication Channel	
Table 5-85 Platform RAS capabilities bitmap	
Table 5-86 Parameter Block Structure for PATROL_SCRUB	
Table 5-87 MPST Table Structure	1/0
Table 5-88 PCC Command Codes used by MPST Platform Communication Channel	
Table 5-89 MPST Platform Communication Channel Shared Memory Region	
Table 5-90 Power state Values	1/3

Table 5-91 Command Status	174
Table 5-92 Memory Power Node Structure definition	175
Table 5-93 Flag format	
Table 5-94 Memory Power State Structure definition	177
Table 5-95 Memory Power State Characteristics Structure	
Table 5-96 Flag format of Memory Power State Characteristics Structure	
Table 5-97 Platform Memory Topology Table	
Table 5-98 Common Memory Aggregator Device Structure	
Table 5-99 Socket Structure	
Table 5-100 Memory Controller Structure	183
Table 5-101 Physical Components Identifier Structure	
Table 5-102 Boot Graphics Resource Table Fields	185
Table 5-103 Status Description Field	
Table 5-104 Image Type Description Field	
Table 5-105 Firmware Performance Data Table (FPDT) Format	
Table 5-106 Performance Record Structure	
Table 5-107 Performance Record Types	
Table 5-108 Runtime Performance Record Types	
Table 5-109 S3 Performance Table Pointer Record	
Table 5-110 S4 Performance Table Pointer Record	
Table 5-111 S3 Performance Table Header	190
Table 5-112 Basic S3 Resume Performance Record	190
Table 5-113 Basic S3 Suspend Performance Record	191
Table 5-114 Firmware Basic Boot Performance Table Header	191
Table 5-115 Firmware Basic Boot Performance Data Record Structure	
Table 5-116 GTDT Table Structure	
Table 5-117 Flag Definitions: Virtual Timer, EL2 timers, and Secure & Non-Secure EL1	
timers	194
Table 5-118 Platform Timer Type Structures	194
Table 5-119 GT Block Structure Format	195
Table 5-120 GT Block Timer Structure Format	
Table 5-121 Flag Definitions: GT Block Physical Timers and Virtual timers	
Table 5-122 Flag Definitions: Common Flags	
Table 5-123 SBSA Generic Watchdog Structure Format	
Table 5-124 Flag Definitions: SBSA Generic Watchdog Timer	
Table 5-125 Namespaces Defined Under the Namespace Root	
Table 5-126 Operation Region Address Space Identifiers	
Table 5-127 IPMI Status Codes	
Table 5-128 Accsessor Type Values	
Table 5-129 ACPI Event Programming Model Components	
Table 5-130 Fixed ACPI Events	
Table 5-131 Device Object Notification Values	
Table 5-132 Control Method Battery Device Notification Values	
Table 5-133 Power Source Object Notification Values	
Table 5-134 Thermal Zone Object Notification Values	
Table 5-135 Control Method Power Button Notification Values	
Table 5-136 Control Method Sleep Button Notification Values	238

Table 5-137 Control Method Lid Notification Values	238
Table 5-138 Processor Device Notification Values	
Table 5-139 User Presence Device Notification Values	
Table 5-140 Ambient Light Sensor Device Notification Values	
Table 5-141 Power Meter Object Notification Values	
Table 5-142 Processor Aggregator Device Notification Values	
Table 5-143 Error Device Notification Values	
Table 5-144 Fan Device Notification Values	
Table 5-145 Memory Device Notification Values	
Table 5-146 Processor Aggregator Device Notification Value	
Table 5-147 Error Device Notification Values	
Table 5-148 ACPI Device IDs	
Table 5-149 Predefined ACPI Names	
Table 5-150 Predefined Object Names	
Table 5-151 Operating System Vendor Strings	
Table 5-151 Operating System Vendor Strings	
Table 5-153 DeviceLockInfo Package Values	
Table 6-154 Device Identification Objects	
Table 6-155 ADR Object Address Encodings	
Table 6-156 Additional Language ID Alias Strings	
Table 6-157 PLD Back Panel Example Settings	
Table 6-158 Device Configuration Objects	
Table 6-159 HPP Package Contents	
Table 6-160 PCI Setting Record Content	
Table 6-161 PCI-X Setting Record Content	
Table 6-162 PCI Express Setting Record Content	
Table 6-163 Platform-Wide _OSC Capabilities DWORD 2	
Table 6-164 Interpretation of _OSC Support Field	
Table 6-165 Interpretation of _OSC Control Field, Passed in via Arg3	
Table 6-166 Interpretation of _OSC Control Field, Returned Value	
Table 6-167 Mapping Fields	
Table 6-168 Example Relative Distances Between Proximity Domains	
Table 6-169 Example System Locality Information Table	
Table 6-170 Example Relative Distances Between Proximity Domains - 5 Node	
Table 6-171 Device Insertion, Removal, and Status Objects	
Table 6-172 OST Source Event Codes	
Table 6-173 General Processing Status Codes	318
Table 6-174 Operating System Shutdown Processing (Source Events : 0x100) Statu	s Codes
319	
Table 6-175 Ejection Request / Ejection Processing (Source Events: 0x03 and 0x103	
Codes	
Table 6-176 Insertion Processing (Source Event: 0x200) Status Codes	
Table 6-177 Small Resource Data Type Tag Bit Definitions	
Table 6-178 Small Resource Items	
Table 6-179 IRQ Descriptor Definition	
Table 6-180 DMA Descriptor Definition	
Table 6-181 Start Dependent Functions Descriptor Definition	327

Table 6-182 Start Dependent Function Priority Byte Definition	328
Table 6-183 End Dependent Functions Descriptor Definition	328
Table 6-184 I/O Port Descriptor Definition	329
Table 6-185 Fixed-Location I/O Port Descriptor Definition	329
Table 6-186 Fixed DMA Resource Descriptor	330
Table 6-187 Vendor-Defined Resource Descriptor Definition	330
Table 6-188 End Tag Definition	
Table 6-189 Large Resource Data Type Tag Bit Definitions	
Table 6-190 Large Resource Items	
Table 6-191 24-bit Memory Range Descriptor Definition	
Table 6-192 Large Vendor-Defined Resource Descriptor Definition	
Table 6-193 32-Bit Memory Range Descriptor Definition	
Table 6-194 32-bit Fixed-Location Memory Range Descriptor Definition	
Table 6-195 Valid combination of Address Space Descriptors fields	336
Table 6-196 QWORD Address Space Descriptor Definition	
Table 6-197 DWORD Address Space Descriptor Definition	340
Table 6-198 WORD Address Space Descriptor Definition	342
Table 6-199 Extended Address Space Descriptor Definition	343
Table 6-200 Memory Resource Flag (Resource Type = 0) Definitions	348
Table 6-201 I/O Resource Flag (Resource Type = 1) Definitions	348
Table 6-202 Bus Number Range Resource Flag (Resource Type = 2) Definitions	349
Table 6-203 Extended Interrupt Descriptor Definition	
Table 6-204 Generic Register Descriptor Definition	351
Table 6-205 GPIO Connection Descriptor Definition	352
Table 6-206 Serial Bus Connection Descriptor	355
Table 6-207 I2C Serial Bus Connection Descriptor	357
Table 6-208 SPI Serial Bus Connection Descriptor	359
Table 6-209 UART Serial Bus Connection Descriptor	360
Table 6-210 Other Objects and Methods	363
Table 6-211 OSPM _INI Object Actions	363
Table 7-212 Power Resource Child Objects	
Table 7-213 Device Power Management Child Objects	
Table 7-214 PSC Device State Codes	377
Table 7-215 Power Resource Requirements Package	378
Table 7-216 S1 Action / Result Table	
Table 7-217 S2 Action / Result Table	
Table 7-218 S3 Action / Result Table	
Table 7-219 S4 Action / Result Table	
Table 7-220 BIOS-Supplied Control Methods for System-Level Functions	
Table 7-221 System State Package	
Table 8-222 Cstate Package Values	
Table 8-223 CStateDependency Package Values	
Table 8-224 PTC Package Values	
Table 8-225 TState Package Values	
Table 8-226 TStateDependency Package Values	
Table 8-227 PCT Package Values	
Table 8-228 PState Package Values	421

Table 8-229 PStateDependency Package Values	424
Table 8-230 Continuous Performance Control Package Values	
Table 8-231 Performance Limited Register Status BitsBits	438
Table 8-232 PCC Commands Codes used by Collaborative Processor Performance Co	ntrol
440	
Table 8-233 Processor Aggregator Device Objects	
Table 9-234 System Indicator Control Methods	
Table 9-235 Control Method Ambient Light Sensor Device	448
Table 9-236 Control Method Lid Device	456
Table 9-237 ATA Specific Objects	458
Table 9-238 GTM Method Result Codes	
Table 9-239 Tape Presence	
Table 9-240 ACPI Floppy Drive Information	
Table 9-241 MBM Package Details	
Table 9-242 MSM Result Encoding	
Table 9-243 Memory Device _OSC Capabilities DWORD number 2	
Table 9-244 UPC Return Package Values	
Table 9-245 User Presence Detection Device	
Table 9-246 Time and Alarm Device	
Table 10-247 Example SMBus Device Slave Addresses	
Table 10-248 Smart Battery Objects	
Table 10-249 Battery Control Methods	
Table 10-250 BIF Return Package Values	
Table 10-251 BIX Return Package Values	
Table 10-252 Control Method Battery OSC Capabilities DWORD2 Bit Definitions	
Table 10-253 BST Return Package Values	
Table 10-254 BMD Return Package Values	
Table 10-255 Power Source Objects	
Table 10-256 PIF Method Result Codes	
Table 10-257 Power Meter Objects	
Table 10-258 PMC Method Result Codes	
Table 11-259 Fan Specific Objects	
Table 11-260 FIF Package Details	
Table 11-261 FPS FanPstate Package Details	
Table 11-262 FST Package Details	
Table 11-263 Thermal Objects	
Table 11-264 Thermal Relationship Package Values	
Table 11-265 Thermal Relationship Package Values	
Table 12-266 Read only register table	
Table 12-267 Register details	
Table 12-268 Embedded Controller Commands	
Table 12-269 Events for Which Embedded Controller Must Generate SCIs	
Table 12-270 Read Command (3 Bytes)	
Table 12-271 Write Command (3 Bytes)	
Table 12-272 Query Command (2 Bytes	
Table 12-273 Burst Enable Command (2 Bytes)	
Table 12-274 Burst Disable Command (1 Byte)	582

Table 12-275 SMBus Status Codes	584
Table 12-276 SMB EC Interface	592
Table 12-277 Embedded Controller Device Object Control Methods	595
Table 12-278 EC SMBus HC Device Objects	596
Table 13-279 SMBus Protocol Types	600
Table 14-280 Platform Communications Channel Table (PCCT)	613
Table 14-281 Platform Communications Channel Global Flags	
Table 14-282 Generic PCC Subspace Structure	614
Table 14-283 PCC Subspace Structure type 0 (Generic Communications Subs	pace) 614
Table 14-284 PCC Subspace Structure type 1 (HW-Reduced Communications	Subspace)
615	
Table 14-285 Generic Communications Channel Shared Memory Region	616
Table 14-286 Generic Communications Channel Command Field	617
Table 14-287 Generic Communications Channel Status Field	617
Table 15-288 Address Range Types	
Table 15-289 Input to the INT 15h E820h Call	622
Table 15-290 Output from the INT 15h E820h Call	623
Table 15-291 Address Range Descriptor Structure	
Table 15-292 Extended Attributes for Address Range Descriptor Structure	
Table 15-293 UEFI Memory Types and mapping to ACPI address range types	625
Table 15-294 Sample Memory Map	
Table 18-295 Boot Error Record Table (BERT) Table	
Table 18-296 Boot Error Region	
Table 18-297 Hardware Error Source Table (HEST)	
Table 18-298 IA-32 Architecture Machine Check Exception Structure	
Table 18-299 IA-32 Architecture Machine Check Error Bank Structure	
Table 18-300 IA-32 Architecture Corrected Machine Check Structure	
Table 18-301 IA-32 Architecture NMI Error Structure	
Table 18-302 PCI Express Root Port AER Structure	
Table 18-303 PCI Express Device AER Structure	
Table 18-304 PCI Express Bridge AER Structure	
Table 18-305 Generic Hardware Error Source Structure	
Table 18-306 Generic Error Status Block	
Table 18-307 Generic Error Data Entry	
Table 18-308 Hardware Error Notification Structure	
Table 18-309 Error Record Serialization Table (ERST)	
Table 18-310 Error Record Serialization Actions	
Table 18-311 Command Status Definition	
Table 18-312 Serialization Instruction Entry	
Table 18-313 Serialization Instructions	
Table 18-314 Instruction Flags	
Table 18-315 Error Record Serialization Info	
Table 18-316 Error Injection Table (EINJ)	
Table 18-317 Error Injection Actions	
Table 18-318 Injection Instruction Entry	
Table 18-319 Instruction Flags	
Table 18-320 Injection Instructions	683

Table 18-321 Command Status Definition	
Table 18-322 Error Type Definition	. 683
Table 18-323 SET_ERROR_TYPE_WITH_ADDRESS Data Structure	. 684
Table 18-324 Vendor Error Type Extension Structure	
Table 18-325 Trigger Error Action	. 686
Table 19-326 ASL Grammar Notation	. 690
Table 19-327 Named Object Reference Encodings	. 716
Table 19-328 Definition Block Name Modifier Encodings	. 716
Table 19-329 ASL Escape Sequences	
Table 19-330 Example ASL Built-in Macros	. 720
Table 19-331 Summary of ASL Data Types	
Table 19-332 Data Types and Type Conversions	. 724
Table 19-333 Object Conversion Rules	. 726
Table 19-334 Object Storing and Copying Rules	. 729
Table 19-335 Reading from ArgX Objects	. 729
Table 19-336 Writing to ArgX Objects	
Table 19-337 Reading from LocalX Objects	. 730
Table 19-338 Writing to LocalX Objects	
Table 19-339 Reading from Named Objects	. 731
Table 19-340 Writing to Named Objects	. 731
Table 19-341 Concatenate Data Types	. 745
Table 19-342 Debug Object Display Formats	. 750
Table 19-343 Field Unit list entires	. 769
Table 19-344 OperationRegion Region Types and Access Types	. 769
Table 19-345 Match Term Operator Meanings	. 789
Table 19-346 TValues Returned By the ObjectType Operator	. 798
Table 19-347 Predefined Operation Region types	
Table 19-348 UUID Buffer Format	. 823
Table 20-349 AML Grammar Notation Conventions	. 835
Table 20-350 AML Byte Stream Byte Values	. 847
Table A-351 Default Power State Definitions	. 872
Table B-352 Video Extension Object Requirements	. 895
Table B-353 Video Output Device Attributes	. 900
Table B-354 Example Device Ids	. 901
Table B-355 Notifications for Display Devices.	. 904
Table B-356 Device Status	
Table B-357 Device State for _DGS	. 908
Table B-358 Device State for _DSS	
Table B-359 Notification Values for Output Devices	. 909

Figures

Figure 1-1 OSPM/ACPI Global System	5
Figure 3-2 Global System Power States and Transitions	33
Figure 3-3 Example Modem and COM Port Hardware	41
Figure 3-4 Reporting Battery Capacity	46
Figure 3-5 Remaining Battery Percent Formula	46
Figure 3-6 Re;maining Battery Life Formula	
Figure 3-7 Low Battery and Warning	
Figure 3-8 Thermal Zone	
Figure 4-9 Generic Hardware Feature Model	58
Figure 4-10 Global States and Their Transitions	
Figure 4-11 Example Event Structure for a Legacy/ACPI Compatible Event Model	63
Figure 4-12 Block Diagram of a Status/Enable Cell	
Figure 4-13 Example Fixed Hardware Feature Register Grouping	69
Figure 4-14 Register Blocks versus Register Groupings	
Figure 4-15 Power Management Timer	73
Figure 4-16 Fixed Power Button Logic	75
Figure 4-17 Fixed Hardware Sleep Button Logic	77
Figure 4-18 Sleeping/Wake Logic	79
Figure 4-19 RTC Alarm	80
Figure 4-20 Power Management Events to SMI/SCI Control Logic	82
Figure 4-21 Example of General-Purpose vs. Generic Hardware Events	
Figure 4-22 Example Generic Address Space Lid Switch Logic	96
Figure 5-23 Root System Description Pointer and Table	
Figure 5-24 Description Table Structures	
Figure 5-25 APIC-Global System Interrupts	147
Figure 5-26 8259–Global System Interrupts	152
Figure 5-27 MPST ACPI Table Overview	169
Figure 5-28 Memory Power State Transitions	
Figure 5-29 Image Offset	
Figure 5-30 Example ACPI NameSpace	199
Figure 5-31 AML Encoding	
Figure 6-32 System Panel and Panel Origin Positions	267
Figure 6-33 Laptop Panel and Panel Origin Positions	268
Figure 6-34 Default Shape Definitions	
Figure 6-35 PLD Back Panel Rendering	
Figure 6-36 System Locality information Table	308
Figure 6-37 Device Ejection Flow Example Using OST	
Figure 7-38 Working / Sleeping State object evaluation flow	
Figure 8-39 Processor Power States	
Figure 8-40 Throttling Example	
Figure 8-41 Equation 1 Duty Cycle Equation	399
Figure 8-42 Example Control for the STPCLK#	
Figure 8-43 ACPI Clock Logic (One per Processor)	400

Figure 8-44 Platform performance thresholds	431
Figure 8-45 OSPM performance controls	433
Figure 9-46 A five-point ALS Response Curve	452
Figure 9-47 A two-point ALS Response Curve	453
Figure 9-48 Example Response Curve for a Transflective Display	454
Figure 9-49 USB ports	476
Figure 9-50 Persistence of expired timer events	489
Figure 9-51 System transitions with WakeAlarm Timer	
Figure 9-52 System transitions with WakeAlarm Policy	491
Figure 10-53 Typical Smart Battery Subsystem (SBS)	505
Figure 10-54 Single Smart Battery Subsystem	
Figure 10-55 Smart Battery Subsystem	
Figure 10-56 Remaining Battery Percent Formula	520
Figure 10-57 Remaining Battery Life Formula	520
Figure 10-58 Power Meter and Power Source/Docking Namespace Example	
Figure 11-59 ACPI Thermal Zone	534
Figure 11-60 Thermal Events	537
Figure 11-61 Temperature and CPU Performance Versus Time	539
Figure 11-62 Active and Passive Threshold Values	541
Figure 11-63 Cooling Preferences	542
Figure 12-64 Shared Interface	
Figure 12-65 Private Interface	575
Figure 12-66 Interrupt Model	581
Figure 13-67 Bit Encoding Example	600
Figure 13-68 Smart Battery Subsystem Devices	603
Figure 13-69 Smart Battery Device Virtual Registers	605
Figure 16-70 Example Sleeping States	631
Figure 16-71 BIOS Initialization	639
Figure 16-72 Example Physical Memory Map	642
Figure 16-73 Memory as Configured after Boot	643
Figure 16-74 OS Initialization	
Figure B-1 Example Display Architecture	901

The Advanced Configuration and Power Interface (ACPI) specification was developed to establish industry common interfaces enabling robust operating system (OS)-directed motherboard device configuration and power management of both devices and entire systems. ACPI is the key element in Operating System-directed configuration and Power Management (OSPM).

ACPI evolved the existing pre-ACPI collection of power management BIOS code, Advanced Power Management (APM) application programming interfaces (APIs, PNPBIOS APIs, Multiprocessor Specification (MPS) tables and so on into a well-defined power management and configuration interface specification. ACPI provides the means for an orderly transition from existing (legacy) hardware to ACPI hardware, and it allows for both ACPI and legacy mechanisms to exist in a single machine and to be used as needed.

Further, system architectures being built at the time of the original ACPI specification's inception, stretched the limits of historical "Plug and Play" interfaces. ACPI evolved existing motherboard configuration interfaces to support advanced architectures in a more robust, and potentially more efficient manner.

The interfaces and OSPM concepts defined within this specification are suitable to all classes of computers including (but not limited to) desktop, mobile, workstation, and server machines. From a power management perspective, OSPM/ACPI promotes the concept that systems should conserve energy by transitioning unused devices into lower power states including placing the entire system in a low-power state (sleeping state) when possible.

This document describes ACPI hardware interfaces, ACPI software interfaces and ACPI data structures that, when implemented, enable support for robust OS-directed configuration and power management (OSPM).

1.1 Principal Goals

ACPI is the key element in implementing OSPM. ACPI-defined interfaces are intended for wide adoption to encourage hardware and software vendors to build ACPI-compatible (and, thus, OSPM-compatible) implementations.

The principal goals of ACPI and OSPM are to:

- 1. Enable all computer systems to implement motherboard configuration and power management functions, using appropriate cost/function tradeoffs.
 - Computer systems include (but are not limited to) desktop, mobile, workstation, and server machines.
 - Machine implementers have the freedom to implement a wide range of solutions, from the very simple to the very aggressive, while still maintaining full OS support.
 - Wide implementation of power management will make it practical and compelling for applications to support and exploit it. It will make new uses of PCs practical and existing uses of PCs more economical.

- 2. Enhance power management functionality and robustness.
 - Power management policies too complicated to implement in a ROM BIOS can be implemented and supported in the OS, allowing inexpensive power managed hardware to support very elaborate power management policies.
 - Gathering power management information from users, applications, and the hardware together into the OS will enable better power management decisions and execution.
 - Unification of power management algorithms in the OS will reduce conflicts between the firmware and OS and will enhance reliability.
- 3. Facilitate and accelerate industry-wide implementation of power management.
 - OSPM and ACPI reduces the amount of redundant investment in power management throughout the industry, as this investment and function will be gathered into the OS. This will allow industry participants to focus their efforts and investments on innovation rather than simple parity.
 - The OS can evolve independently of the hardware, allowing all ACPI-compatible machines to gain the benefits of OS improvements and innovations.
- 4. Create a robust interface for configuring motherboard devices.
 - Enable new advanced designs not possible with existing interfaces.

1.2 Power Management Rationale

It is necessary to move power management into the OS and to use an abstract interface (ACPI) between the OS and the hardware to achieve the principal goals set forth above.

- Minimal support for power management inhibits application vendors from supporting or exploiting it.
 - Moving power management functionality into the OS makes it available on every machine
 on which the OS is installed. The level of functionality (power savings, and so on) varies
 from machine to machine, but users and applications will see the same power interfaces and
 semantics on all OSPM machines.
 - This will enable application vendors to invest in adding power management functionality to their products.
- Legacy power management algorithms were restricted by the information available to the BIOS that implemented them. This limited the functionality that could be implemented.
 - Centralizing power management information and directives from the user, applications, and hardware in the OS allows the implementation of more powerful functionality. For example, an OS can have a policy of dividing I/O operations into normal and lazy. Lazy I/O operations (such as a word processor saving files in the background) would be gathered up into clumps and done only when the required I/O device is powered up for some other reason. A non-lazy I/O request made when the required device was powered down would cause the device to be powered up immediately, the non-lazy I/O request to be carried out, and any pending lazy I/O operations to be done. Such a policy requires knowing when I/O devices are powered up, knowing which application I/O requests are lazy, and being able to assure that such lazy I/O operations do not starve.
 - Appliance functions, such as answering machines, require globally coherent power decisions. For example, a telephone-answering application could call the OS and assert, "I am waiting for incoming phone calls; any sleep state the system enters must allow me to

wake and answer the telephone in 1 second." Then, when the user presses the "off" button, the system would pick the deepest sleep state consistent with the needs of the phone answering service.

- BIOS code has become very complex to deal with power management. It is difficult to make work with an OS and is limited to static configurations of the hardware.
 - There is much less state information for the BIOS to retain and manage (because the OS manages it).
 - Power management algorithms are unified in the OS, yielding much better integration between the OS and the hardware.
 - Because additional ACPI tables (Definition Blocks) can be loaded, for example, when a mobile system docks, the OS can deal with dynamic machine configurations.
 - Because the BIOS has fewer functions and they are simpler, it is much easier (and therefore cheaper) to implement and support.
- The existing structure of the PC platform constrains OS and hardware designs.
- Because ACPI is abstract, the OS can evolve separately from the hardware and, likewise, the hardware from the OS.
- ACPI is by nature more portable across operating systems and processors. ACPI control methods allow for very flexible implementations of particular features.

1.3 Legacy Support

ACPI provides support for an orderly transition from legacy hardware to ACPI hardware, and allows for both mechanisms to exist in a single machine and be used as needed.

Table 1-1	Hardware	Type vs.	OS Type	Interaction

Hardware\OS	Legacy OS	ACPI OS with OSPM
Legacy hardware	A legacy OS on legacy hardware does what it always did.	If the OS lacks legacy support, legacy support is completely contained within the hardware functions.
Legacy and ACPI hardware support in machine	It works just like a legacy OS on legacy hardware.	During boot, the OS tells the hardware to switch from legacy to OSPM/ACPI mode and from then on, the system has full OSPM/ACPI support.
ACPI-only hardware	There is no power management.	There is full OSPM/ACPI support.

1.4 OEM Implementation Strategy

Any OEM is, as always, free to build hardware as they see fit. Given the existence of the ACPI specification, two general implementation strategies are possible:

 An original equipment manufacturer (OEM) can adopt the OS vendor-provided ACPI OSPM software and implement the hardware part of the ACPI specification (for a given platform) in one of many possible ways.

• An OEM can develop a driver and hardware that are not ACPI-compatible. This strategy opens up even more hardware implementation possibilities. However, OEMs who implement hardware that is OSPM-compatible but *not* ACPI-compatible will bear the cost of developing, testing, and distributing drivers for their implementation.

1.5 Power and Sleep Buttons

OSPM provides a new appliance interface to consumers. In particular, it provides for a sleep button that is a "soft" button that does *not* turn the machine physically off but signals the OS to put the machine in a soft off or sleeping state. ACPI defines two types of these "soft" buttons: one for putting the machine to sleep and one for putting the machine in soft off.

This gives the OEM two different ways to implement machines: A one-button model or a two-button model. The one-button model has a single button that can be used as a power button or a sleep button as determined by user settings. The two-button model has an easily accessible sleep button and a separate power button. In either model, an override feature that forces the machine to the soft-off state without OSPM interaction is also needed to deal with various rare, but problematic, situations.

1.6 ACPI Specification and the Structure Of ACPI

This specification defines ACPI hardware interfaces, ACPI software interfaces and ACPI data structures. This specification also defines the semantics of these interfaces.

<u>Figure 1-1</u> lays out the software and hardware components relevant to OSPM/ACPI and how they relate to each other. This specification describes the *interfaces between* components, the contents of the ACPI System Description Tables, and the related semantics of the other ACPI components. Notice that the ACPI System Description Tables, which describe a particular platform's hardware, are at heart of the ACPI implementation and the role of the ACPI System Firmware is primarily to supply the ACPI Tables (rather than a native instruction API).

ACPI is *not* a software specification; it is *not* a hardware specification, although it addresses both software and hardware and how they must behave. ACPI is, instead, an interface specification comprised of both software and hardware elements.




Figure 1-1 OSPM/ACPI Global System

There are three run-time components to ACPI:

ACPI System Description Tables.

Describe the interfaces to the hardware. Some descriptions limit what can be built (for example, some controls are embedded in fixed blocks of registers and the table specifies the address of the register block). Most descriptions allow the hardware to be built in arbitrary ways and can describe arbitrary operation sequences needed to make the hardware function. ACPI Tables containing "Definition Blocks" can make use of a pseudo-code type of language, the interpretation of which is performed by the OS. That is, OSPM contains and uses an interpreter that executes procedures encoded in

the pseudo-code language and stored in the ACPI tables containing "Definition Blocks." The pseudo-code language, known as ACPI Machine Language (AML), is a compact, tokenized, abstract type of machine language.

ACPI Registers.

The constrained part of the hardware interface, described (at least in location) by the ACPI System Description Tables.

ACPI System Firmware.

Refers to the portion of the firmware that is compatible with the ACPI specifications. Typically, this is the code that boots the machine (as legacy BIOSs have done) and implements interfaces for sleep, wake, and some restart operations. It is called rarely, compared to a legacy BIOS. The ACPI Description Tables are also provided by the ACPI System Firmware.

1.7 OS and Platform Compliance

The ACPI specification contains only interface specifications. ACPI does not contain any platform compliance requirements. The following sections provide guidelines for class specific platform implementations that reference ACPI-defined interfaces and guidelines for enhancements that operating systems may require to completely support OSPM/ACPI. The minimum feature implementation requirements of an ACPI-compatible OS are also provided.

1.7.1 Platform Implementations of ACPI-defined Interfaces

System platforms implement ACPI-defined hardware interfaces via the platform hardware and ACPI-defined software interfaces and system description tables via the ACPI system firmware. Specific ACPI-defined interfaces and OSPM concepts while appropriate for one class of machine (for example, a mobile system), may not be appropriate for another class of machine (for example, a multi-domain enterprise server). It is beyond the capability and scope of this specification to specify all platform classes and the appropriate ACPI-defined interfaces that should be required for the platform class.

Platform design guide authors are encouraged to require the appropriate ACPI-defined interfaces and hardware requirements suitable to the particular system platform class addressed in a particular design guide. Platform design guides should not define alternative interfaces that provide similar functionality to those defined in the ACPI specification.

1.7.1.1 Recommended Features and Interface Descriptions for Design Guides

Common description text and category names should be used in design guides to describe all features, concepts, and interfaces defined by the ACPI specification as requirements for a platform class. Listed below is the recommended set of high-level text and category names to be used to describe the features, concepts, and interfaces defined by ACPI.

Note: Where definitions or relational requirements of interfaces are localized to a specific section, the section number is provided. The interface definitions and relational requirements of the interfaces

specified below are generally spread throughout the ACPI specification. The ACPI specification defines:

System address map reporting interfaces (Section 14)

ACPI System Description Tables (Section 5.2):

Root System Description Pointer (RSDP)

System Description Table Header

Root System Description Table (RSDT)

Fixed ACPI Description Table (FADT)

Firmware ACPI Control Structure (FACS)

Differentiated System Description Table (DSDT)

Secondary System Description Table (SSDT)

Multiple APIC Description Table (MADT)

Smart Battery Table (SBST)

Extended System Description Table (XSDT)

Embedded Controller Boot Resources Table (ECDT)

System Resource Affinity Table (SRAT)

System Locality Information Table (SLIT)

Corrected Platform Error Polling Table (CPEP)

Maximum System Characteristics Table (MSCT)

ACPI RAS FeatureTable (RASF)

Memory Power StateTable (MPST)

Platform Memory Topology Table (PMTT)

Boot Graphics Resource Table (BGRT)

Firmware Performance Data Table (FPDT)

Generic Timer Description Table (GTDT)

ACPI-defined Fixed Registers Interfaces (Section 4, Section 5.2.9):

Power management timer control/status

Power or sleep button with S5 override (also possible in generic space)

Real time clock wakeup alarm control/status

SCI/SMI routing control/status for Power Management and General-purpose events

System power state controls (sleeping/wake control) (Section 7)

Processor power state control (c states) (Section 8)

Processor throttling control/status (Section 8)

Processor performance state control/status (Section 8)

General-purpose event control/status

Global Lock control/status

System Reset control (Section 4.7.3.6)

Embedded Controller control/status (Section 12)

SMBus Host Controller (HC) control/status (Section 13)

Smart Battery Subsystem (Section 10.1)

```
ACPI-defined Generic Register Interfaces and object definitions in the ACPI Namespace (Section 4.2, Section 5.6.5):
   General-purpose event processing
   Motherboard device identification, configuration, and insertion/removal (Section 6)
   Thermal zones (Section 11)
   Power resource control (Section 7.1)
   Device power state control (Section 7.2)
   System power state control (Section 7.3)
   System indicators (Section 9.1)
   Devices and device controls (Section 9):
      Processor (Section 8)
      Control Method Battery (Section 10)
      Smart Battery Subsystem (Section 10)
      Mobile Lid
      Power or sleep button with S5 override (also possible in fixed space)
      Embedded controller (Section 12)
      Fan
      Generic Bus Bridge
      ATA Controller
      Floppy Controller
      GPE Block
      Module
      Memory
    Global Lock related interfaces
ACPI Event programming model (Section 5.6)
ACPI-defined System BIOS Responsibilities (Section 15)
ACPI-defined State Definitions (Section 2):
   Global system power states (G-states, S0, S5)
   System sleeping states (S-states S1-S4) (Section 15)
   Device power states (D-states (Appendix B))
   Processor power states (C-states) (Section 8)
   Device and processor performance states (P-states) (Section 3, Section 8)
```

1.7.1.2 Terminology Examples for Design Guides

The following provides an example of how a client platform design guide, whose goal is to require robust configuration and power management for the system class, could use the recommended terminology to define ACPI requirements.

Note: This example is provided as a guideline for how ACPI terminology can be used. It should not be interpreted as a statement of ACPI requirements.

Platforms compliant with this platform design guide must implement the following ACPI defined system features, concepts, and interfaces, along with their associated event models:

System address map reporting interfaces

ACPI System Description Tables provided in the system firmware

ACPI-defined Fixed Registers Interfaces:

Power management timer control/status

Power or sleep button with S5 override (may also be implemented in generic register space)

Real time clock wakeup alarm control/status

General-purpose event control/status

SCI/SMI routing control/status for Power Management and General-purpose events

(control required only if system supports legacy mode)

System power state controls (sleeping/wake control)

Processor power state control (for C1)

Global Lock control/status (if Global Lock interfaces are required by the system)

· ACPI-defined Generic Register Interfaces and object definitions in the ACPI Namespace:

General-purpose event processing

Motherboard device identification, configuration, and insertion/removal (Section 6)

System power state control (Section 7.3)

Devices and device controls:

Processor

Control Method Battery (or Smart Battery Subsystem on a mobile system)

Smart Battery Subsystem (or Control Method Battery on a mobile system)

Power or sleep button with S5 override (may also be implemented in fixed register space)

Global Lock related interfaces when a logical register in the hardware is shared between OS and firmware environments

- · ACPI Event programming model (Section 5.6)
- · ACPI-defined System BIOS Responsibilities (Section 15)
- · ACPI-defined State Definitions:

System sleeping states (At least one system sleeping state, S1-S4, must be implemented)

Device power states (D-states must be implemented in accordance with device class specifications)

Processor power states (All processors must support the C1 Power State)

The following provides an example of how a design guide for systems that execute multiple OS instances, whose goal is to require robust configuration and continuous availability for the system class, could use the recommended terminology to define ACPI related requirements.

Note: This example is provided as a guideline for how ACPI terminology can be used. It should not be interpreted as a statement of ACPI requirements.

Platforms compliant with this platform design guide must implement the following ACPI defined system features and interfaces, along with their associated event models:

System address map reporting interfaces

ACPI System Description Tables provided in the system firmware

ACPI-defined Fixed Registers Interfaces:

Power management timer control/status

General-purpose event control/status

SCI/SMI routing control/status for Power Management and General-purpose events

(control required only if system supports legacy mode)

System power state controls (sleeping/wake control)

Processor power state control (for C1)

Global Lock control/status (if Global Lock interfaces are required by the system)

· ACPI-defined Generic Register Interfaces and object definitions in the ACPI Namespace:

General-purpose event processing

Motherboard device identification, configuration, and insertion/removal (Section 6)

System power state control (Section 7.3)

System indicators

Devices and device controls:

Processor

Global Lock related interfaces when a logical register in the hardware is shared between OS and firmware environments

- · ACPI Event programming model (Section 5.6)
- ACPI-defined System BIOS Responsibilities (Section 15)
- · ACPI-defined State Definitions:

Processor power states (All processors must support the C1 Power State)

1.7.2 OSPM Implementations

OS enhancements are needed to support ACPI-defined features, concepts, and interfaces, along with their associated event models appropriate to the system platform class upon which the OS executes. This is the implementation of OSPM. The following outlines the OS enhancements and elements necessary to support all ACPI-defined interfaces. To support ACPI through the implementation of OSPM, the OS needs to be modified to:

- Use system address map reporting interfaces.
- Find and consume the ACPI System Description Tables.
- Interpret ACPI machine language (AML).
- Enumerate and configure motherboard devices described in the ACPI Namespace.
- Interface with the power management timer.
- Interface with the real-time clock wake alarm.
- Enter ACPI mode (on legacy hardware systems).
- Implement device power management policy.
- Implement power resource management.
- Implement processor power states in the scheduler idle handlers.
- Control processor and device performance states.
- Implement the ACPI thermal model.

- Support the ACPI Event programming model including handling SCI interrupts, managing fixed events, general-purpose events, embedded controller interrupts, and dynamic device support.
- Support acquisition and release of the Global Lock.
- Use the reset register to reset the system.
- Provide APIs to influence power management policy.
- Implement driver support for ACPI-defined devices.
- Implement APIs supporting the system indicators.
- Support all system states S1–S5.

1.7.3 OS Requirements

The following list describes the minimum requirements for an OSPM/ACPI-compatible OS:

- Use system address map reporting interfaces to get the system address map on Intel Architecture (IA) platforms:
 - INT 15H, E820H Query System Address Map interface (see <u>Section 15</u>, "System Address Map Interfaces")
 - EFI GetMemoryMap() Boot Services Function (see <u>Section 15</u>, "System Address Map Interfaces")
- Find and consume the ACPI System Description Tables (see <u>Section 5</u>, "ACPI Software Programming Model").
- Implementation of an AML interpreter supporting all defined AML grammar elements (see Section 20, ACPI Machine Language Specification").
- Support for the ACPI Event programming model including handling SCI interrupts, managing fixed events, general-purpose events, embedded controller interrupts, and dynamic device support.
- Enumerate and configure motherboard devices described in the ACPI Namespace.
- Implement support for the following ACPI devices defined within this specification:
 - Embedded Controller Device (see <u>Section 12</u>, "ACPI Embedded Controller Interface Specification")
 - GPE Block Device (see Section 9.10, "GPE Block Device")
 - Module Device (see Section 9.11, "Module Device")
- Implementation of the ACPI thermal model (see Section 11, "Thermal Management").
- Support acquisition and release of the Global Lock.
- OS-directed power management support (device drivers are responsible for maintaining device context as described by the Device Power Management Class Specifications described in Section A).

1.8 Target Audience

This specification is intended for the following users:

• OEMs building hardware containing ACPI-compatible interfaces

- Operating system and device driver developers
- BIOS and ACPI system firmware developers
- CPU and chip set vendors
- Peripheral vendors

1.9 Document Organization

The ACPI specification document is organized into the following four parts:

- The first part of the specification (sections 1 through 3) introduces ACPI and provides an
 executive overview.
- The second part (sections 4 and 5) defines the ACPI hardware and software programming models.
- The third part (sections 6 through 17) specifies the ACPI implementation details; this part of the specification is primarily for developers.
- The fourth part (sections 18 and 19) is technical reference material; section 18 is the ACPI Source Language (ASL) reference, parts of which are referred to by most of the other sections in the document.
- Appendices contain device class specifications, describing power management characteristics of specific classes of devices, and device class-specific ACPI interfaces.

1.9.1 ACPI Introduction and Overview

The first three sections of the specification provide an executive overview of ACPI.

Section 1: Introduction.

Discusses the purpose and goals of the specification, presents an overview of the ACPI-compatible system architecture, specifies the minimum requirements for an ACPI-compatible system, and provides references to related specifications.

Section 2: Definition of Terms.

Defines the key terminology used in this specification. In particular, the global system states (Mechanical Off, Soft Off, Sleeping, Working, and Non-Volatile Sleep) are defined in this section, along with the device power state definitions: Off (D3), D3hot, D2, D1, and Fully-On (D0). Device and processor performance states (P0, P1, ...Pn) are also discussed.

Section 3: ACPI Overview.

Gives an overview of the ACPI specification in terms of the functional areas covered by the specification: system power management, device power management, processor power management, Plug and Play, handling of system events, battery management, and thermal management.

1.9.2 Programming Models

Sections 4 and 5 define the ACPI hardware and software programming models. This part of the specification is primarily for system designers, developers, and project managers.

All of the implementation-oriented, reference, and platform example sections of the specification that follow (all the rest of the sections of the specification) are based on the models defined in sections 4 and 5. These sections are the heart of the ACPI specification. There are extensive cross-references between the two sections.

Section 4: ACPI Hardware Specification.

Defines a set of hardware interfaces that meet the goals of this specification.

Section 5: ACPI Software Programming Model.

Defines a set of software interfaces that meet the goals of this specification.

1.9.3 Implementation Details

The third part of the specification defines the implementation details necessary to actually build components that work on an ACPI-compatible platform. This part of the specification is primarily for developers.

Section 6: Configuration.

Defines the reserved Plug and Play objects used to configure and assign resources to devices, and share resources and the reserved objects used to track device insertion and removal. Also defines the format of ACPI-compatible resource descriptors.

Section 7: Power and Performance Management.

Defines the reserved device power-management objects and the reserved-system power-management objects.

Section 8: Processor Configuration and Control.

Defines how the OS manages the processors' power consumption and other controls while the system is in the working state.

Section 9: ACPI-Specific Device Objects.

Lists the integrated devices that need support for some device-specific ACPI controls, along with the device-specific ACPI controls that can be provided. Most device objects are controlled through generic objects and control methods and have generic device IDs; this section discusses the exceptions.

Section 10: Power Source Devices.

Defines the reserved battery device and AC adapter objects.

Section 11: Thermal Management.

Defines the reserved thermal management objects.

Section 12: ACPI Embedded Controller Interface Specification.

Defines the interfaces between an ACPI-compatible OS and an embedded controller.

Section 13: ACPI System Management Bus Interface Specification.

Defines the interfaces between an ACPI-compatible OS and a System Management Bus (SMBus) host controller.

Section 14: Platform Communications Channel.

Explains the generic mechanism for OSPM to communicate with an entity in the platform defines a new address space type

Section 15: System Address Map Interfaces.

Explains the special INT 15 call for use in ISA/EISA/PCI bus-based systems. This call supplies the OS with a clean memory map indicating address ranges that are reserved and ranges that are available on the motherboard. UEFI-based memory address map reporting interfaces are also described.

Section 16: Waking and Sleeping.

Defines in detail the transitions between system working and sleeping states and their relationship to wake events. Refers to the reserved objects defined in sections 6, 7, and 8

Section 17: Non-Uniform Memory Access (NUMA) Architecture Platforms.

Discusses in detail how ACPI define interfaces can be used to describe a NUMA architecture platform. Refers to the reserved objects defined in sections 5, 6, 8, and 9.

Section 18: ACPI Platform Error Interfaces.

Defines interfaces that enable OSPM to processes different types of hardware error events that are detected by platform-based error detection hardware.

1.9.4 Technical Reference

The fourth part of the specification contains reference material for developers.

Section 19: ACPI Source Language Reference.

Defines the syntax of all the ASL statements that can be used to write ACPI control methods, along with example syntax usage.

Section 20: ACPI Machine Language Specification.

Defines the grammar of the language of the ACPI virtual machine language. An ASL translator (compiler) outputs AML.

Section 2: ACPI Data Tables and Table Language Definition.

Describes a simple language (the Table Definition Language or TDL) that can be used to generate any ACPI data table.

Appendix A: Device class specifications.

Describes device-specific power management behavior on a per device-class basis.

Appendix B: Video Extensions.

Contains video device class-specific ACPI interfaces.

1.10 Related Documents

Power management and Plug and Play specifications for legacy hardware platforms are the following, available from "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Legacy PNP Guidelines".

- Advanced Power Management (APM) BIOS Specification, Revision 1.2.
- Plug and Play BIOS Specification, Version 1.0a.

Intel Architecture specifications are available from http://developer.intel.com:

Intel® *Itanium* **M* Architecture Software Developer's Manual, see "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Intel Architecture Specifications".

Itanium **Processor Family System Abstraction Layer Specification, Intel Corporation, December 2003 (June 2004 Update).

Unified Extensible Firmware Interface Specifications are available from http://www.uefi.org: *Unified Extensible Firmware Interface Specification*, see "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Unified Extensible Firmware Interface Specifications" Documentation and specifications for the Smart Battery System components and the SMBus are available from http://www.sbs-forum.org:

- "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Smart Battery System Components and SMBus Specification".
- Smart Battery Data Specification, see "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Smart Battery System Components and SMBus Specification".
- *Smart Battery Selector Specification*, Revision 1.1, Smart Battery System Implementers Forum, December, 1998.
- Smart Battery System Manager Specification, Revision 1.0, Smart Battery System Implementers Forum, December, 1998.
- System Management Bus Specification, Revision 1.1, Smart Battery System Implementers Forum, December, 1998.

This specification uses a particular set of terminology, defined in this section. This section has three parts:

General ACPI terms are defined and presented alphabetically.

The ACPI global system states (working, sleeping, soft off, and mechanical off) are defined. Global system states apply to the entire system, and *are* visible to the user.

The ACPI device power states are defined. Device power states are states of particular devices; as such, they are generally *not* visible to the user. For example, some devices may be in the off state even though the system as a whole is in the working state. Device states apply to any device on any bus.

2.1 General ACPI Terminology

Advanced Configuration and Power Interface (ACPI)

As defined in this document, ACPI is a method for describing hardware interfaces in terms abstract enough to allow flexible and innovative hardware implementations and concrete enough to allow shrink-wrap OS code to use such hardware interfaces.

ACPI Hardware

Computer hardware with the features necessary to support OSPM and with the interfaces to those features described using the Description Tables as specified by this document.

ACPI Namespace

A hierarchical tree structure in OS-controlled memory that contains named objects. These objects may be data objects, control method objects, bus/device package objects, and so on. The OS dynamically changes the contents of the namespace at runtime by loading and/or unloading definition blocks from the ACPI Tables that reside in the ACPI BIOS. All the information in the ACPI Namespace comes from the Differentiated System Description Table (DSDT), which contains the Differentiated Definition Block, and one or more other definition blocks.

ACPI Machine Language (AML)

Pseudo-code for a virtual machine supported by an ACPI-compatible OS and in which ACPI control methods and objects are written. The AML encoding definition is provided in section 19, "ACPI Machine Language (AML) Specification."

Advanced Programmable Interrupt Controller (APIC)

An interrupt controller architecture commonly found on Intel Architecture-based 32-bit PC systems. The APIC architecture supports multiprocessor interrupt management (with symmetric interrupt distribution across all processors), multiple I/O subsystem

support, 8259A compatibility, and inter-processor interrupt support. The architecture consists of local APICs commonly attached directly to processors and I/O APICs commonly in chip sets.

ACPI Source Language (ASL)

The programming language equivalent for AML. ASL is compiled into AML images. The ASL statements are defined in section 18, "ACPI Source Language (ASL) Reference."

Control Method

A control method is a definition of how the OS can perform a simple hardware task. For example, the OS invokes control methods to read the temperature of a thermal zone. Control methods are written in an encoded language called AML that can be interpreted and executed by the ACPI-compatible OS. An ACPI-compatible system must provide a minimal set of control methods in the ACPI tables. The OS provides a set of well-defined control methods that ACPI table developers can reference in their control methods. OEMs can support different revisions of chip sets with one BIOS by either including control methods in the BIOS that test configurations and respond as needed or including a different set of control methods for each chip set revision.

Central Processing Unit (CPU) or Processor

The part of a platform that executes the instructions that do the work. An ACPI-compatible OS can balance processor performance against power consumption and thermal states by manipulating the processor performance controls. The ACPI specification defines a working state, labeled G0 (S0), in which the processor executes instructions. Processor sleeping states, labeled C1 through C3, are also defined. In the sleeping states, the processor executes no instructions, thus reducing power consumption and, potentially, operating temperatures. The ACPI specification also defines processor performance states, where the processor (while in C0) executes instructions, but with lower performance and (potentially) lower power consumption and operating temperature. For more information, see section 8, "Processor Configuration and Control."

A definition block contains information about hardware implementation and configuration details in the form of data and control methods, encoded in AML. An OEM can provide one or more definition blocks in the ACPI Tables. One definition block must be provided: the Differentiated Definition Block, which describes the base system. Upon loading the Differentiated Definition Block, the OS inserts the contents of the Differentiated Definition Block into the ACPI Namespace. Other definition blocks, which the OS can dynamically insert and remove from the active ACPI Namespace, can contain references to the Differentiated Definition Block. For more information, see section 5.2.11, "Definition Blocks."

Device

Hardware component outside the core chip set of a platform. Examples of devices are liquid crystal display (LCD) panels, video adapters, Integrated Drive Electronics (IDE) CD-ROM and hard disk controllers, COM ports, and so on. In the ACPI scheme

of power management, buses are devices. For more information, see section 3.3.2, "Device Power States."

Device Context

The variable data held by the device; it is usually volatile. The device might forget this information when entering or leaving certain states (for more information, see section 2.3, "Device Power State Definitions."), in which case the OS software is responsible for saving and restoring the information. Device Context refers to small amounts of information held in device peripherals. See System Context.

Differentiated System Description Table (DSDT)

An OEM must supply a DSDT to an ACPI-compatible OS. The DSDT contains the Differentiated Definition Block, which supplies the implementation and configuration information about the base system. The OS always inserts the DSDT information into the ACPI Namespace at system boot time and never removes it.

Unified Extensible Firmware Interface (UEFI)

An interface between the OS and the platform firmware. The interface is in the form of data tables that contain platform related information, and boot and run-time service calls that are available to the OS and loader. Together, these provide a standard environment for booting an OS.

Embedded Contorller

The general class of microcontrollers used to support OEM-specific implementations, mainly in mobile environments. The ACPI specification supports embedded controllers in any platform design, as long as the microcontroller conforms to one of the models described in this section. The embedded controller performs complex low-level functions through a simple interface to the host microprocessor(s).

Embedded Controller Interface

A standard hardware and software communications interface between an OS driver and an embedded controller. This allows any OS to provide a standard driver that can directly communicate with an embedded controller in the system, thus allowing other drivers within the system to communicate with and use the resources of system embedded controllers (for example, Smart Battery and AML code). This in turn enables the OEM to provide platform features that the OS and applications can use.

Firmware ACPI Control Structure (FACS)

A structure in read/write memory that the BIOS uses for handshaking between the firmware and the OS. The FACS is passed to an ACPI-compatible OS via the Fixed ACPI Description Table (FADT). The FACS contains the system's hardware signature at last boot, the firmware waking vector, and the Global Lock.

Fixed ACPI Description Table (FADT)

A table that contains the ACPI Hardware Register Block implementation and configuration details that the OS needs to directly manage the ACPI Hardware Register Blocks, as well as the physical address of the DSDT, which contains other platform implementation and configuration details. An OEM must provide an FADT

to an ACPI-compatible OS in the RSDT/XSDT. The OS always inserts the namespace information defined in the Differentiated Definition Block in the DSDT into the ACPI Namespace at system boot time, and the OS never removes it.

Fixed Features

A set of features offered by an ACPI interface. The ACPI specification places restrictions on where and how the hardware programming model is generated. All fixed features, if used, are implemented as described in this specification so that OSPM can directly access the fixed feature registers.

Fixed Feature Events

A set of events that occur at the ACPI interface when a paired set of status and event bits in the fixed feature registers are set at the same time. When a fixed feature event occurs, a system control interrupt (SCI is raised. For ACPI fixed feature events, OSPM (or an ACPI-aware driver) acts as the event handler.

Fixed Feature Registers

A set of hardware registers in fixed feature register space at specific address locations in system I/O address space. ACPI defines register blocks for fixed features (each register block gets a separate pointer from the FADT). For more information, see section 4.6, "ACPI Hardware Features."

General-Purpose Event Registers

The general-purpose event registers contain the event programming model for generic features. All general-purpose events generate SCIs.

Generic Feature

A generic feature of a platform is value-added hardware implemented through control methods and general-purpose events.

Global System Status

Global system states apply to the entire system, and are visible to the user. The various global system states are labeled G0 through G3 in the ACPI specification. For more information, see Section 2.2, "Global System State Definitions."

Ignored Bits

Some unused bits in ACPI hardware registers are designated as "ignored" in the ACPI specification. Ignored bits are undefined and can return zero or one (in contrast to reserved bits, which always return zero). Software ignores ignored bits in ACPI hardware registers on reads and preserves ignored bits on writes.

Intel Architecture-Personal Computer (IA-PC)

A general descriptive term for computers built with processors conforming to the architecture defined by the Intel processor family based on the Intel Architecture instruction set and having an industry-standard PC architecture.

I/O APIC

An Input/Output Advanced Programmable Interrupt Controller routes interrupts from devices to the processor's local APIC.

I/O SAPIC

An Input/Output Streamlined Advanced Programmable Interrupt Controller routes interrupts from devices to the processor's local APIC.

Legacy

A computer state where power management policy decisions are made by the platform hardware/firmware shipped with the system. The legacy power management features found in today's systems are used to support power management in a system that uses a legacy OS that does not support the OS-directed power management architecture.

Legacy Hardware

A computer system that has no ACPI or OSPM power management support.

Legacy OS

An OS that is not aware of and does not direct the power management functions of the system. Included in this category are operating systems with APM 1.x support.

Local APIC

A local Advanced Programmable Interrupt Controller receives interrupts from the I/O APIC.

Local SAPIC

A local Streamlined Advanced Programmable Interrupt Controller receives interrupts from the I/O SAPIC.

Multiple APIC Description Table (MADT)

The Multiple APIC Description Table (MADT) is used on systems supporting the APIC and SAPIC to describe the APIC implementation. Following the MADT is a list of APIC/SAPIC structures that declare the APIC/SAPIC features of the machine.

Object

The nodes of the ACPI Namespace are objects inserted in the tree by the OS using the information in the system definition tables. These objects can be data objects, package objects, control method objects, and so on. Package objects refer to other objects. Objects also have type, size, and relative name.

Object name

Part of the ACPI Namespace. There is a set of rules for naming objects.

Operating System-directed Power Management (OSPM)

A model of power (and system) management in which the OS plays a central role and uses global information to optimize system behavior for the task at hand.

Package

An array of objects.

Power Button

A user push button or other switch contact device that switches the system from the sleeping/soft off state to the working state, and signals the OS to transition to a sleeping/soft off state from the working state.

Power Management

Mechanisms in software and hardware to minimize system power consumption, manage system thermal limits, and maximize system battery life. Power management involves trade-offs among system speed, noise, battery life, processing speed, and alternating current (AC) power consumption. Power management is required for some system functions, such as appliance (for example, answering machine, furnace control) operations.

Power Resources

Resources (for example, power planes and clock sources) that a device requires to operate in a given power state.

Power Sources

The battery (including a UPS battery) and AC line powered adapters or power supplies that supply power to a platform.

Register Grouping

Consists of two register blocks (it has two pointers to two different blocks of registers). The fixed-position bits within a register grouping can be split between the two register blocks. This allows the bits within a register grouping to be split between two chips.

Reserved Bits

Some unused bits in ACPI hardware registers are designated as "Reserved" in the ACPI specification. For future extensibility, hardware-register reserved bits always return zero, and data writes to them have no side effects. OSPM implementations must write zeros to all reserved bits in enable and status registers and preserve bits in control registers.

Root System Description Pointer (RSDP)

An ACPI-compatible system must provide an RSDP in the system's low address space. This structure's only purpose is to provide the physical address of the RSDT and XSDT.

Root System Description Table (RSDT)

A table with the signature 'RSDT,' followed by an array of physical pointers to other system description tables. The OS locates that RSDT by following the pointer in the RSDP structure.

Secondary System Description Table (SSDT)

SSDTs are a continuation of the DSDT. Multiple SSDTs can be used as part of a platform description. After the DSDT is loaded into the ACPI Namespace, each secondary description table listed in the RSDT/XSDT with a unique OEM Table ID is

loaded. This allows the OEM to provide the base support in one table, while adding smaller system options in other tables.

Note: Additional tables can only add data; they cannot overwrite data from previous tables.

Sleep Button

A user push button that switches the system from the sleeping/soft off state to the working state, and signals the OS to transition to a sleeping state from the working state.

Smart Battery Subsystem

A battery subsystem that conforms to the following specifications: Smart Battery and either Smart Battery System Manager or Smart Battery Charger and Selector—and the additional ACPI requirements.

Smart Battery Table

An ACPI table used on platforms that have a Smart Battery subsystem. This table indicates the energy-level trip points that the platform requires for placing the system into different sleeping states and suggested energy levels for warning the user to transition the platform into a sleeping state.

System Management Bus (SMBus)

A two-wire interface based upon the I²C protocol. The SMBus is a low-speed bus that provides positive addressing for devices, as well as bus arbitration.

SMBus Interface

A standard hardware and software communications interface between an OS bus driver and an SMBus controller.

Streamlined Advanced Programmable Interrupt Controller (SAPIC)

An advanced APIC commonly found on Intel ItaniumTM Processor Family-based 64-bit systems.

System Context

The volatile data in the system that is not saved by a device driver.

System Control Interrupt (SCI)

A system interrupt used by hardware to notify the OS of ACPI events. The SCI is an active, low, shareable, level interrupt.

System Management Interrupt (SMI)

An OS-transparent interrupt generated by interrupt events on legacy systems. By contrast, on ACPI systems, interrupt events generate an OS-visible interrupt that is shareable (edge-style interrupts will not work). Hardware platforms that want to support both legacy operating systems and ACPI systems must support a way of remapping the interrupt events between SMIs and SCIs when switching between ACPI and legacy models.

Thermal States

Thermal states represent different operating environment temperatures within thermal zones of a system. A system can have one or more thermal zones; each thermal zone is the volume of space around a particular temperature-sensing device. The transitions from one thermal state to another are marked by trip points, which are implemented to generate an SCI when the temperature in a thermal zone moves above or below the trip point temperature.

Extended Root System Description Table (XSDT)

The XSDT provides identical functionality to the RSDT but accommodates physical addresses of DESCRIPTION HEADERs that are larger than 32 bits. Notice that both the XSDT and the RSDT can be pointed to by the RSDP structure.

2.2 Global System State Definitions

Global system states (Gx states) apply to the entire system and are visible to the user.

Global system states are defined by six principal criteria:

- 1. Does application software run?
- 2. What is the latency from external events to application response?
- 3. What is the power consumption?
- 4. Is an OS reboot required to return to a working state?
- 5. Is it safe to disassemble the computer?
- 6. Can the state be entered and exited electronically?

Following is a list of the system states:

G3 Mechanical Off

A computer state that is entered and left by a mechanical means (for example, turning off the system's power through the movement of a large red switch). It is implied by the entry of this off state through a mechanical means that no electrical current is running through the circuitry and that it can be worked on without damaging the hardware or endangering service personnel. The OS must be restarted to return to the Working state. No hardware context is retained. Except for the real-time clock, power consumption is zero.

G2/S5 Soft Off

A computer state where the computer consumes a minimal amount of power. No user mode or system mode code is run. This state requires a large latency in order to return to the Working state. The system's context will not be preserved by the hardware. The system must be restarted to return to the Working state. It is not safe to disassemble the machine in this state.

G1 Sleeping

A computer state where the computer consumes a small amount of power, user mode threads are not being executed, and the system "appears" to be off (from an end user's perspective, the display is off, and so on). Latency for returning to the Working state

varies on the wake environment selected prior to entry of this state (for example, whether the system should answer phone calls). Work can be resumed without rebooting the OS because large elements of system context are saved by the hardware and the rest by system software. It is not safe to disassemble the machine in this state.

G0 Working

A computer state where the system dispatches user mode (application) threads and they execute. In this state, peripheral devices (peripherals) are having their power state changed dynamically. The user can select, through some UI, various performance/power characteristics of the system to have the software optimize for performance or battery life. The system responds to external events in real time. It is not safe to disassemble the machine in this state.

S4 Non-Volatile Sleep

A special global system state that allows system context to be saved and restored (relatively slowly) when power is lost to the motherboard. If the system has been commanded to enter S4, the OS will write all system context to a file on non-volatile storage media and leave appropriate context markers. The machine will then enter the S4 state. When the system leaves the Soft Off or Mechanical Off state, transitioning to Working (G0) and restarting the OS, a restore from a NVS file can occur. This will only happen if a valid non-volatile sleep data set is found, certain aspects of the configuration of the machine have not changed, and the user has not manually aborted the restore. If all these conditions are met, as part of the OS restarting, it will reload the system context and activate it. The net effect for the user is what looks like a resume from a Sleeping (G1) state (albeit slower). The aspects of the machine configuration that must not change include, but are not limited to, disk layout and memory size. It might be possible for the user to swap a PC Card or a Device Bay device, however.

Notice that for the machine to transition directly from the Soft Off or Sleeping states to S4, the system context must be written to non-volatile storage by the hardware; entering the Working state first so that the OS or BIOS can save the system context takes too long from the user's point of view. The transition from Mechanical Off to S4 is likely to be done when the user is not there to see it.

Because the S4 state relies only on non-volatile storage, a machine can save its system context for an arbitrary period of time (on the order of many years).

Table 2-2 Sum	imary of Globa	I Power States
---------------	----------------	----------------

Global system state	Software runs	Latency	Power consumption	OS restart required	Safe to disassemble computer	Exit state electronically
G0 Working	Yes	0	Large	No	No	Yes
G1 Sleeping	No	>0, varies with sleep state	Smaller	No	No	Yes

Global system state	Software runs	Latency	Power consumption	OS restart required	Safe to disassemble computer	Exit state electronically
G2/S5 Soft Off	No	Long	Very near 0	Yes	No	Yes
G3 Mechanical Off	No	Long	RTC battery	Yes	Yes	No

Notice that the entries for G2/S5 and G3 in the Latency column of the above table are "Long." This implies that a platform designed to give the user the appearance of "instant-on," similar to a home appliance device, will use the G0 and G1 states almost exclusively (the G3 state may be used for moving the machine or repairing it).

2.3 Device Power State Definitions

Device power states are states of particular devices; as such, they are generally not visible to the user. For example, some devices may be in the Off state even though the system as a whole is in the Working state.

Device states apply to any device on any bus. They are generally defined in terms of four principal criteria:

- Power consumption-How much power the device uses.
- Device context--How much of the context of the device is retained by the hardware. The OS is responsible for restoring any lost device context (this may be done by resetting the device).
- Device driver--What the device driver must do to restore the device to full on.
- Restore time--How long it takes to restore the device to full on.

The device power states are defined below, although very generically. Many devices do not have all four power states defined. Devices may be capable of several different low-power modes, but if there is no user-perceptible difference between the modes, only the lowest power mode will be used. The Device Class Power Management Specifications, included in Appendix A of this specification, describe which of these power states are defined for a given type (class) of device and define the specific details of each power state for that device class. For a list of the available *Device Class Power Management Specifications*, see "Appendix A: Device Class Specifications."

D3 (Off)

Power has been fully removed from the device. The device context is lost when this state is entered, so the OS software will reinitialize the device when powering it back on. Since device context and power are lost, devices in this state do not decode their address lines. Devices in this state have the longest restore times. All classes of devices define this state.

D3hot

The meaning of the D3hot State is defined by each device class. Devices in the D3hot State are required to be software enumerable. In general, D3hot is expected to save more power and optionally preserve device context. If device context is lost when this state is entered, the OS software will reinitialize the device when transitioning to D0.

Devices in this state can have long restore times. All classes of devices define this state.

Note: The D3hot state differs from the D3 state in two distinct parameters; the main power rail is present and software can access a device in D3hot. For devices that support both D3hot and D3 exposed to OSPM via _PR3, device software/drivers must always assume OSPM will target D3and must assume device context will be lost.

D2

The meaning of the D2 Device State is defined by each device class. Many device classes may not define D2. In general, D2 is expected to save more power and preserve less device context than D1 or D0. Buses in D2 may cause the device to lose some context (for example, by reducing power on the bus, thus forcing the device to turn off some of its functions).

D1

The meaning of the D1 Device State is defined by each device class. Many device classes may not define D1. In general, D1 is expected to save less power and preserve more device context than D2.

D0 (Fully-On)

This state is assumed to be the highest level of power consumption. The device is completely active and responsive, and is expected to remember all relevant context continuously.

Table 2-3 Summary of Device Power States

Device State	Power Consumption	Device Context Retained	Driver Restoration
D0 - Fully-On	As needed for operation	All	None
D1	D0>D1>D2> D3hot>D3	>D2	<d2< td=""></d2<>
D2	D0>D1>D2> D3hot>D3	<d1< td=""><td>>D1</td></d1<>	>D1
D3hot	D0>D1>D2>D3hot>D3	Optional	None <->Full initialization and load
D3 - Off	0	None	Full initialization and load

Note: Devices often have different power modes within a given state. Devices can use these modes as long as they can automatically transparently switch between these modes from the software, without violating the rules for the current Dx state the device is in. Low-power modes that adversely affect performance (in other words, low speed modes) or that are not transparent to software cannot be done automatically in hardware; the device driver must issue commands to use these modes.

2.4 Sleeping State Definitions

Sleeping states (Sx states) are types of sleeping states within the global sleeping state, G1. The Sx states are briefly defined below. For a detailed definition of the system behavior within each Sx state, see Section 7.3.2, "System \Sx States." For a detailed definition of the transitions between each of the Sx states, see Section 16.1, "Sleeping States."

S1 Sleeping State

The S1 sleeping state is a low wake latency sleeping state. In this state, no system context is lost (CPU or chip set) and hardware maintains all system context.

S2 Sleeping State

The S2 sleeping state is a low wake latency sleeping state. This state is similar to the S1 sleeping state except that the CPU and system cache context is lost (the OS is responsible for maintaining the caches and CPU context). Control starts from the processor's reset vector after the wake event.

S3 Sleeping State

The S3 sleeping state is a low wake latency sleeping state where all system context is lost except system memory. CPU, cache, and chip set context are lost in this state. Hardware maintains memory context and restores some CPU and L2 configuration context. Control starts from the processor's reset vector after the wake event.

S4 Sleeping State

The S4 sleeping state is the lowest power, longest wake latency sleeping state supported by ACPI. In order to reduce power to a minimum, it is assumed that the hardware platform has powered off all devices. Platform context is maintained.

S5 Soft Off State

The S5 state is similar to the S4 state except that the OS does not save any context. The system is in the "soft" off state and requires a complete boot when it wakes. Software uses a different state value to distinguish between the S5 state and the S4 state to allow for initial boot operations within the BIOS to distinguish whether or not the boot is going to wake from a saved memory image.

2.5 Processor Power State Definitions

Processor power states (*Cx* states) are processor power consumption and thermal management states within the global working state, G0. The *Cx* states possess specific entry and exit semantics and are briefly defined below. For a more detailed definition of each *Cx* state, see section 8.1, "Processor Power States."

C0 Processor Power State

While the processor is in this state, it executes instructions.

C1 Processor Power State

This processor power state has the lowest latency. The hardware latency in this state must be low enough that the operating software does not consider the latency aspect of the state when deciding whether to use it. Aside from putting the processor in a non-executing power state, this state has no other software-visible effects.

C2 Processor Power State

The C2 state offers improved power savings over the C1 state. The worst-case hardware latency for this state is provided via the ACPI system firmware and the operating software can use this information to determine when the C1 state should be

used instead of the C2 state. Aside from putting the processor in a non-executing power state, this state has no other software-visible effects.

C3 Processor Power State

The C3 state offers improved power savings over the C1 and C2 states. The worst-case hardware latency for this state is provided via the ACPI system firmware and the operating software can use this information to determine when the C2 state should be used instead of the C3 state. While in the C3 state, the processor's caches maintain state but ignore any snoops. The operating software is responsible for ensuring that the caches maintain coherency.

2.6 Device and Processor Performance State Definitions

Device and Processor performance states (Px states) are power consumption and capability states within the active/executing states, C0 for processors and D0 for devices. The Px states are briefly defined below. For a more detailed definition of each Px state from a processor perspective, see section 8.4.4, "Processor Performance Control." For a more detailed definition of each Px state from a device perspective see section 3.6, "Device and Processor Performance States," and the device class specifications in Appendix A.

P0 Performance State

While a device or processor is in this state, it uses its maximum performance capability and may consume maximum power.

P1 Performance State

In this performance power state, the performance capability of a device or processor is limited below its maximum and consumes less than maximum power.

Pn Performance State

In this performance state, the performance capability of a device or processor is at its minimum level and consumes minimal power while remaining in an active state. State n is a maximum number and is processor or device dependent. Processors and devices may define support for an arbitrary number of performance states not to exceed 16.

ACPI Overview

Platforms compliant with the ACPI specification provide OSPM with direct and **exclusive** control over the power management and motherboard device configuration functions of a computer. During OS initialization, OSPM **takes over** these functions from legacy implementations such as the APM BIOS, SMM-based firmware, legacy applications, and the PNPBIOS. Having done this, OSPM is responsible for handling motherboard device configuration events as well as for controlling the power, performance, and thermal status of the system based on user preference, application requests and OS imposed Quality of Service (QOS) / usability goals. ACPI provides low-level interfaces that allow OSPM to perform these functions. The functional areas covered by the ACPI specification are:

System power management

ACPI defines mechanisms for putting the computer as a whole in and out of system sleeping states. It also provides a general mechanism for any device to wake the computer.

Device power management

ACPI tables describe motherboard devices, their power states, the power planes the devices are connected to, and controls for putting devices into different power states. This enables the OS to put devices into low-power states based on application usage.

Processor power management

While the OS is idle but not sleeping, it will use commands described by ACPI to put processors in low-power states.

Device and processor performance management.

While the system is active, OSPM will transition devices and processors into different performance states, defined by ACPI, to achieve a desirable balance between performance and energy conservation goals as well as other environmental requirements (for example, visibility and acoustics).

Configuration / Plug and Play

ACPI specifies information used to enumerate and configure motherboard devices. This information is arranged hierarchically so when events such as docking and undocking take place, the OS has precise, *a priori* knowledge of which devices are affected by the event.

System Events

ACPI provides a general event mechanism that can be used for system events such as thermal events, power management events, docking, device insertion and removal, and so on. This mechanism is very flexible in that it does not define specifically how events are routed to the core logic chip set.

Battery management

Battery management policy moves from the APM BIOS to the ACPI OS. An ACPIcompatible battery device needs either a Smart Battery subsystem interface, which is

ACPI Overview

controlled by the OS directly through the embedded controller interface, or a Control Method Battery interface. A Control Method Battery interface is completely defined by AML control methods, allowing an OEM to choose any type of the battery and any kind of communication interface supported by ACPI. The battery must comply with the requirements of its interface, as described either herein or in other applicable standards. The OS may choose to alter the behavior of the battery, for example, by adjusting the Low Battery or Battery Warning trip point. When there are multiple batteries present, the battery subsystem is not required to perform any synthesis of a "composite battery" from the data of the separate batteries. In cases where the battery subsystem does not synthesize a "composite battery" from the separate battery's data, the OS must provide that synthesis.

Thermal management

Since the OS controls the power and performance states of devices and processors, ACPI also addresses system thermal management. It provides a simple, scalable model that allows OEMs to define thermal zones, thermal indicators, and methods for cooling thermal zones.

Embedded Controller

ACPI defines a standard hardware and software communications interface between an OS bus enumerator and an embedded controller. This allows any OS to provide a standard bus enumerator that can directly communicate with an embedded controller in the system, thus allowing other drivers within the system to communicate with and use the resources of system embedded controllers. This in turn enables the OEM to provide platform features that the OS and applications can use.

SMBus Controller

ACPI defines a standard hardware and software communications interface between an OS bus driver and an SMBus Controller. This allows any OS to provide a standard bus driver that can directly communicate with SMBus devices in the system. This in turn enables the OEM to provide platform features that the OS and applications can use.

OSPM's mission is to optimally configure the platform and to optimally manage the system's power, performance, and thermal status given the user's preferences and while supporting OS imposed Quality of Service (QOS) / usability goals. To achieve these goals, ACPI requires that once an ACPI compliant platform is in ACPI mode, the platform's hardware, firmware, or other non-OS software must not manipulate the platform's configuration, power, performance, and thermal control interfaces independently of OSPM. OSPM alone is responsible for coordinating the configuration, power management, performance management, and thermal control policy of the system. Manipulation of these interfaces independently of OSPM undermines the purpose of OSPM/ACPI and may adversely impact the system's configuration, power, performance, and thermal policy goals. There are two exceptions to this requirement. The first is in the case of the possibility of damage to a system from an excessive thermal conditions where an ACPI compatible OS is present and OSPM latency is insufficient to remedy an adverse thermal condition. In this case, the platform may exercise a failsafe thermal control mechanism that reduces the performance of a system component to avoid damage. If this occurs, the platform must notify OSPM of the performance reduction if the reduction is of significant duration (in other words, if the duration of reduced performance could adversely impact OSPM's power or performance control policy - operating

system vendors can provide guidance in this area). The second exception is the case where the platform contains Active cooling devices but does not contain Passive cooling temperature trip points or controls,. In this case, a hardware based Active cooling mechanism may be implemented without impacting OSPM's goals. Any platform that requires both active and passive cooling must allow OSPM to manage the platform thermals via ACPI defined active and passive cooling interfaces.

3.1 System Power Management

Under OSPM, the OS directs all system and device power state transitions. Employing user preferences and knowledge of how devices are being used by applications, the OS puts devices in and out of low-power states. Devices that are not being used can be turned off. Similarly, the OS uses information from applications and user settings to put the system as a whole into a low-power state. The OS uses ACPI to control power state transitions in hardware.

3.2 Power States

From a user-visible level, the system can be thought of as being in one of the states in the following diagram:




Figure 3-2 Global System Power States and Transitions

See Section 2.2, "Global System State Definitions," for detailed definitions of these states.

ACPI Overview

In general use, computers alternate between the Working and Sleeping states. In the Working state, the computer is used to do work. User-mode application threads are dispatched and running. Individual devices can be in low-power (Dx) states and processors can be in low-power (Cx) states if they are not being used. Any device the system turns off because it is not actively in use can be turned on with short latency. (What "short" means depends on the device. An LCD display needs to come on in sub-second times, while it is generally acceptable to wait a few seconds for a printer to wake.)

The net effect of this is that the entire machine is functional in the Working state. Various Working sub-states differ in speed of computation, power used, heat produced, and noise produced. Tuning within the Working state is largely about trade-offs among speed, power, heat, and noise.

When the computer is idle or the user has pressed the power button, the OS will put the computer into one of the sleeping (Sx) states. No user-visible computation occurs in a sleeping state. The sleeping sub-states differ in what events can arouse the system to a Working state, and how long this takes. When the machine must awaken to all possible events or do so very quickly, it can enter only the sub-states that achieve a partial reduction of system power consumption. However, if the only event of interest is a user pushing on a switch and a latency of minutes is allowed, the OS could save all system context into an NVS file and transition the hardware into the S4 sleeping state. In this state, the machine draws almost zero power and retains system context for an arbitrary period of time (years or decades if needed).

The other states are used less often. Computers that support legacy BIOS power management interfaces boot in the Legacy state and transition to the Working state when an ACPI OS loads. A system without legacy support (for example, a RISC system) transitions directly from the Mechanical Off state to the Working state. Users typically put computers into the Mechanical Off state by flipping the computer's mechanical switch or by unplugging the computer.

3.2.1 Power Button

In legacy systems, the power button typically either forces the machine into Soft Off or Mechanical Off or, on a laptop, forces it to some sleeping state. No allowance is made for user policy (such as the user wants the machine to "come on" in less than 1 second with all context as it was when the user turned the machine "off"), system alert functions (such as the system being used as an answering machine or fax machine), or application function (such as saving a user file).

In an OSPM system, there are two switches. One is to transition the system to the Mechanical Off state. A mechanism to stop current flow is required for legal reasons in some jurisdictions (for example, in some European countries). The other is the "main" power button. This is in some obvious place (for example, beside the keyboard on a laptop). Unlike legacy on/off buttons, all it does is send a request to the system. What the system does with this request depends on policy issues derived from user preferences, user function requests, and application data.

3.2.2 Platform Power Management Characteristics

3.2.2.1 Mobile PC

Mobile PCs will continue to have aggressive power management functionality. Going to OSPM/ ACPI will allow enhanced power savings techniques and more refined user policies.

Aspects of mobile PC power management in the ACPI specification are thermal management (see <u>Section 11</u>, "Thermal Management") and the embedded controller interface (see <u>Section 12</u>, "ACPI Embedded Controller Interface Specification").

3.2.2.2 Desktop PCs

Power-managed desktops will be of two types, though the first type will migrate to the second over time.

Ordinary "Green PC"

Here, new appliance functions are not the issue. The machine is really only used for productivity computations. At least initially, such machines can get by with very minimal function. In particular, they need the normal ACPI timers and controls, but don't need to support elaborate sleeping states, and so on. They, however, do need to allow the OS to put as many of their devices/resources as possible into device standby and device off states, as independently as possible (to allow for maximum compute speed with minimum power wasted on unused devices). Such PCs will also need to support wake from the sleeping state by means of a timer, because this allows administrators to force them to turn on just before people are to show up for work.

Home PC

Computers are moving into home environments where they are used in entertainment centers and to perform tasks like answering the phone. A home PC needs all of the functionality of the ordinary green PC. In fact, it has all of the ACPI power functionality of a laptop except for docking and lid events (and need not have any legacy power management). Note that there is also a thermal management aspect to a home PC, as a home PC user wants the system to run as quietly as possible, often in a thermally constrained environment.

3.2.2.3 Multiprocessor and Server PCs

Perhaps surprisingly, server machines often get the largest absolute power savings. Why? Because they have the largest hardware configurations and because it's not practical for somebody to hit the off switch when they leave at night.

Day Mode

In day mode, servers are power-managed much like a corporate ordinary green PC, staying in the Working state all the time, but putting unused devices into low-power states whenever possible. Because servers can be very large and have, for example, many disk spindles, power management can result in large savings. OSPM allows careful tuning of when to do this, thus making it workable.

Night Mode

In night mode, servers look like home PCs. They sleep as deeply as they can and are still able to wake and answer service requests coming in over the network, phone links, and so on, within specified latencies. So, for example, a print server might go into deep sleep until it receives a print job at 3 A.M., at which point it wakes in perhaps less than 30 seconds, prints the job, and then goes back to sleep. If the print

request comes over the LAN, then this scenario depends on an intelligent LAN adapter that can wake the system in response to an interesting received packet.

3.3 Device Power Management

This section describes ACPI-compatible device power management. The ACPI device power states are introduced, the controls and information an ACPI-compatible OS needs to perform device power management are discussed, the wake operation devices use to wake the computer from a sleeping state is described, and an example of ACPI-compatible device management using a modem is given.

3.3.1 Power Management Standards

To manage power of all the devices in the system, the OS needs standard methods for sending commands to a device. These standards define the operations used to manage power of devices on a particular I/O interconnect and the power states that devices can be put into. Defining these standards for each I/O interconnect creates a baseline level of power management support the OS can utilize. Independent Hardware Vendors (IHVs) do not have to spend extra time writing software to manage power of their hardware, because simply adhering to the standard gains them direct OS support. For OS vendors, the I/O interconnect standards allow the power management code to be centralized in the driver for each I/O interconnect. Finally, I/O interconnect-driven power management allows the OS to track the states of all devices on a given I/O interconnect. When all the devices are in a given state (or example, D3 - off), the OS can put the entire I/O interconnect into the power supply mode appropriate for that state (for example, D3 - off).

I/O interconnect-level power management specifications are written for a number of buses including:

- PCI
- PCI Express
- CardBus
- USB
- IEEE 1394

3.3.2 Device Power States

To unify nomenclature and provide consistent behavior across devices, standard definitions are used for the power states of devices. Generally, these states are defined in terms of the following criteria:

- Power consumption--How much power the device uses.
- Device context--How much of the context of the device is retained by the hardware.
- Device driver--What the device driver must do to restore the device to fully on.
- Restore latency--How long it takes to restore the device to fully on.

More specifically, power management specifications for each class of device (for example, modem, network adapter, hard disk, and so on) more precisely define the power states and power policy for the class. See Section 2.3, "Device Power State Definitions," for the detailed description of the general device power states (D0-D3).

3.3.3 Device Power State Definitions

The device power state definitions are device-independent, but classes of devices on a bus must support some consistent set of power-related characteristics. For example, when the bus-specific mechanism to set the device power state to a given level is invoked, the actions a device might take and the specific sorts of behaviors the OS can assume while the device is in that state will vary from device type to device type. For a fully integrated device power management system, these class-specific power characteristics must also be standardized:

Device Power State Characteristics.

Each class of device has a standard definition of target power consumption levels, state-change latencies, and context loss.

Minimum Device Power Capabilities.

Each class of device has a minimum standard set of power capabilities.

Device Functional Characteristics.

Each class of device has a standard definition of what subset of device functionality or features is available in each power state (for example, the net card can receive, but cannot transmit; the sound card is fully functional except that the power amps are off, and so on).

Device Wakeup Characteristics.

Each class of device has a standard definition of its wake policy.

The Microsoft Device Class Power Management specifications define these power state characteristics for each class of device.

3.4 Controlling Device Power

ACPI interfaces provides control and information needed to perform device power management. ACPI interfaces describe to OSPM the capabilities of all the devices it controls. It also gives the OS the control methods used to set the power state or get the power status for each device. Finally, it has a general scheme for devices to wake the machine.

Note: Other buses enumerate some devices on the main board. For example, PCI devices are reported through the standard PCI enumeration mechanisms. Power management of these devices is handled through their own bus specification (in this case, PCI). All other devices on the main board are handled through ACPI. Specifically, the ACPI table lists legacy devices that cannot be reported through their own bus specification, the root of each bus in the system, and devices that have additional power management or configuration options not covered by their own bus specification.

For more detailed information see Section 7, "Power and Performance Management."

3.4.1 Getting Device Power Capabilities

As the OS enumerates devices in the system, it gets information about the power management features that the device supports. The Differentiated Definition Block given to the OS by the BIOS describes every device handled by ACPI. This description contains the following information:

- A description of what power resources (power planes and clock sources) the device needs in each power state that the device supports. For example, a device might need a high power bus and a clock in the D0 state but only a low-power bus and no clock in the D2 state.
- A description of what power resources a device needs in order to wake the machine (or none to indicate that the device does not support wake). The OS can use this information to infer what device and system power states from which the device can support wake.
- The optional control method the OS can use to set the power state of the device and to get and set resources.

In addition to describing the devices handled by ACPI, the table lists the power planes and clock sources themselves and the control methods for turning them on and off. For detailed information, see Section 7, "Power and Performance Management."

3.4.2 Setting Device Power States

OSPM uses the Set Power State operation to put a device into one of the four power states.

When a device is put in a lower power state, it configures itself to draw as little power from the bus as possible. The OS tracks the state of all devices on the bus, and will put the bus in the best power state based on the current device requirements on that bus. For example, if all devices on a bus are in the D3 state, the OS will send a command to the bus control chip set to remove power from the bus (thus putting the bus in the D3 state). If a particular bus supports a low-power supply state, the OS puts the bus in that state if all devices are in the D1 or D2 state. Whatever power state a device is in, the OS must be able to issue a Set Power State command to resume the device.

Note: The device does not need to have power to do this. The OS must turn on power to the device before it can send commands to the device.

OSPM also uses the Set Power State operation to enable power management features such as wake (described in <u>Section 7</u>, "Power and Performance Management.").

Once the power resources have been switched, the OS executes the appropriate control method to put the device in that power state. Notice that this might not mean that power is removed from the device. If other active devices are sharing a power resource, the power resources will remain on.

3.4.3 Getting Device Power Status

OSPM uses the Get Power Status operation to determine the current power configuration (states and features), as well as the status of any batteries supported by the device. The device can signal an SCI to inform the OS of changes in power status. For example, a device can trigger an interrupt to inform the OS that the battery has reached low power level.

Devices use the ACPI event model to signal power status changes (for example, battery status changes) to OSPM. The platform signals events to the OS via the SCI interrupt. An SCI interrupt status bit is set to indicate the event to the OS. The OS runs the control method associated with the event. This control method signals to the OS which device has changed.

ACPI supports two types of batteries: batteries that report only basic battery status information and batteries that support the Smart Battery System Implementers Forum Smart Battery Specification. For batteries that report only basic battery status information (such as total capacity and remaining capacity), the OS uses control methods from the battery's description table to read this information.

To read status information for Smart Batteries, the OS can use a standard Smart Battery driver that directly interfaces to Smart Batteries through the appropriate bus enumerator.

3.4.4 Waking the Computer

The wake operation enables devices to wake the computer from a sleeping power state. This operation must not depend on the CPU because the CPU will not be executing instructions.

The OS ensures any bridges between the device and the core logic are in the lowest power state in which they can still forward the wake signal. When a device with wake enabled decides to wake the machine, it sends the defined signal on its bus. Bus bridges must forward this signal to upstream bridges using the appropriate signal for that bus. Thus, the signal eventually reaches the core chip set (for example, an ACPI chip set), which in turn wakes the machine.

Before putting the machine in a sleeping power state, the OS determines which devices are needed to wake the machine based on application requests, and then enables wake on those devices in a device and bus specific manner.

The OS enables the wake feature on devices by setting that device's SCI Enable bit. The location of this bit is listed in the device's entry in the description table. Only devices that have their wake feature enabled can wake the machine. The OS keeps track of the power states that the wake devices support, and keeps the machine in a power state in which the wake can still wake the machine (based on capabilities reported in the description table).

When the computer is in the Sleeping state and a wake device decides to wake the machine, it signals to the ACPI chip set. The SCI status bit corresponding to the device waking the machine is set, and the ACPI chip set resumes the machine. After the OS is running again, it clears the bit and handles the event that caused the wake. The control method for this event then uses the Notify command to tell the OS which device caused the wake.

Note: Besides using ACPI mechanism to enable a particular device to wake the system, an ACPI platform must also be able to record and report the wake source to OSPM. When a system is woken from certain states (such as the S4 state), it may start out in non-ACPI mode. In this case, the SCI status bit may be cleared when ACPI mode is re-entered. However the platform must still attempt to record the wake source for retrieval by OSPM at a later point.

Note: Although the above description explains how a device can wake the system, note that a device can also be put into a low power state during the S0 system state, and that this device may generate a wake signal in the S0 state as the following example illustrates.

3.4.5 Example: Modem Device Power Management

To illustrate how these power management methods function in ACPI, consider an integrated modem. (This example is greatly simplified for the purposes of this discussion.) The power states of a modem are defined as follows (this is an excerpt from the Modem Device Class Power Management Specification):

^{1.} Some OS policies may require the OS to put the machine into a global system state for which the device can no longer wake the system. Such as when a system has very low battery power.

ACPI Overview

 $\mathbf{D0}$

Modem controller on Phone interface on Speaker on

Can be on hook or off hook Can be waiting for answer

D1

Modem controller in low-power mode (context retained by device) Phone interface powered by phone line or in low-power mode Speaker off

Must be on hook

D2

Same as **D3**

D3

Modem controller off (context lost)
Phone interface powered by phone line or off
Speaker off
On hook

The power policy for the modem is defined as follows:

D3 D0

COM port opened

D0, D1 D3

COM port closed

D0 D1

Modem put in answer mode

D1 D0

Application requests dial or the phone rings while the modem is in answer mode

The wake policy for the modem is very simple: When the phone rings and wake is enabled, wake the machine.

Based on that policy, the modem and the COM port to which it is attached can be implemented in hardware as shown in Figure 3-2. This is just an example for illustrating features of ACPI. This example is not intended to describe how OEMs should build hardware.




Figure 3-3 Example Modem and COM Port Hardware

Note: Although not shown above, each discrete part has some isolation logic so that the part is isolated when power is removed from it. Isolation logic controls are implemented as power resources in the ACPI Differentiated Description Block so that devices are isolated as power planes are sequenced off.

3.4.5.1 Obtaining the Modem Capabilities

The OS determines the capabilities of this modem when it enumerates the modem by reading the modem's entry in the Differentiated Definition Block. In this case, the entry for the modem would report:

The device supports **D0**, **D1**, and **D3**:

- D0 requires PWR1 and PWR2 as power resources
 D1 requires PWR1 as a power resource
 (D3 implicitly requires no power resources)
- To wake the machine, the modem needs no power resources (implying it can wake the machine from **D0**, **D1**, and **D3**)

Control methods for setting power state and resources

3.4.5.2 Setting the Modem Power State

While the OS is running (G0 state), it switches the modem to different power states according to the power policy defined for modems.

When an application opens the COM port, the OS turns on the modem by putting it in the D0 state. Then if the application puts the modem in answer mode, the OS puts the modem in the D1 state to wait for the call. To make this state transition, the ACPI first checks to see what power resources are no longer needed. In this case, PWR2 is not needed. Then it checks to make sure no other device in the system requires the use of the PWR2 power resource. If the resource is no longer needed, the OSPM uses the OFF control method associated with that power resource in the Differentiated

ACPI Overview

Definition Block to turn off the PWR2 power plane. This control method sends the appropriate commands to the core chip set to stop asserting the PWR2_EN line. Then, OSPM runs a control method (_PS1) provided in the modem's entry to put the device in the D1 state. This control method asserts the MDM_D1 signal that tells the modem controller to go into a low-power mode.

OSPM does not always turn off power resources when a given device is put in a lower power state. For example, assume that the PWR1 power plane also powers an active line printer (LPT) port. Suppose the user terminates the modem application, causing the COM port to be closed, and therefore causing the modem to be shut off (state D3). As always, OSPM checks to see which power resources are no longer needed. Because the LPT port is still active, PWR1 is in use. OSPM does not turn off the PWR1 resource. It continues the state transition process by running the modem's control method to switch the device to the D3 power state. The control method causes the MDM_D3 line to be asserted. The modem controller now turns off all its major functions so that it draws little power, if any, from the PWR1 line. Because the COM port is closed, the same sequence of events will take place to put it in the D3 state. Notice that these registers might not be in the device itself. For example, the control method could read the register that controls MDM_D3.

3.4.5.3 Obtaining the Modem Power Status

Integrated modems have no batteries; the only power status information for the device is the power state of the modem. To determine the modem's current power state (D0-D3), OSPM runs a control method (_PSC) supplied in the modem's entry in the Differentiated Definition Block. This control method reads from the necessary registers to determine the modem's power state.

3.4.5.4 Waking the Computer

As indicated in the modem capabilities, this modem can wake the machine from any device power state. Before putting the computer in a sleep state, the OS enables wake on any devices that applications have requested to be able to wake the machine. Then, it chooses the lowest sleeping state that can still provide the power resources necessary to allow all enabled wake devices to wake the machine. Next, the OS puts each of those devices in the appropriate power state, and puts all other devices in the D3 state. In this case, the OS puts the modem in the D3 state because it supports wake from that state. Finally, the OS saves a resume vector and puts the machine into a sleep state through an ACPI register.

Waking the computer via modem starts with the modem's phone interface asserting its ring indicate (RI) line when it detects a ring on the phone line. This line is routed to the core chip set to generate a wake event. The chip set then wakes the system and the hardware will eventually passes control back to the OS (the wake mechanism differs depending on the sleeping state). After the OS is running, it puts the device in the D0 state and begins handling interrupts from the modem to process the event.

3.5 Processor Power Management

To further save power in the Working state, the OS puts the CPU into low-power states (C1, C2, and C3) when the OS is idle. In these low-power states, the CPU does not run any instructions, and wakes when an interrupt, such as the OS scheduler's timer interrupt, occurs.

The OS determines how much time is being spent in its idle loop by reading the ACPI Power Management Timer. This timer runs at a known, fixed frequency and allows the OS to precisely

determine idle time. Depending on this idle time estimate, the OS will put the CPU into different quality low-power states (which vary in power and latency) when it enters its idle loop.

The CPU states are defined in detail in Section 8, "Processor Configuration and Control."

3.6 Device and Processor Performance States

This section describes the concept of device and processor performance states. Device and processor performance states (Px states) are power consumption and capability states within the active/executing states, C0 for processors and D0 for devices. Performance states allow OSPM to make tradeoffs between performance and energy conservation. Device and processor performance states have the greatest impact when the states invoke different device and processor efficiency levels as opposed to a linear scaling of performance and energy consumption. Since performance state transitions occur in the active/executing device states, care must be taken to ensure that performance state transitions do not adversely impact the system.

Examples of device performance states include:

- A hard drive that provides levels of maximum throughput that correspond to levels of power consumption.
- An LCD panel that supports multiple brightness levels that correspond to levels of power consumption.
- A graphics component that scales performance between 2D and 3D drawing modes that corresponds to levels of power consumption.
- An audio subsystem that provides multiple levels of maximum volume that correspond to levels of maximum power consumption.
- A Direct-RDRAMTM controller that provides multiple levels of memory throughput performance, corresponding to multiple levels of power consumption, by adjusting the maximum bandwidth throttles.

Processor performance states are described in Section 8, "Processor Configuration and Control."

3.7 Configuration and "Plug and Play"

In addition to power management, ACPI interfaces provide controls and information that enable OSPM to configure the required resources of motherboard devices along with their dynamic insertion and removal. ACPI Definition Blocks, including the Differentiated System Description Table (DSDT) and Secondary System Description Tables (SSDTs), describe motherboard devices in a hierarchical format called the ACPI namespace. The OS enumerates motherboard devices simply by reading through the ACPI Namespace looking for devices with hardware IDs.

Each device enumerated by ACPI includes ACPI-defined objects in the ACPI Namespace that report the hardware resources that the device could occupy, an object that reports the resources that are currently used by the device, and objects for configuring those resources. The information is used by the Plug and Play OS (OSPM) to configure the devices.

Note: When preparing to boot a computer, the BIOS only needs to configure boot devices. This includes boot devices described in the ACPI system description tables as well as devices that are controlled through other standards.

3.7.1 Device Configuration Example: Configuring the Modem

Returning to the modem device example above, the OS will find the modem and load a driver for it when the OS finds it in the DSDT. This table will have control methods that give the OS the following information:

- The device can use IRQ 3, I/O 3F8-3FF or IRQ 4, I/O 2E8-2EF
- The device is currently using IRQ 3, I/O 3F8-3FF

The OS configures the modem's hardware resources using Plug and Play algorithms. It chooses one of the supported configurations that does not conflict with any other devices. Then, OSPM configures the device for those resources by running a control method supplied in the modem's section of the Differentiated Definition Block. This control method will write to any I/O ports or memory addresses necessary to configure the device to the given resources.

3.7.2 NUMA Nodes

Systems employing a Non Uniform Memory Access (NUMA) architecture contain collections of hardware resources including processors, memory, and I/O buses, that comprise what is commonly known as a "NUMA node". Processor accesses to memory or I/O resources within the local NUMA node is generally faster than processor accesses to memory or I/O resources outside of the local NUMA node. ACPI defines interfaces that allow the platform to convey NUMA node topology information to OSPM both statically at boot time and dynamically at run time as resources are added or removed from the system.

3.8 System Events

ACPI includes a general event model used for Plug and Play, Thermal, and Power Management events. There are two registers that make up the event model: an event status register and an event enable register.

When an event occurs, the core logic sets a bit in the status register to indicate the event. If the corresponding bit in the enable register is set, the core logic will assert the SCI to signal the OS. When the OS receives this interrupt, it will run the control methods corresponding to any bits set in the event status register. These control methods use AML commands to tell the OS what event occurred.

For example, assume a machine has all of its Plug and Play, Thermal, and Power Management events connected to the same pin in the core logic. The event status and event enable registers would only have one bit each: the bit corresponding to the event pin.

When the computer is docked, the core logic sets the status bit and signals the SCI. The OS, seeing the status bit set, runs the control method for that bit. The control method checks the hardware and determines the event was a docking event (for example). It then signals to the OS that a docking event has occurred, and can tell the OS specifically where in the device hierarchy the new devices will appear.

Since the event model registers are generalized, they can describe many different platform implementations. The single pin model above is just one example. Another design might have Plug and Play, Thermal, and Power Management events wired to three different pins so there would be three status bits (and three enable bits). Yet another design might have every individual event wired to its own pin and status bit. This design, at the opposite extreme from the single pin design, allows very complex hardware, yet very simple control methods. Countless variations in wiring up events are possible. However, note that care must be taken to ensure that if events share a signal that the event that generated the signal can be determined in the corresponding event handling control method allowing the proper device notification to be sent.

3.9 Battery Management

Battery management policy moves from the APM BIOS to the ACPI-compatible OS. Batteries must comply with the requirements of their associated interfaces, as described either herein or in other applicable standards. The OS may choose to alter the behavior of the battery, for example, by adjusting the Low Battery or Battery Warning trip point. When there are multiple batteries present, the battery subsystem is not required to perform any synthesis of a "composite battery" from the data of the separate batteries. In cases where the battery subsystem does not synthesize a "composite battery" from the separate battery's data, the OS must provide that synthesis.

An ACPI-compatible battery device needs either a Smart Battery subsystem interface or a Control Method Battery interface.

- *Smart Battery* is controlled by the OS directly through the embedded controller (EC). For more information about the ACPI Embedded Controller SMBus interface, see <u>Section 12.9</u>, "SMBus Host Controller Interface via Embedded Controller." For additional information about the Smart Battery subsystem interface, see <u>Section 10.1</u>, "Smart Battery Subsystems."
- Control Method Battery is completely accessed by AML code control methods, allowing the
 OEM to choose any type of battery and any kind of communication interface supported by
 ACPI. For more information about the Control Method Battery Interface, see Section 10.2,
 "Control Method Batteries."

This section describes concepts common to all battery types.

3.9.1 Battery Communications

Both the Smart Battery and Control Method Battery interfaces provide a mechanism for the OS to query information from the platform's battery system. This information may include full charged capacity, present battery capacity, rate of discharge, and other measures of the battery's condition. All battery system types must provide notification to the OS when there is a change such as inserting or removing a battery, or when a battery starts or stops discharging. Smart Batteries and some Control Method Batteries are also able to give notifications based on changes in capacity. Smart batteries provide extra information such as estimated run-time, information about how much power the battery is able to provide, and what the run-time would be at a predetermined rate of consumption.

3.9.2 Battery Capacity

Each battery must report its designed capacity, latest full-charged capacity, and present remaining capacity. Remaining capacity decreases during usage, and it also changes depending on the environment. Therefore, the OS must use latest full-charged capacity to calculate the battery percentage. In addition the battery system must report warning and low battery levels at which the user must be notified and the system transitioned to a sleeping state. See<u>Figure 3-4</u> for the relation of these five values.

A system may use either rate and capacity [mA/mAh] or power and energy [mW/mWh] for the unit of battery information calculation and reporting. Mixing [mA] and [mW] is not allowed on a system.




Figure 3-4 Reporting Battery Capacity

3.9.3 Battery Gas Gauge

At the most basic level, the OS calculates Remaining Battery Percentage [%] using the following formula:

Figure 3-5 Remaining Battery Percent Formula

Control Method Battery also reports the Present Drain Rate [mA or mW] for calculating the remaining battery life. At the most basic level, Remaining Battery life is calculated by following formula:

Figure 3-6 Re; maining Battery Life Formula

Smart Batteries also report the present rate of drain, but since they can directly report the estimated run-time, this function should be used instead as it can more accurately account for variations specific to the battery.

3.9.4 Low Battery Levels

A system has an OEM-designed initial capacity for warning, initial capacity for low, and a critical battery level or flag. The values for warning and low represent the amount of energy or battery capacity needed by the system to take certain actions. The critical battery level or flag is used to indicate when the batteries in the system are completely drained. OSPM can determine independent warning and low battery capacity values based on the OEM-designed levels, but cannot set these values lower than the OEM-designed values, as shown in the figure below




Figure 3-7 Low Battery and Warning

Each Control Method Battery in a system reports the OEM-designed initial warning capacity and OEM-designed initial low capacity as well as a flag to report when that battery has reached or is below its critical energy level. Unlike Control Method Batteries, Smart Batteries are not necessarily specific to one particular machine type, so the OEM-designed warning, low, and critical levels are reported separately in a Smart Battery Table described in Section 5.2.14.

The table below describes how these values should be set by the OEM and interpreted by the OS.

Table 3-4 Low Battery Levels

Level	Description
Warning	When the total available energy (mWh) or capacity (mAh) in the batteries falls below this level, the OS will notify the user through the UI. This value should allow for a few minutes of run-time before the "Low" level is encountered so the user has time to wrap up any important work, change the battery, or find a power outlet to plug the system in.

Level	Description
Low	This value is an estimation of the amount of energy or battery capacity required by the system to transition to any supported sleeping state. When the OS detects that the total available battery capacity is less than this value, it will transition the system to a user defined system state (S1-S5). In most situations this should be S4 so that system state is not lost if the battery eventually becomes completely empty. The design of the OS should consider that users of a multiple battery system may remove one or more of the batteries in an attempt replace or charge it. This might result in the remaining capacity falling below the "Low" level not leaving sufficient battery capacity for the OS to safely transition the system into the sleeping state. Therefore, if the batteries are discharging simultaneously, the action might need to be initiated at the point when both batteries reach this level.
Critical	The Critical battery state indicates that all available batteries are discharged and do not appear to be able to supply power to run the system any longer. When this occurs, the OS must attempt to perform an emergency shutdown as described below. For a smart battery system, this would typically occur when all batteries reach a capacity of 0, but an OEM may choose to put a larger value in the Smart Battery Table to provide an extra margin of safely. For a Control Method Battery system with multiple batteries, the flag is reported per battery. If any battery in the system is in a critically low state and is still providing power to the system (in other words, the battery is discharging), the system is considered to be in a critical energy state. The _BST control method is required to return the Critical flag on a discharging battery only when all batteries have reached a critical state; the ACPI BIOS is otherwise required to switch to a non-critical battery.

3.9.4.1 Emergency Shutdown

Running until all batteries in a system are critical is not a situation that should be encountered normally, since the system should be put into a sleeping state when the battery becomes low. In the case that this does occur, the OS should take steps to minimize any damage to system integrity. The emergency shutdown procedure should be designed to minimize bad effects based on the assumption that power may be lost at any time. For example, if a hard disk is spun down, the OS should not try to spin it up to write any data, since spinning up the disk and attempting to write data could potentially corrupt files if the write were not completed. Even if a disk is spun up, the decision to attempt to save even system settings data before shutting down would have to be evaluated since reverting to previous settings might be less harmful than having the potential to corrupt the settings if power was lost halfway through the write operation.

3.9.5 Battery Calibration

The reported capacity of many batteries generally degrade over time, providing less run time for the user. However, it is possible with many battery systems to provide more useable runtime on an old battery if a calibration or conditioning cycle is run occasionally. The user has typically been able to perform a calibration cycle either by going into the BIOS setup menu, or by running a custom driver and calibration application provided by the OEM. The calibration process typically takes several hours, and the laptop must be plugged in during this time. Ideally the application that controls this should make this as good of a user experience as possible, for example allowing the user to schedule the system to wake up and perform the calibration at some time when the system will not be in use.

Since the calibration user experience does not need to be different from system to system it makes sense for this service to be provided by the OSPM. In this way OSPM can provide a common experience for end users and eliminate the need for OEMs to develop custom battery calibration software.

In order for OSPM to perform generic battery calibration, generic interfaces to control the two basic calibration functions are required. These functions are defined in Section 10.2.2.5 and Section 10.2.2.6. First, there is a means to detect when it would be beneficial to calibrate the battery. Second there is a means to perform that calibration cycle. Both of those functions may be implemented by dedicated hardware such as a battery controller chip, by firmware in the embedded controller, by the BIOS, or by OSPM. From here on any function implemented through AML, whether or not the AML code relies on hardware, will be referred to as "AML controlled" since the interface is the same whether the AML passes control to the hardware or not.

Detection of when calibration is necessary can be implemented by hardware or AML code and be reported through the _BMD method. Alternately, the _BMD method may simply report the number of cycles before calibration should be performed and let the OS attempt to count the cycles. A counter implemented by the hardware or the BIOS will generally be more accurate since the batteries can be used without the OS running, but in some cases, a system designer may opt to simplify the hardware or BIOS implementation.

When calibration is desirable and the user has scheduled the calibration to occur, the calibration cycle can be AML controlled or OSPM controlled. OSPM can only implement a very simple algorithm since it doesn't have knowledge of the specifics of the battery system. It will simply discharge the battery until it quits discharging, then charge it until it quits charging. In the case where the AC adapter cannot be controlled through the _BMC, it will prompt the user to unplug the AC adapter and reattach it after the system powers off. If the calibration cycle is controlled by AML, the OS will initiate the calibration cycle by calling _BMC. That method will either give control to the hardware, or will control the calibration cycle itself. If the control of the calibration cycle is implemented entirely in AML code, the BIOS may avoid continuously running AML code by having the initial call to _BMC start the cycle, set some state flags, and then exit. Control of later parts of the cycle can be accomplished by putting code that checks these state flags in the battery event handler (Qxx, Lxx, or Exx).

Details of the control methods for this interface are defined in <u>Section 10.2</u>.

3.10 Thermal Management

ACPI allows the OS to play a role in the thermal management of the system while maintaining the platform's ability to mandate cooling actions as necessary. In the passive cooling mode, OSPM can make cooling decisions based on application load on the CPU as well as the thermal heuristics of the system. OSPM can also gracefully shutdown the computer in case of high temperature emergencies.

The ACPI thermal design is based around regions called thermal zones. Generally, the entire PC is one large thermal zone, but an OEM can partition the system into several logical thermal zones if necessary. Figure 3-8 is an example mobile PC diagram that depicts a single thermal zone with a central processor as the thermal-coupled device. In this example, the whole notebook is covered as one large thermal zone. This notebook uses one fan for active cooling and the CPU for passive cooling.




Figure 3-8 Thermal Zone

The following sections are an overview of the thermal control and cooling characteristics of a computer. For some thermal implementation examples on an ACPI platform, see <u>Section 11.6</u>, "Thermal Zone Interface Requirements."

3.10.1 Active and Passive Cooling Modes

ACPI defines two cooling modes, Active and Passive:

Passive cooling

OS reduces the power consumption of devices at the cost of system performance to reduce the temperature of the machine.

Active cooling

OS increases the power consumption of the system (for example, by turning on a fan) to reduce the temperature of the machine.

These two cooling modes are inversely related to each other. Active cooling requires increased power to reduce the heat within the system while Passive cooling requires reduced power to decrease the temperature. The effect of this relationship is that Active cooling allows maximum system performance, but it may create undesirable fan noise, while Passive cooling reduces system performance, but is inherently quiet.

3.10.2 Performance vs. Energy Conservation

A robust OSPM implementation provides the means for the end user to convey to OSPM a preference (or a level of preference) for either performance or energy conservation. Allowing the end user to choose this preference is most critical to mobile system users where maximizing system run-time on a battery charge often has higher priority over realizing maximum system performance.

A user's preference for performance corresponds to the Active cooling mode while a user's preference for energy conservation corresponds to the Passive cooling mode. ACPI defines an interface to convey the cooling mode to the platform. Active cooling can be performed with minimal OSPM thermal policy intervention. For example, the platform indicates through thermal zone parameters that crossing a thermal trip point requires a fan to be turned on. Passive cooling requires OSPM thermal policy to manipulate device interfaces that reduce performance to reduce thermal zone temperature.

3.10.3 Acoustics (Noise)

Active cooling mode generally implies that fans will be used to cool the system and fans vary in their audible output. Fan noise can be quite undesirable given the loudness of the fan and the ambient noise environment. In this case, the end user's physical requirement for fan silence may override the preference for either performance or energy conservation.

A user's desire for fan silence corresponds to the Passive cooling mode. Accordingly, a user's desire for fan silence also means a preference for energy conservation.

For more information on thermal management and examples of platform settings for active and passive cooling, see <u>Section 11</u>, "Thermal Management."

3.10.4 Multiple Thermal Zones

The basic thermal management model defines one thermal zone, but in order to provide extended thermal control in a complex system, ACPI specifies a multiple thermal zone implementation. Under a multiple thermal zone model, OSPM will independently manage several thermal-coupled devices and a designated thermal zone for each thermal-coupled device, using Active and/or Passive cooling methods available to each thermal zone. Each thermal zone can have more than one Passive and Active cooling device. Furthermore, each zone might have unique or shared cooling resources. In a multiple thermal zone configuration, if one zone reaches a critical state then OSPM must shut down the entire system.

3.11 Flexible Platform Architecture Support

ACPI defines mechanisms and models to accommodate platform architectures that deviate from the traditional PC. ACPI provides support for platform technologies that enable lower-power, lower cost, more design flexibility and more device diversity. This support is described in the following sections, and detailed in later chapters.

3.11.1 Hardware-reduced ACPI

ACPI offers an alternative platform interface model that removes ACPI hardware requirements for platforms that do not implement the PC Architecture. In the *Hardware-reduced ACPI* model, the

ACPI Overview

Fixed hardware interface requirements of Chapter 4 are removed, and Generic hardware interfaces are used instead. This provides the level of flexibility needed to innovate and differentiate in low-power hardware designs while enabling support by multiple Operating Systems.

Hardware-reduced ACPI has the following requirements:

- UEFI firmware interface for boot (Legacy BIOS is not supported).
- Boot in ACPI mode only (ACPI Enable, ACPI Disable, SMI_CMD and Legacy mode are not supported)
- No hardware resource sharing between OSPM and other asynchronous operating environments, such as UEFI Runtime Services or System Management Mode. (The Global Lock is not supported)
- No dependence on OS-support for maintaining cache coherency across processor sleep states (Bus Master Reload and Arbiter Disable are not supported)
- GPE block devices are not supported

Systems that do not meet the above requirements must implement the ACPI Fixed Hardware interface.

3.11.1.1 Interrupt-based Wake Events

On HW-reduced ACPI platforms, wakeup is an attribute of connected interrupts. Interrupts that are designed to wake the processor or the entire platform are defined as *wake-capable*. Wake-capable interrupts, when enabled by OSPM, wake the system when they assert.

3.11.2 Low-Power Idle

Platform architectures may support hardware power management models other than the traditional ACPI Sleep/Resume model. These are typically implemented in proprietary hardware and are capable of delivering low-latency, connected idle while saving as much energy as ACPI Sleep states. To support the diversity of hardware implementations, ACPI provides a mechanism for the platform to indicate to OSPM that such capability is available.

3.11.2.1 Low Power S0 Idle Capable Flag

This flag in the FADT informs OSPM whether a platform has advanced idle power capabilities such that S0 idle achieves savings similar to or better than those typically achieved in S3. With this flag, OSPM can keep the system in S0 idle for its low-latency response and its connectedness rather than transitioning to a system sleep state which has neither. The flag enables support for a diversity of platform implementations: traditional Sleep/Resume systems, systems with advanced idle power, systems that support neither, and systems that can support both, depending on the capabilities of the installed OS.

3.11.3 Connection Resources

General-purpose I/O (GPIO) and Simple Peripheral Bus (SPB) controllers are hardware resources provided in silicon solutions to enable flexible configuration of a broad range of system designs. These controllers can provide input, output, interrupt and serial communication connections to arbitrary devices in a system. The function to which one of these connections is put depends on the

specific device involved and the needs of the platform design. In order to support these platform technologies, ACPI defines a general abstraction for flexible connections.

In order to maintain compatibility with existing software models, ACPI abstracts these connections as hardware resources.

The Connection Resource abstraction mirrors the hardware functionality of GPIO and SPB controllers. Like other resources, these connections are allocated and configured before use. With the resources described by the platform, OSPM abstracts the underlying configuration from device drivers. Drivers, then, can be written for the device's function only, and reused with that functional hardware regardless of how it is integrated into a given system.

The key aspects of the Connection Resource abstraction are:

- GPIO and SPB controllers are enumerated as devices in the ACPI Namespace.
- GPIO Connection and SPB Connection resource types are defined.
- Namespace devices that are connected to GPIO or SPB controllers use Resource Template Macros to add Connection Resources to their resource methods (CRS, SRS, etc.).
- GPIO Connection Resources can be designated by the platform for use as *GPIO-signaled ACPI Events*.
- Connection Resources can be used by AML methods to access pins and peripherals through *GPIO and SPB operation regions*.

3.11.3.1 Supported Platforms

The HW-reduced ACPI and Low power S0 Idle Capable flags combine to represent 4 platform types that can be implemented. The following table enumerates these, as well as the intended OSPM behavior and specific platform requirements.

Table 3-5 Implementable Platform Types

Low Power S0 Idle Capable	Hardware- reduced ACPI	OSPM Behavior	Platform Implementation
0	0	Fixed hardware interface accessed for features, events and system power management. Traditional Sleep/Resume power management.	Implement Fixed-feature hardware interface.
0	1	Fixed-feature hardware interface not accessed. Sleep/Resume Power Management using FADT SLEEP_*_REG fields and Interrupt-based wake signaling.	Implement GPIO-signaled ACPI Events; Implement software alternatives to any ACPI fixed features, including the Sleep registers. Implement wake-capable interrupts for wake events.

ACPI Overview

Low Power S0 Idle Capable	Hardware- reduced ACPI	OSPM Behavior	Platform Implementation
1	0	Fixed hardware interface accessed for features and events. Platform-specific Low-power Idle power management.	Implement Fixed-feature hardware interface. Implement low-power hardware such that the platform achieves power savings in S0 similar to or better than those typically achieved in S3.
1	1	Fixed-feature hardware interface not accessed. Platform-specific Low-power Idle power management.	Implement GPIO-signaled ACPI Events; Implement software alternatives to any ACPI fixed features desired; Implement wake-capable interrupts for any wake events. Implement low-power hardware such that the platform achieves power savings in S0 similar to or better than those typically achieved in S3.

4

ACPI Hardware Specification

ACPI defines standard interface mechanisms that allow an ACPI-compatible OS to control and communicate with an ACPI-compatible hardware platform. These interface mechanisms are optional (See "Hardware-Reduced ACPI", below). However, if the ACPI Hardware Specification is implemented, platforms must comply with the requirements in this section.

This section describes the hardware aspects of ACPI.

ACPI defines "hardware" as a programming model and its behavior. ACPI strives to keep much of the existing legacy programming model the same; however, to meet certain feature goals, designated features conform to a specific addressing and programming scheme. Hardware that falls within this category is referred to as "fixed."

Although ACPI strives to minimize these changes, hardware engineers should read this section carefully to understand the changes needed to convert a legacy-only hardware model to an ACPI/Legacy hardware model or an ACPI-only hardware model.

ACPI classifies hardware into two categories: Fixed or Generic. Hardware that falls within the fixed category meets the programming and behavior specifications of ACPI. Hardware that falls within the generic category has a wide degree of flexibility in its implementation.

4.1 Hardware-Reduced ACPI

For certain classes of systems the ACPI Hardware Specification may not be adequate. Examples include legacy-free, UEFI-based platforms with recent processors, and those implementing mobile platform architectures. For such platforms, a Hardware-reduced ACPI mode is defined. Under this definition, the ACPI Fixed Hardware interface is not implemented, and software alternatives for many of the features it supports are used instead. Note, though, that Hardware-reduced ACPI is not intended to support every possible ACPI system that can be built today. Rather, it is intended to introduce new systems that are designed to be HW-reduced from the start. The ACPI HW Specification should be used if the platform cannot be designed to work without it. Specifically, the following features are not supported under the HW-reduced definition:

- The Global Lock, SMI_CMD, ACPI Enable and ACPI Disable. Hardware-reduced ACPI systems always boot in ACPI mode, and do not support hardware resource sharing between OSPM and other asynchronous operating environments, such as UEFI Runtime Services or System Management Mode.
- Bus Master Reload and Arbiter Disable. Systems that depend on OS use of these bits to maintain cache coherency across processor sleep states are not supported.
- GPE block devices are not supported.

Platforms that require the above features must implement the ACPI Hardware Specification.

Platforms that are designed for the Hardware-reduced ACPI definition must implement Revision 5 or greater of the Fixed ACPI Descriptor Table, and must set the HW_REDUCED_ACPI flag in the Flags field.

Note: FFH is permitted and applicable to both full and HW-reduced ACPI implementations.

4.1.1 Hardware-Reduced Events

HW-reduced ACPI platforms require alternatives to some of the features supported in the ACPI HW Specification, where none already exists. There are two areas that require such alternatives: The ACPI Platform Event Model, and System and Device Wakeup.

4.1.1.1 GPIO-Signaled Events

General Purpose Input/Output (GPIO) hardware can be used for signaling platform events. GPIO HW is a generalization of the GPE model, and is a shared hardware resource used for many applications. ACPI support for GPIO is described in section 3.11.3, "Connection Resources".

ACPI Events are signaled by GPIO interrupt connections, which describe the connection to a GPIO controller and pin, and which are mapped to the ACPI Event Handling mechanism via the ACPI Event Information namespace object (_AEI). OSPM treats GPIO Interrupt Connections listed in _AEI exactly as it does SCI interrupts: it executes the Event Method associated with the specific event. The name of the method to run is determined by the pin information contained in the GPIO Interrupt Connection resource.

GPIO-signaled events can also be wake events, just as GPE events can on traditional ACPI platforms. Designating which events are wake events is done through attributes of the GPIO Interrupt Connection resource used.

4.1.1.2 Interrupt-based Wake Events

Wake events on HW-reduced ACPI platforms are always caused by an interrupt reaching the processor. Therefore, there are two requirements for waking the system from a sleep or low-power idle state, or a device from a low-power state. First, the interrupt line must be Wake-Capable. Wake-capable interrupts are designed to be able to be delivered to the processor from low-power states. This implies that it must also cause the processor and any required platform hardware to power-up so that an Interrupt Service Routine can run. Secondly, an OS driver must enable the interrupt before entering a low-power state, or before OSPM puts the system into a sleep or low-power idle state.

Wake-capable interrupts are designated as such in their Extended Interrupt or GPIO Interrupt Connection resource descriptor.

4.2 Fixed Hardware Programming Model

Because of the changes needed for migrating legacy hardware to the fixed category, ACPI limits the features specified by fixed hardware. Fixed hardware features are defined by the following criteria:

- Performance sensitive features
- Features that drivers require during wake
- Features that enable catastrophic OS software failure recovery

ACPI defines register-based interfaces to fixed hardware. CPU clock control and the power management timer are defined as fixed hardware to reduce the performance impact of accessing this hardware, which will result in more quickly reducing a thermal condition or extending battery life. If this logic were allowed to reside in PCI configuration space, for example, several layers of drivers

would be called to access this address space. This takes a long time and will either adversely affect the power of the system (when trying to enter a low-power state) or the accuracy of the event (when trying to get a time stamp value).

Access to fixed hardware by OSPM allows OSPM to control the wake process without having to load the entire OS. For example, if PCI configuration space access is needed, the bus enumerator is loaded with all drivers used by the enumerator. Defining these interfaces in fixed hardware at addresses with which OSPM can communicate without any other driver's assistance, allows OSPM to gather information prior to making a decision as to whether it continues loading the entire OS or puts it back to sleep.

If elements of the OS fail, it may be possible for OSPM to access address spaces that need no driver support. In such a situation, OSPM will attempt to honor fixed power button requests to transition the system to the G2 state. In the case where OSPM event handler is no longer able to respond to power button events, the power button override feature provides a back-up mechanism to unconditionally transition the system to the soft-off state.

4.3 Generic Hardware Programming Model

Although the fixed hardware programming model requires hardware registers to be defined at specific address locations, the generic hardware programming model allows hardware registers to reside in most address spaces and provides system OEMs with a wide degree of flexibility in the implementation of specific functions in hardware. OSPM directly accesses the fixed hardware registers, but relies on OEM-provided ACPI Machine Language (AML) code to access generic hardware registers.

AML code allows the OEM to provide the means for OSPM to control a generic hardware feature's control and event logic.

The section entitled "ACPI Source Language Reference" describes the ACPI Source Language (ASL)—a programming language that OEMs use to create AML. The ASL language provides many of the operators found in common object-oriented programming languages, but it has been optimized to enable the description of platform power management and configuration hardware. An ASL compiler converts ASL source code to AML, which is a very compact machine language that the ACPI AML code interpreter executes.

AML does two things:

- Abstracts the hardware from OSPM
- Buffers OEM code from the different OS implementations

One goal of ACPI is to allow the OEM "value added" hardware to remain basically unchanged in an ACPI configuration. One attribute of value-added hardware is that it is all implemented differently. To enable OSPM to execute properly on different types of value added hardware, ACPI defines higher level "control methods" that it calls to perform an action. The OEM provides AML code, which is associated with control methods, to be executed by OSPM. By providing AML code, generic hardware can take on almost any form.

Another important goal of ACPI is to provide OS independence. To do this, the OEM AML code has to execute the same under any ACPI-compatible OS. ACPI allows for this by making the AML code interpreter part of OSPM. This allows OSPM to take care of synchronizing and blocking issues specific to each particular OS.

ACPI Hardware Specification

The generic feature model is represented in the following block diagram. In this model the generic feature is described to OSPM through AML code. This description takes the form of an object that sits in the ACPI Namespace associated with the hardware to which it is adding value.




Figure 4-9 Generic Hardware Feature Model

As an example of a generic hardware control feature, a platform might be designed such that the IDE HDD's D3 state has value-added hardware to remove power from the drive. The IDE drive would then have a reference to the AML **PowerResource** object (which controls the value added power plane) in its namespace, and associated with that object would be control methods that OSPM invokes to control the D3 state of the drive:

- **_PS0**: A control method to sequence the IDE drive to the D0 state.
- **_PS3**: A control method to sequence the IDE drive to the D3 state.
- **PSC**: A control method that returns the status of the IDE drive (on or off).

The control methods under this object provide an abstraction layer between OSPM and the hardware. OSPM understands how to control power planes (turn them on or off or to get their status) through its defined **PowerResource** object, while the hardware has platform-specific AML code (contained in the appropriate control methods) to perform the desired function. In this example, the platform would describe its hardware to the ACPI OS by writing and placing the AML code to turn the hardware off within the _PS3 control method. This enables the following sequence:

When OSPM decides to place the IDE drive in the D3 state, it calls the IDE driver and tells it to place the drive into the D3 state (at which point the driver saves the device's context).

When the IDE driver returns control, OSPM places the drive in the D3 state.

OSPM finds the object associated with the HDD and then finds within that object any AML code associated with the D3 state.

OSPM executes the appropriate _PS3 control method to control the value-added "generic" hardware to place the HDD into an even lower power state.

As an example of a generic event feature, a platform might have a docking capability. In this case, it will want to generate an event. Notice that all ACPI events generate an SCI, which can be mapped to any shareable system interrupt. In the case of docking, the event is generated when a docking has been detected or when the user requests to undock the system. This enables the following sequence:

OSPM responds to the SCI and calls the AML code event handler associated with that generic event. The ACPI table associates the hardware event with the AML code event handler.

The AML-code event handler collects the appropriate information and then executes an AML Notify command to indicate to OSPM that a particular bus needs re-enumeration.

The following sections describe the fixed and generic hardware feature set of ACPI. These sections enable a reader to understand the following:

- Which hardware registers are required or optional when an ACPI feature, concept or interface is required by a design guide for a platform class
- How to design fixed hardware features
- How to design generic hardware features
- The ACPI Event Model

4.4 Diagram Legends

The hardware section uses simplified logic diagrams to represent how certain aspects of the hardware are implemented. The following symbols are used in the logic diagrams to represent programming bits.

abla	Write-only control bit
\otimes	Enable, control or status bit
\boxtimes	Sticky status bit
##	Ouery value

The half round symbol with an inverted "V" represents a write-only control bit. This bit has the behavior that it generates its control function when it is set. Reads to write-only bits are treated as ignore by software (the bit position is masked off and ignored).

The round symbol with an "X" represents a programming bit. As an enable or control bit, software setting or clearing this bit will result in the bit being read as set or clear (unless otherwise noted). As a status bit it directly represents the value of the signal.

The square symbol represents a sticky status bit. A sticky status bit is set by the level (not edge) of a hardware signal (active high or active low). The bit is only cleared by software writing a "1" to its bit position.

The rectangular symbol represents a query value from the embedded controller. This is the value the embedded controller returns to the system software upon a query command in response to an SCI event. The query value is associated with the event control method that is scheduled to execute upon an embedded controller event.

4.5 Register Bit Notation

Throughout this section there are logic diagrams that reference bits within registers. These diagrams use a notation that easily references the register name and bit position. The notation is as follows:

Registername.Bit

ACPI Hardware Specification

Registername contains the name of the register as it appears in this specification *Bit* contains a zero-based decimal value of the bit position.

For example, the SLP_EN bit resides in the PM1x_CNT register bit 13 and would be represented in diagram notation as:

SLP_EN PM1x CNT.13

4.6 The ACPI Hardware Model

The ACPI hardware model is defined to allow OSPM to sequence the platform between the various global system states (G0-G3) as illustrated in the following figure by manipulating the defined interfaces. When first powered on, the platform finds itself in the global system state G3 or "Mechanical Off." This state is defined as one where power consumption is very close to zero—the power plug has been removed; however, the real-time clock device still runs off a battery. The G3 state is entered by any power failure, defined as accidental or user-initiated power loss.

The G3 state transitions into either the G0 working state or the Legacy state depending on what the platform supports. If the platform is an ACPI-only platform, then it allows a direct boot into the G0 working state by always returning the status bit SCI_EN set (1) (for more information, see Section 4.8.2.5, "Legacy/ACPI Select and the SCI Interrupt"). If the platform supports both legacy and ACPI operations (which is necessary for supporting a non-ACPI OS), then it would always boot into the Legacy state (illustrated by returning the SCI_EN clear (0)). In either case, a transition out of the G3 state requires a total boot of OSPM.

The Legacy system state is the global state where a non-ACPI OS executes. This state can be entered from either the G3 "Mechanical Off," the G2 "Soft Off," or the G0 "Working" states only if the hardware supports both Legacy and ACPI modes. In the Legacy state, the ACPI event model is disabled (no SCIs are generated) and the hardware uses legacy power management and configuration mechanisms. While in the Legacy state, an ACPI-compliant OS can request a transition into the G0 working state by performing an ACPI mode request. OSPM performs this transition by writing the ACPI_ENABLE value to the SMI_CMD, which generates an event to the hardware to transition the platform into ACPI mode. When hardware has finished the transition, it sets the SCI_EN bit and returns control back to OSPM. While in the G0 "working state," OSPM can request a transition to Legacy mode by writing the ACPI_DISABLE value to the SMI_CMD register, which results in the hardware going into legacy mode and resetting the SCI_EN bit LOW (for more information, see Section 4.8.2.5, "Legacy/ACPI Select and the SCI Interrupt").

The G0 "Working" state is the normal operating environment of an ACPI machine. In this state different devices are dynamically transitioning between their respective power states (D0, D1, D2, D3hot, or D3) and processors are dynamically transitioning between their respective power states (C0, C1, C2 or C3). In this state, OSPM can make a policy decision to place the platform into the system G1 "sleeping" state. The platform can only enter a single sleeping state at a time (referred to as the global G1 state); however, the hardware can provide up to four system sleeping states that have different power and exit latencies represented by the S1, S2, S3, or S4 states. When OSPM decides to enter a sleeping state it picks the most appropriate sleeping state supported by the hardware (OS policy examines what devices have enabled wake events and what sleeping states these support). OSPM initiates the sleeping transition by enabling the appropriate wake events and then programming the SLP_TYPx field with the desired sleeping state and then setting the

SLP_ENx bit. The system will then enter a sleeping state; when one of the enabled wake events occurs, it will transition the system back to the working state (for more information, see <u>Section 16</u>, "Waking and Sleeping").

Another global state transition option while in the G0 "working" state is to enter the G2 "soft off" or the G3 "mechanical off" state. These transitions represent a controlled transition that allows OSPM to bring the system down in an orderly fashion (unloading applications, closing files, and so on). The policy for these types of transitions can be associated with the ACPI power button, which when pressed generates an event to the power button driver. When OSPM is finished preparing the operating environment for a power loss, it will either generate a pop-up message to indicate to the user to remove power, in order to enter the G3 "Mechanical Off" state, or it will initiate a G2 "soft-off" transition by writing the value of the S5 "soft off" system state to the SLP_TYPx register and setting the SLP EN bit.

The G1 sleeping state is represented by four possible sleeping states that the hardware can support. Each sleeping state has different power and wake latency characteristics. The sleeping state differs from the working state in that the user's operating environment is frozen in a low-power state until awakened by an enabled wake event. No work is performed in this state, that is, the processors are not executing instructions. Each system sleeping state has requirements about who is responsible for system context and wake sequences (for more information, see Section 16, Waking and Sleeping").

The G2 "soft off" state is an OS initiated system shutdown. This state is initiated similar to the sleeping state transition (SLP_TYPx is set to the S5 value and setting the SLP_EN bit initiates the sequence). Exiting the G2 soft-off state requires rebooting the system. In this case, an ACPI-only machine will re-enter the G0 state directly (hardware returns the SCI_EN bit set), while an ACPI/Legacy machine transitions to the Legacy state (SCI_EN bit is clear).

ACPI Hardware Specification




Figure 4-10 Global States and Their Transitions

The ACPI architecture defines mechanisms for hardware to generate events and control logic to implement this behavior model. Events are used to notify OSPM that some action is needed, and control logic is used by OSPM to cause some state transition. ACPI-defined events are "hardware" or "interrupt" events. A hardware event is one that causes the hardware to unconditionally perform some operation. For example, any wake event will sequence the system from a sleeping state (S1, S2, S3, and S4 in the global G1 state) to the G0 working state (see Figure 16-70).

An interrupt event causes the execution of an event handler (AML code or an ACPI-aware driver), which allows the software to make a policy decision based on the event. For ACPI fixed-feature events, OSPM or an ACPI-aware driver acts as the event handler. For generic logic events OSPM will schedule the execution of an OEM-supplied AML control method associated with the event.

For legacy systems, an event normally generates an OS-transparent interrupt, such as a System Management Interrupt, or SMI. For ACPI systems the interrupt events need to generate an OS-visible interrupt that is shareable; edge-style interrupts will not work. Hardware platforms that want to support both legacy operating systems and ACPI systems support a way of re-mapping the interrupt events between SMIs and SCIs when switching between ACPI and legacy models. This is illustrated in the following block diagram.




Figure 4-11 Example Event Structure for a Legacy/ACPI Compatible Event Model

This example logic illustrates the event model for a sample platform that supports both legacy and ACPI event models. This example platform supports a number of external events that are power-related (power button, LID open/close, thermal, ring indicate) or Plug and Play-related (dock, status change). The logic represents the three different types of events:

OS Transparent Events

These events represent OEM-specific functions that have no OS support and use software that can be operated in an OS-transparent fashion (that is, SMIs).

Interrupt Events

These events represent features supported by ACPI-compatible operating systems, but are not supported by legacy operating systems. When a legacy OS is loaded, these events are mapped to the transparent interrupt (SMI# in this example), and when in ACPI mode they are mapped to an OS-visible shareable interrupt (SCI#). This logic is represented by routing the event logic through the decoder that routes the events to the SMI# arbiter when the SCI_EN bit is cleared, or to the SCI# arbiter when the SCI_EN bit is set.

Hardware events

These events are used to trigger the hardware to initiate some hardware sequence such as waking, resetting, or putting the machine to sleep unconditionally.

In this example, the legacy power management event logic is used to determine device/system activity or idleness based on device idle timers, device traps, and the global standby timer. Legacy power management models use the idle timers to determine when a device should be placed in a low-power state because it is idle—that is, the device has not been accessed for the programmed amount of time. The device traps are used to indicate when a device in a low-power state is being accessed by OSPM. The global standby timer is used to determine when the system should be

ACPI Hardware Specification

allowed to go into a sleeping state because it is idle—that is, the user interface has not been used for the programmed amount of time.

These legacy idle timers, trap monitors, and global standby timer are not used by OSPM in the ACPI mode. This work is handled by different software structures in an ACPI-compatible OS. For example, the driver model of an ACPI-compatible OS is responsible for placing its device into a low-power state (D1, D2, D3hot, or D3) and transitioning it back to the On state (D0) when needed. And OSPM is responsible for determining when the system is idle by profiling the system (using the PM Timer) and other knowledge it gains through its operating structure environment (which will vary from OS to OS). When the system is placed into the ACPI mode, these events no longer generate SMIs, as OSPM handles this function. These events are disabled through some OEM-proprietary method.

On the other hand, many of the hardware events are shared between the ACPI and legacy models (docking, the power button, and so on) and this type of interrupt event changes to an SCI event when enabled for ACPI. The ACPI OS will generate a request to the platform's hardware (BIOS) to enter into the ACPI mode. The BIOS sets the SCI_EN bit to indicate that the system has successfully entered into the ACPI mode, so this is a convenient mechanism to map the desired interrupt (SMI or SCI) for these events (as shown in Figure 4-3).

The ACPI architecture specifies some dedicated hardware not found in the legacy hardware model: the power management timer (PM Timer). This is a free running timer that the ACPI OS uses to profile system activity. The frequency of this timer is explicitly defined in this specification and must be implemented as described.

Although the ACPI architecture reuses most legacy hardware as is, it does place restrictions on where and how the programming model is generated. If used, all fixed hardware features are implemented as described in this specification so that OSPM can directly access the fixed hardware feature registers.

Generic hardware features are manipulated by ACPI control methods residing in the ACPI Namespace. These interfaces can be very flexible; however, their use is limited by the defined ACPI control methods (for more information, see Section 9, "ACPI Devices and Device Specific Objects"). Generic hardware usually controls power planes, buffer isolation, and device reset resources. Additionally, "child" interrupt status bits can be accessed via generic hardware interfaces; however, they have a "parent" interrupt status bit in the GP_STS register. ACPI defines eight address spaces that may be accessed by generic hardware implementations. These include:

- System I/O space
- System memory space
- PCI configuration space
- Embedded controller space
- System Management Bus (SMBus) space
- CMOS
- PCI BAR Target
- IPMI space

Generic hardware power management features can be implemented accessing spare I/O ports residing in any of these address spaces. The ACPI specification defines an optional embedded controller and SMBus interfaces needed to communicate with these associated address spaces.

4.6.1 Hardware Reserved Bits

ACPI hardware registers are designed such that reserved bits always return zero, and data writes to them have no side affects. OSPM implementations must write zeros to reserved bits in enable and status registers and preserve bits in control registers, and they will treat these bits as ignored.

4.6.2 Hardware Ignored Bits

ACPI hardware registers are designed such that ignored bits are undefined and are ignored by software. Hardware-ignored bits can return zero or one. When software reads a register with ignored bits, it masks off ignored bits prior to operating on the result. When software writes to a register with ignored bit fields, it preserves the ignored bit fields.

4.6.3 Hardware Write-Only Bits

ACPI hardware defines a number of write-only control bits. These bits are activated by software writing a 1 to their bit position. Reads to write-only bit positions generate undefined results. Upon reads to registers with write-only bits, software masks out all write-only bits.

4.6.4 Cross Device Dependencies

Cross Device Dependency is a condition in which an operation to a device interferes with the operation of other unrelated devices, or allows other unrelated devices to interfere with its behavior. This condition is not supportable and can cause platform failures. ACPI provides no support for cross device dependencies and suggests that devices be designed to not exhibit this behavior. The following two examples describe cross device dependencies:

4.6.4.1 Example 1: Related Device Interference

This example illustrates a cross device dependency where a device interferes with the proper operation of other unrelated devices. Device A has a dependency that when it is being configured it blocks all accesses that would normally be targeted for Device B. Thus, the device driver for Device B cannot access Device B while Device A is being configured; therefore, it would need to synchronize access with the driver for Device A. High performance, multithreaded operating systems cannot perform this kind of synchronization without seriously impacting performance.

To further illustrate the point, assume that Device A is a serial port and Device B is a hard drive controller. If these devices demonstrate this behavior, then when a software driver configures the serial port, accesses to the hard drive need to block. This can only be done if the hard disk driver synchronizes access to the disk controller with the serial driver. Without this synchronization, hard drive data will be lost when the serial port is being configured.

4.6.4.2 Example 2: Unrelated Device Interference

This example illustrates a cross-device dependency where a device demonstrates a behavior that allows other unrelated devices to interfere with its proper operation. Device A exhibits a

ACPI Hardware Specification

programming behavior that requires atomic back-to-back write accesses to successfully write to its registers; if any other platform access is able to break between the back-to-back accesses, then the write to Device A is unsuccessful. If the Device A driver is unable to generate atomic back-to-back accesses to its device, then it relies on software to synchronize accesses to its device with every other driver in the system; then a device cross dependency is created and the platform is prone to Device A failure.

4.7 ACPI Hardware Features

This section describes the different hardware features defined by the ACPI interface. These features are categorized as the following:

- Fixed Hardware Features
- Generic Hardware Features

Fixed hardware features reside in a number of the ACPI-defined address spaces at the locations described by the ACPI programming model. Generic hardware features reside in one of four address spaces (system I/O, system memory, PCI configuration, embedded controller, or serial device I/O space) and are described by the ACPI Namespace through the declaration of AML control methods.

Fixed hardware features have exact definitions for their implementation. Although many fixed hardware features are optional, if implemented they must be implemented as described since OSPM manipulates the registers of fixed hardware devices and expects the defined behavior. Functional fixed hardware provides functional equivalents of the fixed hardware feature interfaces as described in Section 4.3, "Functional Fixed Hardware."

Generic hardware feature implementation is flexible. This logic is controlled by OEM-supplied AML code (for more information, see Section 5, "ACPI Software Programming Model"), which can be written to support a wide variety of hardware. Also, ACPI provides specialized control methods that provide capabilities for specialized devices. For example, the Notify command can be used to notify OSPM from a generic hardware event handler (control method) that a docking or thermal event has taken place. A good understanding of this section and Section 5 of this specification will give designers a good understanding of how to design hardware to take full advantage of an ACPI-compatible OS.

Notice that the generic features are listed for illustration only, the ACPI specification can support many types of hardware not listed.

Table 4-6 Feature/Programming Model Summar	Table 4-6	Feature/F	Programming	⊦Model	Summary
--	-----------	-----------	-------------	--------	---------

Feature Name	Description	Programming Model
Power Management Timer	24-bit or 32-bit free running timer.	Fixed Hardware Feature Control Logic
Power Button	User pushes button to switch the system between the working and sleeping states.	Fixed Hardware Event and Control Logic or Generic Hardware Event and Logic
Sleep Button	User pushes button to switch the system between the working and sleeping state.	Fixed Hardware Event and Control Logic or Generic Hardware Event and Logic

Feature Name	Description	Programming Model
Power Button Override	User sequence (press the power button for 4 seconds) to turn off a hung system.	
Real Time Clock Alarm	Programmed time to wake the system.	Optional Fixed Hardware Event ^a
Sleep/Wake Control Logic	Logic used to transition the system between the sleeping and working states.	Fixed Hardware Control and Event Logic
Embedded Controller Interface	ACPI Embedded Controller protocol and interface, as described in Section 12, "ACPI Embedded Controller Interface Specification."	Generic Hardware Event Logic, must reside in the general-purpose register block
Legacy/ACPI Select	Status bit that indicates the system is using the legacy or ACPI power management model (SCI_EN).	Fixed Hardware Control Logic
Lid switch	Button used to indicate whether the system's lid is open or closed (mobile systems only).	Generic Hardware Event Feature
C1 Power State	Processor instruction to place the processor into a low-power state.	Processor ISA
C2 Power Control	Logic to place the processor into a C2 power state.	Fixed Hardware Control Logic
C3 Power Control	Logic to place the processor into a C3 power state.	Fixed Hardware Control Logic
Thermal Control	Logic to generate thermal events at specified trip points.	Generic Hardware Event and Control Logic (See description of thermal logic in <u>Section 3.10</u> , "Thermal Management.")
Device Power Management	Control logic for switching between different device power states.	Generic Hardware control logic
AC Adapter	Logic to detect the insertion and removal of the AC adapter.	Generic Hardware event logic
Docking/device insertion and removal	Logic to detect device insertion and removal events.	Generic Hardware event logic

a. RTC wakeup alarm is required, the fixed hardware feature status bit is optional.

4.8 ACPI Register Model

ACPI hardware resides in one of six address spaces:

- System I/O
- System memory
- PCI configuration
- SMBus
- Embedded controller
- Functional Fixed Hardware

ACPI Hardware Specification

Different implementations will result in different address spaces being used for different functions. The ACPI specification consists of fixed hardware registers and generic hardware registers. Fixed hardware registers are required to implement ACPI-defined interfaces. The generic hardware registers are needed for any events generated by value-added hardware.

ACPI defines register blocks. An ACPI-compatible system provides an ACPI table (the FADT, built in memory at boot-up) that contains a list of pointers to the different fixed hardware register blocks used by OSPM. The bits within these registers have attributes defined for the given register block. The types of registers that ACPI defines are:

- Status/Enable Registers (for events)
- Control Registers

If a register block is of the status/enable type, then it will contain a register with status bits, and a corresponding register with enable bits. The status and enable bits have an exact implementation definition that needs to be followed (unless otherwise noted), which is illustrated by the following diagram:




Figure 4-12 Block Diagram of a Status/Enable Cell

Notice that the status bit, which hardware sets by the Event Input being set in this example, can only be cleared by software writing a 1 to its bit position. Also, the enable bit has no effect on the setting or resetting of the status bit; it only determines if the SET status bit will generate an "Event Output," which generates an SCI when set if its enable bit is set.

ACPI also defines register groupings. A register grouping consists of two register blocks, with two pointers to two different blocks of registers, where each bit location within a register grouping is fixed and cannot be changed. The bits within a register grouping, which have fixed bit positions, can be split between the two register blocks. This allows the bits within a register grouping to reside in either or both register blocks, facilitating the ability to map bits within several different chips to the same register thus providing the programming model with a single register grouping bit structure.

OSPM treats a register grouping as a single register; but located in multiple places. To read a register grouping, OSPM will read the "A" register block, followed by the "B" register block, and then will logically "OR" the two results together (the SLP_TYP field is an exception to this rule). Reserved bits, or unused bits within a register block always return zero for reads and have no side effects for writes (which is a requirement).

The SLP_TYPx field can be different for each register grouping. The respective sleeping object _Sx contains a SLP_TYPa and a SLP_TYPb field. That is, the object returns a package with two integer values of 0-7 in it. OSPM will always write the SLP_TYPa value to the "A" register block followed by the SLP_TYPb value within the field to the "B" register block. All other bit locations will be written with the same value. Also, OSPM does not read the SLP_TYPx value but throws it away.




Figure 4-13 Example Fixed Hardware Feature Register Grouping

As an example, the above diagram represents a register grouping consisting of register block A and register block b. Bits "a" and "d" are implemented in register block B and register block A returns a zero for these bit positions. Bits "b", "c" and "e" are implemented in register block A and register block B returns a zero for these bit positions. All reserved or ignored bits return their defined ACPI values.

When accessing this register grouping, OSPM must read register block a, followed by reading register block b. OSPM then does a logical OR of the two registers and then operates on the results.

When writing to this register grouping, OSPM will write the desired value to register group A followed by writing the same value to register group B.

ACPI defines the following fixed hardware register blocks. Each register block gets a separate pointer from the FADT. These addresses are set by the OEM as static resources, so they are never changed—OSPM cannot re-map ACPI resources. The following register blocks are defined:

Registers	Register Blocks	Register Groupings
PM1a_STS PM1a_EN PM1b_STS PM1b_EN	PM1a_EVT_BLK	—— PM1 EVT Grouping
PM1a_CNT PM1b_CNT	PM1a_CNT_BLK	PM1 CNT Grouping
PM2_CNT	PM2_CNT_BLK	—— PM2 Control Block
PM_TMR	PM_TMR_BLK	—— PM Timer Block
P_CNT P_LVL2 P_LVL3	P_BLK —	—— Processor Block
GPE0_STS GPE0_EN	GPE0_BLK-	—— General Purpose Event 0 Block
GPE1_STS GPE1_EN	GPE1_BLK	General Purpose Event 1 Block

Figure 4-14 Register Blocks versus Register Groupings

The PM1 EVT grouping consists of the PM1a_EVT and PM1b_EVT register blocks, which contain the fixed hardware feature event bits. Each event register block (if implemented) contains two registers: a status register and an enable register. Each register grouping has a defined bit position

that cannot be changed; however, the bit can be implemented in either register block (A or B). The A and B register blocks for the events allow chipsets to vary the partitioning of events into two or more chips. For read operations, OSPM will generate a read to the associated A and B registers, OR the two values together, and then operate on this result. For write operations, OSPM will write the value to the associated register in both register blocks. Therefore, there are two rules to follow when implementing event registers:

- Reserved or unimplemented bits always return zero (control or enable).
- Writes to reserved or unimplemented bits have no affect.

The PM1 CNT grouping contains the fixed hardware feature control bits and consists of the PM1a_CNT_BLK and PM1b_CNT_BLK register blocks. Each register block is associated with a single control register. Each register grouping has a defined bit position that cannot be changed; however, the bit can be implemented in either register block (A or B). There are two rules to follow when implementing CNT registers:

- Reserved or unimplemented bits always return zero (control or enable).
- Writes to reserved or unimplemented bits have no affect.

The PM2_CNT_BLK register block currently contains a single bit for the arbiter disable function. The general-purpose event register contains the event programming model for generic features. All generic events, just as fixed events, generate SCIs. Generic event status bits can reside anywhere; however, the top-level generic event resides in one of the general-purpose register blocks. Any generic feature event status not in the general-purpose register space is considered a child or sibling status bit, whose parent status bit is in the general-purpose event register space. Notice that it is possible to have N levels of general-purpose events prior to hitting the GPE event status.

General-purpose event registers are described by two register blocks: The GPE0_BLK or the GPE1_BLK. Each register block is pointed to separately from within the FADT. Each register block is further broken into two registers: GPEx_STS and GPEx_EN. The status and enable registers in the general-purpose event registers follow the event model for the fixed hardware event registers.

4.8.1 ACPI Register Summary

The following tables summarize the ACPI registers:

Table 4-7 PM1 Event Registers

Register	Size (Bytes)	Address (relative to register block)
PM1a_STS	PM1_EVT_LEN/2	<pm1a_evt_blk></pm1a_evt_blk>
PM1a_EN	PM1_EVT_LEN/2	<pm1a_evt_blk>+PM1_EVT_LEN/2</pm1a_evt_blk>
PM1b_STS	PM1_EVT_LEN/2	<pm1b_evt_blk></pm1b_evt_blk>
PM1b_EN	PM1_EVT_LEN/2	<pm1b_evt_blk>+PM1_EVT_LEN/2</pm1b_evt_blk>

Table 4-8 PM1 Control Registers

Register	Size (Bytes)	Address (relative to register block)
PM1_CNTa	PM1_CNT_LEN	<pm1a_cnt_blk></pm1a_cnt_blk>
PM1_CNTb	PM1_CNT_LEN	<pm1b_cnt_blk></pm1b_cnt_blk>

Table 4-9 PM2 Control Register

Register	Size (Bytes)	Address (relative to register block)
PM2_CNT	PM2_CNT_LEN	<pm2_cnt_blk></pm2_cnt_blk>

Table 4-10 PM Timer Register

Register	Size (Bytes)	Address (relative to register block)
PM_TMR	PM_TMR_LEN	<pm_tmr_blk></pm_tmr_blk>

Table 4-11 Processor Control Registers

Register	Size (Bytes)	Address (relative to register block)
P_CNT	4	Either <p_blk> or specified by the PTC object (See Section 8.4.3.1, "PTC [Processor Throttling Control].")</p_blk>
P_LVL2	1	<p_blk>+4h</p_blk>
P_LVL3	1	<p_blk>+5h</p_blk>

Table 4-12 General-Purpose Event Registers

Register	Size (Bytes)	Address (relative to register block)
GPE0_STS	GPE0_LEN/2	<gpe0_blk></gpe0_blk>
GPE0_EN	GPE0_LEN/2	<gpe0_blk>+GPE0_LEN/2</gpe0_blk>
GPE1_STS	GPE1_LEN/2	<gpe1_blk></gpe1_blk>
GPE1_EN	GPE1_LEN/2	<gpe1_blk>+GPE1_LEN/2</gpe1_blk>

4.8.1.1 PM1 Event Registers

The PM1 event register grouping contains two register blocks: the PM1a_EVT_BLK is a required register block when the following ACPI interface categories are required by a class specific platform design guide:

- Power management timer control/status
- Processor power state control/status
- Global Lock related interfaces
- Power or Sleep button (fixed register interfaces)
- System power state controls (sleeping/wake control)

The PM1b_EVT_BLK is an optional register block. Each register block has a unique 32-bit pointer in the Fixed ACPI Table (FADT) to allow the PM1 event bits to be partitioned between two chips. If the PM1b_EVT_BLK is not supported, its pointer contains a value of zero in the FADT.

Each register block in the PM1 event grouping contains two registers that are required to be the same size: the PM1x_STS and PM1x_EN (where x can be "a" or "b"). The length of the registers is variable and is described by the PM1_EVT_LEN field in the FADT, which indicates the total length of the register block in bytes. Hence if a length of "4" is given, this indicates that each register contains two bytes of I/O space. The PM1 event register block has a minimum size of 4 bytes.

4.8.1.2 PM1 Control Registers

The PM1 control register grouping contains two register blocks: the PM1a_CNT_BLK is a required register block when the following ACPI interface categories are required by a class specific platform design guide:

- SCI/SMI routing control/status for power management and general-purpose events
- Processor power state control/status
- Global Lock related interfaces
- System power state controls (sleeping/wake control)

The PM1b_CNT_BLK is an optional register block. Each register block has a unique 32-bit pointer in the Fixed ACPI Table (FADT) to allow the PM1 event bits to be partitioned between two chips. If the PM1b_CNT_BLK is not supported, its pointer contains a value of zero in the FADT.

Each register block in the PM1 control grouping contains a single register: the PM1x_CNT. The length of the register is variable and is described by the PM1_CNT_LEN field in the FADT, which indicates the total length of the register block in bytes. The PM1 control register block must have a minimum size of 2 bytes.

4.8.1.3 PM2 Control Register

The PM2 control register is contained in the PM2_CNT_BLK register block. The FADT contains a length variable for this register block (PM2_CNT_LEN) that is equal to the size in bytes of the PM2_CNT register (the only register in this register block). This register block is optional, if not supported its block pointer and length contain a value of zero.

4.8.1.4 PM Timer Register

The PM timer register is contained in the PM_TMR_BLK register block. It is an optional register block that must be implemented when the power management timer control/status ACPI interface category is required by a class specific platform design guide.

If defined, this register block contains the register that returns the running value of the power management timer. The FADT also contains a length variable for this register block (PM_TMR_LEN) that is equal to the size in bytes of the PM_TMR register (the only register in this register block).

4.8.1.5 Processor Control Block (P_BLK)

There is an optional processor control register block for each processor in the system. As this is a homogeneous feature, all processors must have the same level of support. The ACPI OS will revert to the lowest common denominator of processor control block support. The processor control block contains the processor control register (P_CNT-a 32-bit performance control configuration register), and the P_LVL2 and P_LVL3 CPU sleep state control registers. The 32-bit P_CNT register controls the behavior of the processor clock logic for that processor, the P_LVL2 register is used to place the CPU into the C2 state, and the P_LVL3 register is used to place the processor into the C3 state.

4.8.1.6 General-Purpose Event Registers

The general-purpose event registers contain the root level events for all generic features. To facilitate the flexibility of partitioning the root events, ACPI provides for two different general-

purpose event blocks: GPE0_BLK and GPE1_BLK. These are separate register blocks and are not a register grouping, because there is no need to maintain an orthogonal bit arrangement. Also, each register block contains its own length variable in the FADT, where GPE0_LEN and GPE1_LEN represent the length in bytes of each register block.

Each register block contains two registers of equal length: GPEx_STS and GPEx_EN (where x is 0 or 1). The length of the GPE0_STS and GPE0_EN registers is equal to half the GPE0_LEN. The length of the GPE1_STS and GPE1_EN registers is equal to half the GPE1_LEN. If a generic register block is not supported then its respective block pointer and block length values in the FADT table contain zeros. The GPE0_LEN and GPE1_LEN do not need to be the same size.

4.8.2 Fixed Hardware Features

This section describes the fixed hardware features defined by ACPI.

4.8.2.1 Power Management Timer

The ACPI specification defines an optional power management timer that provides an accurate time value that can be used by system software to measure and profile system idleness (along with other tasks). The power management timer provides an accurate time function while the system is in the working (G0) state. To allow software to extend the number of bits in the timer, the power management timer generates an interrupt when the last bit of the timer changes (from 0 to 1 or 1 to 0). ACPI supports either a 24-bit or 32-bit power management timer. The PM Timer is accessed directly by OSPM, and its programming model is contained in fixed register space. The programming model can be partitioned in up to three different register blocks. The event bits are contained in the PM1_EVT register grouping, which has two register blocks, and the timer value can be accessed through the PM_TMR_BLK register block. A block diagram of the power management timer is illustrated in the following figure:




Figure 4-15 Power Management Timer

The power management timer is a 24-bit or 32-bit fixed rate free running count-up timer that runs off a 3.579545 MHz clock. The ACPI OS checks the FADT to determine whether the PM Timer is a 32-bit or 24-bit timer. The programming model for the PM Timer consists of event logic, and a read port to the counter value. The event logic consists of an event status and enable bit. The status bit is set any time the last bit of the timer (bit 23 or bit 31) goes from set to clear or clear to set. If the TMR_EN bit is set, then the setting of the TMR_STS will generate an ACPI event in the PM1_EVT register grouping (referred to as PMTMR_PME in the diagram). The event logic is only used to emulate a larger timer.

OSPM uses the read-only TMR_VAL field (in the PM TMR register grouping) to read the current value of the timer. OSPM never assumes an initial value of the TMR VAL field; instead, it reads an

initial TMR_VAL upon loading OSPM and assumes that the timer is counting. It is allowable to stop the Timer when the system transitions out of the working (G0/S0) state. The only timer reset requirement is that the timer functions while in the working state.

The PM Timer's programming model is implemented as a fixed hardware feature to increase the accuracy of reading the timer.

4.8.2.2 Console Buttons

ACPI defines user-initiated events to request OSPM to transition the platform between the G0 working state and the G1 sleeping, G2 soft off and G3 mechanical off states. ACPI also defines a recommended mechanism to unconditionally transition the platform from a hung G0 working state to the G2 soft-off state.

ACPI operating systems use power button events to determine when the user is present. As such, these ACPI events are associated with buttons in the ACPI specification.

The ACPI specification supports two button models:

- A single-button model that generates an event for both sleeping and entering the soft-off state. The function of the button can be configured using OSPM UI.
- A dual-button model where the power button generates a soft-off transition request and a sleeping button generates a sleeping transition request. The type of button implies the function of the button.

Control of these button events is either through the fixed hardware programming model or the generic hardware programming model (control method based). The fixed hardware programming model has the advantage that OSPM can access the button at any time, including when the system is crashed. In a crashed system with a fixed hardware power button, OSPM can make a "best" effort to determine whether the power button has been pressed to transition to the system to the soft-off state, because it doesn't require the AML interpreter to access the event bits.

4.8.2.2.1 Power Button

The power button logic can be used in one of two models: single button or dual button. In the single-button model, the user button acts as both a power button for transitioning the system between the G0 and G2 states and a sleeping button for transitioning the system between the G0 and G1 states. The action of the user pressing the button is determined by software policy or user settings. In the dual-button model, there are separate buttons for sleeping and power control. Although the buttons still generate events that cause software to take an action, the function of the button is now dedicated: the sleeping button generates a sleeping request to OSPM and the power button generates a waking request.

Support for a power button is indicated by a combination of the PWR_BUTTON flag and the power button device object, as shown in the following:

Table 4-13 Power Button Support

Indicated Support	PWR_BUTTON Flag	Power Button Device Object
Fixed hardware power button	Clear	Absent
Control method power button	Set	Present

The power button can also have an additional capability to unconditionally transition the system from a hung working state to the G2 soft-off state. In the case where OSPM event handler is no longer able to respond to power button events, the power button override feature provides a back-up mechanism to unconditionally transition the system to the soft-off state. This feature can be used when the platform doesn't have a mechanical off button, which can also provide this function. ACPI defines that holding the power button active for four seconds or longer will generate a power button override event.

4.8.2.2.1.1 Fixed Power Button




Figure 4-16 Fixed Power Button Logic

The fixed hardware power button has its event programming model in the PM1x_EVT_BLK. This logic consists of a single enable bit and sticky status bit. When the user presses the power button, the power button status bit (PWRBTN_STS) is unconditionally set. If the power button enable bit (PWRBTN_EN) is set and the power button status bit is set (PWRBTN_STS) due to a button press while the system is in the G0 state, then an SCI is generated. OSPM responds to the event by clearing the PWRBTN_STS bit. The power button logic provides debounce logic that sets the PWRBTN STS bit on the button press "edge."

While the system is in the G1 or G2 global states (S1, S2, S3, S4 or S5 states), any further power button press after the button press that transitioned the system into the sleeping state unconditionally sets the power button status bit and wakes the system, regardless of the value of the power button enable bit. OSPM responds by clearing the power button status bit and waking the system.

4.8.2.2.1.2 Control Method Power Button

The power button programming model can also use the generic hardware programming model. This allows the power button to reside in any of the generic hardware address spaces (for example, the embedded controller) instead of fixed space. If the power button is implemented using generic hardware, then the OEM needs to define the power button as a device with an _HID object value of "PNP0C0C," which then identifies this device as the power button to OSPM. The AML event handler then generates a Notify command to notify OSPM that a power button event was generated. While the system is in the working state, a power button press is a user request to transition the system into either the sleeping (G1) or soft-off state (G2). In these cases, the power button event handler issues the Notify command with the device specific code of 0x80. This indicates to OSPM to pass control to the power button driver (PNP0C0C) with the knowledge that a transition out of the G0 state is being requested. Upon waking from a G1 sleeping state, the AML event handler generates a notify command with the code of 0x2 to indicate it was responsible for waking the system.

The power button device needs to be declared as a device within the ACPI Namespace for the platform and only requires an HID. An example definition follows.

This example ASL code performs the following:

- Creates a device named "PWRB" and associates the Plug and Play identifier (through the _HID object) of "PNP0C0C."
- The Plug and Play identifier associates this device object with the power button driver.
- Creates an operational region for the control method power button's programming model: System I/O space at 0x200.
- Fields that are not accessed are written as zeros. These status bits clear upon writing a 1 to their bit position, therefore preserved would fail in this case.
- Creates a field within the operational region for the power button status bit (called PBP). In this case the power button status bit is a child of the general-purpose event status bit 0. When this bit is set, it is the responsibility of the ASL-code to clear it (OSPM clears the general-purpose status bits). The address of the status bit is 0x200.0 (bit 0 at address 0x200).
- Creates an additional status bit called PBW for the power button wake event. This is the next bit and its physical address would be 0x200.1 (bit 1 at address 0x200).
- Generates an event handler for the power button that is connected to bit 0 of the general-purpose event status register 0. The event handler does the following:
- Clears the power button status bit in hardware (writes a one to it).
- Notifies OSPM of the event by calling the Notify command passing the power button object and the device specific event indicator 0x80.

```
// Define a control method power button
Device(\_SB.PWRB){
    Name(_HID, EISAID("PNP0C0C"))
    Name(_{PRW}, Package(){0, 0x4})
    OperationRegion(\PHO, SystemIO, 0x200, 0x1)
    Field(\PHO, ByteAcc, NoLock, WriteAsZeros){
        PBP, 1,
                                   // sleep/off request
        PBW, 1
                                    // wakeup request
} // end of power button device object
Scope(\_GPE){
                                    // Root level event handlers
   Method(_L00){
                                    // uses bit 0 of GPO_STS register
        If(\PBP){
             Store(One, \PBP) // clear power button status
             Notify(\_SB.PWRB, 0x80) // Notify OS of event
        If(\PBW){
             Store(One, \PBW)
             Notify(\LSB.PWRB, 0x2)
        }
    } // end of _L00 handler
} // end of \_GPE scope
```

4.8.2.2.1.3 Power Button Override

The ACPI specification also allows that if the user presses the power button for more than four seconds while the system is in the working state, a hardware event is generated and the system will transition to the soft-off state. This hardware event is called a power button override. In reaction to the power button override event, the hardware clears the power button status bit (PWRBTN STS).

4.8.2.2.2 Sleep Button

When using the two button model, ACPI supports a second button that when pressed will request OSPM to transition the platform between the G0 working and G1 sleeping states. Support for a sleep button is indicated by a combination of the SLEEP_BUTTON flag and the sleep button device object:

Table 4-14 Sleep Button Support

Indicated Support	SLEEP_BUTTON Flag	Sleep Button Device Object
No sleep button	Set	Absent
Fixed hardware sleep button	Clear	Absent
Control method sleep button	Set	Present

4.8.2.2.2.1 Fixed Hardware Sleeping Button




Figure 4-17 Fixed Hardware Sleep Button Logic

The fixed hardware sleep button has its event programming model in the PM1x_EVT_BLK. This logic consists of a single enable bit and sticky status bit. When the user presses the sleep button, the sleep button status bit (SLPBTN_STS) is unconditionally set. Additionally, if the sleep button enable bit (SLPBTN_EN) is set, and the sleep button status bit is set (SLPBTN_STS, due to a button press) while the system is in the G0 state, then an SCI is generated. OSPM responds to the event by clearing the SLPBTN_STS bit. The sleep button logic provides debounce logic that sets the SLPBTN STS bit on the button press "edge."

While the system is sleeping (in either the S0, S1, S2, S3 or S4 states), any further sleep button press (after the button press that caused the system transition into the sleeping state) sets the sleep button status bit (SLPBTN_STS) and wakes the system if the SLP_EN bit is set. OSPM responds by clearing the sleep button status bit and waking the system.

4.8.2.2.2.2 Control Method Sleeping Button

The sleep button programming model can also use the generic hardware programming model. This allows the sleep button to reside in any of the generic hardware address spaces (for example, the embedded controller) instead of fixed space. If the sleep button is implemented via generic hardware, then the OEM needs to define the sleep button as a device with an _HID object value of "PNP0C0E", which then identifies this device as the sleep button to OSPM. The AML event handler then generates a Notify command to notify OSPM that a sleep button event was generated. While in the working state, a sleep button press is a user request to transition the system into the sleeping (G1) state. In these cases the sleep button event handler issues the Notify command with the device specific code of 0x80. This will indicate to OSPM to pass control to the sleep button driver (PNP0C0E) with the knowledge that the user is requesting a transition out of the G0 state. Upon

waking-up from a G1 sleeping state, the AML event handler generates a Notify command with the code of 0x2 to indicate it was responsible for waking the system.

The sleep button device needs to be declared as a device within the ACPI Namespace for the platform and only requires an _HID. An example definition is shown below.

The AML code below does the following:

- Creates a device named "SLPB" and associates the Plug and Play identifier (through the _HID object) of "PNP0C0E."
- The Plug and Play identifier associates this device object with the sleep button driver.
- Creates an operational region for the control method sleep button's programming model: System I/O space at 0x201.
- Fields that are not accessed are written as "1s" (these status bits clear upon writing a "1" to their bit position, hence preserved would fail in this case).
- Creates a field within the operational region for the sleep button status bit (called PBP). In this case the sleep button status bit is a child of the general-purpose status bit 0. When this bit is set it is the responsibility of the AML code to clear it (OSPM clears the general-purpose status bits). The address of the status bit is 0x201.0 (bit 0 at address 0x201).
- Creates an additional status bit called PBW for the sleep button wake event. This is the next bit and its physical address would be 0x201.1 (bit 1 at address 0x201).
- Generates an event handler for the sleep button that is connected to bit 0 of the general-purpose status register 0. The event handler does the following:
- Clears the sleep button status bit in hardware (writes a "1" to it).
- Notifies OSPM of the event by calling the Notify command passing the sleep button object and the device specific event indicator 0x80.

```
// Define a control method sleep button
Device(\_SB.SLPB){
    Name(_HID, EISAID("PNP0C0E"))
    Name(\_PRW, Package()\{0x01, 0x04\})
    OperationRegion(\Boo, SystemIO, 0x201, 0x1)
    Field(\Boo, ByteAcc, NoLock, WriteAsZeros){
        SBP, 1,
                                           // sleep request
        SBW, 1
                                            // wakeup request
    }
                                            // end of field definition
}
Scope(\_GPE){
                                            // Root level event handlers
                                            // uses bit 1 of GPO_STS register
    Method(_L01){
        If(\SBP){
              Store(One, \SBP)
                                            // clear sleep button status
              Notify(\_SB.SLPB, 0x80)
                                            // Notify OS of event
         If(\SBW){
              Store(One, \SBW)
              Notify(\_SB.SLPB, 0x2)
     } // end of _L01 handler
} // end of \_GPE scope
```

4.8.2.3 Sleeping/Wake Control

The sleeping/wake logic consists of logic that will sequence the system into the defined low-power hardware sleeping state (S1-S4) or soft-off state (S5) and will wake the system back to the working state upon a wake event. Notice that the S4BIOS state is entered in a different manner (for more information, see Section 16.1.4.2, "The S4BIOS Transition").




Figure 4-18 Sleeping/Wake Logic

The logic is controlled via two bit fields: Sleep Enable (SLP_EN) and Sleep Type (SLP_TYPx). The type of sleep state desired is programmed into the SLP_TYPx field and upon assertion of the SLP_EN the hardware will sequence the system into the defined sleeping state. OSPM gets values for the SLP_TYPx field from the $\$ Sx objects defined in the static definition block. If the object is missing OSPM assumes the hardware does not support that sleeping state. Prior to entering the desired sleeping state, OSPM will read the designated $\$ Sx object and place this value in the SLP TYP field.

Additionally ACPI defines a fail-safe Off protocol called the "power button override," which allows the user to initiate an Off sequence in the case where the system software is no longer able to recover the system (the system has hung). ACPI defines that this sequence be initiated by the user pressing the power button for over 4 seconds, at which point the hardware unconditionally sequences the system to the Off state. This logic is represented by the PWRBTN_OR signal coming into the sleep logic.

While in any of the sleeping states (G1), an enabled "Wake" event will cause the hardware to sequence the system back to the working state (G0). The "Wake Status" bit (WAK_STS) is provided for OSPM to "spin-on" after setting the SLP_EN/SLP_TYP bit fields. When waking from the S1 sleeping state, execution control is passed backed to OSPM immediately, whereas when waking from the S2-S5 states execution control is passed to the BIOS software (execution begins at the CPU's reset vector). The WAK_STS bit provides a mechanism to separate OSPM's sleeping and waking code during an S1 sequence. When the hardware has sequenced the system into the sleeping state (defined here as the processor is no longer able to execute instructions), any enabled wake event is allowed to set the WAK_STS bit and sequence the system back on (to the G0 state). If the system does not support the S1 sleeping state, the WAK_STS bit can always return zero.

-If more than a single sleeping state is supported, then the sleeping/wake logic is required to be able to dynamically sequence between the different sleeping states. This is accomplished by waking the system; OSPM programs the new sleep state into the SLP_TYP field, and then sets the SLP_EN bit—placing the system again in the sleeping state.

4.8.2.4 Real Time Clock Alarm

If implemented, the Real Time Clock (RTC) alarm must generate a hardware wake event when in the sleeping state. The RTC can be programmed to generate an alarm. An enabled RTC alarm can be used to generate a wake event when the system is in a sleeping state. ACPI provides for additional hardware to support OSPM in determining that the RTC was the source of the wake event: the RTC_STS and RTC_EN bits. Although these bits are optional, if supported they must be implemented as described here.

If the RTC_STS and RTC_EN bits are not supported, OSPM will attempt to identify the RTC as a possible wake source; however, it might miss certain wake events. If implemented, the RTC wake feature is required to work in the following sleeping states: S1-S3. S4 wake is optional and supported through the RTC_S4 flag within the FADT (if set, then the platform supports RTC wake in the S4 state)¹.

When the RTC generates a wake event the RTC_STS bit will be set. If the RTC_EN bit is set, an RTC hardware power management event will be generated (which will wake the system from a sleeping state, provided the battery low signal is not asserted).




Figure 4-19 RTC Alarm

The RTC wake event status and enable bits are an optional fixed hardware feature and a flag within the FADT (FIX_RTC) indicates if the register bits are to be used by OSPM. If the RTC wake event status and enable bits are implemented in fixed hardware, OSPM can determine if the RTC was the source of the wake event without loading the entire OS. This also gives the platform the capability of indicating an RTC wake source without consuming a GPE bit, as would be required if RTC wake was not implemented using the fixed hardware RTC feature. If the fixed hardware feature event bits are not supported, then OSPM will attempt to determine this by reading the RTC's status field. If the platform implements the RTC fixed hardware feature, and this hardware consumes resources, the __FIX method can be used to correlate these resources with the fixed hardware. See <u>Section 6.2.5</u>, "FIX (Fixed Register Resource Provide", for details.

OSPM supports enhancements over the existing RTC device (which only supports a 99 year date and 24-hour alarm). Optional extensions are provided for the following features:

Day Alarm.

The DAY_ALRM field points to an optional CMOS RAM location that selects the day within the month to generate an RTC alarm.

^{1.} Notice that the G2/S5 "soft off" and the G3 "mechanical off" states are not sleeping states. The OS will disable the RTC_EN bit prior to entering the G2/S5 or G3 states regardless.

Month Alarm.

The MON_ALRM field points to an optional CMOS RAM location that selects the month within the year to generate an RTC alarm.

Centenary Value.

The CENT field points to an optional CMOS RAM location that represents the centenary value of the date (thousands and hundreds of years).

The RTC_STS bit may be set through the RTC interrupt (IRQ8 in IA-PC architecture systems). OSPM will insure that the periodic and update interrupt sources are disabled prior to sleeping. This allows the RTC's interrupt pin to serve as the source for the RTC_STS bit generation. Note however that if the RTC interrupt pin is used for RTC_STS generation, the RTC_STS bit value may not be accurate when waking from S4. If this value is accurate when waking from S4, the platform should set the S4 RTC STS VALID flag, so that OSPM can utilize the RTC STS information.

Table 4-15 Alarm Field Decodings within the FADT

Field	Value	Address (Location) in RTC CMOS RAM (Must be Bank 0)
DAY_ALRM	Eight bit value that can represent 0x01-0x31 days in BCD or 0x01-0x1F days in binary. Bits 6 and 7 of this field are treated as Ignored by software. The RTC is initialized such that this field contains a "don't care" value when the BIOS switches from legacy to ACPI mode. A don't care value can be any unused value (not 0x1-0x31 BCD or 0x01-0x1F hex) that the RTC reverts back to a 24 hour alarm.	The DAY_ALRM field in the FADT will contain a non-zero value that represents an offset into the RTC's CMOS RAM area that contains the day alarm value. A value of zero in the DAY_ALRM field indicates that the day alarm feature is not supported.
MON_ALRM	Eight bit value that can represent 01-12 months in BCD or 0x01-0xC months in binary. The RTC is initialized such that this field contains a don't care value when the BIOS switches from legacy to ACPI mode. A "don't care" value can be any unused value (not 1-12 BCD or x01-xC hex) that the RTC reverts back to a 24 hour alarm and/or 31 day alarm).	The MON_ALRM field in the FADT will contain a non-zero value that represents an offset into the RTC's CMOS RAM area that contains the month alarm value. A value of zero in the MON_ALRM field indicates that the month alarm feature is not supported. If the month alarm is supported, the day alarm function must also be supported.
CENTURY	8-bit BCD or binary value. This value indicates the thousand year and hundred year (Centenary) variables of the date in BCD (19 for this century, 20 for the next) or binary (x13 for this century, x14 for the next).	The CENTURY field in the FADT will contain a non-zero value that represents an offset into the RTC's CMOS RAM area that contains the Centenary value for the date. A value of zero in the CENTURY field indicates that the Centenary value is not supported by this RTC.

4.8.2.5 Legacy/ACPI Select and the SCI Interrupt

As mentioned previously, power management events are generated to initiate an interrupt or hardware sequence. ACPI operating systems use the SCI interrupt handler to respond to events,

while legacy systems use some type of transparent interrupt handler to respond to these events (that is, an SMI interrupt handler). ACPI-compatible hardware can choose to support both legacy and ACPI modes or just an ACPI mode. Legacy hardware is needed to support these features for non-ACPI-compatible operating systems. When the ACPI OS loads, it scans the BIOS tables to determine that the hardware supports ACPI, and then if the it finds the SCI_EN bit reset (indicating that ACPI is not enabled), issues an ACPI activate command to the SMI handler through the SMI command port. The BIOS acknowledges the switching to the ACPI model of power management by setting the SCI_EN bit (this bit can also be used to switch over the event mechanism as illustrated below):




Figure 4-20 Power Management Events to SMI/SCI Control Logic

The interrupt events (those that generate SMIs in legacy mode and SCIs in ACPI mode) are sent through a decoder controlled by the SCI_EN bit. For legacy mode this bit is reset, which routes the interrupt events to the SMI interrupt logic. For ACPI mode this bit is set, which routes interrupt events to the SCI interrupt logic. This bit always returns set for ACPI-compatible hardware that does not support a legacy power management mode (in other words, the bit is wired to read as "1" and ignore writes).

The SCI interrupt is defined to be a shareable interrupt and is connected to an OS visible interrupt that uses a shareable protocol. The FADT has an entry that indicates what interrupt the SCI interrupt is mapped to (see Section 5.2.6, "System Description Table Header").

If the ACPI platform supports both legacy and ACPI modes, it has a register that generates a hardware event (for example, SMI for IA-PC processors). OSPM uses this register to make the hardware switch in and out of ACPI mode. Within the FADT are three values that signify the address (SMI_CMD) of this port and the data value written to enable the ACPI state (ACPI_ENABLE), and to disable the ACPI state (ACPI_DISABLE).

To transition an ACPI/Legacy platform from the Legacy mode to the ACPI mode the following would occur:

- ACPI driver checks that the SCI EN bit is zero, and that it is in the Legacy mode.
- OSPM does an OUT to the SMI_CMD port with the data in the ACPI_ENABLE field of the FADT.
- OSPM polls the SCI EN bit until it is sampled as SET.

To transition an ACPI/Legacy platform from the ACPI mode to the Legacy mode the following would occur:

• ACPI driver checks that the SCI EN bit is one, and that it is in the ACPI mode.

- OSPM does an OUT to the SMI_CMD port with the data in the ACPI_DISABLE field of the FADT.
- OSPM polls the SCI EN bit until it is sampled as RESET.

Platforms that only support ACPI always return a 1 for the SCI_EN bit. In this case OSPM skips the Legacy to ACPI transition stated above.

4.8.2.6 Processor Control

The ACPI specification defines several processor controls including power state control, throttling control, and performance state control. See <u>Section 8</u>, "Processor Configuration and Control," for a complete description of the processor controls.

4.8.3 Fixed Hardware Registers

The fixed hardware registers are manipulated directly by OSPM. The following sections describe fixed hardware features under the programming model. OSPM owns all the fixed hardware resource registers; these registers cannot be manipulated by AML code. Registers are accessed with any width up to its register width (byte granular).

4.8.3.1 PM1 Event Grouping

The PM1 Event Grouping has a set of bits that can be distributed between two different register blocks. This allows these registers to be partitioned between two chips, or all placed in a single chip. Although the bits can be split between the two register blocks (each register block has a unique pointer within the FADT), the bit positions are maintained. The register block with unimplemented bits (that is, those implemented in the other register block) always returns zeros, and writes have no side effects.

4.8.3.1.1 PM1 Status Registers

```
Register Location: <PM1a_EVT_BLK / PM1b_EVT_BLK> System I/O or Memory Space
Default Value: 00h
Attribute: Read/Write
Size: PM1_EVT_LEN / 2
```

The PM1 status registers contain the fixed hardware feature status bits. The bits can be split between two registers: PM1a_STS or PM1b_STS. Each register grouping can be at a different 32-bit aligned address and is pointed to by the PM1a_EVT_BLK or PM1b_EVT_BLK. The values for these pointers to the register space are found in the FADT. Accesses to the PM1 status registers are done through byte or word accesses.

For ACPI/legacy systems, when transitioning from the legacy to the G0 working state this register is cleared by BIOS prior to setting the SCI_EN bit (and thus passing control to OSPM). For ACPI only platforms (where SCI_EN is always set), when transitioning from either the mechanical off (G3) or soft-off state to the G0 working state this register is cleared prior to entering the G0 working state.

This register contains optional features enabled or disabled within the FADT. If the FADT indicates that the feature is not supported as a fixed hardware feature, then software treats these bits as ignored.

Table 4-16 PM1 Status Registers Fixed Hardware Feature Status Bits

Bit	Name	Description
0	TMR_STS	This is the timer carry status bit. This bit gets set any time the most significant bit of a 24/32-bit counter changes from clear to set or set to clear. While TMR_EN and TMR_STS are set, an interrupt event is raised.
1-3	Reserved	Reserved
4	BM_STS	This is the bus master status bit. This bit is set any time a system bus master requests the system bus, and can only be cleared by writing a "1" to this bit position. Notice that this bit reflects bus master activity, not CPU activity (this bit monitors any bus master that can cause an incoherent cache for a processor in the C3 state when the bus master performs a memory transaction).
5	GBL_STS	This bit is set when an SCI is generated due to the BIOS wanting the attention of the SCI handler. BIOS will have a control bit (somewhere within its address space) that will raise an SCI and set this bit. This bit is set in response to the BIOS releasing control of the Global Lock and having seen the pending bit set.
6-7	Reserved	Reserved. These bits always return a value of zero.
8	PWRBTN_STS	This optional bit is set when the Power Button is pressed. In the system working state, while PWRBTN_EN and PWRBTN_STS are both set, an interrupt event is raised. In the sleeping or soft-off state, a wake event is generated when the power button is pressed (regardless of the PWRBTN_EN bit setting). This bit is only set by hardware and can only be reset by software writing a "1" to this bit position. ACPI defines an optional mechanism for unconditional transitioning a system that has stopped working from the G0 working state into the G2 soft-off state called the power button override. If the Power Button is held active for more than four seconds, this bit is cleared by hardware and the system transitions into the G2/S5 Soft Off state (unconditionally). Support for the power button is indicated by the PWR_BUTTON flag in the FADT being reset (zero). If the PWR_BUTTON flag is set or a power button device object is present in the ACPI Namespace, then this bit field is ignored by OSPM. If the power button was the cause of the wake (from an S1-S4 state), then this bit is set prior to returning control to OSPM.
9	SLPBTN_STS	This optional bit is set when the sleep button is pressed. In the system working state, while SLPBTN_EN and SLPBTN_STS are both set, an interrupt event is raised. In the sleeping or soft-off states a wake event is generated when the sleeping button is pressed and the SLPBTN_EN bit is set. This bit is only set by hardware and can only be reset by software writing a "1" to this bit position. Support for the sleep button is indicated by the SLP_BUTTON flag in the FADT being reset (zero). If the SLP_BUTTON flag is set or a sleep button device object is present in the ACPI Namespace, then this bit field is ignored by OSPM. If the sleep button was the cause of the wake (from an S1-S4 state), then this bit is set prior to returning control to OSPM.

Bit	Name	Description
10	RTC_STS	This optional bit is set when the RTC generates an alarm (asserts the RTC IRQ signal). Additionally, if the RTC_EN bit is set then the setting of the RTC_STS bit will generate a power management event (an SCI, SMI, or resume event). This bit is only set by hardware and can only be reset by software writing a "1" to this bit position. If the RTC was the cause of the wake (from an S1-S3 state), then this bit is set prior to returning control to OSPM. If the RTC_S4 flag within the FADT is set, and the RTC was the cause of the wake from the S4 state), then this bit is set prior to returning control to OSPM.
11	Ignore	This bit field is ignored by software.
12-13	Reserved	Reserved. These bits always return a value of zero.
14	PCIEXP_WAKE_ STS	This bit is required for chipsets that implement PCI Express. This bit is set by hardware to indicate that the system woke due to a PCI Express wakeup event. A PCI Express wakeup event is defined as the PCI Express WAKE# pin being active, one or more of the PCI Express ports being in the beacon state, or receipt of a PCI Express PME message at a root port. This bit should only be set when one of these events causes the system to transition from a non-S0 system power state to the S0 system power state. This bit is set independent of the state of the PCIEXP_WAKE_DIS bit. Software writes a 1 to clear this bit. If the WAKE# pin is still active during the write, one or more PCI Express ports is in the beacon state or the PME message received indication has not been cleared in the root port, then the bit will remain active (i.e. all inputs to this bit are level-sensitive). Note: This bit does not itself cause a wake event or prevent entry to a sleeping state. Thus if the bit is 1 and the system is put into a sleeping state, the system will not automatically wake.
15	WAK_STS	This bit is set when the system is in the sleeping state and an enabled wake event occurs. Upon setting this bit system will transition to the working state. This bit is set by hardware and can only be cleared by software writing a "1" to this bit position.

4.8.3.1.2 PM1Enable Registers

```
Register Location: <PM1a_EVT_BLK / PM1b_EVT_BLK> + PM1_EVT_LEN / 2 System I/O or Memory Space
Default Value: 00h
Attribute: Read/Write
Size: PM1_EVT_LEN / 2
```

The PM1 enable registers contain the fixed hardware feature enable bits. The bits can be split between two registers: PM1a_EN or PM1b_EN. Each register grouping can be at a different 32-bit aligned address and is pointed to by the PM1a_EVT_BLK or PM1b_EVT_BLK. The values for these pointers to the register space are found in the FADT. Accesses to the PM1 Enable registers are done through byte or word accesses.

For ACPI/legacy systems, when transitioning from the legacy to the G0 working state the enables are cleared by BIOS prior to setting the SCI_EN bit (and thus passing control to OSPM). For ACPI-only platforms (where SCI_EN is always set), when transitioning from either the mechanical off (G3) or soft-off state to the G0 working state this register is cleared prior to entering the G0 working state.

This register contains optional features enabled or disabled within the FADT. If the FADT indicates that the feature is not supported as a fixed hardware feature, then software treats the enable bits as write as zero.

Table 4-17 PM1 Enable Registers Fixed Hardware Feature Enable Bits

This is the timer carry interrupt enable bit. When this bit is set then an SCI event is generated anytime the TMR_STS bit is set. When this bit is reset then no interrupt is generated when the TMR_STS bit is set. 1-4 Reserved Reserved. These bits always return a value of zero. 5 GBL_EN The global enable bit. When both the GBL_EN bit and the GBL_STS bit are set, an SCI is raised. 6-7 Reserved Reserved 8 PWRBTN_EN This optional bit is used to enable the setting of the PWRBTN_STS bit to generate a power management event (SCI or wake). The PWRBTN_STS bit is set anytime the power button is asserted. The enable bit does not have to be set to enable the setting of the PWRBTN_STS bit by the assertion of the power button (see description of the power button hardware). Support for the power button is indicated by the PWR_BUTTON flag in the FADT being reset (zero). If the PWR_BUTTON flag is set or a power button device object is present in the ACPI Namespace, then this bit field is ignored by OSPM. SLPBTN_EN This optional bit is used to enable the setting of the SLPBTN_STS bit to generate a power management event (SCI or wake). The SLPBTN_STS bit is set anytime the sleep button is asserted. The enable bit does not have to be set to enable the setting of the SLPBTN_STS bit by the active assertion of the sleep button (see description of the sleep button hardware). Support for the sleep button is indicated by the SLP_BUTTON flag in the FADT being reset (zero). If the SLP_BUTTON flag is set or a sleep button device object is present in the ACPI Namespace, then this bit field is increased by OSPM.
5 GBL_EN The global enable bit. When both the GBL_EN bit and the GBL_STS bit are set, an SCI is raised. Reserved Reserved PWRBTN_EN This optional bit is used to enable the setting of the PWRBTN_STS bit to generate a power management event (SCI or wake). The PWRBTN_STS bit is set anytime the power button is asserted. The enable bit does not have to be set to enable the setting of the PWRBTN_STS bit by the assertion of the power button (see description of the power button hardware). Support for the power button is indicated by the PWR_BUTTON flag in the FADT being reset (zero). If the PWR_BUTTON flag is set or a power button device object is present in the ACPI Namespace, then this bit field is ignored by OSPM. SLPBTN_EN This optional bit is used to enable the setting of the SLPBTN_STS bit to generate a power management event (SCI or wake). The SLPBTN_STS bit is set anytime the sleep button is asserted. The enable bit does not have to be set to enable the setting of the SLPBTN_STS bit by the active assertion of the sleep button (see description of the sleep button hardware). Support for the sleep button is indicated by the SLP_BUTTON flag in the FADT being reset (zero). If the SLP_BUTTON flag is set or a sleep button device object is present in the ACPI Namespace, then this bit field
are set, an SCI is raised. Reserved Reserved This optional bit is used to enable the setting of the PWRBTN_STS bit to generate a power management event (SCI or wake). The PWRBTN_STS bit is set anytime the power button is asserted. The enable bit does not have to be set to enable the setting of the PWRBTN_STS bit by the assertion of the power button (see description of the power button hardware). Support for the power button is indicated by the PWR_BUTTON flag in the FADT being reset (zero). If the PWR_BUTTON flag is set or a power button device object is present in the ACPI Namespace, then this bit field is ignored by OSPM. SLPBTN_EN This optional bit is used to enable the setting of the SLPBTN_STS bit to generate a power management event (SCI or wake). The SLPBTN_STS bit is set anytime the sleep button is asserted. The enable bit does not have to be set to enable the setting of the SLPBTN_STS bit by the active assertion of the sleep button (see description of the sleep button hardware). Support for the sleep button is indicated by the SLP_BUTTON flag in the FADT being reset (zero). If the SLP_BUTTON flag is set or a sleep button device object is present in the ACPI Namespace, then this bit field
PWRBTN_EN This optional bit is used to enable the setting of the PWRBTN_STS bit to generate a power management event (SCI or wake). The PWRBTN_STS bit is set anytime the power button is asserted. The enable bit does not have to be set to enable the setting of the PWRBTN_STS bit by the assertion of the power button (see description of the power button hardware). Support for the power button is indicated by the PWR_BUTTON flag in the FADT being reset (zero). If the PWR_BUTTON flag is set or a power button device object is present in the ACPI Namespace, then this bit field is ignored by OSPM. This optional bit is used to enable the setting of the SLPBTN_STS bit to generate a power management event (SCI or wake). The SLPBTN_STS bit is set anytime the sleep button is asserted. The enable bit does not have to be set to enable the setting of the SLPBTN_STS bit by the active assertion of the sleep button (see description of the sleep button hardware). Support for the sleep button is indicated by the SLP_BUTTON flag in the FADT being reset (zero). If the SLP_BUTTON flag is set or a sleep button device object is present in the ACPI Namespace, then this bit field
generate a power management event (SCI or wake). The PWRBTN_STS bit is set anytime the power button is asserted. The enable bit does not have to be set to enable the setting of the PWRBTN_STS bit by the assertion of the power button (see description of the power button hardware). Support for the power button is indicated by the PWR_BUTTON flag in the FADT being reset (zero). If the PWR_BUTTON flag is set or a power button device object is present in the ACPI Namespace, then this bit field is ignored by OSPM. SLPBTN_EN This optional bit is used to enable the setting of the SLPBTN_STS bit to generate a power management event (SCI or wake). The SLPBTN_STS bit is set anytime the sleep button is asserted. The enable bit does not have to be set to enable the setting of the SLPBTN_STS bit by the active assertion of the sleep button (see description of the sleep button hardware). Support for the sleep button is indicated by the SLP_BUTTON flag in the FADT being reset (zero). If the SLP_BUTTON flag is set or a sleep button device object is present in the ACPI Namespace, then this bit field
generate a power management event (SCI or wake). The SLPBTN_STS bit is set anytime the sleep button is asserted. The enable bit does not have to be set to enable the setting of the SLPBTN_STS bit by the active assertion of the sleep button (see description of the sleep button hardware). Support for the sleep button is indicated by the SLP_BUTTON flag in the FADT being reset (zero). If the SLP_BUTTON flag is set or a sleep button device object is present in the ACPI Namespace, then this bit field
is ignored by OSPM.
This optional bit is used to enable the setting of the RTC_STS bit to generate a wake event. The RTC_STS bit is set any time the RTC generates an alarm.
11-13 Reserved Reserved. These bits always return a value of zero.
PCIEXP_WAKE_DIS This bit is required for chipsets that implement PCI Express. This bit disables the inputs to the PCIEXP_WAKE_STS bit in the PM1 Status register from waking the system. Modification of this bit has no impact on the value of the PCIEXP_WAKE_STS bit.
15 Reserved Reserved. These bits always return a value of zero.

4.8.3.2 PM1 Control Grouping

The PM1 Control Grouping has a set of bits that can be distributed between two different registers. This allows these registers to be partitioned between two chips, or all placed in a single chip.

Although the bits can be split between the two register blocks (each register block has a unique pointer within the FADT), the bit positions specified here are maintained. The register block with unimplemented bits (that is, those implemented in the other register block) returns zeros, and writes have no side effects.

4.8.3.2.1 PM1 Control Registers

Register Location: <PM1a_CNT_BLK / PM1b_CNT_BLK> System I/O or Memory Space

Default Value: 00h
Attribute: Read/Write
Size: PM1_CNT_LEN

The PM1 control registers contain the fixed hardware feature control bits. These bits can be split between two registers: PM1a_CNT or PM1b_CNT. Each register grouping can be at a different 32-bit aligned address and is pointed to by the PM1a_CNT_BLK or PM1b_CNT_BLK. The values for these pointers to the register space are found in the FADT. Accesses to PM1 control registers are accessed through byte and word accesses.

This register contains optional features enabled or disabled within the FADT. If the FADT indicates that the feature is not supported as a fixed hardware feature, then software treats these bits as ignored.

Table 4-18 PM1 Control Registers Fixed Hardware Feature Control Bits

Bit	Name	Description			
0	SCI_EN	Selects the power management event to be either an SCI or SMI interrupt for the following events. When this bit is set, then power management events will generate an SCI interrupt. When this bit is reset power management events will generate an SMI interrupt. It is the responsibility of the hardware to set or reset this bit. OSPM always preserves this bit position.			
1	BM_RLD	When set, this bit allows the generation of a bus master request to cause any processor in the C3 state to transition to the C0 state. When this bit is reset, the generation of a bus master request does not affect any processor in the C3 state.			
2	GBL_RLS	This write-only bit is used by the ACPI software to raise an event to the BIOS software, that is, generates an SMI to pass execution control to the BIOS for IA-PC platforms. BIOS software has a corresponding enable and status bit to control its ability to receive ACPI events (for example, BIOS_EN and BIOS_STS). The GBL_RLS bit is set by OSPM to indicate a release of the Global Lock and the setting of the pending bit in the FACS memory structure.			
3-8	Reserved	Reserved. These bits are reserved by OSPM.			
9	Ignore	Software ignores this bit field.			
10-12	SLP_TYPx	Defines the type of sleeping state the system enters when the SLP_EN bit is set to one. This 3-bit field defines the type of hardware sleep state the system enters when the SLP_EN bit is set. The \slash _Sx object contains 3-bit binary values associated with the respective sleeping state (as described by the object). OSPM takes the two values from the \slash _Sx object and programs each value into the respective SLP_TYPx field.			
13	SLP_EN	This is a write-only bit and reads to it always return a zero. Setting this bit causes the system to sequence into the sleeping state associated with the SLP_TYPx fields programmed with the values from the _Sx object.			
14-15	Reserved	Reserved. This field always returns zero.			

4.8.3.3 Power Management Timer (PM_TMR)

Register Location: <PM_TMR_BLK> System I/O or Memory Space

Default Value: 00h Attribute: Read-Only Size: 32 bits

This optional read-only register returns the current value of the power management timer (PM timer) if it is implemented on the platform. The FADT has a flag called TMR_VAL_EXT that an OEM sets to indicate a 32-bit PM timer or reset to indicate a 24-bit PM timer. When the last bit of the timer toggles the TMR_STS bit is set. This register is accessed as 32 bits.

This register contains optional features enabled or disabled within the FADT. If the FADT indicates that the feature is not supported as a fixed hardware feature, then software treats these bits as ignored.

Table 4-19 PM Timer Bits

Bit	Name	Description			
0-23	TMR_VAL	This read-only field returns the running count of the power management timer. This is a 24-bit counter that runs off a 3.579545-MHz clock and counts while in the S0 working system state. The starting value of the timer is undefined, thus allowing the timer to be reset (or not) by any transition to the S0 state from any other state. The timer is reset (to any initial value), and then continues counting until the system's 14.31818 MHz clock is stopped upon entering its Sx state. If the clock is restarted without a reset, then the counter will continue counting from where it stopped.			
24-31	E_TMR_VAL	This read-only field returns the upper eight bits of a 32-bit power management timer. If the hardware supports a 32-bit timer, then this field will return the upper eight bits; if the hardware supports a 24-bit timer then this field returns all zeros.			

4.8.3.4 PM2 Control (PM2_CNT)

Register Location: <PM2_CNT_BLK> System I/O, System Memory, or Functional

Fixed Hardware Space

Default Value: 00h

Attribute: Read/Write Size: PM2_CNT_LEN

This register block is naturally aligned and accessed based on its length. For ACPI 1.0 this register is byte aligned and accessed as a byte.

This register contains optional features enabled or disabled within the FADT. If the FADT indicates that the feature is not supported as a fixed hardware feature, then software treats these bits as ignored.

Table 4-20 PM2 Control Register Bits

Bit	Name	Description			
0	ARB_DIS	This bit is used to enable and disable the system arbiter. When this bit is CLEAR the system arbiter is enabled and the arbiter can grant the bus to other bus masters. When this bit is SET the system arbiter is disabled and the default CPU has ownership of the system. OSPM clears this bit when using the C0, C1 and C2 power states.			
>0	Reserved	Reserved			

4.8.3.5 Processor Register Block (P_BLK)

This optional register block is used to control each processor in the system. There is one unique processor register block per processor in the system. For more information about controlling processors and control methods that can be used to control processors, see <u>Section 8</u>, "Processor Configuration and Control." This register block is DWORD aligned and the context of this register block is not maintained across S3 or S4 sleeping states, or the S5 soft-off state.

4.8.3.5.1 Processor Control (P CNT): 32

Register Location: Either <P_BLK>: System I/O Space

or specified by _PTC Object: System I/O, System Memory, or Functional Fixed Hardware Space

Default Value: 00h
Attribute: Read/Write
Size: 32 bits

This register is accessed as a DWORD. The CLK_VAL field is where the duty setting of the throttling hardware is programmed as described by the DUTY_WIDTH and DUTY_OFFSET values in the FADT. Software treats all other CLK_VAL bits as ignored (those not used by the duty setting value).

Table 4-21 Processor Control Register Bits

Bit	Name	Description
0-3	CLK_VAL	Possible locations for the clock throttling value.
4	THT_EN	This bit enables clock throttling of the clock as set in the CLK_VAL field. THT_EN bit must be reset LOW when changing the CLK_VAL field (changing the duty setting).
5-31	CLK_VAL	Possible locations for the clock throttling value.

4.8.3.5.2 Processor LVL2 Register (P_LVL2): 8

Register Location: Either <P_BLK> + 4: System I/O Space

or specified by _CST Object: System I/O, System Memory, or Functional Fixed Hardware Space

Default Value: 00h
Attribute: Read-Only
Size: 8 bits

This register is accessed as a byte.

Table 4-22 Processor LVL2 Register Bits

Bit	Name	Description
0-7	P_LVL2	Reads to this register return all zeros; writes to this register have no effect. Reads to
		this register also generate an "enter a C2 power state" to the clock control logic.

4.8.3.5.3 Processor LVL3 Register (P LVL3): 8

Register Location: Either <P_BLK> + 5: System I/O Space

or specified by _CST Object: System I/O, System Memory, or Functional Fixed Hardware Space

Default Value: 00h
Attribute: Read-Only
Size: 8 bits

This register is accessed as a byte.

Table 4-23 Processor LVL3 Register Bits

Bit	Name	Description	
0-7	P_LVL3	Reads to this register return all zeros; writes to this register have no effect. Reads to	
		this register also generate an "enter a C3 power state" to the clock control logic.	

4.8.3.6 Reset Register

The optional ACPI reset mechanism specifies a standard mechanism that provides a complete system reset. When implemented, this mechanism must reset the entire system. This includes processors, core logic, all buses, and all peripherals. From an OSPM perspective, asserting the reset mechanism is the logical equivalent to power cycling the machine. Upon gaining control after a reset, OSPM will perform actions in like manner to a cold boot.

The reset mechanism is implemented via an 8-bit register described by RESET_REG in the FADT (always accessed via the natural alignment and size described in RESET_REG). To reset the machine, software will write a value (indicated in RESET_VALUE in FADT) to the reset register. The RESET_REG field in the FADT indicates the location of the reset register.

The reset register may exist only in I/O space, Memory space, or in PCI Configuration space on a function in bus 0. Therefore, the Address_Space_ID value in RESET_REG must be set to I/O space, Memory space, or PCI Configuration space (with a bus number of 0). As the register is only 8 bits, Register_Bit_Width must be 8 and Register_Bit_Offset must be 0.

The system must reset immediately following the write to this register. OSPM assumes that the processor will not execute beyond the write instruction. OSPM should execute spin loops on the CPUs in the system following a write to this register.

4.8.3.7 Sleep Control and Status Registers

The optional ACPI sleep registers (SLEEP_CONTROL_REG and SLEEP_STATUS_REG) specify a standard mechanism for system sleep state entry on HW-Reduced ACPI systems. When implemented, the Sleep registers are a replacement for the SLP_TYP, SLP_EN and WAK_STS registers in the PM1_BLK. Use of these registers is at the discretion of OSPM. OSPM can decide whether to enter sleep states on the platform based on the LOW_POWER_S0_IDLE_CAPABLE flag. Even when implemented, OSPM may use other provided options for hibernate and shutdown (e.g. UEFI ResetSystem()).

The HW-reduced Sleep mechanism is implemented via two 8-bit registers described by SLEEP_CONTROL_REG and SLEEP_STATUS_REG in the FADT (always accessed via the natural alignment and size described in SLEEP_*_REG). To put the machine into a system sleep state, software will write the HW-reduced Sleep Type value (obtained from the _Sx object in the DSDT) and the SLP_EN bit to the sleep control register. The OSPM then polls the WAK_STS bit of

the SLEEP_STATUS_REG waiting for it to be one (1), indicating that the system has been transitioned back to the Working state.

The Sleep registers may exist only in I/O space, Memory space, or in PCI Configuration space on a function in bus 0. Therefore, the Address_Space_ID value must be set to I/O space, Memory space, or PCI Configuration space (with a bus number of 0). As the registers are only 8 bits, Register Bit Width must be 8 and Register Bit Offset must be 0.

Table 4-24 Sleep Control Register

Field Name	Bit Length	Bit Offset	Description
Reserved	1	0	Reserved. This bit is reserved by OSPM.
Ignore	1	1	Software ignores this bit field.
SLP_TYPx	3	2	Defines the type of sleeping state the system enters when the SLP_EN bit is set to one. This 3-bit field defines the type of hardware sleep state the system enters when the SLP_EN bit is set. The _Sx object contains 3-bit binary values associated with the respective sleeping state (as described by the object). OSPM takes the HW-reduced Sleep Type value from the _SX object and programs it into the SLP_TYPx field.
SLP_EN	1	5	This is a write-only bit and reads to it always return a zero. Setting this bit causes the system to sequence into the sleeping state associated with the SLP_TYPx fields programmed with the values from the _Sx object.
Reserved	2	6	Reserved. This field always returns zero.

Table 4-25 Sleep Status Register

Field Name	Bit Length	Bit Offset	Description
Ignore	4	0	Software ignores this bit field.
Reserved	2	4	Reserved. These bits always return a value of zero.
Ignore	1	6	Software ignores this bit field.
WAK_STS	1	7	This bit is set when the system is in the sleeping state and an enabled wake event occurs. Upon setting this bit system will transition to the working state. This bit is set by hardware and can only be cleared by software writing a "1" to this bit position.

4.8.4 Generic Hardware Registers

ACPI provides a mechanism that allows a unique piece of "value added" hardware to be described to OSPM in the ACPI Namespace. There are a number of rules to be followed when designing ACPI-compatible hardware.

Programming bits can reside in any of the defined generic hardware address spaces (system I/O, system memory, PCI configuration, embedded controller, or SMBus), but the top-level event bits are contained in the general-purpose event registers. The general-purpose event registers are pointed to

by the GPE0_BLK and GPE1_BLK register blocks, and the generic hardware registers can be in any of the defined ACPI address spaces. A device's generic hardware programming model is described through an associated object in the ACPI Namespace, which specifies the bit's function, location, address space, and address location.

The programming model for devices is normally broken into status and control functions. Status bits are used to generate an event that allows OSPM to call a control method associated with the pending status bit. The called control method can then control the hardware by manipulating the hardware control bits or by investigating child status bits and calling their respective control methods. ACPI requires that the top level "parent" event status and enable bits reside in either the GPE0_STS or GPE1_STS registers, and "child" event status bits can reside in generic address space.

The example below illustrates some of these concepts. The top diagram shows how the logic is partitioned into two chips: a chipset and an embedded controller.

- The chipset contains the interrupt logic, performs the power button (which is part of the fixed register space, and is not discussed here), the lid switch (used in portables to indicate when the clam shell lid is open or closed), and the RI# function (which can be used to wake a sleeping system).
- The embedded controller chip is used to perform the AC power detect and dock/undock event logic. Additionally, the embedded controller supports some system management functions using an OS-transparent interrupt in the embedded controller (represented by the EXTSMI# signal).




Figure 4-21 Example of General-Purpose vs. Generic Hardware Events

At the top level, the generic events in the GPEx STS register are the:

- Embedded controller interrupt, which contains two query events: one for AC detection and one for docking (the docking query event has a child interrupt status bit in the docking chip).
- Ring indicate status (used for waking the system).
- Lid status.

The embedded controller event status bit (EC_STS) is used to indicate that one of two query events is active.

• A query event is generated when the AC# signal is asserted. The embedded controller returns a query value of 34 (any byte number can be used) upon a query command in response to this event; OSPM will then schedule for execution the control method associated with query value 34.

Another query event is for the docking chip that generates a docking event. In this case, the embedded controller will return a query value of 35 upon a query command from system software responding to an SCI from the embedded controller. OSPM will then schedule the control method associated with the query value of 35 to be executed, which services the docking event.

For each of the status bits in the GPEx_STS register, there is a corresponding enable bit in the GPEx_EN register. Notice that the child status bits do not necessarily need enable bits (see the DOCK_STS bit).

The lid logic contains a control bit to determine if its status bit is set when the LID is open (LID_POL is set and LID is set) or closed (LID_POL is clear and LID is clear). This control bit resides in generic I/O space (in this case, bit 2 of system I/O space 33h) and would be manipulated with a control method associated with the lid object.

As with fixed hardware events, OSPM will clear the status bits in the GPEx register blocks. However, AML code clears all sibling status bits in the generic hardware.

Generic hardware features are controlled by OEM supplied control methods, encoded in AML. ACPI provides both an event and control model for development of these features. The ACPI specification also provides specific control methods for notifying OSPM of certain power management and Plug and Play events. Section 5, "ACPI Software Programming Model," provides information on the types of hardware functionality that support the different types of subsystems. The following is a list of features supported by ACPI. The list is not intended to be complete or comprehensive.

- Device insertion/ejection (for example, docking, device bay, A/C adapter)
- Batteries¹
- Platform thermal subsystem
- Turning on/off power resources
- Mobile lid Interface
- Embedded controller
- System indicators
- OEM-specific wake events
- Plug and Play configuration

4.8.4.1 General-Purpose Event Register Blocks

ACPI supports up to two general-purpose register blocks as described in the FADT (see Section 5, "ACPI Software Programming Model") and an arbitrary number of additional GPE blocks described as devices within the ACPI namespace. Each register block contains two registers: an enable and a status register. Each register block is 32-bit aligned. Each register in the block is accessed as a byte. It is up to the specific design to determine if these bits retain their context across sleeping or soft-off states. If they lose their context across a sleeping or soft-off state, then BIOS resets the respective enable bit prior to passing control to the OS upon waking.

4.8.4.1.1 General-Purpose Event 0 Register Block

This register block consists of two registers: The GPE0_STS and the GPE0_EN registers. Each register's length is defined to be half the length of the GPE0 register block, and is described in the

^{1.} ACPI operating systems assume the use of the Smart Battery System Implementers Forum defined standard for batteries, called the "Smart Battery Specification" (SBS). ACPI provides a set of control methods for use by OEMs that use a proprietary "control method" battery interface.

ACPI FADT's GPE0_BLK and GPE0_BLK_LEN operators. OSPM owns the general-purpose event resources and these bits are only manipulated by OSPM; AML code cannot access the general-purpose event registers.

It is envisioned that chipsets will contain GPE event registers that provide GPE input pins for various events.

The platform designer would then wire the GPEs to the various value-added event hardware and the AML code would describe to OSPM how to utilize these events. As such, there will be the case where a platform has GPE events that are not wired to anything (they are present in the chip set), but are not utilized by the platform and have no associated AML code. In such, cases these event pins are to be tied inactive such that the corresponding SCI status bit in the GPE register is not set by a floating input pin.

4.8.4.1.1.1 General-Purpose Event 0 Status Register

Register Location:<GPE0_STS> System I/O or System Memory Space
Default Value: 00h
Attribute: Read/Write
Size: GPE0_BLK_LEN/2

The general-purpose event 0 status register contains the general-purpose event status bits in bank zero of the general-purpose registers. Each available status bit in this register corresponds to the bit with the same bit position in the GPE0_EN register. Each available status bit in this register is set when the event is active, and can only be cleared by software writing a "1" to its respective bit position. For the general-purpose event registers, unimplemented bits are ignored by OSPM.

Each status bit can optionally wake the system if asserted when the system is in a sleeping state with its respective enable bit set. OSPM accesses GPE registers through byte accesses (regardless of their length).

4.8.4.1.1.2 General-Purpose Event 0 Enable Register

Register Location: <GPE0_EN> System I/O or System Memory Space
Default Value: 00h
Attribute: Read/Write
Size: GPE0_BLK_LEN/2

The general-purpose event 0 enable register contains the general-purpose event enable bits. Each available enable bit in this register corresponds to the bit with the same bit position in the GPE0_STS register. The enable bits work similarly to how the enable bits in the fixed-event registers are defined: When the enable bit is set, then a set status bit in the corresponding status bit will generate an SCI bit. OSPM accesses GPE registers through byte accesses (regardless of their length).

4.8.4.1.2 General-Purpose Event 1 Register Block

This register block consists of two registers: The GPE1_STS and the GPE1_EN registers. Each register's length is defined to be half the length of the GPE1 register block, and is described in the ACPI FADT's GPE1_BLK_and GPE1_BLK_LEN operators.

4.8.4.1.2.1 General-Purpose Event 1 Status Register

Register Location: <GPE1_STS> System I/O or System Memory Space
Default Value: 00h
Attribute: Read/Write
Size: GPE1_BLK_LEN/2

The general -purpose event 1 status register contains the general-purpose event status bits. Each available status bit in this register corresponds to the bit with the same bit position in the GPE1_EN register. Each available status bit in this register is set when the event is active, and can only be cleared by software writing a "1" to its respective bit position. For the general-purpose event registers, unimplemented bits are ignored by the operating system.

Each status bit can optionally wake the system if asserted when the system is in a sleeping state with its respective enable bit set.

OSPM accesses GPE registers through byte accesses (regardless of their length).

4.8.4.1.2.2 General-Purpose Event 1 Enable Register

Register Location: <GPE1_EN> System I/O or System Memory Space
Default Value: 00h
Attribute: Read/Write
Size: GPE1_BLK_LEN/2

The general-purpose event 1 enable register contains the general-purpose event enable. Each available enable bit in this register corresponds to the bit with the same bit position in the GPE1_STS register. The enable bits work similarly to how the enable bits in the fixed-event registers are defined: When the enable bit is set, a set status bit in the corresponding status bit will generate an SCI bit.

OSPM accesses GPE registers through byte accesses (regardless of their length).

4.8.4.2 Example Generic Devices

This section points out generic devices with specific ACPI driver support.

4.8.4.2.1 Lid Switch

The Lid switch is an optional feature present in most "clam shell" style mobile computers. It can be used by the OS as policy input for sleeping the system, or for waking the system from a sleeping state. If used, then the OEM needs to define the lid switch as a device with an _HID object value of "PNP0C0D", which identifies this device as the lid switch to OSPM. The Lid device needs to contain a control method that returns its status. The Lid event handler AML code reconfigures the lid hardware (if it needs to) to generate an event in the other direction, clear the status, and then notify OSPM of the event.

Example hardware and ASL code is shown below for such a design.




Figure 4-22 Example Generic Address Space Lid Switch Logic

This logic will set the Lid status bit when the button is pressed or released (depending on the LID POL bit).

The ASL code below defines the following:

- An operational region where the lid polarity resides in address space System address space in registers 0x201.
- A field operator to allow AML code to access this bit: Polarity control bit (LID_POL) is called LPOL and is accessed at 0x201.0.
- A device named \ SB.LID with the following:
 - A Plug and Play identifier "PNP0C0D" that associates OSPM with this object.
 - Defines an object that specifies a change in the lid's status bit can wake the system from the S4 sleep state and from all higher sleep states (S1, S2, or S3).
- The lid switch event handler that does the following:
 - Defines the lid status bit (LID STS) as a child of the general-purpose event 0 register bit 1.
 - Defines the event handler for the lid (only event handler on this status bit) that does the following:
 - Flips the polarity of the LPOL bit (to cause the event to be generated on the opposite condition).
 - Generates a notify to the OS that does the following:
 - Passes the \ SB.LID object.
 - Indicates a device specific event (notify value 0x80).

```
// Define a Lid switch
OperationRegion(\PHO, SystemIO, 0x201, 0x1)
Field(\PHO, ByteAcc, NoLock, Preserve) {
   LPOL, 1
                            // Lid polarity control bit
Device(\_SB.LID){
    Name(_HID, EISAID("PNP0C0D"))
    Method(_LID) {Return(LPOL)}
    Name(_PRW, Package(2){
        1,
                            // bit 1 of GPE to enable Lid wakeup
        0x04
                            // can wakeup from S4 state
Scope(\_GPE){
                            // Root level event handlers
                            // uses bit 1 of GPO_STS register
   Method(_L01){
        Not(LPOL, LPOL) // Flip the lid polarity bit
        Notify(LID, 0x80) // Notify OS of event
    }
```

4.8.4.2.2 Embedded Controller

ACPI provides a standard interface that enables AML code to define and access generic logic in "embedded controller space." This supports current computer models where much of the value added hardware is contained within the embedded controller while allowing the AML code to access this hardware in an abstracted fashion.

The embedded controller is defined as a device and must contain a set number of control
methods:

- HID with a value of PNP0C09 to associate this device with the ACPI's embedded controller's driver.
- CRS to return the resources being consumed by the embedded controller.
- GPE that returns the general-purpose event bit that this embedded controller is wired to.

Additionally the embedded controller can support up to 255 generic events per embedded controller, referred to as query events. These query event handles are defined within the embedded controller's device as control methods. An example of defining an embedded controller device is shown below:

```
Device(EC0) {
     // PnP ID
    Name(_HID, EISAID("PNP0C09"))
     // Returns the "Current Resources" of EC
    Name ( CRS,
        ResourceTemplate(){
             IO(Decode16, 0x62, 0x62, 0, 1)
             IO(Decode16, 0x66, 0x66, 0, 1)
     })
     // Indicate that the EC SCI is bit 0 of the GP_STS register
    Name(_GPE, 0) // embedded controller is wired to bit 0 of GPE
    OperationRegion(\EC0, EmbeddedControl, 0, 0xFF)
    Field(ECO, ByteAcc, Lock, Preserve) {
     // Field definitions
     // Query methods
    Method(Q00)\{...\}
    Method(_QFF){...}
```

For more information on the embedded controller, see <u>Section 12</u>, "ACPI Embedded Controller Interface Specification."

4.8.4.2.3 Fan

ACPI has a device driver to control fans (active cooling devices) in platforms. A fan is defined as a device with the Plug and Play ID of "PNP0C0B." It should then contain a list power resources used to control the fan.

For more information, see Section 9, "ACPI-Defined Devices and Device Specific Objects.".

5 **ACPI Software Programming Model**

ACPI defines a hardware register interface that an ACPI-compatible OS uses to control core power management features of a machine, as described in Section 4, "ACPI Hardware Specification." ACPI also provides an abstract interface for controlling the power management and configuration of an ACPI system. Finally, ACPI defines an interface between an ACPI-compatible OS and the system BIOS.


To give hardware vendors flexibility in choosing their implementation, ACPI uses tables to describe system information, features, and methods for controlling those features. These tables list devices on the system board or devices that cannot be detected or power managed using some other hardware standard, plus their capabilities as described in Section 3, "Overview." They also list system capabilities such as the sleeping power states supported, a description of the power planes and clock sources available in the system, batteries, system indicator lights, and so on. This enables OSPM to control system devices without needing to know how the system controls are implemented.

Topics covered in this section are:

- The ACPI system description table architecture is defined, and the role of OEM-provided definition blocks in that architecture is discussed.
- The concept of the ACPI Namespace is discussed.

5.1 Overview of the System Description Table Architecture

The Root System Description Pointer (RSDP) structure is located in the system's memory address space and is setup by the platform firmware. This structure contains the address of the Extended System Description Table (XSDT), which references other description tables that provide data to OSPM, supplying it with knowledge of the base system's implementation and configuration (see Figure 5-23).



99

Figure 5-23 Root System Description Pointer and Table

All system description tables start with identical headers. The primary purpose of the system description tables is to define for OSPM various industry-standard implementation details. Such definitions enable various portions of these implementations to be flexible in hardware requirements and design, yet still provide OSPM with the knowledge it needs to control hardware directly.

The Extended System Description Table (XSDT) points to other tables in memory. Always the first table, it points to the Fixed ACPI Description table (FADT). The data within this table includes various fixed-length entries that describe the fixed ACPI features of the hardware. The FADT table always refers to the Differentiated System Description Table (DSDT), which contains information and descriptions for various system features. The relationship between these tables is shown in Figure 5-24.




Figure 5-24 Description Table Structures

• OSPM finds the RSDP structure as described in <u>Figure 5.2.5.1</u> ("Finding the RSDP on IA-PC Systems") or <u>Figure 5.2.5.2</u> ("Finding the RSDP on UEFI Enabled Systems").

When OSPM locates the structure, it looks at the physical address for the Root System Description Table or the Extended System Description Table. The Root System Description Table starts with the signature "RSDT", while the Extended System Description Table starts with the signature "XSDT".

These tables contain one or more physical pointers to other system description tables that provide various information about the system. As shown in <u>Figure 5-24</u>, there is always a physical address in the Root System Description Table for the Fixed ACPI Description table (FADT).

When OSPM follows a physical pointer to another table, it examines each table for a known signature. Based on the signature, OSPM can then interpret the implementation-specific data within the description table.

The purpose of the FADT is to define various static system information related to configuration and power management. The Fixed ACPI Description Table starts with the "FACP" signature. The FADT describes the implementation and configuration details of the ACPI hardware registers on the platform.

For a specification of the ACPI Hardware Register Blocks (PM1a_EVT_BLK, PM1b_EVT_BLK, PM1a_CNT_BLK, PM1b_CNT_BLK, PM2_CNT_BLK, PM_TMR_BLK, GP0_BLK, GP1_BLK, and one or more P_BLKs), see Section 4.8, "ACPI Register Model." The PM1a_EVT_BLK, PM1b_EVT_BLK, PM1b_EVT_BLK, PM1b_CNT_BLK, PM2_CNT_BLK, and PM_TMR_BLK blocks are for controlling low-level ACPI system functions.

The GPE0_BLK and GPE1_BLK blocks provide the foundation for an interrupt-processing model for Control Methods. The P BLK blocks are for controlling processor features.

Besides ACPI Hardware Register implementation information, the FADT also contains a physical pointer to a data structure known as the Differentiated System Description Table (DSDT), which is encoded in Definition Block format (See Section 5.2.11, "Definition Blocks").

A Definition Block contains information about the platform's hardware implementation details in the form of data objects arranged in a hierarchical (tree-structured) entity known as the "ACPI namespace", which represents the platform's hardware configuration. All definition blocks loaded by OSPM combine to form one namespace that represents the platform. Data objects are encoded in a format known as ACPI Machine Language or AML for short. Data objects encoded in AML are "evaluated" by an OSPM entity known as the AML interpreter. Their values may be static or dynamic. The AML interpreter's dynamic data object evaluation capability includes support for programmatic evaluation, including accessing address spaces (for example, I/O or memory accesses), calculation, and logical evaluation, to determine the result. Dynamic namespace objects are known as "control methods". OSPM "loads" or "unloads" an entire definition block as a logical unit – adding to or removing the associated objects from the namespace. The DSDT is always loaded by OSPM at boot time and cannot be unloaded. It contains a Definition Block named the Differentiated Definition Block that contains implementation and configuration information OSPM can use to perform power management, thermal management, or Plug and Play functionality that goes beyond the information described by the ACPI hardware registers.

Definition Blocks can either define new system attributes or, in some cases, build on prior definitions. A Definition Block can be loaded from system memory address space. One use of a Definition Block is to describe and distribute platform version changes.

Definition blocks enable wide variations of hardware platform implementations to be described to the ACPI-compatible OS while confining the variations to reasonable boundaries. Definition blocks enable simple platform implementations to be expressed by using a few well-defined object names. In theory, it might be possible to define a PCI configuration space-like access method within a Definition Block, by building it from I/O space, but that is not the goal of the Definition Block specification. Such a space is usually defined as a "built in" operator.

ACPI Software Programming Model

Some operators perform simple functions and others encompass complex functions. The power of the Definition Block comes from its ability to allow these operations to be glued together in numerous ways, to provide functionality to OSPM. The operators present are intended to allow many useful hardware designs to be ACPI-expressed, not to allow all hardware designs to be expressed.

5.1.1 Address Space Translation

Some platforms may contain bridges that perform translations as I/O and/or Memory cycles pass through the bridges. This translation can take the form of the addition or subtraction of an offset. Or it can take the form of a conversion from I/O cycles into Memory cycles and back again. When translation takes place, the addresses placed on the processor bus by the processor during a read or write cycle are not the same addresses that are placed on the I/O bus by the I/O bus bridge. The address the processor places on the processor bus will be known here as the processor-relative address. And the address that the bridge places on the I/O bus will be known as the bus-relative address. Unless otherwise noted, all addresses used within this section are processor-relative addresses.

For example, consider a platform with two root PCI buses. The platform designer has several choices. One solution would be to split the 16-bit I/O space into two parts, assigning one part to the first root PCI bus and one part to the second root PCI bus. Another solution would be to make both root PCI buses decode the entire 16-bit I/O space, mapping the second root PCI bus's I/O space into memory space. In this second scenario, when the processor needs to read from an I/O register of a device underneath the second root PCI bus, it would need to perform a memory read within the range that the root PCI bus bridge is using to map the I/O space.

Note: Industry standard PCs do not provide address space translations because of historical compatibility issues.

5.2 ACPI System Description Tables

This section specifies the structure of the system description tables:

- Root System Description Pointer (RSDP)
- System Description Table Header
- Root System Description Table (RSDT)
- Fixed ACPI Description Table (FADT)
- Firmware ACPI Control Structure (FACS)
- Differentiated System Description Table (DSDT)
- Secondary System Description Table (SSDT)
- Multiple APIC Description Table (MADT)
- Smart Battery Table (SBST)
- Extended System Description Table (XSDT)
- Embedded Controller Boot Resources Table (ECDT)
- System Locality Distance Information Table (SLIT)

- System Resource Affinity Table (SRAT)
- Corrected Platform Error Polling Table (CPEP)
- Maximum System Characteristics Table (MSCT)
- ACPI RAS FeatureTable (RASF)
- Memory Power StateTable (MPST)
- Platform Memory Topology Table (PMTT)
- Boot Graphics Resource Table (BGRT)
- Firmware Performance Data Table (FPDT)
- Generic Timer Description Table (GTDT)

All numeric values in ACPI-defined tables, blocks, and structures are always encoded in little endian format. Signature values are stored as fixed-length strings.

5.2.1 Reserved Bits and Fields

For future expansion, all data items marked as *reserved* in this specification have strict meanings. This section lists software requirements for *reserved* fields. Notice that the list contains terms such as ACPI tables and AML code defined later in this section of the specification.

5.2.1.1 Reserved Bits and Software Components

- OEM implementations of software and AML code return the bit value of 0 for all reserved bits in ACPI tables or in other software values, such as resource descriptors.
- For all reserved bits in ACPI tables and registers, OSPM implementations must:
- Ignore all reserved bits that are read.
- Preserve reserved bit values of read/write data items (for example, OSPM writes back reserved bit values it reads).
- Write zeros to reserved bits in write-only data items.

5.2.1.2 Reserved Values and Software Components

- OEM implementations of software and AML code return only defined values and do not return reserved values.
- OSPM implementations write only defined values and do not write reserved values.

5.2.1.3 Reserved Hardware Bits and Software Components

- Software ignores all reserved bits read from hardware enable or status registers.
- Software writes zero to all reserved bits in hardware enable registers.
- Software ignores all reserved bits read from hardware control and status registers.
- Software preserves the value of all reserved bits in hardware control registers by writing back read values

5.2.1.4 Ignored Hardware Bits and Software Components

• Software handles ignored bits in ACPI hardware registers the same way it handles reserved bits in these same types of registers.

5.2.2 Compatability

All versions of the ACPI tables must maintain backward compatibility. To accomplish this, modifications of the tables consist of redefinition of previously reserved fields and values plus appending data to the 1.0 tables. Modifications of the ACPI tables require that the version numbers of the modified tables be incremented. The length field in the tables includes all additions and the checksum is maintained for the entire length of the table.

5.2.3 Address Format

Addresses used in the ACPI 1.0 system description tables were expressed as either system memory or I/O space. This was targeted at the IA-32 environment. Newer architectures require addressing mechanisms beyond that defined in ACPI 1.0. To support these architectures ACPI must support 64-bit addressing and it must allow the placement of control registers in address spaces other than System I/O.

5.2.3.1 Functional Fixed Hardware

ACPI defines the fixed hardware low-level interfaces as a means to convey to the system OEM the minimum interfaces necessary to achieve a level of capability and quality for motherboard configuration and system power management. Additionally, the definition of these interfaces, as well as others defined in this specification, conveys to OS Vendors (OSVs) developing ACPI-compatible operating systems, the necessary interfaces that operating systems must manipulate to provide robust support for system configuration and power management.

While the definition of low-level hardware interfaces defined by ACPI 1.0 afforded OSPM implementations a certain level of stability, controls for existing and emerging diverse CPU architectures cannot be accommodated by this model as they can require a sequence of hardware manipulations intermixed with native CPU instructions to provide the ACPI-defined interface function. In this case, an ACPI-defined fixed hardware interface can be functionally implemented by the CPU manufacturer through an equivalent combination of both hardware and software and is defined by ACPI as Functional Fixed Hardware.

In IA-32-based systems, functional fixed hardware can be accommodated in an OS independent manner by using System Management Mode (SMM) based system firmware. Unfortunately, the nature of SMM-based code makes this type of OS independent implementation difficult if not impossible to debug. As such, this implementation approach is **not** recommended. In some cases, Functional Fixed Hardware implementations may require coordination with other OS components. As such, an OS independent implementation may not be viable.

OS-specific implementations of functional fixed hardware can be implemented using technical information supplied by the CPU manufacturer. The downside of this approach is that functional fixed hardware support must be developed for each OS. In some cases, the CPU manufacturer may provide a software component providing this support. In other cases support for the functional fixed hardware may be developed directly by the OS vendor.

The hardware register definition was expanded, in ACPI 2.0, to allow registers to exist in address spaces other than the System I/O address space. This is accomplished through the specification of an address space ID in the register definition (see Section 5.2.3.2, "Generic Address Structure," for more information). When specifically directed by the CPU manufacturer, the system firmware may define an interface as functional fixed hardware by supplying a special address space identifier, FfixedHW (0x7F), in the address space ID field for register definitions. It is emphasized that functional fixed hardware definitions may be declared in the ACPI system firmware only as indicated by the CPU Manufacturer for specific interfaces as the use of functional fixed hardware requires specific coordination with the OS vendor.

Only certain ACPI-defined interfaces may be implemented using functional fixed hardware and only when the interfaces are common across machine designs for example, systems sharing a common CPU architecture that does not support fixed hardware implementation of an ACPI-defined interface. OEMs are cautioned *not* to anticipate that functional fixed hardware support will be provided by OSPM differently on a system-by-system basis. The use of functional fixed hardware carries with it a reliance on OS specific software that must be considered. OEMs should consult OS vendors to ensure that specific functional fixed hardware interfaces are supported by specific operating systems.

Note: FFH is permitted and applicable to both full and HW-reduced ACPI implementations.

5.2.3.2 Generic Address Structure

The Generic Address Structure (GAS) provides the platform with a robust means to describe register locations. This structure, described below (<u>Table 5-26</u>), is used to express register addresses within tables defined by ACPI.

Table 5-26 Generic Address Structure (GAS)

Field	Byte Length	Byte Offset	Description
Address Space ID	1	0	The address space where the data structure or register exists. Defined values are: 0 System Memory 1 System I/O 2 PCI Configuration Space 3 Embedded Controller 4 SMBus 5 to 0x09 Reserved 0x0A Platform Communications Channel (PCC) 0x0B to 0x7E Reserved 0x7F Functional Fixed Hardware 0x80 to 0x8F Reserved 0xC0 to 0xFF OEM Defined
Register Bit Width	1	1	The size in bits of the given register. When addressing a data structure, this field must be zero.
Register Bit Offset	1	2	The bit offset of the given register at the given address. When addressing a data structure, this field must be zero.

Field	Byte Length	Byte Offset	Description	
Access Size	1	3	Specifies access size. Undefined (legacy reasons) Byte access Word access Dword access Word access	
Address	8	4	The 64-bit address of the data structure or register in the given address space (relative to the processor). (See below for specific formats.)	

Table 5-27 Address Space Format

Address Space	Format			
0-System Memory	The 64-bit physical memory address (relative to the processor) of the register. 32-bit platforms must have the high DWORD set to 0.			
1–System I/O	The 64-bit I/O address (relative to the processor) of the register. 32-bit platforms must have the high DWORD set to 0.			
2–PCI Configuration Space	PCI Configuration space addresses must be confined to devices on PCI Segment Group 0, bus 0. This restriction exists to accommodate access to fixed hardware prior to PCI bus enumeration. The format of addresses are defined as follows:			
	WORD Location Description			
	Highest WORD	Reserved (must be 0)		
	PCI Device number on bus 0			
		PCI Function number		
	Lowest WORD	Offset in the configuration space header		
	nction 2 on device 7 on bus 0 segment 0 would be 0020023.			
0x7F–Functional Fixed Hardware	Use of GAS fields other than Address_Space_ID is specified by the CPU manufacturer. The use of functional fixed hardware carries with it a reliance on OS specific software that must be considered. OEMs should consult OS vendors to ensure that specific functional fixed hardware interfaces are supported by specific operating systems.			

5.2.4 Universal Uniform Identifiers (UUID)

UUIDs (Universally Unique IDentifiers), also known as GUIDs (Globally Unique IDentifiers) are 128 bit long values that extremely likely to be different from all other UUIDs generated until 3400 A.D. UUIDs are used to distinguish between callers of ASL methods, such as DSM and OSC.

The format of both the binary and string representations of UUIDs along with an algorithm to generate them is specified in ISO/IEC 11578:1996 and can be found as part of the *Distributed Computing Environment 1.1: Remote Procedure Call* specification, which can be found in "Links to

ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Universal Uniform Identifiers (UUID)".

5.2.5 Root System Description Pointer (RSDP)

During OS initialization, OSPM must obtain the Root System Description Pointer (RSDP) structure from the platform. When OSPM locates the Root System Description Pointer (RSDP) structure, it then locates the Root System Description Table (RSDT) or the Extended Root System Description Table (XSDT) using the physical system address supplied in the RSDP.

5.2.5.1 Finding the RSDP on IA-PC Systems

OSPM finds the Root System Description Pointer (RSDP) structure by searching physical memory ranges on 16-byte boundaries for a valid Root System Description Pointer structure signature and checksum match as follows:

- The first 1 KB of the Extended BIOS Data Area (EBDA). For EISA or MCA systems, the EBDA can be found in the two-byte location 40:0Eh on the BIOS data area.
- The BIOS read-only memory space between 0E0000h and 0FFFFFh.

5.2.5.2 Finding the RSDP on UEFI Enabled Systems

In Unified Extensible Firmware Interface (UEFI) enabled systems, a pointer to the RSDP structure exists within the EFI System Table. The OS loader is provided a pointer to the EFI System Table at invocation. The OS loader must retrieve the pointer to the RSDP structure from the EFI System Table and convey the pointer to OSPM, using an OS dependent data structure, as part of the hand off of control from the OS loader to the OS.

The OS loader locates the pointer to the RSDP structure by examining the EFI Configuration Table within the EFI System Table. EFI Configuration Table entries consist of Globally Unique Identifier (GUID)/table pointer pairs. The UEFI specification defines two GUIDs for ACPI; one for ACPI 1.0 and the other for ACPI 2.0 or later specification revisions.

The EFI GUID for a pointer to the ACPI 1.0 specification RSDP structure is:

EB9D2D30-2D88-11D3-9A16-0090273FC14D.

The EFI GUID for a pointer to the ACPI 2.0 or later specification RSDP structure is:

• 8868E871-E4F1-11D3-BC22-0080C73C8881.

The OS loader for an ACPI-compatible OS will search for an RSDP structure pointer using the current revision GUID first and if it finds one, will use the corresponding RSDP structure pointer. If the GUID is not found then the OS loader will search for the RSDP structure pointer using the ACPI 1.0 version GUID.

The OS loader must retrieve the pointer to the RSDP structure from the EFI System Table **before** assuming platform control via the EFI ExitBootServices interface. See the UEFI Specification for more information.

5.2.5.3 RSDP Structure

The revision number contained within the structure indicates the size of the table structure.

Table 5-28 Root System Description Pointer Structure

Field	Byte Length	Byte Offset	Description
Signature	8	0	"RSD PTR" (Notice that this signature must contain a trailing blank character.)
Checksum	1	8	This is the checksum of the fields defined in the ACPI 1.0 specification. This includes only the first 20 bytes of this table, bytes 0 to 19, including the checksum field. These bytes must sum to zero.
OEMID	6	9	An OEM-supplied string that identifies the OEM.
Revision	1	15	The revision of this structure. Larger revision numbers are backward compatible to lower revision numbers. The ACPI version 1.0 revision number of this table is zero. The current value for this field is 2.
RsdtAddress	4	16	32 bit physical address of the RSDT.
Length	4	20	The length of the table, in bytes, including the header, starting from offset 0. This field is used to record the size of the entire table.
XsdtAddress	8	24	64 bit physical address of the XSDT.
Extended Checksum	1	32	This is a checksum of the entire table, including both checksum fields.
Reserved	3	33	Reserved field

5.2.6 System Description Table Header

All system description tables begin with the structure shown in <u>Table 5-29</u>. The Signature field determines the content of the system description table. System description table signatures defined by this specification are listed in <u>Table 5-30</u>.

Table 5-29 DESCRIPTION_HEADER Fields

Field	Byte Length	Byte Offset	Description
Signature	4	0	The ASCII string representation of the table identifier. Notice that if OSPM finds a signature in a table that is not listed in Table 5-30 , OSPM ignores the entire table (it is not loaded into ACPI namespace); OSPM ignores the table even though the values in the Length and Checksum fields are correct.
Length	4	4	The length of the table, in bytes, including the header, starting from offset 0. This field is used to record the size of the entire table.
Revision	1	8	The revision of the structure corresponding to the signature field for this table. Larger revision numbers are backward compatible to lower revision numbers with the same signature.
Checksum	1	9	The entire table, including the checksum field, must add to zero to be considered valid.
OEMID	6	10	An OEM-supplied string that identifies the OEM.

OEM Table ID	8	16	An OEM-supplied string that the OEM uses to identify the particular data table. This field is particularly useful when defining a definition block to distinguish definition block functions. The OEM assigns each dissimilar table a new OEM Table ID.
OEM Revision	4	24	An OEM-supplied revision number. Larger numbers are assumed to be newer revisions.
Creator ID	4	28	Vendor ID of utility that created the table. For tables containing Definition Blocks, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For tables containing Definition Blocks, this is the revision for the ASL Compiler.

For OEMs, good design practices will ensure consistency when assigning OEMID and OEM Table ID fields in any table. The intent of these fields is to allow for a binary control system that support services can use. Because many support functions can be automated, it is useful when a tool can programmatically determine which table release is a compatible and more recent revision of a prior table on the same OEMID and OEM Table ID.

<u>Table 5-30</u> and <u>Table 5-31</u> contain the system description table signatures defined by this specification. These system description tables may be defined by ACPI and documented within this specification (<u>Table 5-30</u>) or they may be simply reserved by ACPI and defined by other industry specifications (<u>Table 5-31</u>). This allows OS and platform specific tables to be defined and pointed to by the RSDT/XSDT as needed. For tables defined by other industry specifications, the ACPI specification acts as gatekeeper to avoid collisions in table signatures.

Table signatures will be reserved by the ACPI promoters and posted independently of this specification in ACPI errata and clarification documents on the ACPI web site. Requests to reserve a 4-byte alphanumeric table signature should be sent to the email address **info@acpi.info** and should include the purpose of the table and reference URL to a document that describes the table format. Tables defined outside of the ACPI specification may define data value encodings in either little endian or big endian format. For the purpose of clarity, external table definition documents should include the endian-ness of their data value encodings.

Since reference URLs can change over time and may not always be up-to-date in this specification, a separate document containing the latest known reference URLs can be found at "Links to ACPI-Related Documents" (http://uefi.org/acpi), which should conspicuously be placed in the same location as this specification.

Table 5-30 DESCRIPTION_HEADER Signatures for tables defined by ACPI

Signature	Description	Reference
"APIC"	Multiple APIC Description Table	Section 5.2.12, "Multiple APIC Description Table"
"BERT"	Boot Error Record Table	Section 18.3.1, "Boot Error Source"
"BGRT"	Boot Graphics Resource Table	Section 5.2.22, "Boot Graphics Resource Table"
"CPEP"	Corrected Platform Error Polling Table	Section 5.2.18, "Corrected Platform Error Polling Table"
"DSDT"	Differentiated System Description Table	Section 5.2.11.1, "Differentiated System Description Table"

Signature	Description	Reference
"ECDT"	Embedded Controller Boot Resources Table	Section 5.2.15 "Embedded Controller Boot Resources Table"
"EINJ"	Error Injection Table	Section 18.6.1, "Error Injection Table"
"ERST"	Error Record Serialization Table	Section 18.5, "Error Serialization"
"FACP"	Fixed ACPI Description Table (FADT)	Section 5.2.9, "Fixed ACPI Description Table"
"FACS"	Firmware ACPI Control Structure	Section 5.2.10, "Firmware ACPI Control Structure"
"FPDT"	Firmware Performance Data Table	Section 5.2.23, "Firmware Performance Data Table"
"GTDT"	Generic Timer Description Table	Section 5.2.24, "Generic Timer Description Table"
"HEST"	Hardware Error Source Table	Section 18.3.2, "ACPI Error Source"
"MSCT"	Maximum System Characteristics Table	Section 5.2.19, "Maximum System Characteristics Table"
"MPST"	Memory Power StateTable	Section 5.2.21, "Memory Power StateTable"
"OEMx"	OEM Specific Information Tables	OEM Specific tables. All table signatures starting with "OEM" are reserved for OEM use.
"PMTT"	Platform Memory Topology Table	Section 5.2.21.12, Memory Topology Table (PMTT)
"PSDT"	Persistent System Description Table	Section 5.2.11.3, "Persistent System Description Table"
"RASF"	ACPI RAS FeatureTable	Section 5.2.20.3, "ACPI RAS FeatureTable"
"RSDT"	Root System Description Table	Section 5.2.7, "Root System Description Table"
"SBST"	Smart Battery Specification Table	Section 5.2.14, "Smart Battery Table"
"SLIT"	System Locality Distance Information Table	Section 5.2.17, "System Locality Distance Information Table"
"SRAT"	System Resource Affinity Table	Section 5.2.16, "System Resource Affinity Table"
"SSDT"	Secondary System Description Table	Section 5.2.11.2, "Secondary System Description Table"
"XSDT"	Extended System Description Table	Section 5.2.8, "Extended System Description Table"

Table 5-31 DESCRIPTION_HEADER Signatures for tables reserved by ACPI

Signature	Description and External Reference
"BOOT"	Simple Boot Flag Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Simple Boot Flag Table".
"CSRT"	Core System Resource Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Core System Resource Table".
"DBG2"	Debug Port Table 2 Microsoft Debug Port Table 2 Specification See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Debug Port Table 2".

Signature	Description and External Reference
"DBGP"	Debug Port Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Debug Port Table".
"DMAR"	DMA Remapping Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "DMA Remapping Table".
"DRTM"	Dynamic Root of Trust for Measurement Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "TCG D-RTM Architecture Specification".
"ETDT"	Event Timer Description Table (Obsolete) IA-PC Multimedia Timers Specification. This signature has been superseded by "HPET" and is now obsolete.
"HPET"	IA-PC High Precision Event Timer Table IA-PC High Precision Event Timer Specification See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "IA-PC High Precision Event Timer Table".
"IBFT"	iSCSI Boot Firmware Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "iSCSI Boot Firmware Table".
"IVRS"	I/O Virtualization Reporting Structure See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "I/O Virtualization Reporting Structure".
"LPIT"	Low Power Idle Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Low Power Idle Table".
"MCFG"	PCI Express memory mapped configuration space base address Description Table PCI Firmware Specification, Revision 3.0 See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "PCI Sig".
"MCHI"	Management Controller Host Interface Table DSP0256 Management Component Transport Protocol (MCTP) Host Interface Specification See"Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Management Controller Host Interface Table".
"MSDM"	Microsoft Data Management Table See: Microsoft Data Management Table Specification See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Microsoft Data Management Table".
"SLIC"	Microsoft Software Licensing Table Specification See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Microsoft Software Licensing Table Specification".
"SPCR"	Serial Port Console Redirection Table Microsoft Serial Port Console Redirection Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Serial Port Console Redirection Table".

Signature	Description and External Reference
"SPMI"	Server Platform Management Interface Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Server Platform Management Interface Table".
"TCPA"	Trusted Computing Platform Alliance Capabilities Table TCPA PC Specific Implementation Specification See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Trusted Computing Platform Alliance Capabilities Table".
TPM2	Trusted Platform Module 2 Table See: Trusted Platform Module 2 Table Specification See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Trusted Platform Module 2 Table".
"UEFI"	UEFI ACPI Data Table UEFI Specification See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Unified Extensible Firmware Interface Specifications".
"WAET"	Windows ACPI Emulated Devices Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Windows ACPI Emulated Devices Table".
"WDAT"	Watch Dog Action Table Requirements for Hardware Watchdog Timers Supported by Windows – Design Specification See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Watchdog Action Table".
"WDRT"	Watchdog Resource Table Watchdog Timer Hardware Requirements for Windows Server 2003 See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Watchdog Timer Resource Table (WDRT)".
"WPBT"	Windows Platform Binary Table See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Windows Platform Binary Table".

5.2.7 Root System Description Table (RSDT)

OSPM locates that Root System Description Table by following the pointer in the RSDP structure. The RSDT, shown in <u>Table 5-32</u>, starts with the signature 'RSDT' followed by an array of physical pointers to other system description tables that provide various information on other standards defined on the current system. OSPM examines each table for a known signature. Based on the signature, OSPM can then interpret the implementation-specific data within the table.

Platforms provide the RSDT to enable compatibility with ACPI 1.0 operating systems. The XSDT, described in the next section, supersedes RSDT functionality.

Table 5-32 Root System Description Table Fields (RSDT)

Field	Byte Length	Byte Offset	Description
Header			

Signaturo	4	0	'PSDT' Signature for the Poet System Description Table
Signature	4	U	'RSDT' Signature for the Root System Description Table.
Length	4	4	Length, in bytes, of the entire RSDT. The length implies the
			number of Entry fields (n) at the end of the table.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	For the RSDT, the table ID is the manufacture model ID. This
			field must match the OEM Table ID in the FADT.
OEM Revision	4	24	OEM revision of RSDT table for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For tables containing
			Definition Blocks, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For tables containing
			Definition Blocks, this is the revision for the ASL Compiler.
Entry	4*n	36	An array of 32-bit physical addresses that point to other
			DESCRIPTION_HEADERs. OSPM assumes at least the
			DESCRIPTION_HEADER is addressable, and then can further
			address the table based upon its Length field.

5.2.8 Extended System Description Table (XSDT)

The XSDT provides identical functionality to the RSDT but accommodates physical addresses of DESCRIPTION HEADERs that are larger than 32 bits. Notice that both the XSDT and the RSDT can be pointed to by the RSDP structure. An ACPI-compatible OS must use the XSDT if present.

Table 5-33 Extended System Description Table Fields (XSDT)

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'XSDT'. Signature for the Extended System Description Table.
Length	4	4	Length, in bytes, of the entire table. The length implies the number of Entry fields (<i>n</i>) at the end of the table.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	For the XSDT, the table ID is the manufacture model ID. This field must match the OEM Table ID in the FADT.
OEM Revision	4	24	OEM revision of XSDT table for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For tables containing Definition Blocks, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For tables containing Definition Blocks, this is the revision for the ASL Compiler.

Field	Byte Length	Byte Offset	Description
Entry	8*n	36	An array of 64-bit physical addresses that point to other DESCRIPTION_HEADERs. OSPM assumes at least the DESCRIPTION_HEADER is addressable, and then can further address the table based upon its Length field.

5.2.9 Fixed ACPI Description Table (FADT)

The Fixed ACPI Description Table (FADT) defines various fixed hardware ACPI information vital to an ACPI-compatible OS, such as the base address for the following hardware registers blocks: PM1a_EVT_BLK, PM1b_EVT_BLK, PM1a_CNT_BLK, PM1b_CNT_BLK, PM2_CNT_BLK, PM_TMR_BLK, GPE0_BLK, and GPE1_BLK.

The FADT also has a pointer to the DSDT that contains the Differentiated Definition Block, which in turn provides variable information to an ACPI-compatible OS concerning the base system design.

All fields in the FADT that provide hardware addresses provide processor-relative physical addresses.

Note: If the HW_REDUCED_ACPI flag in the table is set, OSPM will ignore fields related to the ACPI HW register interface: Fields at offsets 46 through 108 and 148 through 232, as well as FADT Flag bits 1, 2, 3,7,8,12,13, 14, 16 and 17).

Table 5-34 Fixed ACPI Description Table (FADT) Format

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'FACP'. Signature for the Fixed ACPI Description Table. (This signature predates ACPI 1.0, explaining the mismatch with this table's name.)
Length	4	4	Length, in bytes, of the entire FADT.
FADT Major Version	1	8	Major Version of this FADT structure, in "Major.Minor" form, where 'Minor' is the value in the Minor Version Field (Byte offset 131 in this table)
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	For the FADT, the table ID is the manufacture model ID. This field must match the OEM Table ID in the RSDT.
OEM Revision	4	24	OEM revision of FADT for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For tables containing Definition Blocks, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For tables containing Definition Blocks, this is the revision for the ASL Compiler.

Field	Byte Length	Byte Offset	Description
FIRMWARE_CTRL	4	36	Physical memory address of the FACS, where OSPM and Firmware exchange control information. See Section 5.2.6, "Root System Description Table," for a description of the FACS. If the X_FIRMWARE_CTRL field contains a non zero value then this field must be zero. A zero value indicates that no FACS is specified by this field.
DSDT	4	40	Physical memory address (0-4 GB) of the DSDT.
Reserved	1	44	ACPI 1.0 defined this offset as a field named INT_MODEL, which was eliminated in ACPI 2.0. Platforms should set this field to zero but field values of one are also allowed to maintain compatibility with ACPI 1.0.
Preferred_PM_Profile	1	45	This field is set by the OEM to convey the preferred power management profile to OSPM. OSPM can use this field to set default power management policy parameters during OS installation. Field Values: 0
SCI_INT	2	46	System vector the SCI interrupt is wired to in 8259 mode. On systems that do not contain the 8259, this field contains the Global System interrupt number of the SCI interrupt. OSPM is required to treat the ACPI SCI interrupt as a sharable, level, active low interrupt.
SMI_CMD	4	48	System port address of the SMI Command Port. During ACPI OS initialization, OSPM can determine that the ACPI hardware registers are owned by SMI (by way of the SCI_EN bit), in which case the ACPI OS issues the ACPI_ENABLE command to the SMI_CMD port. The SCI_EN bit effectively tracks the ownership of the ACPI hardware registers. OSPM issues commands to the SMI_CMD port synchronously from the boot processor. This field is reserved and must be zero on system that does not support System Management mode.

Field	Byte Length	Byte Offset	Description
ACPI_ENABLE	1	52	The value to write to SMI_CMD to disable SMI ownership of the ACPI hardware registers. The last action SMI does to relinquish ownership is to set the SCI_EN bit. During the OS initialization process, OSPM will synchronously wait for the transfer of SMI ownership to complete, so the ACPI system releases SMI ownership as quickly as possible. This field is reserved and must be zero on systems that do not support Legacy Mode.
ACPI_DISABLE	1	53	The value to write to SMI_CMD to re-enable SMI ownership of the ACPI hardware registers. This can only be done when ownership was originally acquired from SMI by OSPM using ACPI_ENABLE. An OS can hand ownership back to SMI by relinquishing use to the ACPI hardware registers, masking off all SCI interrupts, clearing the SCI_EN bit and then writing ACPI_DISABLE to the SMI_CMD port from the boot processor. This field is reserved and must be zero on systems that do not support Legacy Mode.
S4BIOS_REQ	1	54	The value to write to SMI_CMD to enter the S4BIOS state. The S4BIOS state provides an alternate way to enter the S4 state where the firmware saves and restores the memory context. A value of zero in S4BIOS_F indicates S4BIOS_REQ is not supported. (See Table 5-38)
PSTATE_CNT	1	55	If non-zero, this field contains the value OSPM writes to the SMI_CMD register to assume processor performance state control responsibility.
PM1a_EVT_BLK	4	56	System port address of the PM1a Event Register Block. See Section 4.8.3.1, "PM1 Event Grouping," for a hardware description layout of this register block. This is a required field. This field is superseded by the X_PM1a_EVT_BLK field.
PM1b_EVT_BLK	4	60	System port address of the PM1b Event Register Block. See Section 4.8.3.1, "PM1 Event Grouping," for a hardware description layout of this register block. This field is optional; if this register block is not supported, this field contains zero. This field is superseded by the X_PM1b_EVT_BLK field.
PM1a_CNT_BLK	4	64	System port address of the PM1a Control Register Block. See Section 4.8.3.2, "PM1 Control Grouping," for a hardware description layout of this register block. This is a required field. This field is superseded by the X_PM1a_CNT_BLK field.
PM1b_CNT_BLK	4	68	System port address of the PM1b Control Register Block. See Section 4.8.3.2, "PM1 Control Grouping," for a hardware description layout of this register block. This field is optional; if this register block is not supported, this field contains zero. This field is superseded by the X_PM1b_CNT_BLK field.

Field	Byte Length	Byte Offset	Description
PM2_CNT_BLK	4	72	System port address of the PM2 Control Register Block. See Section 4.8.3.4, "PM2 Control (PM2_CNT)," for a hardware description layout of this register block. This field is optional; if this register block is not supported, this field contains zero. This field is superseded by the X_PM2_CNT_BLK field.
PM_TMR_BLK	4	76	System port address of the Power Management Timer Control Register Block. See Section 4.8.3.3, "Power Management Timer (PM_TMR)," for a hardware description layout of this register block. This is an optional field; if this register block is not supported, this field contains zero. This field is superseded by the X_PM_TMR_BLK field.
GPE0_BLK	4	80	System port address of General-Purpose Event 0 Register Block. See Section 4.8.4.1, "General-Purpose Event Register Blocks," for a hardware description of this register block. This is an optional field; if this register block is not supported, this field contains zero. This field is superseded by the X_GPE0_BLK field.
GPE1_BLK	4	84	System port address of General-Purpose Event 1 Register Block. See Section 4.8.4.1, "General-Purpose Event Register Blocks," for a hardware description of this register block. This is an optional field; if this register block is not supported, this field contains zero. This field is superseded by the X_GPE1_BLK field.
PM1_EVT_LEN	1	88	Number of bytes decoded by PM1a_EVT_BLK and, if supported, PM1b_ EVT_BLK. This value is ≥ 4.
PM1_CNT_LEN	1	89	Number of bytes decoded by PM1a_CNT_BLK and, if supported, PM1b_CNT_BLK. This value is ≥ 2.
PM2_CNT_LEN	1	90	Number of bytes decoded by PM2_CNT_BLK. Support for the PM2 register block is optional. If supported, this value is ≥ 1. If not supported, this field contains zero.
PM_TMR_LEN	1	91	Number of bytes decoded by PM_TMR_BLK. If the PM Timer is supported, this field's value must be 4. If not supported, this field contains zero.
GPE0_BLK_LEN	1	92	Number of bytes decoded by GPE0_BLK. The value is a non-negative multiple of 2.
GPE1_BLK_LEN	1	93	Number of bytes decoded by GPE1_BLK. The value is a non-negative multiple of 2.
GPE1_BASE	1	94	Offset within the ACPI general-purpose event model where GPE1 based events start.
CST_CNT	1	95	If non-zero, this field contains the value OSPM writes to the SMI_CMD register to indicate OS support for the _CST object and C States Changed notification.
P_LVL2_LAT	2	96	The worst-case hardware latency, in microseconds, to enter and exit a C2 state. A value > 100 indicates the system does not support a C2 state.

Field	Byte Length	Byte Offset	Description
P_LVL3_LAT	2	98	The worst-case hardware latency, in microseconds, to enter and exit a C3 state. A value > 1000 indicates the system does not support a C3 state.
FLUSH_SIZE	2	100	If WBINVD=0, the value of this field is the number of flush strides that need to be read (using cacheable addresses) to completely flush dirty lines from any processor's memory caches. Notice that the value in FLUSH_STRIDE is typically the smallest cache line width on any of the processor's caches (for more information, see the FLUSH_STRIDE field definition). If the system does not support a method for flushing the processor's caches, then FLUSH_SIZE and WBINVD are set to zero. Notice that this method of flushing the processor caches has limitations, and WBINVD=1 is the preferred way to flush the processors caches. This value is typically at least 2 times the cache size. The maximum allowed value for FLUSH_SIZE multiplied by FLUSH_STRIDE is 2 MB for a typical maximum supported cache size of 1 MB. Larger cache sizes are supported using WBINVD=1. This value is ignored if WBINVD=1. This field is maintained for ACPI 1.0 processor compatibility on existing systems. Processors in new ACPI-compatible systems are required to support the WBINVD function and indicate this to OSPM by setting the WBINVD field = 1.
FLUSH_STRIDE	2	102	If WBINVD=0, the value of this field is the cache line width, in bytes, of the processor's memory caches. This value is typically the smallest cache line width on any of the processor's caches. For more information, see the description of the FLUSH_SIZE field. This value is ignored if WBINVD=1. This field is maintained for ACPI 1.0 processor compatibility on existing systems. Processors in new ACPI-compatible systems are required to support the WBINVD function and indicate this to OSPM by setting the WBINVD field = 1.
DUTY_OFFSET	1	104	The zero-based index of where the processor's duty cycle setting is within the processor's P_CNT register.

Field	Byte Length	Byte Offset	Description
DUTY_WIDTH	1	105	The bit width of the processor's duty cycle setting value in the P_CNT register. Each processor's duty cycle setting allows the software to select a nominal processor frequency below its absolute frequency as defined by: THTL_EN = 1 BF * DC/(2 ^{DUTY_WIDTH}) Where: BF-Base frequency DC-Duty cycle setting When THTL_EN is 0, the processor runs at its absolute BF. A DUTY_WIDTH value of 0 indicates that processor duty cycle is not supported and the processor continuously runs at its base frequency.
DAY_ALRM	1	106	The RTC CMOS RAM index to the day-of-month alarm value. If this field contains a zero, then the RTC day of the month alarm feature is not supported. If this field has a non-zero value, then this field contains an index into RTC RAM space that OSPM can use to program the day of the month alarm. See Section 4.8.2.4 "Real Time Clock Alarm," for a description of how the hardware works.
MON_ALRM	1	107	The RTC CMOS RAM index to the month of year alarm value. If this field contains a zero, then the RTC month of the year alarm feature is not supported. If this field has a non-zero value, then this field contains an index into RTC RAM space that OSPM can use to program the month of the year alarm. If this feature is supported, then the DAY_ALRM feature must be supported also.
CENTURY	1	108	The RTC CMOS RAM index to the century of data value (hundred and thousand year decimals). If this field contains a zero, then the RTC centenary feature is not supported. If this field has a non-zero value, then this field contains an index into RTC RAM space that OSPM can use to program the centenary field.
IAPC_BOOT_ARCH	2	109	IA-PC Boot Architecture Flags. See <u>Table 5-36</u> for a description of this field.
Reserved	1	111	Must be 0.
Flags	4	112	Fixed feature flags. See <u>Table 5-35</u> for a description of this field.
RESET_REG	12	116	The address of the reset register represented in Generic Address Structure format (See Section 4.8.3.6, "Reset Register," for a description of the reset mechanism.) Note: Only System I/O space, System Memory space and PCI Configuration space (bus #0) are valid for values for Address_Space_ID. Also, Register_Bit_Width must be 8 and Register_Bit_Offset must be 0.

Field	Byte Length	Byte Offset	Description
RESET_VALUE	1	128	Indicates the value to write to the RESET_REG port to reset the system. (See Section 4.8.3.6, "Reset Register," for a description of the reset mechanism.)
ARM_BOOT_ARCH	2	129	ARM Boot Architecture Flags. See <u>Table 5-37</u> for a description of this field.
FADT Minor Version	1	131	1 Minor Version of this FADT structure, in "Major.Minor" form, where 'Major' is the value in the Major Version Field (Byte offset 8 in this table).
X_FIRMWARE_CTRL	8	132	64bit physical address of the FACS. This field is used when the physical address of the FACS is above 4GB. If the FIRMWARE_CTRL field contains a non zero value then this field must be zero. A zero value indicates that no FACS is specified by this field.
X_DSDT	8	140	64bit physical address of the DSDT.
X_PM1a_EVT_BLK	12	148	Extended address of the PM1a Event Register Block, represented in Generic Address Structure format. See Section 4.8.3.1, "PM1 Event Grouping," for a hardware description layout of this register block. This is a required field.
X_PM1b_EVT_BLK	12	160	Extended address of the PM1b Event Register Block, represented in Generic Address Structure format. See Section 4.8.3.1, "PM1 Event Grouping," for a hardware description layout of this register block. This field is optional; if this register block is not supported, this field contains zero.
X_PM1a_CNT_BLK	12	172	Extended address of the PM1a Control Register Block, represented in Generic Address Structure format. See Section 4.8.3.2, "PM1 Control Grouping," for a hardware description layout of this register block. This is a required field.
X_PM1b_CNT_BLK	12	184	Extended address of the PM1b Control Register Block, represented in Generic Address Structure format. See Section 4.8.3.2, "PM1 Control Grouping," for a hardware description layout of this register block. This field is optional; if this register block is not supported, this field contains zero.
X_PM2_CNT_BLK	12	196	Extended address of the Power Management 2 Control Register Block, represented in Generic Address Structure format. See Section 4.8.3.4 "PM2 Control (PM2_CNT)," for a hardware description layout of this register block. This field is optional; if this register block is not supported, this field contains zero.

Field	Byte Length	Byte Offset	Description
X_PM_TMR_BLK	12	208	Extended address of the Power Management Timer Control Register Block, represented in Generic Address Structure format. See Section 4.8.3.3, "Power Management Timer (PM_TMR)," for a hardware description layout of this register block. This field is optional; if this register block is not supported, this field contains zero.
X_GPE0_BLK	12	220	Extended address of the General-Purpose Event 0 Register Block, represented in Generic Address Structure format. See Section 5.2.9 "Fixed ACPI Description Table," for a hardware description of this register block. This is an optional field; if this register block is not supported, this field contains zero.
X_GPE1_BLK	12	232	Extended address of the General-Purpose Event 1 Register Block, represented in Generic Address Structure format. See Section 5.2.9, "Fixed ACPI Description Table," for a hardware description of this register block. This is an optional field; if this register block is not supported, this field contains zero.
SLEEP_CONTROL_RE G	12	244	The address of the Sleep register, represented in Generic Address Structure format (See Section 4.8.3.7, "Sleep Control and Status Registers," for a description of the sleep mechanism.) Note: Only System I/O space, System Memory space and PCI Configuration space (bus #0) are valid for values for Address_Space_ID. Also, Register_Bit_Width must be 8 and Register_Bit_Offset must be 0.
SLEEP_STATUS_REG	12	256	The address of the Sleep status register, represented in Generic Address Structure format (See Section 4.8.3.7, "Sleep Control and Status Registers," for a description of the sleep mechanism.) Note: Only System I/O space, System Memory space and PCI Configuration space (bus #0) are valid for values for Address_Space_ID. Also, Register_Bit_Width must be 8 and Register_Bit_Offset must be 0.

Table 5-35 Fixed ACPI Description Table Fixed Feature Flags

FACP - Flag	Bit Length	Bit Offset	Description
WBINVD	1	0	Processor properly implements a functional equivalent to the WBINVD IA-32 instruction. If set, signifies that the WBINVD instruction correctly flushes the processor caches, maintains memory coherency, and upon completion of the instruction, all caches for the current processor contain no cached data other than what OSPM references and allows to be cached. If this flag is not set, the ACPI OS is responsible for disabling all ACPI features that need this function. This field is maintained for ACPI 1.0 processor compatibility on existing systems. Processors in new ACPI-compatible systems are required to support this function and indicate this to OSPM by setting this field.
WBINVD_FLUSH	1	1	If set, indicates that the hardware flushes all caches on the WBINVD instruction and maintains memory coherency, but does not guarantee the caches are invalidated. This provides the complete semantics of the WBINVD instruction, and provides enough to support the system sleeping states. If neither of the WBINVD flags is set, the system will require FLUSH_SIZE and FLUSH_STRIDE to support sleeping states. If the FLUSH parameters are also not supported, the machine cannot support sleeping states S1, S2, or S3.
PROC_C1	1	2	A one indicates that the C1 power state is supported on all processors.
P_LVL2_UP	1	3	A zero indicates that the C2 power state is configured to only work on a uniprocessor (UP) system. A one indicates that the C2 power state is configured to work on a UP or multiprocessor (MP) system.
PWR_BUTTON	1	4	A zero indicates the power button is handled as a fixed feature programming model; a one indicates the power button is handled as a control method device. If the system does not have a power button, this value would be "1" and no sleep button device would be present. Independent of the value of this field, the presence of a power button device in the namespace indicates to OSPM that the power button is handled as a control method device.
SLP_BUTTON	1	5	A zero indicates the sleep button is handled as a fixed feature programming model; a one indicates the sleep button is handled as a control method device. If the system does not have a sleep button, this value would be "1" and no sleep button device would be present. Independent of the value of this field, the presence of a sleep button device in the namespace indicates to OSPM that the sleep button is handled as a control method device.

FACP - Flag	Bit Length	Bit Offset	Description
FIX_RTC	1	6	A zero indicates the RTC wake status is supported in fixed register space; a one indicates the RTC wake status is not supported in fixed register space.
RTC_S4	1	7	Indicates whether the RTC alarm function can wake the system from the S4 state. The RTC must be able to wake the system from an S1, S2, or S3 sleep state. The RTC alarm can optionally support waking the system from the S4 state, as indicated by this value.
TMR_VAL_EXT	1	8	A zero indicates TMR_VAL is implemented as a 24-bit value. A one indicates TMR_VAL is implemented as a 32-bit value. The TMR_STS bit is set when the most significant bit of the TMR_VAL toggles.
DCK_CAP	1	9	A zero indicates that the system cannot support docking. A one indicates that the system can support docking. Notice that this flag does not indicate whether or not a docking station is currently present; it only indicates that the system is capable of docking.
RESET_REG_SUP	1	10	If set, indicates the system supports system reset via the FADT RESET_REG as described in Section 4.8.3.6, "Reset Register."
SEALED_CASE	1	11	System Type Attribute. If set indicates that the system has no internal expansion capabilities and the case is sealed.
HEADLESS	1	12	System Type Attribute. If set indicates the system cannot detect the monitor or keyboard / mouse devices.
CPU_SW_SLP	1	13	If set, indicates to OSPM that a processor native instruction must be executed after writing the SLP_TYPx register.
PCI_EXP_WAK	1	14	If set, indicates the platform supports the PCIEXP_WAKE_STS bit in the PM1 Status register and the PCIEXP_WAKE_EN bit in the PM1 Enable register. This bit must be set on platforms containing chipsets that implement PCI Express.

FACP - Flag	Bit Length	Bit Offset	Description
USE_PLATFORM_CLO	1	15	A value of one indicates that OSPM should use a platform provided timer to drive any monotonically non-decreasing counters, such as OSPM performance counter services. Which particular platform timer will be used is OSPM specific, however, it is recommended that the timer used is based on the following algorithm: If the HPET is exposed to OSPM, OSPM should use the HPET. Otherwise, OSPM will use the ACPI power management timer. A value of one indicates that the platform is known to have a correctly implemented ACPI power management timer. A platform may choose to set this flag if a internal processor clock (or clocks in a multi-processor configuration) cannot provide consistent monotonically non-decreasing counters. Note: If a value of zero is present, OSPM may arbitrarily choose to use an internal processor clock or a platform timer clock for these operations. That is, a zero does not imply that OSPM will necessarily use the internal processor clock to generate a monotonically non-decreasing counter to the system.
S4_RTC_STS_VALID	1	16	A one indicates that the contents of the RTC_STS flag is valid when waking the system from S4. See <u>Table 4-16</u> – PM1 Status Registers Fixed Hardware Feature Status Bits for more information. Some existing systems do not reliably set this input today, and this bit allows OSPM to differentiate correctly functioning platforms from platforms with this errata.
REMOTE_POWER_ON _CAPABLE	1	17	A one indicates that the platform is compatible with remote power- on. That is, the platform supports OSPM leaving GPE wake events armed prior to an S5 transition. Some existing platforms do not reliably transition to S5 with wake events enabled (for example, the platform may immediately generate a spurious wake event after completing the S5 transition). This flag allows OSPM to differentiate correctly functioning platforms from platforms with this type of errata.
FORCE_ APIC_CLUSTER_MOD EL	1	18	A one indicates that all local APICs must be configured for the cluster destination model when delivering interrupts in logical mode. If this bit is set, then logical mode interrupt delivery operation may be undefined until OSPM has moved all local APICs to the cluster model. Note that the cluster destination model doesn't apply to Itanium TM Processor Family (IPF) local SAPICs. This bit is intended for xAPIC based machines that require the cluster destination model even when 8 or fewer local APICs are present in the machine.

FACP - Flag	Bit Length	Bit Offset	Description
FORCE_APIC_PHYSIC AL_DESTINATION_MO DE	1	19	A one indicates that all local xAPICs must be configured for physical destination mode. If this bit is set, interrupt delivery operation in logical destination mode is undefined. On machines that contain fewer than 8 local xAPICs or that do not use the xAPIC architecture, this bit is ignored.
HW_REDUCED_ACPI	1	20	A one indicates that the ACPI Hardware Interface (chapter 4) is not implemented. Software-only alternatives are used for supported fixed-features defined in chapter 4.
LOW_POWER_S0_IDL E_CAPABLE	1	21	A one informs OSPM that the platform is able to achieve power savings in S0 similar to or better than those typically achieved in S3. In effect, when this bit is set it indicates that the system will achieve no power benefit by making a sleep transition to S3.
Reserved	10	22	

5.2.9.1 Preferred PM Profile System Types

The following descriptions of preferred power management profile system types are to be used as a guide for setting the Preferred_PM_Profile field in the FADT. OSPM can use this field to set default power management policy parameters during OS installation.

Desktop

A single user, full featured, stationary computing device that resides on or near an individual's work area. Most often contains one processor. Must be connected to AC power to function. This device is used to perform work that is considered mainstream corporate or home computing (for example, word processing, Internet browsing, spreadsheets, and so on).

Mobile

A single-user, full-featured, portable computing device that is capable of running on batteries or other power storage devices to perform its normal functions. Most often contains one processor. This device performs the same task set as a desktop. However it may have limitations dues to its size, thermal requirements, and/or power source life.

Workstation

A single-user, full-featured, stationary computing device that resides on or near an individual's work area. Often contains more than one processor. Must be connected to AC power to function. This device is used to perform large quantities of computations in support of such work as CAD/CAM and other graphics-intensive applications.

Enterprise Server

A multi-user, stationary computing device that frequently resides in a separate, often specially designed, room. Will almost always contain more than one processor. Must be connected to AC power to function. This device is used to support large-scale

networking, database, communications, or financial operations within a corporation or government.

SOHO Server

A multi-user, stationary computing device that frequently resides in a separate area or room in a small or home office. May contain more than one processor. Must be connected to AC power to function. This device is generally used to support all of the networking, database, communications, and financial operations of a small office or home office.

Appliance PC

A device specifically designed to operate in a low-noise, high-availability environment such as a consumer's living rooms or family room. Most often contains one processor. This category also includes home Internet gateways, Web pads, set top boxes and other devices that support ACPI. Must be connected to AC power to function. Normally they are sealed case style and may only perform a subset of the tasks normally associated with today's personal computers.

Performance Server

A multi-user stationary computing device that frequently resides in a separate, often specially designed room. Will often contain more than one processor. Must be connected to AC power to function. This device is used in an environment where power savings features are willing to be sacrificed for better performance and quicker responsiveness.

Tablet

A full-featured, highly mobile computing device which resembles writing tablets and which users interact with primarily through a touch interface. The touch digitizer is the primary user input device, although a keyboard and/or mouse may be present. Tablet devices typically run on battery power and are generally only plugged into AC power in order to charge. This device performs many of the same tasks as Mobile; however battery life expectations of Tablet devices generally require more aggressive power savings especially for managing display and touch components.

5.2.9.2 System Type Attributes

This set of flags is used by the OS to assist in determining assumptions about power and device management. These flags are read at boot time and are used to make decisions about power management and device settings. For example, a system that has the SEALED_CASE bit set may take a very aggressive low noise policy toward thermal management. In another example an OS might not load video, keyboard or mouse drivers on a HEADLESS system.

5.2.9.3 IA-PC Boot Architecture Flags

This set of flags is used by an OS to guide the assumptions it can make in initializing hardware on IA-PC platforms. These flags are used by an OS at boot time (before the OS is capable of providing an operating environment suitable for parsing the ACPI namespace) to determine the code paths to take during boot. In IA-PC platforms with reduced legacy hardware, the OS can skip code paths for legacy devices if none are present. For example, if there are no ISA devices, an OS could skip code

that assumes the presence of these devices and their associated resources. These flags are used independently of the ACPI namespace. The presence of other devices must be described in the ACPI namespace as specified in <u>Section 6</u>, "Configuration." These flags pertain only to IA-PC platforms. On other system architectures, the entire field should be set to 0.

Table 5-36 Fixed ACPI Description Table Boot IA-PC Boot Architecture Flags

IAPC_BOOT_ARCH	Bit length	Bit offset	Description
LEGACY_DEVICES	1	0	If set, indicates that the motherboard supports user-visible devices on the LPC or ISA bus. User-visible devices are devices that have end-user accessible connectors (for example, LPT port), or devices for which the OS must load a device driver so that an end-user application can use a device. If clear, the OS may assume there are no such devices and that all devices in the system can be detected exclusively via industry standard device enumeration mechanisms (including the ACPI namespace).
8042	1	1	If set, indicates that the motherboard contains support for a port 60 and 64 based keyboard controller, usually implemented as an 8042 or equivalent micro-controller.
VGA Not Present	1	2	If set, indicates to OSPM that it must not blindly probe the VGA hardware (that responds to MMIO addresses A0000h-BFFFFh and IO ports 3B0h-3BBh and 3C0h-3DFh) that may cause machine check on this system. If clear, indicates to OSPM that it is safe to probe the VGA hardware.
MSI Not Supported	1	3	If set, indicates to OSPM that it must not enable Message Signaled Interrupts (MSI) on this platform.
PCIe ASPM Controls	1	4	If set, indicates to OSPM that it must not enable OSPM ASPM control on this platform.
CMOS RTC Not Present	1	5	If set, indicates that the CMOS RTC is either not implemented, or does not exist at the legacy addresses. OSPM uses the Control Method Time and Alarm Namespace device instead.
Reserved	10	6	Must be 0.

5.2.9.4 ARM Architecture boot flags

These flags are used by an OS at boot time (before the OS is capable of providing an operating environment suitable for parsing the ACPI namespace) to determine the code paths to take during boot. For the PSCI flags, specifically, the flags describe if the platform is compliant with the PSCI specification. The PSCI specification is found at *Links to ACPI-Related Document*" (http://uefi.org/acpi) under the heading *PSCI Specification*.

The ARM Architecture boot flags are described in <u>Table 5-37</u>:

Table 5-37 Fixed ACPI Description Table ARM Boot Architecture Flags

ARM_BOOT_ARCH	Bit Length	Bit Offset	Description
PSCI_COMPLIANT	1	0	1 if PSCI is implemented.

PSCI_USE_HVC	1	1	1 if HVC must be used as the PSCI conduit.instead of SMC.
Reserved	14	2	This value is zero.

5.2.10 Firmware ACPI Control Structure (FACS)

The Firmware ACPI Control Structure (FACS) is a structure in read/write memory that the BIOS reserves for ACPI usage. This structure is passed to an ACPI-compatible OS using the FADT. For more information about the FADT FIRMWARE_CTRL field, see <u>Table 5.2.9</u>, "Fixed ACPI Description Table (FADT)."

The BIOS aligns the FACS on a 64-byte boundary anywhere within the system's memory address space. The memory where the FACS structure resides must not be reported as system AddressRangeMemory in the system address map. For example, the E820 address map reporting interface would report the region as AddressRangeReserved. For more information about system address map reporting interfaces, see Section 15, "System Address Map Interfaces."

Table 5-38 Firmware ACPI Control Structure (FACS)

Field	Byte Length	Byte Offset	Description
Signature	4	0	'FACS'
Length	4	4	Length, in bytes, of the entire Firmware ACPI Control Structure. This value is 64 bytes or larger.
Hardware Signature	4	8	The value of the system's "hardware signature" at last boot. This value is calculated by the BIOS on a best effort basis to indicate the base hardware configuration of the system such that different base hardware configurations can have different hardware signature values. OSPM uses this information in waking from an S4 state, by comparing the current hardware signature to the signature values saved in the non-volatile sleep image. If the values are not the same, OSPM assumes that the saved non-volatile image is from a different hardware configuration and cannot be restored.

Field	Byte Length	Byte Offset	Description
Firmware Waking Vector	4	12	This field is superseded by the X_Firmware_Waking_Vector field. The 32-bit address field where OSPM puts its waking vector. Before transitioning the system into a global sleeping state, OSPM fills in this field with the physical memory address of an OS-specific wake function. During POST, the platform firmware first checks if the value of the X_Firmware_Waking_Vector field is non-zero and if so transfers control to OSPM as outlined in the X_Firmware_Waking_vector field description below. If the X_Firmware_Waking_Vector field is zero then the platform firmware checks the value of this field and if it is non-zero, transfers control to the specified address. On PCs, the wake function address is in memory below 1 MB and the control is transferred while in real mode. OSPM's wake function restores the processors' context. For IA-PC platforms, the following example shows the relationship between the physical address in the Firmware Waking Vector and the real mode address the BIOS jumps to. If, for example, the physical address is 0x12345, then the BIOS must jump to real mode address 0x1234:0x0005. In general this relationship is Real-mode address = Physical address>>4: Physical address and 0x000F Notice that on IA-PC platforms, A20 must be enabled when the BIOS jumps to the real mode address derived from the physical address stored in the Firmware Waking Vector.
Global Lock	4	16	This field contains the Global Lock used to synchronize access to shared hardware resources between the OSPM environment and an external controller environment (for example, the SMI environment). This lock is owned exclusively by either OSPM or the firmware at any one time. When ownership of the lock is attempted, it might be busy, in which case the requesting environment exits and waits for the signal that the lock has been released. For example, the Global Lock can be used to protect an embedded controller interface such that only OSPM or the firmware will access the embedded controller interface at any one time. See Section 5.2.10.1 , "Global Lock," for more information on acquiring and releasing the Global Lock.
Flags	4	20	Firmware control structure flags. See <u>Table 5-39</u> for a description of this field.

Field	Byte Length	Byte Offset	Description
X Firmware Waking Vector	8	24	64-bit physical address of OSPM's Waking Vector. Before transitioning the system into a global sleeping state, OSPM fills in this field and the OSPM Flags field to describe the waking vector. OSPM populates this field with the physical memory address of an OS-specific wake function. During POST, the platform firmware checks if the value of this field is non-zero and if so transfers control to OSPM by jumping to this address after creating the appropriate execution environment, which must be configured as follows: For 64-bit Itanium™ Processor Family (IPF) -based platforms: Interrupts must be disabled
			The processor must have psr.i set to 0. See the Intel® Itanium Architecture Software Developer's Manual for more information. Memory address translation must be disabled The processor must have psr.it, psr.dt, and psr.rt set to 0. See
Name of the state			the Intel® Itanium™ Architecture Software Developer's Manual for more information. For IA 32 and x64 platforms, platform firmware is required to support a 32 bit execution environment. Platform firmware can additionally support a 64 bit execution environment. If platform firmware supports a 64 bit execution environment, firmware inspects the OSPM Flags during POST. If the 64BIT_WAKE_F flag is set, the platform firmware creates a 64 bit execution environment. Otherwise, the platform firmware creates a 32 bit execution environment. For 64 bit execution environment: Interrupts must be disabled EFLAGS.IF set to 0 Long mode enabled Paging mode is enabled and physical memory for waking vector is identity mapped (virtual address equals physical address) Waking vector must be contained within one physical page Selectors are set to be flat and are otherwise not used For 32 bit execution environment: Interrupts must be disabled EFLAGS.IF set to 0 Memory address translation / paging must be disabled 4 GB flat address space for all segment registers
Version	1	32	2–Version of this table
Reserved	3	33	This value is zero.
OSPM Flags	4	36	OSPM enabled firmware control structure flags. Platform firmware must initialize this field to zero. See <u>Table 5-40</u> for a description of the OSPM control structure feature flags.
Reserved	24	40	This value is zero.

Table 5-39 Firmware Control Structure Feature Flags

FACS – Flag	Bit Length	Bit Offset	Description
S4BIOS_F	1	0	Indicates whether the platform supports S4BIOS_REQ. If S4BIOS_REQ is not supported, OSPM must be able to save and restore the memory state in order to use the S4 state.
64BIT_WAKE_SUPP ORTED_F	1	1	Indicates that the platform firmware supports a 64 bit execution environment for the waking vector. When set and the OSPM additionally set 64BIT_WAKE_F, the platform firmware will create a 64 bit execution environment before transferring control to the X_Firmware_Waking_Vector.
Reserved	30	2	The value is zero.

Table 5-40 OSPM Enabled Firmware Control Structure Feature Flags

FACS – Flag	Bit Length	Bit Offset	Description
64BIT_WAKE_F	1	0	OSPM sets this bit to indicate to platform firmware that the X_Firmware_Waking_Vector requires a 64 bit execution environment. This flag can only be set if platform firmware sets 64BIT_WAKE_SUPPORTED_F in the FACS flags field. This bit field has no affect on Itanium TM Processor Family (IPF) -based platforms, which require a 64 bit execution environment.
Reserved	31	1	The value is zero.

5.2.10.1 Global Lock

The purpose of the ACPI Global Lock is to provide mutual exclusion between the host OS and the ROM BIOS. The Global Lock is a 32-bit (DWORD) value in read/write memory located within the FACS and is accessed and updated by both the OS environment and the SMI environment in a defined manner to provide an exclusive lock. Note: this is not a *pointer* to the Global Lock, it is the *actual* memory location of the lock. The FACS and Global Lock may be located anywhere in physical memory.

By convention, this lock is used to ensure that while one environment is accessing some hardware, the other environment is not. By this convention, when ownership of the lock fails because the other environment owns it, the requesting environment sets a "pending" state within the lock, exits its attempt to acquire the lock, and waits for the owning environment to signal that the lock has been released before attempting to acquire the lock again. When releasing the lock, if the pending bit in the lock is set after the lock is released, a signal is sent via an interrupt mechanism to the other environment to inform it that the lock has been released. During interrupt handling for the "lock released" event within the corresponding environment, if the lock ownership were still desired an attempt to acquire the lock would be made. If ownership is not acquired, then the environment must again set "pending" and wait for another "lock release" signal.

The table below shows the encoding of the Global Lock DWORD in memory.

Table 5-41 Global Lock Structure within the FACS

Field	Bit Length	Bit Offset	Description
Pending	1	0	Non-zero indicates that a request for ownership of the Global Lock is pending.
Owned	1	1	Non-zero indicates that the Global Lock is Owned.
Reserved	30	2	Reserved for future use.

The following code sequence is used by both OSPM and the firmware to acquire ownership of the Global Lock. If non-zero is returned by the function, the caller has been granted ownership of the Global Lock and can proceed. If zero is returned by the function, the caller has not been granted ownership of the Global Lock, the "pending" bit has been set, and the caller must wait until it is signaled by an interrupt event that the lock is available before attempting to acquire access again.

Note: In the examples that follow, the "GlobalLock" variable is a pointer that has been previously initialized to point to the 32-bit Global Lock location within the FACS.

```
AcquireGlobalLock:
          mov ecx, GlobalLock ; ecx = Address of Global Lock in FACS
acq10:
                 eax, [ecx]
                                             ; Get current value of Global Lock
          mov
                edx. eax
           mov
           and edx, not 1 ; Clear pending bit
bts edx, 1 ; Check and set owner bit
add edx 0 ; If owned, set pending b.
           adc
                                            ; If owned, set pending bit
                  edx, 0
           lock cmpxchg dword ptr[ecx], edx  ; Attempt to set new value
           jnz short acq10
                                              ; If not set, try again
                                  ; Was it acquired or marked pending?
; acquired = -1, pending = 0
           cmp
                 dl, 3
                eax, eax
           sbb
           ret
```

The following code sequence is used by OSPM and the firmware to release ownership of the Global Lock. If non-zero is returned, the caller must raise the appropriate event to the other environment to signal that the Global Lock is now free. Depending on the environment, this signaling is done by setting the either the GBL_RLS or BIOS_RLS within their respective hardware register spaces. This signal only occurs when the other environment attempted to acquire ownership while the lock was owned.

```
ReleaseGlobalLock:
         mov ecx, GlobalLock ; ecx = Address of Global Lock in FACS
rel10:
                                         ; Get current value of Global Lock
         mov eax, [ecx]
               edx, eax
          mov
               edx, not 03h
                                         ; Clear owner and pending field
          lock cmpxchg dword ptr[ecx], edx ; Attempt to set it
          jnz short rel10
                                          ; If not set, try again
                                          ; Was pending set?
          and eax, 1
          ; If one is returned (we were pending) the caller must signal that the
          ; lock has been released using either GBL_RLS or BIOS_RLS as appropriate
```

Although using the Global Lock allows various hardware resources to be shared, it is important to notice that its usage when there is ownership contention could entail a significant amount of system overhead as well as waits of an indeterminate amount of time to acquire ownership of the Global Lock. For this reason, implementations should try to design the hardware to keep the required usage of the Global Lock to a minimum.

The Global Lock is required whenever a logical register in the hardware is shared. For example, if bit 0 is used by ACPI (OSPM) and bit 1 of the same register is used by SMI, then access to that register needs to be protected under the Global Lock, ensuring that the register's contents do not change from underneath one environment while the other is making changes to it. Similarly if the entire register is shared, as the case might be for the embedded controller interface, access to the register needs to be protected under the Global Lock.

5.2.11 Definition Blocks

A Definition Block consists of data in AML format (see Section 5.4 "Definition Block Encoding") and contains information about hardware implementation details in the form of AML objects that contain data, AML code, or other AML objects. The top-level organization of this information after a definition block is loaded is name-tagged in a hierarchical namespace.

OSPM "loads" or "unloads" an entire definition block as a logical unit. OSPM will load a definition block either as a result of executing the AML **Load()** or **LoadTable()** operator or encountering a table definition during initialization. During initialization, OSPM loads the Differentiated System Description Table (DSDT), which contains the Differentiated Definition Block, using the DSDT pointer retrieved from the FADT. OSPM will load other definition blocks during initialization as a result of encountering Secondary System Description Table (SSDT) definitions in the RSDT/XSDT. The DSDT and SSDT are described in the following sections.

As mentioned, the AML **Load()** and **LoadTable()** operators make it possible for a Definition Block to load other Definition Blocks, either statically or dynamically, where they in turn can either define new system attributes or, in some cases, build on prior definitions. Although this gives the hardware the ability to vary widely in implementation, it also confines it to reasonable boundaries. In some cases, the Definition Block format can describe only specific and well-understood variances. In other cases, it permits implementations to be expressible only by means of a specified set of "built in" operators. For example, the Definition Block has built in operators for I/O space.

In theory, it might be possible to define something like PCI configuration space in a Definition Block by building it from I/O space, but that is not the goal of the definition block. Such a space is usually defined as a "built in" operator.

Some AML operators perform simple functions, and others encompass complex functions. The power of the Definition block comes from its ability to allow these operations to be glued together in numerous ways, to provide functionality to OSPM.

The AML operators defined in this specification are intended to allow many useful hardware designs to be easily expressed, not to allow all hardware designs to be expressed.

Note: To accommodate addressing beyond 32 bits, the integer type was expanded to 64 bits in ACPI 2.0, see Section 19.2.5, "ASL Data Types". Existing ACPI definition block implementations may contain an inherent assumption of a 32-bit integer width. Therefore, to maintain backwards compatibility, OSPM uses the Revision field, in the header portion of system description tables containing Definition Blocks, to determine whether integers declared within the Definition Block are to be evaluated as 32-bit or 64-bit values. A Revision field value greater than or equal to 2 signifies that integers declared within the Definition Block are to be evaluated as 64-bit values. The ASL writer specifies the value for the Definition Block table header's Revision field via the ASL Definition Block's ComplianceRevision field. See Section 19.5.28, "DefinitionBlock (Declare Definition Block)", for more information. It is the responsibility of the ASL writer to ensure the Definition Block's compatibility with the corresponding integer width when setting the ComplianceRevision field.

5.2.11.1 Differentiated System Description Table (DSDT)

The Differentiated System Description Table (DSDT) is part of the system fixed description. The DSDT is comprised of a system description table header followed by data in Definition Block format. This Definition Block is like all other Definition Blocks, with the exception that it cannot be unloaded. See Section 5.2.11, "Definition Blocks," for a description of Definition Blocks. During initialization, OSPM finds the pointer to the DSDT in the Fixed ACPI Description Table (using the FADT's DSDT or X_DSDT fields) and then loads the DSDT to create the ACPI Namespace.

Table 5-42 Differentiated Syst	em Description Ta	ble Fields	(DSDT)
--------------------------------	-------------------	------------	--------

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'DSDT' Signature for the Differentiated System Description Table.
Length	4	4	Length, in bytes, of the entire DSDT (including the header).
Revision	1	8	2. This field also sets the global integer width for the AML interpreter. Values less than two will cause the interpreter to use 32-bit integers and math. Values of two and greater will cause the interpreter to use full 64-bit integers and math.
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	The manufacture model ID.
OEM Revision	4	24	OEM revision of DSDT for supplied OEM Table ID.

Field	Byte Length	Byte Offset	Description
Creator ID	4	28	Vendor ID for the ASL Compiler.
Creator Revision	4	32	Revision number of the ASL Compiler.
Definition Block	n	36	n bytes of AML code (see Section 5.4, "Definition Block Encoding")

5.2.11.2 Secondary System Description Table (SSDT)

Secondary System Description Tables (SSDT) are a continuation of the DSDT. The SSDT is comprised of a system description table header followed by data in Definition Block format. There can be multiple SSDTs present. After OSPM loads the DSDT to create the ACPI Namespace, each secondary system description table listed in the RSDT/XSDT with a unique OEM Table ID is loaded.

Note: Additional tables can only add data; they cannot overwrite data from previous tables.

This allows the OEM to provide the base support in one table and add smaller system options in other tables. For example, the OEM might put dynamic object definitions into a secondary table such that the firmware can construct the dynamic information at boot without needing to edit the static DSDT. A SSDT can only rely on the DSDT being loaded prior to it.

Table 5-43 Secondary System Description Table Fields (SSDT)

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'SSDT' Signature for the Secondary System Description Table.
Length	4	4	Length, in bytes, of the entire SSDT (including the header).
Revision	1	8	2
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	The manufacture model ID.
OEM Revision	4	24	OEM revision of DSDT for supplied OEM Table ID.
Creator ID	4	28	Vendor ID for the ASL Compiler.
Creator Revision	4	32	Revision number of the ASL Compiler.
Definition Block	n	36	n bytes of AML code (see Section 5.4, "Definition Block Encoding")

5.2.11.3 Persistent System Description Table (PSDT)

The table signature, "PSDT" refers to the Persistent System Description Table (PSDT) defined in the ACPI 1.0 specification. The PSDT was judged to provide no specific benefit and as such has been deleted from follow-on versions of the ACPI specification. OSPM will evaluate a table with the "PSDT" signature in like manner to the evaluation of an SSDT as described in <u>Section 5.2.11.2</u>, "Secondary System Description Table."

5.2.12 Multiple APIC Description Table (MADT)

The ACPI interrupt model describes all interrupts for the entire system in a uniform interrupt model implementation. Supported interrupt models include the PC-AT-compatible dual 8259 interrupt controller, for Intel processor-based systems, the Intel Advanced Programmable Interrupt Controller (APIC) and Intel Streamlined Advanced Programmable Interrupt Controller (SAPIC), and, for ARM processor-based systems, the Generic Interrupt Controller (GIC). The choice of the interrupt model(s) to support is up to the platform designer. The interrupt model cannot be dynamically changed by the system firmware; OSPM will choose which model to use and install support for that model at the time of installation. If a platform supports multiple models, an OS will install support for only one of the models; it will not mix models. Multi-boot capability is a feature in many modern operating systems. This means that a system may have multiple operating systems or multiple instances of an OS installed at any one time. Platform designers must allow for this.

This section describes the format of the Multiple APIC Description Table (MADT), which provides OSPM with information necessary for operation on systems with APIC, SAPIC or GIC implementations.

ACPI represents all interrupts as "flat" values known as global system interrupts. Therefore to support APICs, SAPICs or GICs on an ACPI-enabled system, each used interrupt input must be mapped to the global system interrupt value used by ACPI. See <u>Section 5.2.13</u>. Global System Interrupts," for a description of Global System Interrupts.

Additional support is required to handle various multi-processor functions that implementations might support (for example, identifying each processor's local interrupt controller ID).

All addresses in the MADT are processor-relative physical addresses.

Table 5-44 Multiple APIC Description Table (MADT) Format

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'APIC' Signature for the Multiple APIC Description Table.
Length	4	4	Length, in bytes, of the entire MADT.
Revision	1	8	3
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	For the MADT, the table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision of MADT for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For tables containing Definition Blocks, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For tables containing Definition Blocks, this is the revision for the ASL Compiler.
Local Interrupt Controller Address	4	36	The 32-bit physical address at which each processor can access its local interrupt controller.
Flags	4	40	Multiple APIC flags. See <u>Table 5-45</u> for a description of this field.

Field	Byte Length	Byte Offset	Description
Interrupt Controller Structure[n]	_	44	A list of interrupt controller structures for this implementation. This list will contain all of the structures from <u>Table 5-46</u> needed to support this platform. These structures are described in the following sections.

Table 5-45 Multiple APIC Flags

Multiple APIC Flags	Bit Length	Bit Offset	Description
PCAT_COMPAT	1	0	A one indicates that the system also has a PC-AT-compatible dual-8259 setup. The 8259 vectors must be disabled (that is, masked) when enabling the ACPI APIC operation.
Reserved	31	1	This value is zero.

Immediately after the Flags value in the MADT is a list of interrupt controller structures that declare the interrupt features of the machine. The first byte of each structure declares the type of that structure and the second byte declares the length of that structure.

Table 5-46 Interrupt Controller Structure Types

Value	Description
0	Processor Local APIC
1	I/O APIC
2	Interrupt Source Override
3	Non-maskable Interrupt Source (NMI)
4	Local APIC NMI
5	Local APIC Address Override
6	I/O SAPIC
7	Local SAPIC
8	Platform Interrupt Sources
9	Processor Local x2APIC
0xA	Local x2APIC NMI
0xB	GICC CPU Interface Structure
0xC	GICD GIC Distributor Structure
0xD	GICv2m MSI Frame
0xE	GICR Redistributor Structure
0xF-0x7F	Reserved. OSPM skips structures of the reserved type.
0x80-0xFF	Reserved for OEM use

5.2.12.1 MADT Processor Local APIC / SAPIC Structure Entry Order

OSPM implementations may limit the number of supported processors on multi-processor platforms. OSPM executes on the boot processor to initialize the platform including other processors. To ensure that the boot processor is supported post initialization, two guidelines should be followed. The first is that OSPM should initialize processors in the order that they appear in the MADT. The second is that platform firmware should list the boot processor as the first processor entry in the MADT.

The advent of multi-threaded processors yielded multiple logical processors executing on common processor hardware. ACPI defines logical processors in an identical manner as physical processors. To ensure that non multi-threading aware OSPM implementations realize optimal performance on platforms containing multi-threaded processors, two guidelines should be followed. The first is the same as above, that is, OSPM should initialize processors in the order that they appear in the MADT. The second is that platform firmware should list the first logical processor of each of the individual multi-threaded processors in the MADT before listing any of the second logical processors. This approach should be used for all successive logical processors.

Failure of OSPM implementations and platform firmware to abide by these guidelines can result in both unpredictable and non optimal platform operation.

5.2.12.2 Processor Local APIC Structure

When using the APIC interrupt model, each processor in the system is required to have a Processor Local APIC record and an ACPI Processor object. OSPM does not expect the information provided in this table to be updated if the processor information changes during the lifespan of an OS boot. While in the sleeping state, processors are not allowed to be added, removed, nor can their APIC ID or Flags change. When a processor is not present, the Processor Local APIC information is either not reported or flagged as disabled.

Table 5-47 Processor Local APIC Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	0 Processor Local APIC structure
Length	1	1	8
ACPI Processor ID	1	2	The ProcessorId for which this processor is listed in the ACPI Processor declaration operator. For a definition of the Processor operator, see Section 19.5.100 , "Processor (Declare Processor)."
APIC ID	1	3	The processor's local APIC ID.
Flags	4	4	Local APIC flags. See <u>Table 5-47</u> for a description of this field.

Table 5-48 Local APIC Flags

LocalAPIC Flags	Bit Length	Bit Offset	Description
Enabled	1	0	If zero, this processor is unusable, and the operating system support will not attempt to use it.
Reserved	31	1	Must be zero.

5.2.12.3 I/O APIC Structure

In an APIC implementation, there are one or more I/O APICs. Each I/O APIC has a series of interrupt inputs, referred to as INTIn, where the value of n is from 0 to the number of the last interrupt input on the I/O APIC. The I/O APIC structure declares which global system interrupts are uniquely associated with the I/O APIC interrupt inputs. There is one I/O APIC structure for each I/O APIC in the system. For more information on global system interrupts see Section 5.2.13, "Global System Interrupts."

Table 5-49 I/O APIC Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	1 I/O APIC structure
Length	1	1	12
I/O APIC ID	1	2	The I/O APIC's ID.
Reserved	1	3	0
I/O APIC Address	4	4	The 32-bit physical address to access this I/O APIC. Each I/O APIC resides at a unique address.
Global System Interrupt Base	4	8	The global system interrupt number where this I/O APIC's interrupt inputs start. The number of interrupt inputs is determined by the I/O APIC's <i>Max Redir Entry</i> register.

5.2.12.4 Platforms with APIC and Dual 8259 Support

Systems that support both APIC and dual 8259 interrupt models must map global system interrupts 0-15 to the 8259 IRQs 0-15, except where Interrupt Source Overrides are provided (see Section 5.2.12.5, "Interrupt Source Override Structure" below). This means that I/O APIC interrupt inputs 0-15 must be mapped to global system interrupts 0-15 and have identical sources as the 8259 IRQs 0-15 unless overrides are used. This allows a platform to support OSPM implementations that use the APIC model as well as OSPM implementations that use the 8259 model (OSPM will only use one model; it will not mix models).

When OSPM supports the 8259 model, it will assume that all interrupt descriptors reporting global system interrupts 0-15 correspond to 8259 IRQs. In the 8259 model all global system interrupts greater than 15 are ignored. If OSPM implements APIC support, it will enable the APIC as described by the APIC specification and will use all reported global system interrupts that fall within the limits of the interrupt inputs defined by the I/O APIC structures. For more information on hardware resource configuration see Section 6, "Configuration."

5.2.12.5 Interrupt Source Override Structure

Interrupt Source Overrides are necessary to describe variances between the IA-PC standard dual 8259 interrupt definition and the platform's implementation.

It is assumed that the ISA interrupts will be identity-mapped into the first I/O APIC sources. Most existing APIC designs, however, will contain at least one exception to this assumption. The Interrupt Source Override Structure is provided in order to describe these exceptions. It is not necessary to provide an Interrupt Source Override for every ISA interrupt. Only those that are not identity-mapped onto the APIC interrupt inputs need be described.

Note: This specification only supports overriding ISA interrupt sources.

For example, if your machine has the ISA Programmable Interrupt Timer (PIT) connected to ISA IRQ 0, but in APIC mode, it is connected to I/O APIC interrupt input 2, then you would need an Interrupt Source Override where the source entry is '0' and the Global System Interrupt is '2.'

Table 5-50 Interrupt Source Override Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	2 Interrupt Source Override
Length	1	1	10
Bus	1	2	0 Constant, meaning ISA
Source	1	3	Bus-relative interrupt source (IRQ)
Global System Interrupt	4	4	The Global System Interrupt that this bus-relative interrupt source will signal.
Flags	2	8	MPS INTI flags. See <u>Table 5-51</u> for a description of this field.

The MPS INTI flags listed in <u>Table 5-51</u> are identical to the flags used in Table 4-10 of the MPS version 1.4 specifications. The Polarity flags are the PO bits and the Trigger Mode flags are the EL bits.

Table 5-51 MPS INTI Flags

Local APIC - Flags	Bit Length	Bit Offset	Description
Polarity	2	0	Polarity of the APIC I/O input signals: 00 Conforms to the specifications of the bus (For example, EISA is active-low for level-triggered interrupts) 01 Active high 10 Reserved 11 Active low
Trigger Mode	2	2	Trigger mode of the APIC I/O Input signals: 00 Conforms to specifications of the bus (For example, ISA is edge-triggered) 01 Edge-triggered 10 Reserved 11 Level-triggered
Reserved	12	4	Must be zero.

Interrupt Source Overrides are also necessary when an identity mapped interrupt input has a non-standard polarity.

Note: You must have an interrupt source override entry for the IRQ mapped to the SCI interrupt if this IRQ is not identity mapped. This entry will override the value in SCI_INT in FADT. For example, if SCI is connected to IRQ 9 in PIC mode and IRQ 9 is connected to INTIN11 in APIC mode, you

should have 9 in SCI_INT in the FADT and an interrupt source override entry mapping IRQ 9 to INTIN11.

5.2.12.6 Non-Maskable Interrupt Source Structure

This structure allows a platform designer to specify which I/O (S)APIC interrupt inputs should be enabled as non-maskable. Any source that is non-maskable will not be available for use by devices.

Table 5-52 Non-maskable Source Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	3 NMI
Length	1	1	8
Flags	2	2	Same as MPS INTI flags
Global System Interrupt	4	4	The Global System Interrupt that this NMI will signal.

5.2.12.7 Local APIC NMI Structure

This structure describes the Local APIC interrupt input (LINT*n*) that NMI is connected to for each of the processors in the system where such a connection exists. This information is needed by OSPM to enable the appropriate local APIC entry.

Each Local APIC NMI connection requires a separate Local APIC NMI structure. For example, if the platform has 4 processors with ID 0-3 and NMI is connected LINT1 for processor 3 and 2, two Local APIC NMI entries would be needed in the MADT.

Table 5-53 Local APIC NMI Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	4 Local APIC NMI Structure
Length	1	1	6
ACPI Processor ID	1	2	Processor ID corresponding to the ID listed in the processor object. A value of 0xFF signifies that this applies to all processors in the machine.
Flags	2	3	MPS INTI flags. See <u>Table 5-51</u> for a description of this field.
Local APIC LINT#	1	5	Local APIC interrupt input LINTn to which NMI is connected.

5.2.12.8 Local APIC Address Override Structure

This optional structure supports 64-bit systems by providing an override of the physical address of the local APIC in the MADT's table header, which is defined as a 32-bit field.

If defined, OSPM must use the address specified in this structure for all local APICs (and local SAPICs), rather than the address contained in the MADT's table header. Only one Local APIC Address Override Structure may be defined.

Table 5-54 Local APIC Address Override Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	5 Local APIC Address Override Structure
Length	1	1	12
Reserved	2	2	Reserved (must be set to zero)
Local APIC Address	8	4	Physical address of Local APIC. For Itanium™ Processor Family (IPF)-based platforms, this field contains the starting address of the
			Processor Interrupt Block. See the Intel® Itanium TM Architecture Software Developer's Manual for more information.

5.2.12.9 I/O SAPIC Structure

The I/O SAPIC structure is very similar to the I/O APIC structure. If both I/O APIC and I/O SAPIC structures exist for a specific APIC ID, the information in the I/O SAPIC structure must be used.

The I/O SAPIC structure uses the I/O_APIC_ID field as defined in the I/O APIC table. The Vector_Base field remains unchanged but has been moved. The I/O APIC address has been deleted. A new address and reserved field have been added.

Table 5-55 I/O SAPIC Structure

Field	Byte Length	Byte Offset	Description
Type	1	0	6 I/O SAPIC Structure
Length	1	1	16
I/O APIC ID	1	2	I/O SAPIC ID
Reserved	1	3	Reserved (must be zero)
Global System Interrupt Base	4	4	The global system interrupt number where this I/O SAPIC's interrupt inputs start. The number of interrupt inputs is determined by the I/O SAPIC's <i>Max Redir Entry</i> register.
I/O SAPIC Address	8	8	The 64-bit physical address to access this I/O SAPIC. Each I/O SAPIC resides at a unique address.

If defined, OSPM must use the information contained in the I/O SAPIC structure instead of the information from the I/O APIC structure.

If both I/O APIC and an I/O SAPIC structures exist in an MADT, the OEM/BIOS writer must prevent "mixing" I/O APIC and I/O SAPIC addresses. This is done by ensuring that there are at least as many I/O SAPIC structures as I/O APIC structures and that every I/O APIC structure has a corresponding I/O SAPIC structure (same APIC ID).

5.2.12.10 Local SAPIC Structure

The Processor local SAPIC structure is very similar to the processor local APIC structure. When using the SAPIC interrupt model, each processor in the system is required to have a Processor Local SAPIC record and an ACPI Processor object. OSPM does not expect the information provided in

this table to be updated if the processor information changes during the lifespan of an OS boot. While in the sleeping state, processors are not allowed to be added, removed, nor can their SAPIC ID or Flags change. When a processor is not present, the Processor Local SAPIC information is either not reported or flagged as disabled.

Table 5-56 Processor Local SAPIC Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	7 Processor Local SAPIC structure
Length	1	1	Length of the Local SAPIC Structure in bytes.
ACPI Processor ID	1	2	OSPM associates the Local SAPIC Structure with a processor object declared in the namespace using the Processor statement by matching the processor object's ProcessorID value with this field. For a definition of the Processor object, see Section 19.5.100, "Processor (Declare Processor)."
Local SAPIC ID	1	3	The processor's local SAPIC ID
Local SAPIC EID	1	4	The processor's local SAPIC EID
Reserved	3	5	Reserved (must be set to zero)
Flags	4	8	Local SAPIC flags. See <u>Table 5-48</u> for a description of this field.
ACPI Processor UID Value	4	12	OSPM associates the Local SAPIC Structure with a processor object declared in the namespace using the Device statement, when the _UID child object of the processor device evaluates to a numeric value, by matching the numeric value with this field.
ACPI Processor UID String	>=1	16	OSPM associates the Local SAPIC Structure with a processor object declared in the namespace using the Device statement, when the _UID child object of the processor device evaluates to a string, by matching the string with this field. This value is stored as a null-terminated ASCII string.

5.2.12.11 Platform Interrupt Source Structure

The Platform Interrupt Source structure is used to communicate which I/O SAPIC interrupt inputs are connected to the platform interrupt sources.

Platform Management Interrupts (PMIs) are used to invoke platform firmware to handle various events (similar to SMI in IA-32). The Intel® ItaniumTM architecture permits the I/O SAPIC to send a vector value in the interrupt message of the PMI type. This value is specified in the I/O SAPIC Vector field of the Platform Interrupt Sources Structure.

INIT messages cause processors to soft reset.

If a platform can generate an interrupt after correcting platform errors (e.g., single bit error correction), the interrupt input line used to signal such corrected errors is specified by the Global System Interrupt field in the following table. Some systems may restrict the retrieval of corrected platform error information to a specific processor. In such cases, the firmware indicates the processor that can retrieve the corrected platform error information through the Processor ID and EID fields in the structure below. OSPM is required to program the I/O SAPIC redirection table entries with the Processor ID, EID values specified by the ACPI system firmware. On platforms

where the retrieval of corrected platform error information can be performed on any processor, the firmware indicates this capability by setting the CPEI Processor Override flag in the Platform Interrupt Source Flags field of the structure below. If the CPEI Processor Override Flag is set, OSPM uses the processor specified by Processor ID, and EID fields of the structure below only as a target processor hint and the error retrieval can be performed on any processor in the system. However, firmware is required to specify valid values in Processor ID, EID fields to ensure backward compatibility.

If the CPEI Processor Override flag is clear, OSPM may reject a ejection request for the processor that is targeted for the corrected platform error interrupt. If the CPEI Processor Override flag is set, OSPM can retarget the corrected platform error interrupt to a different processor when the target processor is ejected.

Note that the _MAT object can return a buffer containing Platform Interrupt Source Structure entries. It is allowed for such an entry to refer to a Global System Interrupt that is already specified by a Platform Interrupt Source Structure provided through the static MADT table, provided the value of platform interrupt source flags are identical.

Refer to the ItaniumTM Processor Family System Abstraction Layer (SAL) Specification for details on handling the Corrected Platform Error Interrupt.

Table 5-57 Platform Interrupt Sources Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	8 Platform Interrupt Source structure
Length	1	1	16
Flags	2	2	MPS INTI flags. See <u>Table 5-51</u> for a description of this field.
Interrupt Type	1	4	1 PMI 2 INIT 3 Corrected Platform Error Interrupt All other values are reserved.
Processor ID	1	5	Processor ID of destination.
Processor EID	1	6	Processor EID of destination.
I/O SAPIC Vector	1	7	Value that OSPM must use to program the vector field of the I/O SAPIC redirection table entry for entries with the PMI interrupt type.
Global System Interrupt	4	8	The Global System Interrupt that this platform interrupt will signal.
Platform Interrupt Source Flags	4	12	Platform Interrupt Source Flags. See <u>Table 5-58</u> for a description of this field

Table 5-58 Platform Interrupt Source Flags

Platform Interrupt Source Flags	Bit Length	Bit Offset	Description
CPEI Processor Override	1	0	When set, indicates that retrieval of error information is allowed from any processor and OSPM is to use the information provided by the processor ID, EID fields of the Platform Interrupt Source Structure (Table 5-57) as a target processor hint.
Reserved	31	1	Must be zero.

5.2.12.12 Processor Local x2APIC Structure

The Processor X2APIC structure is very similar to the processor local APIC structure. When using the X2APIC interrupt model, logical processors with APIC ID values of 255 and greater are required to have a Processor Device object and must convey the processor's APIC information to OSPM using the Processor Local X2APIC structure. Logical processors with APIC ID values less than 255 must use the Processor Local APIC structure to convey their APIC information to OSPM. OSPM does not expect the information provided in this table to be updated if the processor information changes during the lifespan of an OS boot. While in the sleeping state, logical processors must not be added or removed, nor can their X2APIC ID or x2APIC Flags change. When a logical processor is not present, the processor local X2APIC information is either not reported or flagged as disabled.

The format of x2APIC structure is listed in Table 5-59

Table 5-59 Processor Local x2APIC Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	9 Processor Local x2APIC structure
Length	1	1	16
Reserved	2	2	Reserved - Must be zero
X2APIC ID	4	4	The processor's local x2APIC ID.
Flags	4	8	Same as Local APIC flags. See <u>Table 5-47</u> for a description of this field.
ACPI Processor UID	4	12	OSPM associates the X2APIC Structure with a processor object declared in the namespace using the Device statement, when the _UID child object of the processor device evaluates to a numeric value, by matching the numeric value with this field

5.2.12.13 Local x2APIC NMI Structure

The Local APIC NMI and Local x2APIC NMI structures describe the interrupt input (LINTn) that NMI is connected to for each of the logical processors in the system where such a connection exists. Each NMI connection to a processor requires a separate NMI structure. This information is needed by OSPM to enable the appropriate APIC entry.

NMI connection to a logical processor with local x2APIC ID 255 and greater requires an X2APIC NMI structure. NMI connection to a logical processor with an x2APIC ID less than 255 requires a

Local APIC NMI structure. For example, if the platform contains 8 logical processors with x2APIC IDs 0-3 and 256-259 and NMI is connected LINT1 for processor 3, 2, 256 and 257 then two Local APIC NMI entries and two X2APIC NMI entries must be provided in the MADT.

The Local APIC NMI structure is used to specify global LINTx for all processors if **all** logical processors have x2APIC ID less than 255. If the platform contains **any** logical processors with an x2APIC ID of 255 or greater then the Local X2APIC NMI structure must be used to specify global LINTx for **ALL** logical processors. The format of x2APIC NMI structure is listed in <u>Table 5-60</u>.

Table 5-60 Local x2APIC NMI Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	0AH Local x2APIC NMI Structure
Length	1	1	12
Flags	2	2	Same as MPS INTI flags. See <u>Table 5-51</u> for a description of this field.
ACPI Processor UID	4	4	UID corresponding to the ID listed in the processor Device object. A value of 0xFFFFFFFF signifies that this applies to all processors in the machine.
Local x2APIC LINT#	1	8	Local x2APIC interrupt input LINTn to which NMI is connected.
Reserved	3	9	Reserved - Must be zero.




Figure 5-25 APIC-Global System Interrupts

5.2.12.14 GICC Structure

In the GICC interrupt model, logical processors are required to have a Processor Device object in the DSDT, and must convey each processor's GICC information to the OS using the GICC structure.

The format of the GICC structure is shown in <u>Table 5-61</u>.

Table 5-61 GICC Structure Format

Field	Byte Length	Byte Offset	Description
Туре	1	0	0xB GICC structure
Length	1	1	76
Reserved	2	2	Reserved - Must be zero
CPU Interface Number	4	4	GIC's CPU Interface Number. In GICv1/v2 implementations, this value matches the bit index of the associated processor in the GIC distributor's GICD_ITARGETSR register. For GICv3/4 implementations this field must be provided by the platform, if compatibility mode is supported. If it is not supported by the implementation, then this field must be ignored by the OSPM.

Field	Byte Length	Byte Offset	Description
ACPI Processor UID	4	8	The OS associates this GICC Structure with a processor device object in the namespace when the _UID child object of the processor device evaluates to a numeric value that matches the numeric value in this field.
Flags	4	12	See <u>Table 5-62</u> .
Parking Protocol Version	4	16	Version of the ARM-Processor Parking Protocol implemented. See http://infocenter.arm.com/help/index.jsp . The document is under "Multiprocessor Startup for ARM Platforms" For systems that support PSCI exclusively and do not support the parking protocol, this field must be set to 0.
Performance Interrupt GSIV	4	20	The GSIV used for Performance Monitoring Interrupts
Parked Address	8	24	The 64-bit physical address of the processor's Parking Protocol mailbox
Physical Base Address	8	32	On GICv1/v2 systems and GICv3/4 systems in GICv2 compatibility mode, this field holds the 64-bit physical address at which the processor can access this GIC CPU Interface. If provided here, the "Local Interrupt Controller Address" field in the MADT must be ignored by the OSPM.
GICV	8	40	Address of the GIC virtual CPU interface registers. If the platform is not presenting a GICv2 with virtualization extensions this field can be 0.
GICH	8	48	Address of the GIC virtual interface control block registers. If the platform is not presenting a GICv2 with virtualization extensions this field can be 0.
VGIC Maintenance interrupt	4	56	GSIV for Virtual GIC maintenance interrupt
GICR Base Address	8	60	On systems supporting GICv3 and above, this field holds the 64-bit physical address of the associated Redistributor. If all of the GIC Redistributors are in the always-on power domain, GICR structures should be used to describe the Redistributors instead, and this field must be set to 0.

Field	Byte Length	Byte Offset	Description
MPIDR	8	68	This fields follows the MPIDR formatting of ARM architecture.
			If the implements ARMv7 architecure then the format must be:
			Bits [24:63] Must be zero
			Bits [16:23] Aff2: Match Aff2 of target processor MPIDR
			Bits [8:15] Aff1: Match Aff1 of target processor MPIDR
			Bits [0:7] Aff0: Match Aff0 of target processor MPIDR
			For platforms implementing ARMv8 the format must be:
			Bits [40:63]: Must be zero
			Bits [32:39] Aff3: Match Aff3 of target processor MPIDR
			Bits [24:31] Must be zero
			Bits [16:23] Aff2: Match Aff2 of target processor MPIDR
			Bits [8:15] Aff1: Match Aff1 of target processor MPIDR
			Bits [0:7] Aff0 : Match Aff0 of target processor MPIDR

Table 5-62 GICC CPU Interface Flags

GIC Flags	Bit Length	Bit Offset	Description
Enabled	1	0	If zero, this processor is unusable, and the operating system support will not attempt to use it.
Performance Interrupt Mode	1	1	0 - Level-triggered 1 - Edge-Triggered
VGIC Maintenance interrupt Mode Flags	1	2	0 - Level-triggered 1 - Edge-Triggered
Reserved	29	3	Must be zero.

Note: GICC descriptor structures are listed immediately after the Flags field in the MADT, one descriptor for each GICC, followed by one for each GICC Distributor. The Local GICC corresponding to the boot processor must be the first entry in the Interrupt Controller Structure list.

5.2.12.15 GIC Distributor Structure

ACPI represents all interrupts as "flat" values known as global system interrupts (GSIVs) (Section 5.2.13). On ARM, the GIC Distributor has some number of interrupt inputs corresponding to the same number of contiguous GSIVs. Therefore, each used interrupt input must be mapped to the global system interrupt value used by ACPI for that input. This mapping is provided by the GIC Distributor structure, by setting the base GSIV for the GIC Distributor.

The format of the GIC Distributor structure is listed in Table 5-63.

Table 5-63 GIC Distributor Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	0xC GIC Distributor structure
Length	1	1	24
Reserved	2	2	Reserved - Must be zero
GIC ID	4	4	This GIC Distributor's hardware ID
Physical Base Address	8	8	The 64-bit physical address for this Distributor
System Vector Base	4	16	The global system interrupt number where this GIC Distributor's interrupt inputs start.
Reserved	4	20	Must be zero

5.2.12.16 GIC MSI Frame Structure

Each GICv2m MSI frame consists of a 4k page which includes registers to generate message signaled interrupts to an associated GIC distributor. The frame also includes registers to discover the set of distributor lines which may be signaled by MSIs from that frame. A system may have multiple MSI frames, and separate frames may be defined for secure and non-secure access. This structure must only be used to describe non-secure MSI frames.

The format of the GIC MSI Frame Structure is listed in <u>Table 5-64</u>.

Table 5-64 GIC MSI Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	0xD GIC MSI structure
Length	1	1	24
Reserved	2	2	Reserved - Must be zero
GIC MSI Frame ID	4	4	GIC MSI Frame ID. In a system with multiple GIC MSI frames, this value must be unique to each one.
Physical Base Address	8	8	The 64-bit physical address for this MSI Frame
Flags	4	16	GIC MSI Frame Flags. See <u>Table 5-65</u>
SPI Count	2	20	SPI Count used by this frame. Unless the SPI Count Select flag is set to 1 this value should match the lower 16 bits of the MSI_TYPER register in the frame.
SPI Base	2	22	SPI Base used by this frame. Unless the SPI Base Select flag is set to 1 this value should match the upper 16 bits of the MSI_TYPER register in the frame.

Table 5-65 GIC MSI Frame Flags

GIC MSI Frame	Bit	Bit	Description
Flags	Length	Offset	
SPI Count/Base Select	1	0	O: The SPI Count and Base fields should be ignored, and the actual values should be queried from the MSI_TYPER register in the associated GIC MSI frame. 1: The SPI Count and Base values override the values specified in the MSI_TYPER register in the associated GIC MSI frame.
Reserved	31	1	Must be zero.

5.2.12.17 GICR Structure

The GICR Structure is described in <u>Table 5-68</u>. This structure enables the discovery of GIC Redistributor base addresses by providing the Physical Base Address of a page range containing the GIC Redistributors. More than one GICR Structure may be presented in the MADT. GICR structures should only be used when describing GIC implementations which conform to version 3 or higher of the GIC architecture and which place all Redistributors in the always-on power domain.

Table 5-66 GIC Redistributor Structure

Field	Byte	Byte	Description
	Length	Offset	
Туре	1	0	0xE GIC Redistributor structure
Length	1	1	16
Reserved	2	2	Reserved - Must be zero
Discovery Range Base Address	8	4	The 64-bit physical address of a page range containing all GIC Redistributors
Discovery Range Length	4	12	Length of the GIC Redistributor Discovery page range.

5.2.13 Global System Interrupts

Global System Interrupts can be thought of as ACPI Plug and Play IRQ numbers. They are used to virtualize interrupts in tables and in ASL methods that perform resource allocation of interrupts. Do not confuse global system interrupts with ISA IRQs although in the case of the IA-PC 8259 interrupts they correspond in a one-to-one fashion.

There are two interrupt models used in ACPI-enabled systems.

The first model is the APIC model. In the APIC model, the number of interrupt inputs supported by each I/O APIC can vary. OSPM determines the mapping of the Global System Interrupts by determining how many interrupt inputs each I/O APIC supports and by determining the global system interrupt base for each I/O APIC as specified by the I/O APIC Structure. OSPM determines the number of interrupt inputs by reading the Max Redirection register from the I/O APIC. The global system interrupts mapped to that I/O APIC begin at the global system interrupt base and extending through the number of interrupts specified in the Max Redirection register. This mapping is depicted in Figure 5-25.

Global System Interrupt Vector
(ie ACPI PnP IRQ#)

0

IRQ0

IRQ3

IRQ3

IRQ7

IRQ7

IRQ7

IR8

Slave
8259

8

IRQ11

There is exactly one I/O APIC structure per I/O APIC in the system.

Figure 5-26 8259–Global System Interrupts

15

IRO15

The other interrupt model is the standard AT style mentioned above which uses ISA IRQs attached to a master slave pair of 8259 PICs. The system vectors correspond to the ISA IRQs. The ISA IRQs and their mappings to the 8259 pair are part of the AT standard and are well defined. This mapping is depicted in Figure 5-26.

5.2.14 Smart Battery Table (SBST)

If the platform supports batteries as defined by the Smart Battery Specification 1.0 or 1.1, then an Smart Battery Table (SBST) is present. This table indicates the energy level trip points that the platform requires for placing the system into the specified sleeping state and the suggested energy levels for warning the user to transition the platform into a sleeping state. Notice that while Smart Batteries can report either in current (mA/mAh) or in energy (mW/mWh), OSPM must set them to operate in energy (mW/mWh) mode so that the energy levels specified in the SBST can be used. OSPM uses these tables with the capabilities of the batteries to determine the different trip points. For more precise definitions of these levels, see Section 3.9.3, "Battery Gas Gauge."

Table 5-67 Smart Battery Description Table (SBST) Format

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'SBST' Signature for the Smart Battery Description Table.
Length	4	4	Length, in bytes, of the entire SBST
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.

Field	Byte Length	Byte Offset	Description
OEMID	6	10	OEM ID
OEM Table ID	8	16	For the SBST, the table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision of SBST for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For tables containing Definition Blocks, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For tables containing Definition Blocks, this is the revision for the ASL Compiler.
Warning Energy Level	4	36	OEM suggested energy level in milliWatt-hours (mWh) at which OSPM warns the user.
Low Energy Level	4	40	OEM suggested platform energy level in mWh at which OSPM will transition the system to a sleeping state.
Critical Energy Level	4	44	OEM suggested platform energy level in mWh at which OSPM performs an emergency shutdown.

5.2.15 Embedded Controller Boot Resources Table (ECDT)

This optional table provides the processor-relative, translated resources of an Embedded Controller. The presence of this table allows OSPM to provide Embedded Controller operation region space access before the namespace has been evaluated. If this table is not provided, the Embedded Controller region space will not be available until the Embedded Controller device in the AML namespace has been discovered and enumerated. The availability of the region space can be detected by providing a REG method object underneath the Embedded Controller device.

Table 5-68 Embedded Controller Boot Resources Table Format

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'ECDT' Signature for the Embedded Controller Table.
Length	4	4	Length, in bytes, of the entire Embedded Controller Table
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	For the Embedded Controller Table, the table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision of Embedded Controller Table for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For tables containing Definition Blocks, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For tables containing Definition Blocks, this is the revision for the ASL Compiler.

Field	Byte Length	Byte Offset	Description
EC_CONTROL	12	36	Contains the processor relative address, represented in Generic Address Structure format, of the Embedded Controller Command/ Status register. Note: Only System I/O space and System Memory space are valid for values for Address_Space_ID.
EC_DATA	12	48	Contains the processor-relative address, represented in Generic Address Structure format, of the Embedded Controller Data register. Note: Only System I/O space and System Memory space are valid for values for Address_Space_ID.
UID	4	60	Unique ID–Same as the value returned by the _UID under the device in the namespace that represents this embedded controller.
GPE_BIT	1	64	The bit assignment of the SCI interrupt within the GPEx_STS register of a GPE block described in the FADT that the embedded controller triggers.
EC_ID	Variable	65	ASCII, null terminated, string that contains a fully qualified reference to the namespace object that is this embedded controller device (for example, "_SB.PCI0.ISA.EC"). Quotes are omitted in the data field.

ACPI OSPM implementations supporting Embedded Controller devices must also support the ECDT. ACPI 1.0 OSPM implementation will not recognize or make use of the ECDT. The following example code shows how to detect whether the Embedded Controller operation regions are available in a manner that is backward compatible with prior versions of ACPI/OSPM.

```
Device(EC0) {
    Name(REGC, Ones)
     Method(_REG,2) {
         If(Lequal(Arg0, 3)) {
             Store(Arg1, REGC)
Method(ECAV, 0) {
     If(Lequal(REGC,Ones)) {
         If(LgreaterEqual(_REV,2)) {
             Return(One)
         Else {
             Return(Zero)
     Else {
         Return(REGC)
To detect the availability of the region, call the ECAV method. For example:
if (\_SB.PCIO.ECO.ECAV()) {
     ...regions are available...
else {
     ...regions are not available...
```

5.2.16 System Resource Affinity Table (SRAT)

This optional table provides information that allows OSPM to associate processors and memory ranges, including ranges of memory provided by hot-added memory devices, with system localities / proximity domains and clock domains. On NUMA platforms, SRAT information enables OSPM to optimally configure the operating system during a point in OS initialization when evaluation of objects in the ACPI Namespace is not yet possible. OSPM evaluates the SRAT only during OS initialization. The Local APIC ID / Local SAPIC ID / Local x2APIC ID or the GICC ACPI Processor UID of all processors started at boot time must be present in the SRAT. If the Local APIC ID / Local SAPIC ID / Local x2APIC ID or the GICC ACPI Processor UID of a dynamically added processor is not present in the SRAT, a _PXM object must exist for the processor's device or one of its ancestors in the ACPI Namespace.

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'SRAT'. Signature for the System Resource Affinity Table.
Length	4	4	Length, in bytes, of the entire SRAT. The length implies the number of Entry fields at the end of the table
Revision	1	8	3
Checksum	1	9	Entire table must sum to zero.

OEMID	6	10	OEM ID.
OEM Table ID	8	16	For the System Resource Affinity Table, the table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision of System Resource Affinity Table for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table.
Creator Revision	4	32	Revision of utility that created the table.
Reserved	4	36	Reserved to be 1 for backward compatibility
Reserved	8	40	Reserved
Static Resource Allocation Structure[n]		48	A list of static resource allocation structures for the platform. See Section 5.2.16.1,"Processor Local APIC/SAPIC Affinity Structure", Section 5.2.16.2 "Memory Affinity Structure", Section 5.2.16.3 "Processor Local x2APIC Affinity Structure", and Section 5.2.16.4, "GICC Affinity Structure.

5.2.16.1 Processor Local APIC/SAPIC Affinity Structure

The Processor Local APIC/SAPIC Affinity structure provides the association between the APIC ID or SAPIC ID/EID of a processor and the proximity domain to which the processor belongs. <u>Table 5-70</u> provides the details of the Processor Local APIC/SAPIC Affinity structure.

Table 5-70 Processor Local APIC/SAPIC Affinity Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	0 Processor Local APIC/SAPIC Affinity Structure
Length	1	1	16
Proximity Domain [7:0]	1	2	Bit[7:0] of the proximity domain to which the processor belongs.
APIC ID	1	3	The processor local APIC ID.
Flags	4	4	Flags – Processor Local APIC/SAPIC Affinity Structure. See Table 5-56 for a description of this field.
Local SAPIC EID	1	8	The processor local SAPIC EID.
Proximity Domain [31:8]	3	9	Bit[31:8] of the proximity domain to which the processor belongs.
Clock Domain	4	12	The clock domain to which the processor belongs. See Section 6.2.1, "_CDM (Clock Domain)".

Table 5-71 Flags – Processor Local APIC/SAPIC Affinity Structure

Field	Bit	Bit	Description
	Lengt	Offset	
	h		

Enabled	1	0	If clear, the OSPM ignores the contents of the Processor Local APIC/SAPIC Affinity Structure. This allows system firmware to populate the SRAT with a static number of structures but only enable them as necessary.
Reserved	31	1	Must be zero.

5.2.16.2 Memory Affinity Structure

The Memory Affinity structure provides the following topology information statically to the operating system:

- The association between a range of memory and the proximity domain to which it belongs
- Information about whether the range of memory can be hot-plugged.

<u>Table 5-72</u> provides the details of the Memory Affinity structure.

Table 5-72 Memory Affinity Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	1 Memory Affinity Structure
Length	1	1	40
Proximity Domain	4	2	Integer that represents the proximity domain to which the processor belongs
Reserved	2	6	Reserved
Base Address Low	4	8	Low 32 Bits of the Base Address of the memory range
Base Address High	4	12	High 32 Bits of the Base Address of the memory range
Length Low	4	16	Low 32 Bits of the length of the memory range.
Length High	4	20	High 32 Bits of the length of the memory range.
Reserved	4	24	Reserved.
Flags	4	28	Flags – Memory Affinity Structure. Indicates whether the region of memory is enabled and can be hot plugged. See <u>Table 5-73</u> .
Reserved	8	32	Reserved.

Table 5-73 Flags – Memory Affinity Structure

Field	Bit Length	Bit Offset	Description
Enabled	1	0	If clear, the OSPM ignores the contents of the Memory Affinity Structure. This allows system firmware to populate the SRAT with a static number of structures but only enable then as necessary.

Hot Pluggable ^a	1	1	The information conveyed by this bit depends on the value of the Enabled bit. If the Enabled bit is set and the Hot Pluggable bit is also set. The system hardware supports hot-add and hot-remove of this memory region If the Enabled bit is set and the Hot Pluggable bit is clear, the system hardware does not support hot-add or hot-remove of this memory region. If the Enabled bit is clear, the OSPM will ignore the contents of the Memory Affinity Structure
NonVolatile	1	2	If set, the memory region represents Non-Volatile memory
Reserved	29	3	Must be zero.

a.

5.2.16.3 Processor Local x2APIC Affinity Structure

The Processor Local x2APIC Affinity structure provides the association between the local x2APIC ID of a processor and the proximity domain to which the processor belongs. <u>Table 5-74</u> provides the details of the Processor Local x2APIC Affinity structure.

Table 5-74 Processor Local x2APIC Affinity Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	2 Processor Local x2APIC Affinity Structure
Length	1	1	24
Reserved	2	2	Reserved – Must be zero
Proximity Domain	4	4	The proximity domain to which the logical processor belongs.
X2APIC ID	4	8	The processor local x2APIC ID.
Flags	4	12	Same as Processor Local APIC/SAPIC Affinity Structure flags. See <u>Table 5-71</u> for a description of this field.
Clock Domain	4	16	The clock domain to which the logical processor belongs. See Section 6.2.1, "_CDM (Clock Domain)".
Reserved	4	20	Reserved.

On x86-based platforms, the OSPM uses the Hot Pluggable bit to determine whether it should shift into PAE mode to allow for insertion of hot-plug memory with physical addresses over 4 GB.

5.2.16.4 GICC Affinity Structure

The GICC Affinity Structure provides the association between the ACPI Processor UID of a processor and the proximity domain to which the processor belongs. <u>Table 5-75</u> provides the details of the GICC Affinity structure.

Table 5-75 GICC Affinity Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	3 GICC Affinity Structure.
Length	1	1	18
Proximity Domain	4	2	The proximity domain to which the logical processor belongs.
ACPI Processor UID	4	6	The ACPI Processor UID of the associated GICC.
Flags	4	10	Flags – GICC Affinity Structure. See <u>Table 5-76</u> for a description of this field.
Clock Domain	4	14	The clock domain to which the logical processor belongs. See Section 6.2.1, "_CDM (Clock Domain)".

Table 5-76 Flags - GICC Affinity Structure

Field	Byte Length	Byte Offset	Description
Enabled	1	0	If clear, the OSPM ignores the contents of the GICC Affinity Structure. This allows system firmware to populate the SRAT with a static number of structures but only enable them as necessary.
Reserved	31	1	Must be zero.

5.2.17 System Locality Distance Information Table (SLIT)

This optional table provides a matrix that describes the relative distance (memory latency) between all System Localities, which are also referred to as Proximity Domains. Systems employing a Non Uniform Memory Access (NUMA) architecture contain collections of hardware resources including for example, processors, memory, and I/O buses, that comprise what is known as a "NUMA node". Processor accesses to memory or I/O resources within the local NUMA node is generally faster than processor accesses to memory or I/O resources outside of the local NUMA node.

The value of each Entry[i,j] in the SLIT table, where i represents a row of a matrix and j represents a column of a matrix, indicates the relative distances from System Locality / Proximity Domain i to every other System Locality j in the system (including itself).

The i,j row and column values correlate to the value returned by the PXM object in the ACPI namespace. See Section 6.2.14, "PXM (Proximity)" for more information.

The entry value is a one-byte unsigned integer. The relative distance from System Locality i to System Locality j is the i*N + j entry in the matrix, where N is the number of System Localities. Except for the relative distance from a System Locality to itself, each relative distance is stored twice in the matrix. This provides the capability to describe the scenario where the relative distances for the two directions between System Localities is different.

The diagonal elements of the matrix, the relative distances from a System Locality to itself are normalized to a value of 10. The relative distances for the non-diagonal elements are scaled to be relative to 10. For example, if the relative distance from System Locality *i* to System Locality *j* is

2.4, a value of 24 is stored in table entry i*N+j and in j*N+i, where N is the number of System Localities.

If one locality is unreachable from another, a value of 255 (0xFF) is stored in that table entry. Distance values of 0-9 are reserved and have no meaning.

Table 5-77 SLIT Format

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'SLIT'. Signature for the System Locality Distance Information Table.
Length	4	4	Length, in bytes, of the entire System Locality Distance Information Table.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID.
OEM Table ID	8	16	For the System Locality Information Table, the table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision of System Locality Information Table for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For the DSDT, RSDT, SSDT, and PSDT tables, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For the DSDT, RSDT, SSDT, and PSDT tables, this is the revision for the ASL Compiler.
Number of System Localities	8	36	Indicates the number of System Localities in the system.
Entry[0][0]	1	44	Matrix entry (0,0), contains a value of 10.
Entry[0][Number of System Localities-1]	1		Matrix entry (0, Number of System Localities-1)
Entry[1][0]	1		Matrix entry (1,0)
Entry[Number of System Localities- 1][Number of System Localities-1]	1		Matrix entry (Number of System Localities-1, Number of System Localities-1), contains a value of 10

5.2.18 Corrected Platform Error Polling Table (CPEP)

Platforms may contain the ability to detect and correct certain operational errors while maintaining platform function. These errors may be logged by the platform for the purpose of retrieval. Depending on the underlying hardware support, the means for retrieving corrected platform error

information varies. If the platform hardware supports interrupt-based signaling of corrected platform errors, the MADT Platform Interrupt Source Structure describes the Corrected Platform Error Interrupt (CPEI). See Section 5.2.12.11,"Platform Interrupt Source Structure". Alternatively, OSPM may poll processors for corrected platform error information. Error log information retrieved from a processor may contain information for all processors within an error reporting group. As such, it may not be necessary for OSPM to poll all processors in the system to retrieve complete error information. This optional table provides information that allows OSPM to poll only the processors necessary for a complete report of the platform's corrected platform error information.

Table 5-78 Corrected Platform Error Polling Table Format

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'CPEP'. Signature for the Corrected Platform Error Polling Table.
Length	4	4	Length, in bytes, of the entire CPET. The length implies the number of Entry fields at the end of the table
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID.
OEM Table ID	8	16	For the Corrected Platform Error Polling Table, the table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision of Corrected Platform Error Polling Table for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table.
Creator Revision	4	32	Revision of utility that created the table.
Reserved	8	36	Reserved, must be 0.
CPEP Processor Structure[n]		44	A list of Corrected Platform Error Polling Processor structures for the platform. See Section 5.2.18.1," Corrected Platform Error Polling Processor Structure".

5.2.18.1 Corrected Platform Error Polling Processor Structure

The Corrected Platform Error Polling Processor structure provides information on the specific processors OSPM polls for error information. <u>Table 5-79</u> provides the details of the Corrected Platform Error Polling Processor structure.

Table 5-79 Corrected Platform Error Polling Processor Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	0 Corrected Platform Error Polling Processor structure for APIC/SAPIC based processors
Length	1	1	8

Processor ID	1	2	Processor ID of destination.	
Processor EID	1	3	Processor EID of destination.	
Polling Interval	4	4	Platform-suggested polling interval (in milliseconds)	

5.2.19 Maximum System Characteristics Table (MSCT)

This section describes the format of the Maximum System Characteristic Table (MSCT), which provides OSPM with information characteristics of a system's maximum topology capabilities. If the system maximum topology is not known up front at boot time, then this table is not present. OSPM will use information provided by the MSCT only when the System Resource Affinity Table (SRAT) exists. The MSCT must contain all proximity and clock domains defined in the SRAT.

Table 5-80 Maximum System Characteristics Table (MSCT) Format

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'MSCT' Signature for the Maximum System Characteristics Table.
Length	4	4	Length, in bytes, of the entire MSCT.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	For the MSCT, the table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision of MSCT for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For tables containing Definition Blocks, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For tables containing Definition Blocks, this is the revision for the ASL Compiler.
Offset to Proximity Domain Information Structure [OffsetProxDomInfo]	4	Offset in bytes to the Proximity Domain Information Structure table entry.	
Maximum Number of Proximity Domains	4	40	Indicates the maximum number of Proximity Domains ever possible in the system. The number reported in this field is (maximum domains – 1). For example if there are 0x10000 possible domains in the system, this field would report 0xFFFF.
Maximum Number of Clock Domains	4	44	Indicates the maximum number of Clock Domains ever possible in the system. The number reported in this field is (maximum domains – 1). See Section 6.2.1, "_CDM (Clock Domain)".

Field	Byte Length	Byte Offset	Description
Maximum Physical Address	8	48	Indicates the maximum Physical Address ever possible in the system. Note: this is the top of the reachable physical address.
Proximity Domain Information Structure[Maximum Number of Proximity Domains]	_	[OffsetProx DomInfo]	A list of Proximity Domain Information for this implementation. The structure format is defined in the Maximum Proximity Domain Information Structure section.

5.2.19.1 Maximum Proximity Domain Information Structure

The Maximum Proximity Domain Information Structure is used to report system maximum characteristics. It is likely that these characteristics may be the same for many proximity domains, but they can vary from one proximity domain to another. This structure optimizes to cover the former case, while allowing the flexibility for the latter as well. These structures must be organized in ascending order of the proximity domain enumerations. All proximity domains within the Maximum Number of Proximity Domains reported in the MSCT must be covered by one of these structures.

Table 5-81 Maximum Proximity Domain Information Structure

Field	Byte Length	Byte Offset	Description
Revision	1	0	1
Length	1	1	22
Proximity Domain Range (low)	4	2	The starting proximity domain for the proximity domain range that this structure is providing information.
Proximity Domain Range (high)	4	6	The ending proximity domain for the proximity domain range that this structure is providing information.
Maximum Processor Capacity	4	10	The Maximum Processor Capacity of each of the Proximity Domains specified in the range. A value of 0 means that the proximity domains do not contain processors. This field must be >= the number of processor entries for the domain in the SRAT.
Maximum Memory Capacity	8	14	The Maximum Memory Capacity (size in bytes) of the Proximity Domains specified in the range. A value of 0 means that the proximity domains do not contain memory.

5.2.20 ACPI RAS FeatureTable (RASF)

The following table describes structure of ACPI RAS Feature Table.

Table 5-82 RASF Table format

Field	Byte Length	Byte Offset	Description
Header			

Signature	4	0	'RASF' is Signature for RAS Feature Table
Length	4	4	Length in bytes for entire RASF. The length implies the number of Entry fields at the end of the table
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero
OEMID	6	10	OEM ID
OEM Table ID	8	16	The table ID is the manufacturer model ID
OEM Revision	4	24	OEM revision of table for supplied OEM Table ID
Creator ID	4	28	Vendor ID of utility that created the table
Creator Revision	4	32	Revision of utility that created the table
RASF Specific Entries			
RASF Platform Communication Channel Identifier	12	36	Identifier of the RASF Platform Communication Channel. OSPM should use this value to identify the PCC Sub channel structure in the RASF table

5.2.20.1 RASF PCC Sub Channel Identifier

RASF PCC Sub Channel Identifier is used by the OSPM to identify the PCC Sub channel structure. RASF table references its PCC Subspace by this identifier as shown in <u>Table 5-82</u>.

5.2.20.2 Using PCC registers

OSPM will write PCC registers by filling in the register value in PCC sub channel space and issuing a PCC Execute command. See <u>Table 5-84</u>.

To minimize the cost of PCC transactions, OSPM should read or write all registers in the same PCC subspace via a single read or write command.

5.2.20.3 RASF Communication Channel

RASF Action Entries are defined in the PCC sub channel as below.

Table 5-83 RASF Platform Communication Channel Shared Memory Region

Field	Byte Length	Byte Offset	Description
Signature	4	0	The PCC Signature of 0x52415346 (corresponds to ASCII signature of RASF)
Command	2	4	PCC command field; see <u>Table 5-84</u> and <u>Section 14</u> .
Status	2	6	PCC status field, see Section 14.
Communication Space			
Version	2	8	Byte 0 – Minor Version Byte 1 – Major Version

Field	Byte Length	Byte Offset	Description
RAS Capabilities	16	10	Bit Map describing the platform RAS capabilities as shown in Section 5.2.20.4. The Platform populates this field. The OSPM uses this field to determine the RAS capabilities of the platform.
Set RAS Capabilities	16	26	BIT Map of the RAS features for which the OSPM is invoking the command. The BIT Map is described in Section 5.2.20.4. OSPM sets the bit corresponding to a RAS capability to invoke a command on that capability. The bitmap implementation allows OSPM to invoke a command on each RAS feature supported by the platform at the same time.
Number of RASF Parameter blocks	2	42	The Number of parameter blocks will depend on how many RAS Capabilities the Platform Supports. Typically, there will be one Parameter Block per RAS Feature, using which that feature can be managed by OSPM.
Set RAS Capabilities Status	4	44	Status $0000b = Success$ $0001b = Not Valid$ $0010b = Not Supported$ $0011b = Busy$ $0100b = Failed$ $0101b = Aborted$ $0110b = Invalid Data$
Parameter Blocks	Varies (N Bytes)	48	Start of the parameter blocks, the structure of which is shown in Table 5-86. These parameter blocks are used as communication mailbox between the OSPM and the platform, and there is 1 parameter block for each RAS feature. NOTE: There can be only on parameter block per type.

Table 5-84 PCC Command Codes used by RASF Platform Communication Channel

Command	Description
0x00	Reserved
0x01	Execute RASF Command.

Command	Description
0x02-0xFF	All other values are reserved.

5.2.20.4 Platform RAS Capabilities

The following table defines the Platform RAS capabilities:

Table 5-85 Platform RAS capabilities bitmap

Bit	RAS Feature	Description
0	Hardware based patrol scrub supported	Indicates that platform support hardware based patrol scrub of DRAM memory
1	Hardware based patrol scrub supported and exposed to software	Indicates that platform support hardware based patrol scrub of DRAM memory and platform exposes this capability to software using this RASF mechanism
2-127	Reserved	Reserved for future use

5.2.20.5 Parameter Block

The following table describes the Parameter Blocks. The structure is used to pass parameters for controlling the corresponding RAS Feature.

Each RAS Feature is assigned a TYPE number, which is the bit index into the RAS capabilities bitmap described in <u>Table 5-85</u>.

Table 5-86 Parameter Block Structure for PATROL_SCRUB

Field	Byte Length	Byte Offset	Description
Туре	2	0	0x0000 – Patrol scrub
Version	2	2	BYTE 0 – Minor Version BYTE 1 – Major Version
Length	2	4	Length, in bytes of the entire parameter block structure
Patrol Scrub Command (INPUT)	2	6	0x01 - GET_PATROL_PARAMETERS 0x02 - START_PATROL_SCRUBBER 0x03 - STOP_PATROL_SCRUBBER
Requested Address Range (INPUT)	16	8	OSPM Specifies the BASE (Bytes 7:0) and SIZE (Bytes 15:8) of the address range to be patrol scrubbed.
			OSPM sets this parameter for the following commands GET_PATROL_PARAMETERS START_PATROL_SCRUBBER

Field	Byte Length	Byte Offset	Description
Actual Address Range (OUTPUT)	16	24	The platform returns this value in response to GET_PATROL_PARAMETERS. The platform calculates the nearest patrol scrub boundary address from where it can start. This range should be a superset of the Requested Address Range. BASE (Bytes 7:0) and SIZE (Bytes 15:8) of the address
Flags (OUTPUT)	2	40	The platform returns this value in response to GET_PATROL_PARAMETERS BIT 0: Will be set if patrol scrubber is already running for address range specified in "Actual Address Range" BITs 1-3: Current Patrol Speeds, if BIT 0 is set 000b – Slow 100b – Medium 111b – Fast All other combinations are reserved. BITs 4 – 15: RESERVED
Requested Speed (INPUT)	1	42	The OSPM Sets this field as follows, for the START_PATROL_SCRUBBER command BIT 0: Will be set if patrol scrubber is already running for address range specified in "Actual Address Range" BITs 0-2: Requested Patrol Speeds 000b – Slow 100b – Medium 111b – Fast All other combinations are reserved. BITs 3 – 7: RESERVED

5.2.20.5.1 Sequence of Operations:

The following sequence documents the steps for OSPM to identify whether the platform supports hardware based patrol scrub and invoke commands to request hardware to patrol scrub the specified address range.

- 1. Identify whether the platform supports hardware based patrol scrub and exposes the support to software by reading the RAS capabilities bitmap in RASF table
- 2. Call GET PATROL PARAMETERS, by setting the Requested Address Range.

- 3. Platform Returns Actual Address Range and Flags.
- 4. Based on the above two data, if the OPSM decides to start the patrol scrubber or change the speed of the patrol scrubber, then the OSPM calls START_PATROL_SCRUBBER, by setting the *Requested Address Range* and *Requested Speed*.

5.2.21 Memory Power StateTable (MPST)

The following table describes the structure of new ACPI memory power state table (MPST). This table defines the memory power node topology of the configuration, as described earlier in Section 1. The configuration includes specifying memory power nodes and their associated information. Each memory power node is specified using address ranges, supported memory power states. The memory power states will include both hardware controlled and software controlled memory power states. There can be multiple entries for a given memory power node to support non contiguous address ranges. MPST table also defines the communication mechanism between OSPM and BIOS for triggering software controlled memory powerstate transitions implemented in BIOS.

<u>Figure 5-27</u> below provides structure organization overview of MPST table.




Figure 5-27 MPST ACPI Table Overview

Table 5-87 MPST Table Structure

Field	Byte Length	Byte Offset	Description	
Header				
Signature	4	0	'MPST'. Signature for Memory Power State Table	
Length	4	4	Length in bytes for entire MPST. The length implies the number of Entry fields at the end of the table	
Revision	1	8	1	
Checksum	1	9	Entire table must sum to zero	
OEMID	6	10	OEM ID	
OEM Table ID	8	16	For the memory power state table, the table ID is the manufacturer model ID	
OEM Revision	4	24	OEM revision of memory power state Table for supplied OEM Table ID	
Creator ID	4	28	Vendor ID of utility that created the table	
Creator Revision	4	32	Revision of utility that created the table	
Memory PCC				
MPST Platform Communication Channel Identifier	1	36	Identifier of the MPST Platform Communication Channel.	
Reserved	3	37	Reserved	
Memory Power Node				
Memory Power Node Count	2	40	Number of Memory power Node structure entries	
Reserved	2	42	Reserved	
Memory Power Node Structure[Memory Power Node Count]			This field provides information on the memory power nodes present in the system. The information includes memory node id, power states supported & associated latencies. Further details of this field are specified in Section 5.2.21.4	
Memory Power State Characteristics				
Memory Power State Characteristics Count	2		Number of Memory power State Characteristics Structure entries	
Reserved	2		Reserved	
Memory Power State Characteristics Structure [m]			This field provides information of memory power states supported in the system. The information includes power consumed, transition latencies, relevant flags.	

5.2.21.1 MPST PCC Sub Channel

The MPST PCC Sub Channel Identifier value provided by the platform in this field should be programmed to the Type field of PCC Communications Subspace Structure. The MPST table references its PCC Subspace in a given platform by this identifier, as shown in <u>Table 5-87</u>.

5.2.21.1.1 Using PCC registers

OSPM will write PCC registers by filling in the register value in PCC sub channel space and issuing a PCC Execute command. See <u>Table 5-88</u>, below. All other command values are reserved.

Table 5-88 PCC Command Codes used by MPST Platform Communication Channel

Command	Description
0x00-0x02	All other values are reserved.
0x03	Execute MPST Command.
0x04-0xFF	All other values are reserved.

Table 5-89 MPST Platform Communication Channel Shared Memory Region

Field	Byte Length	Byte Offset	Description
Signature	4	0	The PCC signature. The signature of a subspace is computed by a bitwise-or of the value 0x50434300 with the subspace ID. For example, subspace 3 has signature 0x50434303.
Command	2	4	PCC command field, see <u>Section 14</u> and <u>Table 5-88</u> .
Status	2	6	PCC status field, see Section 14
Communication Spa	ace		
MEMORY_POWER _COMMAND_REGI STER	4	8	Memory region for OSPM to write the requested memory power state. Write: 1 to this field to GET the memory power state 2 to this field to set the memory power state 3 – GET AVERAGE POWER CONSUMED 4 – GET MEMORY ENERGY CONSUMED

MEMORY_POWER _STATUS_REGIST ER	4	12	Bits 3-0: Status (specific to MEMORY_POWER_COMMAND_REGISTER) • 0000b = Success • 0001b = Not Valid • 0010b = Not Supported • 0011b = Busy • 0100b = Failed • 0101b = Aborted • 0110b = Invalid Data • Other values reserved Bit 4: Background Activity specific to the following MEMORY_POWER_COMMAND_REGISTER value: 3 - GET AVERAGE POWER CONSUMED 4 - GET MEMORY ENERGY CONSUMED 0b = inactive 1b = background memory activity is in progress Bits 5-31: Reserved
POWER STATE ID	4	16	On completion of a GET operation, OSPM reads the current platform state ID from this field. Prior to a SET operation, OSPM populates this field with the power state value which needs to be triggered. Power State values will be based on the platform capability
MEMORY_POWER _NODE_ID	4	20	This field identifies Memory power node number for the command.
MEMORY_ENERG Y_CONSUMED	8	24	This field returns the energy consumed by the memory that constitutes the MEMORY_POWER_NODE_ID specified in the previous field. A value of all 1s in this field indicates that platform does not implement this field.
EXPECTED_AVER AGE_POWER_CO NSUMED	8	32	This field returns the expected average power consumption for the memory constituted by MEMORY_POWER_NODE_ID. A value of all 1s in this field indicates that platform does not implement this field.

Note: OSPM should use the ratio of computed memory power consumed to expected average power consumed in determining the memory power management action.

5.2.21.2 Memory Power State

Memory Power State represents the state of a memory power node (which maps to a memory address range) while the platform is in the G0 working state. Memory power node could be in active state named MPS0 or in one of the power manage states MPS1-MPSn.

It should be noted that active memory power state (MPS0) does not preclude memory power management in that state. It only indicates that any active state memory power management in MPS0 is transparent to the OSPM and more importantly does not require assist from OSPM in terms of restricting memory occupancy and activity.

MPS1-MPSn states are characterized by non-zero exit latency for exit from the state to MPS0. These states could require explicit OSPM-initiated entry and exit, explicit OSPM-initiated entry but autonomous exit or autonomous entry and exit. In all three cases, these states require explicit OSPM action to isolate and free the memory address range for the corresponding memory power node.

Transitions to more aggressive memory power states (for example, from MPS1 to MPS2) can be entered on progressive idling but require transition through MPS0 (i.e. MPS1→MPS0→MPS2). Power state transition diagram is shown in Figure 5-28.

It is possible that after OSPM request a memory power state, a brief period of activity returns the memory power node to MPS0 state . If platform is capable of returning to a memory power state on subsequent period of idle, the platform must treat the previously requested memory power state as a persistent hint.




Figure 5-28 Memory Power State Transitions

The following table enumerates the power state values that a node can transition to.

Table 5-90 Power stat	te 1	valı	ues
-----------------------	------	------	-----

Value	State Name	Description
0	MPS0	This state value maps to active state of memory node (Normal operation). OSPM can access memory during this state.
1	MPS1	This state value can be mapped to any memory power state depending on the platform capability. The platform will inform the features of MPS1 state using the Memory Power State Structure. By convention, it is required that low value power state will have lower power savings and lower latencies than the higher valued power states.
2,3n	MPS2, MPS3, MPSn	Same description as MPS1.

The following provides the list of command status:

Table 5-91 Command Status

Field	Bit Length	Bit Offset	Description
Command Complete	1	0	If set, the platform has completed processing the last command.
SCI Doorbell	1	1	If set, then this PCC Sub-Channel has signaled the SCI door bell. In Response to this SCI, OSPM should probe the Command Complete and the Platform Notification fields to determine the cause of SCI.
Error	1	2	If set, an error occurred executing the last command.
Platform Notification	1	3	Indicates that the SCI doorbell was invoked by the platform.
Reserved	12	4	Reserved.

5.2.21.3 Action Sequence

SetMemoryPowerState: The following sequence needs to be done to set a memory power state

- 1. Write target POWER NODE ID value to MEMORY_POWER_NODE_ID register of PCC sub channel.
- 2. Write desired POWER STATE ID value to POWER STATE ID register of PCC sub channel.
- 3. Write SET (See <u>Table 5-89</u>) to MEMORY POWER STATE register of PCC sub channel.
- 4. Write PCC EXECUTE (See <u>Table 5-88</u>) to PCC Command register for the PCC sub channel.
- 5. OSPM rings the door bell by writing to Doorbell register.
- 6. Platform completes the request and will generate SCI to indicate that the command is complete.
- 7. OSPM reads the Status register for the PCC sub channel and confirms that the command was successfully completed.

GetMemoryPowerState: The following sequence needs to be done to get the current memory power state

- 1. Write target POWER NODE ID value to MEMORY_POWER_NODE_ID register of PCC sub channel.
- 2. Write GET (See <u>Table 5-89</u>) to MEMORY POWER STATE register of PCC sub channel.
- 3. Write PCC EXECUTE (See Table 5-88) to PCC Command register for the PCC sub channel.
- 4. OSPM rings the door bell by writing to Doorbell register.
- 5. Platform completes the request and will generate SCI to indicate that command is complete.
- 6. OSPM reads Status register for the PCC sub channel and confirms that the command was successfully completed.
- 7. OSPM reads POWER STATE from POWER STATE ID register of PCC sub channel.

5.2.21.4 Memory Power Node

Memory Power Node is a representation of a logical memory region that needs to be transitioned in and out of a memory power state as a unit. This logical memory region is made up of one more system memory address range(s). A Memory Power Node is uniquely identified by Memory Power Node ID.

Note that memory power node structure defined in <u>Table 5-92</u> can only represent a single address range. This address range should be 4K aligned. If a Memory Power Node contains more than one memory address range (i.e. non-contiguous range), firmware must construct a Memory power Node structure for each of the memory address ranges but specify the same Memory Power Node ID in all the structures.

Memory Power Nodes are not hierarchical. However, a given memory address range covered by a Memory power node could be fully covered by another memory power node if that nodes memory address range is inclusive of the other node's range. For example, memory power node MPN0 may cover memory address range 1G-2G and memory power node MPN1 covers 1-4G. Here MPN1 memory address range also comprehends the range covered by MPN0.

OSPM is expected to identify the memory power node(s) that corresponds to the maximum memory address range that OSPM is able to power manage at a given time. For example, if MPN0 covers 1G-2G and MPN1 covers 1-4G and OSPM is able to power manage 1-4G, it should select MPN1. If MPN0 is in a non-active memory power state, OSPM must move MPN0 to MPS0 (Active state) before placing MPN1 in desired Memory Power State. Further, MPN1 can support more power states than MPN0. If MPN1 is in such a state, say MPS3, that MPN0 does not support, software must not query MPN0. If queried, MPN0 will return "not Valid" until MPN1 returns to MPS0.

Note: [Implementation Note] In general, memory nodes corresponding to larger address space ranges correspond to higher memory aggregation (e.g. memory covered by a DIMM vs. memory covered by a memory channel) and hence typically present higher power saving opportunities.

5.2.21.4.1 Memory Power Node Structure

The following structure specifies the fields used for communicating memory power node information. Each entry in the MPST table will be having corresponding memory power node structure defined.

This structure communicates address range, number of power states implemented, information about individual power states, number of distinct physical components that comprise this memory power node.

The physical component identifiers can be cross-referenced against the memory topology table entries.

Table 5-92	Memory	Power	Node	Structure (definition
I abic 5-32			11000	Oli dolai o i	acillilici

Field	Byte Length	Byte Offset	Description
Flag	1	0	The flag describes type of memory node. Refer to <u>Table 5-93</u> for details.
Reserved	1	1	For future use

Memory Power Node Id	2	2	This field provides memory power node number. This is a unique identification for Memory Power State Command and creation of freelists/cache lists in OSPM memory manager to bias allocation of non power managed nodes vs. power managed nodes.
Length	4	4	Length in bytes for Memory Power Node Structure. The length implies the number of Entry fields at the end of the table
Base Address Low	4	8	Low 32 bits of Base Address of the memory range.
Base Address High	4	12	High 32 bits of Base Address of the memory range.
Length Low	4	16	Low 32 bits of Length of the memory range. This field along with "Length High" field is used to derive end physical address of this address range.
Length High	4	20	High 32 bits of Length of the memory range.
Number of Power States (n)	4	24	This field indicates number of power states supported for this memory power node and in turn determines the number of entries in memory power state structure.
Number of Physical Components	4	28	This field indicates the number of distinct Physical Components that constitute this memory power node. This field is also used to identify the number of entries of Physical Component Identifier entries present at end of this table.
Memory Power State Structure [n]		32	This field provides information of various power states supported in the system for a given memory power node
Physical Component Identifier1	2		2 byte identifier of distinct physical component that makes up this memory power node
Physical Component Identifier m	2		2 byte identifier of distinct physical component that makes up this memory power node

Table 5-93 Flag format

Bit	Name	Description
0	Enabled	If clear, the OSPM ignores this Memory Power Node Structure. This allows system firmware to populate the MPST with a static number of structures but enable them as necessary.
1	Power Managed Flag	1 – Memory node is power managed 0 – Memory node is not power managed. For non power managed node, OSPM shall not attempt to transition node into low power state. System behavior is undefined if OSPM attempts this. NOTE: If the memory range corresponding to the memory node include BIOS reserved memory that cannot be power managed, platform should indicate such memory as "not power managed" to OSPM. This allows OSPM to ignore such ranges from its power optimization.

Bit	Name	Description
2	Hot Pluggable	This flag indicates memory node supports hot plug feature. Refer to Section 5.2.21.10 for interaction with memory hot plug.
3-7	Reserved	Reserved for future use

5.2.21.5 Memory Power State Structure

Table 5-94 Memory Power State Structure definition

Field	Byte Length	Byte Offset	Description
Power State Value	1	0	This field provides value of power state. The specific value to be used is system dependent. However convention needs to be maintained where higher numbers indicates deeper power states with higher power savings and higher latencies. For example, a power state value of 2 will have higher power savings and higher latencies than a power state value of 1.
Power State Information Index	1	1	This field provides unique index into the memory power state characteristics entries which will provide details about the power consumed, power state characteristics and transition latencies. The indexing mechanism is to avoid duplication (and hence reduce potential for mismatch errors) of memory power state characteristics entries across multiple memory nodes.

5.2.21.6 Memory Power State Characteristics structure

The table below describes the power consumed, exit latency and the characteristics of the memory power state. This table is referenced by a memory power node.

Table 5-95 Memory Power State Characteristics Structure

Field	Byte Length		Byte Offset
Power State Structure ID	1	0	Bit 0:5 = This field describes the format of table Structure
			Power State Structure ID Value = 1 Bit 6:7 = Structure Revision Current revision is 1
Flag	1	1	The flag describes the caveats associated with entering the specified power state. Refer to Table 5-96 for details.
Reserved	2	2	Reserved

Field	Byte Length		Byte Offset
Average Power Consumed in MPS0 state (in milli watts)	4	4	This field provides average power consumed for this memory power node in MPS0 state. This power is measured in milliWatts and signifies the total power consumed by this memory the given power state as measured in DC watts. Note that this value should be used as guideline only for estimating power savings and not as actual power consumed. Also memory power node can map to single or collection of RANKs/DIMMs. The actual power consumed is dependent on DIMM type, configuration and memory load.
Relative Power Saving to MPS0 state	4	8	This is a percentage of power saved in MPSx state relative to MPS0 state and should be calculated as ((MPS0 power – MPSx power)/MPS0 Power)*100. When this entry is describing MPS0 state itself, OSPM should ignore this field.
Exit Latency (in ns) (MPSx→ MPS0)	8	12	This field provides latency of exiting out of a power state (MPSx) to active state (MPS0). The unit of this field is nanoseconds. When this entry is describing MPS0 state itself, OSPM should ignore this field.
Reserved	8	20	Reserved for future use.

Table 5-96 Flag format of Memory Power State Characteristics Structure

Bit	Name	Description
0	Memory Content Preserved	If Bit 0 is set, it indicates memory contents will be preserved in the specified power state If Bit 0 is clear, it indicates memory contents will be lost in the specified power state (e.g. for states like offline)
1	Autonomous Memory Power State Entry	If Bit 1 is set, this field indicates that given memory power state entry transition needs to be triggered explicitly by OSPM by calling the Set Power State command. If Bit 1 is clear, this field indicates that given memory power state entry transition is automatically implemented in hardware and does not require a OSPM trigger. The role of OSPM in this case is to ensure that the corresponding memory region is idled from a software standpoint to facilitate entry to the state. Not meaningful for MPS0 – write it for this table
2	Autonomous Memory Power State Exit	If Bit 1 is set, this field indicates that given memory power state exit needs to be explicitly triggered by the OSPM before the memory can be accessed. System behavior is undefined if OSPM or other software agents attempt to access memory that is currently in a low power state. If Bit 1 is clear, this field indicates that given memory power state is exited automatically on access to the memory address range corresponding to the memory power node.
3-7	Reserved	Reserved for future use

5.2.21.6.1 Power Consumed

Average Power Consumed in MPS0 state indicates the power in milli Watts for the MPS0 state. Relative power savings to MPS0 indicates the savings in the MPSx state as a percentage of savings relative to MPS0 state.

5.2.21.6.2 Exit Latency

Exit Latency provided in the Memory Power Characteristics structure for a specific power state is inclusive of the entry latency for that state.

Exit latency must always be provided for a memory power state regardless of whether the memory power state entry and/or exit are autonomous or requires explicit trigger from OSPM.

5.2.21.7 Autonomous Memory Power Management

Not all memory power management states require OSPM to actively transition a memory power node in and out of the memory power state. Platforms may implement memory power states that are fully handled in hardware in terms of entry and exit transition. In such fully autonomous states, the decision to enter the state is made by hardware based on the utilization of the corresponding memory region and the decision to exit the memory power state is initiated in response to a memory access targeted to the corresponding memory region.

The role of OSPM software in handling such autonomous memory power states is to vacate the use of such memory regions when possible in order to allow hardware to effectively save power. No other OSPM initiated action is required for supporting these autonomously power managed regions. However, it is not an error for OSPM explicitly initiates a state transition to an autonomous entry memory power state through the MPST command interface. The platform may accept the command and enter the state immediately in which case it must return command completion with SUCCESS (00000b) status. If platform does not support explicit entry, it must return command completion with NOT SUPPORTED (00010b) status.

5.2.21.8 Handling BIOS Reserved Memory

Platform BIOS may have regions of memory reserved for its own us that are unavailable to OSPM for allocation. Memory nodes where all or portion of the memory is reserved by BIOS pose a problem for OSPM because it does not know whether the BIOS reserved memory is in use or not.

If the BIOS reserved memory impacts the ability of the memory power node to enter memory power state(s), the platform must indicate to OSPM (by clearing the Power Managed Flag – see <u>Table 5-93</u> for details) that this memory power node cannot be power managed. This allows OSPM to ignore such ranges from its memory power optimization.

5.2.21.9 Interaction with NUMA processor and memory affinity tables

The memory power state table describes address range for each of the memory power nodes specified. OSPM can use the address ranges information provided in MPST table and derive processor affinity of a given memory power node based on the SRAT entries created by the BIOS. The association of memory power node to proximity domain can be used by OSPM to implement memory coalescing taking into account NUMA node topology for memory allocation/release and manipulation of different page lists in memory management code (implementation specific).

An example of policy which can be implemented in OSPM for memory coalescing is: OSPM can prefer allocating memory from local memory power nodes before going to remote memory power nodes. The later sections provide sample NUMA configurations and explain the policy for various memory power nodes.

5.2.21.10 Interaction with Memory Hot Plug

The hot pluggable memory regions are described using memory device objects in ACPI namespace. The memory address range of these memory device objects is defined using _CRS method. E.g. Refer to description of memory device object (MEM0) taken from Section 9.13.2 of ACPI specifications 3.0b.

```
Scope (\_SB) {
     Device (MEM0) {
            Name (_HID, EISAID ("PNPOC80"))
            Name (_CRS, ResourceTemplate () {
                  QwordMemory (
                        ResourceConsumer,
                        MinFixed.
                        MaxFixed,
                        Cacheable,
                        ReadWrite,
                        0xFFFFFFF,
                        0x10000000.
                        0x30000000,
                        0,,,
                  )
           })
```

The memory power state table (MPST) is a static structure created for all memory objects independent of hot plug status (online or offline) during initialization. The OSPM will populate the MPST table during the boot. If hot-pluggable flag is set for a given memory power node in MPST table, OSPM will not use this node till physical presence of memory is communicated through ACPI notification mechanism.

The association between memory device object (e.g. MEM0) to the appropriate memory power node id in the MPST table is determined by comparing the address range specified using _CRS method and address ranges configured in the MPST table entries. This association needs to be identified by OSPM as part of ACPI memory hot plug implementation. When memory device is hot added, as part of existing acpi driver for memory hot plug, OSPM will scan device object for _CRS method and get the relevant address ranges for the given memory object, OSPM will determine the appropriate memory power node ids based on the address ranges from _CRS and enable it for power management and memory coalescing.

Similarly when memory is hot removed, the corresponding memory power nodes will be disabled.

5.2.21.11 OS Memory Allocation Considerations

OSes (non-virtualized OS or a hypervisor/VMM) may need to allocate non-migratable memory. It is recommended that the OSes (if possible) allocate this memory from memory ranges corresponding to memory power nodes that indicate they are not power manageable. This allows OS to optimize the power manageable memory power nodes for optimal power savings.

OSes can assume that memory ranges that belong to memory power nodes that are power manageable (as indicated by the flag) are interleaved in a manner that does no impact the ability of that range to enter power managed states. For example, such memory is not cacheline interleaved.

Reference to memory in this document always refers to host physical memory. For virtualized environments, this requires hypervisors to be responsible for memory power management. Hypervisors also have the ability to create opportunities for memory power management by vacating appropriate host physical memory through remapping guest physical memory.

OSes can assume that the memory ranges included in MPST always refer to memory store – either volatile or non-volatile and never to MMIO or MMCFG ranges.

5.2.21.12 Memory Topology Table (PMTT)

This table describes the memory topology of the system to OSPM, where the memory topology can be logical or physical. The topology is provided to the last level physical component (e.g. DIMM).

Table 5-97 Platform Memory Topology Table

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'PMTT'. Signature for Platform Memory Topology Table.
Length	4	4	Length in bytes of the entire PMTT. The length implies the number of Memory Aggregator structures at the end of the table.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	For the PMTT, the table ID is the manufacturer model ID
OEM Revision	4	24	OEM revision of the PMTT for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table.
Creator Revision	4	32	Revision of utility that created the table.
Reserved	4	36	Reserved, must be zero.
Memory Aggregator Device Structure [n]		40	A list of memory aggregator device structures for the platform. See <u>Table 5-98</u> .

Table 5-98 Common Memory Aggregator Device Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	The field describes type of the Memory Aggregator Device. 0 – Socket 1 – Memory Controller 2 – DIMM 3 – 0xFF - Reserved
Reserved	1	1	Reserved, must be zero.
Length	2	2	Length in bytes for this Structure. This length implies the length of the Type Specific Data at the end of the structure.

Flags	2	4	Bit 0 – set to 1 to indicate that this is a top level aggregator device. This device must be counted in the number of top level aggregator devices in PMTT table and must be surfaces via PMTT. Bit 0 – Set to 0 to indicate that this is not a top level aggregator device. Bit 1 - set to 1 to indicate physical element of the topology. Set to 0 to indicate logical element of topology Bit 2 and 3 – If 00, indicates that all components aggregated by this device implements volatile memory If 01, indicates that components aggregated by this device implements both volatile and non-volatile memory If 10, indicates that all components aggregated by this device implements non-volatile memory 11 - Reserved Bit 4 – Bit 15 Reserved, must be zero
Reserved	2	6	Reserved, must be zero.
Type Specific Data		8	Type specific data. Interpretation of this data is specific to the type of the memory aggregator device. See <u>Table 5-99</u> , <u>Table 5-100</u> , and <u>Table 5-101</u> .

Table 5-99 Socket Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	0 - Socket
Reserved	1	1	Reserved, must be zero.
Length	2	2	Length in bytes for this Structure. The length implies the number of memory controller structures at the end of this structure.
Flags	2	4	 Bit 0 – set to 1 to indicate that this is a top level aggregator device. Bit 1 – set to 1 since socket is a physical element of the topology Bit 2 and 3 – If 00, indicates that all components aggregated by this device implements volatile memory If 01, indicates that components aggregated by this device implements both volatile and non-volatile memory If 10, indicates that all components aggregated by this device implements non-volatile memory 11 - Reserved Bit 4 – Bit 15 Reserved, must be zero
Reserved	2	6	Reserved, must be zero.
Socket Identifier	2	8	Uniquely identifies the socket in the system.
Reserved	2	10	Reserved, must be zero.
Memory Controller Structure [n]		12	A list of Memory Controller Structures. This list provides information on the memory controllers present in the socket. See <u>Table 5-100</u> .

Table 5-100 Memory Controller Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	1 – Memory Controller
Reserved	1	1	Reserved, must be zero.
Length	2	2	Length in bytes for this Structure. The length implies the number of physical component identifier structures at the end of this structure.
Flag	2	4	Bit 0 – set to 1 to indicate that this is a top level aggregator device. Bit 1 – set to 1 to indicate physical element of the topology. Set to 0 to indicate logical element of topology Bit 2 and 3 – • If 00, indicates that all components aggregated by this device implements volatile memory • If 01, indicates that components aggregated by this device implements both volatile and non-volatile memory • If 10, indicates that all components aggregated by this device implements non-volatile memory • 11 - Reserved Bit 4 – Bit 15 Reserved
Reserved	2	6	Reserved, must be zero.
Read Latency (typical)	4	8	In nanoseconds as seen at the controller for a cacheline access.
Write latency (typical)	4	12	In nanoseconds as seen at the controller for a cacheline access.
Read Bandwidth (typical)	4	16	In MB/s
Write Bandwidth (typical)	4	20	In MB/s
Optimal access unit	2	24	In bytes
Optimal access alignment	2	26	In bytes
Reserved	2	28	Reserved , must be zero.
Number of Proximity Domains (m)	2	30	Number of Proximity Domains that immediately follow. A zero in this field indicates that proximity domain information is not provided by the platform and that no 4-byte domains follow
Proximity Domain [m]	4*m	32	Proximity domains for memory address space(s) spawned by this memory controller. Each proximity domain is a 4-byte entity as defined in the System Resource Allocation Table (SRAT).
Physical Component Identifier Structure [n]		-	A list of Physical Components structures for this memory controller. See <u>Table 5-101</u> .

Table 5-101 Physical Components Identifier Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	2- DIMM
Reserved	1	1	Reserved, must be zero.
Length	2	2	Length in bytes for this Structure.
Flag	2	4	Bit 0 – Set 0 to indicate that this is not a top level memory aggregator. DIMM is typically behind a memory controller or a socket device or both. Bit 1 – set to 1 to indicate physical element of the topology. Set to 0 to indicate logical element of topology Bit 2 and 3 – If 00, indicates that all components aggregated by this device implements volatile memory If 01, indicates that components aggregated by this device implements both volatile and non-volatile memory If 10, indicates that all components aggregated by this device implements non-volatile memory
			Bit 4 – Bit 15 Reserved
Reserved	2	6	Reserved, must be zero.
Physical Component Identifier	2	8	Uniquely identifies the physical memory component in the system.
Reserved	2	10	Reserved, must be zero.
Size of DIMM	4	12	Size in MB of the DIMM device.
SMBIOS Handle	4	16	Refers to Type 17 table handle of corresponding SMBIOS record. The platform indicates that this field is not valid by setting a value of 0xFFFFFFFF. If the platform provides a valid handle, the upper 2 bytes must be 0 (since SMBIOS handles are 2 bytes only). NOTE: The use of this handle is for management software to be able to cross-reference the physical DIMM described in SMBIOS against the topology described in this table. It is not expected that OSPM will utilize this field.

5.2.22 Boot Graphics Resource Table (BGRT)

The Boot Graphics Resource Table (BGRT) is an optional table that provides a mechanism to indicate that an image was drawn on the screen during boot, and some information about the image.

The table is written when the image is drawn on the screen. This should be done after it is expected that any firmware components that may write to the screen are done doing so and it is known that the image is the only thing on the screen. If the boot path is interrupted (e.g. by a key press), the valid bit within the status field should be changed to 0 to indicate to the OS that the current image is invalidated.

This table is only supported on UEFI systems.

Table 5-102 Boot Graphics Resource Table Fields

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	"BGRT" Signature for the table.
Length	4	4	Length, in bytes, of the entire table
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	The table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table.
Creator Revision	4	32	Revision of utility that created the table.
Version	2	36	2-bytes (16 bit) version ID. This value must be 1.
Status	1	38	1-byte status field indicating current status about the table. Bits[7:1] = Reserved (must be zero) Bit [0] = Displayed. A one indicates the boot image graphic is displayed.
Image Type	1	39	1-byte enumerated type field indicating format of the image. 0 = Bitmap 1 - 255 Reserved (for future use)
Image Address	8	40	8-byte (64 bit) physical address pointing to the firmware's inmemory copy of the image bitmap.
Image Offset X	4	48	A 4-byte (32-bit) unsigned long describing the display X-offset of the boot image. (X, Y) display offset of the top left corner of the boot image. The top left corner of the display is at offset (0, 0).
Image Offset Y	4	52	A 4-byte (32-bit) unsigned long describing the display Y-offset of the boot image. (X, Y) display offset of the top left corner of the boot image. The top left corner of the display is at offset (0, 0).

The BGRT is a dynamic ACPI table that enables boot firmware to provide OPSM with a pointer to the location in memory where the boot graphics image is stored.

5.2.22.1 Version

The version field identifies which revision of the BGRT table is implemented. The version field should be set to 1.

5.2.22.2 Status

Table 5-103 Status Description Field

Offset	Field Name
Bit 0	Displayed

The status field contains information about the current status of the table. The Valid bit is bit 0 of the lowest byte. It should be set to 1 while the image resource is displayed on the screen, and set to 0 while it is not displayed.

All other bits are reserved.

5.2.22.3 Image Type

Table 5-104 Image Type Description Field

Value	Definition
0	Image Type is Bitmap

The Image type field contains information about the format of the image being returned. If the value is 0, the Image Type is Bitmap. The format for a Bitmap is defined at the reference located in "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Types of Bitmaps".

All other values not defined in the table are reserved for future use.

5.2.22.4 Image Address

The Image Address contains the location in memory where an in-memory copy of the boot image can be found. The image should be stored in EfiBootServicesData, allowing the system to reclaim the memory when the image is no longer needed.

Implementations must present the image in a 24 bit bitmap with pixel format 0xRRGGBB, or a32-bit bitmap with the pixel format 0xrrRRGGBB, where 'rr' is reserved.

5.2.22.5 Image Offset

The Image Offset contains 2 consecutive 4 byte unsigned longs describing the (X, Y) display offset of the top left corner of the boot image. The top left corner of the display is at offset (0, 0).




Figure 5-29 Image Offset

5.2.23 Firmware Performance Data Table (FPDT)

This section describes the format of the Firmware Performance Data Table (FPDT), which provides sufficient information to describe the platform initialization performance records. This information represents the boot performance data relating to specific tasks within the firmware boot process. The FPDT includes only those mileposts that are part of every platform boot process:

- End of reset sequence (Timer value noted at beginning of BIOS initialization typically at reset vector)
- Handoff to OS Loader

This information represents the firmware boot performance data set that would be used to track performance of each UEFI phase, and would be useful for tracking impacts resulting from changes due to hardware/software configuration.

All timer values are express in 1 nanosecond increments. For example, if a record indicates an event occurred at a timer value of 25678, this means that 25.678 microseconds have elapsed from the last reset of the timer measurement. All timer values will be required to have an accuracy of +/- 10%.

Table 5-105 Firmware Performance Data Table (FPDT) Format

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'FPDT' Signature for the Firmware Performance Data Table.
Length	4	4	The length of the table, in bytes, of the entire FPDT.
Revision	1	8	The revision of the structure corresponding to the signature field for this table. For the Firmware Performance Data Table conforming to this revision of the specification, the revision is 1.
Checksum	1	9	The entire table, including the checksum field, must add to zero to be considered valid.
OEMID	6	10	An OEM-supplied string that identifies the OEM.
OEM Table ID	8	16	An OEM-supplied string that the OEM uses to identify this particular data table.
OEM Revision	4	24	An OEM-supplied revision number.
Creator ID	4	28	The Vendor ID of the utility that created this table.
Creator Revision	4	32	The revision of the utility that created this table.
Performance Records	_	36	The set of Performance Records.

5.2.23.1 Performance Record Format

A performance record is comprised of a sub-header including a record type and length, and a set of data, which may include a timer. The format of the record layout is specific to the record type. In this manner, records are only as large as needed to contain the specific type of data to be conveyed.

Table 5-106 Performance Record Structure

Field	Byte Length	Byte Offset	Description
Performance Record Type	2	0	This value depicts the format and contents of the performance record.
Record Length	1	2	This value depicts the length of the performance record, in bytes.
Revision	1	3	This value is updated if the format of the record type is extended. Any changes to a performance record layout must be backwards-compatible in that all previously defined fields must be maintained if still applicable, but newly defined fields allow the length of the performance record to be increased. Previously defined record fields must not be redefined, but are permitted to be deprecated.
Data	_	4	The content of this field is defined by the Performance Record Type definition.

5.2.23.2 Performance Record Types

The table below describes the various types of records contained within the FPDT, and their associated Performance Record Type. Note that unless otherwise specified, multiple performance records are permitted in the FPDT for a given type, because some events can occur multiple times during the boot process.

Table 5-107 Performance Record Types

Record Type Value	Туре	Description
0x0000	Firmware Basic Boot Performance Pointer Record	Record containing a pointer to the Basic Boot Performance Data Record.
0x0001	S3 Performance Table Pointer Record	Record containing a pointer to an S3 Performance Table.
0x0002 – 0x0FFF	Reserved	Reserved for ACPI specification usage.
0x1000 - 0x1FFF	Reserved	Reserved for Platform Vendor usage.
0x2000 - 0x2FFF	Reserved	Reserved for Hardware Vendor usage.
0x3000 - 0x3FFF	Reserved	Reserved for BIOS Vendor usage.
0x4000 – 0xFFFF	Reserved	Reserved for future use

5.2.23.3 Runtime Performance Record Types

The table below describes the various types of runtime records and their associated Runtime Performance Record types. These Records are not contained within the FPDT; they are referenced by their respective pointer records in the FPDT.

Table 5-108 Runtime Performance Record Types

Record Type Value	Туре	Description
0x0000	Basic S3 Resume Performance Record	Performance record describing minimal firmware performance metrics for S3 resume operations
0x0001	Basic S3 Suspend Performance Record	Performance record describing minimal firmware performance metrics for S3 suspend operations
0x0002	Firmware Basic Boot Performance Data Record	Performance record showing basic performance metrics for critical phases of the firmware boot process.
0x0003 – 0x0FFF	Reserved	Reserved for ACPI specification usage.
0x1000 – 0x1FFF	Reserved	Reserved for Platform Vendor usage.
0x2000 – 0x2FFF	Reserved	Reserved for Hardware Vendor usage.
0x3000 - 0x3FFF	Reserved	Reserved for BIOS Vendor usage.
0x4000 – 0xFFFF	Reserved	Reserved for future use

5.2.23.4 S3 Performance Table Pointer Record

The S3 Performance Table Pointer Record contains a pointer to the S3 Performance Table. The S3 Performance Table itself exists in a range of memory described as ACPI AddressRangeReserved in the system memory map. The record pointer is a required entry in the FPDT for any system supporting the S3 state, and the pointer must point to a valid static physical address. Only one of these records will be produced.

Table 5-109 S3 Performance Table Pointer Record

Field	Byte Length	Byte Offset	Description
Performance Record Type	2	0	1 - S3 Performance Table Record
Record Length	1	2	16 - This value depicts the length of the performance record, in bytes.
Revision	1	3	1 - Revision of this Performance Record
Reserved	4	4	Reserved
S3PT Pointer	8	8	64-bit processor-relative physical address of the S3 Performance Table

5.2.23.5 Firmware Basic Boot Performance Pointer Record

The Firmware Basic Boot Performance Pointer Record contains a pointer to the Firmware Basic Boot Performance Data Record. The Firmware Basic Boot Performance Data Record itself exists in

a range of memory described as ACPI AddressRangeReserved in the system memory map. The record pointer is a required entry in the FPDT for any system and the pointer must point to a valid static physical address. Only one of these records will be produced.

Table 5-110 S4 Performance Table Pointer Record

Field	Byte Length	Byte Offset	Description
Performance Record Type	2	0	0 – Firmware Basic Boot Performance Pointer Record
Record Length	1	2	16 - This value depicts the length of the performance record, in bytes.
Revision	1	3	1 - Revision of this Performance Record
Reserved	4	4	Reserved
FBPT Pointer	8	8	64-bit processor-relative physical address of the Firmware Basic Boot Performance Table

5.2.23.6 S3 Performance Table

The S3 Performance Table resides outside of the FPDT. It includes a header, defined in <u>Table 5-112</u>, and one or more Performance Records.

All event entries must be initialized to zero during the initial boot sequence, and overwritten during the BIOS S3 resume sequence. The S3 Performance Table must include the Basic S3 Resume Performance Record. Other entries are optional.

Table 5-111 S3 Performance Table Header

Field	Byte Length	Byte Offset	Description
Signature	4	0	'S3PT' is the signature to use.
Length	4	4	Length of the S3 Performance Table. This includes the header and allocated size of the subsequent records. This size would at minimum include the size of the header and the Basic S3 Resume Performance Record.

Table 5-112 Basic S3 Resume Performance Record

Field	Byte Length	Byte Offset	Description
Runtime Performance Record Type	2	0	0 - The Basic S3 Resume Performance Record Type. Zero to one of these records will be produced.
Record Length	1	2	24 - The value depicts the length of this performance record, in bytes.
Revision	1	3	1 - Revision of this Performance Record
Resume Count	4	4	A count of the number of S3 resume cycles since the last full boot sequence.

Field	Byte Length	Byte Offset	Description
FullResume	8	8	Timer recorded at the end of BIOS S3 resume, just prior to handoff to the OS waking vector. Only the most recent resume cycle's time is retained.
AverageResume	8	16	Average timer value of all resume cycles logged since the last full boot sequence, including the most recent resume. Note that the entire log of timer values does not need to be retained in order to calculate this average. AverageResume _{new} = (AverageResume _{old} * (ResumeCount -1) + FullResume) / ResumeCount

Table 5-113 Basic S3 Suspend Performance Record

Field	Byte Length	Byte Offset	Description
Runtime Performance Record Type	2	0	1 - The Basic S3 Suspend Performance Record Type. Zero to one of these records will be produced.
Record Length	1	2	20 - The value depicts the length of this performance record, in bytes.
Revision	1	3	1 - Revision of this Performance Record
SuspendStart	8	4	Timer value recorded at the OS write to SLP_TYP upon entry to S3. Only the most recent suspend cycle's timer value is retained.
SuspendEnd	8	12	Timer value recorded at the final firmware write to SLP_TYP (or other mechanism) used to trigger hardware entry to S3. Only the most recent suspend cycle's timer value is retained.

5.2.23.7 Firmware Basic Boot Performance Table

The Firmware Basic Boot Performance Table resides outside of the FPDT. It includes a header, defined in <u>Table 5-114</u>, and one or more Performance Records.

All event entries will be overwritten during the BIOS S4 resume sequence. The Firmware Basic Boot Performance Table must include the Firmware Basic Boot Performance Table.

Table 5-114 Firmware Basic Boot Performance Table Header

Field	Byte Length	Byte Offset	Description
Signature	4	0	'FBPT' is the signature to use.
Length	4	4	Length of the Firmware Basic Boot Performance Table. This includes the header and allocated size of the subsequent records. This size would at minimum include the size of the header and the Firmware Basic Boot Performance Record.

5.2.23.8 Firmware Basic Boot Performance Data Record

A firmware basic boot performance data record which contains timer information associated with final OS loader activity as well as the data associated with starting and ending boot time information. Only one of these records will be produced.

Table 5-115 Firmware Basic Boot Performance Data Record Structure

Field	Byte Length	Byte Offset	Description	
Performance Record Type	2	0	2 – Firmware Basic Boot Performance Data Record	
Record Length	1	2	48 - This value depicts the length of the performance record, in bytes.	
Revision	1	3	2 - Revision of this Performance Record	
Reserved	4	4	Reserved	
Reset End	8	8	Timer value logged at the beginning of firmware image execution. This may not always be zero or near zero.	
OS Loader LoadImage Start	8	16	Timer value logged just prior to loading the OS boot loader into memory. For non-UEFI compatible boots, this field must be zero.	
OS Loader StartImage Start	8	24	Timer value logged just prior to launching the currently loaded OS boot loader image. For non-UEFI compatible boots, the timer value logged will be just prior to the INT 19h handler invocation.	
ExitBootServices Entry	8	32	Timer value logged at the point when the OS loader calls the ExitBootServices function for UEFI compatible firmware. For non-UEFI compatible boots, this field must be zero.	
ExitBootServices Exit	8	40	Timer value logged at the point just prior to the OS loader gaining control back from the ExitBootServices function for UEFI compatible firmware. For non-UEFI compatible boots, this field must be zero.	

5.2.24 Generic Timer Description Table (GTDT)

This section describes the format of the Generic Timer Description Table (GTDT), which provides OSPM with information about a system's Generic Timers configuration. The Generic Timer (GT) is a standard timer interface implemented on ARM processor-based systems. The GT hardware specification can be found at *Links to ACPI-Related Documents* (http://uefi.org/acpi) under the heading *ARM Architecture*. The GTDT provides OSPM with information about a system's GT interrupt configurations, for both per-processor timers, and platform (memory-mapped) timers.

The GT specification defines the following per-processor timers:

- Secure privilege level 1 (EL1) timer,
- Non-Secure EL1 timer,
- Non-Secure privilege level 2 (EL2) timer,
- Virtual timer,

and the following Platform (memory-mapped) timers.

- GT Block
- Server Base System Architecture (SBSA) Generic Watchdog

Table 5-116 GTDT Table Structure

Field	Byte Length	Byte Offset	Description	
Header				
Signature	4	0	'GTDT'. Signature for the Generic Timer Description Table.	
Length	4	4	Length, in bytes, of the entire Generic Timer Description Table.	
Revision	1	8	2	
Checksum	1	9	Entire table must sum to zero.	
OEMID	6	10	OEM ID.	
OEM Table ID	8	16	For the Generic Timer Description Table, the table ID is the manufacturer model ID.	
OEM Revision	4	24	OEM revision of Generic Timer Description Table for supplied OEM Table ID.	
Creator ID	4	28	Vendor ID of utility that created the table.	
Creator Revision	4	32	Revision of utility that created the table.	
CntControlBase Physical Address	8	36	The 64-bit physical address at which the Counter Control block is located. This value is optional if the system implements EL3 (Security Extensions). If not provided, this field must be 0xFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFFF	
Reserved	4	44	Must be zero	
Secure EL1 timer GSIV	4	48	GSIV for the secure EL1 physical timer. This value is optional. If not provided, this field must be 0.	
Secure EL1 timer Flags	4	52	Flags for the secure EL1 physical timer (defined below). If th "Secure EL1 timer GSIV" field (above) is 0, this field must be	
Non-Secure EL1 timer GSIV	4	56	GSIV for the non-secure EL1 timer physical timer interrupt	
Non-Secure EL1 timer Flags	4	60	Flags for the non-secure EL1 physical timer (defined below)	
Virtual timer GSIV	4	64	GSIV for the non-secure virtual timer interrupt	
Virtual Timer Flags	4	68	Flags for the virtual timer (defined below)	
Non-Secure EL2 timer GSIV	4	72	GSIV for the Non-Secure EL2 physical timer	
Non-Secure EL2 timer Flags	4	76	Flags for the Non-Secure EL2 physical timer(defined below)	
CntReadBase Physical address	8	80	The 64-bit physical address at which the Counter Read block is located	
Platform Timer Count	4	88	Number of entries in the Platform Timer Structure[] array	
Platform Timer Offset	4	92	Offset to the Platform Timer Structure[] array from the start of this table	

Field	Byte Length	Byte Offset	Description
Platform Timer Structure[]		Platfor m Timer Offset	Array of Platform Timer Type structures describing memory- mapped Timers available on this platform. These structures are described in the below sections.

Secure EL1 timer Flags, Non-Secure EL1 timer flags, Virtual Timer Flags, and EL2 timer Flags all have the same definition.

Table 5-117 Flag Definitions: Virtual Timer, EL2 timers, and Secure & Non-Secure EL1 timers

Bit Field	bit Offset	Number of bits	Description
Timer interrupt Mode	0	1	This bit indicates the mode of the timer interrupt
			1: Interrupt is Edge triggered
			0: Interrupt is Level triggered
Timer Interrupt polarity	1	1	This bit indicates the polarity of the timer interrupt
			1: Interrupt is Active low
			0: Interrupt is Active high
Always-on Capability	2	1	This bit indicates the always-on capability of the timer implementation.
			1: This timer is guaranteed to assert its interrupt and wake a processor, regardless of the processor's power state. All of the methods by which an ARM Generic Timer may generate an interrupt must be supported, and must be capable of waking the processor.
			0: This timer may lose context or may not be guaranteed to assert interrupts when its associated processor enters a low-power state
Reserved	3	29	Reserved, must be zero.

The GTDT Platform Timer Structure [] field is an array of Platform Timer Type structures, each of which describes the configuration of an available platform timer. These timers are in addition to the per-processor timers described above them in the GTDT.

Table 5-118 Platform Timer Type Structures

Value	Description
0	GT Block
1	SBSA Generic Watchdog
0x02-0xFF	Reserved for future use

The first byte of each structure declares the type of that structure and the second and third bytes declare the length of that structure.

5.2.24.1.1 GT Block Structure

The GT Block is a standard timer block that is mapped into the system address space. Each GT Block implements up to 8 GTs (GT0 – GT7).

The format of the GT Block structure is shown in <u>Table 5-119</u>.

Table 5-119 GT Block Structure Format

Field	Byte Lengt h	Byte Offset	Description	
Туре	1	0	0x0 GT Block	
Length	2	1	20+n*40, where n is the number of timers implemented in the GT Block	
Reserved	1	3	Must be zero	
GT Block Physical address (CntCtlBase)	8	4	The 64-bit physical address at which the GT CntCTLBase Block is located	
GT Block Timer Count	4	12	Number of Timers implemented in this GT Block ('n'). Must be less than or equal to 8.	
GT Block Timer Offset	4	16	Offset to the Platform Timer Structure array from the start of this structure	
GT Block Timer Structure[]	n*40	GT Block Timer Offset	Array of GT Block Timer Structures. See <u>Table 5-120</u> .	

Table 5-120 GT Block Timer Structure Format

Field	Byte Length	Byte Offset	Description	
GT Frame Number	1	0	The frame number (0-7) for this timer ('x')	
Reserved	3	1	Must be zero	
GTx Physical Address (CntBaseX)	8	4 Physical Address at which the CntBase block for GTx is locate		
GTx Physical Address (CntEL0BaseX)	8	12	Physical Address at which the CntEL0Base block for GTx is located. If this block is not implemented for GTx, must be 0xFFFFFFFFFFFFFF.	
GTx Physical Timer GSIV	4	20	GSIV for the GTx physical timer	
GTx Physical Timer Flags	4	24	Flags for the GTx physical timer. See <u>Table 5-121</u>	
GTx Virtual Timer GSIV	4	28	GSIV for the GTx virtual timer If the Virtual Timer is not implemented for GTx, this field must be 0.	

GTx Virtual Timer	4	32	Flags for the GTx virtual timer, if implemented. See <u>Table 5-121</u> .
Flags			
GTx Common Flags	4	36	See <u>Table 5-122</u> .

Table 5-121 Flag Definitions: GT Block Physical Timers and Virtual timers

Bit Field	bit	Number	Description	
	Offset	of bits		
Timer interrupt	0	1	This bit indicates the mode of the timer interrupt	
Mode				
			1: Interrupt is Edge triggered	
			0: Interrupt is Level triggered	
Timer Interrupt	1	1	This bit indicates the polarity of the timer interrupt	
polarity				
			1: Interrupt is Active low	
			0: Interrupt is Active high	
Reserved	2	30	Reserved, must be zero.	

Table 5-122 Flag Definitions: Common Flags

Bit Field	bit	Number	Description
	Offset	of bits	
Secure Timer	0	1	This bit indicates whether the timer is secure or non-secure
			1: Timer is Secure
			0: Timer is Non-secure
Always-on Capability	1	1	This bit indicates the always-on capability of the Physical and Virtual Timers implementation. 1: This timer is guaranteed to assert its interrupt and wake a processor, regardless of the processor's power state. All of the methods by which an ARM Generic Timer may generate an interrupt must be supported, and must be capable of waking the processor. 0: This timer may lose context or may not be guaranteed to assert interrupts when its associated processor enters a low-power state.
Reserved	2	30	Reserved, must be zero.

5.2.24.0.1 SBSA Generic Watchdog Structure

The SBSA Generic Watchdog is a Platform GT with built-in support for use as the Watchdog timer on Server Base System Architecture (SBSA)-compliant platforms.

The format of the SBSA Generic Watchdog structure is shown in <u>Table 5-123</u>.

The link for SBSA is http://infocenter.arm.com/help/index.jsp?topic=/com.arm.doc.den0029/index.html.

Table 5-123 SBSA Generic Watchdog Structure Format

Field	Byte Length	Byte Offset	Description
Туре	1	0	0x1 Watchdog GT
Length	2	1	28
Reserved	1	3	Must be zero
RefreshFrame Physical Address	8	4	Physical Address at which the RefreshFrame block is located
WatchdogControlFrame Physical Address	8	12	Physical Address at which the Watchdog Control Frame block is located
Watchdog Timer GSIV	4	20	GSIV for the SBSA Generic Watchdog timer
Watchdog Timer Flags	4	24	Flags for the SBSA Generic Watchdog timer. See Table 5-124

Table 5-124 Flag Definitions: SBSA Generic Watchdog Timer

Bit Field	bit	Number	Description
	Offset	of bits	
Timer interrupt	0	1	This bit indicates the mode of the timer interrupt
Mode			
			1: Interrupt is Edge triggered
			0: Interrupt is Level triggered
Timer Interrupt polarity	1	1	This bit indicates the polarity of the timer interrupt
			1: Interrupt is Active low
			0: Interrupt is Active high
Secure Timer	2	1	This bit indicates whether the timer is secure or non-secure
			1: Timer is Secure
			0: Timer is Non-secure
Reserved	3	29	Reserved, must be zero.

5.3 ACPI Namespace

For all Definition Blocks, the system maintains a single hierarchical namespace that it uses to refer to objects. All Definition Blocks load into the same namespace. Although this allows one Definition Block to reference objects and data from another (thus enabling interaction), it also means that OEMs must take care to avoid any naming collisions¹. Only an unload operation of a Definition Block can remove names from the namespace, so a name collision in an attempt to load a Definition Block is considered fatal. The contents of the namespace changes only on a load or unload operation.

The namespace is hierarchical in nature, with each name allowing a collection of names "below" it. The following naming conventions apply to all names:

- All names are a fixed 32 bits.
- The first byte of a name is inclusive of: 'A'-'Z', ', (0x41–0x5A, 0x5F).
- The remaining three bytes of a name are inclusive of: 'A'-'Z', '0'-'9', '_', (0x41-0x5A, 0x30-0x39, 0x5F).
- By convention, when an ASL compiler pads a name shorter than 4 characters, it is done so with trailing underscores ('_'). See the language definition for AML NameSeg in <u>Section 17</u>, "ACPI Source Language Reference."
- Names beginning with '_' are reserved by this specification. Definition Blocks can only use names beginning with '_' as defined by this specification.
- A name proceeded with '\' causes the name to refer to the root of the namespace ('\' is not part of the 32-bit fixed-length name).
- A name proceeded with '^' causes the name to refer to the parent of the current namespace ('^' is not part of the 32-bit fixed-length name).

Except for names preceded with a '\', the current namespace determines where in the namespace hierarchy a name being created goes and where a name being referenced is found. A name is located by finding the matching name in the current namespace, and then in the parent namespace. If the parent namespace does not contain the name, the search continues recursively upwards until either the name is found or the namespace does not have a parent (the root of the namespace). This indicates that the name is not found¹.

An attempt to access names in the parent of the root will result in the name not being found.

There are two types of namespace paths: an absolute namespace path (that is, one that starts with a '\' prefix), and a relative namespace path (that is, one that is relative to the current namespace). The namespace search rules discussed above, only apply to single NameSeg paths, which is a relative namespace path. For those relative name paths that contain multiple NameSegs or Parent Prefixes, '^', the search rules do not apply. If the search rules do not apply to a relative namespace path, the namespace object is looked up relative to the current namespace. For example:

ABCD //search rules apply

^ABCD //search rules do not apply

XYZ.ABCD //search rules do not apply

\XYZ.ABCD //search rules do not apply

198

^{1.} For the most part, since the name space is hierarchical, typically the bulk of a dynamic definition file will load into a different part of the hierarchy. The root of the name space and certain locations where interaction is being designed are the areas in which extra care must be taken.

^{1.} Unless the operation being performed is explicitly prepared for failure in name resolution, this is considered an error and may cause the system to stop working.

All name references use a 32-bit fixed-length name or use a Name Extension prefix to concatenate multiple 32-bit fixed-length name components together. This is useful for referring to the name of an object, such as a control method, that is not in the scope of the current namespace.

The figure below shows a sample of the ACPI namespace after a Differentiated Definition Block has been loaded.




Figure 5-30 Example ACPI NameSpace

Care must be taken when accessing namespace objects using a relative single segment name because of the namespace search rules. An attempt to access a relative object recurses toward the root until the object is found or the root is encountered. This can cause unintentional results. For example, using the namespace described in Figure 5.5, attempting to access a _CRS named object from within the _SB_.PCI0.IDE0 will have different results depending on if an absolute or relative path name is used. If an absolute pathname is specified (_SB_.PCI0.IDE0._CRS) an error will result since the object does not exist. Access using a single segment name (_CRS) will actually access the _SB_.PCI0._CRS object. Notice that the access will occur successfully with no errors.

5.3.1 Predefined Root Namespaces

The following namespaces are defined under the namespace root.

Table 5-125 Namespaces Defined Under the Namespace Root

Name	Description			
_GPE	General events in GPE register block.			
_PR	ACPI 1.0 Processor Namespace. ACPI 1.0 requires all Processor objects to be defined under this namespace. ACPI allows Processor object definitions under the _SB namespace. Platforms may maintain the _PR namespace for compatibility with ACPI 1.0 operating systems. An ACPI-compatible namespace may define Processor objects in either the _SB or _PR scope but not both. For more information about defining Processor objects, see Section 8 , "Processor Configuration and Control."			
_SB	All Device/Bus Objects are defined under this namespace.			
_SI	System indicator objects are defined under this namespace. For more information about defining system indicators, see Section 9.1 , _SI System Indicators."			
_TZ	ACPI 1.0 Thermal Zone namespace. ACPI 1.0 requires all Thermal Zone objects to be defined under this namespace. Thermal Zone object definitions may now be defined under the \SB namespace. ACPI-compatible systems may maintain the \TZ namespace for compatibility with ACPI 1.0 operating systems. An ACPI-compatible namespace may define Thermal Zone objects in either the \SB or \TZ scope but not both. For more information about defining Thermal Zone objects, see Section 11, "Thermal Management."			

5.3.2 Objects

All objects, except locals, have a global scope. Local data objects have a per-invocation scope and lifetime and are used to process the current invocation from beginning to end.

The contents of objects vary greatly. Nevertheless, most objects refer to data variables of any supported data type, a control method, or system software-provided functions.

Objects may contain a revision field. Successive ACPI specifications define object revisions so that they are backwards compatible with OSPM implementations that support previous specifications / object revisions. New object fields are added at the end of previous object definitions. OSPM interprets objects according to the revision number it supports including all earlier revisions. As such, OSPM expects that an object's length can be greater than or equal to the length of the known object revision. When evaluating objects with revision numbers greater than that known by OSPM, OSPM ignores internal object fields values that are beyond the defined object field range for the known revision.

5.4 Definition Block Encoding

This section specifies the encoding used in a Definition Block to define names (load time only), objects, and packages. The Definition Block is encoded as a stream from beginning to end. The lead byte in the stream comes from the AML encoding tables shown in Section 19, "ACPI Source Language (ASL) Reference," and signifies how to interpret some number of following bytes, where each following byte can in turn signify how to interpret some number of following bytes. For a full specification of the AML encoding, see Section 19, "ACPI Source Language (ASL) Reference."

Within the stream there are two levels of data being defined. One is the packaging and object declarations (load time), and the other is an object reference (package contents/run-time).

All encodings are such that the lead byte of an encoding signifies the type of declaration or reference being made. The type either has an implicit or explicit length in the stream. All explicit length declarations take the form shown below, where *PkgLength* is the length of the inclusive length of the data for the operation.




Figure 5-31 AML Encoding

Encodings of implicit length objects either have fixed length encodings or allow for nested encodings that, at some point, either result in an explicit or implicit fixed length.

The *PkgLength* is encoded as a series of 1 to 4 bytes in the stream with the most significant two bits of byte zero, indicating how many following bytes are in the *PkgLength* encoding. The next two bits are only used in one-byte encodings, which allows for one-byte encodings on a length up to 0x3F. Longer encodings, which do not use these two bits, have a maximum length of the following: two-byte encodings of 0x0FFF, three-byte encodings of 0x0FFFFF, and four-byte length encodings of 0x0FFFFFFFF.

It is fatal for a package length to not fall on a logical boundary. For example, if a package is contained in another package, then by definition its length must be contained within the outer package, and similarly for a datum of implicit length.

At some point, the system software decides to "load" a Definition Block. Loading is accomplished when the system makes a pass over the data and populates the ACPI namespace and initializes objects accordingly. The namespace for which population occurs is either from the *current namespace location*, as defined by all nested packages or from the root if the name is preceded with '\'.

The first object present in a Definition Block must be a named control method. This is the Definition Block's initialization control.

Packages are objects that contain an ordered reference to one or more objects. A package can also be considered a vertex of an array, and any object contained within a package can be another package. This permits multidimensional arrays of fixed or dynamic depths and vertices.

Unnamed objects are used to populate the contents of named objects. Unnamed objects cannot be created in the "root." Unnamed objects can be used as arguments in control methods.

Control method execution may generate errors when creating objects. This can occur if a Method that creates named objects blocks and is reentered while blocked. This will happen because all named objects have an absolute path. This is true even if the object name specified is relative. For example, the following ASL code segments are functionally identical.

```
(1)
Method (DEAD,) {
    Scope (\_SB_.FOO) {
        Name (BAR,) // Run time definition
    }
}
(2)
Scope (\_SB_) {
        Name (\_SB_. FOO.BAR,) // Load time definition
}
```

Notice that in the above example the execution of the DEAD method will always fail because the object _SB_.FOO.BAR is created at load time.

5.5 Using the ACPI Control Method Source Language

OEMs and BIOS vendors write definition blocks using the ACPI Control Method Source language (ASL) and use a translator to produce the byte stream encoding described in <u>Section 5.4</u>, "Definition Block Encoding". For example, the ASL statements that produce the example byte stream shown in that earlier section are shown in the following ASL example. For a full specification of the ASL statements, see <u>Section 19</u>, "ACPI Source Language (ASL) Reference."

```
// ASL Example
DefinitionBlock (
   "forbook.aml",
"DSDT",
                     // Output Filename
                       // Signature
// DSDT Compliance Revision
   0x02,
                    // OEMID
// TABLE ID
// OEM Revision
   "OEM",
   "forbook",
   0x1000
                         // start of definition block
   OperationRegion(\GIO, SystemIO, 0x125, 0x1)
   Field(\GIO, ByteAcc, NoLock, Preserve) {
      CT01, 1,
                                      // start of scope
   Scope(\_SB)
          Device(PCI0) {
              Method (_ON) {
                  Store (Ones, CT01) // assert power
                  Sleep (30)
                                     // wait 30ms
               Method (_OFF) {
                  Store (Zero, CT01) // assert reset#
               Method (_STA) {
                  Return (CT01)
                                     // end of power
           }
        } // end of device
   } // end of scope
} // end of definition block
```

5.5.1 ASL Statements

ASL is principally a declarative language. ASL statements declare objects. Each object has three parts, two of which can be null:

```
Object := ObjectType FixedList VariableList
```

FixedList refers to a list of known length that supplies data that all instances of a given ObjectType must have. It is written as (a, b, c,), where the number of arguments depends on the specific ObjectType, and some elements can be nested objects, that is (a, b, (q, r, s, t), d). Arguments to a FixedList can have default values, in which case they can be skipped. Some ObjectTypes can have a null FixedList.

VariableList refers to a list, not of predetermined length, of child objects that help define the parent. It is written as {x, y, z, aa, bb, cc}, where any argument can be a nested object. ObjectType determines what terms are legal elements of the *VariableList*. Some ObjectTypes can have a null variable list.

For a detailed specification of the ASL language, see Section 19, "ACPI Source Language (ASL) Reference." For a detailed specification of the ACPI Control Method Machine Language (AML), upon which the output of the ASL translator is based, see Section 20, "ACPI Machine Language (AML) Specification."

5.5.2 Control Method Execution

OSPM evaluates control method objects as necessary to either interrogate or adjust the system-level hardware state. This is called an invocation.

A control method can use other internal, or well defined, control methods to accomplish the task at hand, which can include defined control methods provided by the operating software. Control Methods can reference any objects anywhere in the Namespace. Interpretation of a Control Method is not preemptive, but it can block. When a control method does block, OSPM can initiate or continue the execution of a different control method. A control method can only assume that access to global objects is exclusive for any period the control method does not block.

Global objects are those NameSpace objects created at table load time.

5.5.2.1 Arguments

Up to seven arguments can be passed to a control method. Each argument is an object that in turn could be a "package" style object that refers to other objects. Access to the argument objects is provided via the ASL **ArgTerm** (*ArgX*) language elements. The number of arguments passed to any control method is fixed and is defined when the control method package is created.

Method arguments can take one of the following forms:

- An ACPI name or namepath that refers to a named object. This includes the LocalX and ArgX names. In this case, the object associated with the name is passed as the argument.
- An ACPI name or namepath that refers to another control method. In this case, the method is invoked and the return value of the method is passed as the argument. A fatal error occurs if no object is returned from the method. If the object is not used after the method invocation it is automatically deleted.
- A valid ASL expression. In the case, the expression is evaluated and the object that results from this evaluation is passed as the argument. If this object is not used after the method invocation it is automatically deleted.

5.5.2.2 Method Calling Convention

The calling convention for control methods can best be described as *call-by-reference-constant*. In this convention, objects passed as arguments are passed by "reference", meaning that they are not copied to new objects as they are passed to the called control method (A calling convention that copies objects or object *wrappers* during a call is known as *call-by-value* or *call-by-copy*).

This *call-by-reference-constant* convention allows internal objects to be shared across each method invocation, therefore reducing the number of object copies that must be performed as well as the number of buffers that must be copied. This calling convention is appropriate to the low-level nature of the ACPI subsystem within the kernel of the host operating system where non-paged dynamic memory is typically at a premium. The ASL programmer must be aware of the calling convention and the related side effects.

However, unlike a pure *call-by-reference* convention, the ability of the called control method to modify arguments is extremely limited. This reduces aliasing issues such as when a called method unexpectedly modifies a object or variable that has been passed as an argument by the caller. In effect, the arguments that are passed to control methods are passed as constants that cannot be modified except under specific controlled circumstances.

Generally, the objects passed to a control method via the ArgX terms cannot be directly written or modified by the called method. In other words, when an ArgX term is used as a target operand in an ASL statement, the existing ArgX object is not modified. Instead, the new object replaces the existing object and the ArgX term effectively becomes a LocalX term.

The only exception to the read-only argument rule is if an ArgX term contains an Object Reference created via the *RefOf* ASL operator. In this case, the use of the ArgX term as a target operand will cause any existing object stored at the ACPI name referred to by the *RefOf* operation to be overwritten.

In some limited cases, a new, writable object may be created that will allow a control method to change the value of an ArgX object. These cases are limited to Buffer and Package objects where the "value" of the object is represented indirectly. For Buffers, a writable Index or Field can be created that refers to the original buffer data and will allow the called method to read or modify the data. For Packages, a writable Index can be created to allow the called method to modify the contents of individual elements of the Package.

5.5.2.3 Local Variables and Locally Created Data Objects

Control methods can access up to eight local data objects. Access to the local data objects have shorthand encodings. On initial control method execution, the local data objects are NULL. Access to local objects is via the ASL LocalTerm language elements.

Upon control method execution completion, one object can be returned that can be used as the result of the execution of the method. The "caller" must either use the result or save it to a different object if it wants to preserve it. See the description of the Return ASL operator for additional details

NameSpace objects created within the scope of a method are dynamic. They exist only for the duration of the method execution. They are created when specified by the code and are destroyed on exit. A method may create dynamic objects outside of the current scope in the NameSpace using the scope operator or using full path names. These objects will still be destroyed on method exit. Objects created at load time outside of the scope of the method are static. For example:

The object \XYZ.BAR is a static object created when the table that contains the above ASL is loaded. The object \XYZ.FOO.BAR is a dynamic object that is created when the Name (BAR, 7) statement in the FOO method is executed. The object \XYZ.FOOB is a dynamic object created by the \XYZ.FOO method when the Name (\XYZ.FOOB, 3) statement is executed. Notice that the \XYZ.FOOB object is destroyed after the \XYZ.FOO method exits.

5.5.2.4 Access to Operation Regions

Control Methods read and write data to locations in address spaces (for example, System memory and System I/O) by using the Field operator (see <u>Section 19.5.46</u> Field (Declare Field Objects)") to declare a data element within an entity known as an "Operation Region" and then performing

accesses using the data element name. An Operation Region is a specific region of operation within an address space that is declared as a subset of the entire address space using a starting address (offset) and a length (see Section 19.5.96 "OperationRegion (Declare Operation Region)"). Control methods must have exclusive access to any address accessed via fields declared in Operation Regions. Control methods may not directly access any other hardware registers, including the ACPI-defined register blocks. Some of the ACPI registers, in the defined ACPI registers blocks, are maintained on behalf of control method execution. For example, the GPEx_BLK is not directly accessed by a control method but is used to provide an extensible interrupt handling model for control method invocation.

Note: Accessing an OpRegion may block, even if the OpRegion is not protected by a mutex. For example, because of the slow nature of the embedded controller, an embedded controller OpRegion field access may block.

There are eight predefined Operation Region types specified by ACPI as described in Table 5-126.

Table 5-126 Operation Region Address Space Identifiers

Name (RegionSpace Keyword)	Value
SystemMemory	0
SystemIO	1
PCI_Config	2
EmbeddedControl	3
SMBus	4
SystemCMOS	5
PCIBARTarget	6
IPMI	7
GeneralPurposeIO	8
GenericSerialBus	9
Reserved	0x0A-0x7F

In addition, OEMs may define Operation Regions Address Space ID types 0x80 to 0xFF.

Operation region access to the SystemMemory, SystemIO, and PCI_Config address spaces is simple and straightforward. Operation region access to the EmbeddedControl address space is described in Section 12, "ACPI Embedded Controller Interface Specification". Operation region access to the SMBus address space is described in Section 13, "ACPI System Management Bus Interface Specification". Operation region access to the CMOS, PCIBARTarget, IPMI, GenericSerialBus and GeneralPurposeIO address spaces is described in the following sections.

5.5.2.4.1 CMOS Protocols

This section describes how CMOS battery-backed non-volatile memory can be accessed from ASL. Most computers contain an RTC/CMOS device that can be represented as a linear array of bytes of non-volatile memory. There is a standard mechanism for accessing the first 64 bytes of non-volatile RAM in devices that are compatible with the Motorola RTC/CMOS device used in the original IBM PC/AT. Existing RTC/CMOS devices typically contain more than 64 bytes of non-volatile RAM, and no standard mechanism exists for access to this additional storage area. To provide access to all

of the non-volatile memory in these devices from AML, PnP IDs exist for each type of extension. These are PNP0B00, PNP0B01, and PNP0B02. The specific devices that these PnP IDs support are described in Section 9.15, "PC/AT RTC/CMOS Device", along with field definition ASL example code. The drivers corresponding to these device handle operation region accesses to the SystemCMOS operation region for their respective device types.

All bytes of CMOS that are related to the current time, day, date, month, year and century are readonly.

5.5.2.4.2 PCI Device BAR Target Protocols

This section describes how PCI devices' control registers can be accessed from ASL. PCI devices each have an address space associated with them called the Configuration Space. At offset 0x10 through offset 0x27, there are as many as six Base Address Registers, (BARs). These BARs contain the base address of a series of control registers (in I/O or Memory space) for the PCI device. Since a Plug and Play OS may change the values of these BARs at any time, ASL cannot read and write from these deterministically using I/O or Memory operation regions. Furthermore, a Plug and Play OS will automatically assign ownership of the I/O and Memory regions associated with these BARs to a device driver associated with the PCI device. An ACPI OS (which must also be a Plug and Play operating system) will not allow ASL to read and write regions that are owned by native device drivers.

If a platform uses a PCI BAR Target operation region, an ACPI OS will not load a native device driver for the associated PCI function. For example, if any of the BARs in a PCI function are associated with a PCI BAR Target operation region, then the OS will assume that the PCI function is to be entirely under the control of the ACPI BIOS. No driver will be loaded. Thus, a PCI function can be used as a platform controller for some task (hot-plug PCI, and so on) that the ACPI BIOS performs.

5.5.2.4.2.1 Declaring a PCI BAR Target Operation Region

PCI BARs contain the base address of an I/O or Memory region that a PCI device's control registers lie within. Each BAR implements a protocol for determining whether those control registers are within I/O or Memory space and how much address space the PCI device decodes. (See the PCI Specification for more details.)

PCI BAR Target operation regions are declared by providing the offset of the BAR within the PCI device's PCI configuration space. The BAR determines whether the actual access to the device occurs through an I/O or Memory cycle, not by the declaration of the operation region. The length of the region is similarly implied.

In the term <code>OperationRegion(PBAR, PciBarTarget, 0x10, 0x4)</code>, the offset is the offset of the BAR within the configuration space of the device. This would be an example of an operation region that uses the first BAR in the device.

5.5.2.4.2.2 PCI Header Types and PCI BAR Target Operation Regions

PCI BAR Target operation regions may only be declared in the scope of PCI devices that have a PCI Header Type of 0. PCI devices with other header types are bridges. The control of PCI bridges is beyond the scope of ASL.

5.5.2.4.3 Declaring IPMI Operation Regions

This section describes the Intelligent Platform Management Interface (IPMI) address space and the use of this address space to communicate with the Baseboard Management Controller (BMC) hardware from AML.

Similar to SMBus, IPMI operation regions are command based, where each offset within an IPMI address space represent an IPMI command and response pair. Given this uniqueness, IPMI operation regions include restrictions on their field definitions and require the use of an IPMI-specific data buffer for all transactions. The IPMI interface presented in this section is intended for use with any hardware implementation compatible with the IPMI specification, regardless of the system interface type.

Support of the IPMI generic address space by ACPI-compatible operating systems is optional, and is contingent on the existence of an ACPI IPMI device, i.e. a device with the "IPI0001" plug and play ID. If present, OSPM should load the necessary driver software based on the system interface type as specified by the _IFT (IPMI Interface Type) control method under the device, and register handlers for accesses into the IPMI operation region space.

For more information, refer to the IPMI specification.

Each IPMI operation region definition identifies a single IPMI network function. Operation regions are defined only for those IPMI network functions that need to be accessed from AML. As with other regions, IPMI operation regions are only accessible via the **Field** term (see <u>Section 5.5.2.4.3.1</u>, "Declaring IPMI Fields").

This interface models each IPMI network function as having a 256-byte linear address range. Each byte offset within this range corresponds to a single command value (for example, byte offset 0xC1 equates to command value 0xC1), with a maximum of 256 command values. By doing this, IPMI address spaces appear linear and can be processed in a manner similar to the other address space types.

The syntax for the **OperationRegion** term (from <u>Section 19.5.96</u>, "OperationRegion (Declare Operation Region]") is described below.

Where:

- RegionName specifies a name for this IPMI network function (for example, "POWR").
- RegionSpace must be set to **IPMI** (operation region type value 0x07).
- Offset is a word-sized value specifying the network function and initial command value offset for the target device. The network function address is stored in the high byte and the command value offset is stored in the low byte. For example, the value 0x3000 would be used for a device with the network function of 0x06, and an initial command value offset of zero (0).
- Length is set to the 0x100 (256), representing the maximum number of possible command values, for regions with an initial command value offset of zero (0). The difference of these two values is used for regions with non-zero offsets. For example, a region with an Offset value of 0x3010 would have a corresponding Length of 0xF0 (0x100 minus 0x10).

For example, a Baseboard Management Controller will support power metering capabilities at the network function 0x30, and IPMI commands to query the BMC device information at the network function 0x06.

The following ASL code shows the use of the OperationRegion term to describe these IPMI functions:

Notice that these operation regions in this example are defined within the immediate context of the 'owning' IPMI device. This ensures the correct operation region handler will be used, based on the value returned by the _IFT object. Each definition corresponds to a separate network function, and happens to use an initial command value offset of zero (0).

5.5.2.4.3.1 Declaring IPMI Fields

As with other regions, IPMI operation regions are only accessible via the Field term. Each field element is assigned a unique command value and represents a virtual command for the targeted network function.

The syntax for the **Field** term (from <u>Section 19.5.40</u>, "Event (Declare Event Synchronization Object]") is described below.

Where:

- RegionName specifies the operation region name previously defined for the network function.
- AccessType must be set to **BufferAcc**. This indicates that access to field elements will be done using a region-specific data buffer. For this access type, the field handler is not aware of the data buffer's contents which may be of any size. When a field of this type is used as the source argument in an operation it simply evaluates to a buffer. When used as the destination, however, the buffer is passed bi-directionally to allow data to be returned from write operations. The modified buffer then becomes the response message of that command. This is slightly different than the normal case in which the execution result is the same as the value written to the destination. Note that the source is never changed, since it only represents a virtual register for a particular IPMI command.
- LockRule indicates if access to this operation region requires acquisition of the Global Lock for synchronization. This field should be set to Lock on system with firmware that may access the BMC via IPMI, and NoLock otherwise.
- *UpdateRule* is not applicable to IPMI operation regions since each virtual register is accessed in its entirety. This field is ignored for all IPMI field definitions.

IPMI operation regions require that all field elements be declared at command value granularity. This means that each virtual register cannot be broken down to its individual bits within the field definition.

Access to sub-portions of virtual registers can be done only outside of the field definition. This limitation is imposed both to simplify the IPMI interface and to maintain consistency with the physical model defined by the IPMI specification.

Since the system interface used for IPMI communication is determined by the _IFT object under the IPMI device, there is no need for using of the AccessAs term within the field definition. In fact its usage will be ignored by the operation handler.

For example, the register at command value 0xC1 for the power meter network function might represent the command to set a BMC enforced power limit, while the register at command value 0xC2 for the same network function might represent the current configured power limit. At the same time, the register at command value 0xC8 might represent the latest power meter measurement.

The following ASL code shows the use of the OperationRegion, Field, and Offset terms to represent these virtual registers:

Notice that command values are equivalent to the field element's byte offset (for example, SPWL=0xC1, GPWL=0xC2, GPMM=0xC8).

5.5.2.4.3.2 Declaring and Using IPMI Request and Response Buffer

Since each virtual register in the IPMI operation region represents an individual IPMI command, and the operation relies on use of bi-directional buffer, a common buffer structure is required to represent the request and response messages. The use of a data buffer for IPMI transactions allows AML to receive status and data length values.

The IPMI data buffer is defined as a fixed-length 66-byte buffer that, if represented using a 'C'-styled declaration, would be modeled as follows:

Where:

- *Status* (byte 0) indicates the status code of a given IPMI command. See <u>Section 5.5.2.4.3.3</u>, "IPMI Status Code," for more information.
- *Length* (byte 1) specifies the number of bytes of valid data that exists in the data buffer. Valid *Length* values are 0 through 64. Before the operation is carried out, this value represents the

length of the request data buffer. Afterwards, this value represents the length of the result response data buffer.

• *Data* (bytes 2-65) represents a 64-byte buffer, and is the location where actual data is stored. Before the operation is carried out, this represents the actual request message payload. Afterwards, this represents the response message payload as returned by the IPMI command.

For example, the following ASL shows the use of the IPMI data buffer to carry out a command for a power function. This code is based on the example ASL presented in <u>Section 5.5.2.4.3.1</u>, "Declaring IPMI Fields," which lists the operation region and field definitions for relevant IPMI power metering commands.

```
/* Create the IPMI data buffer */
                                               // Create IPMI data buffer as BUFF
// STAT = Status (Byte)
// LENG = Length (Byte)
Name(BUFF, Buffer(66){})
CreateByteField(BUFF, 0x00, STAT)
CreateByteField(BUFF, 0x01, LENG)
                                                // MODE = Mode (Byte)
CreateByteField(BUFF, 0x02, MODE)
CreateByteField(BUFF, 0x03, RESV)
                                                // RESV = Reserved (Byte)
Store(0x2, LENG)
                                                 // Request message is 2 bytes long
Store(0x1, MODE)
                                                  // Set Mode to 1
Store(Store(BUFF, GPMM), BUFF)
                                                  // Write the request into the GPMM command,
                                                  // then read the results
CreateByteField(BUFF, 0x02, CMPC)
                                                 // CMPC = Completion code (Byte)
CreateWordField(BUFF, 0x03, APOW)
                                                 // APOW = Average power measurement (Word)
If(LAnd(LEqual(STAT, 0x0), LEqual(CMPC, 0x0))) // Successful?
    Return(APOW)
                                                  // Return the average power measurement
}
Else
                                                   // Return invalid
    Return(Ones)
```

Notice the use of the **CreateField** primitives to access the data buffer's sub-elements (*Status*, *Length*, and *Data*), where *Data* (bytes 2-65) is 'typecast' into different fields (including the result completion code).

The example above demonstrates the use of the Store() operator and the bi-directional data buffer to invoke the actual IPMI command represented by the virtual register. The inner Store() writes the request message data buffer to the IPMI operation region handler, and invokes the command. The outer Store() takes the result of that command and writes it back into the data buffer, this time representing the response message.

5.5.2.4.3.3 IPMI Status Code

Every IPMI command results in a status code returned as the first byte of the response message, contained in the bi-directional data buffer. This status code can indicate success, various errors, and possibly timeout from the IPMI operation handler. This is necessary because it is possible for certain IPMI commands to take up to 5 seconds to carry out, and since an AML Store() operation is synchronous by nature, it is essential to make sure the IPMI operation returns in a timely fashion so as not to block the AML interpreter in the OSPM.

Note: This status code is different than the IPMI completion code, which is returned as the first byte of the response message in the data buffer payload. The completion code is described in the complete IPMI specification.

Table 5-127 IPMI Status Codes

Status Code	Name	Description
00h	IPMI OK	Indicates the command has been successfully completed.
07h	IPMI Unknown Failure	Indicates failure because of an unknown IPMI error.
10h	IPMI Command Operation Timeout	Indicates the operation timed out.

5.5.2.4.4 Declaring GeneralPurposeIO Operation Regions

For GeneralPurposeIO Operation Regions, the syntax for the **OperationRegion** term (from section Section 19.5.96, "OperationRegion (Declare Operation Region]") is described below.

Where:

- RegionName specifies a name for this General Purpose IO region (for example, "GPI1").
- RegionSpace must be set to GeneralPurposeIO (operation region type value 0x08).
- *Offset* is ignored for the GeneralPurposeIO RegionSpace.
- Length is the maximum number of GPIO IO pins to be included in the Operation Region, rounded up to the next byte.

GeneralPurposeIO OpRegions must be declared within the scope of the GPIO controller device being accessed.

5.5.2.4.4.1 Declaring General Purpose IO Fields

As with other regions, GeneralPurposeIO operation regions are only accessible via the Field term. Each field element represents a subset of the *length* bits declared in the OpRegion declaration. The pins within the OpRegion that are accessed via a given field name are defined by a Connection descriptor. The total number of defined field bits following a connection descriptor must equal the number of pins listed in the descriptor.

The syntax for the **Field** term (from <u>Section 19.5.46</u>) is described below.

Where:

• RegionName specifies the operation region name previously declared.

- AccessType must be set to ByteAcc.
- LockRule indicates if access to this operation region requires acquisition of the Global Lock for synchronization. Note that, on HW-reduced ACPI platforms, this field must be set to NoLock.
- *UpdateRule* is not applicable to GeneralPurposeIO operation regions since **Preserve** is always required. This field is ignored for all GeneralPurposeIO field definitions.

The following ASL code shows the use of the OperationRegion, Field, and Offset terms as they apply to GeneralPurposeIO space.

```
Device(DEVA) //An Arbitrary Device Scope
 .../Other required stuff for this device
 Name (GMOD, ResourceTemplate ()
                                   //An existing GPIO Connection (to be used later)
  //2 Outputs that define the Power mode of the device
  GpioIo (Exclusive, PullDown, , , , "\\_SB.GPI2") \{10, 12\}
 })
 } //End DEVA
Device (GPI2) //The OpRegion declaration, and the _REG method, must be in the controller's
namespace scope
 .../Other required stuff for the GPIO controller
 OperationRegion(GPO2, GeneralPurposeIO, 0, 1) // Note: length of 1 means region is (or less
than) 1 byte (8 pins) long
 Method(_REG,2) {} // Track availability of GeneralPurposeIO space
 } //End GPI2
Device (DEVB) //Access some GPIO Pins from this device scope to change the device's power mode
 .../Other required stuff for this device
 Name(_DEP, Package() {"\\_SB.GPI2"}) //OpRegion Dependency hint for OSPM
 Field(\_SB.GPI2.GPO2, ByteAcc, NoLock, Preserve)
  Connection (GMOD),
                       // Re-Use an existing connection (defined elsewhere)
  MODE, 2, // Power Mode
  Connection (GpioIo(Exclusive, PullUp, , , , "\\_SB.GPI2") {7}),
  STAT, 1, // e.g. Status signal from the device
  Connection (GpioIo (Exclusive, PullUp, , , , "\\_SB.GPI2") \{9\}),
  RSET. 1
              // e.g. Reset signal to the device
 Method(_PS3)
  If (1) // Make sure GeneralPurposeIO Region is available
   Store(0x03, MODE) //Set both MODE bits. Power Mode 3
 } //End DEVB
```

5.5.2.4.5 Declaring GenericSerialBus Operation Regions

For GenericSerialBus Operation Regions, the syntax for the **OperationRegion** term (from Section 19.5.96, "OperationRegion (Declare Operation Region]") is described below.

Where:

- RegionName specifies a name for this region (for example, TOP1).
- RegionSpace must be set to **GenericSerialBus** (operation region type value 0x09).
- Offset specifies the initial command value offset for the target device. For example, the value 0x00 refers to a command value offset of zero (0). Raw protocols ignore this value.
- *Length* is set to the 0x100 (256), representing the maximum number of possible command values.

Note: The Operation Region must be declared within the scope of the Serial Bus controller device.

The following ASL code shows the use of the OperationRegion, Field, and Offset terms as they apply to SPB space.

```
Scope(\_SB.I2C){
    OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100) // GenericSerialBus device at command
                                                       // offset 0x00
Name (SDB0, ResourceTemplate() {
    I2CSerialBus(0x4a,,100000,,"\_SB.I2C",,,,RawDataBuffer(){1,2,3,4,5,6})
})
Field(TOP1, BufferAcc, NoLock, Preserve)
   Connection(SDB0) // Use the Resource Descriptor defined above
    AccessAs(BufferAcc, AttribWord) // Use the GenericSerialBus Read/Write Word protocol
    FLD0, 8,
                                         // Virtual register at command value 0.
    FLD1, 8
                                         // Virtual register at command value 1.
Field(TOP1, BufferAcc, NoLock, Preserve)
   \texttt{Connection(I2CSerialBus(0x5a,,100000,,"} \subseteq \texttt{SB.I2C",,,,} \texttt{RawDataBuffer()} \{1,6\}))
    AccessAs(BufferAcc, AttribBytes (16))
    FLD2, 8
                                          // Virtual register at command value 0.
// Create the GenericSerialBus data buffer
                             // Create GenericSerialBus data buffer as BUFF
Name(BUFF, Buffer(34){})
```

The Operation Region in this example is defined within the scope of the target controller device, I2C.

GenericSerialBus regions are only accessible via the Field term (see Section 19.5.46 "Field (Declare Field Objects)) GenericSerialBus protocols are assigned to field elements using the AccessAs term (see Section 19.2.4 "ASL Macros") within the field definition.

Table 5-128 Accsessor Type Values

Accessor Type	Value	Description
AttribQuick	0x02	Read/Write Quick Protocol
AttribSendReceive	0x04	Send/Receive Byte Protocol
AttribByte	0x06	Read/Write Byte Protocol
AttribWord	0x08	Read/Write Word Protocol
AttribBlock	0x0A	Read/Write Block Protocol
AttribBytes	0x0B	Read/Write N-Bytes Protocol
AttribProcessCall	0x0C	Process Call Protocol
AttribBlockProcessCall	0x0D	Write Block-Read Block Process Call Protocol
AttribRawBytes	0x0E	Raw Read/Write N-Bytes Protocol
AttribRawProcessBytes	0x0F	Raw Process Call Protocol

5.5.2.4.5.1 Declaring GenericSerialBus Fields

As with other regions, GenericSerialBus operation regions are only accessible via the Field term. Each field element is assigned a unique command value and represents a virtual register on the targeted GenericSerialBus device.

The syntax for the **Field** term (see <u>Section 19.5.46</u> "Field (Declare Field Objects)) is described below.

Field(

Where:

- RegionName specifies the operation region name previously defined for the device.
- Access Type must be set to **BufferAcc**. This indicates that access to field elements will be done using a region-specific data buffer. For this access type, the field handler is not aware of the data buffer's contents which may be of any size. When a field of this type is used as the source argument in an operation it simply evaluates to a buffer. When used as the destination, however, the buffer is passed bi-directionally to allow data to be returned from write operations. The modified buffer then becomes the execution result of that operation. This is slightly different than the normal case in which the execution result is the same as the value written to the destination. Note that the source is never changed, since it could be a read only object (see Section 5.5.2.4.5.2, "Declaring an GenericSerialBus Data Buffer" and Section 19.1.5, "Opcode Terms").
- LockRule indicates if access to this operation region requires acquisition of the Global Lock for synchronization. This field should be set to Lock on system with firmware that may access the GenericSerialBus, and NoLock otherwise. On Hardware-reduced ACPI platforms, there is not a global lock so this parameter is ignored.

• *UpdateRule* is not applicable to GenericSerialBus operation regions since each virtual register is accessed in its entirety. This field is ignored for all GenericSerialBus field definitions.

GenericSerialBus operation regions require that all field elements be declared at command value granularity. This means that each virtual register cannot be broken down to its individual bits within the field definition.

Access to sub-portions of virtual registers can be done only outside of the field definition. This limitation is imposed to simplify the GenericSerialBus interface.

GenericSerialBus protocols are assigned to field elements using the AccessAs term within the field definition. The syntax for this term (from <u>Section 19.1.3</u>, "ASL Root and SecondaryTerms") is described below

Where:

- *AccessType* must be set to **BufferAcc**.
- AccessAttribute indicates the GenericSerialBus protocol to assign to command values that follow this term. SeeSection 5.5.2.4.5.3, "Using the GenericSerialBus Protocols," for a listing of the GenericSerialBus protocols.

An AccessAs term must appear in a field definition to set the initial GenericSerialBus protocol for the field elements that follow. A maximum of one GenericSerialBus protocol may be defined for each field element. Devices supporting multiple protocols for a single command value can be modeled by specifying multiple field elements with the same offset (command value), where each field element is preceded by an AccessAs term specifying an alternate protocol.

For GenericSerialBus operation regions, connection attributes must be defined for each set of field elements. GenericSerialBus resources are assigned to field elements using the Connection term within the field definition. The syntax for this term (from Section 19.5.15 "Connection (Declare Field Connection Attributes)") is described below.

Connection (ConnectionResourceObj)

Where:

• ConnectionResourceObj points to a Serial Bus Resource Connection Descriptor (see Section 6.4.3.8.2, "Serial Bus Connection Resource Descriptors" for valid types), or a named object that specifies a buffer field containing the connection resource information.

Each Field definition references the initial command offset specified in the operation region definition. The offset is iterated for each subsequent field element defined in that respective Field. If a new connection is described in the same Field definition, the offset will not be returned to its initial value and a new Field must be defined to inherit the initial command value offset from the operation region definition. The following example illustrates this point.

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100) //Initial offset is 0
Field(TOP1, BufferAcc, NoLock, Preserve)
    \texttt{Connection}(\texttt{I2CSerialBus}(\texttt{0x5a},\texttt{,100000},, \texttt{"}\_\texttt{SB}.\texttt{I2C"},,,,\texttt{RawDataBuffer}()\{\texttt{1},\texttt{6}\}))
          Offset(0x0),
         AccessAs(BufferAcc, AttribBytes (4)),
         TFK1, 8,
                                    //TFK1 at command value offset 0
         TFK2, 8
                                    //TFK2 at command value offset 1
    Connection(I2CSerialBus(0x5c,,100000,, "\SB.I2C",,,,RawDataBuffer() \{3,1\}))
          Offset(0x0),
         AccessAs(BufferAcc, AttribBytes (12)),
                                  //TS1 at command value offset 2
     Field(TOP1, BufferAcc, NoLock, Preserve)
     \label{local_connection} Connection(I2CSerialBus(0x5b,,100000,, "\SB.I2C",,,,,RawDataBuffer()\{2,9\}))
          AccessAs(BufferAcc, AttribByte),
                                     //TM1 at command value offset 0
     }
```

5.5.2.4.5.2 Declaring and Using a GenericSerialBus Data Buffer

The use of a data buffer for GenericSerialBus transactions allows AML to receive status and data length values, as well as making it possible to implement the Process Call protocol. The **BufferAcc** access type is used to indicate to the field handler that a region-specific data buffer will be used.

For GenericSerialBus operation regions, this data buffer is defined as an arbitrary length buffer that, if represented using a 'C'-styled declaration, would be modeled as follows:

Where:

- Status (byte 0) indicates the status code of a given GenericSerialBus transaction.
- *Length* (byte 1) specifies the number of bytes of valid data that exists in the data buffer. Use of this field is only defined for the Read/Write Block protocol. For other protocols—where the data length is implied by the protocol—this field is reserved.
- *Data* (bytes 2-x) represents an arbitrary length buffer, and is the location where actual data is stored.

For example, the following ASL shows the use of the GenericSerialBus data buffer for performing transactions to a Smart Battery device.

```
/* Create the GenericSerialBus data buffer */
Name(BUFF, Buffer(34){}) // Create GenericSerialBus data buffer as BUFF
CreateByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)
CreateByteField(BUFF, 0x01, LEN) // LEN = Length (Byte)
CreateWordField(BUFF, 0x02, DATW) // DATW = Data (Word - Bytes 2 & 3)
CreateField(BUFF, 0x10, 256, DBUF) // DBUF = Data (Block - Bytes 2-33)
/* Read the battery temperature */
Store(BTMP, BUFF)
                                        // Invoke Read Word transaction
If(LEqual(STAT, 0x00))
                                        // Successful?
                                       // DATW = Battery temperature in 1/10<sup>th</sup> degrees Kelvin
}
/* Read the battery manufacturer name */
Store(MFGN, BUFF) // Invoke Read Blocktransaction
If(LEqual(STAT, 0x00))
                                       // Successful?
   // LEN = Length of the manufacturer name
   // DBUF = Manufacturer name (as a counted string)
```

Notice the use of the **CreateField** primitives to access the data buffer's sub-elements (*Status*, *Length*, and *Data*), where *Data* (bytes 2-33) is 'typecast' as both word (DATW) and block (DBUF) data.

The example above demonstrates the use of the Store() operator to invoke a Read Block transaction to obtain the name of the battery manufacturer. Evaluation of the *source* operand (MFGN) results in a 34-byte buffer that gets copied by Store() to the *destination* buffer (BUFF).

Capturing the results of a write operation, for example to check the status code, requires an additional Store() operator, as shown below.

```
Store(Store(BUFF, MFGN), BUFF) // Invoke Write Block transaction If(LEqual(STAT, 0x00)) {...} // Transaction successful?
```

Note that the outer Store() copies the results of the Write Block transaction back into BUFF. This is the nature of BufferAcc's bi-directionality. It should be noted that storing (or parsing) the result of a GenericSerialBus Write transaction is not required although useful for ascertaining the outcome of a transaction.

GenericSerialBus Process Call protocols require similar semantics due to the fact that only destination operands are passed bi-directionally. These transactions require the use of the double-Store() semantics to properly capture the return results.

5.5.2.4.5.3 Using the GenericSerialBus Protocols

This section provides information and examples on how each of the GenericSerialBus protocols can be used to access GenericSerialBus devices from AML.

5.5.2.4.5.3.1 Read/Write Quick (AttribQuick)

The GenericSerialBus Read/Write Quick protocol (AttribQuick) is typically used to control simple devices using a device-specific binary command (for example, ON and OFF). Command values are not used by this protocol and thus only a single element (at offset 0) can be specified in the field definition. This protocol transfers no data.

The following ASL code illustrates how a device supporting the Read/Write Quick protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100) // GenericSerialBus device at command value
Field(TOP1, BufferAcc, NoLock, Preserve)
     Connection(I2CSerialBus(0x5a,,100000,,"\_SB.I2C",,,,RawDataBuffer(){1,6}))
    AccessAs(BufferAcc, AttribQuick) // Use the GenericSerialBus Read/Write Quick protocol
                                              // Virtual register at command value 0.
    FLD0, 8
/* Create the GenericSerialBus data buffer */
\label{eq:local_particle_potential} $$\operatorname{Name}(\operatorname{BUFF}, \operatorname{Buffer}(2)\{\})$ // \operatorname{Create GenericSerialBus data buffer as BUFF CreateByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)
/* Signal device (e.g. OFF) */
Store(FLD0, BUFF)
                                             // Invoke Read Quick transaction
If(LEqual(STAT, 0x00)) {...}
                                             // Successful?
/* Signal device (e.g. ON) */
Store(BUFF, FLD0)
                                              // Invoke Write Quick transaction
```

In this example, a single field element (FLD0) at offset 0 is defined to represent the protocol's read/write bit. Access to FLD0 will cause a GenericSerialBus transaction to occur to the device. Reading the field results in a Read Quick, and writing to the field results in a Write Quick. In either case data is not transferred—access to the register is simply used as a mechanism to invoke the transaction.

5.5.2.4.5.3.2 Send/Receive Byte (AttribSendReceive)

The GenericSerialBus Send/Receive Byte protocol (AttribSendReceive) transfers a single byte of data. Like Read/Write Quick, command values are not used by this protocol and thus only a single element (at offset 0) can be specified in the field definition.

The following ASL code illustrates how a device supporting the Send/Receive Byte protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100) // GenericSerialBus device at command value
offset 0
Field(TOP1, BufferAcc, NoLock, Preserve)
    Connection(I2CSerialBus(0x5a,,100000,,"\_SB.I2C",,,,RawDataBuffer()\{1,6\}))
    AccessAs(BufferAcc, AttribSendReceive) // Use the GenericSerialBus Send/Receive Byte protocol
    FLD0, 8
                                          // Virtual register at command value 0.
// Create the GenericSerialBus data buffer
Name(BUFF, Buffer(3)\{\}) // Create GenericSerialBus data buffer as BUFF
CreateByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)
CreateByteField(BUFF, 0x02, DATA) // DATA = Data (Byte)
// Receive a byte of data from the device
Store(FLD0, BUFF)
                    // Invoke a Receive Byte transaction
If(LEqual(STAT, 0x00))
                                 // Successful?
    // DATA = Received byte...
```

```
// Send the byte '0x16' to the device Store(0x16, DATA) // Save 0x16 into the data buffer Store(BUFF, FLD0) // Invoke a Send Byte transaction
```

In this example, a single field element (FLD0) at offset 0 is defined to represent the protocol's data byte. Access to FLD0 will cause a GenericSerialBus transaction to occur to the device. Reading the field results in a Receive Byte, and writing to the field results in a Send Byte.

5.5.2.4.5.3.3 Read/Write Byte (AttribByte)

The GenericSerialBus Read/Write Byte protocol (AttribByte) also transfers a single byte of data. But unlike Send/Receive Byte, this protocol uses a command value to reference up to 256 byte-sized virtual registers.

The following ASL code illustrates how a device supporting the Read/Write Byte protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100) // GenericSerialBus device at command value
offset
Field(TOP1, BufferAcc, NoLock, Preserve)
           \texttt{Connection}(\texttt{I2CSerialBus}(\texttt{0x5a},\texttt{,100000},\texttt{,"}\_\texttt{SB.I2C"},\texttt{,,,},\texttt{RawDataBuffer}()\{\texttt{1,6}\}))
           AccessAs(BufferAcc, AttribByte) // Use the GenericSerialBus Read/Write Byte protocol
           FLD0, 8,
                                                                                                          // Virtual register at command value 0.
           FLD1, 8,
                                                                                                            // Virtual register at command value 1.
           FLD2, 8
                                                                                                              // Virtual register at command value 2.
// Create the GenericSerialBus data buffer
Name(BUFF, Buffer(3){})
// Create GenericSerialBus data buffer as BUFF
CreateByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)
// Read a byte of data from the device using command value 1
Score(FLDI, BUFF) // Invoke a Read Byte transaction
If(LEqual(STAT, 0x00)) // Green for the state of the stat
               // DATA = Byte read from FLD1...
}
// Write the byte '0x16' to the device using command value 2
Store(0x16, DATA)
                                                                                                         // Save 0x16 into the data buffer
Store(BUFF, FLD2)
                                                                                                               // Invoke a Write Byte transaction
```

In this example, three field elements (FLD0, FLD1, and FLD2) are defined to represent the virtual registers for command values 0, 1, and 2. Access to any of the field elements will cause a GenericSerialBus transaction to occur to the device. Reading FLD1 results in a Read Byte with a command value of 1, and writing to FLD2 results in a Write Byte with command value 2.

5.5.2.4.5.3.4 Read/Write Word (AttribWord)

The GenericSerialBus Read/Write Word protocol (AttribWord) transfers 2 bytes of data. This protocol also uses a command value to reference up to 256 word-sized virtual device registers.

The following ASL code illustrates how a device supporting the Read/Write Word protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100) // GenericSerialBus device at command value
Field(TOP1, BufferAcc, NoLock, Preserve)
                \texttt{Connection(I2CSerialBus(0x5a,,100000,,"} \_\texttt{SB.I2C",,,,,RawDataBuffer()\{1,6\}))}
                AccessAs(BufferAcc, AttribWord)// Use the GenericSerialBus Read/Write Word protocol
                FLD0, 8,
                                                                                                                                                 // Virtual register at command value 0.
               FLD1, 8,
                                                                                                                                                 // Virtual register at command value 1.
               FLD2, 8
                                                                                                                                                  // Virtual register at command value 2.
}
// Create the GenericSerialBus data buffer
Name(BUFF, Buffer(6)\{\}) // Create GenericSerialBus data buffer as BUFF
\label{eq:createByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)} % \[ \frac{1}{2} \left( \frac
CreateWordField(BUFF, 0x02, DATA) // DATA = Data (Word)
// Read two bytes of data from the device using command value 1
                                                                                             // Invoke a Read Word transaction
Store(FLD1, BUFF)
If(LEqual(STAT, 0x00))
                                                                                                                                              // Successful?
                     // DATA = Word read from FLD1...
// Write the word '0x5416' to the device using command value 2
Store(0x5416, DATA) // Save 0x5416 into the data buffer
Store(BUFF, FLD2)
                                                                                                                                              // Invoke a Write Word transaction
```

In this example, three field elements (FLD0, FLD1, and FLD2) are defined to represent the virtual registers for command values 0, 1, and 2. Access to any of the field elements will cause a GenericSerialBus transaction to occur to the device. Reading FLD1 results in a Read Word with a command value of 1, and writing to FLD2 results in a Write Word with command value 2.

Notice that although accessing each field element transmits a word (16 bits) of data, the fields are listed as 8 bits each. The actual data size is determined by the protocol. Every field element is declared with a length of 8 bits so that command values and byte offsets are equivalent.

5.5.2.4.5.3.5 Read/Write Block (AttribBlock)

The GenericSerialBus Read/Write Block protocol (AttribBlock) transfers variable-sized data. This protocol uses a command value to reference up to 256 block-sized virtual registers.

The following ASL code illustrates how a device supporting the Read/Write Block protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100)
Field(TOP1, BufferAcc, NoLock, Preserve)
   {
    Connection(I2CSerialBus(0x5a,,100000,,"\_SB.I2C",,,,RawDataBuffer(){1,6}))
    Offset(0x0),
    AccessAs(BufferAcc, AttribBlock),
    TFK1, 8,
    TFK2, 8
}
```

In this example, two field elements (TFK1, and TFK2) are defined to represent the virtual registers for command values 0 and 1. Access to any of the field elements will cause a GenericSerialBus transaction to occur to the device.

Writing blocks of data requires similar semantics, such as in the following example.

```
Store(16, LEN) // In bits, so 4 bytes
Store(Store(BUFF, TFK1), BUFF) // Invoke Write Block transaction
If(LEqual(STAT, 0x00)) {...} // Transaction successful?
```

This accessor is not viable for some SPBs because the bus may not support the appropriate functionality. In cases that variable length buffers are desired but the bus does not support block accessors, refer to the SerialBytes protocol.

5.5.2.4.5.3.6 Word Process Call (AttribProcessCall)

The GenericSerialBus Process Call protocol (AttribProcessCall) transfers 2 bytes of data bidirectionally (performs a Write Word followed by a Read Word as an atomic transaction). This protocol uses a command value to reference up to 256 word-sized virtual registers.

The following ASL code illustrates how a device supporting the Process Call protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100) // GenericSerialBus device at slave address
0x42
Field(TOP1, BufferAcc, NoLock, Preserve)
{
    Connection(I2CSerialBus(0x5a,,100000,,"\_SB.I2C",,,,RawDataBuffer(){1,6}))
    AccessAs(BufferAcc, AttribProcessCall) // Use the GenericSerialBus Process Call protocol
    FLD0, 8, // Virtual register at command value 0.
    FLD1, 8, // Virtual register at command value 1.
    FLD2, 8 // Virtual register at command value 2.
}

// Create the GenericSerialBus data buffer
Name(BUFF, Buffer(6){}) // Create GenericSerialBus data buffer as BUFF
CreateByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)
CreateWordField(BUFF, 0x02, DATA) // DATA = Data (Word)
```

In this example, three field elements (FLD0, FLD1, and FLD2) are defined to represent the virtual registers for command values 0, 1, and 2. Access to any of the field elements will cause a GenericSerialBus transaction to occur to the device. Reading *or* writing FLD1 results in a Process Call with a command value of 1. Notice that unlike other protocols, Process Call involves both a write and read operation in a single atomic transaction. This means that the *Data* element of the GenericSerialBus data buffer is set with an input value before the transaction is invoked, and holds the output value following the successful completion of the transaction.

5.5.2.4.5.3.7 Block Process Call (AttribBlockProcessCall)

The GenericSerialBus Block Write-Read Block Process Call protocol (AttribBlockProcessCall) transfers a block of data bi-directionally (performs a Write Block followed by a Read Block as an atomic transaction). This protocol uses a command value to reference up to 256 block-sized virtual registers.

The following ASL code illustrates how a device supporting the Process Call protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100) // GenericSerialBus device at slave address
0 \times 42
Field(TOP1, BufferAcc, NoLock, Preserve)
    \texttt{Connection(I2CSerialBus(0x5a,,100000,,"\\_SB.I2C",,,,,RawDataBuffer()\{1,6\}))}
         AccessAs(BufferAcc, AttribBlockProcessCall) // Use the Block Process Call protocol
          FLD0, 8,
                                                  // Virtual register representing a command value of 0
          FLD1, 8
                                                   // Virtual register representing a command value of 1
}
// Create the GenericSerialBus data buffer as BUFF
Name(BUFF, Buffer(35)())

// Create GenericSerialBus data buffer as BUFF
CreateByteField(BUFF, 0x00, STAT)

// STAT = Status (Byte)
CreateByteField(BUFF, 0x01, LEN)

// LEN = Length (Byte)
CreateField(BUFF, 0x10, 256, DATA)

// Data (Block)
// Process Call with input value "ACPI" to the device using command value 1
Store("ACPI", DATA)
                                                   // Fill in outgoing data
Store(8, LEN)
                                                   // Length of the valid data
Store(Store(BUFF, FLD1), BUFF)
                                                   // Execute the PC
if (LEqual(STAT, 0x00))
                                                   // Test the status
     // BUFF now contains information returned from PC
     // LEN now equals size of data returned
```

5.5.2.4.5.3.8 Read/Write N Bytes (AttribBytes)

The GenericSerialBus Read/Write N Bytes protocol (AttribBytes) transfers variable-sized data. The actual number of bytes to read or write is specified as part of the AccessAs attribute.

The following ASL code illustrates how a device supporting the Read/Write N Bytes protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100)
Field(TOP1, BufferAcc, NoLock, Preserve)
    \texttt{Connection}(\texttt{I2CSerialBus}(\texttt{0x5a},\texttt{,100000},\texttt{,"}\_\texttt{SB.I2C"},\texttt{,,,},\texttt{RawDataBuffer}()\{\texttt{1,6}\}))
        Offset(0x0),
        AccessAs(BufferAcc, AttribBytes (4)),
        TFK1, 8,
                                 //TFK1 at command value 0
                                     //TFK2 at command value 1
        TFK2, 8,
    Connection(I2CSerialBus(0x5b,,100000,,"\_SB.I2C",,,,RawDataBuffer(){2,9}))
     // same connection attribute, but different vendor data passed to driver
         AccessAs(BufferAcc, AttribByte)
         TM1, 8
                                     //TM1 at command value 2
// Create the GenericSerialBus data buffer
Name(BUFF, Buffer(34)\{\}) // Create SerialBus buf as BUFF
CreateByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)
CreateBytefield(BUFF, 0x01, LEN) // LEN = Length (Byte)
CreateWordField(BUFF, 0x02, DATW) // DATW = Data (Word - Bytes 2 & 3, or 16 bits)
CreateField(BUFF, 16, 256, DBUF) // DBUF = Data (Bytes 2-34)
CreateField(BUFF, 16, 32, DATD) // DATD = Data (DWord)
// Read block of data from the device using command value 0
Store(TFK1, BUFF)
If(LNotEqual(STAT, 0x00)) {
     Return(0)
// Write block of data to the device using command value 1
Store(Store(BUFF,TFK2), BUFF)
If(LNotEqual(STAT, 0x00)) {
     Return(0)
```

In this example, two field elements (TFK1, and TFK2) are defined to represent the virtual registers for command values 0 and 1. Access to any of the field elements will cause a GenericSerialBus transaction to occur to the device of the length specified in the AccessAttributes.

5.5.2.4.5.3.9 Raw Read/Write N Bytes (AttribRawBytes)

The GenericSerialBus Raw Read/Write N Bytes protocol (AttribRawBytes) transfers variable-sized data. The actual number of bytes to read or write is specified as part of the AccessAs attribute. The initial command value specified in the operation region definition is ignored by Raw accesses.

The following ASL code illustrates how a device supporting the Read/Write N Bytes protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100)
Field(TOP1, BufferAcc, NoLock, Preserve)
     \texttt{Connection}(\texttt{I2CSerialBus}(\texttt{0x5a},\texttt{,100000},\texttt{,"} \setminus \texttt{SB.I2C"},\texttt{,,,,RawDataBuffer}() \{\texttt{1,6}\}))
        AccessAs(BufferAcc, AttribRawBytes (4))
        TFK1, 8
// Create the GenericSerialBus data buffer
Name(BUFF, Buffer(34)\{\}) // Create SerialBus buf as BUFF
\label{eq:createByteField(BUFF, 0x00, STAT)} \textit{// STAT = Status (Byte)}
CreateByteField(BUFF, 0x01, LEN) // LEN = Length (Byte)
CreateWordField(BUFF, 0x02, DATW) // DATW = Data (Word - Bytes 2 & 3, or 16 bits)
Store(0x0B,DATW)
                                      //Store appropriate reference data for driver to interpret
//Read from TFK1
Store(TFK1, BUFF)
If(LNotEqual(STAT, 0x00)) {
     Return(0)
//Write to TFK1
Store(Store(BUFF,TFK1), BUFF)
If(LNotEqual(STAT, 0x00)) {
     Return(0)
}
```

Access to any field elements will cause a GenericSerialBus transaction to occur to the device of the length specified in the AccessAttributes.

Raw accesses assume that the writer has knowledge of the bus that the access is made over and the device that is being accessed. The protocol may only ensure that the buffer is transmitted to the appropriate driver, but the driver must be able to interpret the buffer to communicate to a register.

5.5.2.4.5.3.10 Raw Block Process Call (AttribRawProcessBytes)

The GenericSerialBus Raw Write-Read Block Process Call protocol (AttribRawProcessBytes) transfers a block of data bi-directionally (performs a Write Block followed by a Read Block as an atomic transaction). The initial command value specified in the operation region definition is ignored by Raw accesses.

The following ASL code illustrates how a device supporting the Process Call protocol should be accessed:

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100) // GenericSerialBus device at slave address
0x42
Field(TOP1, BufferAcc, NoLock, Preserve)
{
          Connection(I2CSerialBus(0x5a,,100000,,"\_SB.I2C",,,,RawDataBuffer(){1,6}))
          AccessAs(BufferAcc, AttribRawProcessBytes) // Use the Raw Bytes Process Call protocol
          FLD0, 8
}
```

```
// Create the GenericSerialBus data buffer as BUFF
Name(BUFF, Buffer(34)())
                          // Create GenericSerialBus data buffer as BUFF
CreateByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)
CreateByteField(BUFF, 0x01, LEN) // LEN = Length (Byte)
CreateWordField(BUFF,0x02, DATW) // Data (Bytes 2 and 3)
CreateField(BUFF, 0x10, 256, DATA) // Data (Block)
Store(0x0B.DATW)
                                 //Store appropriate reference data for driver to interpret
// Process Call with input value "ACPI" to the device
                      // Fill in outgoing data
Store("ACPI", DATA)
Store(8, LEN)
                              // Length of the valid data
Store(Store(BUFF, FLD0), BUFF) // Execute the PC
if (LEqual(STAT, 0x00)) // Test the status
    // BUFF now contains information returned from PC
    // LEN now equals size of data returned
}
```

Raw accesses assume that the writer has knowledge of the bus that the access is made over and the device that is being accessed. The protocol may only ensure that the buffer is transmitted to the appropriate driver, but the driver must be able to interpret the buffer to communicate to a register.

5.6 ACPI Event Programming Model

The ACPI event programming model is based on the SCI interrupt and General-Purpose Event (GPE) register. ACPI provides an extensible method to raise and handle the SCI interrupt, as described in this section.

Hardware-reduced ACPI platforms (<u>Section 4.1</u>) use GPIO Interrupt Connections to signal ACPI Events, described in <u>Section 5.6.5</u>.

5.6.1 ACPI Event Programming Model Components

The components of the ACPI event programming model are the following:

- OSPM
- FADT
- PM1a STS, PM1b STS and PM1a EN, PM1b EN fixed register blocks
- GPE0 BLK and GPE1 BLK register blocks
- GPE register blocks defined in GPE block devices
- SCI interrupt
- ACPI AML code general-purpose event model
- ACPI device-specific model events
- ACPI Embedded Controller event model

The role of each component in the ACPI event programming model is described in the following table.

Table 5-129 ACPI Event Programming Model Components

Component	Description
OSPM	Receives all SCI interrupts raised (receives all SCI events). Either handles the event or masks the event off and later invokes an OEM-provided control method to handle the event. Events handled directly by OSPM are fixed ACPI events; interrupts handled by control methods are general-purpose events.
FADT	Specifies the base address for the following fixed register blocks on an ACPI-compatible platform: PM1x_STS and PM1x_EN fixed registers and the GPEx_STS and GPEx_EN fixed registers.
PM1x_STS and PM1x_EN fixed registers	PM1x_STS bits raise fixed ACPI events. While a PM1x_STS bit is set, if the matching PM1x_EN bit is set, the ACPI SCI event is raised.
GPEx_STS and GPEx_EN fixed registers	GPEx_STS bits that raise general-purpose events. For every event bit implemented in GPEx_STS, there must be a comparable bit in GPEx_EN. Up to 256 GPEx_STS bits and matching GPEx_EN bits can be implemented. While a GPEx_STS bit is set, if the matching GPEx_EN bit is set, then the general-purpose SCI event is raised.
SCI interrupt	A level-sensitive, shareable interrupt mapped to a declared interrupt vector. The SCI interrupt vector can be shared with other low-priority interrupts that have a low frequency of occurrence.
ACPI AML code general-purpose event model	A model that allows OEM AML code to use GPEx_STS events. This includes using GPEx_STS events as "wake" sources as well as other general service events defined by the OEM ("button pressed," "thermal event," "device present/not present changed," and so on).
ACPI device-specific model events	Devices in the ACPI namespace that have ACPI-specific device IDs can provide additional event model functionality. In particular, the ACPI embedded controller device provides a generic event model.
ACPI Embedded Controller event model	A model that allows OEM AML code to use the response from the Embedded Controller Query command to provide general-service event defined by the OEM.

5.6.2 Types of ACPI Events

At the ACPI hardware level, two types of events can be signaled by an SCI interrupt:

- Fixed ACPI events
- General-purpose events

In turn, the general-purpose events can be used to provide further levels of events to the system. And, as in the case of the embedded controller, a well-defined second-level event dispatching is defined to make a third type of typical ACPI event. For the flexibility common in today's designs, two first-level general-purpose event blocks are defined, and the embedded controller construct allows a large number of embedded controller second-level event-dispatching tables to be supported. Then if needed, the OEM can also build additional levels of event dispatching by using AML code on a general-purpose event to sub-dispatch in an OEM defined manner.

5.6.3 Fixed Event Handling

When OSPM receives a fixed ACPI event, it directly reads and handles the event registers itself. The following table lists the fixed ACPI events. For a detailed specification of each event, see Section 4, "ACPI Hardware Specification."

Table 5-130 Fixed ACPI Events

Event	Comment
Power management timer carry bit set.	For more information, see the description of the TMR_STS and TMR_EN bits of the PM1x fixed register block in <u>Section 4.8.3.1</u> , "PM1 Event Grouping," as well as the TMR_VAL register in the PM_TMR_BLK in <u>Section 4.8.3.3</u> , "Power Management Timer."
Power button signal	A power button can be supplied in two ways. One way is to simply use the fixed status bit, and the other uses the declaration of an ACPI power device and AML code to determine the event. For more information about the alternate-device based power button, see Section 4.8.2.2.1.2, Control Method Power Button." Notice that during the S0 state, both the power and sleep buttons merely notify OSPM that they were pressed. If the system does not have a sleep button, it is recommended that OSPM use the power button to initiate sleep operations as requested by the user.
Sleep button signal	A sleep button can be supplied in one of two ways. One way is to simply use the fixed status button. The other way requires the declaration of an ACPI sleep button device and AML code to determine the event.
RTC alarm	ACPI-defines an RTC wake alarm function with a minimum of one-month granularity. The ACPI status bit for the device is optional. If the ACPI status bit is not present, the RTC status can be used to determine when an alarm has occurred. For more information, see the description of the RTC_STS and RTC_EN bits of the PM1x fixed register block in Section 4.8.3.1, "PM1 Event Grouping."
Wake status	The wake status bit is used to determine when the sleeping state has been completed. For more information, see the description of the WAK_STS and WAK_EN bits of the PM1x fixed register block in Section 4.8.3.1, "PM1 Event Grouping."
System bus master request	The bus-master status bit provides feedback from the hardware as to when a bus master cycle has occurred. This is necessary for supporting the processor C3 power savings state. For more information, see the description of the BM_STS bit of the PM1x fixed register block in Section 4.8.3.1 , "PM1 Event Grouping."
Global release status	This status is raised as a result of the Global Lock protocol, and is handled by OSPM as part of Global Lock synchronization. For more information, see the description of the GBL_STS bit of the PM1x fixed register block in Section 4.8.3.1, "PM1 Event Grouping." For more information on Global Lock, see Section 5.2.10.1, "Global Lock."

5.6.4 General-Purpose Event Handling

When OSPM receives a general-purpose event, it either passes control to an ACPI-aware driver, or uses an OEM-supplied control method to handle the event. An OEM can implement up to 128 general-purpose event inputs in hardware per GPE block, each as either a level or edge event. It is also possible to implement a single 256-pin block as long as it's the only block defined in the system.

An example of a general-purpose event is specified in Section 4, "ACPI Hardware Specification," where EC_STS and EC_EN bits are defined to enable OSPM to communicate with an ACPI-aware embedded controller device driver. The EC_STS bit is set when either an interface in the embedded controller space has generated an interrupt or the embedded controller interface needs servicing. Notice that if a platform uses an embedded controller in the ACPI environment, then the embedded controller's SCI output must be directly and exclusively tied to a single GPE input bit.

Hardware can cascade other general-purpose events from a bit in the GPEx_BLK through status and enable bits in Operational Regions (I/O space, memory space, PCI configuration space, or embedded controller space). For more information, see the specification of the General-Purpose Event Blocks (GPEx_BLK) in Section 4.8.4.1, "General-Purpose Event Register Blocks."

OSPM manages the bits in the GPEx blocks directly, although the source to those events is not directly known and is connected into the system by control methods. When OSPM receives a general-purpose event (the event is from a GPEx_BLK STS bit), OSPM does the following:

- 1. Disables the interrupt source (GPEx BLK EN bit).
- 2. If an edge event, clears the status bit.
- 3. Performs one of the following:
 - Dispatches to an ACPI-aware device driver.
 - Queues the matching control method for execution.
 - Manages a wake event using device _PRW objects.
- 4. If a level event, clears the status bit.
- 5. Enables the interrupt source.

For OSPM to manage the bits in the GPEx BLK blocks directly:

- Enable bits must be read/write.
- Status bits must be latching.
- Status bits must be read/clear, and cleared by writing a "1" to the status bit.

5.6.4.1 Exx, Lxx, and Qxx Methods for GPE Processing

The OEM AML code can perform OEM-specific functions custom to each event the particular platform might generate by executing a control method that matches the event. For GPE events, OSPM will execute the control method of the name _GPE._TXX where XX is the hex value format of the event that needs to be handled and T indicates the event handling type (T must be either 'E' for an edge event or 'L' for a level event). The event values for status bits in GPE0_BLK start at zero (_T00) and end at the (GPE0_BLK_LEN / 2) - 1. The event values for status bits in GPE1_BLK start at GPE1_BASE and end at GPE1_BASE + (GPE1_BLK_LEN / 2) - 1. GPE0_BLK_LEN, GPE1_BASE, and GPE1_BLK_LEN are all defined in the FADT.

The _Qxx methods are used for the Embedded Controller and SMBus (below.)

5.6.4.1.1 Queuing the Matching Control Method for Execution

When a general-purpose event is raised, OSPM uses a naming convention to determine which control method to queue for execution and how the GPE EOI is to be handled. The GPEx_STS bits in the GPEx_BLK are indexed with a number from 0 through FF. The name of the control method to queue for an event raised from an enable status bit is always of the form _GPE._Txx where xx is the

event value and T indicates the event EOI protocol to use (either 'E' for edge triggered, or 'L' for level triggered). The event values for status bits in GPE0_BLK start at zero (_T00), end at the (GPE0_BLK_LEN / 2) - 1, and correspond to each status bit index within GPE0_BLK. The event values for status bits in GPE1_BLK are offset by GPE_BASE and therefore start at GPE1_BASE and end at GPE1_BASE + (GPE1_BLK_LEN / 2) - 1.

For example, suppose an OEM supplies a wake event for a communications port and uses bit 4 of the GPE0_STS bits to raise the wake event status. In an OEM-provided Definition Block, there must be a Method declaration that uses the name _GPE._L04 or \GPE._E04 to handle the event. An example of a control method declaration using such a name is the following:

```
Method (\_GPE._L04) { // GPE 4 level wake handler
   Notify (\_SB.PCIO.COM0, 2)
}
```

The control method performs whatever action is appropriate for the event it handles. For example, if the event means that a device has appeared in a slot, the control method might acknowledge the event to some other hardware register and signal a change notify request of the appropriate device object. Or, the cause of the general-purpose event can result from more then one source, in which case the control method for that event determines the source and takes the appropriate action.

When a general-purpose event is raised from the GPE bit tied to an embedded controller, the embedded controller driver uses another naming convention defined by ACPI for the embedded controller driver to determine which control method to queue for execution. The queries that the embedded controller driver exchanges with the embedded controller are numbered from 0 through FF, yielding event codes 01 through FF. (A query response of 0 from the embedded controller is reserved for "no outstanding events.") The name of the control method to queue is always of the form _Qxx where xx is the number of the query acknowledged by the embedded controller. An example declaration for a control method that handles an embedded controller query is the following:

```
\label{eq:Method} $$ \mbox{Method}(\Q34) $ $ \mbox{$/$ embedded controller event for thermal} $$ \mbox{Notify}(\SB.TZ0.THM1, 0x80) $$ $$ $\mbox{$/$ embedded controller} $$$ $\mbox{$/$ embedded controller} $$$$ $\mbox{$/$ embedded controller} $$$$$ $\mbox{
```

When an SMBus alarm is handled by the SMBus driver, the SMBus driver uses a similar naming convention defined by ACPI for the driver to determine the control method to queue for execution. When an alarm is received by the SMBus host controller, it generally receives the SMBus address of the device issuing the alarm and one word of data. On implementations that use SMBALERT# for notifications, only the device address will be received. The name of the control method to queue is always of the form _Qxx where xx is the SMBus address of the device that issued the alarm. The SMBus address is 7 bits long corresponding to hex values 0 through 7F, although some addresses are reserved and will not be used. The control method will always be queued with one argument that contains the word of data received with the alarm. An exception is the case of an SMBus using SMBALERT# for notifications, in this case the argument will be 0. An example declaration for a control method that handles a SMBus alarm follows:

5.6.4.1.2 Dispatching to an ACPI-Aware Device Driver

Certain device support, such as an embedded controller, requires a dedicated GPE to service the device. Such GPEs are dispatched to native OS code to be handled and not to the corresponding GPE-specific control method.

In the case of the embedded controller, an OS-native, ACPI-aware driver is given the GPE event for its device. This driver services the embedded controller device and determines when events are to be reported by the embedded controller by using the Query command. When an embedded controller event occurs, the ACPI-aware driver dispatches the requests to other ACPI-aware drivers that have registered to handle the embedded controller queries or queues control methods to handle each event. If there is no device driver to handle specific queries, OEM AML code can perform OEM-specific functions that are customized to each event on the particular platform by including specific control methods in the namespace to handle these events. For an embedded controller event, OSPM will queue the control method of the name _QXX, where XX is the hex format of the query code. Notice that each embedded controller device can have query event control methods.

Similarly, for an SMBus driver, if no driver registers for SMBus alarms, the SMBus driver will queue control methods to handle these. Methods must be placed under the SMBus device with the name _QXX where XX is the hex format of the SMBus address of the device sending the alarm.

5.6.4.2 GPE Wake Events

An important use of the general-purpose events is to implement device wake events. The components of the ACPI event programming model interact in the following way:

- When a device asserts its wake signal, the general-purpose status event bit used to track that device is set.
- While the corresponding general-purpose enable bit is enabled, the SCI interrupt is asserted.
- If the system is sleeping, this will cause the hardware, if possible, to transition the system into the S0 state.
- Once the system is running, OSPM will dispatch the corresponding GPE handler.
- The handler needs to determine which device object has signaled wake and performs a wake Notify
- command on the corresponding device object(s) that have asserted wake.
- In turn OSPM will notify OSPM native driver(s) for each device that will wake its device to service it.

Events that wake may not be intermixed with non-wake (runtime) events on the same GPE input. The only exception to this rule is made for the special devices below. Only the following devices are allowed to utilize a single GPE for both wake and runtime events:

1. 1) Button Devices

- PNP0C0C Power Button Device
- PNP0C0D Lid Device
- PNP0C0E Sleep Button Device
- 2. 2) PCI Bus Wakeup Event Reporting (PME)
 - PNP0A03 PCI Host Bridge

All wake events that are not exclusively tied to a GPE input (for example, one input is shared for multiple wake events) must have individual enable and status bits in order to properly handle the semantics used by the system.

5.6.4.2.1 Managing a Wake Event Using Device _PRW Objects

A device's _PRW object provides the zero-based bit index into the general-purpose status register block to indicate which general-purpose status bit from either GPE0_BLK or GPE1_BLK is used as the specific device's wake mask. Although the hardware must maintain individual device wake enable bits, the system can have multiple devices using the same general-purpose event bit by using OEM-specific hardware to provide second-level status and enable bits. In this case, the OEM AML code is responsible for the second-level enable and status bits.

OSPM enables or disables the device wake function by enabling or disabling its corresponding GPE and by executing its _PSW control method (which is used to take care of the second-level enables). When the GPE is asserted, OSPM still executes the corresponding GPE control method that determines which device wakes are asserted and notifies the corresponding device objects. The native OS driver is then notified that its device has asserted wake, for which the driver powers on its device to service it.

If the system is in a sleeping state when the enabled GPE bit is asserted the hardware will transition the system into the S0 state, if possible.

5.6.4.2.2 Determining the System Wake Source Using _Wxx Control Methods

After a transition to the S0 state, OSPM may evaluate the _SWS object in the _GPE scope to determine the index of the GPE that was the source of the transition event. When a single GPE is shared among multiple devices, the platform provides a $_Wxx$ control method, where xx is GPE index as described in Section 5.6.2.2.3, that allows the source device of the transition to be determined. If implemented, the $_Wxx$ control method must exist in the _GPE scope or in the scope of a GPE block device.

If _Wxx is implemented, either hardware or firmware must detect and save the source device as described in Section 7.3.3, "_SWS (System Wake Source)". During invocation, the _Wxx control method determines the source device and issues a Notify(<device>,0x2) on the device that caused the system to transition to the S0 state. If the device uses a bus-specific method of arming for wakeup, then the Notify must be issued on the parent of the device that has a _PRW method. The _Wxx method must issue a Notify(<device>,0x2) only to devices that contain a _PRW method within their device scope. OSPM's evaluation of the _SWS and _Wxx objects is indeterminate. As such, the platform must not rely on _SWS or _Wxx evaluation to clear any hardware state, including GPEx STS bits, or to perform any wakeup-related actions.

If the GPE index returned by the _SWS object is only referenced by a single _PRW object in the system, it is implied that the device containing that _PRW is the wake source. In this case, it is not necessary for the platform to provide a _Wxx method.

5.6.5 GPIO-signaled ACPI Events

On Hardware-reduced ACPI platforms, ACPI events are signaled when a GPIO Interrupt is received by OSPM, and that GPIO Interrupt Connection is listed in a GPIO controller device's _AEI object. OSPM claims all such GPIO interrupts, and maps them to the appropriate event method required by the ACPI event model.

5.6.5.1 Declaring GPIO Controller Devices

A GPIO controller is modeled as a device in the namespace, with _HID or _ADR and _CRS objects, at a minimum. Optionally, the GPIO controller device scope may include GeneralPurposeIO OpRegion declarations (Section 5.5.2.4.4) and GPIO interrupt-to-ACPI Event mappings (Section 5.6.5.2). Note that for GPIO-signaled ACPI events, the corresponding event method (e.g. _Exx, _Lxx, or _EVT) must also appear in the target GPIO controller's scope. For GPIO event numbers larger than 255 (0xFF), the EVT method is used.

Each pin on a GPIO Controller has a configuration (e.g. level-sensitive interrupt, de-bounced input, high-drive output, etc.), which is described to OSPM in the GPIO Interrupt or GPIO IO Connection resources claimed by peripheral devices or used in operation region accesses.

5.6.5.2 _AEI Object

The _AEI object designates those GPIO interrupts that shall be handled by OSPM as ACPI events (See <u>Section 5.6.5</u>). This object appears within the scope of the GPIO controller device whose pins are to be used as GPIO-signaled events.

Arguments:

None

Return Value:

A resource template **Buffer** containing only GPIO Interrupt Connection descriptors.

Example:

```
Device (\_SB.GPI2)
    Name(_HID, "XYZ0003")
    Name(_UID, 2)
                                         //Third instance of this controller on the platform
     Name(_CRS, ResourceTemplate ()
                                          //Register Interface
        MEMORY32FIXED(ReadWrite, 0x30000000, 0x200, )
                                         //Interrupt line (GSIV 21)
         Interrupt(ResourceConsumer, Level, ActiveHigh, Exclusive) {21}
     })
     Name(_AEI, ResourceTemplate ()
                                          //Thermal Zone Event
        GpioInt(Edge, ActiveHigh, Exclusive, PullDown, , " \\_SB.GPI2") {14}
                                          //Power Button
        GpioInt(Edge, ActiveLow, ExclusiveAndWake, PullUp, , " \\_SB.GPI2") {36}
    })
}
```

5.6.5.3 The Event (_EVT) Method for Handling GPIO-signaled Events

GPIO Interrupt Connection Descriptors assign GPIO pins a controller-relative, 0-based pin number. GPIO Pin numbers can be as large as 65, 535. GPIO Interrupt Connections that are assigned by the platform to signal ACPI events are listed in the _AEI object under the GPIO controller. Since the GPIO interrupt connection descriptor also provides the mode of the interrupt associated with an event, it gives OSPM all the information it needs to invoke a handler method for the event. No naming convention is required to encode the mode and pin number of the event. Instead, a handler for a GPIO-signaled event simply needs to have a well-known name and take the pin number of the event as a parameter. A single instance of the method handles all ACPI events for a given GPIO controller device.

For GPIO-signaled events, the Event (EVT) method is used.

EVT is defined as follows:

Arguments: (1)

Arg0 - EventNumber. An Integer indicating the event number (Controller-relative zero-based GPIO pin number) of the current event. Must be in the range 0x0000 - 0xffff.

Return Value:

None

Description

The _EVT method handles a GPIO-signaled event. It must appear within the scope of the GPIO controller device whose pins are used to signal the event.

OSPM handles GPIO-signaled events as follows:

- The GPIO interrupt is handled by OSPM because it is listed in the _AEI object under a GPIO controller.
- When the event fires, OSPM handles the interrupt according to its mode and invokes the _EVT method, passing it the pin number of the event.
- From this point on, handling is exactly like that for GPEs. The _EVT method does a Notify() on the appropriate device, and OS-specific mechanisms are used to notify the driver of the event.

Note: For event numbers less than 255, _Exx and _Lxx methods may be used instead. In this case, they take precedence and _EVT will not be invoked.

Example:

5.6.6 Device Object Notifications

During normal operation, the platform needs to notify OSPM of various device-related events. These notifications are accomplished using the Notify operator, which indicates a target device, thermal zone, or processor object and a notification value that signifies the purpose of the notification. Notification values from 0 through 0x7F are common across all device object types. Notification values of 0xC0 and above are reserved for definition by hardware vendors for hardware specific notifications. Notification values from 0x80 to 0xBF are device-specific and defined by each such device. For more information on the Notify operator, see Section 19.5.91, "Notify (Notify)."

Table 5-131 Device Object Notification Values

Value	Description
0	Bus Check. This notification is performed on a device object to indicate to OSPM that it needs to perform a Plug and Play re-enumeration operation on the device tree starting from the point where it has been notified. OSPM will typically perform a full enumeration automatically at boot time, but after system initialization it is the responsibility of the ACPI AML code to notify OSPM whenever a re-enumeration operation is required. The more accurately and closer to the actual change in the device tree the notification can be done, the more efficient the operating system's response will be; however, it can also be an issue when a device change cannot be confirmed. For example, if the hardware cannot recognize a device change for a particular location during a system sleeping state, it issues a Bus Check notification on wake to inform OSPM that it needs to check the configuration for a device change.

Value	Description
1	Device Check. Used to notify OSPM that the device either appeared or disappeared. If the device has appeared, OSPM will re-enumerate from the parent. If the device has disappeared, OSPM will invalidate the state of the device. OSPM may optimize out re-enumeration. If _DCK is present, then Notify(object,1) is assumed to indicate an undock request. If the device is a bridge, OSPM may re-enumerate the bridge and the child bus.
2	Device Wake. Used to notify OSPM that the device has signaled its wake event, and that OSPM needs to notify OSPM native device driver for the device. This is only used for devices that support _PRW.
3	Eject Request. Used to notify OSPM that the device should be ejected, and that OSPM needs to perform the Plug and Play ejection operation. OSPM will run the _EJx method.
4	Device Check Light. Used to notify OSPM that the device either appeared or disappeared. If the device has appeared, OSPM will re-enumerate from the device itself, not the parent. If the device has disappeared, OSPM will invalidate the state of the device.
5	Frequency Mismatch. Used to notify OSPM that a device inserted into a slot cannot be attached to the bus because the device cannot be operated at the current frequency of the bus. For example, this would be used if a user tried to hot-plug a 33 MHz PCI device into a slot that was on a bus running at greater than 33 MHz.
6	Bus Mode Mismatch. Used to notify OSPM that a device has been inserted into a slot or bay that cannot support the device in its current mode of operation. For example, this would be used if a user tried to hot-plug a PCI device into a slot that was on a bus running in PCI-X mode.
7	Power Fault. Used to notify OSPM that a device cannot be moved out of the D3 state because of a power fault.
8	Capabilities Check. This notification is performed on a device object to indicate to OSPM that it needs to re-evaluate the _OSC control method associated with the device.
9	Device _PLD Check. Used to notify OSPM to reevaluate the _PLD object, as the Device's connection point has changed.
0xA	Reserved.
0xB	System Locality Information Update. Dynamic reconfiguration of the system may cause existing relative distance information to change. The platform sends the System Locality Information Update notification to a point on a device tree to indicate to OSPM that it needs to invoke the _SLI objects associated with the System Localities on the device tree starting from the point notified.
0x0C	Graceful Shutdown Request . Used to notify OSPM that a graceful shutdown of the operating system has been requested. Once the operating system has finished its graceful shutdown procedure it should initiate a transition to the G2 "soft off" state. See Section 6.3.5 for a description of shutdown processing.
0x0D	System Resource Affinity Update. Dynamic migration of devices may cause existing system resource affinity to change. The platform software issues the System Resource Affinity Update notification to a point on a device tree to indicate to OSPM that it needs to invoke the _PXM object of the notified device to update the resource affinity.
0x0E-0x7F	Reserved.

Below are the notification values defined for specific ACPI devices. For more information concerning the object-specific notification, see the section on the corresponding device/object.

Table 5-132 Control Method Battery Device Notification Values

Hex value	Description
0x80	Battery Status Changed. Used to notify OSPM that the Control Method Battery device status has changed.
0x81	Battery Information Changed. Used to notify OSPM that the Control Method Battery device information has changed. This only occurs when a battery is replaced.
0x82	Battery Maintenance Data Status Flags Check. Used to notify OSPM that the Control Method Battery device battery maintenance data status flags should be checked.
0x83-0xBF	Reserved.

Table 5-133 Power Source Object Notification Values

Hex value	Description
0x80	Power Source Status Changed . Used to notify OSPM that the power source status has changed.
0x81	Power Source Information Changed. Used to notify OSPM that the power source information has changed.
0x82-0xBF	Reserved.

Table 5-134 Thermal Zone Object Notification Values

Hex value	Description
0x80	Thermal Zone Status Changed. Used to notify OSPM that the thermal zone temperature has changed.
0x81	Thermal Zone Trip points Changed. Used to notify OSPM that the thermal zone trip points have changed.
0x82	Device Lists Changed. Used to notify OSPM that the thermal zone device lists (_ALx, _PSL, _TZD) have changed.
0x83	Thermal / Active Cooling Relationship Table Changed. Used to notify OSPM that values in the either the thermal relationship table or the active cooling relationship table have changed.
0x84-0xBF	Reserved.

Table 5-135 Control Method Power Button Notification Values

Hex value	Description
0x80	S0 Power Button Pressed. Used to notify OSPM that the power button has been pressed while the system is in the S0 state. Notice that when the button is pressed while the system is in the S1-S4 state, a Device Wake notification must be issued instead.
0x81-0xBF	Reserved.

Table 5-136 Control Method Sleep Button Notification Values

Hex value	Description
0x80	SO Sleep Button Pressed. Used to notify OSPM that the sleep button has been pressed while the system is in the S0 state. Notice that when the button is pressed while the system is in the S1-S4 state, a Device Wake notification must be issued instead.
0x81-0xBF	Reserved.

Table 5-137 Control Method Lid Notification Values

Hex value	Description
0x80	Lid Status Changed. Used to notify OSPM that the control method lid device status has changed.
0x81-0xBF	Reserved.

Table 5-138 Processor Device Notification Values

Hex value	Description
0x80	Performance Present Capabilities Changed . Used to notify OSPM that the number of supported processor performance states has changed. This notification causes OSPM to reevaluate the _PPC object. See Section 8 "Processor Configuration and Control," for more information.
0x81	C States Changed. Used to notify OSPM that the number or type of supported processor C States has changed. This notification causes OSPM to re-evaluate the _CST object. See Section 8, "Processor Configuration and Control," for more information.
0x82	Throttling Present Capabilities Changed . Used to notify OSPM that the number of supported processor throttling states has changed. This notification causes OSPM to reevaluate the _TPC object. See Section 8 , "Processor Configuration and Control," for more information.
0x83	Guaranteed Changed. Used to notify OSPM that the value of the CPPC Guaranteed Register has changed.
0x84	Minimum Excursion. Used to notify OSPM that an excursion to CPPC Minimum has occurred.
0x85-0xBF	Reserved.

Table 5-139 User Presence Device Notification Values

Hex value	Description
0x80	User Presence Changed. Used to notify OSPM that a meaningful change in user presence has occurred, causing OSPM to re-evaluate the _UPD object.
0x81-0xBF	Reserved.

Table 5-140 Ambient Light Sensor Device Notification Values

Hex value	Description
0x80	ALS Illuminance Changed. Used to notify OSPM that a meaningful change in ambient light
	illuminance has occurred, causing OSPM to re-evaluate the _ALI object.

Hex value	Description
0x81	ALS Color Temperature Changed. Used to notify OSPM that a meaningful change in ambient light color temperature or chromaticity has occurred, causing OSPM to re-evaluate the _ALT and/or _ALC objects.
0x82	ALS Response Changed. Used to notify OSPM that the set of points used to convey the ambient light response has changed, causing OSPM to re-evaluate the _ALR object.
0x83-0xBF	Reserved.

Table 5-141 Power Meter Object Notification Values

Hex value	Description
0x80	Power Meter Capabilities Changed. Used to notify OSPM that the power meter information has changed.
0x81	Power Meter Trip Points Crossed. Used to notify OSPM that one of the power meter trip points has been crossed.
0x82	Power Meter Hardware Limit Changed. Used to notify OSPM that the hardware limit has been changed by the platform.
0x83	Power Meter Hardware Limit Enforced. Used to notify OSPM that the hardware limit has been enforced by the platform.
0x84	Power Meter Averaging Interval Changed. Used to notify OSPM that the power averaging interval has changed.
0x85-0xBF	Reserved.

Table 5-142 Processor Aggregator Device Notification Values

Hex value	Description
0x80	Processor Utilisation Request. Used to notify OSPM that OSPM evaluates the _PUR object which indicates to OSPM the number of logical processors to be idled.
0x81-0xBF	Reserved.

Table 5-143 Error Device Notification Values

Hex value	Description
0x80	Notification For Generic Error Sources. Used to notify OSPM to respond to this notification by checking the error status block of all generic error sources to identify the source reporting the error.
0x81-0xBF	Reserved.

Table 5-144 Fan Device Notification Values

Hex value	Description
0x80	Low Fan Speed. Used to notify OSPM of a low (errant) fan speed. Causes OSPM to reevaluate the _FSL object.
0x81-0xBF	Reserved.

Table 5-145 Memory Device Notification Values

Hex value	Description
0x80	Memory Bandwidth Low Threshold crossed. Used to notify OSPM that bandwidth of memory described by the memory device has been reduced by the platform to less than the low memory bandwidth threshold.
0x81	Memory Bandwidth High Threshold crossed. Used to notify OSPM that bandwidth of memory described by the memory device has been increased by the platform to greater than or equal to the high memory bandwidth threshold.
0x82-0xBF	Reserved.

Table 5-146 Processor Aggregator Device Notification Value

Hex value	Description
0x80	Processor Utilization Request. Used to notify OSPM that OSPM evaluates the _PUR object which indicates to OSPM the number of logical processors to be idled.
0x81-0xBF	Reserved.

Table 5-147 Error Device Notification Values

Hex value	Description
0x80	Notification For Generic Error Sources. Used to notify OSPM to respond to this notification by checking the error status block of all generic error sources to identify the source reporting the error.
0x81-0xBF	Reserved.

5.6.7 Device Class-Specific Objects

Most device objects are controlled through generic objects and control methods and they have generic device IDs. These generic objects, control methods, and device IDs are specified in Section 6, through Section 11. Section 5.6.8, "Predefined ACPI Names for Objects, Methods, and Resources," lists all the generic objects and control methods defined in this specification.

However, certain integrated devices require support for some device-specific ACPI controls. This section lists these devices, along with the device-specific ACPI controls that can be provided.

Some of these controls are for ACPI-aware devices and as such have Plug and Play IDs that represent these devices. The table below lists the Plug and Play IDs defined by the ACPI specification.

Note: Plug and Play IDs that are not defined by the ACPI specification are defined and described in the "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Legacy PNP Guidelines".

Table 5-148 ACPI Device IDs

Plug and Play ID	Description
PNP0C08	ACPI. Not declared in ACPI as a device. This ID is used by OSPM for the hardware resources consumed by the ACPI fixed register spaces, and the operation regions used by AML code. It represents the core ACPI hardware itself.
PNP0A05	Generic Container Device. A device whose settings are totally controlled by its ACPI resource information, and otherwise needs no device or bus-specific driver support. This was originally known as Generic ISA Bus Device. This ID should only be used for containers that do not produce resources for consumption by child devices. Any system resources claimed by a PNP0A05 device's _CRS object must be consumed by the container itself.
PNP0A06	Generic Container Device. This device behaves exactly the same as the PNP0A05 device. This was originally known as Extended I/O Bus. This ID should only be used for containers that do not produce resources for consumption by child devices. Any system resources claimed by a PNP0A06 device's _CRS object must be consumed by the container itself.
PNP0C09	Embedded Controller Device. A host embedded controller controlled through an ACPI-aware driver.
PNP0C0A	Control Method Battery. A device that solely implements the ACPI Control Method Battery functions. A device that has some other primary function would use its normal device ID. This ID is used when the devices primary function is that of a battery.
PNP0C0B	Fan. A device that causes cooling when "on" (D0 device state).
PNP0C0C	Power Button Device. A device controlled through an ACPI-aware driver that provides power button functionality. This device is only needed if the power button is not supported using the fixed register space.
PNP0C0D	Lid Device. A device controlled through an ACPI-aware driver that provides lid status functionality. This device is only needed if the lid state is not supported using the fixed register space.
PNP0C0E	Sleep Button Device. A device controlled through an ACPI-aware driver that provides power button functionality. This device is optional.
PNP0C0F	PCI Interrupt Link Device. A device that allocates an interrupt connected to a PCI interrupt pin. See Section 6., "Device Configuration," for more details.
PNP0C80	Memory Device. This device is a memory subsystem.
ACPI0001	SMBus 1.0 Host Controller. An SMBus host controller (SMB-HC) compatible with the embedded controller-based SMB-HC interface (as specified in Section 12.9 "SMBus Host Controller Interface via Embedded Controller") and implementing the SMBus 1.0 Specification.
ACPI0002	Smart Battery Subsystem. The Smart battery Subsystem specified in <u>Section 10</u> , "Power Source Devices."
ACPI0003	Power Source Device. The Power Source device specified in Section 10, "Power Source Devices." This can represent either an AC Adapter (on mobile platforms) or a fixed Power Supply.

Plug and Play ID	Description
ACPI0004	Module Device. This device is a container object that acts as a bus node in a namespace. A Module Device without any of the _CRS, _PRS and _SRS methods behaves the same way as the Generic Container Devices (PNP0A05 or PNP0A06). If the Module Device contains a _CRS method, only these resources described in the _CRS are available for consumption by its child devices. Also, the Module Device can support _PRS and _SRS methods if _CRS is supported.
ACPI0005	SMBus 2.0 Host Controller. An SMBus host controller (SMB-HC compatible with the embedded controller-based SMB-HC interface (as specified in Section 12.9, "SMBus Host Controller Interface via Embedded Controller") and implementing the SMBus 2.0 Specification.
ACPI0006	GPE Block Device. This device allows a system designer to describe GPE blocks beyond the two that are described in the FADT.
ACPI0007	Processor Device. This device provides an alternative to declaring processors using the Processor ASL statement. See <u>Section 8.4</u> , "Declaring Processors", for more details.
ACPI0008	Ambient Light Sensor Device. This device is an ambient light sensor. See Section 9.2, "Ambient Light Sensor Device".
ACPI0009	I/OxAPIC Device. This device is an I/O unit that complies with both the APIC and SAPIC interrupt models.
ACPI000A	I/O APIC Device. This device is an I/O unit that complies with the APIC interrupt model.
ACPI000B	I/O SAPIC Device. This device is an I/O unit that complies with the SAPIC interrupt model.
ACPI000C	Processor Aggregator Device. This device provides a control point for all processors in the platform. See Section 8.5, "Processor Aggregator Device".
ACPI000D	Power Meter Device. This device is a power meter. See Section 10.4. "Power Meters".
ACPI000E	Time and Alarm Device. This device is a control method-based real-time clock and wake alarm. See Section 9.18. "Time and Alarm Device".
ACPI000F	User Presence Detection Device. This device senses user presence (proximity). See Section 9.16, "User Presence Detection Device")

5.6.8 Predefined ACPI Names for Objects, Methods, and Resources

The following table summarizes the predefined names for the ACPI namespace objects, control methods, and resource descriptor fields defined in this specification. Provided for each name is a short description and a reference to the section number and page number of the actual definition of the name. ACPI names that are predefined by other specifications are also listed along with their corresponding specification reference.

Note: All names that begin with an underscore are reserved for ACPI use only

Table 5-149 Predefined ACPI Names.

Name	Description	Heading	
_ACx	<u>Active</u> <u>Cooling</u> – returns the active cooling policy threshold	Section 11.4.1	page 548
	values.		

Name	Description	Heading	
_ADR	<u>Address</u> – (1) returns the address of a device on its parent	Section 6.1.1	page 262
	bus.	Section B.5.1	page 905
	(2) returns a unique ID for the display output device.(3) resource descriptor field.	<u>Section 19.1.8</u>	page 709
_AEI	Designates those GPIO interrupts that shall be handled by OSPM as ACPI events	<u>Section 5.6.5.2</u>	page 233
_ALC	<u>Ambient Light Chromaticity</u> – returns the ambient light color chromaticity.	Section 9.2.4	page 450
_ALI	Ambient Light Illuminance – returns the ambient light brightness.	Section 9.2.2	page 449
_ALN	<u>Alignment</u> – base alignment, resource descriptor field.	<u>Section 19.1.8</u>	page 709
_ALP	<u>Ambient Light Polling</u> – returns the ambient light sensor polling frequency.	Section 9.2.6	page 455
_ALR	<u>Ambient Light Response</u> – returns the ambient light brightness to display brightness mappings.	Section 9.2.5	page 451
_ALT	<u>Ambient Light Temperature</u> – returns the ambient light color temperature.	Section 9.2.3	page 450
_ALx	Active List – returns a list of active cooling device objects.	<u>Section 11.4.2</u>	page 548
_ART	<u>Active cooling Relationship Table</u> – returns thermal relationship information between platform devices and fan devices.	Section 11.4.3	page 549
_ASI	<u>A</u> ddress <u>S</u> pace <u>I</u> d – resource descriptor field.	<u>Section 19.1.8</u>	page 809
_ASZ	Access Size – resource descriptor field.	Section 19.1.8	page 709
_ATT	Type-Specific <u>Att</u> ribute – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_BAS	<u>B</u> ase <u>A</u> ddre <u>s</u> s – range base address, resource descriptor field.	Section 19.1.8	page 709
_BBN	<u>B</u> ios <u>B</u> us <u>N</u> umber – returns the PCI bus number returned by the BIOS.	Section 6.5.5	page 367
_BCL	<u>Brightness</u> <u>Control</u> <u>Levels</u> – returns a list of supported brightness control levels.	Section B.5.2	page 905
_BCM	<u>Brightness</u> <u>Control</u> <u>Method</u> – sets the brightness level of the display device.	Section B.5.3	page 906
_BCT	<u>Battery Charge Time</u> – returns time remaining to complete charging battery.	<u>Section 10.2.2.9</u>	page 521
_BDN	<u>B</u> ios <u>D</u> ock <u>N</u> ame – returns the Dock ID returned by the BIOS.	Section 6.5.3	page 364
_BIF	<u>B</u> attery <u>Information</u> – returns a Control Method Battery information block.	Section 10.2.2.1	page 512
_BIX	<u>B</u> attery <u>I</u> nformation Extended – returns a Control Method Battery extended information block.	Section 10.2.2.2	page 514
_BLT	<u>B</u> attery <u>Level Threshold</u> – set battery level threshold preferences.	Section 19.5.106	page 448
_BM	<u>B</u> us <u>M</u> aster − resource descriptor field.	<u>Section 19.1.8</u>	page 709
		•	

Name	Description	Heading	
_BMA	B attery M easurement A veraging Interval – Sets battery measurement averaging interval.	Section 10.2.2.4	page 517
_BMC	B attery M aintenance C ontrol – Sets battery maintenance and control features.	Section 10.2.2.11	page 523
_BMD	B attery M aintenance D ata – returns battery maintenance, control, and state data.	Section 10.2.2.10	page 521
_BMS	<u>B</u> attery <u>M</u> easurement <u>Sampling Time</u> – Sets the battery measurement sampling time.	Section 10.2.2.5	page 518
_BQC	B rightness Q uery C urrent – returns the current display brightness level.	Section B.5.4	page 906
_BST	<u>B</u> attery <u>St</u> atus – returns a Control Method Battery status block.	<u>Section 10.2.2.6</u>	page 518
_BTM	<u>B</u> attery <u>Time</u> – returns the battery runtime.	Section 10.2.2.8	page 520
_BTP	<u>B</u> attery <u>Trip</u> <u>Point</u> – sets a Control Method Battery trip point.	Section 10.2.2.7	page 520
_CBA	<u>Configuration</u> <u>B</u> ase <u>A</u> ddress – sets the CBA for a PCI Express host bridge. See the PCI Firmware Specification, Revision 3.0 at "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "PCI Sig".		
_CCA	<u>Cache Coherency Attribute</u> specifies whether a device and its descendants support hardware managed cache coherency.	<u>Section 6.2.17</u>	page 310
_CDM	<u>C</u> lock <u>D</u> o <u>m</u> ain – returns a logical processor's clock domain identifier.	Section 6.2.1	page 277
_CID	C ompatible ID – returns a device's Plug and Play Compatible ID list.	Section 6.1.2	page 263
_CLS	<u>Class</u> Code – supplies OSPM with the PCI-defined class, subclass and programming interface for a device. Optional.	Section 6.1.3	page 264
_CPC	<u>Continuous Performance Control</u> – declares an interface that allows OSPM to transition the processor into a performance state based on a continuous range of allowable values.	Section 8.4.5.1	page 427
_CRS	<u>Current Resource Settings</u> – returns the current resource settings for a device.	Section 6.2.2	page 278
_CRT	<u>Cr</u> itical <u>Temperature</u> – returns the shutdown critical temperature.	Section 11.4.4	page 552
_CSD	<u>C State Dependencies</u> – returns a list of C-state dependencies.	Section 8.4.2.2	page 409
_CST	<u>C</u> <u>S</u> tates – returns a list of supported C-states.	Section 8.4.2.1	page 407
_CWS	<u>C</u> lear <u>W</u> ake <u>S</u> tatus – Clears the wake status of a Time and Alarm Control Method Device.	Section 9.18.6	page 494
_DBT	D ebounce T imeout -Debounce timeout setting for a GPIO input connection, resource descriptor field	<u>Section 19.5.53</u>	page 774
_DCK	<u>Dock</u> – sets docking isolation. Presence indicates device is a docking station.	Section 6.5.2	page 364
_DCS	<u>Display Current Status</u> – returns status of the display output device.	Section B.5.6	page 907

Name	Description	Heading	
_DDC	<u>D</u> isplay <u>D</u> ata <u>C</u> urrent – returns the EDID for the display output device.	Section B.5.5	page 907
_DDN	<u>D</u> os <u>D</u> evice <u>Name</u> – returns a device logical name.	Section 6.1.4	page 264
_DEC	<u>Dec</u> ode – device decoding type, resource descriptor field.	Section 19.1.8	page 709
_DEP	Operation Region <u>Dep</u> endencies evaluates to a package and designates device objects that OSPM should assign a higher priority in start ordering due to future operation region accesses.	Section 6.5.8	page 369
_DGS	<u>Display Graphics State</u> – returns the current state of the output device.	Section B.5.7	page 908
_DIS	<u>Dis</u> able – disables a device.	Section 6.2.3	page 278
_DLM	<u>Device Lock Mutex- Designates a mutex as a Device Lock</u>	Section 5.7.5	page 258
_DMA	<u>Direct Memory Access</u> – returns a device's current resources for DMA transactions.	Section 6.2.4	page 278
_DOD	<u>D</u> isplay <u>Qutput <u>D</u>evices – enumerate all devices attached to the display adapter.</u>	Section B.3.2	page 899
_DOS	<u>Disable Output Switching</u> – sets the display output switching mode.	Section B.3.1	page 898
_DPL	<u>D</u> evice Selection <u>P</u> o <u>larity</u> - The polarity of the Device Selection signal on a SPISerialBus connection, resource descriptor field	Section 19.5	page 716
_DRS	Drive Strength – Drive strength setting for a GPIO output connection, resource descriptor field	Section 19.5.54	page 775
_DSD	<u>Device Specific Data</u> — returns device-specific information.	Section 6.2.5	page 281
_DSM	<u>Device Specific Method</u> – executes device-specific functions.	<u>Section 9.14.1</u>	page 480
_DSS	<u>D</u> evice <u>S</u> et <u>S</u> tate − sets the display device state.	Section B.5.8	page 908
_DSW	<u>Device Sleep Wake</u> – sets the sleep and wake transition states for a device.	Section 7.2.1	page 375
_DTI	<u>D</u> evice <u>Temperature <u>I</u>ndication – conveys native device temperature to the platform.</u>	Section 11.4.5	page 552
_Exx	E dge GPE – method executed as a result of a general-purpose event.	Section 5.6.4.1	page 229
_EC	Embedded Controller – returns EC offset and query information.	Section 12.12	page 596
_EDL	E ject D evice L ist – returns a list of devices that are dependent on a device (docking).	Section 6.3.1	page 314
_EJD	<u>Ejection Dependent Device</u> – returns the name of dependent (parent) device (docking).	Section 6.3.2	page 315
_EJx	Eject – begin or cancel a device ejection request (docking).	Section 6.3.3	page 316
_END	Endian-ness – Endian orientation of a UART SerialBus connection, resource descriptor field	Section 19.5	page 716
_EVT	<u>Event Method</u> - Event method for GPIO-signaled events numbered larger than 255.	<u>Section 5.6.5.3</u>	page 234

Name	Description	Heading	
_FDE	<u>Floppy Disk Enumerate</u> – returns floppy disk configuration information.	Section 9.9.1	page 464
_FDI	<u>Floppy <u>D</u>rive <u>Information</u> – returns a floppy drive information block.</u>	Section 9.9.2	page 465
_FDM	<u>Floppy</u> <u>Drive</u> <u>Mode</u> – sets a floppy drive speed.	Section 9.9.3	page 466
_FIF	<u>Fan Information</u> – returns fan device information.	Section 11.3.1.1	page 544
_FIX	<u>Fix</u> ed Register Resource Provider – returns a list of devices that implement FADT register blocks.	Section 6.2.5	page 281
_FLC	<u>Fl</u> ow <u>C</u> ontrol – Flow Control mechanism for a UART SerialBus connection, resource descriptor field	Section 19.5	page 740
_FPS	<u>Fan Performance States</u> – returns a list of supported fan performance states.	<u>Section 11.3.1.2</u>	page 545
_FSL	<u>Fan Set Level</u> – Control method that sets the fan device's speed level (performance state).	<u>Section 11.3.1.3</u>	page 546
_FST	<u>Fan Status</u> – returns current status information for a fan device.	<u>Section 11.3.1.4</u>	page 546
_GAI	G et A veraging I nterval – returns the power meter averaging interval.	Section 10.4.5	page 530
_GCP	Get Capabilities – Returns the capabilities of a Time and Alarm Control Method Device	Section 9.18.2	page 491
_GHL	G et H ardware L imit – returns the hardware limit enforced by the power meter.	Section 10.4.7	page 531
_GL	<u>G</u> lobal <u>L</u> ock – OS-defined Global Lock mutex object.	Section 5.7.1	page 254
_GLK	G lobal L oc k – returns a device's Global Lock requirement for device access.	Section 6.5.7	page 368
_GPD	G et P ost D ata – returns the value of the VGA device that will be posted at boot.	Section B.3.4	page 902
_GPE	G eneral P urpose E vents − (1) predefined Scope (_GPE.)	Section 5.3.1	page 199
	(2) Returns the SCI interrupt associated with the Embedded Controller.	Section 12.11	page 594
_GRA	<u>Gra</u> nularity – address space granularity, resource descriptor field.	Section 19.1.8	page 709
_GRT	<u>Get Real Time</u> – Returns the current time from a Time and Alarm Control Method Device.	Section 9.18.3	page 492
_GSB	G lobal S ystem Interrupt B ase – returns the GSB for a I/O APIC device.	Section 6.2.7	page 285
_GTF	G et T ask E ile – returns a list of ATA commands to restore a drive to default state.	<u>Section 9.8.1.1</u>	page 458
_GTM	G et T iming M ode – returns a list of IDE controller timing information.	Section 9.8.2.1.1	page 461
_GWS	G et W ake S tatus – Gets the wake status of a Time and Alarm Control Method Device.	Section 9.18.5	page 494
_HE	<u>High-Edge</u> – interrupt triggering, resource descriptor field.	<u>Section 19.1.8</u>	page 709

Name	Description	Heading	
_HID	<u>Hardware</u> <u>ID</u> – returns a device's Plug and Play Hardware ID.	Section 6.1.5	page 265
_HOT	Hot Temperature – returns the critical temperature for sleep (entry to S4).	<u>Section 11.4.6</u>	page 552
_HPP	<u>H</u> ot <u>P</u> lug <u>P</u> arameters – returns a list of hot-plug information for a PCI device.	Section 6.2.8	page 290
_HPX	<u>H</u> ot <u>P</u> lug Parameter <u>E</u> xtensions – returns a list of hot-plug information for a PCI device. Supersedes _HPP.	Section 6.2.9	page 290
_HRV	<u>H</u> ardware <u>Revision</u> — supplies OSPM with the device's hardware revision. Optional	Section 6.1.6	page 265
_IFT	<u>IPMI Interface Type</u> . See the Intelligent Platform Management Interface Specification at "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Server Platform Management Interface Table".	Section 19.5	page 740
_INI	<u>Ini</u> tialize – performs device specific initialization.	Section 6.5.1	page 363
_INT	<u>Interrupts</u> – interrupt mask bits, resource descriptor field.	<u>Section 19.1.8</u>	page 709
_IOR	IO Restriction – IO restriction setting for a GPIO IO connection, resource descriptor field	<u>Section 19.5.54</u>	page 775
_IRC	<u>Inrush</u> <u>Current</u> – presence indicates that a device has a significant inrush current draw.	<u>Section 7.2.15</u>	page 382
_Lxx	<u>Level GPE</u> – Control method executed as a result of a general-purpose event.	<u>Section 5.6.4.1</u>	page 229
_LCK	<u>Lock</u> – locks or unlocks a device (docking).	Section 6.3.4	page 317
_LEN	<u>Len</u> gth – range length, resource descriptor field.	<u>Section 19.1.8</u>	page 709
_LID	<u>Lid</u> – returns the open/closed status of the lid on a mobile system.	Section 9.4.1	page 456
_LIN	<u>L</u> ines <u>in</u> Use - Handshake lines in use in a UART SerialBus connection, resource descriptor field	Section 19.5	page 740
_LL	<u>L</u> ow <u>L</u> evel − interrupt polarity, resource descriptor field.	<u>Section 19.1.8</u>	page 709
_MAF	<u>M</u> aximum <u>A</u> ddress <u>F</u> ixed – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_MAT	<u>Multiple Apic Table Entry</u> – returns a list of MADT APIC structure entries.	Section 6.2.10	page 294
_MAX	<u>Max</u> imum Base Address – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_MBM	<u>Memory Bandwidth Monitoring Data</u> – returns bandwidth monitoring data for a memory device.	Section 9.12.2.1	page 471
_MEM	<u>Mem</u> ory Attributes – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_MIF	<u>Mi</u> nimum Address <u>F</u> ixed – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_MIN	<u>Min</u> imum Base Address – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_MLS	<u>Multiple Language String</u> – returns a device description in multiple languages.	Section 6.1.7	page 266
_MOD	<u>Mod</u> e –Resource descriptor field	Section 19.5, Section 19.5.53	page 740 page 774
_MSG	$\underline{\textbf{\textit{M}}}$ e $\underline{\textbf{\textit{s}}}$ sa $\underline{\textbf{\textit{g}}}$ e – sets the system message waiting status indicator.	Section 9.1.2	page 447

Name	Description	Heading	
_MSM	<u>Memory Set Monitoring</u> – sets bandwidth monitoring parameters for a memory device.	Section 9.12.2.2	page 472
_MTP	<u>Memory Type</u> – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_NTT	<u>Motification <u>Temperature Threshold</u> – returns a threshold for device temperature change that requires platform notification.</u>	Section 11.4.7	page 553
_OFF	Off – sets a power resource to the off state.	Section 7.1.2	page 372
_ON	<u>On</u> – sets a power resource to the on state.	Section 7.1.3	page 373
_OS	<u>Operating System</u> – returns a string that identifies the operating system.	Section 5.7.3	page 257
_OSC	<u>Operating</u> <u>System</u> <u>Capabilities</u> – inform AML of host features and capabilities.	Section 6.2.11	page 295
_OSI	Operating System Interfaces – returns supported interfaces, behaviors, and features.	Section 5.7.2	page 254
_OST	<u>Ospm Status Indication</u> – inform AML of event processing status.	Section 6.3.5	page 317
_PAI	<u>Power Averaging Interval</u> – sets the averaging interval for a power meter.	Section 10.4.4	page 529
_PAR	Parity – Parity for a UART SerialBus connection, resource descriptor field	Section 19.5	page 740
_PCL	<u>Power Consumer List</u> – returns a list of devices powered by a power source.	Section 10.3.2	page 525
_PCT	<u>Performance</u> <u>Control</u> – returns processor performance control and status registers.	Section 8.4.4.1	page 420
_PDC	<u>Processor</u> <u>Priver</u> <u>Capabilities</u> – inform AML of processor driver capabilities.	Section 8.4.1	page 405
_PDL	<u>P</u> -state <u>D</u> epth <u>Limit</u> – returns the lowest available performance P-state.	Section 8.4.4.6	page 426
_PHA	Clock <u>Pha</u> se – Clock phase for a SPISerialBus connection, resource descriptor field	Section 19.5	page 740
_PIC	<u>PIC</u> – inform AML of the interrupt model in use.	Section 5.8.1	page 259
_PIF	<u>Power Source Information</u> – returns a Power Source information block.	Section 10.3.3	page 525
_PIN	<u>Pin List</u> – List of GPIO pins described, resource descriptor field.	<u>Section 19.5.53</u>	page 774
_PLD	Physical Location of Device – returns a device's physical location information.	Section 6.1.8	page 267
_PMC	Power Meter Capabilities – returns a list of Power Meter capabilities info.	Section 10.4.1	page 527
_PMD	<u>Power Metered Devices</u> – returns a list of devices that are measured by the power meter device.	Section 10.4.8	page 531
_PMM	<u>Power Meter Measurement</u> – returns the current value of the Power Meter.	Section 10.4.3	page 529

Name	Description	Heading		
_POL	<u>Pol</u> arity – Resource descriptor field	Section 19.5, Section 19.5.53	page 740p age 774	
_PPC	<u>Performance Present Capabilites</u> – returns a list of the performance states currently supported by the platform.	Section 8.4.4.3	page 422	
_PPE	<u>Polling for Platform Error</u> – returns the polling interval to retrieve Corrected Platform Error information.	Section 8.4.6	page 443	
_PPI	Pin Configuration – Pin configuration for a GPIO connection, resource descriptor field	Section 19.5.53	page 774	
_PR	<u>Pr</u> ocessor – predefined scope for processor objects.	Section 5.3.1	page 199	
_PR0	<u>Power Resources for DO</u> – returns a list of dependent power resources to enter state D0 (fully on).	Section 7.2.8	page 377	
_PR1	<u>Power Resources for D1</u> – returns a list of dependent power resources to enter state D1.	Section 7.2.9	page 378	
_PR2	<u>Power Resources for D2</u> – returns a list of dependent power resources to enter state D2.	<u>Section 7.2.10</u>	page 378	
_PR3	<u>Power Resources for D3hot</u> – returns a list of dependent power resources to enter state D3hot.	<u>Section 7.2.11</u>	page 379	
_PRE	<u>Power Resources for Enumeration</u> - Returns a list of dependent power resources to enumerate devices on a bus.	<u>Section 7.2.12</u>	page 379	
_PRL	<u>Power Source Redundancy List</u> – returns a list of power source devices in the same redundancy grouping.	Section 10.3.4	page 526	
_PRS	<u>Possible Resource Settings</u> – returns a list of a device's possible resource settings.	<u>Section 6.2.12</u>	page 304	
_PRT	Pci Routing Table – returns a list of PCI interrupt mappings.	Section 6.2.13	page 304	
_PRW	<u>Power Resources for Wake</u> – returns a list of dependent power resources for waking.	<u>Section 7.2.12</u>	page 379	
_PS0	Power State Q – sets a device's power state to D0 (device fully on).	Section 7.2.2	page 376	
_PS1	Power State 1 – sets a device's power state to D1.	Section 7.2.3	page 376	
_PS2	Power State 2 – sets a device's power state to D2.	Section 7.2.4	page 376	
_PS3	Power State 3 – sets a device's power state to D3 (device off).	Section 7.2.5	page 376	
_PSC	Power State Current – returns a device's current power state.	Section 7.2.6	page 377	
_PSD	<u>Power State Dependencies</u> – returns processor P-State dependencies.		page 424	
_PSE	Power State for Enumeration	<u>Section 7.2.14</u>	page 381	
_PSL	Passive List – returns a list of passive cooling device objects.	<u>Section 11.4.8</u>	page 553	
_PSR	<u>Power Source</u> – returns the power source device currently in use.	Section 10.3.1	page 524	
_PSS	<u>Performance Supported States</u> – returns a list of supported processor performance states.	Section 8.4.4.2	page 420	
_PSV	<u>Passive</u> – returns the passive trip point temperature.	<u>Section 11.4.9</u>	page 553	
_PSW	Power State Wake – sets a device's wake function.	<u>Section 7.2.14</u>	page 381	

ACPI Software Programming Model

Name	Description	Heading	
_PTC	<u>Processor Throttling Control</u> – returns throttling control and status registers.	Section 8.4.3.1	page 412
_PTP	<u>Power Trip Points</u> – sets trip points for the Power Meter device.	Section 10.4.2	page 528
_PTS	<u>Prepare To Sleep</u> – inform the platform of an impending sleep transition.	Section 7.3.1	page 387
_PUR	<u>Processor</u> <u>Utilization</u> <u>Request</u> – returns the number of processors that the platform would like to idle.	Section 8.5.1.1	page 444
_PXM	Proximity – returns a device's proximity domain identifier.	Section 6.2.14	page 306
_Q <i>xx</i>	Q uery – Embedded Controller query and SMBus Alarm control method.	Section 5.6.4.1	page 229
_RBO	Register Bit Offset – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_RBW	Register Bit Width – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_REG	Reg ion – inform AML code of an operation region availability change.	Section 6.5.4	page 365
_REV	Rev ision – returns the revision of the ACPI specification that is implemented.	Section 5.7.4	page 257
_RMV	<u>Remove</u> – returns a device's removal ability status (docking).	Section 6.3.6	page 323
_RNG	Range – memory range type, resource descriptor field.	<u>Section 19.1.8</u>	page 709
_ROM	<u>Read-Qnly Memory</u> – returns a copy of the ROM data for a display device.	Section B.3.3	page 902
_RT	Resource Type – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_RTV	<u>Relative Temperature Values</u> – returns temperature value information.	<u>Section 11.4.10</u>	page 554
_RW	<u>Read-Write Status</u> – resource descriptor field.	<u>Section 19.1.8</u>	page 709
_RXL	<u>Receive Buffer Size</u> - Size of the receive buffer in a UART Serialbus connection, resource descriptor field.	Section 19.5	page 740
_S0	SO System State – returns values to enter the system into the SO state.	Section 7.3.2	page 387
_S1	<u>\$1</u> System State – returns values to enter the system into the S1 state.	Section 7.3.2	page 387
_S2	<u>\$2</u> System State – returns values to enter the system into the S2 state.	Section 7.3.2	page 387
_S3	<u>\$3</u> System State – returns values to enter the system into the S3 state.	Section 7.3.2	page 387
_S4	<u>\$4</u> System State – returns values to enter the system into the \$4 state.	Section 7.3.2	page 387
_S5	<u>\$5</u> System State – returns values to enter the system into the S5 state.	Section 7.3.2	page 387
_S1D	<u>\$1</u> <u>Device State</u> – returns the highest D-state supported by a device when in the S1 state.	<u>Section 7.2.16</u>	page 382
_S2D	<u>\$2</u> <u>D</u> evice State – returns the highest D-state supported by a device when in the S2 state.	Section 7.2.17	page 383

Name	Description	Heading	
_S3D	<u>S3 Device State</u> – returns the highest D-state supported by a device when in the S3 state.	Section 7.2.18	page 383
_S4D	<u>S4</u> <u>D</u> evice State – returns the highest D-state supported by a device when in the S4 state.	Section 7.2.19	page 384
_S0W	<u>\$0</u> Device <u>W</u> ake State – returns the lowest D-state that the device can wake itself from S0.	Section 7.2.20	page 385
_S1W	<u>\$1</u> Device <u>W</u> ake State – returns the lowest D-state for this device that can wake the system from \$1.	<u>Section 7.2.21</u>	page 385
_S2W	<u>\$2</u> Device <u>W</u> ake State – returns the lowest D-state for this device that can wake the system from \$2.	Section 7.2.22	page 385
_S3W	<u>\$3</u> Device <u>W</u> ake State – returns the lowest D-state for this device that can wake the system from \$3.	Section 7.2.23	page 386
_S4W	<u>\$4</u> Device <u>W</u> ake State – returns the lowest D-state for this device that can wake the system from \$4.	Section 7.2.24	page 386
_SB	System Bus – scope for device and bus objects.	Section 5.3.1	page 199
_SBS	<u>S</u> mart <u>B</u> attery <u>S</u> ubsystem – returns the subsystem configuration.	Section 10.1.3	page 508
_SCP	<u>Set</u> <u>Cooling</u> <u>Policy</u> – sets the cooling policy (active or passive).	Section 11.4.11	page 554
_SDD	<u>Set Device Data</u> – sets data for a SATA device.	Section 9.8.3.3.1	page 464
_SEG	<u>Seg</u> ment – returns a device's PCI Segment Group number.	Section 6.5.6	page 367
_SHL	<u>Set Hardware Limit</u> – sets the hardware limit enforced by the Power Meter.	Section 10.4.6	page 530
_SHR	<u>Sh</u> a <u>r</u> able – interrupt share status, resource descriptor field.	<u>Section 19.1.8</u>	page 709
_SI	<u>S</u> ystem <u>I</u> ndicators – predefined scope.	Section 5.3.1	page 199
_SIZ	<u>Siz</u> e – DMA transfer size, resource descriptor field.	<u>Section 19.1.8</u>	page 709
_SLI	<u>System Locality Information</u> – returns a list of NUMA system localities.	Section 6.2.15	page 307
_SLV	<u>Slave Mode</u> – Slave mode setting for a SerialBus connection, resource descriptor field.		page 740
_SPD	<u>Set Post Device</u> – sets which video device will be posted at boot.		page 903
_SPE	Connection Speed – Connection speed for a SerialBus connection, resource descriptor field		page 740
_SRS	<u>Set Resource</u> Settings – sets a device's resource allocation.	Section 6.2.16	page 310
_SRT	<u>Set Real Time</u> – Sets the current time to a Time and Alarm Control Method Device. Section 9.18.4		page 492
_SRV	IPMI <u>Spec Revision</u> . See the Intelligent Platform Management Interface Specification at "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Server Platform Management Interface Table".		
_SST	System Status – sets the system status indicator.	Section 9.1.1	page 447
_STA	<u>Sta</u>tus – (1) returns the current status of a device.(2) Returns the current on or off state of a Power Resource.	Section 6.3.7 Section 7.1.4	page 323 page 373

ACPI Software Programming Model

Name	Description	Heading	
_STB	Stop Bits - Number of stop bits used in a UART SerialBus connection, resource descriptor field	Section 19.5	page 740
_STM	<u>Set Timing</u> <u>Mode</u> – sets an IDE controller transfer timings.	Section 9.8.2.1.2	page 462
_STP	<u>Set Expired Timer Wake Policy</u> – sets expired timer policies of the wake alarm device.	Section 9.18.7	page 494
_STR	<u>Str</u> ing – returns a device's description string.	<u>Section 6.1.10</u>	page 275
_STV	S et T imer V alue – set timer values of the wake alarm device.	<u>Section 9.18.8</u>	page 495
_SUB	Supplies OSPM with the device's Subsystem ID. Optional.	Section 6.1.9	page 274
_SUN	<u>S</u> lot <u>U</u> ser <u>N</u> umber – returns the slot unique ID number.	<u>Section 6.1.11</u>	page 275
_SWS	S ystem W ake S ource – returns the source event that caused the system to wake.	Section 7.3.3	page 393
_T_x	<u>Temporary</u> – reserved for use by ASL compilers.	Section 19.2.1.1	page 716
_TC1	<u>Thermal Constant 1</u> – returns TC1 for the passive cooling formula.	<u>Section 11.4.12</u>	page 557
_TC2	<u>Thermal Constant 2</u> – returns TC2 for the passive cooling formula.	<u>Section 11.4.13</u>	page 557
_TDL	<u>T</u> -State <u>Depth Limit</u> – returns the _TSS entry number of the lowest power throttling state.	Section 8.4.3.5	page 419
_TIP	Expired <u>Ti</u> mer Wake <u>P</u> olicy – returns timer policies of the wake alarm device.	Section 9.18.9	page 495
_TIV	<u>Timer Values</u> – returns remaining time of the wake alarm device.	Section 9.18.10	page 496
_TMP	<u>Temp</u> erature – returns a thermal zone's current temperature.	<u>Section 11.4.14</u>	page 558
_TPC	<u>Throttling Present Capabilities</u> – returns the current number of supported throttling states.	Section 8.4.3.3	page 415
_TPT	<i>Irip Point Iemperature</i> – inform AML that a devices' embedded temperature sensor has crossed a temperature trip point.		page 558
_TRA	<u>Translation</u> – address translation offset, resource descriptor field.	Section 19.1.8	page 709
_TRS	<u>Tr</u> anslation <u>S</u> parse – sparse/dense flag, resource descriptor field.	Section 19.1.8	page 709
_TRT	<u>Thermal Relationship Table</u> – returns thermal relationships between platform devices.		page 558
_TSD	<u>Throttling State Dependencies</u> – returns a list of T-state dependencies.		page 415
_TSF	Type-Specific Flags – resource descriptor field. Section 19.1.		page 709
_TSP	<u>Thermal Sampling Period</u> – returns the thermal sampling Section 11.4.17 period for passive cooling.		page 559
_TSS	<u>Throttling Supported States</u> – returns supported throttling state information. <u>Section 8.4.3.2</u>		page 413
_TST	<u>Temperature Sensor Threshold</u> – returns the minimum separation for a device's temperature trip points.	<u>Section 11.4.18</u>	page 559

Name	Description	Heading	
_TTP	<u>Iranslation Iype</u> – translation/static flag, resource descriptor field.	Section 19.1.8	page 709
_TTS	<u>I</u> ransition <u>I</u> o <u>S</u> tate – inform AML of an S-state transition.	Section 7.3.4	page 394
_TXL	<u>Iransmit Buffer Size</u> – Size of the transmit buffer in a UART Serialbus connection, resource descriptor field	Section 19.5	page 740
_TYP	<u>Type</u> – DMA channel type (speed), resource descriptor field.	<u>Section 19.1.8</u>	page 709
_TZ	<u>T</u> hermal <u>Z</u> one – predefined scope: ACPI 1.0.	Section 5.3.1	page 199
_TZD	<u>Thermal</u> <u>Zone</u> <u>Devices</u> – returns a list of device names associated with a Thermal Zone.	<u>Section 11.4.19</u>	page 560
_TZM	<u>Thermal</u> <u>Zone</u> <u>Member</u> – returns a reference to the thermal zone of which a device is a member.	Section 11.4.20	page 560
_TZP	<u>Thermal</u> <u>Zone</u> <u>Polling</u> – returns a Thermal zone's polling frequency.	Section 11.4.21	page 560
_UID	<u>U</u> nique <u>ID</u> – return a device's unique persistent ID.	<u>Section 6.1.12</u>	page 276
_UPC	<u>U</u> SB <u>P</u> ort <u>C</u> apabilities – returns a list of USB port capabilities.	Section 9.13	page 474
_UPD	<u>U</u> ser <u>P</u> resence <u>D</u> etect – returns user detection information. <u>Section 9.16.1</u>		page 486
_UPP	<u>U</u> ser <u>P</u> resence <u>P</u> olling – returns the recommended user presence polling interval.	Section 9.16.2	page 486
_VEN	Vendor-defined Data – Vendor-defined data for a GPIO or Section SerialBus connection, resource descriptor field Section		page 774
_VPO	<u>V</u> ideo <u>P</u> ost <u>O</u> ptions – returns the implemented video post options.		page 903
_WAK	<u>Wak</u> e – inform AML that the system has just awakened. <u>Section 7.3.5</u>		page 394
_Wxx	<u>W</u> ake Event – method executed as a result of a wake event. <u>Section 5.6.4.2.2</u>		

5.7 Predefined Objects

The AML interpreter of an ACPI compatible operating system supports the evaluation of a number of predefined objects. The objects are considered "built in" to the AML interpreter on the target operating system.

A list of predefined object names are shown in the following table.

Table 5-150 Predefined Object Names

Name	Description	
_GL	Global Lock mutex	
_OS	Name of the operating system	
_OSI	Operating System Interface support	
_REV	Revision of the ACPI specification that is implemented	

5.7.1 _GL (Global Lock Mutex)

This predefined object is a Mutex object that behaves like a Mutex as defined in Section 19.5.85, "Mutex (Declare Synchronization/Mutex Object)," with the added behavior that acquiring this Mutex also acquires the shared environment Global Lock defined in Section 5.2.10.1, "Global Lock." This allows Control Methods to explicitly synchronize with the Global Lock if necessary.

5.7.2 OSI (Operating System Interfaces)

This object provides the platform with the ability to query OSPM to determine the set of ACPI related interfaces, behaviors, or features that the operating system supports.

The _OSI method has one argument and one return value. The argument is an OS vendor defined string representing a set of OS interfaces and behaviors or an ACPI defined string representing an operating system and an ACPI feature group of the form, "OSVendorString-FeatureGroupString".

Arguments: (1)

Arg0 – A **String** containing the OS interface / behavior compatibility string or the Feature Group string, as defined in <u>Section 5-152</u>, or the "OS Vendor String Prefix – OS Vendor Specific String". OS Vendor String Prefixes are defined in <u>Section 5-151</u>

Return Value:

An **Integer** containing a Boolean that indicates whether the requested feature is supported:

0x0 – The interface, behavior, or feature is not supported

0xFFFFFFF - The interface, behavior, or feature is supported

OSPM may indicate support for multiple OS interface / behavior strings if the operating system supports the behaviors. For example, a newer version of an operating system may indicate support for strings from all or some of the prior versions of that operating system.

_OSI provides the platform with the ability to support new operating system versions and their associated features when they become available. OSPM can choose to expose new functionality based on the _OSI argument string. That is, OSPM can use the strings passed into _OSI to ensure compatibility between older platforms and newer operating systems by maintaining known compatible behavior for a platform. As such, it is recommended that _OSI be evaluated by the _SB.INI control method so that platform compatible behavior or features are available early in operating system initialization.

Since feature group functionality may be dependent on OSPM implementation, it may be required that OS vendor-defined strings be checked before feature group strings.

Platform developers should consult OS vendor specific information for OS vendor defined strings representing a set of OS interfaces and behaviors. ACPI defined strings representing an operating system and an ACPI feature group are listed in the following tables.

Table 5-151 Operating System Vendor Strings

Operating System Vendor String Prefix	Description
"FreeBSD"	Free BSD
"HP-UX"	HP Unix Operating Environment

Operating System Vendor String Prefix	Description
"Linux"	GNU/Linux Operating system
"OpenVMS"	HP OpenVMS Operating Environment
"Windows"	Microsoft Windows

Table 5-152 Feature Group Strings

Feature Group String	Description
"Module Device"	OSPM supports the declaration of module device (ACPI0004) in the namespace and will enumerate objects under the module device scope.
"Processor Device"	OSPM supports the declaration of processors in the namespace using the ACPI0007 processor device HID.
"3.0 Thermal Model"	OSPM supports the extensions to the ACPI thermal model in Revision 3.0.
"Extended Address Space Descriptor"	OSPM supports the Extended Address Space Descriptor
"3.0 _SCP Extensions"	OSPM evaluates _SCP with the additional acoustic limit and power limit arguments defined in ACPI 3.0.
"Processor Aggregator Device"	OSPM supports the declaration of the processor aggregator device in the namespace using the ACPI000C processor aggregator device HID.

_OSI Example ASL using OS vendor defined string:

```
Scope (_SB) //Scope
   Name (TOOS, 0)
                                        // Global variable for type of OS.
   \ensuremath{//} This methods sets the "TOOS" variable depending on the type of OS
    // installed on the system.
    // TOOS = 1
                                        // Windows 98 & SE
    // TOOS = 2
                                        // Windows Me.
    // TOOS = 3
                                        // Windows 2000 OS or above version.
    // TOOS = 4
                                        // Windows XP OS or above version.
    Method (_INI)
        If (CondRefOf (_OSI,Local0))
            If (\_OSI ("Windows 2001"))
                Store(4, TOOS)
        }
        Else
            Store (\_OS, local0)
            If (LEqual (local0, "Microsoft Windows NT"))
                Store (3, TOOS)
            ElseIf (LEqual (Local0, "Microsoft Windows"))
                Store (1, TOOS)
            ElseIf (LEqual (Local0, "Microsoft WindowsME:Millennium Edition"))
                Store (2, TOOS)
        }
   }
}
```

_OSI Example ASL using an ACPI defined string:

```
DefinitionBlock ("MD1SSDT.aml", "OEM1", 0x02,
            "OEMID", "Table1", 0) {
    Scope(\_SB) {
        Device (\_SB.NOD0) {
              Name (_HID, "ACPI0004") // Module device
               Name (_UID, 0)
               Name (_PRS, ResourceTemplate() {...})
               Method (_SRS, 1) {...}
              Method (_CRS, 0) {...}
               Device (PCIO) { // PCI Root Bridge
                Name (_HID, EISAID("PNP0A03"))
                Name (_UID, 0)
                Name (\_BBN, 0x00)
                Name (_PRS, ResourceTemplate () {...})
            } // end of PCI Root Bridge
          } // end of Module device
     } // end of \_SB Scope
} // end of Definition Block
DefinitionBlock ("MD1SSDT.aml", "OEM1", 0x02,
            "OEMID", "Table2", 0) {
    Scope(\_SB) {
         Device (PCI0) { // PCI Root Bridge
               Name (_HID, EISAID("PNP0A03"))
               Name (_UID, 0)
               Name (\_BBN, 0x00)
               Name (_PRS, ResourceTemplate () {...})
          } // end of PCI Root Bridge
     } // end of \_SB Scope
} // end of Definition Block
```

5.7.3 _OS (OS Name Object)

This predefined object evaluates to a string that identifies the operating system. In robust OSPM implementations, _OS evaluates differently for each OS release. This may allow AML code to accommodate differences in OSPM implementations. This value does not change with different revisions of the AML interpreter.

Arguments:

None

Return Value:

A **String** containing the operating system name.

5.7.4 _REV (Revision Data Object)

This predefined object evaluates to the revision of the ACPI Specification that the specified _OS implements as a DWORD. Larger values are newer revisions of the ACPI specification.

Arguments:

None

Return Value:

An **Integer** containing the revision of the currently executing ACPI implementation

5.7.5 _DLM (DeviceLock Mutex)

This object appears in a device scope when AML access to the device must be synchronized with the OS environment. It is used in conjunction with a standard Mutex object. With _DLM, the standard Mutex provides synchronization within the AML environment as usual, but also synchronizes with the OS environment.

_DLM evaluates to a package of packages, each containing a reference to a Mutex and an optional resource template protected by the Mutex, If only the Mutex name is specified, then the sharing rules (i.e. which resources are protected by the lock) are defined by a predefined contract between the AML and the OS device driver. If the resource template is specified, then only those resources within the resource template are protected.

Arguments:

None

Return Value:

A variable-length **Package** containing sub-**packages** of Mutex **References** and resource templates. The resource template in each subpackage is optional.

Return Value Information

```
Package {
    DeviceLockInfo [0] // Package
    . . .
    DeviceLockInfo [n] // Package
```

Each variable-length DeviceLockInfo sub-**Package** contains either one element or 2 elements, as described below:

Table 5-153 DeviceLockInfo Package Values

Element	Object Type	Description
DeviceLockMutex	Reference	A reference to the mutex that is to be shared between the AML code and the host operating system.
Resources	Buffer (or reference to a Buffer)	Optional. Contains a Resource Template that describes the resources that are to be protected by the Device Lock Mutex.

Example:

```
Device (DEV1)
    Mutex (MTX1, 0)
    Name (RES1, ResourceTemplate ()
        I2cSerialBus (0x0400, DeviceInitiated, 0x00001000,
            AddressingMode10Bit, "\\_SB.DEV1",
            0, ResourceConsumer, I2C1)
    })
    Name (_DLM, Package (1)
        Package (2)
            MTX1,
            RES1
    })
Device (DEV2)
    Mutex (MTX2, 0)
    Mutex (MTX3, 0)
    Name (_DLM, Package (2)
        Package (2)
            \DEV2.MTX2,
            ResourceTemplate ()
                I2cSerialBus (0x0400, DeviceInitiated, 0x00001000,
                    AddressingMode10Bit, "\\ SB.DEV2",
                    0, ResourceConsumer, I2C2)
        Package (1) // Optional resource not needed
            \DEV2.MTX3
    })
```

5.8 System Configuration Objects

5.8.1 _PIC Method

The _PIC optional method is used to report to the BIOS the current interrupt model used by the OS. This control method returns nothing. The argument passed into the method signifies the interrupt model OSPM has chosen, PIC mode, APIC mode, or SAPIC mode. Notice that calling this method is optional for OSPM. If the method is never called, the BIOS must assume PIC mode. It is important that the BIOS save the value passed in by OSPM for later use during wake operations.

Arguments: (1)

Arg0 – An **Integer** containing a code for the current interrupt model:

ACPI Software Programming Model

0 – PIC mode
1 – APIC mode
2 – SAPIC mode

Other values –Reserved

Return Value:

None

Device Configuration

This section specifies the objects OSPM uses to configure devices. There are three types of configuration objects:

- Device identification objects associate platform devices with Plug and Play IDs.
- Device configuration objects declare and configure hardware resources and characteristics for devices enumerated via ACPI.
- Device insertion and removal objects provide mechanisms for handling dynamic insertion and removal of devices.

This section also defines the ACPI device—resource descriptor formats. Device—resource descriptors are used as parameters by some of the device configuration objects.

6.1 Device Identification Objects

Device identification objects associate each platform device with a Plug and Play device ID for each device. All the device identification objects are listed in the table below:

Table 6-154 Device Identification Objects

Object	Description
_ADR	Object that evaluates to a device's address on its parent bus.
_CCA	Cache Coherency Attribute specifies whether a device and its descendants support hardware managed cache coherency.
_CID	Object that evaluates to a device's Plug and Play-compatible ID list.
_CLS	Object that evaluates to a package of coded device-class information.
_DDN	Object that associates a logical software name (for example, COM1) with a device.
_HID	Object that evaluates to a device's Plug and Play hardware ID.
_HRV	Object that evaluates to an integer hardware revision number.
_MLS	Object that provides a human readable description of a device in multiple languages.
_PLD	Object that provides physical location description information.
_PRD	Object that evaluates to a package of device property subpackages.
_SUB	Object that evaluates to a device's Plug and Play subsystem ID.
_SUN	Object that evaluates to the slot-unique ID number for a slot.
_STR	Object that contains a Unicode identifier for a device.
_UID	Object that specifies a device's unique persistent ID, or a control method that generates it.

For any device that is not on an enumerable type of bus (for example, an ISA bus), OSPM enumerates the devices' Plug and Play ID(s) and the ACPI BIOS must supply an _HID object (plus an optional CID object) for each device to enable OSPM to do that. For devices on an enumerable

Device Configuration

type of bus, such as a PCI bus, the ACPI system must identify which device on the enumerable bus is identified by a particular Plug and Play ID; the ACPI BIOS must supply an _ADR object for each device to enable this. A device object must contain either an _HID object or an _ADR object, but can contain both.

If any of these objects are implemented as control methods, these methods may depend on operation regions. Since the control methods may be evaluated before an operation region provider becomes available, the control method must be structured to execute in the absence of the operation region provider. (_REG methods notify the BIOS of the presence of operation region providers.) When a control method cannot determine the current state of the hardware due to a lack of operation region provider, it is recommended that the control method should return the condition that was true at the time that control passed from the BIOS to the OS. (The control method should return a default, boot value).

6.1.1 _ADR (Address)

This object is used to supply OSPM with the address of a device on its parent bus. An _ADR object must be used when specifying the address of any device on a bus that has a standard enumeration algorithm (see Section 3.7, "Configuration and Plug and Play", for the situations when these devices do appear in the ACPI namespace).

Arguments:

None

Return Value:

An Integer containing the address of the device

An _ADR object can be used to provide capabilities to the specified address even if a device is not present. This allows the system to provide capabilities to a slot on the parent bus.

OSPM infers the parent bus and segment from the location of the _ADR object's device package in the ACPI namespace. For more information about the positioning of device packages in the ACPI namespace, see <u>Section 19.5.30</u>, "Device (Declare Bus/Device Package)"

_ADR object information must be static and can be defined for the following bus types listed in <u>Table 6-155</u>.

BUS	Address Encoding
EISA	EISA slot number 0–F
Floppy Bus	Drive select values used for programming the floppy controller to access the specified INT13 unit number. The _ADR Objects should be sorted based on drive select encoding from 0-3.
IDE Controller	0-Primary Channel, 1-Secondary Channel
IDE Channel	0-Master drive, 1-Slave drive
Intel® High Definition Audio	High word – SDI (Serial Data In) ID of the codec that contains the function group. Low word – Node ID of the function group.

BUS	Address Encoding
PCI	High word–Device #, Low word–Function #. (for example, device 3, function 2 is 0x00030002). To refer to all the functions on a device #, use a function number of FFFF).
PCMCIA	Socket #; 0-First Socket
PC CARD	Socket #; 0–First Socket
Serial ATA	SATA Port: High word—Root port #, Low word—port number off of a SATA port multiplier, or 0xFFFF if no port multiplier attached. (For example, root port 2 would be 0x0002FFFF. If instead a port multiplier had been attached to root port 2, the ports connected to the multiplier would be encoded 0x00020000, 0x00020001, etc.) The value 0xFFFFFFF is reserved.
SMBus	Lowest Slave Address
USB Root HUB	Only one child of the host controller. It must have an _ADR of 0. No other children or values of _ADR are allowed.
USB Ports	Port number (1-n)
SDIO Bus	High word - Slot number (0-First Slot) Low word - Function number (see SD specification for definitions.)

6.1.2 _CID (Compatible ID)

This optional object is used to supply OSPM with a device's Plug and Play-Compatible Device ID. Use _CID objects when a device has no other defined hardware standard method to report its compatible IDs.

Arguments:

None

Return Value:

An **Integer** or **String** containing a single CID or a **Package** containing a list of CIDs

A CID object evaluates to either:

- A single Compatible Device ID
- A package of Compatible Device IDs for the device in the order of preference, highest preference first.

Each Compatible Device ID must be either:

- A valid HID value (a 32-bit compressed EISA type ID or a string such as "ACPI0004").
- A string that uses a bus-specific nomenclature. For example, _CID can be used to specify the PCI ID. The format of a PCI ID string is one of the following:

```
"PCI\CC_ccss"

"PCI\CC_ccsspp"

"PCI\VEN_vvvv&DEV_dddd&SUBSYS_sssssss&REV_rr"

"PCI\VEN_vvvv&DEV_dddd&SUBSYS_ssssssss"

"PCI\VEN_vvvv&DEV_dddd&REV_rr"

"PCI\VEN_vvvv&DEV_dddd"
```

Device Configuration

cc	 hexadecimal representation of the Class Code byte
SS	- hexadecimal representation of the Subclass Code byte
pp	- hexadecimal representation of the Programming Interface byte
vvvv	- hexadecimal representation of the Vendor ID
dddd	 hexadecimal representation of the Device ID
SSSSSSS	- hexadecimal representation of the Subsystem ID
rr	 hexadecimal representation of the Revision byte

A compatible ID retrieved from a _CID object is only meaningful if it is a non-NULL value.

Example ASL:

6.1.3 _CLS (Class Code)

This object is used to supply OSPM with the PCI-defined class, subclass and programming interface for a device. This object is optional but may be useful for generic drivers written for PCI devices that move off of PCI and are enumerated by ACPI.

Arguments:

None

Return Value:

A **Package** containing the PCI class information as a list of **Integers**.

A list of available class codes and programming interface codes is provided by the PCI SIG.

Example ASL:

```
Name (_CLS, Package (3) {
      0x3A02,
      0x7780,
      9,
})
```

6.1.4 _DDN (DOS Device Name)

This object is used to associate a logical name (for example, COM1) with a device. This name can be used by applications to connect to the device.

Arguments:

None

Return Value:

A String containing the DOS device name

6.1.5 HID (Hardware ID)

This object is used to supply OSPM with the device's PNP ID or ACPI ID. 1

When describing a platform, use of any _HID objects is optional. However, a _HID object must be used to describe any device that will be enumerated by OSPM. OSPM only enumerates a device when no bus enumerator can detect the device ID. For example, devices on an ISA bus are enumerated by OSPM. Use the _ADR object to describe devices enumerated by bus enumerators other than OSPM.

Arguments:

None

Return Value:

An Integer or String containing the HID

- A _HID object evaluates to either a numeric 32-bit compressed EISA type ID or a string. If a string, the format must be an alphanumeric PNP or ACPI ID with no asterisk or other leading characters.
- A valid PNP ID must be of the form "AAA####" where A is an uppercase letter and # is a hex digit. A valid ACPI ID must be of the form "NNNN####" where N is an uppercase letter or a digit ('0'-'9') and # is a hex digit. This specification reserves the string "ACPI" for use only with devices defined herein. It further reserves all strings representing 4 HEX digits for exclusive use with PCI-assigned Vendor IDs.

Example ASL:

```
Name (_HID, EISAID ("PNPOCOC")) // Control-Method Power Button
Name (_HID, EISAID ("INTO800")) // Firmware Hub
Name (_HID, "ACPI0003") // AC adapter device
Name (_HID, "MSFT0003") // Vendor-defined device
Name (_HID, "80860003") // PCI-assigned device identifier
```

6.1.6 _HRV (Hardware Revision)

This object is used to supply OSPM with the device's hardware revision. The use of _HRV is optional.

Arguments:

None

Return Value:

An **Integer** (**DWORD**) containing the hardware revision number

^{1.} PNP ID and ACPI ID Registry is at http://www.uefi.org/PNP ACPI Registry.

Example ASL:

Name (_HRV, 0x0003)// Revision number 3 of this hardware device

6.1.7 _MLS (Multiple Language String)

The _MLS object provides OSPM a human readable description of a device in multiple languages. This information may be provided to the end user when the OSPM is unable to get any other information about this device. Although this functionality is also provided by the _STR object, _MLS expands that functionality and provides vendors with the capability to provide multiple strings in multiple languages. The _MLS object evaluates to a package of packages. Each subpackage consists of a Language identifier and corresponding unicode string for a given locale. Specifying a language identifier allows OSPM to easily determine if support for displaying the Unicode string is available. OSPM can use this information to determine whether or not to display the device string, or which string is appropriate for a user's preferred locale.

It is assumed that OSPM will always support the primary English locale to accommodate English embedded in a non-English string, such as a brand name.

If OSPM doesn't support the specific sub-language ID it may choose to use the primary language ID for displaying device text.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of language descriptor **Packages** as described below.

Return Value Information

Each Language Descriptor sub-**Package** contains the elements described below:

LanguageId is a string identifying the language. This string follows the format specified in the Internet RFC 3066 document (Tags for the Identification of Languages). In addition to supporting the existing strings in RFC 3066, Table 6-156 lists aliases that are also supported.

Table 6-156 Additional Language ID Alias Strings

RFC String	Supported Alias String				
zh-Hans	zh-chs				
zh-Hant	zh-cht				

UnicodeDescription is a Buffer containing a Unicode (UTF-16) string. This string contains the language-specific description of the device corresponding to the LanguageID. The Unicode() ASL macro can be used to create this Buffer.

Example:

```
Device (XYZ) {
    Name (_ADR, 0x00020001)
    Name ( _MLS, Package(){(2){"en", Unicode("ACME super DVD controller")}})
}
```

6.1.8 PLD (Physical Location of Device)


This optional object is a method that conveys to OSPM a general description of the physical location of a device's external connection point. The _PLD may be child object for any ACPI Namespace object the system wants to describe. This information can be used by system software to describe to the user which specific connector or device input mechanism may be used for a given task or may need user intervention for correct operation. The _PLD should only be evaluated when its parent device is present as indicated by the device's presence mechanism (i.e. STA or other)


An externally exposed device connection point can reside on any surface of a system's housing. The respective surfaces of a system's housing are identified by the "Panel" field (described below). The _PLD method returns data to describe the location of where the device's connection point resides and a Shape (described below) that may be rendered at that position. One physical device may have several connection points. A _PLD describes the offset and rotation of a single device connection point from an "origin" that resides in the lower left hand corner of its Panel.

All Panel references (Top, Bottom, Right, Left, etc.) are interpreted as though the user is facing the front of the system. For handheld mobile devices, the front panel is the one holding the display screen, and its origin is in the lower-left corner when the display is viewed in the Portrait orientation. For example, the Right Panel is the right side of the system as viewed from the front.

All "origin" references for a Panel are interpreted as its lower left corner when the user is facing the respective Panel. The Top Panel shall be viewed with the system is viewed resting on its Front Panel, and the Bottom Panel shall be viewed with the system resting on its Back Panel. All other Panels shall be viewed with the system resting on its Bottom Panel. Refer to <u>Figure 6-32</u> for more information.


Figure 6-32 System Panel and Panel Origin Positions





The data bits also assume that if the system is capable of opening up like a laptop that the device may exist on the base of the laptop system or on the lid. In the case of the latter, the "Lid" bit (described below) should be set indicating the device connection point is on the lid. If the device is on the lid, the description describes the device's connection point location when the system is opened with the lid up. If the device connection point is not on the lid, then the description describes the device's connection point location when the system with the lid closed.

Figure 6-33 Laptop Panel and Panel Origin Positions



To render a view of a system Panel, all _PLDs that define the same Panel and Lid values are collected. The _PLDs are then sorted by the value of their Order field and the view of the panel is rendered by drawing the shapes of each connection point (in their correct Shape, Color, Horizontal Offset, Vertical Offset, Width, Height, and Orientation) starting with all Order = 0 _PLDs first. Refer to Figure 6-35 for an example.

The location of a device connection point may change as a result of the system connecting or disconnecting to a docking station or a port replicator. As such, Notify event of type 0x09 will cause OSPM to re-evaluate the _PLD object residing under the particular device notified. If a platform is unable to detect the change of connecting or disconnecting to a docking station or port replicator, a _PLD object should not be used to describe the device connection points that will change location after such an event.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **Buffers**

This method returns a package containing a single or multiple buffer entries. At least one buffer entry must be returned using the bit definitions below.

Buffer 0 Return Value:

Name	Definition	DWORD	Bit Offset (DWORD)	Bit Offset (Buffer)	Length (bits)	
Revision	The current Revision is 0x2	0	0	0	7	
Ignore Color	If this bit is set, the Color field is ignored, as the color is unknown.	0	7	7	1	
Color	24-bit RGB value for the color of the device connection point. Bits 8:15=red value Bits 16:23=green value Bits 24:31=blue value	0	8	8	24	
Width	Width of the widest point of the device connection point, in millimeters	1	0	32	16	
Height	Height of the tallest point of the device connection point, in millimeters	1	16	48	16	
User Visible	Set if the device connection point can be seen by the user without disassembly.	2	0	64	1	
Dock	Set if the device connection point resides in a docking station or port replicator.	2		65	1	
Lid	Set if this device connection point resides on the lid of laptop system.	2		66	1	
Panel	Describes which panel surface of the system's housing the device connection point resides on. 0 – Top 1 – Bottom 2 – Left 3 – Right 4 – Front 5 – Back 6 – Unknown (Vertical Position and	2		67	3	


Device Configuration

	I			ı
Vertical Position on the panel where the device connection point resides.	0 – Upper 1 – Center 2 – Lower	2	70	2
Horizontal Position on the panel where the device connection point resides.		2	72	2
Shape	Describes the shape of the device connection point. The Width and Height fields may be used to distort a shape, e.g. A Round shape will look like an Oval shape if the Width and Height are not equal. And a Vertical Rectangle or Horizontal Rectangle may look like a square if Width and Height are equal. Refer to Figure 6-34. 0 – Round 1 – Oval 2 – Square 3 – Vertical Rectangle 4 – Horizontal Rectangle 5 – Vertical Trapezoid 6 – Horizontal Trapezoid 7 – Unknown – Shape rendered as a Rectangle with dotted lines 8 – Chamfered 15:9 – Reserved	2	74	4
Group Orientation	if Set, indicates vertical grouping, otherwise horizontal is assumed.	2	78	1
Group Token	Unique numerical value identifying a group.	2	79	1
Group Position	Identifies this device connection point's position in the group (i.e. 1 st , 2 nd)	2	87	8
Bay	Set if describing a device in a bay or if device connection point is a bay.	2	95	1

Ejectable	Set if the device is ejectable. Indicates ejectability in the absence of _EJx objects.	2	96	1
OSPM Ejection required	OSPM Ejection required: Set if OSPM needs to be involved with ejection process. User-operated physical hardware ejection is not possible.	2	97	1
Cabinet Number	For single cabinet system, this field is always 0.	2	98	8
Card Cage Number	For single card cage system, this field is always 0.	2	106	8
reference	if Set, this _PLD defines a "reference" shape that is used to help orient the user with respect to the other shapes when rendering _PLDs.	2	114	1
Rotation	Rotates the Shape clockwise in 45 degree steps around its origin where: 0 - 0° 1 - 45° 2 - 90° 3 - 135° 4 - 180° 5 - 225° 6 - 270° 7 - 315°	2	115	4
Order	Identifies the drawing order of the connection point described by a _PLD. Order = 0 connection points are drawn before Order = 1 connection points. Order = 1 before Order = 2, and so on. Order = 31 connection points are drawn last. Order should always start at 0 and be consecutively assigned.	2	119	5
Reserved	Reserved, must contain a value of 0.	2	124	4
Vertical Offset	Offset of Shape Origin from Panel Origin (in mm). A value of 0xFFFFFFF indicates that this field is not supplied.	2	128	16
Horizontal Offset	Offset of Shape Origin from Panel Origin (in mm). A value of 0xFFFFFFF indicates that this field is not supplied.	2	144	16

Note: All additional buffer entries returned may contain OEM-specific data, but must begin in a {GUID, data} pair. These additional data may provide complimentary physical location information specific to certain systems or class of machines.

Figure 6-34 Default Shape Definitions



Buffers 1 - N Return Value (Optional):

Buffer 1 Bit 127:0 - GUID 1

Buffer 2 Bit 127:0 – Data 1

Buffer 3 Bit 127:0 – GUID 2

Buffer 4 Bit 127:0 - Data 2

.

<u>Figure 6-35</u> provides an example of a rendering of the external device connection points that may be conveyed to the user by _PLD information. Note that three _PLDs (*System Back Panel, Power Supply*, and *Motherboard (MB) Connector Area*) that are associated with the System Bus tree (_SB) object. Their Reference flag is set indicating that are used to provide the user with visual queues for identifying the relative locations of the other device connection points.

The connection points (C1 through C16) are defined by _PLD objects found in the System bus tree. The following connection points all have their Panel and Lid fields set to Back and 0, respectively. And the Reference flag of the System Back Panel, Power Supply, and MB Connector Area connection points are set to 1. in this example are used to render <u>Figure 6-35</u>:

Table 6-157 PLD Back Panel Example Settings

Name	Ignore Color	R	G	В	Width	Height	VOff	HOff	Shape	Notation	Goup Position	Rota-tion

Name	Ignore Color	Z	G	B	Width	Height	VOff	HOff	Shape	Notation	Goup Position	Rota-tion
Back Panel	Yes	0	0	0	2032	4318	0	0	V Rect		1	0
MB Conn area	Yes	0	0	0	445	1556	1588	127	V Rect		2	0
Power Supply	Yes	0	0	0	1524	889	3302	127	H Rect		2	0
USB Port 1	No	0	0	0	125	52	2223	159	H Rect	C1	3	90
USB Port 2	No	0	0	0	125	52	2223	254	H Rect	C2	3	90
USB Port 3	No	0	0	0	125	52	2223	350	H Rect	C3	3	90
USB Port 4	No	0	0	0	125	52	2223	445	H Rect	C4	3	90
USB Port 5	No	0	0	0	125	52	2007	159	H Rect	C5	3	90
USB Port 6	No	0	0	0	125	52	2007	254	H Rect	C6	3	90
Ethern et	No	0	0	0	157	171	2007	350	V Rect	C7	3	90
Audio 1	No	FF	FF	FF	127	127	1945	151	Round	C8	3	90
Audio 2	No	15 1	24 7	12 7	127	127	1945	286	Round	C9	3	90
Audio 3	No	0	0	0	127	127	1945	427	Round	C10	3	90
SPDIF	No	0	0	0	112	126	1756	176	V Trap	C11	3	90
Audio 4	No	0	FF	0	127	127	1765	288	Round	C12	3	90
Audio 5	No	0	0	FF	127	127	1765	429	Round	C13	3	90
SATA	No	0	0	0	239	88	3091	159	H Rect	C14	3	90
1394	No	0	0	0	112	159	2890	254	H Trap	C15	3	0
Coax	No	0	0	0	159	159	2842	143	Round	C16	3	90
PCI 1	No	0	0	0	1016	127	127	127	H Rect	1	3	0
PCI 2	No	0	0	0	1016	127	334	127	H Rect	2	3	0
PCI 3	No	0	0	0	1016	127	540	127	H Rect	3	3	0

Name	Ignore Color	Z	G	σ.	Width	Height	VOff	HOff	Shape	Notation	Goup Position	Rota-tion
PCI 4	No	0	0	0	1016	127	747	127	H Rect	4	3	0
PCI 5	No	0	0	0	1016	127	953	127	H Rect	5	3	0
PCI 6	No	0	0	0	1016	127	1159	127	H Rect	6	3	0
PCI 7	No	0	0	0	1016	127	1366	127	H Rect	7	3	0

Note that the origin is in the lower left hand corner of the Back Panel, where positive Horizontal and Vertical Offset values are to the right and up, respectively.

Power Supply Motherboard connector area PCI Backpanels Vertical C8 C9 C10 Offset C11 C12 C13 6 System Backpanel 5 4 3 2 Origin Horizontal Offset

Figure 6-35 PLD Back Panel Rendering

6.1.9 SUB

This object is used to supply OSPM with the device's Subsystem ID. The use of _SUB is optional.

Arguments:

None

Return Value:

A String containing the SUB

A_SUB object evaluates to a string and the format must be a valid PNP or ACPI ID with no asterisk or other leading characters.

See the definition of _HID (<u>Section 6.1.5</u>) for the definition of PNP and ACPI ID strings.

Example ASL:

```
Name (_SUB, "MSFT3000")// Vendor-defined subsystem
```

6.1.10 _STR (String)

The _STR object evaluates to a Unicode string that describes the device. It may be used by an OS to provide information to an end user. This information is particularly valuable when no other information is available.

Arguments:

None

Return Value:

A **Buffer** containing a Unicode string that describes the device

Example ASL:

```
Device (XYZ) {
    Name (_ADR, 0x00020001)
    Name (_STR, Unicode ("ACME super DVD controller"))
}
```

Then, when all else fails, an OS can use the info included in the _STR object to describe the hardware to the user.

6.1.11 _SUN (Slot User Number)

_SUN is an object that evaluates to the slot-unique ID number for a slot. _SUN is used by OSPM UI to identify slots for the user. For example, this can be used for battery slots, PCI slots, PCMCIA slots, or swappable bay slots to inform the user of what devices are in each slot. _SUN evaluates to an integer that is the number to be used in the user interface.

Arguments:

None

Return Value:

An **Integer** containing the slot's unique ID

The _SUN value is required to be unique among the slots of the same type. It is also recommended that this number match the slot number printed on the physical slot whenever possible.

6.1.12 _UID (Unique ID)

This object provides OSPM with a logical device ID that does not change across reboots. This object is optional, but is required when the device has no other way to report a persistent unique device ID. The _UID must be unique across all devices with either a common _HID or _CID. This is because a device needs to be uniquely identified to the OSPM, which may match on either a _HID or a _CID to identify the device. The uniqueness match must be true regardless of whether the OSPM uses the _HID or the _CID. OSPM typically uses the unique device ID to ensure that the device-specific information, such as network protocol binding information, is remembered for the device even if its relative location changes. For most integrated devices, this object contains a unique identifier.

A _UID object evaluates to either a numeric value or a string.

Arguments:

None

Return Value:

An **Integer** or **String** containing the Unique ID

6.2 Device Configuration Objects

This section describes objects that provide OSPM with device specific information and allow OSPM to configure device operation and resource utilization.

OSPM uses device configuration objects to configure hardware resources for devices enumerated via ACPI. Device configuration objects provide information about current and possible resource requirements, the relationship between shared resources, and methods for configuring hardware resources.

Note: these objects must only be provided for devices that cannot be configured by any other hardware standard such as PCI, PCMCIA, and so on.

When OSPM enumerates a device, it calls _PRS to determine the resource requirements of the device. It may also call _CRS to find the current resource settings for the device. Using this information, the Plug and Play system determines what resources the device should consume and sets those resources by calling the device's SRS control method.

In ACPI, devices can consume resources (for example, legacy keyboards), provide resources (for example, a proprietary PCI bridge), or do both. Unless otherwise specified, resources for a device are assumed to be taken from the nearest matching resource above the device in the device hierarchy.

Some resources, however, may be shared amongst several devices. To describe this, devices that share a resource (resource consumers) must use the extended resource descriptors (0x7-0xA) described in Section 6.4.3, "Large Resource Data Type." These descriptors point to a single device object (resource producer) that claims the shared resource in its PRS. This allows OSPM to clearly understand the resource dependencies in the system and move all related devices together if it needs to change resources. Furthermore, it allows OSPM to allocate resources only to resource producers when devices that consume that resource appear.

The device configuration objects are listed in <u>Table 6-158</u>

Table 6-158 Device Configuration Objects

Object	Description
_CDM	Object that specifies a clock domain for a processor.
_CRS	Object that specifies a device's <i>current</i> resource settings, or a control method that generates such an object.
_DIS	Control method that disables a device.
_DMA	Object that specifies a device's <i>current</i> resources for DMA transactions.
_DSD	Object that evaluates to device specific information
_FIX	Object used to provide correlation between the fixed-hardware register blocks defined in the FADT and the devices that implement these fixed-hardware registers.
_GSB	Object that provides the Global System Interrupt Base for a hot-plugged I/O APIC device.
_HPP	Object that specifies the cache-line size, latency timer, SERR enable, and PERR enable values to be used when configuring a PCI device inserted into a hot-plug slot or initial configuration of a PCI device at system boot.
_HPX	Object that provides device parameters when configuring a PCI device inserted into a hot-plug slot or initial configuration of a PCI device at system boot. Supersedes _HPP.
_MAT	Object that evaluates to a buffer of MADT APIC Structure entries.
_OSC	An object OSPM evaluates to convey specific software support / capabilities to the platform allowing the platform to configure itself appropriately.
_PRS	An object that specifies a device's <i>possible</i> resource settings, or a control method that generates such an object.
_PRT	Object that specifies the PCI interrupt routing table.
_PXM	Object that specifies a proximity domain for a device.
_SLI	Object that provides updated distance information for a system locality.
_SRS	Control method that sets a device's settings.

6.2.1 _CDM (Clock Domain)

This optional object conveys the processor clock domain to which a processor belongs. A processor clock domain is a unique identifier representing the hardware clock source providing the input clock for a given set of processors. This clock source drives software accessible internal counters, such as the Time Stamp Counter, in each processor. Processor counters in the same clock domain are driven by the same hardware clock source. In multi-processor platforms that utilize multiple clock domains, such counters may exhibit drift when compared against processor counters on different clock domains.

The _CDM object evaluates to an integer that identifies the device as belonging to a specific clock domain. OSPM assumes that two devices in the same clock domain are connected to the same hardware clock.

Arguments:

None

Return Value:

An Integer (DWORD) containing a clock domain identifier.

In the case the platform does not convey any clock domain information to OSPM via the SRAT or the _CDM object, OSPM assumes all logical processors to be on a common clock domain. If the platform defines _CDM object under a logical processor then it must define _CDM objects under all logical processors whose clock domain information is not provided via the SRAT.

6.2.2 CRS (Current Resource Settings)

This required object evaluates to a byte stream that describes the system resources currently allocated to a device. Additionally, a bus device must supply the resources that it decodes and can assign to its children devices. If a device is disabled, then _CRS returns a valid resource template for the device, but the actual resource assignments in the return byte stream are ignored. If the device is disabled when _CRS is called, it must remain disabled.

The format of the data contained in a _CRS object follows the formats defined in <u>Section 6.4</u> "Resource Data Types for ACPI," a compatible extension of the formats specified in the PNPBIOS specification. The resource data is provided as a series of data structures, with each of the resource data structures having a unique tag or identifier. The resource descriptor data structures specify the standard PC system resources, such as memory address ranges, I/O ports, interrupts, and DMA channels.

Arguments:

None

Return Value:

A **Buffer** containing a resource descriptor byte stream

6.2.3 _DIS (Disable)

This control method disables a device. When the device is disabled, it must not be decoding any hardware resources. Prior to running this control method, OSPM will have already put the device in the D3 state.

When a device is disabled via the _DIS, the _STA control method for this device must return with the Disabled bit set.

Arguments:

None

Return Value:

None

6.2.4 _DMA (Direct Memory Access)

This optional object returns a byte stream in the same format as a _CRS object. _DMA is only defined under devices that represent buses. It specifies the ranges the bus controller (bridge) decodes on the child-side of its interface. (This is analogous to the _CRS object, which describes the

^{1.} Plug and Play BIOS Specification Version 1.0A, May 5, 1994, Compaq Computer Corp., Intel Corp., Phoenix Technologies Ltd.

resources that the bus controller decodes on the parent-side of its interface.) Any ranges described in the resources of a DMA object can be used by child devices for DMA or bus master transactions.

The _DMA object is only valid if a _CRS object is also defined. OSPM must re-evaluate the _DMA object after an _SRS object has been executed because the _DMA ranges resources may change depending on how the bridge has been configured.

If the _DMA object is not present for a bus device, the OS assumes that any address placed on a bus by a child device will be decoded either by a device on the bus or by the bus itself, (in other words, all address ranges can be used for DMA).

For example, if a platform implements a PCI bus that cannot access all of physical memory, it has a _DMA object under that PCI bus that describes the ranges of physical memory that can be accessed by devices on that bus.

A _DMA object is not meant to describe any "map register" hardware that is set up for each DMA transaction. It is meant only to describe the DMA properties of a bus that cannot be changed without reevaluating the SRS method.

Arguments:

None

Return Value:

A **Buffer** containing a resource descriptor byte stream

DMA Example ASL:

Device Configuration

```
Device(BUS0)
   11
   // The _DMA method returns a resource template describing the
   // addresses that are decoded on the child side of this
   // bridge. The contained resource descriptors thus indicate
   // the address ranges that bus masters living below this
   // bridge can use to send accesses through the bridge toward a
   // destination elsewhere in the system (e.g. main memory).
   11
   // In our case, any bus master addresses need to fall between
   // 0 and 0x80000000 and will have 0x200000000 added as they
   // cross the bridge. Furthermore, any child-side accesses
   // falling into the range claimed in our _CRS will be
   // interpreted as a peer-to-peer traffic and will not be
    // forwarded upstream by the bridge.
   \ensuremath{//} Our upstream address decoder will only claim one range from
   // 0x20000000 to 0x5ffffffff in the _CRS. Therefore _DMA
   // should return two QWORDMemory descriptors, one describing
    // the range below and one describing the range above this
    // "peer-to-peer" address range.
    11
    Method(_DMA, ResourceTemplate()
       QWORDMemory(
           ResourceConsumer,
           PosDecode, // _DEC MinFixed, // _MIF
           MaxFixed,
                              // _MAF
           Prefetchable, // _MEM
           ReadWrite,
                               // _RW
                               // _GRA
                               // _MIN
           0x1fffffff,
                               // _MAX
           0x200000000,
                              // _TRA
                              // _LEN
           0x20000000,
       QWORDMemory(
           ResourceConsumer,
           PosDecode,
                               // _DEC
                             // _MIF
           MinFixed.
           MaxFixed,
                              // _MAF
           Prefetchable, // _MEM
           ReadWrite,
                              // _RW
           0,
                              // _GRA
           0x60000000,
                              // _MIN
            0x7fffffff,
                              // _MAX
                               // _TRA
// _LEN
            0x200000000,
           0x20000000,
   })
}
```

6.2.5 _DSD (Device Specific Data)

This optional object is used to provide device drivers (via OSPM) with additional device properties and information. _DSD returns a variable-length package containing a list of Device Data Descriptor structures each consisting of a Universal Unique Identifier (UUID) and a package (Data Structure). The UUID is all that is needed to define the Data Structure. The UUID itself may place a restriction based on HID/ CID, but it also may not.

New UUIDs may be created by OEMs and IHVs or other interface or device governing bodies (e.g. the PCI SIG or the UEFI Forum), as long as the UUID is different from other published UUIDs.

The list of well-known UUIDs allocated for _DSD and the definition of data formats associated with them is available in the following auxiliary document hosted by the UEFI Forum: http://www.uefi.org/acpi.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of Device Data Descriptor structures as described below.

Return Value Information

```
Package ()
{
    Device Data Descriptor 0
    ...
    Device Data Descriptor n
}
```

Each Device Data Descriptor structure consists of two elements, as follows:

```
UUID // Buffer (16 bytes)
Data Structure // Package (depending on UUID)
```

UUID is a Universal Unique Identifier (16 bytes) that uniquely determines the format of *Data Structure*.

Data Structure is a set of device specific data items the format of which is uniquely determined by the *UUID* and the meaning of which is uniquely determined by the *UUID* possibly in combination with a PNP or ACPI device ID.

Multiple Device Data Descriptor structures with the same *UUID* are not permitted.

_DSD must return the same data each time it is evaluated. Firmware should not expect it to be evaluated every time (in case it is implemented as a method).

Examples:

Note: The UUID used in the following examples is assumed to define the data format for Data Structure as a list of packages of length 2 (Properties) whose first element (Key) must be a String and the second element is a Value associated with that key. The set of valid Keys and the format and

Device Configuration

interpretation of the Values associated with them is then dependent on the PNP or ACPI device ID of the device.

```
Device (MDEV) {
    Name (_HID, "PNP####")
    Name (_{DSD}, Package () {
        ToUUID("daffd814-6eba-4d8c-8a91-bc9bbf4aa301"),
        Package () {
            Package (2) {...},// Property 1
            Package (2) {...}// Property n
    })
}
// PWM controller with two pins that can be driven and a device using
// those pins with the periods of 5000000 and 4500000 nanoseconds,
// respectively.
11
Device (\_SB.PCI0.PWM) {
    Name (_HID, "PNP####")
    Name (_DSD, Package () {
        ToUUID( "daffd814-6eba-4d8c-8a91-bc9bbf4aa301"),
        Package () {
             Package (2) {"#pwm-cells", 2}
    })
}
Device (\_SB.PCI0.BL) {
    Name (_HID, "ACPI####")
    Name (_DSD, Package () {
        ToUUID("daffd814-6eba-4d8c-8a91-bc9bbf4aa301"),
        Package () {
            Package (2) {
                "pwms",
                Package () {
                    \_SB.PCIO.PWM, 0, 5000000,
                    \_SB.PCI0.PWM, 1, 4500000
               }
        }
     })
}
\ensuremath{//} SPI controller using a fixed frequency clock represented by the CLKO
// device object.
11
Device (\_SB_.PCI0) {
    Device (CLK0) {
       Name (_HID, "PNP####")
        Name (_DSD, Package () {
            ToUUID("daffd814-6eba-4d8c-8a91-bc9bbf4aa301"),
            Package () {
```

6.2.6 FIX (Fixed Register Resource Provider)

This optional object is used to provide a correlation between the fixed-hardware register blocks defined in the FADT and the devices in the ACPI namespace that implement these fixed-hardware registers. This object evaluates to a package of Plug and Play-compatible IDs (32-bit compressed EISA type IDs) that correlate to the fixed-hardware register blocks defined in the FADT. The device under which _FIX appears plays a role in the implementation of the fixed-hardware (for example, implements the hardware or decodes the hardware's address). _FIX conveys to OSPM whether a given device can be disabled, powered off, or should be treated specially by conveying its role in the implementation of the ACPI fixed-hardware register interfaces. This object takes no arguments.

The _CRS object describes a device's resources. That _CRS object may contain a superset of the resources in the FADT, as the device may actually decode resources beyond what the FADT requires. Furthermore, in a machine that performs translation of resources within I/O bridges, the processor-relative resources in the FADT may not be the same as the bus-relative resources in the CRS.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **Integers**, each containing a PNP ID Each of fields in the FADT has its own corresponding Plug and Play ID, as shown below:

```
PNP0C20 - SMI_CMD
PNPOC21 - PM1a_EVT_BLK / X_ PM1a_EVT_BLK
PNP0C22 - PM1b_EVT_BLK / X_PM1b_EVT_BLK
PNP0C23 - PM1a_CNT_BLK / X_PM1a_CNT_BLK
PNP0C24 - PM1b_CNT_BLK / X_ PM1b_CNT_BLK
PNP0C25 - PM2_CNT_BLK / X_ PM2_CNT_BLK
PNP0C26 - PM_TMR_BLK / X_ PM_TMR_BLK
PNP0C27 - GPE0_BLK / X_GPE0_BLK
PNP0C28 - GPE1_BLK / X_ GPE1_BLK
PNP0B00 - FIXED_RTC
PNP0B01 - FIXED_RTC
PNP0B02 - FIXED_RTC
     Example ASL for _FIX usage:
Scope(\_SB) {
   Device(PCI0) {
                                          // Root PCI Bus
       Name(_HID, EISAID("PNP0A03"))
                                          // Need _HID for root device
       Name(ADR,0)
                                          // Device 0 on this bus
       Method (_CRS,0){
                                          // Need current resources for root device
                                          // Return current resources for root bridge 0
       Name(_PRT, Package(){
                                          // Need PCI IRQ routing for PCI bridge
                                          // Package with PCI IRQ routing table information
       Name(_FIX, Package(1) {
           EISAID("PNP0C25")}
                                          // PM2 control ID
       Device (PX40) {
                                          // ISA
           Name(_ADR,0x00070000)
           Name(_FIX, Package(1) {
               EISAID("PNP0C20")}
                                          // SMI command port
           Device (NS17) {
                                          // NS17 (Nat. Semi 317, an ACPI part)
               Name(_HID, EISAID("PNP0C02"))
               Name(_FIX, Package(3) {
                   EISAID("PNP0C22"),
                                          // PM1b event ID
                   EISAID("PNP0C24"),
                                         // PM1b control ID
                   EISAID("PNPOC28")}
                                          // GPE1 ID
                                          // end PX40
        Device (PX43) {
                                          // PM Control
           Name(\_ADR, 0x00070003)
           Name(_FIX, Package(4) {
               EISAID("PNP0C21"),
                                          // PMla event ID
               EISAID("PNP0C23"),
                                          // PMla control ID
               EISAID("PNPOC26"),
                                          // PM Timer ID
               EISAID("PNP0C27")}
                                          // GPE0 ID
       }
                                          // end PX43
   }
                                          // end PCI0
                                           // end scope SB
```

6.2.7 _GSB (Global System Interrupt Base)

_GSB is an optional object that evaluates to an integer that corresponds to the Global System Interrupt Base for the corresponding I/O APIC device. The I/O APIC device may either be bus

enumerated (e.g. as a PCI device) or enumerated in the namespace as described in <u>Section 9.17</u>,"I/O APIC Device". Any I/O APIC device that either supports hot-plug or is not described in the MADT must contain a _GSB object.

If the I/O APIC device also contains a _MAT object, OSPM evaluates the _GSB object first before evaluating the _MAT object. By providing the Global System Interrupt Base of the I/O APIC, this object enables OSPM to process only the _MAT entries that correspond to the I/O APIC device. See Section 6.2.10, "_MAT (Multiple APIC Table Entry)". Since _MAT is allowed to potentially return all the MADT entries for the entire platform, _GSB is needed in the I/O APIC device scope to enable OSPM to identify the entries that correspond to that device.

If an I/O APIC device is activated by a device-specific driver, the physical address used to access the I/O APIC will be exposed by the driver and cannot be determined from the _MAT object. In this case, OSPM cannot use the _MAT object to determine the Global System Interrupt Base corresponding to the I/O APIC device and hence requires the GSB object.

The Global System Interrupt Base is a 64-bit value representing the corresponding I/OAPIC device as defined in <u>Section 5.2.13</u>, "Global System Interrupts".

Arguments:

None

Return Value:

An **Integer** containing the interrupt base

Example ASL for _GSB usage for a non-PCI based I/O APIC Device:

Example ASL for GSB usage for a PCI-based I/O APIC Device:

6.2.8 _HPP (Hot Plug Parameters)

This optional object evaluates to a package containing the cache-line size, latency timer, SERR enable, and PERR enable values to be used when configuring a PCI device inserted into a hot-plug slot or for performing configuration of a PCI devices not configured by the BIOS at system boot. The object is placed under a PCI bus where this behavior is desired, such as a bus with hot-plug slots. HPP provided settings apply to all child buses, until another HPP object is encountered.

Arguments:

None

Return Value:

A Package containing the Integer hot-plug parameters

Example:

Table 6-159 HPP Package Contents

Field	Object Type	Definition
Cache-line size	Integer	Cache-line size reported in number of DWORDs.
Latency timer	Integer	Latency timer value reported in number of PCI clock cycles.
Enable SERR	Integer	When set to 1, indicates that action must be performed to enable SERR in the command register.
Enable PERR	Integer	When set to 1, indicates that action must be performed to enable PERR in the command register.

6.2.8.1 Example: Using _HPP

```
Scope(\_SB) {
   Device(PCI0) {
                                       // Root PCI Bus
       Name(_HID, EISAID("PNPOA03"))
                                      // _HID for root device
       Name(_ADR,0)
                                        // Device 0 on this bus
       Method (_CRS,0){
                                        // Need current resources for root dev
                                        // Return current resources for root bridge 0
       Name(_PRT, Package(){
                                   // Need PCI IRQ routing for PCI bridge
                                        // Package with PCI IRQ routing table information
       })
       Device (P2P1) {
                                        // First PCI-to-PCI bridge (No Hot Plug slots)
           Name(_ADR,0x000C0000)
                                        // Device#Ch, Func#0 on bus PCI0
           Name(_PRT, Package(){
                                        // Need PCI IRQ routing for PCI bridge
                                        // Package with PCI IRQ routing table information
           })
                                        // end P2P1
       Device (P2P2) {
                                        // Second PCI-to-PCI bridge (Bus contains Hot plug slots)
           Name(_ADR,0x000E0000)
                                        // Device#Eh, Func#0 on bus PCI0
           Name(_PRT, Package(){
                                        // Need PCI IRQ routing for PCI bridge
                                        // Package with PCI IRQ routing table information
           })
           Name(_{HPP}, Package()\{0x08,0x40, 0x01, 0x00\})
```

```
// Device definitions for Slot 1- HOT PLUG SLOT
Device (S1F0) {
                           // Slot 1, Func#0 on bus P2P2
   Name(_{ADR},0x00020000)
   Method(_EJ0, 1) {
                          // Remove all power to device}
Device (S1F1) {
                           // Slot 1, Func#1 on bus P2P2
   Name(_ADR,0x00020001)
   Method(_EJ0, 1) {
                           // Remove all power to device}
Device (S1F2) {
                          // Slot 1, Func#2 on bus P2P2
   Name(_ADR,0x000200 02)
   Method(_EJ0, 1) {
                          // Remove all power to device}
Device (S1F3) {
                           // Slot 1, Func#3 on bus P2P2
   Name(_ADR,0x00020003)
   Method(_EJ0, 1) {
                           // Remove all power to device}
Device (S1F4) {
                           // Slot 1, Func#4 on bus P2P2
   Name(_ADR,0x00020004)
   Method(_EJ0, 1) {
                           // Remove all power to device}
Device (S1F5) {
                           // Slot 1, Func#5 on bus P2P2
   Method(_EJ0, 1) {
                           // Remove all power to device}
Device (S1F6) {
                           // Slot 1, Func#6 on bus P2P2
   Name(_{ADR}, 0x00020006)
   Method(_EJ0, 1) {
                           // Remove all power to device}
                           // Slot 1, Func#7 on bus P2P2
Device (S1F7) {
   Name(_ADR,0x00020007)
   Method(_EJ0, 1) {
                           // Remove all power to device}
// Device definitions for Slot 2- HOT PLUG SLOT
Device (S2F0) {
                           // Slot 2, Func#0 on bus P2P2
   Name(_ADR,0x00030000)
   Method(_EJ0, 1) {
                           // Remove all power to device}
Device (S2F1) {
                           // Slot 2, Func#1 on bus P2P2
   Name(_ADR,0x00030001)
   Method(_EJ0, 1) {
                           // Remove all power to device}
Device (S2F2) {
                            // Slot 2, Func#2 on bus P2P2
   Name(_ADR,0x00030002)
   Method(_EJ0, 1) {
                            // Remove all power to device}
Device (S2F3) {
                            // Slot 2, Func#3 on bus P2P2
   Name(_ADR,0x00030003)
   Method(_EJ0, 1) {
                           // Remove all power to device}
Device (S2F4) {
                           // Slot 2, Func#4 on bus P2P2
   Name( ADR, 0x00030004)
                           // Remove all power to device}
   Method(_EJ0, 1) {
Device (S2F5) {
                            // Slot 2, Func#5 on bus P2P2
   Name(_ADR,0x00030005)
   Method(_EJ0, 1) {
                           // Remove all power to device}
Device (S2F6) {
                            // Slot 2, Func#6 on bus P2P2
   Name(\_ADR,0x00030006)
```

OSPM will configure a PCI device on a card hot-plugged into slot 1 or slot 2, with a cache line size of 32 (Notice this field is in DWORDs), latency timer of 64, enable SERR, but leave PERR alone.

6.2.9 _HPX (Hot Plug Parameter Extensions)

This optional object provides platform-specific information to the OSPM PCI driver component responsible for configuring hot-add PCI, PCI-X, or PCI Express devices. The information conveyed applies to the entire hierarchy downward from the scope containing the _HPX object. If another _HPX object is encountered downstream, the settings conveyed by the lower-level object apply to that scope downward.

OSPM uses the information returned by _HPX to determine how to configure PCI devices that are hot-plugged into the system, and to configure devices not configured by the platform firmware during initial system boot. The _HPX object is placed within the scope of a PCI-compatible bus (see the second Note below for restrictions) where this behavior is desired, such as a bus with hot-plug slots. It returns a single package that contains one or more sub-packages, each containing a single Setting Record. Each such Setting Record contains a Setting Type (INTEGER), a Revision number (INTEGER) and type/revision specific contents.

The format of data returned by the _HPX object is extensible. The Setting Type and Revision number determine the format of the Setting Record. OSPM ignores Setting Records of types that it does not understand. A Setting Record with higher Revision number supersedes that with lower revision number, however, the _HPX method can return both together, OSPM shall use the one with highest revision number that it understands.

_HPX may return multiple types or Record Settings (each setting in a single sub-package.) OSPM is responsible for detecting the type of hot plugged device and for applying the appropriate settings. OSPM is also responsible for detecting the device / port type of the PCI Express device and applying the appropriate settings provided. For example, the Secondary Uncorrectable Error Severity and Secondary Uncorrectable Error Mask settings of Type 2 record are only applicable to PCI Express to PCI-X/PCI Bridge whose device / port type is 1000b. Similarly, AER settings are only applicable to hot plug PCI Express devices that support the optional AER capability.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **Packages**, each containing a single PCI or PCI-X Record Setting as described below

The _HPX object supersedes the _HPP object. If the _HPP and _HPX objects exist within a device's scope, OSPM will only evaluate the HPX object.

Note: OSPM may override the settings provided by the _HPX object's Type2 record (PCI Express Settings) when OSPM has assumed native control of the corresponding feature. For example, if OSPM has assumed ownership of AER (via _OSC), OSPM may override AER related settings returned by HPX.

Note: The _HPX object may exist under PCI compatible buses including host bridges except when the host bridge spawns a PCI Express hierarchy. For PCI Express hierarchies, the _HPX object may only exist under a root port or a switch downstream port.

Note: Since error status registers do not drive error signaling, OSPM is not required to clear error status registers as part of _HPX handling.

6.2.9.1 PCI Setting Record (Type 0)

The PCI setting record contains the setting type 0, the current revision 1 and the type/revision specific content: cache-line size, latency timer, SERR enable, and PERR enable values.

Field	Object Type	Definition
Header:		
Туре	Integer	0x00: Type 0 (PCI) setting record.
Revision	Integer	0x01: Revision 1, defining the set of fields below.
Cache-line size	Integer	Cache-line size reported in number of DWORDs.
Latency timer	Integer	Latency timer value reported in number of PCI clock cycles.
Enable SERR	Integer	When set to 1, indicates that action must be performed to enable SERR in the command register.
Enable PERR	Integer	When set to 1, indicates that action must be performed to enable PERR in the command register.

If the hot plug device includes bridge(s) in the hierarchy, the above settings apply to the primary side (command register) of the hot plugged bridge(s). The settings for the secondary side of the bridge(s) (Bridge Control Register) are assumed to be provided by the bridge driver.

The Type 0 record is applicable to hot plugged PCI, PCI-X and PCI Express devices. OSPM will ignore settings provided in the Type0 record that are not applicable (for example, Cache-line size and Latency Timer are not applicable to PCI Express).

6.2.9.2 PCI-X Setting Record (Type 1)

The PCI-X setting record contains the setting type 1, the current revision 1 and the type/revision specific content: the maximum memory read byte count setting, the average maximum outstanding split transactions setting and the total maximum outstanding split transactions to be used when configuring PCI-X command registers for PCI-X buses and/or devices.

Table 6-161 PCI-X Setting Record Content

Field	Object Type	Definition
Header:		
Туре	Integer	0x01: Type 1 (PCI-X) setting record.

Field	Object Type	Definition
Revision	Integer	0x01: Revision 1, defining the set of fields below.
Maximum memory read byte count	Integer	Maximum memory read byte count reported: Value 0: Maximum byte count 512 Value 1: Maximum byte count 1024
odun		Value 2: Maximum byte count 2048 Value 3: Maximum byte count 4096
Average maximum outstanding split transactions	Integer	The following values are defined: Value 0: Maximum outstanding split transaction 1 Value 1: Maximum outstanding split transaction 2 Value 2: Maximum outstanding split transaction 3 Value 3: Maximum outstanding split transaction 4 Value 4: Maximum outstanding split transaction 8 Value 5: Maximum outstanding split transaction 12 Value 6: Maximum outstanding split transaction 16 Value 7: Maximum outstanding split transaction 32
Total maximum outstanding split transactions	Integer	See the definition for the average maximum outstanding split transactions.

For simplicity, OSPM could use the Average Maximum Outstanding Split Transactions value as the Maximum Outstanding Split Transactions register value in the PCI-X command register for each PCI-X device. Another alternative is to use a more sophisticated policy and the Total Maximum Outstanding Split Transactions Value to gain even more performance. In this case, the OS would examined each PCI-X device that is directly attached to the host bridge, determine the number of outstanding split transactions supported by each device, and configure each device accordingly. The goal is to ensure that the aggregate number of concurrent outstanding split transactions does not exceed the Total Maximum Outstanding Split Transactions Value: an integer denoting the number of concurrent outstanding split transactions the host bridge can support (the minimum value is 1).

This object does not address providing additional information that would be used to configure registers in bridge devices, whether architecturally-defined or specification-defined registers or device specific registers. It is expected that a driver for a bridge would be the proper implementation mechanism to address both of those issues. However, such a bridge driver should have access to the data returned by the _HPX object for use in optimizing its decisions on how to configure the bridge. Configuration of a bridge is dependent on both system specific information such as that provided by the _HPX object, as well as bridge specific information.

6.2.9.3 PCI Express Setting Record (Type 2)

The PCI Express setting record contains the setting type 2, the current revision 1 and the type/ revision specific content (the control registers as listed in the table below) to be used when configuring registers in the Advanced Error Reporting Extended Capability Structure or PCI Express Capability Structure for the PCI Express devices.

The Type 2 Setting Record allows a PCI Express-aware OS that supports native hot plug to configure the specified registers of the hot plugged PCI Express device. A PCI Express-aware OS that has assumed ownership of native hot plug (via _OSC) but does not support or does not have ownership of the AER register set must use the data values returned by the _HPX object's Type 2

record to program the AER registers of a hot-added PCI Express device. However, since the Type 2 record also includes register bits that have functions other than AER, OSPM must ignore values contained within this setting record that are not applicable.

To support PCIe RsvdP semantics for reserved bits, two values for each register are provided: an "AND mask" and an "OR mask". Each bit understood by firmware to be RsvdP shall be set to 1 in the "AND mask" and 0 in the "OR mask". Each bit that firmware intends to be configured as 0 shall be set to 0 in both the "AND mask" and the "OR mask". Each bit that firmware intends to be configured a 1 shall be set to 1 in both the "AND mask" and the "OR mask".

When configuring a given register, OSPM uses the following algorithm:

- 1. Read the register's current value, which contains the register's default value.
- 2. Perform a bit-wise AND operation with the "AND mask" from the table below.
- 3. Perform a bit-wise OR operation with the "OR mask" from the table below.
- 4. Override the computed settings for any bits if deemed necessary. For example, if OSPM is aware of an architected meaning for a bit that firmware considers to be RsvdP, OSPM may choose to override the computed setting for that bit. Note that firmware sets the "AND value" to 1 and the "OR value" to 0 for each bit that it considers to be RsvdP.
- 5. Write the end result value back to the register.

Note that the size of each field in the following table matches the size of the corresponding PCI Express register.

Table 6-162 PCI Express Setting Record Content

Field	Object Type	Definition
Header:		
Туре	Integer	0x02: Type 2 (PCI Express) setting record.
Revision	Integer	0x01: Revision 1, defining the set of fields below.
Uncorrectable Error Mask Register AND Mask	Integer	Bits 0 to 31 contain the "AND mask" to be used in the OSPM algorithm described above.
Uncorrectable Error Mask Register OR Mask	Integer	Bits 0 to 31 contain the "OR mask" to be used in the OSPM algorithm described above.
Uncorrectable Error Severity Register AND Mask	Integer	Bits 0 to 31 contain the "AND mask" to be used in the OSPM algorithm described above.
Uncorrectable Error Severity Register OR Mask	Integer	Bits 0 to 31 contain the "OR mask" to be used in the OSPM algorithm described above.
Correctable Error Mask Register AND Mask	Integer	Bits 0 to 31 contain the "AND mask" to be used in the OSPM algorithm described above.
Correctable Error Mask Register OR Mask	Integer	Bits 0 to 31 contain the "OR mask" to be used in the OSPM algorithm described above.
Advanced Error Capabilities and Control Register AND Mask	Integer	Bits 0 to 31 contain the "AND mask" to be used in the OSPM algorithm described above.
Advanced Error Capabilities and Control Register OR Mask	Integer	Bits 0 to 31 contain the "OR mask" to be used in the OSPM algorithm described above.
Device Control Register AND Mask	Integer	Bits 0 to 15 contain the "AND mask" to be used in the OSPM algorithm described above.
Device Control Register OR Mask	Integer	Bits 0 to 15 contain the "OR mask" to be used in the OSPM algorithm described above.

Field	Object Type	Definition
Link Control Register AND Mask	Integer	Bits 0 to 15 contain the "AND mask" to be used in the OSPM algorithm described above.
Link Control Register OR Mask	Integer	Bits 0 to 15 contain the "OR mask" to be used in the OSPM algorithm described above.
Secondary Uncorrectable Error Severity Register AND Mask	Integer	Bits 0 to 31 contain the "AND mask" to be used in the OSPM algorithm described above
Secondary Uncorrectable Error Severity Register OR Mask	Integer	Bits 0 to 31 contain the "OR mask" to be used in the OSPM algorithm described above
Secondary Uncorrectable Error Mask Register AND Mask	Integer	Bits 0 to 31 contain the "AND mask" to be used in the OSPM algorithm described above
Secondary Uncorrectable Error Mask Register OR Mask	Integer	Bits 0 to 31 contain the "OR mask" to be used in the OSPM algorithm described above

6.2.9.4 **_HPX Example**

```
Method (_HPX, 0) {
    Return (Package(2){
        Package(6){
                           // PCI Setting Record
                          // Type 0
             0 \times 00.
             0x01,
                          // Revision 1
             0x08,
                          // CacheLineSize in DWORDS
             0x40,
                          // LatencyTimer in PCI clocks
             0x01,
                          // Enable SERR (Boolean)
             0 \times 00
                          // Enable PERR (Boolean)
        },
        Package(5){
                          // PCI-X Setting Record
                           // Type 1
             0 \times 01.
                          // Revision 1
             0 \times 01.
                          // Maximum Memory Read Byte Count
             0 \times 03,
             0 \times 04
                          // Average Maximum Outstanding Split Transactions
             0x07
                          // Total Maximum Outstanding Split Transactions
        }
    })
```

6.2.10 MAT (Multiple APIC Table Entry)

This optional object evaluates to a buffer returning data in the format of a series of Multiple APIC Description Table (MADT) APIC Structure entries. This object can appear under an I/O APIC or processor object definition as processors may contain Local APICs. Specific types of MADT entries are meaningful to (in other words, is processed by) OSPM when returned via the evaluation of this object as described below. Other entry types returned by the evaluation of _MAT are ignored by OSPM.

When _MAT appears under a Processor object, OSPM processes Local APIC (Section 5.2.12.2, "Processor Local APIC Structure"), Local SAPIC Structure (Section 5.2.12.10, "Local SAPIC Structure"), local APIC NMI (Section 5.2.12.7, "Local APIC NMI Structure"), Processor Local x2APIC Structure (Section 5.2.12.12 Processor Local x2APIC Structure), Local x2APIC NMI (Section 5.2.12.13 Local x2APIC NMI Structure), and GICC Structure (Section 5.2.12.14 GICC Structure) entries returned from the object's evaluation. Other entry types are ignored by OSPM. OSPM uses the ACPI processor ID in the entries returned from the object's evaluation to identify the

entries corresponding to either the ACPI processor ID of the Processor object or the value returned by the UID object under a Processor device.

When _MAT appears under an I/O APIC, OSPM processes I/O APIC (Section 5.2.12.3, "I/O APIC Structure"), I/O SAPIC (Section 5.2.12.9, "I/O SAPIC Structure"), non-maskable interrupt sources (Section 5.2.12.6, "Non-Maskable Interrupt Source Structure"), interrupt source overrides (Section 5.2.12.5 "Interrupt Source Override Structure"), and platform interrupt source structure (Section 5.2.12.11, "Platform Interrupt Source Structure") entries returned from the object's evaluation. Other entry types are ignored by OSPM.

Arguments:

None

Return Value:

A **Buffer** containing a list of APIC structure entries

Example ASL for _MAT usage:

```
Scope(\_SB) {
   Device(PCI0) {
                                               // Root PCI Bus
       Name(_HID, EISAID("PNP0A03"))
                                              // Need _HID for root device
       Name(_ADR,0)
                                               // Device 0 on this bus
       Method (_CRS,0){
                                               // Need current resources for root device
                                               // Return current resources for root bridge 0
       Name(_PRT, Package(){
                                               // Need PCI IRQ routing for PCI bridge
                                                // Package with PCI IRQ routing table information
        })
       Device (P64A) {
                                                // P64A ACPI
           Name(_ADR,0)
           OperationRegion(TABD, SystemMemory, // Physical address of first
                                            // data byte of multiple ACPI table, Length of tables)
           Field (TABD, ByteAcc, NoLock, Preserve) {
               MATD, Length of tables x 8
           Method(_MAT, 0){
               Return (MATD)
        }
                                               // end P64A
   }
                                                // end PCIO
}
                                                // end scope SB
```

6.2.11 OSC (Operating System Capabilities)

This optional object is a control method that is used by OSPM to communicate to the platform the feature support or capabilities provided by a device's driver. This object is a child object of a device and may also exist in the \SB scope, where it can be used to convey platform wide OSPM capabilities. When supported, _OSC is invoked by OSPM immediately after placing the device in the D0 power state. Device specific objects are evaluated **after** _OSC invocation. This allows the values returned from other objects to be predicated on the OSPM feature support / capability information conveyed by _OSC. OSPM may evaluate _OSC multiple times to indicate changes in OSPM capability to the device but this may be precluded by specific device requirements. As such, _OSC usage descriptions in <u>Section 9</u>, "ACPI-Defined Devices and Device Specific Objects", or

other governing specifications describe superseding device specific _OSC capabilities and / or preclusions.

_OSC enables the platform to configure its ACPI namespace representation and object evaluations to match the capabilities of OSPM. This enables legacy operating system support for platforms with new features that make use of new namespace objects that if exposed would not be evaluated when running a legacy OS. _OSC provides the capability to transition the platform to native operating system support of new features and capabilities when available through dynamic namespace reconfiguration. _OSC also allows devices with Compatible IDs to provide superset functionality when controlled by their native (For example, _HID matched) driver as appropriate objects can be exposed accordingly as a result of OSPM's evaluation of OSC.

Arguments: (4)

Arg0 – A **Buffer** containing a UUID

Arg1 – An Integer containing a Revision ID of the buffer format

Arg2 – An **Integer** containing a count of entries in Arg3

Arg3 – A **Buffer** containing a list of DWORD capabilities

Return Value:

A **Buffer** containing a list of capabilities

Argument Information

Arg0: UUID – Universal Unique Identifier (16 Byte Buffer) used by the platform in conjunction with Revision ID to ascertain the format of the Capabilities buffer.

Arg1: Revision ID – The revision of the Capabilities Buffer format. The revision level is specific to the UUID.

Arg2: Count – Number of DWORDs in the Capabilities Buffer in Arg3

Arg3: Capabilities Buffer – Buffer containing the number of DWORDs indicated by Count. The first DWORD of this buffer contains standard bit definitions as described below. Subsequent DWORDs contain UUID-specific bits that convey to the platform the capabilities and features supported by OSPM. Successive revisions of the Capabilities Buffer must be backwards compatible with earlier revisions. Bit ordering cannot be changed.

Capabilities Buffers are device-specific and as such are described under specific device definitions. See <u>Section 9</u>, "ACPI Devices and Device Specific Objects" for any _OSC definitions for ACPI devices. The format of the Capabilities Buffer and behavior rules may also be specified by OEMs and IHVs for custom devices and other interface or device governing bodies for example, the PCI SIG.

The first DWORD in the capabilities buffer is used to return errors defined by _OSC. This DWORD must always be present and may not be redefined/reused by unique interfaces utilizing OSC.

Bit 0- Query Support Flag. If set, the _OSC invocation is a query by OSPM to determine or
negotiate with the platform the combination of capabilities for which OSPM may take control.
In this case, OSPM sets bits in the subsequent DWORDs to specify the capabilities for which
OSPM intends to take control. If clear, OSPM is attempting to take control of the capabilities
corresponding to the bits set in subsequent DWORDs. OSPM may only take control of
capabilities as indicated by the platform by the result of the query.

- Bit 1 Always clear (0).
- Bit 2 Always clear (0).
- Bit 3 Always clear (0).
- All others reserved.

Return Value Information

Capabilities Buffer (Buffer) – The platform acknowledges the Capabilities Buffer by returning a buffer of DWORDs of the same length. Set bits indicate acknowledgement that OSPM may take control of the capability and cleared bits indicate that the platform either does not support the capability or that OSPM may not assume control.

The first DWORD in the capabilities buffer is used to return errors defined by _OSC. This DWORD must always be present and may not be redefined/reused by unique interfaces utilizing OSC.

- Bit 0 Reserved (not used)
- Bit 1 OSC failure. Platform Firmware was unable to process the request or query. Capabilities bits may have been masked.
- Bit 2 Unrecognized UUID. This bit is set to indicate that the platform firmware does not recognize the UUID passed in via Arg0. Capabilities bits are preserved.
- Bit 3 Unrecognized Revision. This bit is set to indicate that the platform firmware does not recognize the Revision ID passed in via Arg1. Capabilities bits beyond those comprehended by the firmware will be masked.
- Bit 4 Capabilities Masked. This bit is set to indicate that capabilities bits set by driver software have been cleared by platform firmware.
- All others reserved.

Note: OSPM must not use the results of _OSC evaluation to choose a compatible device driver. OSPM must use _HID, _CID, or native enumerable bus device identification mechanisms to select an appropriate driver for a device.

The platform may issue a **Notify**(device, 0x08) to inform OSPM to re-evaluate _OSC when the availability of feature control changes. Platforms must **not** rely, however, on OSPM to evaluate _OSC after issuing a **Notify** for proper operation as OSPM cannot guarantee the presence of a target entity to receive and process the **Notify** for the device. For example, a device driver for the device may not be loaded at the time the **Notify** is signaled. Further, the issuance and processing rules for notification of changes in the Capabilities Buffer is device specific. As such, the allowable behavior is governed by device specifications either in <u>Section 9</u>, "ACPI-Specific Device Objects", for ACPI-define devices, or other OEM, IHV, or device governing body's' device specifications.

It is permitted for _OSC to return all bits in the Capabilities Buffer cleared. An example of this is when significant time is required to disable platform-based feature support. The platform may then later issue a Notify to tell OSPM to re-evaluate _OSC to take over native control. This behavior is also device specific but may also rely on specific OS capability.

In general, platforms should support both OSPM taking and relinquishing control of specific feature support via multiple invocations of OSC but the required behavior may vary on a per device basis.

Since platform context is lost when the platform enters the S4 sleeping state, OSPM must reevaluate _OSC upon wake from S4 to restore the previous platform state. This requirement will vary depending on the device specific _OSC functionality.

6.2.11.1 Rules for Evaluating OSC

This section defines when and how the OS must evaluate _OSC, as well as restrictions on firmware implementation.

6.2.11.1.1 Query Flag

If the Query Support Flag (Capabilities DWORD 1, bit 0) is set by the OS when evaluating _OSC, no hardware settings are permitted to be changed by firmware in the context of the _OSC call. It is strongly recommended that the OS evaluate _OSC with the Query Support Flag set until _OSC returns the Capabilities Masked bit clear, to negotiate the set of features to be granted to the OS for native support; a platform may require a specific combination of features to be supported natively by an OS before granting native control of a given feature.

6.2.11.1.2 Evaluation Conditions

The OS must evaluate OSC under the following conditions:

During initialization of any driver that provides native support for features described in the section above. These features may be supported by one or many drivers, but should only be evaluated by the main bus driver for that hierarchy. Secondary drivers must coordinate with the bus driver to install support for these features. Drivers may not relinquish control of features previously obtained (i.e., bits set in Capabilities DWORD3 after the negotiation process must be set on all subsequent negotiation attempts.)

When a Notify(<device>, 8) is delivered to the PCI Host Bridge device.

Upon resume from S4. Platform firmware will handle context restoration when resuming from S1-S3.

6.2.11.1.3 Sequence of OSC calls

The following rules govern sequences of calls to _OSC that are issued to the same host bridge and occur within the same boot.

- The OS is permitted to evaluate OSC an arbitrary number of times.
- If the OS declares support of a feature in the Status Field in one call to OSC, then it must preserve the set state of that bit (declaring support for that feature) in all subsequent calls.
- If the OS is granted control of a feature in the Control Field in one call to OSC, then it must preserve the set state of that bit (requesting that feature) in all subsequent calls.
- Firmware may not reject control of any feature it has previously granted control to.
- There is no mechanism for the OS to relinquish control of a feature previously requested and granted.

6.2.11.2 Platform-Wide OSPM Capabilities

OSPM evaluates _SB._OSC to convey platform-wide OSPM capabilities to the platform. Argument definitions are as follows:

Arguments: (4)

Arg0 – UUID (Buffer): 0811B06E-4A27-44F9-8D60-3CBBC22E7B48

Arg1 – Revision ID (**Integer**): 1

Arg2 – Count of Entries in Arg3 (Integer): 2

Arg3 – DWORD capabilities (**Buffer**): First DWORD: as described in <u>Section 6.2.10</u>, Second

DWORD: See Table 6-163

Table 6-163 Platform-Wide OSC Capabilities DWORD 2

Bits	Field Name	Definition
0	Processor Aggregator Device Support	This bit is set if OSPM supports the Processor Aggregator device as described in Section 8.5, "Processor Aggregator Device"
1	_PPC _OST Processing Support	This bit is set if OSPM will evaluate the _OST object defined under a processor as a result of _PPC change notification (Notify 0x80)
2	_PR3 Support	This bit is set if OSPM supports reading _PR3and using power resources to switch power. Note this handshake translates to an operating model that the platform and OSPM supports both the power model containing both D3hot and D3.
3	Insertion / Ejection _OST Processing Support	This bit is set if OSPM will evaluate the _OST object defined under a device when processing insertion and ejection source event codes.
4	APEI Support	This bit is set if OSPM supports the ACPI Platform Error Interfaces. See Section 18, "ACPI Platform Error Interfaces".
5	CPPC Support	This bit is set if OSPM supports controlling processor performance via the interfaces described in the _CPC object.
6	CPPC 2 Support	This bit is set if OSPM supports revision 2 of the _CPC object.
31:6		Reserved (must be 0)

Return Value Information

Capabilities Buffer (Buffer) – The platform acknowledges the Capabilities Buffer by returning a buffer of DWORDs of the same length. Set bits indicate acknowledgement and cleared bits indicate that the platform does not support the capability.

6.2.11.3 OSC Implementation Example for PCI Host Bridge Devices

The following section is an excerpt from the PCI Firmware Specification Revision 3.0 and is reproduced with the permission of the PCI SIG.

Note: The PCI SIG owns the definition of _OSC behavior and parameter bit definitions for PCI devices. In the event of a discrepancy between the following example and the PCI Firmware Specification, the latter has precedence.

The _OSC interface defined in this section applies only to "Host Bridge" ACPI devices that originate PCI, PCI-X or PCI Express hierarchies. These ACPI devices must have a _HID of (or _CID including) either EISAID("PNP0A03") or EISAID("PNP0A08"). For a host bridge device that originates a PCI Express hierarchy, the _OSC interface defined in this section is required. For a host bridge device that originates a PCI/PCI-X bus hierarchy, inclusion of an OSC object is optional.

• The _OSC interface for a PCI/PCI-X/PCI Express hierarchy is identified by the following Universal Uniform Identifier (UUID):

33DB4D5B-1FF7-401C-9657-7441C03DD766

A revision ID of 1 encompasses fields defined in this section of this revision of this specification, comprised of 3 DWORDs, including the first DWORD described by the generic ACPI definition of OSC.

The first DWORD in the _OSC Capabilities Buffer contain bits are generic to _OSC and include status and error information.

The second DWORD in the _OSC capabilities buffer is the Support Field. Bits defined in the Support Field provide information regarding OS supported features. Contents in the Support Field are passed one-way; the OS will disregard any changes to this field when returned. See <u>Table 6-161</u> for descriptions of capabilities bits in this field passed as a parameter into the OSC control method.

The third DWORD in the _OSC Capabilities Buffer is the Control Field. Bits defined in the Control Field are used to submit request by the OS for control/handling of the associated feature, typically (but not excluded to) those features that utilize native interrupts or events handled by an OS-level driver. See <u>Table 6-163</u> for descriptions of capabilities bits in this field passed as a parameter into the _OSC control method. If any bits in the Control Field are returned cleared (masked to zero) by the _OSC control method, the respective feature is designated unsupported by the platform and must not be enabled by the OS. Some of these features may be controlled by platform firmware prior to OS boot or during runtime for a legacy OS, while others may be disabled/inoperative until native OS support is available. See <u>Table 6-164</u> for descriptions of capabilities bits in this returned field.

If the _OSC control method is absent from the scope of a host bridge device, then the OS must not enable or attempt to use any features defined in this section for the hierarchy originated by the host bridge. Doing so could contend with platform firmware operations, or produce undesired results. It is recommended that a machine with multiple host bridge devices should report the same capabilities for all host bridges, and also negotiate control of the features described in the Control Field in the same way for all host bridges.

Table 6-164 Interpretation of OSC Support Field

Support Field bit offset	Interpretation
0	Extended PCI Config operation regions supported The OS sets this bit to 1 if it supports ASL accesses through PCI Config operation regions to extended configuration space (offsets greater than 0xFF). Otherwise, the OS sets this bit to 0.
1	Active State Power Management supported The OS sets this bit to 1 if it natively supports configuration of Active State Power Management registers in PCI Express devices. Otherwise, the OS sets this bit to 0.
2	Clock Power Management Capability supported The OS sets this bit to 1 if it supports the Clock Power Management Capability, and will enable this feature during a native hot plug insertion event if supported by the newly added device. Otherwise, the OS sets this bit to 0. Note: The Clock Power Management Capability is defined in an errata to the PCI Express Base Specification, 1.0.

3	PCI Segment Groups supported The OS sets this bit to 1 if it supports PCI Segment Groups as defined by the _SEG object, and access to the configuration space of devices in PCI Segment Groups as described by this specification. Otherwise, the OS sets this bit to 0.
4	MSI supported The OS sets this bit to 1 if it supports configuration of devices to generate message- signaled interrupts, either through the MSI Capability or the MSI-X Capability. Otherwise, the OS sets this bit to 0.
5-31	Reserved

Table 6-165 Interpretation of _OSC Control Field, Passed in via Arg3

Control Field bit offset	Interpretation
0	PCI Express Native Hot Plug control The OS sets this bit to 1 to request control over PCI Express native hot plug. If the OS successfully receives control of this feature, it must track and update the status of hot plug slots and handle hot plug events as described in the PCI Express Base Specification.
1	SHPC Native Hot Plug control The OS sets this bit to 1 to request control over PCI/PCI-X Standard Hot-Plug Controller (SHPC) hot plug. If the OS successfully receives control of this feature, it must track and update the status of hot plug slots and handle hot plug events as described in the SHPC Specification.
2	PCI Express Native Power Management Events control The OS sets this bit to 1 to request control over PCI Express native power management event interrupts (PMEs). If the OS successfully receives control of this feature, it must handle power management events as described in the PCI Express Base Specification.
3	PCI Express Advanced Error Reporting control The OS sets this bit to 1 to request control over PCI Express Advanced Error Reporting. If the OS successfully receives control of this feature, it must handle error reporting through the Advanced Error Reporting Capability as described in the PCI Express Base Specification.
4	PCI Express Capability Structure control The OS sets this bit to 1 to request control over the PCI Express Capability Structures (standard and extended) defined in the PCI Express Base Specification version 1.1. These capability structures are the PCI Express Capability, the virtual channel extended capability, the power budgeting extended capability, the advanced error reporting extended capability, and the serial number extended capability. If the OS successfully receives control of this feature, it is responsible for configuring the registers in all PCI Express Capabilities in a manner that complies with the PCI Express Base Specification. Additionally, the OS is responsible for saving and restoring all PCI Express Capability register settings across power transitions when register context may have been lost.
5-31	Reserved

Table 6-166 Interpretation of _OSC Control Field, Returned Value

Control Field bit offset	Interpretation
0	PCI Express Native Hot Plug control The firmware sets this bit to 1 to grant control over PCI Express native hot plug interrupts. If firmware allows the OS control of this feature, then in the context of the _OSC method it must ensure that all hot plug events are routed to device interrupts as described in the PCI Express Base Specification. Additionally, after control is transferred to the OS, firmware must not update the state of hot plug slots, including the state of the indicators and power controller. If control of this feature was requested and denied or was not requested, firmware returns this bit set to 0.
1	SHPC Native Hot Plug control The firmware sets this bit to 1 to grant control over control over PCI/PCI-X Standard Hot- Plug Controller (SHPC)hot plug. If firmware allows the OS control of this feature, then in the context of the _OSC method it must ensure that all hot plug events are routed to device interrupts as described in the SHPC Specification. Additionally, after control is transferred to the OS, firmware must not update the state of hot plug slots, including the state of the indicators and power controller. If control of this feature was requested and denied or was not requested, firmware returns this bit set to 0.
2	PCI Express Native Power Management Events control The firmware sets this bit to 1 to grant control over control over PCI Express native power management event interrupts (PMEs). If firmware allows the OS control of this feature, then in the context of the _OSC method it must ensure that all PMEs are routed to root port interrupts as described in the PCI Express Base Specification. Additionally, after control is transferred to the OS, firmware must not update the PME Status field in the Root Status register or the PME Interrupt Enable field in the Root Control register. If control of this feature was requested and denied or was not requested, firmware returns this bit set to 0.
3	PCI Express Advanced Error Reporting control The firmware sets this bit to 1 to grant control over PCI Express Advanced Error Reporting. If firmware allows the OS control of this feature, then in the context of the _OSC method it must ensure that error messages are routed to device interrupts as described in the PCI Express Base Specification. Additionally, after control is transferred to the OS, firmware must not modify the Advanced Error Reporting Capability. If control of this feature was requested and denied or was not requested, firmware returns this bit set to 0.
4	PCI Express Capability Structure control The firmware sets this bit to 1 to grant control over the PCI Express Capability. If the firmware does not grant control of this feature, firmware must handle configuration of the PCI Express Capability Structure. If firmware grants the OS control of this feature, any firmware configuration of the PCI Express Capability may be overwritten by an OS configuration, depending on OS policy.
5-31	Reserved

6.2.11.4 ASL Example

A sample _OSC implementation for a mobile system incorporating a PCI Express hierarchy is shown below:

```
Device(PCI0) // Root PCI bus
   Name(_CID,EISAID("PNP0A03"))
                                // Compatible PCI Root Bridge
                                  // PCI _OSC Support Field value
   Name(SUPP, 0)
   Name(CTRL,0)
                                  // PCI _OSC Control Field value
   Method(_OSC,4)
                                  // Check for proper UUID
       If(LEqual(Arg0,ToUUID("33DB4D5B-1FF7-401C-9657-7441C03DD766")))
           // Create DWord-adressable fields from the Capabilities Buffer
           CreateDWordField(Arg3,0,CDW1)
           CreateDWordField(Arg3,4,CDW2)
           CreateDWordField(Arg3,8,CDW3)
           // Save Capabilities DWord2 & 3
           Store(CDW2,SUPP)
           Store(CDW3,CTRL)
           // Only allow native hot plug control if OS supports:
           // * ASPM
           11
                * Clock PM
               * MSI/MSI-X
           11
           If(LNotEqual(And(SUPP, 0x16), 0x16))
               And(CTRL, 0x1E, CTRL) // Mask bit 0 (and undefined bits)
           // Always allow native PME, AER (no dependencies)
           // Never allow SHPC (no SHPC controller in this system)
           And(CTRL,0x1D,CTRL)
                                   // Query flag clear?
           If(LNot(And(CDW1,1)))
               // Disable GPEs for features granted native control.
               If(And(CTRL,0x01)) // Hot plug control granted?
                   Store(0,HPCE) // clear the hot plug SCI enable bit
                   Store(1,HPCS) // clear the hot plug SCI status bit
               If(And(CTRL,0x04)) // PME control granted?
                   Store(0,PMCE)
                                  // clear the PME SCI enable bit
                   Store(1,PMCS)
                                  // clear the PME SCI status bit
               If(And(CTRL,0x10))
                                  // OS restoring PCIe cap structure?
                                   // Set status to not restore PCIe cap structure
                                   // upon resume from S3
                   Store(1,S3CR)
               }
           If(LNotEqual(Arg1,One))
                                   // Unknown revision
               Or(CDW1,0x08,CDW1)
           If(LNotEqual(CDW3,CTRL))
                                   // Capabilities bits were masked
               Or(CDW1,0x10,CDW1)
```

```
}
    // Update DWORD3 in the buffer
    Store(CTRL,CDW3)
    Return(Arg3)
} Else {
    Or(CDW1,4,CDW1) // Unrecognized UUID
    Return(Arg3)
}
    // End _OSC
}
// End PCI0
```

6.2.12 PRS (Possible Resource Settings)

This optional object evaluates to a byte stream that describes the *possible* resource settings for the device. When describing a platform, specify a _PRS for all the configurable devices. Static (non-configurable) devices do not specify a _PRS object. The information in this package is used by OSPM to select a conflict-free resource allocation without user intervention. This method must not reference any operation regions that have not been declared available by a _REG method.

The format of the data in a _PRS object follows the same format as the _CRS object (for more information, see the _CRS object definition in <u>Section 6.2.2</u>, "_CRS (Current Resource Settings)"). If the device is disabled when PRS is called, it must remain disabled.

Arguments:

None

Return Value:

A **Buffer** containing a Resource Descriptor byte stream

6.2.13 PRT (PCI Routing Table)

PCI interrupts are inherently non-hierarchical. PCI interrupt pins are wired to interrupt inputs of the interrupt controllers. The _PRT object provides a mapping from PCI interrupt pins to the interrupt inputs of the interrupt controllers. The _PRT object is required under all PCI root bridges. _PRT evaluates to a package that contains a list of packages, each of which describes the mapping of a PCI interrupt pin.

Arguments:

None

Return Value:

A **Package** containing variable-length list of PCI interrupt mapping packages, as described below

Note: The PCI function number in the Address field of the _PRT packages must be 0xFFFF, indicating "anv" function number or "all functions".

The PRT mapping packages have the fields listed in Table 6-167.

Table 6-167 Mapping Fields

Field	Туре	Description
Address	DWORD	The address of the device (uses the same format as _ADR).

Field	Туре	Description
Pin	BYTE	The PCI pin number of the device (0–INTA, 1–INTB, 2–INTC, 3–INTD).
Source	NamePath Or BYTE	Name of the device that allocates the interrupt to which the above pin is connected. The name can be a fully qualified path, a relative path, or a simple name segment that utilizes the namespace search rules. Note : This field is a NamePath and not a String literal, meaning that it should not be surrounded by quotes. If this field is the integer constant Zero (or a BYTE value of 0), then the interrupt is allocated from the global interrupt pool.
Source Index	DWORD	Index that indicates which resource descriptor in the resource template of the device pointed to in the Source field this interrupt is allocated from. If the Source field is the BYTE value zero, then this field is the global system interrupt number to which the pin is connected.

There are two ways that _PRT can be used. Typically, the interrupt input that a given PCI interrupt is on is configurable. For example, a given PCI interrupt might be configured for either IRQ 10 or 11 on an 8259 interrupt controller. In this model, each interrupt is represented in the ACPI namespace as a PCI Interrupt Link Device.

These objects have _PRS, _CRS, _SRS, and _DIS control methods to allocate the interrupt. Then, OSPM handles the interrupts not as interrupt inputs on the interrupt controller, but as PCI interrupt pins. The driver looks up the device's pins in the _PRT to determine which device objects allocate the interrupts. To move the PCI interrupt to a different interrupt input on the interrupt controller, OSPM uses PRS, CRS, SRS, and DIS control methods for the PCI Interrupt Link Device.

In the second model, the PCI interrupts are hardwired to specific interrupt inputs on the interrupt controller and are not configurable. In this case, the Source field in _PRT does not reference a device, but instead contains the value zero, and the Source Index field contains the global system interrupt to which the PCI interrupt is hardwired.

6.2.13.1 Example: Using _PRT to Describe PCI IRQ Routing

The following example describes two PCI slots and a PCI video chip. Notice that the interrupts on the two PCI slots are wired differently (barber-poled).

```
Scope(\_SB) {
   Device(LNKA) {
       Name(_HID, EISAID("PNP0C0F"))
                                                       // PCI interrupt link
       Name(_UID, 1)
       Name(_PRS, ResourceTemplate(){
           Interrupt(ResourceProducer,...) {10,11} // IRQs 10,11
       Method(_DIS) {...}
       Method(_CRS) {...}
       Method(_SRS, 1) {...}
   Device(LNKB){
      Name(_HID, EISAID("PNP0C0F"))
                                                       // PCI interrupt link
       Name(_UID, 2)
       Name(_PRS, ResourceTemplate(){
          Interrupt(ResourceProducer,...) {11,12}
                                                       // IRQs 11,12
       Method(_DIS) {...}
       Method(_CRS) {...}
       Method(_SRS, 1) {...}
   Device(LNKC) {
       Name(_HID, EISAID("PNP0C0F"))
                                                      // PCI interrupt link
       Name(_UID, 3)
       Name(_PRS, ResourceTemplate(){
           Interrupt(ResourceProducer,...) {12,14} // IRQs 12,14
       })
       Method(_DIS) {...}
       Method(_CRS) {...}
       Method(_SRS, 1) {...}
   Device(LNKD) {
       Name(_HID, EISAID("PNP0C0F"))
                                                       // PCI interrupt link
       Name(_UID, 4)
       Name(_PRS, ResourceTemplate(){
         Interrupt(ResourceProducer,...) {10,15}
                                                      // IRQs 10,15
       })
       Method(_DIS) {...}
       Method(_CRS) {...}
       Method(_SRS, 1) {...}
   Device(PCI0){
       Name(_PRT, Package{
           Package(0x0004FFFF, 2, \_SB_.LNKC, 0), // Slot 1, INTC // pathname
           \label{eq:package} $$ \operatorname{Ox0004FFFF}, 3, \S_{LNKD}, 0$, $$ // Slot 1, INTD $$ // can be used, $$ $$ $$
           Package { 0x0005FFFF, 0, LNKB, 0},
                                                  // Slot 2, INTA // or a simple
           Package{0x0005FFFF, 1, LNKC, 0},
                                                  // Slot 2, INTB // name segment
                                                  // Slot 2, INTC
                                                                    // utilizing the
           Package\{0x0005FFFF, 2, LNKD, 0\},
                                                  // Slot 2, INTD
           Package{0x0005FFFF, 3, LNKA, 0},
                                                                     // search rules
           Package{0x0006FFFF, 0, LNKC, 0}
                                                  // Video, INTA
       })
   }
```

6.2.14 PXM (Proximity)

This optional object is used to describe proximity domains within a machine. PXM evaluates to an integer that identifies the device as belonging to a specific proximity domain. OSPM assumes that two devices in the same proximity domain are tightly coupled. OSPM could choose to optimize its behavior based on this. For example, in a system with four processors and six memory devices, there might be two separate proximity domains (0 and 1), each with two processors and three memory devices. In this case, the OS may decide to run some software threads on the processors in proximity domain 0 and others on the processors in proximity domain 1. Furthermore, for performance reasons, it could choose to allocate memory for those threads from the memory devices inside the proximity domain common to the processor and the memory device rather than from a memory device outside of the processor's proximity domain. PXM can be used to identify any device belonging to a proximity domain. Children of a device belong to the same proximity domain as their parent unless they contain an overriding PXM. Proximity domains do not imply any ejection relationships.

An OS makes no assumptions about the proximity or nearness of different proximity domains. The difference between two integers representing separate proximity domains does not imply distance between the proximity domains (in other words, proximity domain 1 is not assumed to be closer to proximity domain 0 than proximity domain 6).

If the Local APIC ID / Local SAPIC ID / Local x2APIC ID or the GICC ACPI Processor UID of a dynamically added processor is not present in the System Resource Affinity Table (SRAT), a _PXM object must exist for the processor's device or one of its ancestors in the ACPI Namespace.

Arguments:

None

Return Value:

An **Integer** (DWORD) containing a proximity domain identifier.

6.2.15 _SLI (System Locality Information)

The System Locality Information Table (SLIT) table defined in <u>Section 5.2.17</u>, "System Locality Distance Information Table (SLIT)" provides relative distance information between all System Localities for use during OS initialization.

The value of each Entry [i,j] in the SLIT table, where i represents a row of a matrix and j represents a column of a matrix, indicates the relative distances from System Locality / Proximity Domain i to every other System Locality j in the system (including itself).

The i,j row and column values correlate to the value returned by the _PXM object in the ACPI namespace. See Section 6.2.14, "_PXM (Proximity)" for more information.

Dynamic runtime reconfiguration of the system may cause the distance between System Localities to change.

_SLI is an optional object that enables the platform to provide the OS with updated relative System Locality distance information at runtime. _SLI provide OSPM with an update of the relative distance from System Locality *i* to all other System Localities in the system.

Arguments:

None

Return Value:

A **Buffer** containing a system locality information table

If System Locality $i \ge N$, where N is the number of System Localities, the _SLI method returns a buffer that contains these relative distances:

$$[(i, 0), (i, 1), ..., (i, i-1), (i, i), (0, i), (1, i), ...(i-1, i), (i, i)]$$

If System Locality i < N, the SLI method returns a buffer that contains these relative distances:

$$[(i, 0), (i, 1), ..., (i, i), ..., (i, N-1), (0, i), (1, i), ..., (i, i), ..., (N-1, i)]$$

Note: (i, i) is always a value of 10.




Figure 6-36 System Locality information Table

Figure 6-36 diagrams a 4-node system where the nodes are numbered 0 through 3 (Node n = Node 3) and the granularity is at the node level for the NUMA distance information. In this example we assign System Localities / Proximity Domain numbers equal to the node numbers (0-3). The NUMA relative distances between proximity domains as implemented in this system are described in the matrix represented in Table 6-168. Proximity Domains are represented by the numbers in the top row and left column. Distances are represented by the values in cells internal in the table from the domains

Table 6-168 Example Relative Distances Between Proximity Domains

Proximity Domain	0	1	2	3
0	10	15	20	18
1	15	10	16	24
2	20	16	10	12
3	18	24	12	10

An example of these distances between proximity domains encoded in a System Locality Information Table for consumption by OSPM at boot time is described in Table 6-169.

Table 6-169 Example System Locality Information Table

Field	Byte Length	Byte Offset	Description
Header			

Field	Byte Length	Byte Offset	Description
Signature	4	0	'SLIT'.
Length	4	4	60
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID.
OEM Table ID	8	16	For the System Locality Information Table, the table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision of System Locality Information Table for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For the DSDT, RSDT, SSDT, and PSDT tables, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For the DSDT, RSDT, SSDT, and PSDT tables, this is the revision for the ASL Compiler.
Number of System Localities	8	36	4
Entry[0][0]	1	44	10
Entry[0][1]	1	45	15
Entry[0][2]	1	46	20
Entry[0][3]	1	47	18
Entry[1][0]	1	48	15
Entry[1][1]	1	49	10
Entry[1][2]	1	50	16
Entry[1][3]	1	51	24
Entry[2][0]	1	52	20
Entry[2][1]	1	53	16
Entry[2][2]	1	54	10
Entry[2][3]	1	55	12
Entry[3][0]	1	56	18
Entry[3][1]	1	57	24
Entry[3][2]	1	58	12
Entry[3][3]	1	59	10

If a new node, "Node 4", is added, then <u>Table 6-170</u> represents the updated system's NUMA relative distances of proximity domains.

Table 6-170 Example Relative Distances Between Proximity Domains - 5 Node

Proximity Domain	0	1	2	3	4
0	10	15	20	18	17

Proximity Domain	0	1	2	3	4
1	15	10	16	24	21
2	20	16	10	12	14
3	18	24	12	10	23
4	17	21	14	23	10

The new node's SLI object would evaluate to a buffer containing [17,21,14,23,10,17,21,14,23,10].

Note: Some systems support interleave memory across the nodes. The SLIT representation of these systems is implementation specific.

6.2.16 _SRS (Set Resource Settings)

This optional control method takes one byte stream argument that specifies a new resource allocation for a device. The resource descriptors in the byte stream argument must be specified exactly as listed in the _CRS byte stream – meaning that the identical resource descriptors must appear in the identical order, resulting in a buffer of exactly the same length. Optimizations such as changing an IRQ descriptor to an IRQNoFlags descriptor (or vice-versa) must not be performed. Similarly, changing StartDependentFn to StartDependentFnNoPri is not allowed. A _CRS object can be used as a template to ensure that the descriptors are in the correct format. For more information, see the CRS object definition.

The settings must take effect before the SRS control method returns.

This method must not reference any operation regions that have not been declared available by a _REG method.

If the device is disabled, _SRS enables the device at the specified resources. _SRS is not used to disable a device; use the _DIS control method instead.

Arguments: (1)

Arg0 – A **Buffer** containing a Resource Descriptor byte stream

Return Value:

None

6.2.17 _CCA (Cache Coherency Attribute)

The _CCA object returns whether or not a bus-master device supports hardware managed cache coherency. Expected values are 0 to indicate it is not supported, and 1 to indicate that it is supported. All other values are reserved.

On platforms for which existing default cache-coherency behavior of the OS is not adequate, _CCA enables the OS to adapt to the differences. If used, _CCA must be included under all bus-master-capable devices defined as children of _SB, to ensure that the operating system knows when it can rely on hardware managed cache coherency. The value of _CCA is inherited by all descendants of these devices, so it need not be repeated for their children devices and will be ignored by OSPM if it is provided there. This includes slave devices on a shared DMA controller; thus these DMA controllers must also be defined in the namespace under the System Bus and include a CCA object.

If a device indicates it does not have hardware cache coherency support, then OSPM must use a software cache flushing algorithm to ensure stale or invalid data is not accessed from the caches.

If the _CCA object is not specified for any devices, the OSPM will rely on the following defaults: arm32 does not have hardware supported cache coherency, and x86, x64, and arm64 are hardware cache coherent.

Arguments:

None

Return Value:

An **Integer** indicating the device's support for hardware cache coherency

0 - The device does not have hardware managed cache coherency

1 - The device has hardware managed cache coherency

Other Values - Reserved

Note: There are restrictions related to when this object is evaluated which have implications for implementing this object as a control method. The _CCA method must only access Operation Regions that have been indicated to be available as defined by the _REG method. The _REG method is described in Section 6.5.4, "_REG (Region)."

6.2.17.1 **_CCA Example ASL**:

```
Scope (\_SB) {
   Device (XHCI) {
                                  // Cache-incoherent bus-master, child of \_SB
          Name (_CCA, ZERO)
                                   // Root PCI Bus
   Device (PCI0) {
          Name (_CCA, ONE)
                                   // Cache-coherent bus-master, child of \_SB
           Device (PRT0) {
                                   // Bus-master-capable, not a child of \_SB
                                   // Will inherit coherency from PCIO, no _CCA required
                  Device (NICO) {
                                   // Bus-master-capable, not a child of \_SB
                                   // Will inherit coherency from PRTO, no \_CCA required
   }
 Device (SDHC) {
          Name (_CCA, ONE)
                                   // Cache-coherent bus-master-capable, child of \_SB
   }
 Device (GPIO) {
                                   // Not bus-master-capable
                                   // _CCA not valid
 Device (DMAC) {
                                   // DMA controller; _CCA must be specified
          Name (_CCA, ONE)
                                   // Cache coherent bus-master, child of \_SB
 Device (SPI1) {
          Name (_CRS, ResourceTemplate()
                 {
                        FixedDMA(...)// Sharing the DMA, thus inherits coherency from it
                 })
                                   // _CCA not valid
```

6.3 Device Insertion, Removal, and Status Objects

The objects defined in this section provide mechanisms for handling dynamic insertion and removal of devices and for determining device and notification processing status.

Device insertion and removal objects are also used for docking and undocking mobile platforms to and from a peripheral expansion dock. These objects give information about whether or not devices

are present, which devices are physically in the same device (independent of which bus the devices live on), and methods for controlling ejection or interlock mechanisms.

The system is more stable when removable devices have a software-controlled, VCR-style ejection mechanism instead of a "surprise-style" ejection mechanism. In this system, the eject button for a device does not immediately remove the device, but simply signals the operating system. OSPM then shuts down the device, closes open files, unloads the driver, and sends a command to the hardware to eject the device.

- 1. If the device is physically inserted while the computer is in the working state (in other words, hot insertion), the hardware generates a general-purpose event.
- 2. The control method servicing the event uses the **Notify**(*device*,0) command to inform OSPM of the bus that the new device is on or the device object for the new device. If the Notify command points to the device object for the new device, the control method must have changed the device's status returned by _STA to indicate that the device is now present. The performance of this process can be optimized by having the object of the Notify as close as possible, in the namespace hierarchy, to where the new device resides. The Notify command can also be used from the _WAK control method (for more information about _WAK, see Section 7.3.5 "_WAK (System Wake)") to indicate device changes that may have occurred while the computer was sleeping. For more information about the Notify command, see Section 5.6.3 "Device Object Notification."
- 3. OSPM uses the identification and configuration objects to identify, configure, and load a device driver for the new device and any devices found below the device in the hierarchy.
- 4. If the device has a _LCK control method, OSPM may later run this control method to lock the device.

The new device referred to in step 2 need not be a single device, but could be a whole tree of devices. For example, it could point to the PCI-PCI bridge docking connector. OSPM will then load and configure all devices it found below that bridge. The control method can also point to several different devices in the hierarchy if the new devices do not all live under the same bus. (in other words, more than one bus goes through the connector).

For removing devices, ACPI supports both hot removal (system is in the S0 state), and warm removal (system is in a sleep state: S1-S4). This is done using the _EJx control methods. Devices that can be ejected include an _EJx control method for each sleeping state the device supports (a maximum of 2 _EJx objects can be listed). For example, hot removal devices would supply an _EJ0; warm removal devices would use one of _EJ1-EJ4. These control methods are used to signal the hardware when an eject is to occur.

The sequence of events for dynamically removing a device goes as follows:

- 1. The eject button is pressed and generates a general-purpose event. (If the system was in a sleeping state, it should wake the computer).
- 2. The control method for the event uses the **Notify**(*device*, 3) command to inform OSPM which specific device the user has requested to eject. Notify does not need to be called for every device that may be ejected, but for the top-level device. Any child devices in the hierarchy or any ejection-dependent devices on this device (as described by _EJD, below) are automatically removed.
- 3. The OS shuts down and unloads devices that will be removed.
- 4. If the device has a LCK control method, OSPM runs this control method to unlock the device.

- 5. The OS looks to see what _EJx control methods are present for the device. If the removal event will cause the system to switch to battery power (in other words, an undock) and the battery is low, dead, or not present, OSPM uses the lowest supported sleep state _EJx listed; otherwise it uses the highest state _EJx. Having made this decision, OSPM runs the appropriate _EJx control method to prepare the hardware for eject.
- 6. Warm removal requires that the system be put in a sleep state. If the removal will be a warm removal, OSPM puts the system in the appropriate Sx state. If the removal will be a hot removal, OSPM skips to step 8, below.
- 7. For warm removal, the system is put in a sleep state. Hardware then uses any motors, and so on, to eject the device. Immediately after ejection, the hardware transitions the computer to S0. If the system was sleeping when the eject notification came in, the OS returns the computer to a sleeping state consistent with the user's wake settings.
- 8. OSPM calls _STA to determine if the eject successfully occurred. (In this case, control methods do not need to use the **Notify**(*device*,3) command to tell OSPM of the change in _STA) If there were any mechanical failures, _STA returns 3: device present and not functioning, and OSPM informs the user of the problem.

Note: This mechanism is the same for removing a single device and for removing several devices, as in an undock.

ACPI does not disallow surprise-style removal of devices; however, this type of removal is not recommended because system and data integrity cannot be guaranteed when a surprise-style removal occurs. Because the OS is not informed, its device drivers cannot save data buffers and it cannot stop accesses to the device before the device is removed. To handle surprise-style removal, a general-purpose event must be raised. Its associated control method must use the Notify command to indicate which bus the device was removed from.

The device insertion and removal objects are listed in Table 6-171.

Table 6-171 Device Insertion, Removal, and Status Objects

Object	Description
_EDL	Object that evaluates to a package of namespace references of device objects that depend on the device containing _EDL.
_EJD	Object that evaluates to the name of a device object on which a device depends. Whenever the named device is ejected, the dependent device must receive an ejection notification.
_EJx	Control method that ejects a device.
_LCK	Control method that locks or unlocks a device.
_OST	Control method invoked by OSPM to convey processing status to the platform.
_RMV	Object that indicates that the given device is removable.
_STA	Control method that returns a device's status.

6.3.1 _EDL (Eject Device List)

This object evaluates to a package of namespace references containing the names of device objects that depend on the device under which the _EDL object is declared. This is primarily used to support docking stations. Before the device under which the _EDL object is declared may be ejected, OSPM prepares the devices listed in the _EDL object for physical removal.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of namespace references

Before OSPM ejects a device via the device's _EJx methods, all dependent devices listed in the package returned by _EDL are prepared for removal. Notice that _EJx methods under the dependent devices are not executed.

When describing a platform that includes a docking station, an _EDL object is declared under the docking station device. For example, if a mobile system can attach to two different types of docking stations, _EDL is declared under both docking station devices and evaluates to the packaged list of devices that must be ejected when the system is ejected from the docking station.

An ACPI-compliant OS evaluates the EDL method just prior to ejecting the device.

6.3.2 EJD (Ejection Dependent Device)

This object is used to specify the name of a device on which the device, under which this object is declared, is dependent. This object is primarily used to support docking stations. Before the device indicated by _EJD is ejected, OSPM will prepare the dependent device (in other words, the device under which this object is declared) for removal.

Arguments:

None

Return Value:

A String containing the device name

_EJD is evaluated once when the ACPI table loads. The EJx methods of the device indicated by _EJD will be used to eject all the dependent devices. A device's dependents will be ejected when the device itself is ejected.

Note: OSPM will not execute a dependent device's _EJx methods when the device indicated by _EJD is ejected.

When describing a platform that includes a docking station, usually more than one _EJD object will be needed. For example, if a dock attaches both a PCI device and an ACPI-configured device to a mobile system, then both the PCI device description package and the ACPI-configured device description package must include an _EJD object that evaluates to the name of the docking station (the name specified in an _ADR or _HID object in the docking station's description package). Thus, when the docking connector signals an eject request, OSPM first attempts to disable and unload the drivers for both the PCI and ACPI configured devices.

Note: An ACPI 1.0 OS evaluates the _EJD methods only once during the table load process. This greatly restricts a table designer's freedom to describe dynamic dependencies such as those created in scenarios with multiple docking stations. This restriction is illustrated in the example below; the _EJD information supplied via and ACPI 1.0-compatible namespace omits the IDE2

device from DOCK2's list of ejection dependencies. Starting in ACPI 2.0, OSPM is presented with a more in-depth view of the ejection dependencies in a system by use of the _EDL methods.

Example

An example use of _EJD and _EDL is as follows:

```
Scope(\_SB.PCI0) {
    Device(DOCK1) {
                                          // Pass through dock - DOCK1
       Name(_ADR, ...)
       Method(_EJ0, 0) {...}
       Method(DCK, 1) \{...\}
       Name(_BDN, ...)
       Method(_STA, 0) {0xF}
       Name(_EDL, Package( ) {
                                         // DOCK1 has two dependent devices - IDE2 and CB2
           \_SB.PCIO.IDE2,
           \_SB.PCIO.CB2})
   Device(DOCK2) {
                                         // Pass through dock - DOCK2
       Name(_ADR, ...)
       Method(_EJ0, 0) {...}
       Method(_DCK, 1) {...}
       Name(_BDN, ...)
       Method(\_STA, 0) \{0x0\}
       Name(_EDL, Package( ) {
                                        // DOCK2 has one dependent device - IDE2
           \_SB.PCIO.IDE2})
    }
    Device(IDE1) {
                                          // IDE Drivel not dependent on the dock
        Name(_ADR, ...)
    Device(IDE2) {
                                         // IDE Drive2
       Name(_ADR, ...)
       Name(_EJD,"\\_SB.PCI0.DOCK1")
                                        // Dependent on DOCK1
    Device(CB2) {
                                         // CardBus Controller
       Name(_ADR, ...)
       Name(_EJD,"\\_SB.PCI0.DOCK1")
                                         // Dependent on DOCK1
                                          // end \_SB.PCIO
```

6.3.3 _EJx (Eject)

These control methods are optional and are supplied for devices that support a software-controlled VCR-style ejection mechanism or that require an action be performed such as isolation of power/data lines before the device can be removed from the system. To support warm (system is in a sleep state) and hot (system is in S0) removal, an _EJx control method is listed for each sleep state from which the device supports removal, where x is the sleeping state supported. For example, _EJ0 indicates the device supports hot removal; _EJ1-EJ4 indicate the device supports warm removal.

Arguments: (1)

Arg0 – An **Integer** containing a device ejection control

- 0 Cancel a mark for ejection request (EJ0 will never be called with this value)
- 1 Hot eject or mark for ejection

Return Value:

None

For hot removal, the device must be immediately ejected when OSPM calls the _EJ0 control method. The _EJ0 control method does not return until ejection is complete. After calling _EJ0, OSPM verifies the device no longer exists to determine if the eject succeeded. For _HID devices, OSPM evaluates the _STA method. For _ADR devices, OSPM checks with the bus driver for that device.

For warm removal, the _EJ1-_EJ4 control methods do not cause the device to be immediately ejected. Instead, they set proprietary registers to prepare the hardware to eject when the system goes into the given sleep state. The hardware ejects the device only after OSPM has put the system in a sleep state by writing to the SLP_EN register. After the system resumes, OSPM calls _STA to determine if the eject succeeded.

A device object may have multiple _EJx control methods. First, it lists an EJx control method for the preferred sleeping state to eject the device. Optionally, the device may list an EJ4 control method to be used when the system has no power (for example, no battery) after the eject. For example, a hot-docking notebook might list EJ0 and EJ4.

6.3.4 **_LCK** (Lock)

This control method is optional and is required only for a device that supports a software-controlled locking mechanism. When the OS invokes this control method, the associated device is to be locked or unlocked based upon the value of the argument that is passed. On a lock request, the control method must not complete until the device is completely locked.

Arguments: (1)

Arg0 – An **Integer** containing a device lock control

0 – Unlock the device

1 - Lock the device

Return Value:

None

When describing a platform, devices use either a LCK control method or an _EJx control method for a device.

6.3.5 OST (OSPM Status Indication)

This object is an optional control method that is invoked by OSPM to indicate processing status to the platform. During device ejection, device hot add, or other event processing, OSPM may need to perform specific handshaking with the platform. OSPM may also need to indicate to the platform its inability to complete a requested operation; for example, when a user presses an ejection button for a device that is currently in use or is otherwise currently incapable of being ejected. In this case, the processing of the ACPI **Eject Request** notification by OSPM fails. OSPM may indicate this failure to the platform through the invocation of the _OST control method. As a result of the status notification indicating ejection failure, the platform may take certain action including reissuing the notification or perhaps turning on an appropriate indicator light to signal the failure to the user.

Arguments: (3)

Arg0 – An Integer containing the source event

Arg1 – An **Integer** containing the status code

Arg2 – A **Buffer** containing status information

Return Value:

None

Argument Information:

Arg0 - source event: DWordConst

If the value of *source_event* is ≤ 0 xFF, this argument is the ACPI notification value whose processing generated the status indication. This is the value that was passed into the **Notify** operator.

If the value of source_event is 0x100 or greater then the OSPM status indication is a result of an OSPM action as indicated in <u>Table 6-172</u>. For example, a value of 0x103 will be passed into _OST for this argument upon the failure of a user interface invoked device ejection.

If OSPM is unable to identify the originating notification value, OSPM invokes _OST with a value that contains all bits set (ones) for this parameter.

Arg1 – Status Code: DWordConst. OSPM indicates a notification value specific status. See <u>Table 6-173</u>, <u>Table 6-174</u>, and <u>Table 6-176</u> for status code descriptions.

Arg2 – A buffer containing detailed OSPM-specific information about the status indication. This argument may be null.

Table	6-172	DOT	Source	Event	Codos
i anie	D-1/2	USI	Source	Event	Codes

Source Event Code	Description
0-0xFF	Reserved for Notification Values
0x100	Operation System Shutdown Processing
0x101-0x102	Reserved
0x103	Ejection Processing
0x104-0x1FF	Reserved
0x200	Insertion Processing
0x201-0xFFFFFFF	Reserved

Table 6-173 General Processing Status Codes

Status Code	Description
0	Success
1	Non-specific failure
2	Unrecognized Notify Code
3-0x7F	Reserved
0x80-0xFFFFFFF	Notification value specific status codes

Table 6-174 Operating System Shutdown Processing (Source Events: 0x100) Status Codes

Status Code	Description	
0x80	OS Shutdown Request denied	
0x81	OS Shutdown in progress	
0x82	OS Shutdown completed	
0x83	OS Graceful Shutdown not supported	
0x84-0xFFFFFFF	Reserved	

6.3.5.1 Processing Sequence for Graceful Shutdown Request:

Following receipt of the Graceful Shutdown Request (see <u>Table 5-131</u>, value 0x0C) the OS will be responsible for responding with one of the following status codes:

- 0x80 (OS Shutdown Request denied) –This value will be sent if the OS is not capable of performing a graceful shutdown.
- 0x81 (OS Shutdown in progress) The OS has initiated the graceful shutdown procedure.
- 0x83 (OS Graceful Shutdown not supported) The OS does not support the Graceful Shutdown Request.

If the OS does initiate a graceful shutdown it should continue to generate the "OS Shutdown in progress" message (_OST source event 0x100 status code 0x81) every 10 seconds. This functions as a heartbeat so that the service which requested the graceful shutdown knows that the request is currently being processed. The platform should assume that the OS shutdown is not proceeding if it does not receive the "OS Shutdown in progress" message for 60 seconds.

When the graceful shutdown procedure has completed the OSPM will send the "OS Shutdown completed" message and then transition the platform to the G2 "soft-off" power state.

Table 6-175 Ejection Request / Ejection Processing (Source Events: 0x03 and 0x103) Status Codes

Status Code	Description		
0x80	Device ejection not supported by OSPM		
0x81	Device in use by application		
0x82	Device Busy		
0x83	Ejection dependency is busy or not supported for ejection by OSPM		
0x84	Ejection is in progress (pending)		
0x85-0xFFFFFFF	Reserved		

Table 6-176 Insertion Processing (Source Event: 0x200) Status Codes

Status Code	Description		
0x80	Device insertion in progress (pending)		
0x81	Device driver load failure		
0x82	Device insertion not supported by OSPM		
0x83-0x8F	Reserved		

Status Code	Description		
0x90-0x9F	Insertion failure – Resources Unavailable as described by the following bit encodings:		
	Bit[3]	Bus or Segment Numbers	
	Bit[2]	Interrupts	
	Bit[1]	I/O	
	Bit[0]	Memory	
0xA0-0xFFFFFFF	Reserved		

It is possible for the platform to issue multiple notifications to OSPM and for OSPM to process the notifications asynchronously. As such, OSPM may invoke _OST for notifications independent of the order the notification are conveyed by the platform or by software to OSPM.

The figure below provides and example event flow of device ejection on a platform employing the _OST object.




Figure 6-37 Device Ejection Flow Example Using _OST

Note: To maintain compatibility with OSPM implementations of previous revisions of the ACPI specification, the platform must not rely on OSPM's evaluation of the _OST object for proper platform operation.

Example ASL for OST usage:

```
External (\_SB.PCI4, DeviceObj)
Scope(\_SB.PCI4) {
   OperationRegion(LED1, SystemIO, 0x10C0, 0x20)
   Field(LED1, AnyAcc, NoLock, Preserve)
        // LED controls
       SOLE,
               1,
                                                 // Slot 0 Ejection Progress LED
       SOLF,
                1,
                                                 // Slot 0 Ejection Failure LED
       S1LE,
                                                 // Slot 1 Ejection Progress LED
                1,
               1,
       S1LF,
                                                 // Slot 1 Ejection Failure LED
               1,
       S2LE,
                                                // Slot 2 Ejection Progress LED
               1,
       S2LF,
                                                // Slot 2 Ejection Failure LED
               1,
                                                // Slot 3 Ejection Progress LED
       S3LE,
        S3LF, 1
                                                // Slot 3 Ejection Failure LED
   Device(SLT3) {
                                                 // hot plug device
       Name(_ADR, 0x000C0003)
       Method(_OST, 3, Serialized) {
                                                  // OS calls _OST with notify code 3 or 0x103
                                                  // and status codes 0x80-0x83
                                                  // to indicate a hot remove request failure.
                                                  // Status code 0x84 indicates an ejection
                                                  // request pending.
             If(LEqual(Arg0,Ones))
                                                  // Unspecified event
                                                  // Perform generic event processing here
           Switch(And(Arg0,0xFF))
                                                  // Mask to retain low byte
                Case(0x03)
                                                 // Ejection request
                    Switch(Arg1)
                        Case(Package(){0x80, 0x81, 0x82, 0x83})
                                                 // Ejection Failure for some reason
                            Store(Zero, ^^S3LE)
                                                  // Turn off Ejection Progress LED
                                                 // Turn oil Ejection I...
// Turn on Ejection Failure LED
                            Store(One, ^^S3LF)
                       Case(0x84)
                                                  // Eject request pending
                            Store(One, ^^S3LE)
                                                 // Turn on Ejection Request LED
                            Store(Zero, ^^S3LF)
                                                 // Turn off Ejection Failure LED
                    }
        } // end _OST
```

6.3.6 **_RMV** (Remove)

The optional _RMV object indicates to OSPM whether the device can be removed while the system is in the working state and does not require any ACPI system firmware actions to be performed for the device to be safely removed from the system (in other words, any device that only supports surprise-style removal). Any such removable device that does not have _LCK or _EJx control methods must have an _RMV object. This allows OSPM to indicate to the user that the device can be removed and to provide a way for shutting down the device before removing it. OSPM will transition the device into D3 before telling the user it is safe to remove the device.

This method is reevaluated after a device-check notification.

Arguments:

None

Return Value:

An **Integer** containing the device removal status

- 0 The device cannot be removed
- 1 The device can be removed

Note: Operating Systems implementing ACPI 1.0 interpret the presence of this object to mean that the device is removable.

6.3.7 **_STA** (Status)

This object returns the current status of a device, which can be one of the following: enabled, disabled, or removed.

OSPM evaluates the _STA object before it evaluates a device _INI method. The return values of the Present and Functioning bits determines whether _INI should be evaluated and whether children of the device should be enumerated and initialized. See <u>Section 6.5.1</u>, "_INI (Init)".

If a device object (including the processor object) does not have an _STA object, then OSPM assumes that the device is present, enabled, shown in the UI, and functioning.

This method must not reference any operation regions that have not been declared available by a REG method.

Arguments:

None

Return Value:

An **Integer** containing a device status bitmap:

- Bit 0 Set if the device is present.
- Bit 1 Set if the device is enabled and decoding its resources.
- Bit 2 Set if the device should be shown in the UI.
- Bit 3 Set if the device is functioning properly (cleared if device failed its diagnostics).
- Bit 4 Set if the battery is present.
- Bits 5–31 Reserved (must be cleared).

Return Value Information

If bit 0 is cleared, then bit 1 must also be cleared (in other words, a device that is not present cannot be enabled).

A device can only decode its hardware resources if both bits 0 and 1 are set. If the device is not present (bit 0 cleared) or not enabled (bit 1 cleared), then the device must not decode its resources.

If a device is present in the machine, but should not be displayed in OSPM user interface, bit 2 is cleared. For example, a notebook could have joystick hardware (thus it is present and decoding its resources), but the connector for plugging in the joystick requires a port replicator. If the port replicator is not plugged in, the joystick should not appear in the UI, so bit 2 is cleared.

_STA may return bit 0 clear (not present) with bit 3 set (device is functional). This case is used to indicate a valid device for which no device driver should be loaded (for example, a bridge device.) Children of this device may be present and valid. OSPM should continue enumeration below a device whose _STA returns this bit combination.

Bit 4 of _STA applies only to the Control Method Battery Device (PNP0C0A). For all other devices, OSPM must ignore this bit.

If a device object (including the processor object) does not have an _STA object, then OSPM assumes that all of the above bits are set (i.e., the device is present, enabled, shown in the UI, and functioning).

6.4 Resource Data Types for ACPI

The _CRS, _PRS, and _SRS control methods use packages of resource descriptors to describe the resource requirements of devices.

6.4.1 ASL Macros for Resource Descriptors

ASL includes some macros for creating resource descriptors. The ASL syntax for these macros is defined in <u>Section 19.5</u>, "ASL Operator Reference", along with the other ASL operators.

6.4.2 Small Resource Data Type

A small resource data type may be 2 to 8 bytes in size and adheres to the following format:

Table 6-177 Small Resource Data Type Tag Bit Definitions

Offset	Field		
Byte 0	Tag Bit[7]	Tag Bits[6:3]	Tag Bits [2:0]
	Type-0 (Small item)	Small item name	Length-n bytes
Bytes 1 to n	Data bytes (Length 0 – 7)		

The following small information items are currently defined for Plug and Play devices:

Table 6-178 Small Resource Items

Small Item Name	Value
Reserved	0x00-0x03
IRQ Format Descriptor	0x04
DMA Format Descriptor	0x05
Start Dependent Functions Descriptor	0x06
End Dependent Functions Descriptor	0x07
I/O Port Descriptor	0x08
Fixed Location I/O Port Descriptor	0x09
Fixed DMA Descriptor	0x0A
Reserved	0x0B-0x0D
Vendor Defined Descriptor	0x0E
End Tag Descriptor	0x0F

6.4.2.1 IRQ Descriptor

Type 0, Small Item Name 0x4, Length = 2 or 3

The IRQ data structure indicates that the device uses an interrupt level and supplies a mask with bits set indicating the levels implemented in this device. For standard PC-AT implementation there are 15 possible interrupts so a two-byte field is used. This structure is repeated for each separate interrupt required.

Table 6-179 IRQ Descriptor Definition

Offset	Field Name
Byte 0	Value = 0x22 or 0x23 (0010001nB) - Type = 0, Small item name = 0x4, Length = 2 or 3
Byte 1	IRQ mask bits[7:0], _ INT Bit[0] represents IRQ0, bit[1] is IRQ1, and so on.
Byte 2	IRQ mask bits[15:8], _ INT Bit[0] represents IRQ8, bit[1] is IRQ9, and so on.

Offset	Field Name	
Byte 3	IRQ Information. Each bit, when set, indicates this device is capable of driving a certain type of interrupt. (Optional—if not included then assume edge sensitive, high true interrupts.) These bits can be used both for reporting and setting IRQ resources. Note: This descriptor is meant for describing interrupts that are connected to PIC-compatible interrupt controllers, which can only be programmed for Active-High-Edge-Triggered or Active-Low-Level-Triggered interrupts. Any other combination is invalid. The Extended Interrupt Descriptor can be used to describe other combinations.	
	Bit[7:6] Reserved (must be 0) Bit[5] Wake Capability, _WKC 0x0 = Not Wake Capable: This interrupt is not capable of waking the system. 0x1 = Wake Capable: This interrupt is capable of waking the system from a low-power idle state or a system sleep state.	
	Bit[4] Interrupt Sharing, _SHR 0x0 = Exclusive: This interrupt is not shared with other devices. 0x1 = Shared: This interrupt is shared with other devices.	
	Bit[3] Interrupt Polarity, _LL 0 Active-High – This interrupt is sampled when the signal is high, or true 1 Active-Low – This interrupt is sampled when the signal is low, or false. Bit[2:1] Ignored	
	Bit[0] Interrupt Mode, _HE 0 Level-Triggered – Interrupt is triggered in response to signal in a low state. 1 Edge-Triggered – Interrupt is triggered in response to a change in signal state from low to high.	

Note: Low true, level sensitive interrupts may be electrically shared, but the process of how this might work is beyond the scope of this specification.

Note: If byte 3 is not included, High true, edge sensitive, non-shareable is assumed.

See <u>Section 19.5.63</u>, "IRQ (Interrupt Resource Descriptor Macro)," and <u>Section 19.5.64</u>, "IRQNoFlags (Interrupt Resource Descriptor Macro)," for a description of the ASL macros that create an IRQ descriptor.

6.4.2.2 DMA Descriptor

Type 0, Small Item Name 0x5, Length = 2

The DMA data structure indicates that the device uses a DMA channel and supplies a mask with bits set indicating the channels actually implemented in this device. This structure is repeated for each separate channel required.

Table 6-180 DMA Descriptor Definition

Offset	Field Name
Byte 0	Value = 0x2A (00101010B) - Type = 0, Small item name = 0x5, Length = 2
Byte 1	DMA channel mask bits[7:0] (channels 0 – 7), _DMA Bit[0] is channel 0, etc.

Offset	Field Name	
Byte 2	Bit[7]	Reserved (must be 0)
	Bits[6:5]	DMA channel speed supported, _TYP
	00	Indicates compatibility mode
	01	Indicates Type A DMA as described in the EISA
	10	Indicates Type B DMA
	11	Indicates Type F
	Bits[4:3]	Ignored
	Bit[2]	Logical device bus master status, _BM
	0	Logical device is not a bus master
	1	Logical device is a bus master
	Bits[1:0]	DMA transfer type preference, _SIZ
	00	8-bit only
	01	8- and 16-bit
	10	16-bit only
	11	Reserved

See <u>Section 19.5.32</u>, "DMA (DMA Resource Descriptor Macro)," for a description of the ASL macro that creates a DMA descriptor.

6.4.2.3 Start Dependent Functions Descriptor

Type 0, Small Item Name 0x6, Length = 0 or 1

Each logical device requires a set of resources. This set of resources may have interdependencies that need to be expressed to allow arbitration software to make resource allocation decisions about the logical device. Dependent functions are used to express these interdependencies. The data structure definitions for dependent functions are shown here. For a detailed description of the use of dependent functions refer to the next section.

Table 6-181 Start Dependent Functions Descriptor Definition

Offs	set	Field Name
Byte	e 0	Value = 0x30 or 0x31 (0011000nB) - Type = 0, small item name = 0x6, Length = 0 or 1

Start Dependent Function fields may be of length 0 or 1 bytes. The extra byte is optionally used to denote the compatibility or performance/robustness priority for the resource group following the Start DF tag. The compatibility priority is a ranking of configurations for compatibility with legacy operating systems. This is the same as the priority used in the PNPBIOS interface. For example, for compatibility reasons, the preferred configuration for COM1 is IRQ4, I/O 3F8-3FF. The performance/robustness performance is a ranking of configurations for performance and robustness reasons. For example, a device may have a high-performance, bus mastering configuration that may not be supported by legacy operating systems. The bus-mastering configuration would have the highest performance/robustness priority while its polled I/O mode might have the highest compatibility priority.

If the Priority byte is not included, this indicates the dependent function priority is 'acceptable'. This byte is defined as:

Table 6-182 Start Dependent Function Priority Byte Definition

Bits	Definition	
1:0	Compatibility priority. Acceptable values are: 0 Good configuration: Highest Priority and preferred configuration 1 Acceptable configuration: Lower Priority but acceptable configuration 2 Sub-optimal configuration: Functional configuration but not optimal 3 Reserved	
3:2	Performance/robustness. Acceptable values are: 0 Good configuration: Highest Priority and preferred configuration 1 Acceptable configuration: Lower Priority but acceptable configuration 2 Sub-optimal configuration: Functional configuration but not optimal 3 Reserved	
7:4	Reserved (must be 0)	

Notice that if multiple Dependent Functions have the same priority, they are further prioritized by the order in which they appear in the resource data structure. The Dependent Function that appears earliest (nearest the beginning) in the structure has the highest priority, and so on.

See <u>Section 19.5.120</u>, "StartDependentFn (Start Dependent Function Resource Descriptor Macro)," for a description of the ASL macro that creates a Start Dependent Function descriptor.

6.4.2.4 End Dependent Functions Descriptor

Type 0, Small Item Name 0x7, Length = 0

Only one End Dependent Function item is allowed per logical device. This enforces the fact that Dependent Functions cannot be nested.

Table 6-183 End Dependent Functions Descriptor Definition

Offset	Field Name
Byte 0	Value = 0x38 (00111000B) - Type = 0, Small item name = 0x7, Length =0

See <u>Section 19.5.39</u>, "EndDependentFn (End Dependent Function Resource Descriptor Macro," for a description of the ASL macro that creates an End Dependent Functions descriptor.

6.4.2.5 I/O Port Descriptor

Type 0, Small Item Name 0x8, Length = 7

There are two types of descriptors for I/O ranges. The first descriptor is a full function descriptor for programmable devices. The second descriptor is a minimal descriptor for old ISA cards with fixed I/O requirements that use a 10-bit ISA address decode. The first type descriptor can also be used to describe fixed I/O requirements for ISA cards that require a 16-bit address decode. This is accomplished by setting the range minimum base address and range maximum base address to the same fixed I/O value.

Table 6-184 I/O Port Descriptor Definition

Offset	Field Name	Definition
Byte 0	I/O Port Descriptor	Value = 0x47 (01000111B) – Type = 0, Small item name = 0x8, Length = 7
Byte 1	Information	Bits[7:1] Reserved and must be 0 Bit[0] (_DEC) 1 The logical device decodes 16-bit addresses 0 The logical device only decodes address bits[9:0]
Byte 2	Range minimum base address, _ MIN bits[7:0]	Address bits[7:0] of the minimum base I/O address that the card may be configured for.
Byte 3	Range minimum base address, _ MIN bits[15:8]	Address bits[15:8] of the minimum base I/O address that the card may be configured for.
Byte 4	Range maximum base address, _MAX bits[7:0]	Address bits[7:0] of the maximum base I/O address that the card may be configured for.
Byte 5	Range maximum base address, _MAX bits[15:8]	Address bits[15:8] of the maximum base I/O address that the card may be configured for.
Byte 6	Base alignment, _ALN	Alignment for minimum base address, increment in 1-byte blocks.
Byte 7	Range length, _LEN	The number of contiguous I/O ports requested.

See <u>Section 19.5.62</u>, "IO (IO Resource Descriptor Macro," for a description of the ASL macro that creates an I/O Port descriptor.

6.4.2.6 Fixed Location I/O Port Descriptor

Type 0, Small Item Name 0x9, Length = 3

This descriptor is used to describe 10-bit I/O locations.

Table 6-185 Fixed-Location I/O Port Descriptor Definition

Offset	Field Name	Definition
Byte 0	Fixed Location I/O Port Descriptor	Value = 0x4B (01001011B) – Type = 0, Small item name = 0x9, Length = 3
Byte 1	Range base address, _BAS bits[7:0]	Address bits[7:0] of the base I/O address that the card may be configured for. This descriptor assumes a 10-bit ISA address decode.
Byte 2	Range base address, _BAS bits[9:8]	Address bits[9:8] of the base I/O address that the card may be configured for. This descriptor assumes a 10-bit ISA address decode.
Byte 3	Range length, _LEN	The number of contiguous I/O ports requested.

See <u>Section 19.5.50</u>, "FixedIO (Fixed I/O Resource Descriptor Macro," for a description of the ASL macro that creates a Fixed I/O Port descriptor.

6.4.2.7 Fixed DMA Descriptor

Type 0, Small Item Name 0xA, Length = 5

The Fixed DMA descriptor provides a means for platforms to statically assign DMA request lines and channels to devices connected to a shared DMA controller. This descriptor differs from the DMA descriptor in that it supports many more DMA request lines and DMA controller channels, as well as a flexible mapping between the two. The width of the bus used for transfers to the device is also provided. This structure is repeated for each separate request line/channel pair required, and can only be used in the _CRS object. (Dynamic arbitration of Fixed DMA resource is not supported.)

Table 6-186 Fixed DMA Resource Descriptor

Offset	Field Name	
Byte 0	Value = 0x55 (01010101B) - Type = 0, Small item name = 0xA, Length = 0x5	
Byte 1	DMA Request Line bits [7:0] _DMA[7:0] . A platform-relative number uniquely identifying the request line assigned. Request line-to-Controller mapping is done in a controller-specific OS driver.	
Byte 2	DMA Request Line bits [15:8] _DMA[15:8]	
Byte 3	DMA Channel bits[7:0] _TYP[7:0] . A controller-relative number uniquely identifying the controller's logical channel assigned. Channel numbers can be shared by multiple request lines.	
Byte 4	DMA Channel bits[15:8] _TYP[15:8]	
Byte 5	DMA Transfer WidthSIZ. Bus width that the device connected to this request line supports. 0x00 8-bit 0x01 16-bit 0x02 32-bit 0x03 64-bit 0x04 128-bit 0x05 256-bit 0x06-0xFF Reserved	

6.4.2.8 Vendor-Defined Descriptor

Type 0, Small Item Name 0xE, Length = 1 to 7

The vendor defined resource data type is for vendor use.

Table 6-187 Vendor-Defined Resource Descriptor Definition

Offset	Field Name
Byte 0	Value = 0x71 - 0x77 (01110nnnB) - Type = 0, small item name = 0xE, Length = 1-7
Byte 1 to 7	Vendor defined

See VendorShort (page 826) for a description of the ASL macro that creates a short vendor-defined resource descriptor.

6.4.2.9 End Tag

Type 0, Small Item Name 0xF, Length = 1

The End tag identifies an end of resource data.

Note: If the checksum field is zero, the resource data is treated as if the checksum operation succeeded. Configuration proceeds normally.

Table 6-188 End Tag Definition

Offset	Field Name	
Byte 0	Value = 0x79 (01111001B) - Type = 0, Small item name = 0xF, Length = 1	
Byte 1	Checksum covering all resource data after the serial identifier. This checksum is generated such that adding it to the sum of all the data bytes will produce a zero sum.	

The End Tag is automatically generated by the ASL compiler at the end of the **ResourceTemplate** statement.

6.4.3 Large Resource Data Type

To allow for larger amounts of data to be included in the configuration data structure the large format is shown below. This includes a 16-bit length field allowing up to 64 KB of data.

Table 6-189 Large Resource Data Type Tag Bit Definitions

Offset	Field Name
Byte 0	Value = 1xxxxxxxB - Type = 1 (Large item), Large item name = xxxxxxxB
Byte 1	Length of data items bits[7:0]
Byte 2	Length of data items bits[15:8]
Bytes 3 to (Length + 2)	Actual data items

The following large information items are currently defined:

Table 6-190 Large Resource Items

Large Item Name	Value
Reserved	0x00
24-bit Memory Range Descriptor	0x01
Generic Register Descriptor	0x02
Reserved	0x03
Vendor Defined Descriptor	0x04
32-bit Memory Range Descriptor	0x05
32-bit Fixed Location Memory Range Descriptor	0x06
DWORD Address Space Descriptor	0x07
WORD Address Space Descriptor	0x08

Large Item Name	Value
Extended IRQ Descriptor	0x09
QWORD Address Space Descriptor	0x0A
Extended Address Space Descriptor	0x0B
GPIO Connection Descriptor	0x0C
Reserved	0x0D
GenericSerialBus Connection Descriptor	0x0E
Reserved	0x0F – 0x7F

6.4.3.1 24-Bit Memory Range Descriptor

Type 1, Large Item Name 0x1

The 24-bit memory range descriptor describes a device's memory range resources within a 24-bit address space

Table 6-191 24-bit Memory Range Descriptor Definition.

Offset	Offset Field Name, ASL Field Definition Name	
Byte 0	24-bit Memory Range Descriptor	Value = 0x81 (10000001B) - Type = 1, Large item name = 0x01
Byte 1	Length, bits[7:0]	Value = 0x09 (9)
Byte 2	Length, bits[15:8]	Value = 0x00
Byte 3	Information	This field provides extra information about this memory. Bit[7:1] Ignored Bit[0] Write status, _RW 1 writeable (read/write) 0 non-writeable (read-only)
Byte 4	Range minimum base address, _ MIN , bits[7:0]	Address bits[15:8] of the minimum base memory address for which the card may be configured.
Byte 5	Range minimum base address, _ MIN , bits[15:8]	Address bits[23:16] of the minimum base memory address for which the card may be configured
Byte 6	Range maximum base address, _MAX, bits[7:0]	Address bits[15:8] of the maximum base memory address for which the card may be configured.
Byte 7	Range maximum base address, _MAX, bits[15:8]	Address bits[23:16] of the maximum base memory address for which the card may be configured
Byte 8	Base alignment, _ALN, bits[7:0]	This field contains the lower eight bits of the base alignment. The base alignment provides the increment for the minimum base address. (0x0000 = 64 KB)
Byte 9	Base alignment, _ALN, bits[15:8]	This field contains the upper eight bits of the base alignment. The base alignment provides the increment for the minimum base address. (0x0000 = 64 KB)
Byte 10	Range length, _ LEN , bits[7:0]	This field contains the lower eight bits of the memory range length. The range length provides the length of the memory range in 256 byte blocks.

Offset	Field Name, ASL Field Name	Definition
Byte 11	Range length, _LEN,	This field contains the upper eight bits of the memory range length.
	bits[15:8]	The range length field provides the length of the memory range in
		256 byte blocks.

Note: Address bits [7:0] of memory base addresses are assumed to be 0.

Note: A Memory range descriptor can be used to describe a fixed memory address by setting the range minimum base address and the range maximum base address to the same value.

Note: 24-bit Memory Range descriptors are used for legacy devices.

Note: Mixing of 24-bit and 32-bit memory descriptors on the same device is not allowed.

See <u>Section 19.5.78</u>, "Memory24 (Memory Resource Descriptor Macro)," for a description of the ASL macro that creates a 24-bit Memory descriptor.

6.4.3.2 Vendor-Defined Descriptor

Type 1, Large Item Name 0x4

The vendor defined resource data type is for vendor use.

Table 6-192 Large Vendor-Defined Resource Descriptor Definition

Offset	Field Name	Definition
Byte 0	Vendor Defined Descriptor	Value = 0x84 (10000100B) - Type = 1, Large item name = 0x04
Byte 1	Length, bits[7:0]	Lower eight bits of data length (UUID and vendor data)
Byte 2	Length, bits[15:8]	Upper eight bits of data length (UUID and vendor data)
Byte 3	UUID specific descriptor sub type	UUID specific descriptor sub type value
Byte 4-19	UUID	UUID Value
Byte 20- (Length+20)	Vendor Defined Data	Vendor defined data bytes

ACPI 3.0 defines the UUID specific descriptor subtype field and the UUID field to address potential collision of the use of this descriptor. It is strongly recommended that all newly defined vendor descriptors use these fields prior to Vendor Defined Data.

See VendorLong (page 826) for a description of the ASL macro that creates a long vendor-defined resource descriptor.

6.4.3.3 32-Bit Memory Range Descriptor

Type 1, Large Item Name 0x5

This memory range descriptor describes a device's memory resources within a 32-bit address space.

Table 6-193 32-Bit Memory Range Descriptor Definition

Offset	Field Name	Definition
Byte 0	32-bit Memory Range Descriptor	Value = 0x85 (10000101B) - Type = 1, Large item name = 0x05
Byte 1	Length, bits[7:0]	Value = 0x11 (17)
Byte 2	Length, bits[15:8]	Value = 0x00
Byte 3	Information	This field provides extra information about this memory. Bit[7:1] Ignored Bit[0] Write status, _RW 1 writeable (read/write) 0 non-writeable (read-only)
Byte 4	Range minimum base address, _MIN, bits[7:0]	Address bits[7:0] of the minimum base memory address for which the card may be configured.
Byte 5	Range minimum base address, _MIN, bits[15:8]	Address bits[15:8] of the minimum base memory address for which the card may be configured.
Byte 6	Range minimum base address, _MIN, bits[23:16]	Address bits[23:16] of the minimum base memory address for which the card may be configured.
Byte 7	Range minimum base address, _MIN, bits[31:24]	Address bits[31:24] of the minimum base memory address for which the card may be configured.
Byte 8	Range maximum base address, _MAX, bits[7:0]	Address bits[7:0] of the maximum base memory address for which the card may be configured.
Byte 9	Range maximum base address, _MAX, bits[15:8]	Address bits[15:8] of the maximum base memory address for which the card may be configured.
Byte 10	Range maximum base address, _MAX, bits[23:16]	Address bits[23:16] of the maximum base memory address for which the card may be configured.
Byte 11	Range maximum base address, _MAX, bits[31:24]	Address bits[31:24] of the maximum base memory address for which the card may be configured.
Byte 12	Base alignment, _ALN bits[7:0]	This field contains Bits[7:0] of the base alignment. The base alignment provides the increment for the minimum base address.
Byte 13	Base alignment, _ALN bits[15:8]	This field contains Bits[15:8] of the base alignment. The base alignment provides the increment for the minimum base address.
Byte 14	Base alignment, _ALN bits[23:16]	This field contains Bits[23:16] of the base alignment. The base alignment provides the increment for the minimum base address.
Byte 15	Base alignment, _ALN bits[31:24]	This field contains Bits[31:24] of the base alignment. The base alignment provides the increment for the minimum base address.
Byte 16	Range length, _ LEN bits[7:0]	This field contains Bits[7:0] of the memory range length. The range length provides the length of the memory range in 1-byte blocks.
Byte 17	Range length, _ LEN bits[15:8]	This field contains Bits[15:8] of the memory range length. The range length provides the length of the memory range in 1-byte blocks.

Offset	Field Name	Definition
Byte 18	Range length, _ LEN bits[23:16]	This field contains Bits[23:16] of the memory range length. The range length provides the length of the memory range in 1-byte blocks.
Byte 19	Range length, _ LEN bits[31:24]	This field contains Bits[31:24] of the memory range length. The range length provides the length of the memory range in 1-byte blocks.

Note: Mixing of 24-bit and 32-bit memory descriptors on the same device is not allowed.

See <u>Section 19.5.79</u>, "Memory32 (Memory Resource Descriptor Macro)," for a description of the ASL macro that creates a 32-bit Memory descriptor.

6.4.3.4 32-Bit Fixed Memory Range Descriptor

Type 1, Large Item Name 0x6

This memory range descriptor describes a device's memory resources within a 32-bit address space.

Table 6-194 32-bit Fixed-Location Memory Range Descriptor Definition

Offset	Field Name	Definition	
Byte 0	32-bit Fixed Memory Range Descriptor	Value = 0x86 (10000110B) - Type = 1, Large item name = 0x06	
Byte 1	Length, bits[7:0]	Value = 0x09 (9)	
Byte 2	Length, bits[15:8]	Value = 0x00	
Byte 3	Information	This field provides extra information about this memory. Bit[7:1] Ignored Bit[0] Write status, _RW 1 writeable (read/write) 0 non-writeable (read-only))	
Byte 4	Range base address, _BAS bits[7:0]	Address bits[7:0] of the base memory address for which the card may be configured.	
Byte 5	Range base address, _ BAS bits[15:8]	Address bits[15:8] of the base memory address for which the card may be configured.	
Byte 6	Range base address, _BAS bits[23:16]	Address bits[23:16] of the base memory address for which the card may be configured.	
Byte 7	Range base address, _BAS bits[31:24]	Address bits[31:24] of the base memory address for which the card may be configured.	
Byte 8	Range length, _ LEN bits[7:0]	This field contains Bits[7:0] of the memory range length. The range length provides the length of the memory range in 1-byte blocks.	
Byte 9	Range length, _ LEN bits[15:8]	This field contains Bits[15:8] of the memory range length. The range length provides the length of the memory range in 1-byte blocks.	
Byte 10	Range length, _ LEN bits[23:16]	This field contains Bits[23:16] of the memory range length. The range length provides the length of the memory range in 1-byte blocks.	
Byte 11	Range length, _ LEN bits[31:24]	This field contains Bits[31:24] of the memory range length. The range length provides the length of the memory range in 1-byte blocks.	

Note: Mixing of 24-bit and 32-bit memory descriptors on the same device is not allowed.

See <u>Section 19.5.80</u>, "Memory32Fixed (Memory Resource Descriptor)," for a description of the ASL macro that creates a 32-bit Fixed Memory descriptor.

6.4.3.5 Address Space Resource Descriptors

The QWORD, DWORD, WORD, and Extended Address Space Descriptors are general-purpose structures for describing a variety of types of resources. These resources also include support for advanced server architectures (such as multiple root buses), and resource types found on some RISC processors. These descriptors can describe various kinds of resources. The following table defines the valid combination of each field and how they should be interpreted.

Table 6-195 Valid combination of Address Space Descriptors fields

_LEN	_MIF	_MAF	Definition
0	0	0	Variable size, variable location resource descriptor for _PRS.
0	0	1	If _MIF is set, _MIN must be a multiple of (_GRA+1). If _MAF is set, _MAX must be
0	1	0	(a multiple of (_GRA+1))-1. OS can pick the resource range that satisfies following conditions: If _MIF is not set, start address is a multiple of (_GRA+1) and greater or equal to _MIN. Otherwise, start address is _MIN. If _MAF is not set, end address is (a multiple of (_GRA+1))-1 and less or equal to _MAX. Otherwise, end address is _MAX.
0	1	1	(Invalid combination)
> 0	0	0	Fixed size, variable location resource descriptor for _PRSLEN must be a multiple of (_GRA+1). OS can pick the resource range that satisfies following conditions: Start address is a multiple of (_GRA+1) and greater or equal to _MIN. End address is (start address+_LEN-1) and less or equal to _MAX.
> 0	0	1	(Invalid combination)
> 0	1	0	(Invalid combination)
> 0	1	1	Fixed size, fixed location resource descriptorGRA must be 0 and _LEN must be (_MAXMIN +1).

6.4.3.5.1 QWord Address Space Descriptor

Type 1, Large Item Name 0xA

The QWORD address space descriptor is used to report resource usage in a 64-bit address space (like memory and I/O).

Table 6-196 QWORD Address Space Descriptor Definition

Offset	Field Name	Definition
Byte 0	QWORD Address Space Descriptor	Value = 0x8A (10001010B) - Type = 1, Large item name = 0x0A
Byte 1	Length, bits[7:0]	Variable length, minimum value = 0x2B (43)
Byte 2	Length, bits[15:8]	Variable length, minimum value = 0x00

Offset	Field Name	Definition
Byte 3	Resource Type	Indicates which type of resource this descriptor describes. Defined values are: 0 Memory range 1 I/O range 2 Bus number range 3–191 Reserved 192-255 Hardware Vendor Defined
Byte 4	General Flags	Flags that are common to all resource types: Bits[7:4] Reserved (must be 0) Bit[3] Max Address Fixed, _MAF: 1 The specified maximum address is fixed 0 The specified maximum address is not fixed and can be changed Bit[2] Min Address Fixed,_MIF: 1 The specified minimum address is fixed 0 The specified minimum address is not fixed and can be changed Bit[1] Decode Type, _DEC: 1 This bridge subtractively decodes this address (top level bridges only) 0 This bridge positively decodes this address Bit[0] Ignored
Byte 5	Type Specific Flags	Flags that are specific to each resource type. The meaning of the flags in this field depends on the value of the Resource Type field (see above).
Byte 6	Address space granularity, _GRA bits[7:0]	A set bit in this mask means that this bit is decoded. All bits less significant than the most significant set bit must be set. That is, the value of the full Address Space Granularity field (all 64 bits) must be a number (2 ⁿ -1).
Byte 7	Address space granularity, _GRA bits[15:8]	
Byte 8	Address space granularity, _GRA bits[23:16]	
Byte 9	Address space granularity, _GRA bits[31:24]	
Byte 10	Address space granularity, _GRA bits[39:32]	
Byte 11	Address space granularity, _GRA bits[47:40]	
Byte 12	Address space granularity, _GRA bits[55:48]	

Offset	Field Name	Definition
Byte 13	Address space granularity, _GRA bits[63:56]	
Byte 14	Address range minimum, _MIN bits[7:0]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.
Byte 15	Address range minimum, _MIN bits[15:8]	
Byte 16	Address range minimum, _MIN bits[23:16]	
Byte 17	Address range minimum, _MIN bits[31:24]	
Byte 18	Address range minimum, _MIN bits[39:32]	
Byte 19	Address range minimum, _MIN bits[47:40]	
Byte 20	Address range minimum, _MIN bits[55:48]	
Byte 21	Address range minimum, _MIN bits[63:56]	
Byte 22	Address range maximum, _MAX bits[7:0]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.
Byte 23	Address range maximum, _MAX bits[15:8]	
Byte 24	Address range maximum, _MAX bits[23:16]	
Byte 25	Address range maximum, _MAX bits[31:24]	
Byte 26	Address range maximum, _MAX bits[39:32]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.
Byte 27	Address range maximum, _MAX bits[47:40]	
Byte 28	Address range maximum, _MAX bits[55:48]	
Byte 29	Address range maximum, _MAX bits[63:56]	
Byte 30	Address Translation offset, _TRA bits[7:0]	For bridges that translate addresses across the bridge, this is the offset that must be added to the address on the secondary side to obtain the address on the primary side. Non-bridge devices must list 0 for all Address Translation offset bits.
Byte 31	Address Translation offset, _ TRA bits[15:8]	
Byte 32	Address Translation offset, _TRA bits[23:16]	

Offset	Field Name	Definition
Byte 33	Address Translation offset, _ TRA bits[31:24]	
Byte 34	Address Translation offset, _ TRA bits[39:32]	
Byte 35	Address Translation offset, _ TRA bits[47:40]	
Byte 36	Address Translation offset, _ TRA bits[55:48]	
Byte 37	Address Translation offset, _ TRA bits[63:56]	
Byte 38	Address length, _ LEN bits[7:0]	
Byte 39	Address length, _ LEN , bits[15:8]	
Byte 40	Address length, _LEN bits[23:16]	
Byte 41	Address length, _ LEN bits[31:24]	
Byte 42	Address length, _ LEN bits[39:32]	
Byte 43	Address length, _ LEN bits[47:40]	
Byte 44	Address length, _ LEN bits[55:48]	
Byte 45	Address length, _LEN bits[63:56]	
Byte 46	Resource Source Index	(Optional) Only present if Resource Source (below) is present. This field gives an index to the specific resource descriptor that this device consumes from in the current resource template for the device object pointed to in Resource Source.
String	Resource Source	(Optional) If present, the device that uses this descriptor consumes its resources from the resources produced by the named device object. If not present, the device consumes its resources out of a global pool. If not present, the device consumes this resource from its hierarchical parent.

See QWordIO (page 803), QWordMemory (page 805) and ASL_QWordAddressSpace for a description of the ASL macros that creates a QWORD Address Space descriptor.

6.4.3.5.2 DWord Address Space Descriptor

Type 1, Large Item Name 0x7

The DWORD address space descriptor is used to report resource usage in a 32-bit address space (like memory and I/O).

Table 6-197 DWORD Address Space Descriptor Definition

Offset	Field Name	Definition
Byte 0	DWORD Address Space Descriptor	Value = 0x87 (10000111B) - Type = 1, Large item name = 0x07
Byte 1	Length, bits[7:0]	Variable: Value = 23 (minimum)
Byte 2	Length, bits[15:8]	Variable: Value = 0 (minimum)
Byte 3	Resource Type	Indicates which type of resource this descriptor describes. Defined values are: 0 Memory range 1 I/O range 2 Bus number range 3–191 Reserved 192-255 Hardware Vendor Defined
Byte 4	General Flags	Flags that are common to all resource types: Bits[7:4]
Byte 5	Type Specific Flags	Flags that are specific to each resource type. The meaning of the flags in this field depends on the value of the Resource Type field (see above).
Byte 6	Address space granularity, _GRA bits[7:0]	A set bit in this mask means that this bit is decoded. All bits less significant than the most significant set bit must be set. (in other words, the value of the full Address Space Granularity field (all 32 bits) must be a number (2 ⁿ -1).
Byte 7	Address space granularity, _GRA bits[15:8]	
Byte 8	Address space granularity, _GRA bits [23:16]	
Byte 9	Address space granularity, _GRA bits [31:24]	
Byte 10	Address range minimum, _MIN bits [7:0]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.

Offset	Field Name	Definition
Byte 11	Address range minimum, _MIN bits [15:8]	
Byte 12	Address range minimum, _MIN bits [23:16]	
Byte 13	Address range minimum, _MIN bits [31:24]	
Byte 14	Address range maximum, _MAX bits [7:0]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.
Byte 15	Address range maximum, _MAX bits [15:8]	
Byte 16	Address range maximum, _MAX bits [23:16]	
Byte 17	Address range maximum, _MAX bits [31:24]	
Byte 18	Address Translation offset, _TRA bits [7:0]	For bridges that translate addresses across the bridge, this is the offset that must be added to the address on the secondary side to obtain the address on the primary side. Non-bridge devices must list 0 for all Address Translation offset bits.
Byte 19	Address Translation offset, _TRA bits [15:8]	
Byte 20	Address Translation offset, _TRA bits [23:16]	
Byte 21	Address Translation offset, _ TRA bits [31:24]	
Byte 22	Address Length, _LEN, bits [7:0]	
Byte 23	Address Length, _LEN, bits [15:8]	
Byte 24	Address Length, _LEN, bits [23:16]	
Byte 25	Address Length, _LEN, bits [31:24]	
Byte 26	Resource Source Index	(Optional) Only present if Resource Source (below) is present. This field gives an index to the specific resource descriptor that this device consumes from in the current resource template for the device object pointed to in Resource Source.
String	Resource Source	(Optional) If present, the device that uses this descriptor consumes its resources from the resources produced by the named device object. If not present, the device consumes its resources out of a global pool. If not present, the device consumes this resource from its hierarchical parent.

See DWordIO (page 754), DWordMemory (page 756) and ASL_DWordAddressSpace for a description of the ASL macro that creates a DWORD Address Space descriptor

6.4.3.5.3 Word Address Space Descriptor

Type 1, Large Item Name 0x8

The WORD address space descriptor is used to report resource usage in a 16-bit address space (like memory and I/O).

Note: This descriptor is exactly the same as the DWORD descriptor specified in <u>Table 6-183</u>; the only difference is that the address fields are 16 bits wide rather than 32 bits wide.

Table 6-198 WORD Address Space Descriptor Definition

Offset	Field Name	Definition
Byte 0	WORD Address Space Descriptor	Value = 0x88 (10001000B) - Type = 1, Large item name = 0x08
Byte 1	Length, bits[7:0]	Variable length, minimum value = 0x0D (13)
Byte 2	Length, bits[15:8]	Variable length, minimum value = 0x00
Byte 3	Resource Type	Indicates which type of resource this descriptor describes. Defined values are: 0 Memory range 1 I/O range 2 Bus number range 3–191 Reserved 192-255 Hardware Vendor Defined
Byte 4	General Flags	Flags that are common to all resource types: Bits[7:4] Reserved (must be 0) Bit[3] Max Address Fixed, _MAF: 1 The specified maximum address is fixed 0 The specified maximum address is not fixed and can be changed Bit[2] Min Address Fixed,_MIF: 1 The specified minimum address is fixed 0 The specified minimum address is not fixed and can be changed Bit[1] Decode Type, _DEC: 1 This bridge subtractively decodes this address (top level bridges only) 0 This bridge positively decodes this address Bit[0] Ignored
Byte 5	Type Specific Flags	Flags that are specific to each resource type. The meaning of the flags in this field depends on the value of the Resource Type field (see above).
Byte 6	Address space granularity, _GRA bits[7:0]	A set bit in this mask means that this bit is decoded. All bits less significant than the most significant set bit must be set. (In other words, the value of the full Address Space Granularity field (all 16 bits) must be a number (2 ⁿ -1).
Byte 7	Address space granularity, _GRA bits[15:8]	

Offset	Field Name	Definition
Byte 8	Address range minimum, _MIN, bits [7:0]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.
Byte 9	Address range minimum, _MIN, bits [15:8]	
Byte 10	Address range maximum, _MAX, bits [7:0]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.
Byte 11	Address range maximum, _MAX, bits [15:8]	
Byte 12	Address Translation offset, _TRA, bits [7:0]	For bridges that translate addresses across the bridge, this is the offset that must be added to the address on the secondary side to obtain the address on the primary side. Non-bridge devices must list 0 for all Address Translation offset bits.
Byte 13	Address Translation offset, _TRA, bits [15:8]	
Byte 14	Address Length, _LEN, bits [7:0]	
Byte 15	Address Length, _LEN, bits [15:8]	
Byte 16	Resource Source Index	(Optional) Only present if Resource Source (below) is present. This field gives an index to the specific resource descriptor that this device consumes from in the current resource template for the device object pointed to in Resource Source.
String	Resource Source	(Optional) If present, the device that uses this descriptor consumes its resources from the resources produced by the named device object. If not present, the device consumes its resources out of a global pool. If not present, the device consumes this resource from its hierarchical parent.

See WordIO (page 829), WordBusNumber (page 828) and ASL_WordAddressSpace for a description of the ASL macros that create a Word address descriptor.

6.4.3.5.4 Extended Address Space Descriptor

Type 1, Large Item Name 0xB

The Extended Address Space descriptor is used to report resource usage in the address space (like memory and I/O).

Table 6-199 Extended Address Space Descriptor Definition

Offset	Field Name	Definition
Byte 0	Extended Address Space Descriptor	Value = 0x8B (10001011B) - Type = 1, Large item name = 0x0B
Byte 1	Length, bits[7:0]	Value = 0x35 (53)
Byte 2	Length, bits[15:8]	Value = 0x00

Offset	Field Name	Definition
Byte 3	Resource Type	Indicates which type of resource this descriptor describes. Defined values are: 0 Memory range 1 I/O range 2 Bus number range 3–191 Reserved 192-255 Hardware Vendor Defined
Byte 4	General Flags	Flags that are common to all resource types: Bits[7:4] Reserved (must be 0) Bit[3] Max Address Fixed, _MAF: 1 The specified maximum address is fixed 0 The specified maximum address is not fixed and can be changed Bit[2] Min Address Fixed,_MIF: 1 The specified minimum address is fixed 0 The specified minimum address is not fixed and can be changed Bit[1] Decode Type, _DEC: 1 This bridge subtractively decodes this address (top level bridges only) 0 This bridge positively decodes this address Bit[0] Consumer/Producer: 1—This device consumes this resource 0—This device produces and consumes this resource
Byte 5	Type Specific Flags	Flags that are specific to each resource type. The meaning of the flags in this field depends on the value of the Resource Type field (see above). For the Memory Resource Type, the definition is defined in <u>Section 6.4.3.5.5</u> . For other Resource Types, refer to the existing definitions for the Address Space Descriptors.
Byte 6	Revision ID	Indicates the revision of the Extended Address Space descriptor. For ACPI 3.0, this value is 1.
Byte 7	Reserved	0
Byte 8	Address space granularity, _GRA bits[7:0]	A set bit in this mask means that this bit is decoded. All bits less significant than the most significant set bit must be set. That is, the value of the full Address Space Granularity field (all 64 bits) must be a number (2 ⁿ -1).
Byte 9	Address space granularity, _GRA bits[15:8]	
Byte 10	Address space granularity, _GRA bits[23:16]	
Byte 11	Address space granularity, _GRA bits[31:24]	
Byte 12	Address space granularity, _GRA bits[39:32]	
Byte 13	Address space granularity, _GRA bits[47:40]	

Offset	Field Name	Definition
Byte 14	Address space granularity, _GRA bits[55:48]	
Byte 15	Address space granularity, _GRA bits[63:56]	
Byte 16	Address range minimum, _MIN bits[7:0]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.
Byte 17	Address range minimum, _MIN bits[15:8]	
Byte 18	Address range minimum, _MIN bits[23:16]	
Byte 19	Address range minimum, _MIN bits[31:24]	
Byte 20	Address range minimum, _MIN bits[39:32]	
Byte 21	Address range minimum, _MIN bits[47:40]	
Byte 22	Address range minimum, _MIN bits[55:48]	
Byte 23	Address range minimum, _MIN bits[63:56]	
Byte 24	Address range maximum, _MAX bits[7:0]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.
Byte 25	Address range maximum, _MAX bits[15:8]	
Byte 26	Address range maximum, _MAX bits[23:16]	
Byte 27	Address range maximum, _MAX bits[31:24]	
Byte 28	Address range maximum, _MAX bits[39:32]	For bridges that translate addresses, this is the address space on the secondary side of the bridge.
Byte 29	Address range maximum, _MAX bits[47:40]	
Byte 30	Address range maximum, _MAX bits[55:48]	
Byte 31	Address range maximum, _MAX bits[63:56]	
Byte 32	Address Translation offset, _TRA bits[7:0]	For bridges that translate addresses across the bridge, this is the offset that must be added to the address on the secondary side to obtain the address on the primary side. Non-bridge devices must list 0 for all Address Translation offset bits.
Byte 33	Address Translation offset, _TRA bits[15:8]	
Byte 34	Address Translation offset, _TRA bits[23:16]	

Offset	Field Name	Definition
Byte 35	Address Translation offset, _TRA bits[31:24]	
Byte 36	Address Translation offset, _TRA bits[39:32]	
Byte 37	Address Translation offset, _TRA bits[47:40]	
Byte 38	Address Translation offset, _TRA bits[55:48]	
Byte 39	Address Translation offset, _TRA bits[63:56]	
Byte 40	Address length, _ LEN bits[7:0]	
Byte 41	Address length, _LEN, bits[15:8]	
Byte 42	Address length, _LEN bits[23:16]	
Byte 43	Address length, _ LEN bits[31:24]	
Byte 44	Address length, _ LEN bits[39:32]	
Byte 45	Address length, _ LEN bits[47:40]	
Byte 46	Address length, _ LEN bits[55:48]	
Byte 47	Address length, _ LEN bits[63:56]	
Byte 48	Type Specific Attribute, _ATT bits[7:0]	Attributes that are specific to each resource type. The meaning of the attributes in this field depends on the value of the Resource Type field (see above). For the Memory Resource Type, the definition is defined section <ref>. For other Resource Types, this field is reserved to 0.</ref>
Byte 49	Type Specific Attribute, _ATT bits[15:8]	
Byte 50	Type Specific Attribute, _ATT bits[23:16]	
Byte 51	Type Specific Attribute, _ATT bits[31:24]	
Byte 52	Type Specific Attribute, _ATT bits[39:32]	
Byte 53	Type Specific Attribute, _ATT bits[47:40]	
Byte 54	Type Specific Attribute, _ATT bits[55:48]	

Offset	Field Name	Definition
Byte 55	Type Specific Attribute, _ATT bits[63:56]	

See <u>Section 19.5.43</u>, "ExtendedSpace (Extended Address Space Resource Descriptor Macro)," for a description of the ASL macro that creates an Extended Address Space descriptor.

6.4.3.5.4.1 Type Specific Attributes

The meaning of the Type Specific Attributes field of the Extended Address Space Descriptor depends on the value of the Resource Type field in the descriptor. When Resource Type = 0 (memory resource), the Type Specific Attributes field values are defined as follows:

ACPI_MEMORY_UC – Memory cacheability attribute. The memory region supports being configured as not cacheable.

ACPI_MEMORY_WC – Memory cacheability attribute. The memory region supports being configured as write combining.

ACPI_MEMORY_WT – Memory cacheability attribute. The memory region supports being configured as cacheable with a "write through "policy. Writes that hit in the cache will also be written to main memory.

ACPI_MEMORY_WB – Memory cacheability attribute. The memory region supports being configured as cacheable with a "write back "policy. Reads and writes that hit in the cache do not propagate to main memory. Dirty data is written back to main memory when a new cache line is allocated.

ACPI_MEMORY_UCE – Memory cacheability attribute. The memory region supports being configured as not cacheable, exported, and supports the "fetch and add "semaphore mechanism.

ACPI_MEMORY_NV – Memory non-volatile attribute. The memory region is non-volatile. Use of memory with this attribute is subject to characterization.

Note: These bits are defined so as to match the UEFI definition when applicable.

6.4.3.5.5 Resource Type Specific Flags

The meaning of the flags in the Type Specific Flags field of the Address Space Descriptors depends on the value of the Resource Type field in the descriptor. The flags for each resource type are defined in the following tables:

Table 6-200 Memory Resource Flag (Resource Type = 0) Definitions

Bits	Meaning		
Bits[7:6]	Reserved (must be 0)		
Bit[5]	Memory to I/O Translation, _TTP 1 TypeTranslation: This resource, which is memory on the secondary side of the bridge, is I/O on the primary side of the bridge. 0 TypeStatic: This resource, which is memory on the secondary side of the bridge, is also memory on the primary side of the bridge.		
Bits[4:3]	Memory attributes, _MTP. These bits are only defined if this memory resource describes system RAM. For a definition of the labels described here, see Section 15, "System Address Map Interfaces." 0 AddressRangeMemory 1 AddressRangeReserved 2 AddressRangeACPI 3 AddressRangeNVS		
Bits[2:1]	Memory attributes, _MEM 0 The memory is non-cacheable. 1 The memory is cacheable. 2 The memory is cacheable and supports write combining. 3 The memory is cacheable and prefetchable. (Notice: OSPM ignores this field in the Extended address space descriptor. Instead it uses the Type Specific Attributes field to determine memory attributes)		
Bit[0]	Write status, _RW 1 This memory range is read-write. 0 This memory range is read-only.		

Table 6-201 I/O Resource Flag (Resource Type = 1) Definitions

Bits	Meaning	
Bits[7:6]	Reserved (must be 0)	
Bit[5]	Sparse Translation, _ TRS. This bit is only meaningful if Bit[4] is set. 1 SparseTranslation: The primary-side memory address of any specific I/O port within the secondary-side range can be found using the following function.	
	address = (((port & 0xFFFc) << 10) (port & 0xFFF)) + _TRA	
	In the address used to access the I/O port, bits[11:2] must be identical to bits[21:12], this gives four bytes of I/O ports on each 4 KB page.	
	0 DenseTranslation: The primary-side memory address of any specific I/O port within the secondary-side range can be found using the following function.	
	address = port + _TRA	

Bits	Meaning	
Bit[4]	 I/O to Memory Translation, _TTP 1 TypeTranslation: This resource, which is I/O on the secondary side of the bridge, is memory on the primary side of the bridge. 0 TypeStatic: This resource, which is I/O on the secondary side of the bridge, is also I/O on the primary side of the bridge. 	
Bit[3:2]	Reserved (must be 0)	
Bit[1:0]	on the primary side of the bridge.	

Table 6-202 Bus Number Range Resource Flag (Resource Type = 2) Definitions

Bits	Meaning
Bit[7:0]	Reserved (must be 0)

6.4.3.6 Extended Interrupt Descriptor

Type 1, Large Item Name 0x9

The Extended Interrupt Descriptor is necessary to describe interrupt settings and possibilities for systems that support interrupts above 15.

To specify multiple interrupt numbers, this descriptor allows vendors to list an array of possible interrupt numbers, any one of which can be used.

Table 6-203 Extended Interrupt Descriptor Definition

Offset	Field Name	Definition
Byte 0	Extended Interrupt Descriptor	Value = 0x89 (10001001B) - Type = 1, Large item name = 0x09
Byte 1	Length, bits[7:0]	Variable length, minimum value = 0x06
Byte 2	Length, bits[15:8]	Variable length, minimum value = 0x00

Offset	Field Name	Definition	
Byte 3	Interrupt Vector Flags	Interrupt Vector Information. Bit[7:5] Reserved (must be 0) Bit[4] Wake Capability, _WKC	
Byte 4	Interrupt table length	Indicates the number of interrupt numbers that follow. When this descriptor is returned from _CRS, or when OSPM passes this descriptor to _SRS, this field must be set to 1.	
Byte 4 <i>n</i> +5	Interrupt Number, _INT bits [7:0]	Interrupt number	
Byte 4 <i>n</i> +6	Interrupt Number, _INT bits [15:8]		
Byte 4n+7 Byte 4n+8	Interrupt Number, _INT bits [23:16] Interrupt Number, _INT bits [31:24]		
		Additional interrupt numbers	
Byte x	Resource Source Index	(Optional) Only present if Resource Source (below) is present. This field gives an index to the specific resource descriptor that this device consumes from in the current resource template for the device object pointed to in Resource Source.	
String	Resource Source	(Optional) If present, the device that uses this descriptor consumes its resources from the resources produces by the named device object. If not present, the device consumes its resources out of a global pool. If not present, the device consumes this resource from its hierarchical parent.	

Note: Low true, level sensitive interrupts may be electrically shared, the process of how this might work is beyond the scope of this specification.

If the OS is running using the 8259 interrupt model, only interrupt number values of 0-15 will be used, and interrupt numbers greater than 15 will be ignored.

See Interrupt (page 781) for a description of the ASL macro that creates an Extended Interrupt descriptor.

6.4.3.7 Generic Register Descriptor

Type 1, Large Item Name 0x2

The generic register descriptor describes the location of a fixed width register within any of the ACPI-defined address spaces.

Table 6-204 Generic Register Descriptor Definition

Offset	Field Name, ASL Field Name	Definition
Byte 0	Generic Register Descriptor	Value = 0x82 (10000010B)
		Type = 1, Large item name = 0x02
Byte 1	Length, bits[7:0]	Value = 0x0C (12)
Byte 2	Length, bits[15:8]	Value = 0x00
Byte 3	Address Space ID, _ASI	The address space where the data structure or register exists. Defined values are: 0x00 System Memory 0x01 System I/O 0x02 PCI Configuration Space 0x03 Embedded Controller 0x04 SMBus 0x0A PCC 0x7F Functional Fixed Hardware
Byte 4	Register Bit Width, _RBW	Indicates the register width in bits.
Byte 5	Register Bit Offset, _RBO	Indicates the offset to the start of the register in bits from the Register Address.
Byte 6	Access Size, _ ASZ	Specifies access size. 0 - Undefined (legacy reasons) 1 - Byte access 2 - Word access 3 - Dword access 4 - QWord access
Byte 7	Register Address, _ADR bits[7:0]	Register Address
Byte 8	Register Address, _ADR bits[15:8]	
Byte 9	Register Address, _ADR bits[23:16]	
Byte 10	Register Address, _ADR bits[31:24]	
Byte 11	Register Address, _ADR bits[39:32]	
Byte 12	Register Address, _ADR bits[47:40]	
Byte 13	Register Address, _ADR bits[55:48]	

Offset	Field Name, ASL Field Name	Definition
Byte 14	Register Address, _ADR bits[63:56]	

See Register (page 809) for a description of the ASL macro that creates a Generic Register resource descriptor.

6.4.3.8 Connection Descriptors

General-purpose I/O (GPIO) and Simple Peripheral Bus (SPB) controllers are hardware resources provided in silicon solutions to enable flexible configuration of a broad range of system designs. These controllers can provide input, output, interrupt and serial communication connections to arbitrary devices in a system. The function to which one of these connections is put depends on the specific device involved and the needs of the platform design. In order to support mobile platform architectures, ACPI abstracts these connections as resources.

6.4.3.8.1 GPIO Connection Descriptor

Type 1, Large Item Name 0xC

The GPIO Connection Descriptor describes connections between GPIO controllers and peripheral devices. Two types of GPIO connections can be described: IO connections and Interrupt connections, distinguished by the GPIO Connection Type value in the descriptor. GPIO controllers and the devices that connect to them may be located anywhere in the namespace, but the connection must be described in the peripheral device's resource objects (PRS, _CRS, etc.).

Table 6-205 GPIO Connection Descriptor Definition

Offset	Field Name	Definition
Byte 0	GPIO Connection Descriptor	Value = 0x8C, (10001100B) - Type = 1, Large item name = 0x0C
Byte 1	Length, bits[7:0]	Variable length, minimum value = 0x16 + L (22 + length of the Resource Source Name string)
Byte 2	Length, bits[15:8]	Variable length, minimum value = 0x00
Byte 3	Revision ID	Indicates the revision for the GPIO interrupt descriptor. This value must be 1.
Byte 4	GPIO Connection Type	Indicates the type of the descriptor: 0x00 = Interrupt Connection 0x01 = IO Connection 0x02 - 0xFF Reserved
Byte 5	General Flags, bits [7:0]	Flags. Bit[7:1] Reserved (must be 0) Bit[0] Consumer/Producer: 0x0 = This device produces and consumes this resource 0x1 = This device consumes this resource
Byte 6	General Flags, bits [15:8]	Bit[15:8] Reserved (must be 0).

Offset	Field Name	Definition
Byte 7	Interrupt and IO Flags, bits [7:0]	For Interrupt Connections: Bit[7:5] Reserved (must be 0) Bit[4] Wake Capability, _WKC 0x0 = Not Wake Capable: This interrupt is not capable of waking the system. 0x1 = Wake Capable: This interrupt is capable of waking the system from a low-power idle state or a system sleep state. Bit[3] Interrupt Sharing, _SHR 0x0 = Exclusive: This interrupt is not shared with other devices. 0x1 = Shared: This interrupt is shared with other devices. Bit[2:1] Interrupt Polarity, _POL 0x0 = Active-High: This interrupt is sampled when the signal is high, or true. 0x1 = Active-Low: This interrupt is sampled when the signal is low, or false. 0x2 = Active-Both: This interrupt is sampled on both rising and falling edges. Interrupt mode must be set to Edge-triggered. 0x3 = Reserved (do not use) Bit[0] Interrupt Mode, _MOD 0x0 = Level-Triggered: Interrupt is triggered in response to the signal being in either a high or low state. 0x1 = Edge-Triggered: This interrupt is triggered in response to a change in signal state, either high to low or low to high. For IO Connections: Bit[7:4] Reserved (must be 0) Bit[3] IO Sharing, _SHR 0x0 = Exclusive: This interrupt is not shared with other devices. Bit[2] Reserved (must be 0) Bit[1:0] IO Restriction _IOR 0x0 = This pin or pins can be used for either Input or Output. 0x1 = This pin or pins can only be used for Input, and the pin configuration must be preserved while not in use. 0x2 = This pin or pins can be used for either input or output, but the configuration must be preserved while not in use. 0x3 = This pin or pins can be used for either input or output, but the configuration must be preserved until explicitly changed.
Byte 8	Interrupt and IO Flags, bits [15:8]	Bit[15:8] Reserved (must be 0)

Offset	Field Name	Definition
Byte 9	Pin Configuration	_PPI 0x00 = Default Configuration (no configuration is applied) 0x01 = Pull-up 0x02 = Pull-down 0x03 = No Pull 0x04 - 0x7F; Reserved (do not use) 0x80 - 0xFF; Vendor-defined values
Byte 10	Output Drive Strength, bits [7:0]	The output-drive capability, in hundredths of milliamperes, to be applied when configuring the pin for output (high byte)DRS[7:0]
Byte 11	Output Drive Strength, bits [15:8]	The output-drive capability, in hundredths of milliamperes, to be applied when configuring the pin for output (high byte)DRS[15:8]
Byte 12	Debounce timeout, bits [7:0]	The debounce timeout, in hundredths of milliseconds, to be applied when configuring the pin for interrupt (low byte)DBT[7:0]
Byte 13	Debounce timeout, bits [15:8]	The debounce timeout, in hundredths of milliseconds, to be applied when configuring the pin for interrupt (high byte)DBT [15:8]
Byte 14	Pin Table Offset[7:0]	Offset to the start of the pin table (low byte). The offset is relative to the start of this descriptor. NOTE: The number of pins in the table can be calculated from PinCount = (Resource Source Name Offset – Pin Table Offset) / 2
Byte 15	Pin Table Offset[15:8]	Offset to the start of the pin table (high byte). The offset is relative to the start of this descriptor.
Byte 16	Resource Source Index	Reserved for future use. This field must be 0.
Byte 17	Resource Source Name Offset[7:0]	Offset to the start of the resource source name (low byte). The offset is relative to the start of this descriptor. NOTE: The length of the ResourceSource name string can be calculated from Length L = Vendor Data Offset – Resource Source Name Offset. The length includes the string's terminating NULL character (if present)
Byte 18	Resource Source Name Offset[15:8]	Offset to the start of the resource source name (high byte). The offset is relative to the start of this descriptor.
Byte 19	Vendor Data Offset[7:0]	(low byte) Offset to the start of the Vendor-defined Data (the last byte of the ResourceSource + 1). This value must always be valid to allow for length calculations. In the case where there is no Vendor Data, this offset still must refer to the last byte of the ResourceSource + 1. The offset is relative to the start of this descriptor.

Offset	Field Name	Definition
Byte 20	Vendor Data Offset[15:8]	(high byte) Offset to the start of the Vendor-defined Data .(the last byte of the ResourceSource + 1). This value must always be valid to allow for length calculations. In the case where there is no Vendor Data, this offset still must refer to the last byte of the ResourceSource + 1. The offset is relative to the start of this descriptor.
Byte 21	Vendor Data Length [7:0]	Length of Vendor-defined Data (low-byte).
Byte 22	Vendor Data Length [15:8]	Length of Vendor-defined Data (high-byte).
Byte PinTableOffset[15:0] + 2n (n is the index into the pin table)	Pin Number, bits [7:0]	GPIO controller-relative pin number (low byte) PIN[7:0]. Pin numbers are zero-based. Pin number 0xFFFF = No Pin. OSPM will ignore this pin number.
Byte PinTableOffset[15:0] + 2n + 1 (n is the index into the pin table)	Pin Number, bits [15:8]	GPIO controller-relative pin number (high byte)PIN[15:8]. Pin numbers are zero-based. Pin number 0xFFFF = No Pin. OSPM will ignore this pin number.
Byte ResourceSourceNameO ffset[15:0]	Resource Source (length = L)	Name of the GPIO controller device to which this descriptor applies. The name can be a fully-qualified name, a relative name or a name segment that utilizes the namespace search rules.
Byte VendorDataOffset[15:0]	Vendor-defined Data	(Optional) Data specific to the GPIO controller device supplied by a vendor. This data is provided to the device driver for this GPIO ControllerVEN.

6.4.3.8.2 Serial Bus Connection Descriptors

Type 1, Large Item Name 0x0E

All Serial Bus Resource descriptors utilize the following format. For specific bus types, the type-specific fields are used.

Table 6-206 Serial Bus Connection Descriptor

Offset	Field Name	Definition
Byte 0	Serial Bus Type	Value = 0x8E (10001110B) - Type = 1, Large item name = 0x0E
Byte 1	Length, bits[7:0]	Variable length, minimum value = 0x09 + L(9 + ResourceSource string length)"
Byte 2	Length, bits[15:8]	Variable length, minimum value = 0x00
Byte 3	Revision ID	Indicates the revision of the Serial Bus Connection Descriptor. This value is 1.
Byte 4	Resource Source Index	Reserved (must be 0)

Offset	Field Name	Definition
Byte 5	Serial Bus Type	Serial Bus Type
		Indicates which type of serial bus connection this descriptor describes. Defined values are: 0
		1
		Reserved I2C
		2 SPI
		3 UART
		4-191 Reserved
		192-255 Hardware Vendor Defined
Byte 6	General Flags [7:0]	Flags that are common to all serial bus connection types. Bits[7:2]
		Reserved. Must be 0.
		Bit[1]
		Consumer/Producer: 0x1: This device consumes this resource
		0x0: This device consumes this resource 0x0: This device produces and consumes this resource
		Bit[0]
		Slave Mode. 0x0: The communication over this connection is
		initiated by the controller.
		0x1: The communication over this connection is initiated by the device.
Byte 7	Type Specific Flags, bits[7:0]	Flags specific to the indicated Serial Bus Type (see above).
Byte 8	Type Specific Flags, bits[15:8]	Flags specific to the indicated Serial Bus Type (see above).
Byte 9	Type Specific Revision ID	Revision ID for the data describing the serial bus connection specified by Serial Bus Type (see above).
Byte 10	Type Data Length, bits[7:0]	Variable length, minimum size depends on the indicated Serial Bus Type (see above).
Byte 11	Type Data Length, bits [15:8]	Variable length, minimum size depends on the indicated Serial Bus Type (see above).
Byte 12	Type Specific Data	(Optional) Data specific to the serial bus connection type indicated in Serial Bus Type (see above).
		Additional data specific to the serial bus connection type.

Offset	Field Name	Definition
String	Resource Source	Name of the serial bus controller device to which this connection descriptor applies. The name can be a fully qualified path, a relative path, or a simple name segment that utilizes the namespace search rules.

6.4.3.8.2.1 I2C Serial Bus Connection Resource Descriptor

Table 6-207 I2C Serial Bus Connection Descriptor

Offset	Field Name	Definition
Byte 0	I2C Bus Connection Descriptor	Value = 0x8E (10001110B) – Type = 1, Large item name = 0x0E
Byte 1	Length, bits [7:0]	Variable length, minimum value = 0xF + L (15 + ResourceSource string length)
Byte 2	Length, bits [15:8]	Variable, length minimum value = 0x00
Byte 3	Revision ID	Indicates the revision for the I2C Resource Descriptor. This value is 1.
Byte 4	Resource Source Index	Reserved (must be 0)
Byte 5	Serial Bus Type	Serial Bus Type value must be 1 for I2C
Byte 6	General Flags [7:0]	Flags that are common to all serial bus connection types. Bits[7:2] Reserved. Must be 0.
		Bit[1] Consumer/Producer: 0x1: This device consumes this resource 0x0: This device produces and consumes this resource
		Bit[0] Slave ModeSLV 0x0: The communication over this connection is initiated by the controller. 0x1: The communication over this connection is initiated by the device.
Byte 7	Type Specific Flags, bits[7:0]	Bits[7:1] Reserved. Must be 0. Bit[0] 10-bit addressing modeMOD 0x1: The connection uses 10-bit addressing 0x0: The connection uses 7-bit addressing.
Byte 8	Type Specific Flags, bits[15:8]	Reserved. Must be 0.
Byte 9	Type Specific Revision ID	Indicates the revision of the I2C-specific Serial Bus Connection Descriptor Data. This value is 1.

Device Configuration

Offset	Field Name	Definition
Byte 10	Type Data Length, bits[7:0]	Variable length, minimum value = 0x6 (6).
Byte 11	Type Data Length, bits [15:8]	Variable length, minimum size = 0x0 (0)
Byte 12	Connection Speed, bits [7:0]	Connection speed bits [7:0] of the maximum speed in hertz supported by this connectionSPE[7:0]
Byte 13	Connection Speed, bits [15:8]	Connection speed bits [15:8] of the maximum speed in hertz supported by this connectionSPE[15:8]
Byte 14	Connection Speed, bits [23:16]	Connection speed bits [23:16] of the maximum speed in hertz supported by this connectionSPE[23:16]
Byte 15	Connection Speed, bits [31:24]	Connection speed bits [31:24] of the maximum speed in hertz supported by this connectionSP[31:24]
Byte 16	Slave Address, bits [7:0]	Lower eight bits of the I2C bus address for this connectionADR[7:0] Bit[7] In 7-bit addressing mode this is reserved and must be 0. In 10-bit addressing mode this is bit 7 of the address. Bits[6:0] The lowest 7 bits of the address. In 7-bit addressing mode this represents the complete address.
Byte 17	Slave Address, bits[15:8]	Upper eight bits of the I2C bus address for this connection. The upper eight bits are to support 10-bit addressing and should be set to 0 if 7-bit addressing is being usedADR[15:8] Bits[15:10] Reserved. Must be 0. Bits[9:8] In 7-bit addressing mode these are reserved and must be 0. In 10-bit addressing mode these are the highest two bits of the address.
Byte 18	Vendor-defined Data	(Optional) Data specific to the controller device supplied by a vendor. The number of bytes in this field is Type Data Length – 6.
		(Optional) Additional vendor supplied data.
String	Resource Source (Length = L)	Name of the serial bus controller device to which this connection descriptor applies. The name can be a fully qualified path, a relative path, or a simple name segment that utilizes the namespace search rules

6.4.3.8.2.2 SPI Serial Bus Connection Resource Descriptor

Table 6-208 SPI Serial Bus Connection Descriptor

Offset	Field Name	Definition
Byte 0	SPI Bus Connection Descriptor	Value = 0x8E (10001111B) - Type = 1, Large item name = 0x0E
Byte 1	Length, bits[7:0]	Variable length, minimum value = 0x12 + L (18 + Resource Source string length)
Byte 2	Length, bits[15:8]	Variable length, minimum value = 0x00
Byte 3	Revision ID	Indicates the revision of the Serial Bus Connection Descriptor. This value is 1.
Byte 4	Resource Source Index	Reserved (must be 0)
Byte 5	Serial Bus Type	Serial Bus Type value must be 2 for SPI
Byte 6	General Flags[7:0]	Flags that are common to all serial bus connection types. Bits[7:2] Reserved. Must be 0.
		Bit[1] Consumer/Producer: 0x1: This device consumes this resource 0x0: This device produces and consumes this resource
		Bit[0] Slave ModeSLV 0x0: The communication over this connection is initiated by the controller. 0x1: The communication over this connection is initiated by the device.
Byte 7	Type Specific Flags, bits[7:0]	Bits [7:2] Reserved (must be 0) Bit [1]: Device PolarityDPL 1 - The device selection line is active high 0 - The device selection line is active low Bit [0]: Wire ModeMOD 1 - The connection is over 3 wires 0 - The connection is over 4 wires
Byte 8	Type Specific Flags, bits[15:8]	Reserved. Must be 0.
Byte 9	Type Specific Revision ID	Indicates the revision of the SPI-specific Serial Bus Connection Descriptor Data. This value must be 1.
Byte 10	Type Data Length, bits[7:0]	Variable length, minimum value = 0x9 (9).
Byte 11	Type Data Length, bits [15:8]	Variable length, minimum size = 0x0 (0)
Byte 12	Connection Speed, bits [7:0]	Connection speed bits [7:0] of the maximum speed in hertz supported by this connectionSPE[7:0]

Device Configuration

Offset	Field Name	Definition
Byte 13	Connection Speed, bits [15:8]	Connection speed bits [15:8] of the maximum speed in hertz supported by this connectionSPE[15:8]
Byte 14	Connection Speed, bits [23:16]	Connection speed bits [23:16] of the maximum speed in hertz supported by this connectionSPE[23:16]
Byte 15	Connection Speed, bits [31:24]	Connection speed bits [31:24] of the maximum speed in hertz supported by this connectionSPE[31:24]
Byte 16	Data Bit Length	The size in bits of the smallest transfer unitLEN
Byte 17	Phase	The phase (CPHA) of the clock pulse on which to capture data (the other being used to transmit). _PHA 0 - First phase 1 - Second phase
Byte 18	Polarity	The polarity of the clock (CPOL). This value indicates if the clock is low or high during the first phase (see Phase above). _POL 0 -Start Low 1 -Start High
Byte 19	Device Selection, bits [7:0]	Lower eight bits of the device selection value. This value is specific to the device and may refer to a chip-select line, GPIO line or other line selection mechanismADR[7:0]
Byte 20	Device Selection, bits [15:8]	Upper eight bits of the device selection value. This value is specific to the device and may refer to a chip-select line, GPIO line or other line selection mechanismADR[15:8]
Byte 21	Vendor Defined Data	(Optional) Data specific to the controller device supplied by a vendor. The number of bytes in this field is Type Data Length – 9.
		(Optional) Additional vendor supplied data.
String	Resource Source (Length = L)	Name of the serial bus controller device to which this connection descriptor applies. The name can be a fully qualified path, a relative path, or a simple name segment that utilizes the namespace search rules.

6.4.3.8.2.3 UART Serial Bus Connection Resource Descriptor

Table 6-209 UART Serial Bus Connection Descriptor

Offset	Field Name	Definition
Byte 0	Serial Bus Connection Descriptor	Value = 0x8E (10001110B) - Type = 1, Large item name = 0x0E
Byte 1	Length, bits[7:0]	Variable length, minimum value = 0x13 + L (17 + Resource Source string length)
Byte 2	Length, bits[15:8]	Variable length, minimum value = 0x00
Byte 3	Revision ID	Indicates the revision of the Serial Bus Connection Descriptor. This value is 1.
Byte 4	Resource Source Index	Reserved (must be 0)

Offset	Field Name	Definition
Byte 5	Serial Bus Type	Serial Bus Type value must be 3 for UART
Byte 6	General Flags [7:0]	Flags that are common to all serial bus connection types. Bits[17:2] Reserved. Must be 0.
		Bit[1 Consumer/Producer: 0x1: This device consumes this resource 0x0: This device produces and consumes this resource
		Bit[0] Slave ModeSLV 0x0: The communication over this connection is initiated by the controller. 0x1: The communication over this connection is initiated by the device.
Byte 7	Type Specific Flags, bits[7:0]	Bit [7] – Endian-nessEND Little Endian = 0 Big Endian = 1 Bit [6:4] – Data bits. Number of bits per byteLEN 000B – 5 bits 001B – 6 bits 010B – 7 bits 011B – 8 bits 100B – 9 bits Bits [3:2] – Stop Bits. Number of stop bits per characterSTB 00B (0) – none 01B (1) – 1 10B (2) – 1.5 11B (3) – 2 Bits [1:0] – Flow control. Indicates type of flow control for the connectionFLC 00B (0) – None 01B (1) – Hardware flow control 10B (2) – XON/XOFF
Byte 8	Type Specific Flags, bits[15:8]	Reserved. Must be 0.
Byte 9	Type Specific Revision ID	Indicates the revision of the UART-specific Serial Bus Connection Descriptor Data. This value must be 1.
Byte 10	Type Data Length, bits[7:0]	Variable length, minimum value = 0x0A (10).
Byte 11	Type Data Length, bits [15:8]	Variable length, minimum size = 0x0 (0)
Byte 12	Default Baud rate, bits[7:0]	Default baud rate of connection, in bits-per-secondSPE[7:0] Bits [7:0]

Device Configuration

Offset	Field Name	Definition
Byte 13	Default Baud rate, bits[15:8]	Default baud rate of connection, in bits-per-secondSPE[15:8] Bits[15:8]
Byte 14	Default Baud rate, bits[23:16]	Default baud rate of connection, in bits-per-secondSPE[23:16] Bits[23:16]
Byte 15	Default Baud rate, bits[31:24]	Default baud rate of connection, in bits-per-secondSPE[31:24] Bits[31:24].
Byte 16	Rx FIFO, bits[7:0]	Maximum receive buffer, in bytes, supported by this connectionRXL[7:0] Bits[7:0]
Byte 17	Rx FIFO, bits[15:8]	Maximum receive buffer, in bytes, supported by this connectionRXL[15:8] Bits[15:8]
Byte 18	Tx FIFO, bits[7:0]	Maximum receive buffer, in bytes, supported by this connectionTXL[7;0] Bits[7:0]
Byte 19	Tx FIFO, bits[15:8]	Maximum receive buffer, in bytes, supported by this connectionTXL[15:8] Bits[15:8]
Byte 20	Parity	ParityPAR None = 0x00 Even = 0x01 Odd = 0x02 Mark = 0x03 Space = 0x04
Byte 21	Serial Lines Enabled	Serial lines enabled (Enabled = 1, Disabled = 0)LIN Bit[7] - Request to Send (RTS) Bit[6] - Clear to Send (CTS) Bit[5] - Data Terminal Ready (DTR) Bit[4] - Data Set Ready (DSR) Bit[3] - Ring Indicator (RI) Bit[2] - Data Carrier Detect (DTD) Bit[1] - Reserved. Must be 0. Bit[0] - Reserved. Must be 0
Byte 22	Vendor Defined Data	(Optional) Data specific to the controller device supplied by a vendor. The number of bytes in this field is Type Data Length – 10.
		(Optional) Additional vendor supplied data.
String	Resource Source (Length = L)	Name of the serial bus controller device to which this connection descriptor applies. The name can be a fully qualified path, a relative path, or a simple name segment that utilizes the namespace search rules.

6.5 Other Objects and Control Methods

Table 6-210 Other Objects and Methods

Object	Description
_INI	Device initialization method that is run shortly after ACPI has been enabled.
_DCK	Indicates that the device is a docking station.
_BDN	Correlates a docking station between ACPI and legacy interfaces.
_REG	Notifies AML code of a change in the availability of an operation region.
_BBN	PCI bus number set up by the BIOS.
_SEG	Indicates a bus segment location.
_GLK	Indicates the Global Lock must be acquired when accessing a device.

6.5.1 _INI (Init)

_INI is a device initialization object that performs device specific initialization. This control method is located under a device object and is run only when OSPM loads a description table. There are restrictions related to when this method is called and governing writing code for this method. The _INI method must only access Operation Regions that have been indicated to available as defined by the _REG method. The _REG method is described in <u>Section 6.5.4</u>, "_REG (Region)." This control method is run before ADR, CID, HID, SUN, and UID are run.

Arguments:

None

Return Value:

None

Before evaluating the _INI object, OSPM evaluates the _STA object for the device. If the _STA object does not exist for the device, the device is assumed to be both present and functional. If the _STA method indicates that the device is present, OSPM will evaluate the _INI for the device (if the _INI method exists) and will examine each of the children of the device for _INI methods. If the _STA method indicates that the device is not present and is not functional, OSPM will not run the _INI and will not examine the children of the device for _INI methods. If the _STA object evaluation indicates that the device is not present but is functional, OSPM will not evaluate the _INI object, but will examine each of the children of the device for _INI objects (see the description of _STA for the explanation of this special case.) If the device becomes present after the table has already been loaded, OSPM will not evaluate the _INI method, nor examine the children for _INI methods.

The OSPM performed _INI object actions based upon the _STA Present and Functional bits are summarized in the table below.

Table 6-211 OSPM _INI Object Actions

_STA Present Bit	_STA Functional Bit	Actions
0	0	Do not run _INI, do not examine device children
0	1	Do not run _INI, examine device children

Device Configuration

1	0	Run _INI, examine device children
1	1	Run _INI, examine device children

The _INI control method is generally used to switch devices out of a legacy operating mode. For example, BIOSes often configure CardBus controllers in a legacy mode to support legacy operating systems. Before enumerating the device with an ACPI operating system, the CardBus controllers must be initialized to CardBus mode. For such systems, the vendor can include an _INI control method under the CardBus controller to switch the device into CardBus mode.

In addition to device initialization, OSPM unconditionally evaluates an _INI object under the _SB namespace, if present, at the beginning of namespace initialization.

6.5.2 _DCK (Dock)

This control method is located in the device object that represents the docking station (that is, the device object with all the _EJx control methods for the docking station). The presence of _DCK indicates to the OS that the device is really a docking station.

_DCK also controls the isolation logic on the docking connector. This allows an OS to prepare for docking before the bus is activated and devices appear on the bus.

Arguments: (1)

Arg0 – An **Integer** containing a docking action code

0 – Undock (isolate from connector)

1 – Dock (remove isolation from connector)

Return Value:

An **Integer** containing the docking status code

1 - Successful

0 - Failed

Note: When _DCK is called with 0, OSPM will ignore the return value. The _STA object that follows the EJx control method will notify whether or not the portable has been ejected.

6.5.3 _BDN (BIOS Dock Name)

_BDN is used to correlate a docking station reported via ACPI and the same docking station reported via legacy interfaces. It is primarily used for upgrading over non-ACPI environments.

Arguments:

None

Return Value:

An **Integer** that contains the EISA Dock ID

_BDN must appear under a device object that represents the dock, that is, the device object with _Ejx methods. This object must return a DWORD that is the EISA-packed DockID returned by the Plug and Play BIOS Function 5 (Get Docking Station Identifier) for a dock.

Note: If the machine does not support PNPBIOS, this object is not required.

6.5.4 **_REG** (Region)

The OS runs _REG control methods to inform AML code of a change in the availability of an operation region. When an operation region handler is unavailable, AML cannot access data fields in that region. (Operation region writes will be ignored and reads will return indeterminate data.).

Arguments: (2)

Arg0 – An **Integer** containing the Operation Region address space ID

Arg1 – An Integer containing the handler connection code

0 – disconnect the handler

1 – connect the handler

Return Value:

None

Valid Operation Region address space IDs:

- 0 SystemMemory
- 1 SystemIO
- 2 PCI Config
- 3 Embedded Controller
- 4 SMBus
- 5 SystemCMOS
- 6 PCIBARTarget
- 7 IPMI
- 8 GeneralPurposeIO
- 9 GenericSerialBus

0x0A-0x7F -Reserved

0x80-0xFF -OEM (custom) region space

Except for the cases shown below, control methods must assume all operation regions inaccessible until the _REG(RegionSpace, 1) method is executed. Once _REG has been executed for a particular operation region, indicating that the operation region handler is ready, a control method can access fields in the operation region. Conversely, control methods must not access fields in operation regions when _REG method execution has not indicated that the operation region handler is ready.

For example, until the Embedded Controller driver is ready, the control methods cannot access the Embedded Controller. Once OSPM has run _REG(EmbeddedControl, 1), the control methods can then access operation regions in Embedded Controller address space. Furthermore, if OSPM executes _REG(EmbeddedControl, 0), control methods must stop accessing operation regions in the Embedded Controller address space.

The exceptions for this rule are:

- 1. OSPM must guarantee that the following operation regions must always be accessible:
 - PCI Config operation regions on a PCI root bus containing a BBN object.

- I/O operation regions.
- Memory operation regions when accessing memory returned by the System Address Map reporting interfaces.
- 2. OSPM must make Embedded Controller operation regions, accessed via the Embedded Controllers described in ECDT, available before executing any control method. These operation regions may become inaccessible after OSPM runs REG(EmbeddedControl, 0).

Place _REG in the same scope as operation region declarations. The OS will run the _REG in a given scope when the operation regions declared in that scope are available for use.

Example:

```
Scope(\_SB.PCI0) {
   OperationRegion(OPR1, PCI_Config, ...)
   Method(\_REG, 2)  (...) // OSPM executes this when PCIO operation region handler
                                   // status changes
   Device(PCI1) {
       Method(2) {...}
       Device(ETH0) {
           OperationRegion(OPR2, PCI_Config, ...)
           Method(_REG,2) {...}
   Device(ISA0) {
       OperationRegion(OPR3, SystemI/O, ...)
       Method(_REG, 2) {...} // OSPM executes this when ISAO operation region handler
                                   // status changes
       Device(EC0) {
           Name(_HID, EISAID("PNP0C09"))
           OperationRegion(OPR4, EmbeddedControl, ...)
           Method(_REG, 2) \{\ldots\} // OSPM executes this when EC operation region
                                    // handler status changes
       }
    }
```

When the PCI0 operation region handler is ready, OSPM will run the _REG method declared in PCI0 scope to indicate that PCI Config space operation region access is available within the PCI0 scope (in other words, OPR1 access is allowed). When the ISA0 operation handler is ready, OSPM will run the _REG method in the ISA0 scope to indicate that the I/O space operation region access is available within that scope (in other words, OPR3 access is allowed). Finally, when the Embedded Controller operation region handler is ready, OSPM will run the _REG method in the EC0 scope to indicate that EC space operation region access is available within the EC0 scope (in other words, OPR4 access is allowed). It should be noted that PCI Config Space Operation Regions are ready as soon the host controller or bridge controller has been properly configured. At the same time, the OS will also run ETH0's _REG method since its PCI Config Space would be also available. The OS will again run ETH0's _REG method when the ETH0 device is started. Also, when the host controller or bridge controller is turned off or disabled, PCI Config Space Operation Regions for child devices are no longer available. As such, ETH0's _REG method will be run when it is turned off and will again be run when PCI1 is turned off.

Note: The OS only runs _REG methods that appear in the same scope as operation region declarations that use the operation region type that has just been made available. For example, _REG in the EC device would not be run when the PCI bus driver is loaded since the operation regions declared under EC do not use any of the operation region types made available by the PCI driver (namely, config space, I/O, and memory).

6.5.5 BBN (Base Bus Number)

For multi-root PCI platforms, the _BBN object evaluates to the PCI bus number that the BIOS assigns. This is needed to access a PCI_Config operation region for the specific bus. The _BBN object is located under a PCI host bridge and must be unique for every host bridge within a segment since it is the PCI bus number.

Arguments:

None

Return Value:

An **Integer** that contains the PCI bus number. The lower 8 bits of _BBN returned integer is the PCI Base Bus number. Other bits are reserved.

6.5.6 _SEG (Segment)

The optional _SEG object is located under a PCI host bridge and evaluates to an integer that describes the PCI Segment Group (see PCI Firmware Specification v3.0). If _SEG does not exist, OSPM assumes that all PCI bus segments are in PCI Segment Group 0.

Arguments:

None

Return Value:

PCI Segment Group is purely a software concept managed by system firmware and used by OSPM. It is a logical collection of PCI buses (or bus segments). There is no tie to any physical entities. It is a way to logically group the PCI bus segments and PCI Express Hierarchies. _SEG is a level higher than BBN.

PCI Segment Group supports more than 256 buses in a system by allowing the reuse of the PCI bus numbers. Within each PCI Segment Group, the bus numbers for the PCI buses must be unique. PCI buses in different PCI Segment Group are permitted to have the same bus number.

A PCI Segment Group contains one or more PCI host bridges.

The lower 16 bits of _SEG returned integer is the PCI Segment Group number. Other bits are reserved.

6.5.6.1 Example

```
Device(ND0) { // this is a node 0
    Name(_HID, "ACPI0004")
     // Returns the "Current Resources"
    Name(_CRS,
        ResourceTemplate() {
    )
   Device(PCI0) {
        Name(_HID, EISAID("PNP0A03"))
        Name(\_ADR, 0x00000000)
        Name(_SEG, 0) // The buses below the host bridge belong to PCI segment 0 \,
        Name(_BBN, 0)
    Device(PCI1) {
        Name(_SEG, 0) // The buses below the host bridge belong to PCI segment 0
        Name(_BBN, 16)
Device(ND1) \{ // this is a node 1
    Name(_HID, "ACPI0004")
     // Returns the "Current Resources"
    Name(_CRS,
        ResourceTemplate() {
   Device(PCI0) {
        Name(_HID, EISAID("PNPOA03"))
        Name(_ADR, 0x0000000)
        Name(_SEG, 1) // The buses below the host bridge belong to PCI segment 1
        Name(_BBN, 0)
    Device(PCI1) {
        Name(\_SEG, 1) // The buses below the host bridge belong to PCI segment 1
        Name(_BBN, 16)
}
```

6.5.7 _GLK (Global Lock)

This optional named object is located within the scope of a device object. This object returns a value that indicates to any entity that accesses this device (in other words, OSPM or any device driver)

whether the Global Lock must be acquired when accessing the device. OS-based device accesses must be performed while in acquisition of the Global Lock when potentially contentious accesses to device resources are performed by non-OS code, such as System Management Mode (SMM)-based code in Intel architecture-based systems.

Note: Default behavior: if _GLK is not present within the scope of a given device, then the Global Lock is not required for that device.

Arguments:

None

Return Value:

An Integer that contains the Global Lock requirement code

- 0 The Global Lock is not required for this device
- 1 The Global lock is required for this device

An example of device resource contention is a device driver for an SMBus-based device contending with SMM-based code for access to the Embedded Controller, SMB-HC, and SMBus target device. In this case, the device driver must acquire and release the Global Lock when accessing the device to avoid resource contention with SMM-based code that accesses any of the listed resources.

6.5.8 _DEP (Operation Region Dependencies)

_DEP evaluates to a package and designates device objects that OSPM should assign a higher priority in start ordering due to future operation region accesses.

To increase the likelihood that an SPB operation region handler is available when needed, OSPM needs to know in advance which methods will access it -- _DEP provides OSPM with this information. While the _DEP keyword may be used to determine start ordering, only the _REG method (Section 6.5.4) callbacks can be relied upon to determine whether a region is accessible at a given point in time.

Arguments:

None.

Return Value:

A variable-length **Package** containing object references.

Device Configuration

6.5.8.1 Example Device(_SB.TC3) {

Power and Performance Management

This section specifies the device power management objects and system power management objects. OSPM uses these objects to manage the platform by achieving a desirable balance between performance and energy conservation goals.

Device performance states (Px states) are power consumption and capability states within the active (D0) device power state. Performance states allow OSPM to make tradeoffs between performance and energy conservation. Device performance states have the greatest impact when the implementation is such that the states invoke different device efficiency levels as opposed to a linear scaling of performance and energy consumption. Since performance state transitions occur in the active device states, care must be taken to ensure that performance state transitions do not adversely impact the system.

Device performance state objects, when necessary, are defined on a per device class basis as described in the device class specifications (See <u>Appendix A</u>).

The system state indicator objects are also specified in this section.

7.1 Declaring a Power Resource Object

An ASL **PowerResource** statement is used to declare a **PowerResource** object. A Power Resource object refers to a software-controllable power plane, clock plane, or other resource upon which an integrated ACPI power-managed device might rely. Power resource objects can appear wherever is convenient in namespace.

The syntax of a **PowerResource** statement is:

PowerResource (resourcename, systemlevel, resourceorder) {NamedList}

where the *systemlevel* parameter is a number and the *resourceorder* parameter is a numeric constant (a WORD). For a formal definition of the **PowerResource** statement syntax, see <u>Section 19</u>, "ACPI Source Language Reference."

Systemlevel is the lowest power system sleep level OSPM must maintain to keep this power resource on (0 equates to S0, 1 equates to S1, and so on).

Each power-managed ACPI device lists the resources it requires for its supported power levels. OSPM multiplexes this information from all devices and then enables and disables the required Power Resources accordingly. The *resourceorder* field in the Power Resource object is a unique value per Power Resource, and it provides the system with the order in which Power Resources must be enabled or disabled. Power Resources are enabled from low values to high values and are disabled from high values to low values. The operating software enables or disables all affected Power Resources in any one *resourceorder* level at a time before moving on to the next ordered level. Putting Power Resources in different order levels provides power sequencing and serialization where required.

A Power Resource can have named objects under its Namespace location. For a description of the ACPI-defined named objects for a Power Resource, see <u>Section 7.2</u>, "Device Power Management Objects."

The following block of ASL sample code shows a use of **PowerResource**.

```
PowerResource(PIDE, 0, 0) {
    Method(_STA) {
        Return (Xor (GIO.IDEI, One, Zero)) // inverse of isolation
    }
    Method(_ON) {
        Store (One, GIO.IDEP) // assert power
        Sleep (10) // wait 10ms
        Store (One, GIO.IDER) // de-assert reset#
        Stall (10) // wait 10us
        Store (Zero, GIO.IDEI) // de-assert isolation
    }
    Method(_OFF) {
        Store (One, GIO.IDEI) // assert isolation
        Store (Zero, GIO.IDER) // assert reset#
        Store (Zero, GIO.IDEP) // de-assert power
    }
}
```

7.1.1 Defined Child Objects for a Power Resource

Each power resource object is required to have the following control methods to allow basic control of each power resource. As OSPM changes the state of device objects in the system, the power resources that are needed will also change causing OSPM to turn power resources on and off. To determine the initial power resource settings the STA method can be used.

Table 7-212 Power Resource Child Objects

Object	Description
_OFF	Set the resource off.
_ON	Set the resource on.
_STA	Object that evaluates to the current on or off state of the Power Resource. 0–OFF, 1–ON

7.1.2 OFF

This power resource control method puts the power resource into the OFF state. The control method does not complete until the power resource is off. OSPM only turns on or off one resource at a time, so the AML code can obtain the proper timing sequencing by using Stall or Sleep within the ON (or OFF) method to cause the proper sequencing delays between operations on power resources.

Arguments:

None

Return Value:

None

7.1.3 ON

This power resource control method puts the power resource into the ON state. The control method does not complete until the power resource is on. OSPM only turns on or off one resource at a time, so the AML code can obtain the proper timing sequencing by using Stall or Sleep within the ON (or OFF) method to cause the proper sequencing delays between operations on power resources.

Arguments:

None

Return Value:

None

7.1.4 **_STA** (Status)

Returns the current ON or OFF status for the power resource.

Arguments:

None

Return Value:

An Integer containing the current power status of the device

- 0 The power resource is currently off
- 1 The power resource is currently on

7.2 Device Power Management Objects

For a device that is power-managed using ACPI, a Definition Block contains one or more of the objects found in the table below. Power management of a device is done using two different paradigms:

- Power Resource control
- Device-specific control

Power Resources are resources that could be shared amongst multiple devices. The operating software will automatically handle control of these devices by determining which particular Power Resources need to be in the ON state at any given time. This determination is made by considering the state of all devices connected to a Power Resource.

By definition, a device that is OFF does not have any power resource or system power state requirements. Therefore, device objects do not list power resources for the OFF power state.

For OSPM to put the device in the D3 state, the following must occur:

- All Power Resources no longer referenced by any device in the system must be in the OFF state.
- If present, the PS3 control method is executed to set the device into the D3 device state.

The only transition allowed from the D3 device state is to the D0 device state.

For many devices the Power Resource control is all that is required; however, device objects may include their own device-specific control method.

Power and Performance Management

These two types of power management controls (through Power Resources and through specific devices) can be applied in combination or individually as required.

For systems that do not control device power states through power plane management, but whose devices support multiple D-states, more information is required by the OS to determine the S-state to D-state mapping for the device. The ACPI BIOS can give this information to OSPM by way of the _SxD methods. These methods tell OSPM for S-state "x", the highest D-state supported by the device is "y." OSPM is allowed to pick a lower D-state for a given S-state, but OSPM is not allowed to exceed the given D-state.

Further rules that apply to device power management objects are:

- For a given S-state, a device cannot be in a higher D-state than its parent device.
- If there exists an ACPI Object to turn on a device (either through PSx or PRx objects), then a corresponding object to turn the device off must also be declared and vice versa.
- If there exists an ACPI Object that controls power (PSx or PRx, where x = 0, 1, 2, or 3), then methods to set the device into D0 and D3 device states must be present.
- If a mixture of _PSx and _PRx methods is declared for the device, then the device states supported through _PSx methods must be identical to the device states supported through _PRx methods. ACPI system firmware may enable device power state control exclusively through _PSx (or _PRx) method declarations.

When controlling power to devices which must wake the system during a system sleeping state:

- The device must declare its ability to wake the system by declaring either the _PRW or _PSW object.
- If _PR0 is present, then OSPM must choose a sleeping state which is less than or equal to the sleeping state specified.
- After OSPM has called PTS, it must call the device's PSW to enable wake.
- OSPM must transition the device into a D-state which is greater than or equal that specified by the device's SxD object, but less than or equal to that specified by the device's SxW object.
- OSPM may transition the system to the specified sleep state.

Table 7-213 Device Power Management Child Objects

Object	Description
_DSW	Control method that enables or disables the device's wake function for device-only wake.
_PS0	Control method that puts the device in the D0 device state (device fully on).
_PS1	Control method that puts the device in the D1 device state.
_PS2	Control method that puts the device in the D2 device state.
_PS3	Control method that puts the device in the D3 device state (device off).
_PSC	Object that evaluates to the device's current power state.
_PR0	Object that evaluates to the device's power requirements in the D0 device state (device fully on).
_PR1	Object that evaluates to the device's power requirements in the D1 device state. The only devices that supply this level are those that can achieve the defined D1 device state according to the related device class.

Object	Description
_PR2	Object that evaluates to the device's power requirements in the D2 device state. The only devices that supply this level are those that can achieve the defined D2 device state according to the related device class.
_PR3	Object that evaluates to the device's power requirements in the D3hot device state.
_PRW	Object that evaluates to the device's power requirements in order to wake the system from a system sleeping state.
_PSW	Control method that enables or disables the device's wake function.
_IRC	Object that signifies the device has a significant inrush current draw.
_S1D	Highest D-state supported by the device in the S1 state
_S2D	Highest D-state supported by the device in the S2 state
_S3D	Highest D-state supported by the device in the S3 state
_S4D	Highest D-state supported by the device in the S4 state
_S0W	Lowest D-state supported by the device in the S0 state which can wake the device
_S1W	Lowest D-state supported by the device in the S1 state which can wake the system.
_S2W	Lowest D-state supported by the device in the S2 state which can wake the system.
_S3W	Lowest D-state supported by the device in the S3 state which can wake the system.
_S4W	Lowest D-state supported by the device in the S4 state which can wake the system.

7.2.1 _DSW (Device Sleep Wake)

In addition to _PRW, this control method can be used to enable or disable the device's ability to wake a sleeping system. This control method can only access Operation Regions that are either always available while in a system working state or that are available when the Power Resources referenced by the _PRW object are all ON. For example, do not put a power plane control for a bus controller within configuration space located behind the bus. The method should enable the device only for the last system state/device state combination passed in by OSPM. OSPM will only pass in combinations allowed by the _SxD and _SxW objects.

The arguments provided to _DSW indicate the eventual Device State the device will be transitioned to and the eventual system state that the system will be transitioned to. The target system state is allowed to be the system working state (S0). The _DSW method will be run before the device is placed in the designated state and also before the system is placed in the designated system state.

Compatibility Note: The _PSW method is deprecated in ACPI 3.0. The _DSW method should be used instead. OSPM will only use the _PSW method if OSPM does not support _DSW or if the DSW method is not present.

Arguments: (3)

Arg0 – An **Integer** that contains the device wake capability control

- 0 Disable the device's wake capabilities
- 1 Enable the device's wake capabilities
- Arg1 An **Integer** that contains the target system state (0-4)
- Arg2 An Integer that contains the target device state
 - 0 The device will remain in state **D0**

- 1 The device will be placed in either state **D0** or **D1**
- 2 The device will be placed in either state **D0**, **D1**, or **D2**
- 3 The device will be placed in either state **D0**, **D1**, **D2**, or **D3**

Return Value:

None

7.2.2 **_PS0** (Power State 0)

This Control Method is used to put the specific device into its D0 state. This Control Method can only access Operation Regions that are either always available while in a system working state or that are available when the Power Resources references by the PRO object are all ON.

Arguments:

None

Return Value:

None

7.2.3 **PS1** (Power State 1)

This control method is used to put the specific device into its D1 state. This control method can only access Operation Regions that are either always available while in a system working state or that are available when the Power Resources references by the PR1 object are all ON.

Arguments:

None

Return Value:

None

7.2.4 **PS2** (Power State 2)

This control method is used to put the specific device into its D2 state. This control method can only access Operation Regions that are either always available while in a system working state or that are available when the Power Resources references by the PR2 object are all ON.

Arguments:

None

Return Value:

None

7.2.5 _PS3 (Power State 3)

This control method is used to put the specific device into its D3hot or D3 state. This control method can only access Operation Regions that are always available while in a system working state.

A device in the D3 state must no longer be using its resources (for example, its memory space and I/O ports are available to other devices).

Arguments:

None

Return Value:

None

7.2.6 PSC (Power State Current)

This control method evaluates to the current device state. This control method is not required if the device state can be inferred by the Power Resource settings. This would be the case when the device does not require a PS0, PS1, PS2, or PS3 control method.

Arguments:

None

Return Value:

An Integer that contains a code for the current device state

The device state codes are shown in <u>Table 7-214</u>.

Table 7-214 PSC Device State Codes

Return Value	Device State
0	D0
1	D1
2	D2
3	D3

7.2.7 PSE (Power State for Enumeration)

This control method is used to put a device into a powered mode appropriate for enumeration by its parent bus. This control method can only access Operation Regions that are either always available while in a system working state or that are available when the Power Resources referenced by the PRE object are all ON.

Arguments: (1)

Arg1 – An Integer indicating whether Enumeration power has been turned ON or will be turned OFF.

0 - OFF

1 - ON

Return Value:

None

7.2.8 PR0 (Power Resources for D0)

This object evaluates to a list of power resources that are dependent on this device. For OSPM to put the device in the D0 device state, the following must occur:

Power and Performance Management

- 1. All Power Resources referenced by elements 1 through N must be in the ON state.
- 2. All Power Resources no longer referenced by any device in the system must be in the OFF state.
- 3. If present, the PS0 control method is executed to set the device into the D0 device state.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to power resources

This object returns a package as defined below:

Table 7-215 Power Resource Requirements Package

Element	Object	Description
1	object reference	Reference to required Power Resource #0
N	object reference	Reference to required Power Resource #N

_PR0 must return the same data each time it is evaluated. All power resources referenced must exist in the namespace.

7.2.9 PR1 (Power Resources for D1)

This object evaluates to a list of power resources that are dependent on this device. For OSPM to put the device in the D1 device state, the following must occur:

- 1. All Power Resources referenced by elements 1 through N must be in the ON state.
- 2. All Power Resources no longer referenced by any device in the system must be in the OFF state.
- 3. If present, the PS1 control method is executed to set the device into the D1 device state.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to power resources

This object evaluates to a package as defined in <u>Table 7-215</u>.

_PR1 must return the same data each time it is evaluated. All power resources referenced must exist in the namespace.

7.2.10 PR2 (Power Resources for D2)

This object evaluates to a list of power resources that are dependent on this device. For OSPM to put the device in the D2 device state, the following must occur:

- 1. All Power Resources referenced by elements 1 through N must be in the ON state.
- 2. All Power Resources no longer referenced by any device in the system must be in the OFF state.
- 3. If present, the PS2 control method is executed to set the device into the D2 device state.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to power resources

_PR2 must return the same data each time it is evaluated. All power resources referenced must exist in the namespace.

7.2.11 PR3 (Power Resources for D3hot)

This object evaluates to a list of power resources that are dependent on this device. For OSPM to put the device in the D3hot device state, the following must occur:

- 1. All Power Resources referenced by elements 1 through N must be in the ON state.
- 2. All Power Resources no longer referenced by any device in the system must be in the OFF state.
- 3. If present, the PS3 control method is executed to set the device into the D3hot device state.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to power resources

_PR3 must return the same data each time it is evaluated. All power resources referenced must exist in the namespace.

Interaction between _PR3 and entry to D3/D3hot (only applicable if platform and OSPM have performed the necessary handshake via OSC):

- Platform/drivers must assume that the device will have power completely removed when the device is place into "D3" via PS3
- It is up to OSPM to determine whether to use D3 or D3hot. If there is a PR3 for the device, it is up to OSPM to decided whether or not to keep those power resources on/off after executing PS3. The decision may be based on other factors (e.g. being armed for wake, etc).

7.2.12 PRE (Power Resources for Enumeration)

This object appears under a device and evaluates to a list of power resources that are required for enumeration of the device by its parent bus. For the bus driver to enumerate any devices while they are in the D3Cold device state, OSPM must ensure that the following occur:

- 1. All Power Resources referenced by elements 1 through N must be in the ON state.
- 2. If present, the _PSE control method is executed to perform any actions on the device to make it accessible for enumeration.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to power resources.

_PRE must return the same data each time it is evaluated. All power resources referenced must exist in the namespace.

7.2.13 PRW (Power Resources for Wake)

This object evaluates to a list of power resources that are dependent on this device and additional information needed for wake, including wake GPE and sleep state information. _PRW is only required for devices that have the ability to wake the system from a system sleeping state.

Two types of general purpose events are supported:

- GPEs that are defined by a GPE block described within the FADT.
- GPEs that are defined by a GPE Block Device.

The two types of GPEs are differentiated by the type of the *GpeInfo* object in the returned package. For FADT-based GPEs, *GpeInfo* is an **Integer** containing a bit index. For Block Device-based GPEs, *GpeInfo* is a **Package** containing a **Reference** to the parent block device and an **Integer** containing a bit index.

For HW-Reduced ACPI platforms, the GpeInfo structure is ignored by OSPM. Therefore, _PRW is only required on such platforms if power resources for wakeup must be managed by OSPM (e.g. the _PRW provides a list of Power Resources). Instead, for a device to wake the system, its interrupt must be wake-capable and enabled by the driver. See <u>Section 3.11.1.1</u>"Interrupt-based Wake Events".

Arguments:

None

Return Value:

A variable-length **Package** containing wake information and a list of **References** to power resources

Return Value Information

If *GpeInfo* is a **Package**, it contains GPE block device information as described below:

GpeInfo may be either an **Integer** or a **Package**, depending on the GPE type:

• If it is an **Integer**, then it contains the bit index of the wake GPE within the FADT-based GPE enable register.

• If it is a **Package**, then the package contains GPE info for a event within a GPE block device. It contains a **Reference** to the GPE block device and an **Integer** containing the bit index of the wake GPE within the Block Device-based GPE enable register.

LowestSleepState is an **Integer** that contains the lowest power system sleeping state that can be entered while still providing wake functionality.

PowerResource 0-n are **Reference**s to required power resource objects.

Additional Information

For OSPM to have the defined wake capability properly enabled for the device, the following must occur:

- 1. All Power Resources referenced by elements 2 through N are put into the ON state.
 - a If present, the _PSW control method is executed to set the device-specific registers to enable the wake functionality of the device.
 - b The D-state being entered must be at least that specified in the _SxD state but no greater than that specified in the _SxW state.

Then, if the system enters a sleeping state OSPM must ensure:

- 1. Interrupts are disabled.
- 2. The sleeping state being entered must be less than or equal to the power state declared in element 1 of the _PRW object.
- 3. The proper general-purpose register bits are enabled.

The system sleeping state specified must be a state that the system supports (in other words, a corresponding \Sx object must exist in the namespace).

_PRW must return the same data each time it is evaluated. All power resources referenced must exist in the namespace.

7.2.14 PSW (Power State Wake)

In addition to the _PRW control method, this control method can be used to enable or disable the device's ability to wake a sleeping system. This control method can only access Operation Regions that are either always available while in a system working state or that are available when the Power Resources references by the _PRW object are all ON. For example, do not put a power plane control for a bus controller within configuration space located behind the bus.

Note: Regarding compatability--The _PSW method is deprecated in ACPI 3.0. OSPM must use _DSW if it is present. Otherwise, it may use _PSW.

Arguments: (1)

Arg0 – An **Integer** containing a wake capability control

- 0 Disable the device's wake capabilities
- 1 Enable the device's wake capabilities

Return Value:

None

7.2.15 _IRC (In Rush Current)

Indicates that this device can cause a significant in-rush current when transitioning to state **D0**.

Arguments:

None

Return Value:

None

The presence of this object signifies that transitioning the device to its D0 state causes a system-significant in-rush current load. In general, such operations need to be serialized such that multiple operations are not attempted concurrently. Within ACPI, this type of serialization can be accomplished with the *ResourceOrder* parameter of the device's Power Resources; however, this does not serialize ACPI-controlled devices with non-ACPI controlled devices. _IRC is used to signify this fact outside of OSPM to OSPM such that OSPM can serialize all devices in the system that have in-rush current serialization requirements.

OSPM can only transition one device containing an _IRC object within its device scope to the D0 state at a time.

It is important to note that OSPM does not evaluate the _IRC object. It has no defined input arguments nor does it return any value. OSPM derives meaning simply from the existence of the IRC object.

7.2.16 _S1D (S1 Device State)

This object evaluates to an integer that conveys to OSPM the highest power (lowest number) D-state supported by this device in the S1 system sleeping state. _S1D must return the same integer each time it is evaluated. This value overrides an S-state to D-state mapping OSPM may ascertain from the device's power resource declarations. See <u>Table 7-214</u> for valid return values.

Arguments:

None

Return Value:

An **Integer** containing the highest D-state supported in state **S1**

If the device can wake the system from the S1 system sleeping state (see $_PRW$) then the device must support wake in the D-state returned by this object. However, OSPM cannot assume wake from the S1 system sleeping state is supported in any lower D-state unless specified by a corresponding $_S1W$ object. The table below provides a mapping from Desired Actions to Resultant D-state entered based on the values returned from the $_S1D$, $_PRW$, and $_S1W$ objects if they exist . (D/C means Don't Care – evaluation is irrelevant, and N/A means Non Applicable – object does not exist).

Table 7-216 S1 Action / Result Table

Desired Action	_S1D	_PRW	_S1W	Resultant D-state
Enter S1	D/C	D/C	D/C	OSPM decides
Enter S1, No Wake	2	D/C	D/C	Enter D2 or D3

Enter S1, Wake	2	1	N/A	Enter D2
Enter S1, Wake	2	1	3	Enter D2 or D3
Enter S1, Wake	N/A	1	2	Enter D0,D1 or D2

7.2.17 _S2D (S2 Device State)

This object evaluates to an integer that conveys to OSPM the highest power (lowest number) D-state supported by this device in the S2 system sleeping state. _S2D must return the same integer each time it is evaluated. This value overrides an S-state to D-state mapping OSPM may ascertain from the device's power resource declarations. See <u>Table 7-214</u> for valid return values.

Arguments:

None

Return Value:

An Integer containing the highest D-state supported in state S2

If the device can wake the system from the S2 system sleeping state (see _PRW) then the device must support wake in the D-state returned by this object. However, OSPM cannot assume wake from the S2 system sleeping state is supported in any lower D-state unless specified by a corresponding _S2W object. The table below provides a mapping from Desired Actions to Resultant D-state entered based on the values returned from the _S2D, _PRW, and _S2W objects if they exist . (D/C means Don't Care – evaluation is irrelevant, and N/A means Non Applicable – object does not exist).

Table 7-217 S2 Action / Result Table

Desired Action	_S2D	_PRW	_S2W	Resultant D-state
Enter S2	D/C	D/C	D/C	OSPM decides
Enter S2, No Wake	2	D/C	D/C	Enter D2 or D3
Enter S2, Wake	2	2	N/A	Enter D2
Enter S2, Wake	2	2	3	Enter D2 or D3
Enter S2, Wake	N/A	2	2	Enter D0,D1 or D2

7.2.18 _S3D (S3 Device State)

This object evaluates to an integer that conveys to OSPM the highest power (lowest number) D-state supported by this device in the S3 system sleeping state. _S3D must return the same integer each time it is evaluated. This value overrides an S-state to D-state mapping OSPM may ascertain from the device's power resource declarations. See Table 7-214 for valid return values.

Arguments:

None

Return Value:

An **Integer** containing the highest D-state supported in state **S3**

Power and Performance Management

If the device can wake the system from the S3 system sleeping state (see _PRW) then the device must support wake in the D-state returned by this object. However, OSPM cannot assume wake from the S3 system sleeping state is supported in any lower D-state unless specified by a corresponding _S3W object. The table below provides a mapping from Desired Actions to Resultant D-state entered based on the values returned from the _S3D, _PRW, and _S3W objects if they exist . (D/C means Don't Care – evaluation is irrelevant, and N/A means Non Applicable – object does not exist).

Table 7-218 S3 Action / Result Table

Desired Action	_S3D	_PRW	_S3W	Resultant D-state
Enter S3	N/A	D/C	N/A	OSPM decides
Enter S3, No Wake	2	D/C	D/C	Enter D2 or D3
Enter S3, Wake	2	3	N/A	Enter D2
Enter S3, Wake	2	3	3	Enter D2 or D3
Enter S3, Wake	N/A	3	2	Enter D0, D1 or D2

7.2.19 _S4D (S4 Device State)

This object evaluates to an integer that conveys to OSPM the highest power (lowest number) D-state supported by this device in the S4 system sleeping state. _S4D must return the same integer each time it is evaluated. This value overrides an S-state to D-state mapping OSPM may ascertain from the device's power resource declarations. See Table 7-3 for valid return values.

Arguments:

None

Return Value:

An **Integer** containing the highest D-state supported in state **S4**

If the device can wake the system from the S4 system sleeping state (see _PRW) then the device must support wake in the D-state returned by this object. However, OSPM cannot assume wake from the S4 system sleeping state is supported in any lower D-state unless specified by a corresponding _S4W object. The table below provides a mapping from Desired Actions to Resultant D-state entered based on the values returned from the _S4D, _PRW, and _S4W objects if they exist . (D/C means Don't Care – evaluation is irrelevant, and N/A means Non Applicable – object does not exist).

Table 7-219 S4 Action / Result Table

Desired Action	_S4D	_PRW	_S4W	Resultant D-state
Enter S4	N/A	D/C	N/A	OSPM decides
Enter S4, No Wake	2	D/C	D/C	Enter D2 or D3
Enter S4, Wake	2	4	N/A	Enter D2
Enter S4, Wake	2	4	3	Enter D2 or D3
Enter S4, Wake	N/A	4	2	Enter D0, D1 or D2

7.2.20 _S0W (S0 Device Wake State)

This object evaluates to an integer that conveys to OSPM the lowest power (highest number) D-state supported by this device in the S0 system sleeping state *where the device can wake itself*.

Arguments:

None

Return Value:

An **Integer** containing the lowest D-state supported in state **S0**. If OSPM has not indicated that it supports _PR3 through the OSPM Platform-Wide Capabilities (see <u>Section 6.2.11.2</u>), then the value "3" corresponds to D3. If it has indicated _PR3 support, the value "3" represents D3hot and the value "4" represents D3cold.

_S0W must return the same integer each time it is evaluated. This value allows OSPM to choose the lowest power D-state and still achieve wake functionality. If object evaluates to zero, then the device cannot wake itself from any lower sleeping state.

7.2.21 _S1W (S1 Device Wake State)

This object evaluates to an integer that conveys to OSPM the lowest power (highest number) D-state supported by this device in the S1 system sleeping state *which can wake the system*.

Arguments:

None

Return Value:

An Integer containing the lowest D-state supported in state **S1.** If OSPM has not indicated that it supports _PR3 through the OSPM Platform-Wide Capabilities (see <u>Section 6.2.11.2</u>), then the value "3" corresponds to D3. If it has indicated _PR3 support, the value "3" represents D3hot and the value "4" represents D3cold.

_S1W must return the same integer each time it is evaluated. This value allows OSPM to choose a lower S-state to D-state mapping than specified by _S1D. This value must always be greater than or equal to S1D, if S1D is present.

7.2.22 _S2W (S2 Device Wake State)

This object evaluates to an integer that conveys to OSPM the lowest power (highest number) D-state supported by this device in the S2 system sleeping state *which can wake the system*.

Arguments:

None

Return Value:

An **Integer** containing the lowest D-state supported in state **S2.** If OSPM has not indicated that it supports _PR3 through the OSPM Platform-Wide Capabilities (see <u>Section 6.2.11.2</u>), then the value "3" corresponds to D3. If it has indicated _PR3 support, the value "3" represents D3hot and the value "4" represents D3cold.

_S2W must return the same integer each time it is evaluated. This value allows OSPM to choose a lower S-state to D-state mapping than specified by _S2D. This value must always be greater than or equal to _S2D, if _S2D is present.

7.2.23 S3W (S3 Device Wake State)

This object evaluates to an integer that conveys to OSPM the lowest power (highest number) D-state supported by this device in the S3 system sleeping state *which can wake the system*.

Arguments:

None

Return Value:

An **Integer** containing the lowest D-state supported in state **S3.** If OSPM has not indicated that it supports _PR3 through the OSPM Platform-Wide Capabilities (see <u>Section 6.2.11.2</u>), then the value "3" corresponds to D3. If it has indicated _PR3 support, the value "3" represents D3hot and the value "4" represents D3cold.

_S3W must return the same integer each time it is evaluated. This value allows OSPM to choose a lower S-state to D-state mapping than specified by _S3D. This value must always be greater than or equal to S3D, if S3D is present.

7.2.24 _S4W (S4 Device Wake State)

This object evaluates to an integer that conveys to OSPM the lowest power (highest number) D-state supported by this device in the S4 system sleeping state *which can wake the system*.

Arguments:

None

Return Value:

An **Integer** containing the lowest D-state supported in state **S4.** If OSPM has not indicated that it supports _PR3 through the OSPM Platform-Wide Capabilities (see <u>Section 6.2.11.2</u>), then the value "3" corresponds to D3. If it has indicated _PR3 support, the value "3" represents D3hot and the value "4" represents D3cold.

_S4W must return the same integer each time it is evaluated. This value allows OSPM to choose a lower S-state to D-state mapping than specified by _S4D. This value must always be greater than or equal to S4D, if S4D is present.

7.3 OEM-Supplied System-Level Control Methods

An OEM-supplied Definition Block provides some number of controls appropriate for system-level management. These are used by OSPM to integrate to the OEM-provided features. The following table lists the defined OEM system controls that can be provided.

Table 7-220 BIOS-Supplied Control Methods for System-Level Functions

Object	Description
_PTS	Control method used to notify the platform of impending sleep transition.

_S0	Package that defines system _S0 state mode.
_S1	Package that defines system _S1 state mode.
_S2	Package that defines system _S2 state mode.
_S3	Package that defines system _S3 state mode.
_S4	Package that defines system _S4 state mode.
_S5	Package that defines system _S5 state mode.
_TTS	Control method used to prepare to sleep and run once awakened
_WAK	Control method run once awakened.

Note: Compatibility issue: The _BFS (Back From Sleep) and _GTS (Going To Sleep) methods are deprecated in ACPI 5.0A.

7.3.1 _PTS (Prepare To Sleep)

The _PTS control method is executed by the OS during the sleep transition process for S1, S2, S3, S4, and for orderly S5 shutdown. The sleeping state value (For example, 1, 2, 3, 4 or 5 for the S5 soft-off state) is passed to the _PTS control method. This method is called after OSPM has notified native device drivers of the sleep state transition and before the OSPM has had a chance to fully prepare the system for a sleep state transition. Thus, this control method can be executed a relatively long time before actually entering the desired sleeping state. If OSPM aborts the sleep state transition, OSPM should run the WAK method to indicate this condition to the platform.

Arguments (1):

Arg0 – An Integer containing the value of the sleeping state (1 for S1, 2 for S2, etc.)

Return Value:

None

The _PTS control method cannot modify the current configuration or power state of any device in the system. For example, _PTS would simply store the sleep type in the embedded controller in sequencing the system into a sleep state when the SLP_EN bit is set.

The platform must not make any assumptions about the state of the machine when _PTS is called. For example, operation region accesses that require devices to be configured and enabled may not succeed, as these devices may be in a non-decoding state due to plug and play or power management operations.

7.3.2 System _Sx states

All system states supported by the system must provide a package containing the DWORD value of the following format in the static Definition Block. The system states, known as S0–S5, are referenced in the namespace as $_S0-_S5$ and for clarity the short Sx names are used unless specifically referring to the named $_Sx$ object. For each Sx state, there is a defined system behavior.

Arguments:

None

Power and Performance Management

Return Value:

A Package containing an Integer containing register values for sleeping

Table 7-221 System State Package

Byte Length	Byte Offset	Description
1	0	Value for PM1a_CNT.SLP_TYP register to enter this system state. On HW-reduced platforms, this is the HW-reduced Sleep Type value for SLEEP_CONTROL_REG.SLP_TYP.
1	1	Value for PM1b_CNT.SLP_TYP register to enter this system state. To enter any given state, OSPM must write the PM1a_CNT.SLP_TYP register before the PM1b_CNT.SLP_TYP register. On HW-reduced platforms, this value is ignored.
2	2	Reserved

States S1–S4 represent some system sleeping state. The S0 state is the system working state. Transition into the S0 state from some other system state (such as sleeping) is automatic, and, by virtue that instructions are being executed, OSPM assumes the system to be in the S0 state. Transition into any system sleeping state is only accomplished by the operating software directing the hardware to enter the appropriate state, and the operating software can only do this within the requirements defined in the Power Resource and Bus/Device Package objects.

All run-time system state transitions (for example, to and from the S0 state), except S4 and S5, are done similarly such that the code sequence to do this is the following:

```
Intel Architecture SetSleepingState example
   ULONG
   SetSystemSleeping (
       IN ULONG NewState
   PROCESSOR_CONTEXT Context;
   ULONG
                     PowerSeqeunce;
   BOOLEAN
                     FlushCaches;
   USHORT
                      SlpTyp;
// Required environment: Executing on the system boot
// processor. All other processors stopped. Interrupts
// disabled. All Power Resources (and devices) are in
// corresponding device state to support NewState.
       // Get h/w attributes for this system state
       FlushCaches = SleepType[NewState].FlushCache;
       SlpTyp
                    = SleepType[NewState].SlpTyp & SLP_TYP_MASK;
       _asm {
       lea
               eax, OsResumeContext
                                      ; Build real mode handler the resume
       push
               eax
               offset sp50
       push
                                      ; context, with eip = sp50
               SaveProcessorState
       call
       mov
               eax, ResumeVector
                                     ; set firmware's resume vector
              [eax], offset OsRealModeResumeCode
       mov
                                    ; Make sure wake status is clear
               edx, PMla_STS
       mov
                                      ; (cleared by asserting the bit
       mov
               ax, WAK_STS
       out
               dx, ax
                                      ; in the status register)
               edx, PM1b_STS
                                      ;
       mov
               dx, ax
       out
       and
               eax, not SLP_TYP_MASK
                                     ; set SLP_TYP
       or
               eax, SlpTyp
               ax, SLP_EN
                                      ; set SLP_EN
       or
               FlushCaches, 0
       cmp
                                ; If needed, ensure no dirty data in
       jz
               short sp10
```

Power and Performance Management

```
call
              FlushProcessorCaches
                                    ; the caches while sleeping
              edx, PMla_SLP_TYP ; get address for PMla_SLP_TYP
sp10:
      mov
       out
              dx, ax
                                   ; start h/w sequencing
                                   ; get address for PMlb_SLP_TYP
              edx, PM1b_SLP_TYP
       mov
              dx, ax
                                    ; start h/w sequencing
       out
       mov
              edx, PMla_STS
                                    ; get address for PM1x_STS
       mov
              ecx, PM1b STS
sp20:
      in ax, dx
                                    ; wait for WAK status
       xchg edx, ecx
       test ax, WAK_STS
              short sp20
sp50:
       // Done..
       *ResumeVector = NULL;
       return 0;
```

On HW-reduced ACPI platforms all run-time system state transitions (for example, to and from the S0 state) are done similarly, but include the following instead of PM1*_BLK register bit manipulation:

After ensuring that any desired wake-capable interrupts are enabled, OSPM writes the HW-reduced Sleep Type value to the Sleep Control Register and spins waiting for the WAK_STS bit of the Sleep Status Register to be set, indicating a platform transition to the Working state.

7.3.2.1 System _S0 State (Working)

While the system is in the S0 state, it is in the system working state. The behavior of this state is defined as:

- The processors are in the C0, C1, C2, or C3 states. The processor-complex context is maintained and instructions are executed as defined by any of these processor states.
- Dynamic RAM context is maintained and is read/write by the processors.
- Devices states are individually managed by the operating software and can be in any device state (D0, D1, D2, D3hot, or D3).
- Power Resources are in a state compatible with the current device states.

Transition into the S0 state from some system sleeping state is automatic, and by virtue that instructions are being executed OSPM, assumes the system to be in the S0 state.

7.3.2.2 System _S1 State (Sleeping with Processor Context Maintained)

While the system is in the S1 sleeping state, its behavior is the following:

- The processors are not executing instructions. The processor-complex context is maintained.
- Dynamic RAM context is maintained.
- Power Resources are in a state compatible with the system S1 state. All Power Resources that supply a System-Level reference of S0 are in the OFF state.

- Devices states are compatible with the current Power Resource states. Only devices that solely reference Power Resources that are in the ON state for a given device state can be in that device state. In all other cases, the device is in the D3 (off) state¹.
- Devices that are enabled to wake the system and that can do so from their current device state can initiate a hardware event that transitions the system state to S0. This transition causes the processor to continue execution where it left off.

To transition into the S1 state, the OSPM must flush all processor caches.

7.3.2.3 System _S2 State

The S2 sleeping state is logically lower than the S1 state and is assumed to conserve more power. The behavior of this state is defined as:

- The processors are not executing instructions. The processor-complex context is not maintained.
- Dynamic RAM context is maintained.
- Power Resources are in a state compatible with the system S2 state. All Power Resources that supply a System-Level reference of S0 or S1 are in the OFF state.
- Devices states are compatible with the current Power Resource states. Only devices that solely reference Power Resources that are in the ON state for a given device state can be in that device state. In all other cases, the device is in the D3 (off) state.
- Devices that are enabled to wake the system and that can do so from their current device state can initiate a hardware event that transitions the system state to S0. This transition causes the processor to begin execution at its boot location. The BIOS performs initialization of core functions as needed to exit an S2 state and passes control to the firmware resume vector. See Section 16.3.2, "BIOS Initialization of Memory," for more details on BIOS initialization.

Because the processor context can be lost while in the S2 state, the transition to the S2 state requires that the operating software flush all dirty cache to dynamic RAM (DRAM).

7.3.2.4 System _S3 State

The S3 state is logically lower than the S2 state and is assumed to conserve more power. The behavior of this state is defined as follows:

- The processors are not executing instructions. The processor-complex context is not maintained.
- Dynamic RAM context is maintained.
- Power Resources are in a state compatible with the system S3 state. All Power Resources that supply a System-Level reference of S0, S1, or S2 are in the OFF state.
- Devices states are compatible with the current Power Resource states. Only devices that solely reference Power Resources that are in the ON state for a given device state can be in that device state. In all other cases, the device is in the D3 (off) state.

^{1.} Or it is at least assumed to be in the D3 state by its device driver. For example, if the device doesn't explicitly describe how it can stay in some state non-off state while the system is in a sleeping state, the operating software must assume that the device can lose its power and state.

Power and Performance Management

• Devices that are enabled to wake the system and that can do so from their current device state can initiate a hardware event that transitions the system state to S0. This transition causes the processor to begin execution at its boot location. The BIOS performs initialization of core functions as necessary to exit an S3 state and passes control to the firmware resume vector. See Section 16.3.2, "BIOS Initialization of Memory," for more details on BIOS initialization.

From the software viewpoint, this state is functionally the same as the S2 state. The operational difference can be that some Power Resources that could be left ON to be in the S2 state might not be available to the S3 state. As such, additional devices may need to be in a logically lower D0, D1, D2, or D3 state for S3 than S2. Similarly, some device wake events can function in S2 but not S3.

Because the processor context can be lost while in the S3 state, the transition to the S3 state requires that the operating software flush all dirty cache to DRAM.

7.3.2.5 System _S4 State

While the system is in this state, it is in the system S4 sleeping state. The state is logically lower than the S3 state and is assumed to conserve more power. The behavior of this state is defined as follows:

- The processors are not executing instructions. The processor-complex context is not maintained.
- DRAM context is not maintained.
- Power Resources are in a state compatible with the system S4 state. All Power Resources that supply a System-Level reference of S0, S1, S2, or S3 are in the OFF state.
- Devices states are compatible with the current Power Resource states. In other words, all devices are in the D3 state when the system state is S4.
- Devices that are enabled to wake the system and that can do so from their device state in S4 can initiate a hardware event that transitions the system state to S0. This transition causes the processor to begin execution at its boot location.

After OSPM has executed the _PTS control method and has put the entire system state into main memory, there are two ways that OSPM may handle the next phase of the S4 state transition; saving and restoring main memory. The first way is to use the operating system's drivers to access the disks and file system structures to save a copy of memory to disk and then initiate the hardware S4 sequence by setting the SLP_EN register bit. When the system wakes, the firmware performs a normal boot process and transfers control to the OS via the firmware_waking_vector loader. The OS then restores the system's memory and resumes execution.

The alternate method for entering the S4 state is to utilize the BIOS via the S4BIOS transition. The BIOS uses firmware to save a copy of memory to disk and then initiates the hardware S4 sequence. When the system wakes, the firmware restores memory from disk and wakes OSPM by transferring control to the FACS waking vector.

The S4BIOS transition is optional, but any system that supports this mechanism must support entering the S4 state via the direct OS mechanism. Thus the preferred mechanism for S4 support is the direct OS mechanism as it provides broader platform support. The alternate S4BIOS transition provides a way to achieve S4 support on operating systems that do not have support for the direct method.

7.3.2.6 System _S5 State (Soft Off)

The S5 state is similar to the S4 state except that OSPM does not save any context. The system is in the soft off state and requires a complete boot when awakened (BIOS and OS). Software uses a different state value to distinguish between this state and the S4 state to allow for initial boot operations within the BIOS to distinguish whether or not the boot is going to wake from a saved memory image. OSPM does not disable wake events before setting the SLP_EN bit when entering the S5 system state. This provides support for remote management initiatives by enabling Remote Start capability. An ACPI-compliant OS must provide an end user accessible mechanism for disabling all wake devices, with the exception of the system power button, from a single point in the user interface.

7.3.3 _SWS (System Wake Source)

This object provides a means for OSPM to definitively determine the source of an event that caused the system to enter the S0 state. General-purpose event and fixed-feature hardware registers containing wake event sources information are insufficient for this purpose as the source event information may not be available after transitions to the S0 state from all other system states (S1-S5).

To determine the source event that caused the system to transition to the S0 state, OSPM will evaluate the _SWS object, when it exists, under the _GPE scope (for all fixed-feature general-purpose events from the GPE Blocks), under the _SB scope (for fixed-feature hardware events), and within the scope of a GPE Block device (for GPE events from this device). _SWS objects may exist in any or all of these locations as necessary for the platform to determine the source event that caused the system to transition to the S0 state.

Arguments:

None

Return Value:

An **Integer** containing the *Source Event* as described below

The value of the *Source Event* is dependent on the location of the _SWS object:

- 1. If _SWS is evaluated under the _**GPE** scope, *Source Event* is the index of the GPE that caused the system to transition to **S0**.
- 2. If _SWS is evaluated within the scope of a GPE block device, *Source Event* is the index of the GPE that caused the system to transition to **S0**. In this case, the index is relative to the GPE block device and is not unique system-wide.
- 3. If _SWS is evaluated under the _**SB** scope, *Source Event* is the the index in the PM1 status register that caused the system to transition to **S0**.

In all cases above, if the cause of the **S0** transition cannot be determined, SWS returns **Ones** (-1).

To enable OSPM to determine the source of the S0 state transition via the _SWS object, the hardware or firmware should detect and save the event that caused the transition so that it can be returned during _SWS object evaluation. The single wake source for the system may be latched in hardware during the transition so that no false wake events can be returned by _SWS. An implementation that does not use hardware to latch a single wake source for the system and instead uses firmware to save the wake source must do so as quickly as possible after the wakeup event occurs, so that _SWS does not return values that correspond to events that occurred after the sleep-to-wake transition. Such an

Power and Performance Management

implementation must also take care to ensure that events that occur subsequent to the wakeup source being saved do not overwrite the original wakeup source.

The source event data returned by _SWS must be determined for each transition into the S0 state. The value returned by _SWS must also be persistent during the system's residency in the S0 state as OSPM may evaluate _SWS multiple times. In this case, the platform must return the same source event information for each invocation.

After evaluating an _SWS object within the _GPE scope or within the scope of a GPE block device, OSPM will invoke the _Wxx control method corresponding to the GPE index returned by _SWS if it exists. This allows the platform to further determine source event if the GPE is shared among multiple devices. See Section 5.6.4.2.2 for details.

7.3.4 _TTS (Transition To State)

The _TTS control method is executed by the OSPM at the beginning of the sleep transition process for S1, S2, S3, S4, and orderly S5 shutdown. OSPM will invoke _TTS before it has notified any native mode device drivers of the sleep state transition. The sleeping state value (For example, 1, 2, 3, 4 or 5 for the S5 soft-off state) is passed to the _TTS control method.

The _TTS control method is also executed by the OSPM at the end of any sleep transition process when the system transitions to S0 from S1, S2, S3, or S4. OSPM will invoke _TTS after it has notified any native mode device drivers of the end of the sleep state transition. The working state value (0) is passed to the _TTS control method.

Arguments: (1)

Arg0 – An **Integer** containing the value of the sleeping state (1 for S1, 2 for S2, etc.)

Return Value:

None

If OSPM aborts the sleep transition process, OSPM will still run _TTS for an S0 transition to indicate the OSPM has returned to the S0 state. The platform must assume that if OSPM invokes the _TTS control method for an S1, S2, S3, or S4 transition, that OSPM will invoke _TTS control method for an S0 transition before returning to the S0 state.

The platform must not make any assumptions about the state of the machine when _TTS is called. For example, operation region accesses that require devices to be configured and enabled may not succeed, as these devices may be in a non-decoding state due to plug and play or power management operations.

7.3.5 _WAK (System Wake)

After the system wakes from a sleeping state, it will invoke the _WAK method and pass the sleeping state value that has ended. This operation occurs asynchronously with other driver notifications in the system and is not the first action to be taken when the system wakes. The AML code for this control method issues device, thermal, and other notifications to ensure that OSPM checks the state of devices, thermal zones, and so on, that could not be maintained during the system sleeping state. For example, if the system cannot determine whether a device was inserted or removed from a bus while in the S2 state, the _WAK method would issue a *devicecheck* type of notification for that bus when issued with the sleeping state value of 2 (for more information about

types of notifications, see <u>Section 5.6.6</u>, "Device Object Notifications"). Notice that a device check notification from the \ SB node will cause OSPM to re-enumerate the entire tree¹.

Hardware is not obligated to track the state needed to supply the resulting status; however, this method must return status concerning the last sleep operation initiated by OSPM. The return values can be used to provide additional information to OSPM or user.

Arguments: (1)

Arg0 – An **Integer** containing the value of the sleeping state (1 for S1, 2 for S2, etc.)

Return Value:

A Package containing two Integers containing status and the power supply S-state

Return Value Information

WAK returns a package with the following format:

Element 0 – An **Integer** containing a bitfield that represents conditions that occurred during sleep.

0x00000000 – Wake was signaled and was successful

0x00000001 – Wake was signaled but failed due to lack of power

0x00000002 – Wake was signaled but failed due to thermal condition

Other values – Reserved

Element 1 – An **Integer** containing the power supply S-state.

If non-zero, this is the effective S-state the power supply that was actually entered. This value is used to detect when the targeted S-state was not entered because of too much current being drawn from the power supply. For example, this might occur when some active device's current consumption pushes the system's power requirements over the low power supply mark, thus preventing the lower power mode from being entered as desired.

7.4 OSPM usage of _PTS, _TTS, and _WAK

OSPM will invoke PTS, TTS, and WAK in the following order:

- 1. OSPM decides (through a policy scheme) to place the system into a sleeping state
- 2. TTS(Sx) is run, where Sx is the desired sleep state to enter
- 3. OSPM notifies all native device drivers of the sleep state transition
- 4. PTS is run
- 5. OSPM readies system for the sleep state transition
- 6. OSPM writes the sleep vector and the system enters the specified Sx sleep state
- 7. System Wakes up
- 8. OSPM readies system for the return from the sleep state transition

^{1.} Only buses that support hardware-defined enumeration methods are done automatically at run-time. This would include ACPI-enumerated devices.

Power and Performance Management

- 9. _WAK is run
- 10. OSPM notifies all native device drivers of the return from the sleep state transition
- 11. _TTS(0) is run to indicate the return to the S0 state




Figure 7-38 Working / Sleeping State object evaluation flow

This section describes the configuration and control of the processor's power and performance states. The major controls over the processors are:

- Processor power states: C0, C1, C2, C3, ... Cn
- Processor clock throttling
- Processor performance states: P0, P1, ... Pn

These controls are used in combination by OSPM to achieve the desired balance of the following sometimes conflicting goals:

- Performance
- Power consumption and battery life
- Thermal requirements
- Noise-level requirements

Because the goals interact with each other, the operating software needs to implement a policy as to when and where tradeoffs between the goals are to be made¹. For example, the operating software would determine when the audible noise of the fan is undesirable and would trade off that requirement for lower thermal requirements, which can lead to lower processing performance. Each processor configuration and control interface is discussed in the following sections along with how controls interacts with the various goals.

8.1 Processor Power States

ACPI defines the power state of system processors while in the G0 working state² as being either active (executing) or sleeping (not executing). Processor power states include are designated C0, C1, C2, C3, ...Cn. The C0 power state is an active power state where the CPU executes instructions. The C1 through Cn power states are processor sleeping states where the processor consumes less power and dissipates less heat than leaving the processor in the C0 state. While in a sleeping state, the processor does not execute any instructions. Each processor sleeping state has a latency associated with entering and exiting that corresponds to the power savings. In general, the longer the entry/exit latency, the greater the power savings when in the state. To conserve power, OSPM places the processor into one of its supported sleeping states when idle. While in the C0 state, ACPI allows the performance of the processor to be altered through a defined "throttling" process and through

^{1.} A thermal warning leaves room for operating system tradeoffs to occur (to start the fan or to reduce performance), but a critical thermal alert does not occur.

^{2.} Notice that these CPU states map into the G0 working state. The state of the CPU is undefined in the G3 sleeping state, the Cx states only apply to the G0 state.

transitions into multiple performance states (P-states). A diagram of processor power states is provided below.




Figure 8-39 Processor Power States

ACPI defines logic on a per-CPU basis that OSPM uses to transition between the different processor power states. This logic is optional, and is described through the FADT table and processor objects (contained in the hierarchical namespace). The fields and flags within the FADT table describe the symmetrical features of the hardware, and the processor object contains the location for the particular CPU's clock logic (described by the P BLK register block and CST objects).

The P_LVL2 and P_LVL3 registers provide optional support for placing the system processors into the C2 or C3 states. The P_LVL2 register is used to sequence the selected processor into the C2 state, and the P_LVL3 register is used to sequence the selected processor into the C3 state. Additional support for the C3 state is provided through the bus master status and arbiter disable bits (BM_STS in the PM1_STS register and ARB_DIS in the PM2_CNT register). System software reads the P_LVL2 or P_LVL3 registers to enter the C2 or C3 power state. The Hardware must put the processor into the proper clock state precisely on the read operation to the appropriate P_LVLx register. The platform may alternatively define interfaces allowing OSPM to enter C-states using the _CST object, which is defined in Section 8.4.2.1, "_CST (C States)".

Processor power state support is symmetric when presented via the FADT and P_BLK interfaces; OSPM assumes all processors in a system support the same power states. If processors have non-

symmetric power state support, then the BIOS will choose and use the lowest common power states supported by all the processors in the system through the FADT table. For example, if the CPU0 processor supports all power states up to and including the C3 state, but the CPU1 processor only supports the C1 power state, then OSPM will only place idle processors into the C1 power state (CPU0 will never be put into the C2 or C3 power states). Notice that the C1 power state must be supported. The C2 and C3 power states are optional (see the PROC_C1 flag in the FADT table description in Section 5.2.6, "System Description Table Header").

The following sections describe processor power states in detail.

8.1.1 Processor Power State C0

While the processor is in the C0 power state, it executes instructions. While in the C0 power state, OSPM can generate a policy to run the processor at less than maximum performance. The clock throttling mechanism provides OSPM with the functionality to perform this task in addition to thermal control. The mechanism allows OSPM to program a value into a register that reduces the processor's performance to a percentage of maximum performance.




Figure 8-40 Throttling Example

The FADT contains the duty offset and duty width values. The duty offset value determines the offset within the P_CNT register of the duty value. The duty width value determines the number of bits used by the duty value (which determines the granularity of the throttling logic). The performance of the processor by the clock logic can be expressed with the following equation:

%
$$Performance = \frac{dutysetting}{2^{dutywidth}} * 100\%$$

Figure 8-41 Equation 1 Duty Cycle Equation

Nominal performance is defined as "close as possible, but not below the indicated performance level." OSPM will use the duty offset and duty width to determine how to access the duty setting field. OSPM will then program the duty setting based on the thermal condition and desired power of the processor object. OSPM calculates the nominal performance of the processor using the equation expressed in Equation 1. Notice that a *dutysetting* of zero is reserved. For example, the clock logic could use the stop grant cycle to emulate a divided processor clock frequency on an IA processor (through the use of the STPCLK# signal). This signal internally stops the processor's clock when asserted LOW. To implement logic that provides eight levels of clock control, the STPCLK# pin could be asserted as follows (to emulate the different frequency settings):




Figure 8-42 Example Control for the STPCLK#

To start the throttling logic OSPM sets the desired duty setting and then sets the THT_EN bit HIGH. To change the duty setting, OSPM will first reset the THT_EN bit LOW, then write another value to the duty setting field while preserving the other unused fields of this register, and then set the THT_EN bit HIGH again.

The example logic model is shown below:




Figure 8-43 ACPI Clock Logic (One per Processor)

Implementation of the ACPI processor power state controls minimally requires the support a single CPU sleeping state (C1). All of the CPU power states occur in the G0/S0 system state; they have no meaning when the system transitions into the sleeping state(S1-S4). ACPI defines the attributes

(semantics) of the different CPU states (defines four of them). It is up to the platform implementation to map an appropriate low-power CPU state to the defined ACPI CPU state.

ACPI clock control is supported through the optional processor register block (P_BLK). ACPI requires that there be a unique processor register block for each CPU in the system. Additionally, ACPI requires that the clock logic for multiprocessor systems be symmetrical when using the P_BLK and FADT interfaces; if the P0 processor supports the C1, C2, and C3 states, but P1 only supports the C1 state, then OSPM will limit all processors to enter the C1 state when idle.

The following sections define the different ACPI CPU sleeping states.

8.1.2 Processor Power State C1

All processors must support this power state. This state is supported through a native instruction of the processor (HLT for IA 32-bit processors), and assumes no hardware support is needed from the chipset. The hardware latency of this state must be low enough that OSPM does not consider the latency aspect of the state when deciding whether to use it. Aside from putting the processor in a power state, this state has no other software-visible effects. In the C1 power state, the processor is able to maintain the context of the system caches.

The hardware can exit this state for any reason, but must always exit this state when an interrupt is to be presented to the processor.

8.1.3 Processor Power State C2

This processor power state is optionally supported by the system. If present, the state offers improved power savings over the C1 state and is entered by using the P_LVL2 command register for the local processor or an alternative mechanism as indicated by the _CST object. The worst-case hardware latency for this state is declared in the FADT and OSPM can use this information to determine when the C1 state should be used instead of the C2 state. Aside from putting the processor in a power state, this state has no other software-visible effects. OSPM assumes the C2 power state has lower power and higher exit latency than the C1 power state.

The C2 power state is an optional ACPI clock state that needs chipset hardware support. This clock logic consists of an interface that can be manipulated to cause the processor complex to precisely transition into a C2 power state. In a C2 power state, the processor is assumed capable of keeping its caches coherent; for example, bus master and multiprocessor activity can take place without corrupting cache context.

The C2 state puts the processor into a low-power state optimized around multiprocessor and bus master systems. OSPM will cause an idle processor complex to enter a C2 state if there are bus masters or Multiple processor activity (which will prevent OSPM from placing the processor complex into the C3 state). The processor complex is able to snoop bus master or multiprocessor CPU accesses to memory while in the C2 state.

The hardware can exit this state for any reason, but must always exit this state whenever an interrupt is to be presented to the processor.

8.1.4 Processor Power State C3

This processor power state is optionally supported by the system. If present, the state offers improved power savings over the C1 and C2 state and is entered by using the P LVL3 command

register for the local processor or an alternative mechanism as indicated by the _CST object. The worst-case hardware latency for this state is declared in the FADT, and OSPM can use this information to determine when the C1 or C2 state should be used instead of the C3 state. While in the C3 state, the processor's caches maintain state but the processor is not required to snoop bus master or multiprocessor CPU accesses to memory.

The hardware can exit this state for any reason, but must always exit this state when an interrupt is to be presented to the processor or when BM_RLD is set and a bus master is attempting to gain access to memory.

OSPM is responsible for ensuring that the caches maintain coherency. In a uniprocessor environment, this can be done by using the PM2_CNT.ARB_DIS bus master arbitration disable register to ensure bus master cycles do not occur while in the C3 state. In a multiprocessor environment, the processors' caches can be flushed and invalidated such that no dynamic information remains in the caches before entering the C3 state.

There are two mechanisms for supporting the C3 power state:

- Having OSPM flush and invalidate the caches prior to entering the C3 state.
- Providing hardware mechanisms to prevent masters from writing to memory (uniprocessor-only support).

In the first case, OSPM will flush the system caches prior to entering the C3 state. As there is normally much latency associated with flushing processor caches, OSPM is likely to only support this in multiprocessor platforms for idle processors. Flushing of the cache is accomplished through one of the defined ACPI mechanisms (described below in <u>Section 8.2</u>, "Flushing Caches").

In uniprocessor-only platforms that provide the needed hardware functionality (defined in this section), OSPM will attempt to place the platform into a mode that will prevent system bus masters from writing into memory while the processor is in the C3 state. This is accomplished by disabling bus masters prior to entering a C3 power state. Upon a bus master requesting an access, the CPU will awaken from the C3 state and re-enable bus master accesses.

OSPM uses the BM_STS bit to determine the power state to enter when considering a transition to or from the C2/C3 power state. The BM_STS is an optional bit that indicates when bus masters are active. OSPM uses this bit to determine the policy between the C2 and C3 power states: a lot of bus master activity demotes the CPU power state to the C2 (or C1 if C2 is not supported), no bus master activity promotes the CPU power state to the C3 power state. OSPM keeps a running history of the BM_STS bit to determine CPU power state policy.

The last hardware feature used in the C3 power state is the BM_RLD bit. This bit determines if the Cx power state is exited as a result of bus master requests. If set, then the Cx power state is exited upon a request from a bus master. If reset, the power state is not exited upon bus master requests. In the C3 state, bus master requests need to transition the CPU back to the C0 state (as the system is capable of maintaining cache coherency), but such a transition is not needed for the C2 state. OSPM can optionally set this bit when using a C3 power state, and clear it when using a C1 or C2 power state.

8.1.5 Additional Processor Power States

ACPI introduced optional processor power states beyond C3 starting in ACPI 2.0. These power states, C4... Cn, are conveyed to OSPM through the _CST object defined in <u>Section 8.4.2.1</u>, "_CST

(C-States)." These additional power states are characterized by equivalent operational semantics to the C1 through C3 power states, as defined in the previous sections, but with different entry/exit latencies and power savings. See <u>Section 8.4.2.1</u>, "_CST (C-States)," for more information.

8.2 Flushing Caches

To support the C3 power state without using the ARB_DIS feature, the hardware must provide functionality to flush and invalidate the processors' caches (for an IA processor, this would be the WBINVD instruction). To support the S1, S2 or S3 sleeping states, the hardware must provide functionality to flush the platform caches. Flushing of caches is supported by one of the following mechanisms:

- Processor instruction to write back and invalidate system caches (WBINVD instruction for IA processors).
- Processor instruction to write back but not invalidate system caches (WBINVD instruction for IA processors and some chipsets with partial support; that is, they don't invalidate the caches).

The ACPI specification expects all platforms to support the local CPU instruction for flushing system caches (with support in both the CPU and chipset), and provides some limited "best effort" support for systems that don't currently meet this capability. The method used by the platform is indicated through the appropriate FADT fields and flags indicated in this section.

ACPI specifies parameters in the FADT that describe the system's cache capabilities. If the platform properly supports the processor's write back and invalidate instruction (WBINVD for IA processors), then this support is indicated to OSPM by setting the WBINVD flag in the FADT.

If the platform supports neither of the first two flushing options, then OSPM can attempt to manually flush the cache if it meets the following criteria:

- A cache-enabled sequential read of contiguous physical memory of not more than 2 MB will flush the platform caches.
- There are two additional FADT fields needed to support manual flushing of the caches:
- FLUSH SIZE, typically twice the size of the largest cache in the system.
- FLUSH STRIDE, typically the smallest cache line size in the system.

8.3 Power, Performance, and Throttling State Dependencies

Cost and complexity trade-off considerations have driven into the platform control dependencies between logical processors when entering power, performance, and throttling states. These dependencies exist in various forms in multi-processor, multi-threaded processor, and multi-core processor-based platforms. These dependencies may also be hierarchical. For example, a multi-processor system consisting of processors containing multiple cores containing multiple threads may have various dependencies as a result of the hardware implementation.

Unless OSPM is aware of the dependency between the logical processors, it might lead to scenarios where one logical processor is implicitly transitioned to a power, performance, or throttling state when it is unwarranted, leading to incorrect / non-optimal system behavior. Given knowledge of the dependencies, OSPM can coordinate the transitions between logical processors, choosing to initiate the transition when doing so does not lead to incorrect or non-optimal system behavior. This OSPM coordination is referred to as Software (SW) Coordination. Alternately, it might be possible for the underlying hardware to coordinate the state transition requests on multiple logical processors, causing the processors to transition to the target state when the transition is guaranteed to not lead to incorrect or non-optimal system behavior. This scenario is referred to as Hardware (HW) coordination. When hardware coordinates transitions, OSPM continues to initiate state transitions as it would if there were no dependencies. However, in this case it is required that hardware provide OSPM with a means to determine actual state residency so that correct / optimal control policy can be realized.

Platforms containing logical processors with cross-processor dependencies in the power, performance, or throttling state control areas use ACPI defined interfaces to group logical processors into what is referred to as a dependency domain. The Coordination Type characteristic for a domain specifies whether OSPM or underlying hardware is responsible for the coordination. When OSPM coordinates, the platform may require that OSPM transition ALL (0xFC) or ANY ONE (0xFD) of the processors belonging to the domain into a particular target state. OSPM may choose at its discretion to perform coordination even though the underlying hardware supports hardware coordination. In this case, OSPM must transition all logical processors in the dependency domain to the particular target state.

There are no dependencies implied between a processor's C-states, P-states or T-states. Hence, for example it is possible to use the same dependency domain number for specifying dependencies between P-states among one set of processors and C-states among another set of processors without any dependencies being implied between the P-State transitions on a processor in the first set and C-state transitions on a processor in the second set.

8.4 Declaring Processors

Each processor in the system must be declared in the ACPI namespace in either the _SB or _PR scope but not both. Declaration of processors in the _PR scope is required for platforms desiring compatibility with ACPI 1.0-based OSPM implementations. Processors are declared either via the ASL **Processor** statement or the ASL **Device** statement. A **Processor** definition declares a processor object that provides processor configuration information and points to the processor register block (P_BLK). A **Device** definition for a processor is declared using the ACPI0007 hardware identifier (HID). In this case, processor configuration information is provided exclusively by objects in the processor device's object list.

When the platform uses the APIC interrupt model, OSPM associates processors declared in the namespace with entries in the MADT. Prior to ACPI 3.0, this was accomplished using the processor object's ProcessorID and the ACPI Processor ID fields in MADT entries. UID fields were added to MADT entries in ACPI 3.0. By expanding processor declaration using **Device** definitions, UID object values under a processor device are used to associate processor devices with entries in the MADT. This removes the previous 256 processor declaration limit.

The platform may declare processors with IDs in the range of 0-254 for APIC/x2APIC implementations and 0-255 for SAPIC implementations using either the ASL **Processor** statement or the ASL **Device** statement but not both. Processors with IDs outside these ranges must be declared using the ASL **Device** statement.

Processor-specific objects may be included in the processor object's optional object list or declared within the processor device's scope. These objects serve multiple purposes including providing alternative definitions for the registers described by the processor register block (P_BLK) and processor performance state control. Other ACPI-defined device-related objects are also allowed in the processor object's object list or under the processor device's scope (for example, the unique identifier object UID).

With device-like characteristics attributed to processors, it is implied that a processor device driver will be loaded by OSPM to, at a minimum, process device notifications. OSPM will enumerate processors in the system using the ACPI Namespace, processor-specific native identification instructions, and optionally the _HID method.

OSPM will ignore definitions of ACPI-defined objects in an object list of a processor object declared under the \ PR scope.

For more information on the declaration of the processor object, see <u>Section 19.5.100</u>, "Processor (Declare Processor)." Processor-specific objects are described in the following sections.

8.4.1 _PDC (Processor Driver Capabilities)

This optional object is a method that is used by OSPM to communicate to the platform the level of processor power management support provided by OSPM. This object is a child object of the processor. OSPM evaluates _PDC prior to evaluating any other processor power management objects returning configuration information.

The _PDC object provides OSPM a mechanism to convey to the platform the capabilities supported by OSPM for processor power management. This allows the platform to modify the ACPI namespace objects returning configuration information for processor power management based on the level of support provided by OSPM. Using this method provides a mechanism for OEMs to

provide support for new technologies on legacy OSes, while also allowing OSPM to leverage new technologies on platforms capable of supporting them. This method is evaluated once during processor device initialization, and will not be re-evaluated during resume from a sleep state transition. The platform must preserve state information across S1-S3 sleep state transitions.

Arguments: (1)

Arg0 – A variable-length **Buffer** containing a list of capabilities as described below

Return Value:

None

The buffer argument contains a list of DWORDs in the following format:

RevisionId – Revision of the buffer format

Count – The number of capability values in the capabilities array

Capabilities [Count] – Capabilities array

Each DWORD entry in the capabilities array is a bitfield that defines capabilities and features supported by OSPM for processor configuration and power management as specified by the CPU manufacturer.

The use of _PDC is deprecated in ACPI 3.0 in favor of _OSC. For backwards compatibility, _PDC may be implemented using _OSC as follows:

```
Method(_PDC,1)
{
    CreateDWordField (Arg0, 0, REVS)
    CreateDWordField (Arg0, 4, SIZE)

//
    // Local0 = Number of bytes for Arg0
    //
    Store (SizeOf (Arg0), Local0)

//
    // Local1 = Number of Capabilities bytes in Arg0
    //
    Store (Subtract (Local0, 8), Local1)

//
    // TEMP = Temporary field holding Capability DWORDS
    //
    CreateField (Arg0, 64, Multiply (Local1, 8), TEMP)

//
    // Create the Status (STS0) buffer with the first DWORD = 0
    // This is required to return errors defined by _OSC.
    //
    Name (STS0, Buffer () {0x00, 0x00, 0x00, 0x00})

//
    // Concatenate the _PDC capabilities bytes to the STS0 Buffer
    // and store them in a local variable for calling OSC
    //
    Concatenate (STS0, TEMP, Local2)
```

```
//
// Note: The UUID passed into _OSC is CPU vendor specific. Consult CPU
// vendor documentation for UUID and Capabilities Buffer bit definitions
//
_OSC (ToUUID("4077A616-290C-47BE-9EBD-D87058713953"), REVS, SIZE, Local2)
```

<u>Section 6.2.11</u>, "_OSC (Operating System Capabilities)", describes the _OSC object, which can be used to convey processor related OSPM capabilities to the platform. Consult CPU vendor specific documentation for the UUID and Capabilities Buffer bit definitions used by _OSC for a specific processor.

8.4.2 Processor Power State Control

ACPI defines two processor power state (C state) control interfaces. These are:

- The Processor Register Block's (P_BLK's) P_LVL2 and P_LVL3 registers coupled with FADT P LVLx LAT values and
- 2. The CST object in the processor's object list.

P_BLK based C state controls are described in <u>Section 4</u>, "ACPI Hardware Specification" and <u>Section 8.1</u>, "Processor Power States". _CST based C state controls expand the functionality of the P_BLK based controls allowing the number and type of C states to be dynamic and accommodate CPU architecture specific C state entry and exit mechanisms as indicated by registers defined using the Functional Fixed Hardware address space.

8.4.2.1 _CST (C States)

_CST is an optional object that provides an alternative method to declare the supported processor power states (C States). Values provided by the _CST object override P_LVLx values in P_BLK and P_LVLx_LAT values in the FADT. The _CST object allows the number of processor power states to be expanded beyond C1, C2, and C3 to an arbitrary number of power states. The entry semantics for these expanded states, (in other words), the considerations for entering these states, are conveyed to OSPM by the C-state Type field and correspond to the entry semantics for C1, C2, and C3 as described in Section 8.1.2 through Section 8.1.4. _CST defines ascending C-states characterized by lower power and higher entry/exit latency.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of C-state information **Packages** as described below

Return Value Information

CST returns a variable-length **Package** that contains the following elements:

Count An **Integer** that contains the number of CState sub-packages that follow

CStates[] A list of **Count** CState sub-packages

Each fixed-length Cstate sub-Package contains the elements described below:

Table 8-222 Cstate Package Values

Element	Object Type	Description	
Register	Buffer	Contains a Resource Descriptor with a single Register() descriptor that describes the register that OSPM must read to place the processor in the corresponding C state.	
Туре	Integer (BYTE)	The C State type (1=C1, 2=C2, 3=C3). This field conveys the semantics to be used by OSPM when entering/exiting the C state. Zero is not a valid value.	
Latency	Integer (WORD)	The worst-case latency to enter and exit the C State (in microseconds). There are no latency restrictions.	
Power	Integer (DWORD)	The average power consumption of the processor when in the corresponding C State (in milliwatts).	

The platform must expose a _CST object for either all or none of its processors. If the _CST object exists, OSPM uses the C state information specified in the _CST object in lieu of P_LVL2 and P_LVL3 registers defined in P_BLK and the P_LVLx_LAT values defined in the FADT. Also notice that if the _CST object exists and the _PTC object does **not** exist, OSPM will use the Processor Control Register defined in P_BLK and the C_State_Register registers in the _CST object.

The platform may change the number or type of C States available for OSPM use dynamically by issuing a **Notify** event on the processor object with a notification value of 0x81. This will cause OSPM to re-evaluate any _CST object residing under the processor object notified. For example, the platform might notify OSPM that the number of supported C States has changed as a result of an asynchronous AC insertion / removal event.

The platform must specify unique C_State_Register addresses for all entries within a given _CST object.

_CST eliminates the ACPI 1.0 restriction that all processors must have C State parity. With _CST, each processor can have its own characteristics independent of other processors. For example, processor 0 can support C1, C2 and C3, while processor 1 supports only C1.

The fields in the processor structure remain for backward compatibility.

Example

```
Processor (
\_SB.CPU0,
                // Processor Name
1,
                // ACPI Processor number
0x120,
                // PBlk system IO address
6)
                 // PBlkLen
Name(_CST, Package()
4,
                 // There are four C-states defined here with three semantics
                 // The third and fourth C-states defined have the same C3 entry semantics
Package(){ResourceTemplate(){Register(FFixedHW, 0, 0, 0)},
                                                           1, 20, 1000},
Package(){ResourceTemplate(){Register(SystemIO, 8, 0, 0x161)}, 2, 40, 750},
Package(){ResourceTemplate(){Register(SystemIO, 8, 0, 0x162)}, 3, 60, 500},
Package(){ResourceTemplate(){Register(SystemIO, 8, 0, 0x163)}, 3, 100, 250}
})
```

Notice in the example above that OSPM should anticipate the possibility of a _CST object providing more than one entry with the same C_State_Type value. In this case OSPM must decide which C State Register it will use to enter that C state.

Example

This is an example usage of the CST object using the typical values as defined in ACPI 1.0.

The platform will issue a **Notify**($_$ SB.CPU0, 0x81) to inform OSPM to re-evaluate this object when the number of available processor power states changes.

8.4.2.2 CSD (C-State Dependency)

This optional object provides C-state control cross logical processor dependency information to OSPM. The _CSD object evaluates to a packaged list of information that correlates with the C-state information returned by the _CST object. Each packaged list entry identifies the C-state for which the dependency is being specified (as an index into the _CST object list), a dependency domain number for that C-state, the coordination type for that C-state and the number of logical processors belonging to the domain for the particular C-state. It is possible that a particular C-state may belong to multiple domains. That is, it is possible to have multiple entries in the _CSD list with the same CStateIndex value.

Arguments:

None

Return Value:

A variable-length Package containing a list of C-state dependency Packages as described below.

Return Value Information

Each CstateDependency sub-Package contains the elements described below:

Table 8-223 CStateDependency Package Values

Element	Object Type	Description	
NumEntries	Integer	The number of entries in the cstateDependency package including this field. Current value is 6.	
Revision	Integer (BYTE)	The revision number of the cstateDependency package format. Current value is 0.	
Domain	Integer (DWORD)	The dependency domain number to which this C state entry belongs.	
CoordType	Integer (DWORD)	The type of coordination that exists (hardware) or is required (software) as a result of the underlying hardware dependency. Could be either 0xFC (SW_ALL), 0xFD (SW_ANY) or 0xFE (HW_ALL) indicating whether OSPM is responsible for coordinating the C-state transitions among processors with dependencies (and needs to initiate the transition on all or any processor in the domain) or whether the hardware will perform this coordination.	
Num Processors	Integer (DWORD)	The number of processors belonging to the domain for the particular C-state. OSPM will not start performing power state transitions to a particular C-state until this number of processors belonging to the same domain for the particular C-state have been detected and started.	
Index	Integer (DWORD)	Indicates the index of the C-State entry in the _CST object for which the dependency applies.	

Given that the number or type of available C States may change dynamically, ACPI supports Notify events on the processor object, with Notify events of type 0x81 causing OSPM to re-evaluate any

_CST objects residing under the particular processor object notified. On receipt of Notify events of type 0x81, OSPM should re-evaluate any present _CSD objects also.

Example

This is an example usage of the _CSD structure in a Processor structure in the namespace. The example represents a two processor configuration. The C1-type state can be independently entered on each processor. For the C2-type state, there exists dependence between the two processors, such that one processor transitioning to the C2-type state, causes the other processor to transition to the C2-type state. A similar dependence exists for the C3-type state. OSPM will be required to coordinate the C2 and C3 transitions between the two processors. Also OSPM can initiate a transition on either processor to cause both to transition to the common target C-state.

```
Processor (
\_SB.CPU0,
                                     // Processor Name
1,
                                     // ACPI Processor number
0x120,
                                     // PBlk system IO address
                                     // PBlkLen
6)
Name (_CST, Package()
                 // There are three C-states defined here with three semantics
   Package(){ResourceTemplate(){Register(FFixedHW, 0, 0, 0)}, 1, 20, 1000},
   Package(){ResourceTemplate(){Register(SystemIO, 8, 0, 0x161)}, 2, 40, 750},
    Package(){ResourceTemplate(){Register(SystemIO, 8, 0, 0x162)}, 3, 60, 500}
})
Name(_CSD, Package()
    Package(){6, 0, 0, 0xFD, 2, 1}, // 6 entries, Revision 0, Domain 0, OSPM Coordinate
                                    // Initiate on Any Proc, 2 Procs, Index 1 (C2-type)
    Package(){6, 0, 0, 0xFD, 2, 2} // 6 entries, Revision 0 Domain 0, OSPM Coordinate
                                     // Initiate on Any Proc, 2 Procs, Index 2 (C3-type)
})
Processor (
\_SB.CPU1,
                                     // Processor Name
2,
                                     // ACPI Processor number
                                     // PBlk system IO address
                                     // PBlkLen
Name(_CST, Package()
                 // There are three C-states defined here with three semantics
    Package(){ResourceTemplate(){Register(FFixedHW, 0, 0, 0)}, 1, 20, 1000},
    Package(){ResourceTemplate(){Register(SystemIO, 8, 0, 0x161)}, 2,
    Package(){ResourceTemplate(){Register(SystemIO, 8, 0, 0x162)}, 3, 60, 500}
})
Name(_CSD, Package()
    Package(){6, 0, 0, 0xFD, 2, 1}, // 6 entries, Revision 0, Domain 0, OSPM Coordinate
                                      // Initiate on any Proc, 2 Procs, Index 1 (C2-type)
    Package(){6, 0, 0, 0xFD, 2, 2} // 6 entries, Revision 0, Domain 0, OSPM Coordinate
                                       // Initiate on any Proc, 2 Procs, Index 2 (C3-type)
})
```

When the platform issues a **Notify**(_SB.CPU0, 0x81) to inform OSPM to re-evaluate _CST when the number of available processor power states changes, OSPM should also evaluate _CSD.

8.4.3 Processor Throttling Controls

ACPI defines two processor throttling (T state) control interfaces. These are:

- The Processor Register Block's (P_BLK's) P_CNT register, and
- The combined PTC, TSS, and TPC objects in the processor's object list.

P_BLK based throttling state controls are described in <u>Section 4</u>, "ACPI Hardware Specification" and <u>Section 8.1.1</u>, "Processor Power State C0". Combined _PTC, _TSS, and _TPC based throttling state controls expand the functionality of the P_BLK based control allowing the number of T states to be dynamic and accommodate CPU architecture specific T state control mechanisms as indicated by registers defined using the Functional Fixed Hardware address space. While platform definition of the _PTC, _TSS, and _TPC objects is optional, all three objects must exist under a processor for OSPM to successfully perform processor throttling via these controls.

8.4.3.1 PTC (Processor Throttling Control)

_PTC is an optional object that defines a processor throttling control interface alternative to the I/O address spaced-based P_BLK throttling control register (P_CNT) described in Section 4, "ACPI Hardware Specification". The processor throttling control register mechanism remains as defined in Section 8.1.1, "Processor Power State CO."

OSPM performs processor throttling control by writing the Control field value for the target throttling state (T-state), retrieved from the Throttling Supported States object (_TSS), to the Throttling Control Register (THROTTLE_CTRL) defined by the _PTC object. OSPM may select any processor throttling state indicated as available by the value returned by the _TPC control method.

Success or failure of the processor throttling state transition is determined by reading the Throttling Status Register (THROTTLE_STATUS) to determine the processor's current throttling state. If the transition was successful, the value read from THROTTLE_STATUS will match the "Status" field in the TSS entry that corresponds to the targeted processor throttling state.

Arguments:

None

Return Value:

A Package as described below

Return Value Information

Table 8-224 PTC Package Values

Element	Object Type	Description	
Control	Buffer	Contains a Resource Descriptor with a single Register() descriptor that	
Register		describes the throttling control register.	

Element	Object Type	Description
Status	Buffer	Contains a Resource Descriptor with a single Register() descriptor that
Register		describes the throttling status register.

The platform must expose a _PTC object for either all or none of its processors. Notice that if the _PTC object exists, the specified register is used instead of the P_CNT register specified in the Processor term. Also notice that if the _PTC object exists and the _CST object does **not** exist, OSPM will use the processor control register from the _PTC object and the P_LVLx registers from the P_BLK.

Example

This is an example usage of the PTC object in a Processor object list:

```
Processor (
        \_SB.CPU0,
                                // Processor Name
        1,
                                // ACPI Processor number
        0x120,
                                // PBlk system IO address
                                // PBlkLen
        6)
                                // Object List
    {
       Name(_PTC, Package ()
                                // Processor Throttling Control object
           ResourceTemplate(){Register(FFixedHW, 0, 0, 0)},
                                                                // Throttling_CTRL
           ResourceTemplate(){Register(FFixedHW, 0, 0, 0)}
                                                                  // Throttling_STATUS
        })
                                // End of _PTC object
                                 // End of Object List
```

Example

This is an example usage of the _PTC object using the values defined in ACPI 1.0. This is an illustrative example to demonstrate the mechanism with well-known values.

```
Processor (
       \_SB.CPU0,
                               // Processor Name
       1,
                               // ACPI Processor number
                               // PBLK system IO address
       0x120,
                               // PBLK Len
       6)
   {
                               // Object List
       Name(_PTC, Package () // Processor Throttling Control object -
                               // 32 bit wide IO space-based register at the <P_BLK> address
          ResourceTemplate(){Register(SystemIO, 32, 0, 0x120)}, // Throttling_CTRL
          ResourceTemplate(){Register(SystemIO, 32, 0, 0x120)} // Throttling_STATUS
                               // End of _PTC object
                               // End of Object List
```

8.4.3.2 _TSS (Throttling Supported States)

This optional object indicates to OSPM the number of supported processor throttling states that a platform supports. This object evaluates to a packaged list of information about available throttling states including percentage of maximum internal CPU core frequency, maximum power dissipation, control register values needed to transition between throttling states, and status register values that allow OSPM to verify throttling state transition status after any OS-initiated transition change request. The list is sorted in descending order by power dissipation. As a result, the zeroth entry

describes the highest performance throttling state (no throttling applied) and the 'nth' entry describes the lowest performance throttling state (maximum throttling applied).

When providing the _TSS, the platform must supply a _TSS entry whose *Percent* field value is 100. This provides a means for OSPM to disable throttling and achieve maximum performance.

Arguments:

None

Return Value:

A variable-length Package containing a list of Tstate sub-packages as described below

Return Value Information

Each Tstate sub-**Package** contains the elements described below:

Table 8-225 TState Package Values

Element	Object Type	Description			
Percent	Integer (DWORD)	Indicates the percent of the core CPU operating frequency that will be available when this throttling state is invoked. The range for this field is 1-100. This percentage applies independent of the processor's performance state (P-state). That is, this throttling state will invoke the percentage of maximum frequency indicated by this field as applied to the <i>CoreFrequency</i> field of the _PSS entry corresponding to the P-state for which the processor is currently resident.			
Power	Integer (DWORD)	Indicates the throttling state's maximum power dissipation (in milliWatts). OSPM ignores this field on platforms the support P-states, which provide power dissipation information via the _PSS object.			
Latency	Integer (DWORD)	Indicates the worst-case latency in microseconds that the CPU is unavailable during a transition from any throttling state to this throttling state.			
Control	Integer (DWORD)	Indicates the value to be written to the Processor Control Register (THROTTLE_CTRL) in order to initiate a transition to this throttling state.			

Element	Object Type	Description
Status	Integer (DWORD)	Indicates the value that OSPM will compare to a value read from the Throttle Status Register (THROTTLE_STATUS) to ensure that the transition to the throttling state was successful. OSPM may always place the CPU in the lowest power throttling state, but additional states are only available when indicated by the _TPC control method. A value of zero indicates the transition to the Throttling state is asynchronous, and as such no status value comparison is required.

8.4.3.3 _TPC (Throttling Present Capabilities)

This optional object is a method that dynamically indicates to OSPM the number of throttling states currently supported by the platform. This method returns a number that indicates the _TSS entry number of the highest power throttling state that OSPM can use at a given time. OSPM may choose the corresponding state entry in the _TSS as indicated by the value returned by the _TPC method or any lower power (higher numbered) state entry in the _TSS.

Arguments:

None

Return Value:

An **Integer** containing the number of states supported:

0 – states 0 ... nth state available (all states available)

1 – state 1 ... n^{th} state available

2 – state 2 ... nth state available

n – state n available only

In order to support dynamic changes of _TPC object, Notify events on the processor object of type 0x82 will cause OSPM to reevaluate any _TPC object in the processor's object list. This allows AML code to notify OSPM when the number of supported throttling states may have changed as a result of an asynchronous event. OSPM ignores _TPC Notify events on platforms that support P-states unless the platform has limited OSPM's use of P-states to the lowest power P-state. OSPM may choose to disregard any platform conveyed T-state limits when the platform enables OSPM usage of other than the lowest power P-state.

8.4.3.4 TSD (T-State Dependency)

This optional object provides T-state control cross logical processor dependency information to OSPM. The _TSD object evaluates to a packaged list of information that correlates with the T-state information returned by the _TSS object. Each packaged list entry identifies a dependency domain number for the logical processor's T-states, the coordination type for that T-state, and the number of logical processors belonging to the domain.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of T-state dependency **Packages** as described below.

Return Value Information

Table 8-226 TStateDependency Package Values

Element	Object Type	Description	
NumEntries	Integer	The number of entries in the TstateDependency package including this field Current value is 5.	
Revision	Integer (BYTE)	The revision number of the TStateDependency package format. Current value is 0.	
Domain	Integer (DWORD)	The dependency domain number to which this T state entry belongs.	
CoordType	Integer (DWORD)	The type of coordination that exists (hardware) or is required (software) as a result of the underlying hardware dependency. Could be either 0xFC (SW_ALL), 0xFD (SW_ANY) or 0xFE (HW_ALL) indicating whether OSPM is responsible for coordinating the T-state transitions among processors with dependencies (and needs to initiate the transition on all or any processor in the domain) or whether the hardware will perform this coordination.	
Num Processors	Integer (DWORD)	The number of processors belonging to the domain for this logical processor's T-states. OSPM will not start performing power state transitions to a particular T-state until this number of processors belonging to the same domain have been detected and started.	

Example

This is an example usage of the _TSD structure in a Processor structure in the namespace. The example represents a two processor configuration with three T-states per processor. For all T-states, there exists dependence between the two processors, such that one processor transitioning to a particular T-state, causes the other processor to transition to the same T-state. OSPM will be required to coordinate the T-state transitions between the two processors and can initiate a transition on either processor to cause both to transition to the common target T-state.

```
Processor (
    \_SB.CPU0,
                                     // Processor Name
   1,
                                     // ACPI Processor number
    0 \times 120.
                                     // PBlk system IO address
    6)
                                     // PBlkLen
{ //Object List
    Name(_PTC, Package () // Processor Throttling Control object -
                          // 32 bit wide IO space-based register at the <P_BLK> address
        ResourceTemplate(){Register(SystemIO, 32, 0, 0x120)}, // Throttling_CTRL
        ResourceTemplate(){Register(SystemIO, 32, 0, 0x120)} // Throttling_STATUS
    }) // End of _PTC object
   Name (_TSS, Package()
        Package() {
                                    // Frequency Percentage (100%, Throttling OFF state)
           0x64
            0x0,
                                    // Power
                                    // Transition Latency
            0x0,
            0x7,
                                    // Control THT_EN:0 THTL_DTY:111
            0x0,
                                    // Status
        Package() {
            0x58,
                                   // Frequency Percentage (87.5%)
                                    // Power
            0x0,
                                   // Transition Latency
            0 \times 0.
                                   // Control THT_EN:1 THTL_DTY:111
            0xF,
            0x0,
                                    // Status
        Package() {
            0x4B,
                                    // Frequency Percentage (75%)
            0x0,
                                    // Power
                                    // Transition Latency
            0x0,
                                   // Control THT_EN:1 THTL_DTY:110
            0xE,
            0x0,
                                   // Status
    })
   Name (_TSD, Package()
        Package()\{5, 0, 0, 0xFD, 2\} // 5 entries, Revision 0, Domain 0,
                                     // OSPM Coordinate, 2 Procs
                                     // End of _TSD object
   })
   Method (_TPC, 0)
                                    // Throttling Present Capabilities method
    {
        If (\_SB.AC)
           Return(0)
                                    // All Throttle States are available for use.
        Else
                                    // Throttle States 0 an 1 won't be used.
           Return(2)
    } // End of _TPC method
} // End of processor object list
Processor (
```

```
\_SB.CPU1,
                                  // Processor Name
   2,
                                  // ACPI Processor number
                                   // PBlk system IO address
                                  // PBlkLen
{ //Object List
   Name(_PTC, Package ()
                                   // Processor Throttling Control object -
                                   \ensuremath{//} 32 bit wide IO space-based register at the
                                   // <P_BLK> address
    {
       ResourceTemplate(){Register(SystemIO, 32, 0, 0x120)}, // Throttling_CTRL
       ResourceTemplate(){Register(SystemIO, 32, 0, 0x120)} // Throttling_STATUS
   })
                                   // End of _PTC object
   Name (_TSS, Package()
       Package() {
                                   // Frequency Percentage (100%, Throttling OFF state)
           0x64,
                                  // Power
           0x0,
                                  // Transition Latency
           0x0,
           0x7,
                                  // Control THT_EN:0 THTL_DTY:111
           0x0,
                                  // Status
       Package() {
                                 // Frequency Percentage (87.5%)
           0x58,
                                  // Power
           0x0,
                                  // Transition Latency
           0x0.
           0xF,
                                  // Control THT_EN:1 THTL_DTY:111
                                  // Status
           0x0,
       Package() {
                                   // Frequency Percentage (75%)
           0x4B,
            0x0,
                                   // Power
                                   // Transition Latency
           0x0,
                                   // Control THT_EN:1 THTL_DTY:110
           0xE,
                                   // Status
           0x0,
   })
   Name (_TSD, Package()
       Package()\{5, 0, 0, 0xFD, 2\} // 5 entries, Revision 0, Domain 0,
                                     // OSPM Coordinate, 2 Procs
                                     // End of _TSD object
   })
   Method (_TPC, 0)
                                   // Throttling Present Capabilities method
    {
       If (\_SB.AC)
           Return(0)
                                   // All Throttle States are available for use.
       Else
                                   // Throttle States 0 an 1 won't be used.
           Return(2)
   } // End of _TPC method
} // End of processor object list
```

8.4.3.5 _TDL (T-state Depth Limit)

This optional object evaluates to the _TSS entry number of the lowest power throttling state that OSPM may use. _TDL enables the platform to limit the amount of performance reduction that OSPM may invoke using processor throttling controls in an attempt to alleviate an adverse thermal condition. OSPM may choose the corresponding state entry in the _TSS as indicated by the value returned by the _TDL object or a higher performance (lower numbered) state entry in the _TSS down to and including the _TSS entry number returned by the _TPC object or the first entry in the table (if _TPC is not implemented). The value returned by the _TDL object must be greater than or equal to the value returned by the _TPC object or the corresponding value to the last entry in the _TSS if _TPC is not implemented. In the event of a conflict between the values returned by the evaluation of the _TDL and _TPC objects, OSPM gives precedence to the _TPC object, limiting power consumption.

Arguments:

None

Return Value:

An **Integer** containing the Throttling Depth Limit _TSS entry number:

- 0 throttling disabled.
- 1 state 1 is the lowest power T-state available.
- 2 state 2 is the lowest power T-state available.

. . .

n – state n is the lowest power T-state available.

In order for the platform to dynamically indicate the limit of performance reduction that is available for OSPM use, Notify events on the processor object of type 0x82 will cause OSPM to reevaluate any _TDL object in the processor's object list. This allows AML code to notify OSPM when the number of supported throttling states may have changed as a result of an asynchronous event. OSPM ignores _TDL Notify events on platforms that support P-states unless the platform has limited OSPM's use of P-states to the lowest power P-state. OSPM may choose to disregard any platform conveyed T-state depth limits when the platform enables OSPM usage of other than the lowest power P-state.

8.4.4 Processor Performance Control

Processor performance control is implemented through three optional objects whose presence indicates to OSPM that the platform and CPU are capable of supporting multiple performance states. The platform must supply all three objects if processor performance control is implemented. The platform must expose processor performance control objects for either all or none of its processors. The processor performance control objects define the supported processor performance states, allow the processor to be placed in a specific performance state, and report the number of performance states currently available on the system.

In a multiprocessing environment, all CPUs must support the same number of performance states and each processor performance state must have identical performance and power-consumption parameters. Performance objects must be present under each processor object in the system for OSPM to utilize this feature.

Processor performance control objects include the '_PCT' package, '_PSS' package, and the '_PPC' method as detailed below.

8.4.4.1 _PCT (Performance Control)

This optional object declares an interface that allows OSPM to transition the processor into a performance state. OSPM performs processor performance transitions by writing the performance state–specific control value to a Performance Control Register (PERF CTRL).

OSPM may select a processor performance state as indicated by the performance state value returned by the _PPC method, or any lower power (higher numbered) state. The control value to write is contained in the corresponding PSS entry's "Control" field.

Success or failure of the processor performance transition is determined by reading a Performance Status Register (PERF_STATUS) to determine the processor's current performance state. If the transition was successful, the value read from PERF_STATUS will match the "Status" field in the PSS entry that corresponds to the desired processor performance state.

Arguments:

None

Return Value:

A Package as described below

Return Value Information

Table 8-227 PCT Package Values

Element	Object Type	Description
Control Register	Buffer	Contains a Resource Descriptor with a single Register() descriptor that describes the performance control register.
Status Register	Buffer	Contains a Resource Descriptor with a single Register() descriptor that describes the performance status register.

Example

8.4.4.2 PSS (Performance Supported States)

This optional object indicates to OSPM the number of supported processor performance states that any given system can support. This object evaluates to a packaged list of information about available

performance states including internal CPU core frequency, typical power dissipation, control register values needed to transition between performance states, and status register values that allow OSPM to verify performance transition status after any OS-initiated transition change request. The list is sorted in descending order by typical power dissipation. As a result, the zeroth entry describes the highest performance state and the 'nth' entry describes the lowest performance state.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of Pstate sub-packages as described below

Return Value Information

Each Pstate sub-**Package** contains the elements described below:

Table 8-228 PState Package Values

Element	Object Type	Description
Core Frequency	Integer (DWORD)	Indicates the core CPU operating frequency (in MHz).
Power	Integer (DWORD)	Indicates the performance state's maximum power dissipation (in milliwatts).
Latency	Integer (DWORD)	Indicates the worst-case latency in microseconds that the CPU is unavailable during a transition from any performance state to this performance state.
Bus Master Latency	Integer (DWORD)	Indicates the worst-case latency in microseconds that Bus Masters are prevented from accessing memory during a transition from any performance state to this performance state.
Control	Integer (DWORD)	Indicates the value to be written to the Performance Control Register (PERF_CTRL) in order to initiate a transition to the performance state.
Status	Integer (DWORD)	Indicates the value that OSPM will compare to a value read from the Performance Status Register (PERF_STATUS) to ensure that the transition to the performance state was successful. OSPM may always place the CPU in the lowest power state, but additional states are only available when indicated by the _PPC method.

8.4.4.3 PPC (Performance Present Capabilities)

This optional object is a method that dynamically indicates to OSPM the number of performance states currently supported by the platform. This method returns a number that indicates the _PSS entry number of the highest performance state that OSPM can use at a given time. OSPM may choose the corresponding state entry in the _PSS as indicated by the value returned by the _PPC method or any lower power (higher numbered) state entry in the _PSS.

Arguments:

None

Return Value:

An **Integer** containing the range of states supported

- 0 States 0 through nth state are available (all states available)
- 1 States 1 through nth state are available
- 2 States 2 through nth state are available

. . .

n – State n is available only

In order to support dynamic changes of _PPC object, Notify events on the processor object are allowed. Notify events of type 0x80 will cause OSPM to reevaluate any _PPC objects residing under the particular processor object notified. This allows AML code to notify OSPM when the number of supported states may have changed as a result of an asynchronous event (AC insertion/removal, docked, undocked, and so on).

8.4.4.3.1 OSPM OST Evaluation

When processing of the _PPC object evaluation completes, OSPM evaluates the _OST object, if present under the Processor device, to convey _PPC evaluation status to the platform. _OST arguments specific to _PPC evaluation are described below.

Arguments: (2)

```
Arg0 – Source Event (Integer) : 0x80
Arg1 – Status Code (Integer) : see below
```

Return Value:

None

Argument Information:

```
Arg1 – Status Code
```

- 0: Success OSPM is now using the performance states specified
- 1: Failure OSPM has not changed the number of performance states in use.

8.4.4.4 Processor Performance Control Example

Example

This is an example of processor performance control objects in a processor object list.

In this example, a uniprocessor platform that has processor performance capabilities with support for three performance states as follows:

- 1. 500 MHz (8.2W) supported at any time
- 2. 600 MHz (14.9W) supported only when AC powered
- 3. 650 MHz (21.5W) supported only when docked

It takes no more than 500 microseconds to transition from one performance state to any other performance state.

During a performance transition, bus masters are unable to access memory for a maximum of 300 microseconds.

The PERF_CTRL and PERF_STATUS registers are implemented as Functional Fixed Hardware. The following ASL objects are implemented within the system:

\ SB.DOCK: Evaluates to 1 if system is docked, zero otherwise.

\ SB.AC: Evaluates to 1 if AC is connected, zero otherwise.

```
Processor (
   \_SB.CPU0,
                                                              // Processor Name
   1,
                                                              // ACPI Processor number
    0x120,
                                                              // PBlk system IO address
    6)
                                                              // PBlkLen
   Name(_PCT, Package ()
                                                              // Performance Control object
        ResourceTemplate(){Register(FFixedHW, 0, 0, 0)}, // PERF_CTRL
        ResourceTemplate(){Register(FFixedHW, 0, 0, 0)}
                                                             // PERF_STATUS
    }) // End of _PCT object
    Name (_PSS, Package()
                                                        // Performance State zero (P0)
// Performance State one (P1)
// Performance State one (P1)
        Package(){650, 21500, 500, 300, 0x00, 0x08},
        Package() {600, 14900, 500, 300, 0x01, 0x05},
        Package(){500, 8200, 500, 300, 0x02, 0x06}
                                                            // Performance State two (P2)
    }) // End of _PSS object
    Method (_PPC, 0) // Performance Present Capabilities method
        If (\_SB.DOCK)
            Return(0)
                             // All _PSS states available (650, 600, 500).
        If (\_SB.AC)
        {
            Return(1)
                             // States 1 and 2 available (600, 500).
        Else
        {
                              // State 2 available (500)
            Return(2)
    } // End of _PPC method
} // End of processor object list
```

The platform will issue a **Notify**(\setminus SB.CPU0, 0x80) to inform OSPM to re-evaluate this object when the number of available processor performance states changes.

8.4.4.5 PSD (P-State Dependency)

This optional object provides P-state control cross logical processor dependency information to OSPM. The _PSD object evaluates to a packaged list of information that correlates with the P-state information returned by the _PSS object. Each packaged list entry identifies a dependency domain number for the logical processor's P-states, the coordination type for that P-state, and the number of logical processors belonging to the domain.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of P-state dependency **Packages** as described below.

Return Value Information

Each PStateDependency sub-Package contains the elements described below:

Table 8-229 PStateDependency Package Values

Element	Object Type	Description
NumEntries	Integer	The number of entries in the PstateDependency package including this field. Current value is 5.
Revision	Integer (BYTE)	The revision number of the PstateDependency package format. Current value is 0.
Domain	Integer (DWORD)	The dependency domain number to which this P state entry belongs.
CoordType	Integer (DWORD)	The type of coordination that exists (hardware) or is required (software) as a result of the underlying hardware dependency. Could be either 0xFC (SW_ALL), 0xFD (SW_ANY) or 0xFE (HW_ALL) indicating whether OSPM is responsible for coordinating the P-state transitions among processors with dependencies (and needs to initiate the transition on all or any processor in the domain) or whether the hardware will perform this coordination.
Num Processors	Integer (DWORD)	The number of processors belonging to the domain for this logical processor's P-states. OSPM will not start performing power state transitions to a particular P-state until this number of processors belonging to the same domain have been detected and started.

Example

This is an example usage of the _PSD structure in a Processor structure in the namespace. The example represents a two processor configuration with three performance states per processor. For all performance states, there exists dependence between the two processors, such that one processor transitioning to a particular performance state, causes the other processor to transition to the same performance state. OSPM will be required to coordinate the P-state transitions between the two processors and can initiate a transition on either processor to cause both to transition to the common target P-state.

```
Processor (
    \_SB.CPU0,
                            // Processor Name
    1,
                            // ACPI Processor number
    0x120,
                            // PBlk system IO address
                            // PBlkLen
    6)
   Name(_PCT, Package () // Performance Control object
       ResourceTemplate(){Register(FFixedHW, 0, 0, 0)},
                                                             // PERF_CTRL
                                                             // PERF_STATUS
       ResourceTemplate(){Register(FFixedHW, 0, 0, 0)}
    }) // End of _PCT object
    Name (_PSS, Package()
       Package(){650, 21500, 500, 300, 0x00, 0x08},
                                                      // Performance State zero (P0)
       Package(){600, 14900, 500, 300, 0x01, 0x05},
                                                      // Performance State one (P1)
       Package(){500, 8200, 500, 300, 0x02, 0x06}
                                                     // Performance State two (P2)
    }) // End of _PSS object
   Method (_PPC, 0)
                     // Performance Present Capabilities method
    } // End of _PPC method
    Name (_PSD, Package()
       Package(){5, 0, 0, 0xFD, 2} // 5 entries, Revision 0), Domain 0, OSPM
                                      // Coordinate, Initiate on any Proc, 2 Procs
    }) // End of _PSD object
} // End of processor object list
Processor (
    \_SB.CPU1,
                             // Processor Name
    2,
                             // ACPI Processor number
                             // PBlk system IO address
                             // PBlkLen
{
    Name(_PCT, Package ()
                            // Performance Control object
       ResourceTemplate(){Register(FFixedHW, 0, 0, 0)}, // PERF_CTRL
       ResourceTemplate(){Register(FFixedHW, 0, 0, 0)} // PERF_STATUS
    }) // End of _PCT object
```

8.4.4.6 _PDL (P-state Depth Limit)

This optional object evaluates to the _PSS entry number of the lowest performance P-state that OSPM may use when performing passive thermal control. OSPM may choose the corresponding state entry in the _PSS as indicated by the value returned by the _PDL object or a higher performance (lower numbered) state entry in the _PSS down to and including the _PSS entry number returned by the _PPC object or the first entry in the table (if _PPC is not implemented). The value returned by the _PDL object must be greater than or equal to the value returned by the _PPC object or the corresponding value to the last entry in the _PSS if _PPC is not implemented. In the event of a conflict between the values returned by the evaluation of the _PDL and _PPC objects, OSPM gives precedence to the _PPC object, limiting power consumption.

Arguments:

None

Return Value:

An **Integer** containing the P-state Depth Limit PSS entry number:

- 0 P0 is the only P-state available for OSPM use
- 1 state 1 is the lowest power P-state available
- 2 state 2 is the lowest power P-state available

. . .

n – state n is the lowest power P-state available

In order for the platform to dynamically indicate a change in the P-state depth limit, Notify events on the processor object of type 0x80 will cause OSPM to reevaluate any _PDL object in the processor's object list. This allows AML code to notify OSPM when the number of supported performance states may have changed as a result of an asynchronous event.\

8.4.5 Collaborative Processor Performance Control

Collaborative processor performance control defines an abstracted and flexible mechanism for OSPM to collaborate with an entity in the platform to manage the performance of a logical processor. In this scheme, the platform entity is responsible for creating and maintaining a performance definition that backs a continuous, abstract, unit-less performance scale. During

runtime, OSPM requests desired performance on this abstract scale and the platform entity is responsible for translating the OSPM performance requests into actual hardware performance states. The platform may also support the ability to autonomously select a performance level appropriate to the current workload. In this case, OSPM conveys information to the platform that guides the platform's performance level selection.

Prior processor performance controls (P-states and T-states) have described their effect on processor performance in terms of processor frequency. While processor frequency is a rough approximation of the speed at which the processor completes work, workload performance isn't guaranteed to scale with frequency. Therefore, rather than prescribe a specific metric for processor performance, Collaborative Processor Performance Control leaves the definition of the exact performance metric to the platform. The platform may choose to use a single metric such as processor frequency, or it may choose to blend multiple hardware metrics to create a synthetic measure of performance. In this way the platform is free to deliver the OSPM requested performance level without necessarily delivering a specific processor frequency. OSPM must make no assumption about the exact meaning of the performance values presented by the platform, or how they may correlate to specific hardware metrics like processor frequency.

The control mechanisms are abstracted by the _CPC object method, which describes how to control and monitor processor performance in a generic manner. The register methods may be implemented in the Platform Communications Channel (PCC) interface (see Section 14). This provides sufficient flexibility that the entity OSPM communicates with may be the processor itself, the platform chipset, or a separate entity (e.g., a BMC).

8.4.5.1 _CPC (Continuous Performance Control)

This optional object declares an interface that allows OSPM to transition the processor into a performance state based on a continuous range of allowable values. OSPM writes the desired performance value to the Desired Performance Register, and the platform maps the desired performance to an internal performance state. If supported by the platform, OSPM may alternatively enable autonomous performance level selection while specifying minimum and maximum performance requirements.

Optional CPC package fields that are not supported by the platform should be encoded as follows:

- Integer fields: Integer 0
- Register fields: the following NULL register descriptor should be used:

```
ResourceTemplate() {Register {(SystemMemory, 0, 0, 0, 0)}}
```

Arguments:

None

Return Value:

A Package containing the performance control information

The performance control package contains the elements described below:

```
Package
        NumEntries,
                                                            // Integer
        Revision,
                                                            // Integer
        HighestPerformance,
                                                            // Integer or Buffer (Resource Descriptor)
                                                          // Integer or Buffer (Resource Descriptor)
        NominalPerformance,
                                                           // Integer or Buffer (Resource Descriptor)
        LowestNonlinearPerformance,
        LowestPerformance,
                                                           // Integer or Buffer (Resource Descriptor)
        GuaranteedPerformanceRegister,
                                                           // Buffer (Resource Descriptor)
        DesiredPerformanceRegister,
                                                           // Buffer (Resource Descriptor)
        MinimumPerformanceRegister,
                                                          // Buffer (Resource Descriptor)
        MaximumPerformanceRegister,
                                                          // Buffer (Resource Descriptor)
        PerformanceReductionToleranceRegister, // Buffer (Resource Descriptor)
        TimeWindowRegister,
                                                           // Buffer (Resource Descriptor)
                                                           // Integer or Buffer (Resource Descriptor)
        CounterWraparoundTime,
        ReferencePerformanceCounterRegister,
DeliveredPerformanceCounterRegister,
                                                            // Buffer (Resource Descriptor)
                                                            // Buffer (Resource Descriptor)
                                                            // Buffer (Resource Descriptor)
        PerformanceLimitedRegister,
        CPPCEnableRegister
                                                           // Buffer (Resource Descriptor)
        AutonomousSelectionEnable,
                                                          // Integer or Buffer (Resource Descriptor)
        AutonomousSelectionEnable, // Integer or Buffer (Resource
AutonomousActivityWindowRegister, // Buffer (Resource Descriptor)
EnergyPerformancePreferenceRegister, // Buffer (Resource Descriptor)
                                                          // Buffer (Resource Descriptor)
        ReferencePerformance
                                                          // Integer or Buffer (Resource Descriptor)
```

Table 8-230 Continuous Performance Control Package Values

Element	Object Type	Description
NumEntries	Integer	The number of entries in the _CPC package, including this one. Current value is 21.
Revision	Integer (BYTE)	The revision number of the _CPC package format. Current value is 2.
Highest Performance	Integer (DWORD) or Buffer	Indicates the highest level of performance the processor is theoretically capable of achieving, given ideal operating conditions. If this element is an Integer, OSPM reads the integer value directly. If this element is a Buffer, it must contain a Resource Descriptor with a single Register() to read the value from.
Nominal Performance	Integer (DWORD) or Buffer	Indicates the highest sustained performance level of the processor. If this element is an Integer, OSPM reads the integer value directly. If this element is a Buffer, it must contain a Resource Descriptor with a single Register() to read the value from.
Lowest Nonlinear Performance	Integer (DWORD) or Buffer	Indicates the lowest performance level of the processor with non-linear power savings. If this element is an Integer, OSPM reads the integer value directly. If this element is a Buffer, it must contain a Resource Descriptor with a single Register() to read the value from.
Lowest Performance	Integer (DWORD) or Buffer	Indicates the lowest performance level of the processor. If this element is an Integer, OSPM reads the integer value directly. If this element is a Buffer, it must contain a Resource Descriptor with a single Register() to read the value from.

Element	Object Type	Description	
Guaranteed Buffer Performance Register		Optional. If supported, contains a resource descriptor with a single Register() descriptor that describes the register to read the current guaranteed performance from. See the section "Performance Limiting" for more details.	
Desired Performance Register	Buffer	Contains a resource descriptor with a single Register() descriptor that describes the register to write the desired performance level. This register is optional when OSPM indicates support for CPPC2 in the platform-wide _OSC capabilities and the Autonomous Selection Enable register is Integer 1	
Minimum Buffer Performance Register		Optional. If supported, contains a resource descriptor with a single Register() descriptor that describes the register to write the minimum allowable performance level to. The value 0 is equivalent to Lowest Performance (no limit).	
Maximum Performance Register	Buffer	Optional. If supported, contains a resource descriptor with a single Register() descriptor that describes the register to write the maximum allowable performance level to. All 1s is equivalent to Highest Performance (no limit).	
Performance Reduction Tolerance Register	Buffer	Optional. If supported, contains a resource descriptor with a single Register() descriptor that describes the register to write the performance reduction tolerance.	
Time Window Register	Buffer	Optional. If supported, contains a resource descriptor with a single Register() descriptor that describes the register to write the nominal length of time (in ms) between successive reads of the platform's delivered performance register. See the section "Time Window Register" for more details.	
Counter Wraparound Time	Integer (DWORD) or Buffer	Optional. If supported, indicates the minimum time to counter wraparound, in seconds. If this element is an Integer, OSPM reads the integer value directly. If this element is a Buffer (and supported), it must contain a Resource Descriptor with a single Register() to read the value from.	
Reference Performance Counter Register	Buffer	Contains a resource descriptor with a single Register() descriptor that describes the register to read a counter that accumulates at a rate proportional the reference performance of the processor.	
Delivered Performance Counter Register	Buffer	Contains a resource descriptor with a single Register() descriptor that describes the register to read a counter that accumulates at a rate proportional to the delivered performance of the processor.	
Performance Limited Register	Buffer	Contains a resource descriptor with a single Register() descriptor that describes the register to read to determine if performance was limited. A nonzero value indicates performance was limited. This register is sticky, and will remain set until reset or OSPM clears it by writing 0. See the section "Performance Limiting" for more details.	
CPPC EnableRegister Buffer		Optional. If supported, contains a resource descriptor with a single Register() descriptor that describes a register to which OSPM writes a One to enable CPPC on this processor. Before this register is set, the processor will be controlled by legacy mechanisms (ACPI P-states, firmware, etc.).	

Processor Configuration and Control

Element	Object Type	Description
Autonomous Selection Enable	Integer (DWORD) or Buffer	Optional. If supported, contains a resource descriptor with a single Register() descriptor that describes a register to which OSPM writes a One to enable autonomous performance level selection. Platforms that exclusively support Autonomous Selection must populate this field as an Integer with a value of 1.
AutonomousActivityWindowRegister	Buffer	Optional. If supported, contains a resource descriptor with a single Register() descriptor that describes a register to which OSPM writes a time value that indicates a moving utilization sensitivity window for the autonomous selection policy.
EnergyPerformancePr eferenceRegister	Buffer	Optional. If supported, contains a resource descriptor with a single Register() descriptor that describes a register to which OSPM writes a value to control the Energy vs. Performance preference of the platform's energy efficiency and performance optimization policies when Autonomous Selection is enabled
Reference Performance	Integer (DWORD) or Buffer	Optional. If supported, indicates the performance level at which the Reference Performance Counter accumulates. If not supported, The Reference Performance Counter accumulates at the Nominal performance level. If this element is an Integer, OSPM reads the integer value directly. If this element is a Buffer (and supported), it must contain a Resource Descriptor with a single Register() to read the value from

The _CPC object provides OSPM with platform-specific performance capabilities / thresholds and control registers that OSPM uses to control the platform's processor performance settings. These are described in the following sections. While the platform may specify register sizes within an allowable range, the size of the capabilities / thresholds registers must be compatible with the size of the control registers. If the platform supports CPPC, the _CPC object must exist under all processor objects. That is, OSPM is not expected to support mixed mode (CPPC & legacy PSS, _PCT, _PPC) operation.

8.4.5.1.1 Performance Capabilities / Thresholds

Performance-based controls operate on a continuous range of processor performance levels, not discrete processor states. As a result, platform capabilities and OSPM requests are specified in terms of performance thresholds. Figure 8-44 outlines the static performance thresholds of the platform and the dynamic guaranteed performance threshold.




Figure 8-44 Platform performance thresholds

Note: Not all performance levels need be unique. A platform's nominal performance level may also be its highest performance level, for example.

8.4.5.1.1.1 Highest performance

Register or DWORD
Register Location: PCC or Functional Fixed Hardware
Attribute: Read
Size: 8-32 bits

Highest performance is the absolute maximum performance an individual processor may reach, assuming ideal conditions. This performance level may not be sustainable for long durations, and may only be achievable if other platform components are in a specific state; for example, it may require other processors be in an idle state.

8.4.5.1.1.2 Nominal Performance

Register or DWORD
Register Location: PCC or Functional Fixed Hardware
Attribute: Read
Size: 8-32 bits

Nominal Performance is the maximum sustained performance level of the processor, assuming ideal operating conditions. In absence of an external constraint (power, thermal, etc.) this is the performance level the platform is expected to be able to maintain continuously. All processors are expected to be able to sustain their nominal performance state simultaneously.

Processor Configuration and Control

8.4.5.1.1.3 Reference Performance

Optional

Register or DWORD

Register Location: PCC or Functional Fixed Hardware

Attribute: Read Size: 8-32 bits

If supported by the platform, **Reference Performance** is the rate at which the Reference Performance Counter increments. If not implemented (or zero), the Reference Performance Counter increments at a rate corresponding to the Nominal Performance level.

8.4.5.1.1.4 Lowest Nonlinear Performance

Register or DWORD

Register Location: PCC or Functional Fixed Hardware

Attribute: Read Size: 8-32 bits

Lowest Nonlinear Performance is the lowest performance level at which nonlinear power savings are achieved, for example, due to the combined effects of voltage and frequency scaling. Above this threshold, lower performance levels should be generally more energy efficient than higher performance levels. In traditional terms, this represents the P-state range of performance levels.

This register effectively conveys the most efficient performance level to OSPM.

8.4.5.1.1.5 Lowest Performance

Register or DWORD

Register Location: PCC or Functional Fixed Hardware

Attribute: Read Size: 8-32 bits

Lowest Performance is the absolute lowest performance level of the platform. Selecting a performance level lower than the lowest nonlinear performance level may actually cause an efficiency penalty, but should reduce the instantaneous power consumption of the processor. In traditional terms, this represents the T-state range of performance levels.

8.4.5.1.1.6 Guaranteed Performance Register

Optional

Register Location: PCC or Functional Fixed Hardware

Attribute: Read Size: 8-32 bits

Guaranteed Performance Register conveys to OSPM a Guaranteed Performance level, which is the current maximum sustained performance level of a processor, taking into account all known external constraints (power budgeting, thermal constraints, AC vs DC power source, etc.). All processors are expected to be able to sustain their guaranteed performance levels simultaneously. The guaranteed performance level is required to fall in the range [Lowest Performance, Nominal performance], inclusive.

If this register is not implemented, and Autonomous Selection is not enabled, OSPM assumes guaranteed performance is always equal to nominal performance.

Notify events of type 0x83 to the processor device object will cause OSPM to re-evaluate the Guaranteed Performance Register. Changes to guaranteed performance should not be more frequent than once per second. If the platform is not able to guarantee a given performance level for a

sustained period of time (greater than one second), it should guarantee a lower performance level and opportunistically enter the higher performance level as requested by OSPM and allowed by current operating conditions.

8.4.5.1.2 Performance Controls

Under CPPC, OSPM has several performance settings it may use in conjunction to control/influence the performance of the platform. These control inputs are outlined in <u>Figure 8-45</u>.




Figure 8-45 OSPM performance controls

OSPM may select any performance value within the continuous range of values supported by the platform. Internally, the platform may implement a small number of discrete performance states and may not be capable of operating at the exact performance level desired by OSPM. If a platform-internal state does not exist that matches OSPM's desired performance level, the platform should round desired performance as follows:

- If OSPM has selected a desired performance level greater than or equal to guaranteed performance, the platform may round up or down. The result of rounding must not be less than guaranteed performance.
- If OSPM has selected a desired performance level less than guaranteed performance and a maximum performance level not less than guaranteed performance, the platform must round up.

If OSPM has selected both desired performance level and maximum performance level less than guaranteed performance, the platform must round up if rounding up does not violate the maximum performance level. Otherwise, round down. OSPM must tolerate the platform rounding down if it chooses to set the maximum performance level less than guaranteed performance. This approach favors performance, except in the case where performance has been limited due to a platform or OSPM constraint.

Processor Configuration and Control

When Autonomous Selection is enabled, OSPM limits the processor's performance selection by writing appropriate constraining values to the Minimum and Maximum Performance registers. Setting Minimum and Maximum to the same value effectively disables Autonomous selection.

Note: When processors are within the same dependency domain, Maximum performance may only be actually limited when allowed by hardware coordination.

8.4.5.1.2.1 Maximum Performance Register

Optional

Register Location: PCC or Functional Fixed Hardware

Attribute: Read/Write Size: 8-32 bits

Maximum Performance Register conveys the maximum performance level at which the platform may run. Maximum performance may be set to any performance value in the range [Lowest Performance, Highest Performance], inclusive.

The value written to the Maximum Performance Register conveys a request to limit maximum performance for the purpose of energy efficiency or thermal control and the platform limits its performance accordingly as possible. However, the platform may exceed the requested limit in the event it is necessitated by internal package optimization. For Example, hardware coordination among multiple logical processors with interdependencies.

OSPM's use of this register to limit performance for the purpose of thermal control must comprehend multiple logical processors with interdependencies. i.e. the same value must be written to all processors within a domain to achieve the desired result.

The platform must implement either **both** the Minimum Performance and Maximum Performance registers or neither register. If neither register is implemented and Autonomous Selection is disabled, the platform must always deliver the desired performance.

8.4.5.1.2.2 Minimum Performance Register

Optional

Register Location: PCC or Functional Fixed Hardware

Attribute: Read/Write Size: 8-32 bits

The **Minimum Performance Register** allows OSPM to convey the minimum performance level at which the platform may run. Minimum performance may be set to any performance value in the range [Lowest Performance, Highest Performance], inclusive but must be set to a value that is less than or equal to that specified by the **Maximum Performance Register**.

In the presence of a physical constraint, for example a thermal excursion, the platform may not be able to successfully maintain minimum performance in accordance with that set via the **Minimum Performance Register.** In this case, the platform issues a Notify event of type 0x84 to the processor device object and sets the Minimum Excursion bit within the **Performance Limited Register.**

The platform must implement either **both** the Minimum Performance and Maximum Performance registers or neither register. If neither register is implemented and Autonomous Selection is disabled, the platform must always deliver the desired performance.

8.4.5.1.2.3 Desired Performance Register

Optional (depending on Autonomous Selection support)
Register Location: PCC or Functional Fixed Hardware
Attribute: Read/Write
Size: 8-32 bits

When Autonomous Selection is disabled, the **Desired Performance Register** is required and conveys the performance level OSPM is requesting from the platform. Desired performance may be set to any performance value in the range [Minimum Performance, Maximum Performance], inclusive. Desired performance may take one of two meanings, depending on whether the desired performance is above or below the guaranteed performance level.

- Below the guaranteed performance level, desired performance expresses the average performance level the platform must provide subject to the Performance Reduction Tolerance.
- Above the guaranteed performance level, the platform must provide the guaranteed performance level. The platform should attempt to provide up to the desired performance level, if current operating conditions allow for it, but it is not required to do so

When Autonomous Selection is enabled, it is not necessary for OSPM to assess processor workload performance demand and convey a corresponding performance delivery request to the platform via the Desired Register. If the Desired Performance Register exists, OSPM may provide an explicit performance requirement hint to the platform by writing a non-zero value. In this case, the delivered performance is not bounded by the Performance Reduction Tolerance Register, however, OSPM can influence the delivered performance by writing appropriate values to the Energy Performance Preference Register. Writing a zero value to the Desired Performance Register or the non-existence of the Desired Performance Register causes the platform to autonomously select a performance level appropriate to the current workload.

Note: The Desired Performance Register is optional only when OPSM indicates support for CPPC2 in the platform-wide _OSC capabilities and the Autonomous Selection Enable field is encoded as an Integer with a value of 1.

8.4.5.1.2.4 Performance Reduction Tolerance Register

Optional

Register Location: PCC or Functional Fixed Hardware

Attribute: Read/Write Size: 8-32 bits

The **Performance Reduction Tolerance Register** is used by OSPM to convey the deviation below the Desired Performance that is tolerable. It is expressed by OSPM as an absolute value on the performance scale. Performance Tolerance must be less than or equal to the Desired Performance. If the platform supports the Time Window Register, the Performance Reduction Tolerance conveys the minimal performance value that may be delivered on average over the Time Window. If this register is not implemented, the platform must assume Performance Reduction Tolerance = Desired Performance.

When Autonomous Selection is enabled, values written to the Performance Reduction Tolerance Register are ignored.

8.4.5.1.2.5 Time Window Register

Optional

Register Location: PCC or Functional Fixed Hardware

Attribute: Read/Write
Size: 8-32 bits
Units: milliseconds

When Autonomous Selection is not enabled, OSPM may write a value to the **Time Window Register** to indicate a time window over which the platform must provide the desired performance level (subject to the Performance Reduction Tolerance). OSPM sets the time window when electing a new desired performance The time window represents the minimum time duration for OSPM's evaluation of the platform's delivered performance (see Section 8.4.5.1.3.1 "Performance Counters" for details on how OSPM computes delivered performance). If OSPM evaluates delivered performance over an interval smaller than the specified time window, it has no expectations of the performance delivered by the platform. For any evaluation interval equal to or greater than the time window, the platform must deliver the OSPM desired performance within the specified tolerance bound.

If OSPM specifies a time window of zero or if the platform does not support the time window register, the platform must deliver performance within the bounds of Performance Reduction Tolerance irrespective of the duration of the evaluation interval.

When Autonomous Selection is enabled, values written to the Time Window Register are ignored. Reads of the Time Window register indicate minimum length of time (in ms) between successive reads of the platform's performance counters. If the Time Window register is not supported then there is no minimum time requirement between successive reads of the platform's performance counters.

8.4.5.1.3 Performance Feedback

The platform provides performance feedback via set of performance counters, and a performance limited indicator.

8.4.5.1.3.1 Performance Counters

To determine the actual performance level delivered over time, OSPM may read a set of performance counters from the Reference Performance Counter Register and the Delivered Performance Counter Register.

OSPM calculates the delivered performance over a given time period by taking a beginning and ending snapshot of both the reference and delivered performance counters, and calculating:

 $\label{eq:delivered} \textit{delivered performance} = \textit{reference performance} \qquad \qquad \textbf{X} \\ \hline \Delta \textit{reference performance counter} \\ \Delta \textit{reference performance counter} \\ \\ \Delta \textit{reference performance counter} \\ \hline$

The delivered performance should always fall in the range [Lowest Performance, Highest Performance], inclusive. OSPM may use the delivered performance counters as a feedback mechanism to refine the desired performance state it selects.

When Autonomous Selection is not enabled, there are constraints that govern how and when the performance delivered by the platform may deviate from the OSPM Desired Performance.

Corresponding to OSPM setting a Desired Performance: at any time after that, the following constraints on delivered performance apply

- Delivered performance can be higher than the OSPM requested desired performance if the
 platform is able to deliver the higher performance at same or lower energy than if it were
 delivering the desired performance.
- Delivered performance may be higher or lower than the OSPM desired performance if the
 platform has discrete performance states and needed to round down performance to the nearest
 supported performance level in accordance to the algorithm prescribed in the OSPM controls
 section.
- Delivered performance may be lower than the OSPM desired performance if the platform's efficiency optimizations caused the delivered performance to be less than desired performance. However, the delivered performance should never be lower than the OSPM specified.
- Performance Reduction Tolerance. The Performance Reduction Tolerance provides a bound to the platform on how aggressive it can be when optimizing performance delivery. The platform should not perform any optimization that would cause delivered performance to be lower than the OSPM specified Performance Reduction Tolerance.

8.4.5.1.3.1.1 Reference Performance Counter Register

```
Register Location: PCC, System Memory, or Functional Fixed Hardware Space Attribute: Read
Size: 32 or 64 bits
```

The Reference Performance Counter Register counts at a fixed rate any time the processor is active. It is not affected by changes to Desired Performance, processor throttling, etc. If Reference Performance is supported, the Reference Performance Counter accumulates at a rate corresponding to the Reference Performance level. Otherwise, the Reference Performance Counter accumulates at the Nominal performance level.

8.4.5.1.3.1.2 Delivered Performance Counter Register

```
Register Location: PCC, System Memory, or Functional Fixed Hardware Space
Attribute: Read
Size: 32 or 64 bits
```

The Delivered Performance Counter Register increments any time the processor is active, at a rate proportional to the current performance level, taking into account changes to Desired Performance. When the processor is operating at its reference performance level, the delivered performance counter must increment at the same rate as the reference performance counter.

8.4.5.1.3.1.3 Counter Wraparound Time

```
Optional
Register or DWORD
Register Location: PCC or Functional Fixed Hardware
Attribute: Read
Size: 32 or 64 bits
Units: seconds
```

Counter Wraparound Time provides a means for the platform to specify a rollover time for the Reference/Delivered performance counters. If greater than this time period elapses between OSPM

Processor Configuration and Control

querying the feedback counters, the counters may wrap without OSPM being able to detect that they have done so.

If not implemented (or zero), the performance counters are assumed to never wrap during the lifetime of the platform.

8.4.5.1.3.2 Performance Limited Register

Register Location: PCC or Functional Fixed Hardware

Attribute: Read/Write Size: >=2 bit(s)

In the event that the platform must constrain the delivered performance to less than the minimum performance or the desired performance (or, less than the guaranteed performance, if desired performance is greater than guaranteed performance) due to an unpredictable event, the platform must set the performance limited indicator to a non-zero value. This indicates to OSPM that an unpredictable event has limited processor performance, and the delivered performance may be less than desired / minimum performance.

Table 8-231 Performance Limited Register Status Bits

Bit	Name	Description
0	Desired_Excursion	Set when Delivered Performance has been constrained to less than Desired Performance (or, less than the guaranteed performance, if desired performance is greater than guaranteed performance). This bit is not utilized when Autonomous Selection is enabled.
1	Minimum_Excursion	Set when Delivered Performance has been constrained to less than Minimum Performance
2-n	Reserved	Reserved

Bits within the **Performance Limited Register** are sticky, and will remain non-zero until OSPM clears the bit. The platform should only issue a Notify when Minimum Excursion transitions from 0 to 1 to avoid repeated events when there is sustained or recurring limiting but OSPM has not cleared the previous indication.

Note: All accesses to the Performance Limited Register must be made using interlocked operations, by both accessing entities.

The performance limited register should only be used to report short term, unpredictable events (e.g., PROCHOT being asserted). If the platform is capable of identifying longer term, predictable events that limit processor performance, it should use the guaranteed performance register to notify OSPM of this limitation. Changes to guaranteed performance should not be more frequent than once per second. If the platform is not able to guarantee a given performance level for a sustained period of time (greater than one second), it should guarantee a lower performance level and opportunistically enter the higher performance level as requested by OSPM and allowed by current operating conditions.

8.4.5.1.4 CPPC Enable Register

```
Optional
Register Location: System I/O, PCC, or Functional Fixed Hardware
Attribute: Read/Write
Size: >=1 bit(s)
```

If supported by the platform, OSPM writes a one to this register to enable CPPC on this processor. If not implemented, OSPM assumes the platform always has CPPC enabled.

8.4.5.1.5 Autonomous Selection Enable Register

```
Optional
Register or DWORD
Register Location:System I/O, PCC, or Functional Fixed Hardware
Attribute: Read/Write
Size: >=1 bit(s)
```

If supported by the platform, OSPM writes a one to this register to enable Autonomous Performance Level Selection on this processor. CPPC must be enabled via the CPPC Enable Register to enable Autonomous Performance Level Selection. Platforms that exclusively support Autonomous Selection must populate this field as an Integer with a value of 1.

When Autonomous Selection is enabled, the platform is responsible for selecting performance states. OSPM is not required to assess processor workload performance demand and convey a corresponding performance delivery request to the platform via the Desired Performance Register.

8.4.5.1.6 Autonomous Activity Window Register

```
Optional
Register Location: System I/O, PCC, or Functional Fixed Hardware
Attribute: Read/Write
Size: 10 bit(s)
Units: Bits 06:00 - Significand, Bits 09:07 - Exponent, Base_Time_Unit = 1E-6 seconds
(1 microsecond)
```

If supported by the platform, OSPM may write a time value (10^{^3}-bit exp * 7-bit mantissa in 1μsec units: 1us to 1270 sec) to this field to indicate a moving utilization sensitivity window to the platform's autonomous selection policy. Combined with the Energy Performance Preference Register value, the Activity Window influences the rate of performance increase / decrease of the platform's autonomous selection policy. OSPM writes a zero value to this register to enable the platform to determine an appropriate Activity Window depending on the workload.

Writes to this register only have meaning when Autonomous Selection is enabled.

8.4.5.1.7 Energy Performance Preference Register

```
Optional
Register Location: System I/O, PCC, or Functional Fixed Hardware
Attribute: Read/Write
Size: 4-8 bit(s
```

If supported by the platform, OSPM may write a range of values from 0 (performance preference) to 0xFF (energy efficiency preference) that influences the rate of performance increase /decrease and the result of the hardware's energy efficiency and performance optimization policies. This provides a means for OSPM to limit the energy efficiency impact of the platform's performance-related

Processor Configuration and Control

optimizations / control policy and the performance impact of the platform's energy efficiency-related optimizations / control policy.

Writes to this register only have meaning when Autonomous Selection is enabled.

8.4.5.1.8 OSPM Control Policy

8.4.5.1.8.1 In-Band Thermal Control

A processor using performance controls may be listed in a thermal zone's _PSL list. If it is and the thermal zone engages passive cooling as a result of passing the _PSV threshold, OSPM will apply the $\Delta P[\%]$ to modify the value in the desired performance register. Any time that passive cooling is engaged, OSPM must also set the maximum performance register equal to the desired performance register, to enforce the platform does not exceed the desired performance opportunistically.

Note: In System-on-Chip-based platforms where the SoC is comprised of multiple device components in addition to the processor, OSPM's use of the Desired and Maximum registers for thermal control may not produce an optimal result because of SoC device interaction. The use of proprietary package level thermal controls (if they exist) may produce more optimal results.

8.4.5.1.9 Using PCC Registers

If the PCC register space is used, all PCC registers must be defined to be in the same subspace. OSPM will write registers by filling in the register value and issuing a PCC write command (see <u>Table 8-232</u>). It may read static registers, counters, and the performance limited register by issuing a read command (see <u>Table 8-232</u>). To amortize the cost of PCC transactions, OSPM should read or write all PCC registers via a single read or write command when possible.

Table 8-232 PCC Commands Codes used by Collaborative Processor Performance Control

Command	Description
0x00	Read registers. Executed to request the platform update all registers for all enabled processors with their current value.
0x01	Write registers. Executed to notify the platform one or more read/write registers for an enabled processor has been updated.
0x02-0xFF	All other values are reserved.

8.4.5.1.10 Relationship to other ACPI-defined Objects and Notifications

If CPC is present, its use supersedes the use of the following existing ACPI objects:

- The P BLK P CNT register
- PTC
- TSS
- TPC
- TSD
- TDL
- PCT
- PSS

- PPC
- _PDL
- Notify 0x80 on the processor device
- Notify 0x82 on the processor device

The PSD object may be used to specify domain dependencies between processors.

8.4.5.1.11 _CPC Implementation Example

This example shows a two processor implementation of the _CPC interface via the PCC interface, in PCC subspace 2. This implementation uses registers to describe the processor's capabilities, and does not support the Minimum Performance, Maximum Performance, or Time Window registers.

```
Processor (
   \_SB.CPU0,
   1,
   0,
   0)
   Name(_CPC, Package()
        17,
                     // NumEntries
        1.
                     // Revision
        ResourceTemplate(){Register(PCC, 32, 0, 0x120, 2)},
                    // Highest Performance
        ResourceTemplate(){Register(PCC, 32, 0, 0x124, 2)},
                    // Nominal Performance
        ResourceTemplate(){Register(PCC, 32, 0, 0x128, 2)},
                    // Lowest Nonlinear Performance
        ResourceTemplate() {Register(PCC, 32, 0, 0x12C, 2)},
                    // Lowest Performance
        ResourceTemplate() {Register(PCC, 32, 0, 0x130, 2)},
                   // Guaranteed Performance Register
        ResourceTemplate(){Register(PCC, 32, 0, 0x110, 2)},
                   // Desired Performance Register
        ResourceTemplate(){Register(SystemMemory, 0, 0, 0, 0)},
                    // Minimum Performance Register
        ResourceTemplate(){Register(SystemMemory, 0, 0, 0, 0)},
                    // Maximum Performance Register
        ResourceTemplate() {Register(SystemMemory, 0, 0, 0, 0)},
                    // Performance Reduction Tolerance Register
        ResourceTemplate(){Register(SystemMemory, 0, 0, 0, 0)},
                    // Time Window Register
        ResourceTemplate(){Register(PCC, 8, 0, 0x11B, 2)},
                   // Counter Wraparound Time
        ResourceTemplate(){Register(PCC, 32, 0, 0x114, 2)},
                   // Nominal Counter Register
        ResourceTemplate() {Register(PCC, 32, 0, 0x116, 2)},
                    // Delivered Counter Register
        ResourceTemplate() {Register(PCC, 8, 0, 0x11A, 2)}
                   // Performance Limited Register
        ResourceTemplate(){Register(PCC, 1, 0, 0x100, 2)}
                   // Enable Register
   })
}
Processor (
    \_SB.CPU1,
    2,
   0,
    0)
   Name(_CPC, Package()
                    // NumEntries
        17,
        1,
                    // Revision
        ResourceTemplate(){Register(PCC, 32, 0, 0x220, 2)},
                    // Highest Performance
        ResourceTemplate(){Register(PCC, 32, 0, 0x224, 2)},
                   // Nominal Performance
         ResourceTemplate(){Register(PCC, 32, 0, 0x228, 2)},
                    // Lowest Nonlinear Performance
        ResourceTemplate() {Register(PCC, 32, 0, 0x22C, 2)},
```

```
// Lowest Performance
    ResourceTemplate() {Register(PCC, 32, 0, 0x230, 2)},
                // Guaranteed Performance Register
   ResourceTemplate(){Register(PCC, 32, 0, 0x210, 2)},
               // Desired Performance Register
    ResourceTemplate(){Register(SystemMemory, 0, 0, 0, 0)},
                // Minimum Performance Register
    ResourceTemplate() {Register(SystemMemory, 0, 0, 0, 0)},
                // Maximum Performance Register
    ResourceTemplate(){Register(SystemMemory, 0, 0, 0, 0)},
                // Performance Reduction Tolerance Register
    ResourceTemplate(){Register(SystemMemory, 0, 0, 0, 0)},
                // Time Window Register
    ResourceTemplate(){Register(PCC, 8, 0, 0x21B, 2)},
                // Counter Wraparound Time
    ResourceTemplate() {Register(PCC, 32, 0, 0x214, 2)},
                // Nominal Counter Register
    ResourceTemplate() {Register(PCC, 32, 0, 0x216, 2)},
                // Delivered Counter Register
    ResourceTemplate(){Register(PCC, 8, 0, 0x21A, 2)}
               // Performance Limited Register
    ResourceTemplate(){Register(PCC, 1, 0, 0x200, 2)}
               // Enable Register
})
```

8.4.6 PPE (Polling for Platform Errors)

This optional object, when present, is evaluated by OSPM to determine if the processor should be polled to retrieve corrected platform error information. This object augments /overrides information provided in the CPEP, if supplied. See Section 5.2.18 "Corrected Platform Error Polling Table (CPEP)".

Arguments:

None

Return Value:

An **Integer** containing the recommended polling interval in milliseconds.

0 – OSPM should not poll this processor.

Other values – OSPM should poll this processor at <= the specified interval.

OSPM evaluates the _PPE object during processor object initialization and Bus Check notification processing.

8.5 Processor Aggregator Device

The following section describes the definition and operation of the optional Processor Aggregator device. The Processor Aggregator Device provides a control point that enables the platform to perform specific processor configuration and control that applies to **all** processors in the platform.

The Plug and Play ID of the Processor Aggregator Device is ACPI000C.

Table 8-233 Processor Aggregator Device Objects

Object	Description	
_PUR	Requests a number of logical processors to be placed in an idle state	

8.5.1 Logical Processor Idling

In order to reduce the platform's power consumption, the platform may direct OSPM to remove a logical processor from the operating system scheduler's list of processors where non-processor affinitized work is dispatched. This capability is known as Logical Processor Idling and provides a means to reduce platform power consumption without undergoing processor ejection / insertion processing overhead. Interrupts directed to a logical processor and processor affinitized workloads will impede the effectiveness of logical processor idling in reducing power consumption as OSPM is not expected to retarget this work when a logical processor is idled.

8.5.1.1 PUR (Processor Utilization Request)

The _PUR object is an optional object that may be declared under the Processor Aggregator Device and provides a means for the platform to indicate to OSPM the number of logical processors to be idled. OSPM evaluates the _PUR object as a result of the processing of a Notify event on the Processor Aggregator device object of type 0x80.

Arguments:

None

Return Value:

A **Package** as described below.

Return Value Information

The NumProcessors package element conveys the number of logical processors that the platform wants OSPM to idle. This number is an absolute value. OSPM increments or decrements the number of logical processors placed in the idle state to equal the NumProcessors value as possible. A NumProcessors value of zero causes OSPM to place all logical processor in the active state as possible.

OSPM uses internal logical processor to physical core and package topology knowledge to idle logical processors successively in an order that maximizes power reduction benefit from idling requests. For example, all SMT threads constituting logical processors on a single processing core should be idled to allow the core to enter a low power state before idling SMT threads constituting logical processors on another core.

8.5.2 OSPM OST Evaluation

When processing of the _PUR object evaluation completes, OSPM evaluates the _OST object, if present under the Processor Aggregator device, to convey _PUR evaluation status to the platform. OST arguments specific to PUR evaluation are described below.

Arguments: (3)

Arg0 – Source Event (**Integer**): 0x80 Arg1 – Status Code (**Integer**): see below Arg2 – Idled Procs (**Buffer**): see below

Return Value:

None

Argument Information:

Arg1 – Status Code

0: success – OSPM idled the number of logical processors indicated by the value of Arg2 1: no action was performed

Arg2 – A 4-byte buffer that represents a DWORD that is the number of logical processors that are now idled)

The platform may request a number of logical processors to be idled that exceeds the available number of logical processors that can be idled from an OSPM context for the following reasons:

- The requested number is larger than the number of logical processors currently defined.
- Not all the defined logical processors were onlined by the OS (for example, for licensing reasons)

Logical processors critical to OS function (for example, the BSP) cannot be idled.

Processor Configuration and Control

ACPI-Defined Devices and Device-Specific Objects

This section describes ACPI defined devices and device-specific objects. The system status indicator objects, declared under the \ SI scope in the ACPI Namespace, are also specified in this section.

9.1 _SI System Indicators

ACPI provides an interface for a variety of simple and icon-style indicators on a system. All indicator controls are in the \SI portion of the namespace. The following table lists all defined system indicators. (Notice that there are also per-device indicators specified for battery devices).

Table 9-234 System Indicator Control Methods

Object	Description
_SST	System status indicator
_MSG	Messages waiting indicator
_BLT	Battery Level Threshold

9.1.1 _SST (System Status)

This optional object is a control method that OSPM invokes to set the system status indicator as desired.

Arguments: (1)

Arg0 – An **Integer** containing the system status indicator identifier

- 0 No system state indication. Indicator off
- 1 Working
- 2 Waking
- 3 Sleeping. Used to indicate system state S1, S2, or S3
- 4 Sleeping with context saved to non-volatile storage

Return Value:

None

9.1.2 _MSG (Message)

This control method sets the system's message-waiting status indicator.

Arguments: (1)

Arg0 – An **Integer** containing the number of waiting messages

Return Value:

None

9.1.3 _BLT (Battery Level Threshold)

This optional control method is used by OSPM to indicate to the platform the user's preference for various battery level thresholds. This method allows platform battery indicators to be synchronized with OSPM provided battery notification levels. Note that if _BLT is implemented on a multi-battery system, it is required that the power unit for all batteries must be the same. See <u>Section 10.2</u> for more details on battery levels.

Arguments: (3)

Arg0 – An **Integer** containing the preferred threshold for the battery warning level

Arg1 – An **Integer** containing the preferred threshold for the battery low level

Arg2 – An **Integer** containing the preferred threshold for the battery wake level

Return Value:

None

Additional Information

9.2 Ambient Light Sensor Device

The following section illustrates the operation and definition of the control method-based Ambient Light Sensor (ALS) device.

The ambient light sensor device can optionally support power management objects (e.g. _PS0, PS3) to allow the OS to manage the device's power consumption.

The Plug and Play ID of an ACPI control method ambient light sensor device is ACPI0008.

Table 9-235 Control Method Ambient Light Sensor Device

Object	Description
_ALI	The current ambient light illuminance reading in lux (lumen per square meter). [Required]

_ALC	The current ambient light color chromaticity reading, specified using x and y coordinates per the CIE Yxy color model. [Optional]
_ALT	The current ambient light color temperature reading in degrees Kelvin. [Optional]
_ALR	Returns a set of ambient light illuminance to display brightness mappings that can be used by an OS to calibrate its ambient light policy. [Required]
_ALP	Ambient light sensor polling frequency in tenths of seconds. [Optional]

9.2.1 Overview

This definition provides a standard interface by which the OS may query properties of the ambient light environment the system is currently operating in, as well as the ability to detect meaningful changes in these values when the environment changes. Two ambient light properties are currently supported by this interface: *illuminance* and *color*.

Ambient light illuminance readings are obtained via the _ALI method. Illuminance readings indicate the amount of light incident upon (falling on) a specified surface area. Values are specified in *lux* (lumen per square meter) and give an indication of how "bright" the environment is. For example, an overcast day is roughly 1000 lux, a typical office environment 300-400 lux, and a dimly-lit conference room around 10 lux.

A possible use of ambient light illuminance data by the OS is to automatically adjust the brightness (or *luminance*) of the display device – e.g. increase display luminance in brightly-lit environments and decrease display luminance in dimly-lit environments. Note that Luminance is a measure of light radiated (reflected, transmitted, or emitted) by a surface, and is typically measured in *nits*. The _ALR method provides a set of ambient light illuminance to display luminance mappings that can be used by an OS to calibrate its policy for a given platform configuration.

Ambient light color readings are obtained via the _ALT and/or _ALC methods. Two methods are defined to allow varying types/complexities of ambient light sensor hardware to be used. _ALT returns color temperature readings in degrees Kelvin. Color temperature values correlate a light source to a standard black body radiator and give an indication of the type of light source present in a given environment (e.g. daylight, fluorescent, incandescent). ALC returns color chromaticity readings per the CIE Yxy color model. Chromaticity x and y coordinates provide a more straightforward indication of ambient light color characteristics. Note that the CIE Yxy color model is defined by the International Commission on Illumination (abbreviated as CIE from its French title Commission Internationale de l'Eclairage) and is based on human perception instead of absolute color

A possible use of ambient light color data by the OS is to automatically adjust the color of displayed images depending on the environment the images are being viewed in. This may be especially important for reflective/transflective displays where the type of ambient light may have a large impact on the colors perceived by the user.

9.2.2 _ALI (Ambient Light Illuminance)

This control method returns the current ambient light illuminance reading in lux (lumen per square meter). Expected values range from ~1 lux for a dark room, ~300 lux for a typical office environment, and 10,000+ lux for daytime outdoor environments – although readings may vary

ACPI-Defined Devices and Device-Specific Objects

depending on the location of the sensor to the light source. Special values are reserved to indicate out of range conditions (see below).

Arguments:

None

Return Value:

An **Integer** containing the ambient light brightness in lux (lumens per square meter)

0 – The current reading is below the supported range or sensitivity of

the sensor

Ones (-1) — The current reading is above the supported range or sensitivity of

the sensor

Other values – The current ambient light brightness in lux (lumens per square

meter)

9.2.3 _ALT (Ambient Light Temperature)

This optional control method returns the current ambient light color temperature reading in degrees Kelvin (°K). Lower color temperatures imply warmer light (emphasis on yellow and red); higher color temperatures imply a colder light (emphasis on blue). This value can be used to gauge various properties of the lighting environment – for example, the type of light source. Expected values range from ~1500°K for candlelight, ~3000°K for a 200-Watt incandescent bulb, and ~5500°K for full sunlight on a summer day – although readings may vary depending on the location of the sensor to the light source. Special values are reserved to indicate out of range conditions (see below).

Arguments:

None

Return Value:

An **Integer** containing the ambient light temperature in degrees Kelvin

0 – The current reading is below the supported range or sensitivity of

the sensor

Ones (-1) — The current reading is above the supported range or sensitivity of

the sensor

Other values -The current ambient light temperature in degrees Kelvin

9.2.4 _ALC (Ambient Light Color Chromaticity)

This optional control method returns the current ambient light color chromaticity readings per the CIE Yxy color model. The x and y (chromaticity) coordinates are specified using a fixed 10^{-4} notation due to the lack of floating point values in ACPI. Valid values are within the range 0 (0x0000) through 1 (0x2710). A single 32-bit integer value is used, where the x coordinate is stored in the high word and the y coordinate in the low word. For example, the value 0x0C370CDA would be used to specify the white point for the CIE Standard Illuminant D65 (a standard representation of average daylight) with x = 0.3127 and y = 0.3290. Special values are reserved to indicate out of range conditions (see below).

Arguments:

None

Return Value:

An **Integer** containing the ambient light temperature in degrees Kelvin

0 – The current reading is below the supported range or sensitivity of

the sensor

Ones (-1) — The current reading is above the supported range or sensitivity of

the sensor

Other values – The current ambient light color chromaticity x and y coordinate

values, per the CIE Yxy color model

9.2.5 _ALR (Ambient Light Response)

This object evaluates to a package of *ambient light illuminance* to *display luminance* mappings that can be used by an OS to calibrate its ambient light policy for a given sensor configuration. The OS can use this information to extrapolate an ALS response curve - noting that these values may be treated differently depending on the OS implementation but should be used in some form to calibrate ALS policy.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of luminance mapping **Packages**. Each mapping package consists of two **Integers**.

The return data is specified as a package of packages, where each tuple (inner package) consists of the pair of **Integer** values of the form:

{<display luminance adjustment>, <ambient light illuminance>}

Package elements should be listed in monotonically increasing order based upon the ambient light illuminance value (the Y-coordinate on the graph) to simplify parsing by the OS.

Ambient light illuminance values are specified in lux (lumens per square meter). Display luminance (or brightness) adjustment values are specified using relative percentages in order simplify the means by which these adjustments are applied in lieu of changes to the user's display brightness preference. A value of 100 is used to indicate no (0%) display brightness adjustment given the lack of signed data types in ACPI. Values less than 100 indicate a negative adjustment (dimming); values greater than 100 indicate a positive adjustment (brightening). For example, a display brightness adjustment value of 75 would be interpreted as a -25% adjustment, and a value of 110 as a +10% adjustment.




Figure 9-46 A five-point ALS Response Curve

<u>Figure 9-46</u> illustrates the use of five points to approximate an example response curve, where the dotted line represents an approximation of the desired response (solid curve). Extrapolation of the values between these points is OS-specific – although for the purposes of this example we'll assume a piecewise linear approximation. The ALS response curve (ALR) would be specified as follows:

```
Name(_ALR, Package() {
       Package{70, 0},
                                  // Min
                                                     ( -30% adjust at
                                                                          0 lux)
       Package {73, 10},
                                                       -27% adjust at
                                                                         10 lux)
                                  11
       Package{85, 80},
                                  //
                                                       -15% adjust at
                                                                         80 lux)
       Package {100,300},
                                                         0% adjust at
                                                                       300 lux)
                                  // Baseline
       Package{150,1000}
                                                       +50% adjust at 1000 lux)
                                  // Max
   })
```

Within this data set exist three points of particular interest: *baseline, min,* and *max*. The *baseline* value represents an ambient light illuminance value (in lux) for the environment where this system is most likely to be used. When the system is operating in this ambient environment the ALS policy will apply no (0%) adjustment to the default display brightness setting. For example, given a system with a 300 lux *baseline*, operating in a typical office ambient environment (~300 lux), configured with a default display brightness setting of 50% (e.g. 60 nits), the ALS policy would apply no backlight adjustment, resulting in an absolute display brightness setting of 60 nits.

Min and max are used to indicate cutoff points in order to prevent an over-zealous response by the ALS policy and to influence the policy's mode of operation. For example, the min and max points from the figure above would be specified as (70,0) and (150,1000) respectively – where min indicates a maximum negative adjustment of 30% and max represents a maximum positive adjustment of 50%. Using a large display brightness adjustment for max allows an ALS response

that approaches a fully-bright display (100% absolute) in very bright ambient environments regardless of the user's display brightness preference. Using a small value for max (e.g. 0% @ 300 lux) would influence the ALS policy to limit the use of this technology solely as a power-saving feature (never brighten the display). Conversely, setting min to a 0% adjustment instructs ALS policy to brighten but never dim.

A minimum of two data points are required in the return package, interpreted as *min* and *max*. Note that the *baseline* value does not have to be explicitly stated; it can be derived from the response curve. Addition elements can be provided to fine-tune the response between these points. Figure 9-47 illustrates the use of two data points to achieve a response similar to (but simpler than) that described in Figure 9-46.




Figure 9-47 A two-point ALS Response Curve

This example lacks an explicit *baseline* and includes a *min* with an ambient light value above 0 lux. The *baseline* can easily be extrapolated by ALS Policy (e.g. 0% adjustment at ~400 lux). All ambient light brightness settings below *min* (20 lux) would be treated in a similar fashion by ALS policy (e.g. -30% adjustment). This two-point response curve would be modeled as:

This model can be used to convey a wide range of ambient light to display brightness responses. For example, a transflective display – a technology where illumination of the display can be achieved by reflecting available ambient light, but also augmented in dimly-lit environments with a backlight – could be modeled as illustrated in Figure 9-48.




Figure 9-48 Example Response Curve for a Transflective Display

This three-point approximation would result in an ALS response that allows the backlight to increase as the ambient lighting decreases. In this example, no backlight adjustment is needed in bright environments (1000+ lux), maximum backlight may be needed in dim environments (~30 lux), but a lower backlight setting may be used in a very-dark room (~0 lux) – resulting in an elbow around 30 lux. This response would be modeled in _ALR as follows:

Note the ordering of package elements: monotonically increasing from the lowest ambient light value (0 lux) to the highest ambient light value (1000 lux).

The transflective display example also highlights the need for non-zero values for the user's display brightness preference – which we'll refer to as the *reference* display brightness value. This requirement is derived from the model's use of relative adjustments. For example, applying any adjustment to a 0% reference display brightness value always results in a 0% absolute display brightness setting. Likewise, using a very small reference display brightness (e.g. 5%) results in a muted response (e.g. +30% of 5% = 6.5% absolute). The solution is to apply a reasonably large value (e.g. 50%) as the reference display brightness setting – even in the case where no backlight is applied. This allows relative adjustments to be applied in a meaningful fashion while conveying to the user that the display is still usable (via reflected light) under typical ambient conditions.

The OS derives the user's display brightness preference (this *reference* value) either from the Brightness Control Levels (_BCL) object or another OS-specific mechanism. See <u>Section 9.2.8</u>, "Relationship to Backlight Control Methods", for more information.

9.2.6 _ALP (Ambient Light Polling)

This optional object evaluates to a *recommended* polling frequency (in tenths of seconds) for this ambient light sensor. A value of zero – or the absence of this object when other ALS objects are defined – indicates that OSPM does not need to poll the sensor in order to detect meaningful changes in ambient light (the hardware is capable of generating asynchronous notifications).

The use of polling is allowed but strongly discouraged by this specification. OEMs should design systems that asynchronously notify OSPM whenever a meaningful change in the ambient light occurs—relieving the OS of the overhead associated with polling.

This value is specified as tenths of seconds. For example, a value of 10 would be used to indicate a 1 second polling frequency. As this is a *recommended* value, OSPM will consider other factors when determining the actual polling frequency to use.

Arguments:

None

Return Value:

An **Integer** containing the recommended polling frequency in tenths of seconds

0 – Polling by the host OS is not required

Other – The recommended polling frequency in tenths of seconds

9.2.7 Ambient Light Sensor Events

To communicate meaningful changes in ALS illuminance to OSPM, AML code should issue a **Notify**(als_device, 0x80) whenever the lux reading changes more than 10% (from the last reading that resulted in a notification). OSPM receives this notification and evaluates the _ALI control method to determine the current ambient light status. The OS then adjusts the display brightness based upon its ALS policy (derived from _ALR).

The definition of what constitutes a *meaningful change* is left to the system integrator, but should be at a level of granularity that provides an appropriate response without overly taxing the system with unnecessary interrupts. For example, an ALS configuration may be tuned to generate events for all changes in ambient light illuminance that result in a minimum $\pm 5\%$ display brightness response (as defined by ALR).

To communicate meaningful changes in ALS color temperature to OSPM, AML code should issue a **Notify**(als_device, 0x81) whenever the lux reading changes more than 10% (from the last reading that resulted in a notification). OSPM receives this notification and evaluates the _ALT and ALC control method to determine the current ambient light color temperature.

To communicate meaningful changes in ALS response to OSPM, AML code should issue a **Notify**(als_device, 0x82) whenever the set of points used to convey ambient light response has changed. OSPM receives this notification and evaluates the _ALR object to determine the current response points.

9.2.8 Relationship to Backlight Control Methods

The Brightness Control Levels (_BCL) method – described in section 0 – can be used to indicate user-selectable display brightness levels. The information provided by this method indicates the available display brightness settings, the recommended default brightness settings for AC and DC operation, and the absolute maximum and minimum brightness settings. These values indirectly influence the operation of the OSPM's ALS policy.

Display brightness adjustments produced by ALS policy are relative to the current user backlight setting, and the resulting absolute value must be mapped (rounded) to one of the levels specified in _BCL. This introduces the requirement for fine-grain display brightness control in order to achieve a responsive ALS system – which typically materializes as a need for additional entries in the _BCL list in order to provide reasonable resolution to the OS (e.g. 3-10% granularity). Note that user brightness controls (e.g. hotkeys) are not required to make use of all levels specified in BCL.

9.3 Battery Device

A battery device is required to either have an ACPI Smart Battery Table or a Control Method Battery interface. In the case of an ACPI Smart Battery Table, the Definition Block needs to include a Bus/Device Package for the SMBus host controller. This will install an OS specific driver for the SMBus, which in turn will locate the Smart Battery System Manager or Smart Battery Selector and Smart Battery Charger SMBus devices.

The Control Method Battery interface is defined in section 10.2, "Control Method Batteries."

9.4 Control Method Lid Device

Platforms containing lids convey lid status (open / closed) to OSPM using a Control Method Lid Device.

To implement a control method lid device, AML code should issue a **Notify**(lid_device, 0x80) for the device whenever the lid status has changed. The _LID control method for the lid device must be implemented to report the current state of the lid as either opened or closed.

The lid device can support _PRW and _PSW methods to select the wake functions for the lid when the lid transitions from closed to opened.

The Plug and Play ID of an ACPI control method lid device is PNP0C0D.

Table 9-236 Control Method Lid Device

Object	Description	
_LID	Returns the current status of the lid.	

9.4.1 _LID

Evaluates to the current status of the lid.

Arguments:

None

Return Value:

An Integer containing the current lid status

0 – The lid is closed Non-zero – The lid is open

9.5 Control Method Power and Sleep Button Devices

The system's power or sleep button can either be implemented using the fixed register space as defined in <u>Section 4.8.2.2</u>, "Buttons," or implemented in AML code as a control method power button device. In either case, the power button override function or similar unconditional system power or reset functionality is still implemented in external hardware.

To implement a control method power-button or sleep-button device, implement AML code that delivers two types of notifications concerning the device. The first is Notify(*Object*, 0x80) to signal that the button was pressed while the system was in the S0 state to indicate that the user wants the machine to transition from S0 to some sleeping state. The other notification is Notify(*Object*, 0x2) to signal that the button was pressed while the system was in an S1 to S4 state and to cause the system to wake. When the button is used to wake the system, the wake notification (Notify(*Object*, 0x2)) must occur after OSPM actually wakes, and a button-pressed notification (Notify(*Object*, 0x80)) must not occur.

The Wake Notification indicates that the system is awake because the user pressed the button and therefore a complete system resume should occur (for example, turn on the display immediately, and so on).

9.6 Embedded Controller Device

Operation of the embedded controller host controller register interface requires that the embedded controller driver has ACPI-specific knowledge. Specifically, the driver needs to provide an "operational region" of its embedded controller address space, and needs to use an ACPI event to service the host controller interface. For more information about an ACPI-compatible embedded controller device, see <u>Section 12</u>, "ACPI Embedded Controller Interface Specification."

The embedded controller device object provides the _HID of an ACPI-integrated embedded controller device of PNP0C09 and the host controller register locations using the device standard methods. In addition, the embedded controller must be declared as a named device object that includes a set of control methods. For more information, see Section 12.11, "Defining an Embedded Controller Device in ACPI Namespace").

9.7 Generic Container Device

A generic container device is a bridge that does not require a special OS driver because the bridge does not provide or require any features not described within the normal ACPI device functions. The resources the bridge requires are specified via normal ACPI resource mechanisms. Device enumeration for child devices is supported via ACPI namespace device enumeration and OS drivers require no other features of the bus. Such a bridge device is identified with the Plug and Play ID of PNP0A05 or PNP0A06.

ACPI-Defined Devices and Device-Specific Objects

A generic bus bridge device is typically used for integrated bridges that have no other means of controlling them and that have a set of well-known devices behind them. For example, a portable computer can have a "generic bus bridge" known as an EIO bus that bridges to some number of Super-I/O devices. The bridged resources are likely to be positively decoded as either a function of the bridge or the integrated devices. In this example, a generic bus bridge device would be used to declare the bridge then child devices would be declared below the bridge; representing the integrated Super-I/O devices.

9.8 ATA Controller Devices

There are two types of ATA Controllers: IDE controllers (also known as ATA controllers) and Serial ATA (SATA) controllers. IDE controllers are those using the traditional IDE programming interface, and may support Parallel ATA (P-ATA) or SATA connections. SATA controllers may be designed to operate in emulation mode only, native mode only, or they may be designed to support both native and non-native SATA modes. Regardless of the mode supported, SATA controllers are designed to work solely with drives supporting the Serial ATA physical interface. As described below, SATA controllers are treated similarly but not identically to traditional IDE controllers.

Platforms that contain controllers that support native and non-native SATA modes must take steps to ensure the proper objects are placed in the namespace for the mode in which they are operating.

Table 9-237 ATA Specific Objects	Table	9-237	ATA	Specific	Objects
----------------------------------	--------------	-------	------------	-----------------	----------------

Object	Description	Controller Type
_GTF	Optional object that returns the ATA task file needed to re-initialize the drive to boot up defaults.	Both
_GTM	Optional object that returns the IDE controller timing information.	IDE-only
_STM	Optional control method that sets the IDE controller's transfer timing settings.	IDE-only
_SDD	Optional control method that informs the platform of the type of device attached to a port.	SATA-only

9.8.1 Objects for Both ATA and SATA Controllers

9.8.1.1 _GTF (Get Task File)

This optional object returns a buffer containing the ATA commands used to restore the drive to boot up defaults (that is, the state of the drive after POST). The returned buffer is an array with each element in the array consisting of seven 8-bit register values (56 bits) corresponding to ATA task registers 1F1 thru 1F7. Each entry in the array defines a command to the drive.

Arguments:

None

Return Value:

A **Buffer** containing a byte stream of ATA commands for the drive

This object may appear under SATA port device objects or under IDE channel objects.

ATA task file array definition:

- Seven register values for command 1
 - Reg values: (1F1, 1F2, 1F3, 1F4, 1F5, 1F6, 1F7)
- Seven register values for command 2
 - Reg values: (1F1, 1F2, 1F3, 1F4, 1F5, 1F6, 1F7)
- Seven register values for command 3
 - Reg values: (1F1, 1F2, 1F3, 1F4, 1F5, 1F6, 1F7)
- Etc.

After powering up the drive, OSPM will send these commands to the drive, in the order specified. On SATA HBAs, OSPM evaluates _SDD before evaluating _GTF. The IDE driver may modify some of the feature commands or append its own to better tune the drive for OSPM features before sending the commands to the drive.

This Control Method is listed under each drive device object. OSPM must evaluate the _STM object or the SDD object before evaluating the GTF object.

Example of the return from _GTF:

```
Method(_GTF, 0x0, NotSerialized)
{
    Return(GTF0)
}
Name(GTF0, Buffer(0x1c))
{
    0x03, 0x00, 0x00, 0x00, 0x00, 0xa0, 0xef, 0x03, 0x00, 0x00, 0x00, 0x00, 0xa0, 0xef, 0x00, 0x00,
```

9.8.2 IDE Controller Device

Most device drivers can save and restore the registers of their device. For IDE controllers and drives, this is not true because there are several drive settings for which ATA does not provide mechanisms to read. Further, there is no industry standard for setting timing information for IDE controllers. Because of this, ACPI interface mechanisms are necessary to provide the operating system information about the current settings for the drive and channel, and for setting the timing for the channel.

OSPM and the IDE driver will follow these steps when powering off the IDE subsystem:

- 1. The IDE driver will call the _GTM control method to get the current transfer timing settings for the IDE channel. This includes information about DMA and PIO modes.
- 2. The IDE driver will call the standard OS services to power down the drives and channel.
- 3. As a result, OSPM will execute the appropriate _PS3 methods and turn off unneeded power resources.

To power on the IDE subsystem, OSPM and the IDE driver will follow these steps:

1. The IDE driver will call the standard OS services to turn on the drives and channel.

ACPI-Defined Devices and Device-Specific Objects

- 2. As a result, OSPM will execute the appropriate _PS0 methods and turn on required power resources.
- 3. The IDE driver will call the _STM control method passing in transfer timing settings for the channel, as well as the ATA drive ID block for each drive on the channel. The _STM control method will configure the IDE channel based on this information.
- 4. For each drive on the IDE channel, the IDE driver will run the _GTF to determine the ATA commands required to reinitialize each drive to boot up defaults.
- 5. The IDE driver will finish initializing the drives by sending these ATA commands to the drives, possibly modifying or adding commands to suit the features supported by the operating system.

The following shows the namespace for these objects:

```
\_SB
                        // System bus
                           // PCI bus
   PCI0
                               // First IDE channel
       TDE1
           _ADR
                                   // Indicates address of the channel on the PCI bus
           _GTM
                                   // Control method to get current IDE channel settings
           _STM
                                   // Control method to set current IDE channel settings
                                   // Power resources needed for D0 power state
            PR0
                                   // Drive 0
           DRV1
               _ADR
                                       // Indicates address of master IDE device
                                       // Control method to get task file
               _GTF
                                  // Drive 1
           DRV2
                _ADR
                                        // Indicates address of slave IDE device
                _GTF
                                         // Control method to get task file
        IDE2
                               // Second IDE channel
                                   // Indicates address of the channel on the PCI bus
           _ADR
           _GTM
                                   // Control method to get current IDE channel settings
                                   // Control method to set current IDE channel settings
           _STM
                                   // Power resources needed for D0 power state
           PR0
           DRV1
               _ADR
                                       // Indicates address of master IDE device
                                       // Control method to get task file
           DRV2
                                  // Drive 1
                _ADR
                                       // Indicates address of slave IDE device
                                        // Control method to get task file
               _GTF
```

The sequential order of operations is as follows:

Powering down:

- · Call GTM.
- Power down drive (calls PS3 method and turns off power planes).

Powering up:

- Power up drive (calls PS0 method if present and turns on power planes).
- Call STM passing info from GTM (possibly modified), with ID data from
- each drive.
- Initialize the channel.
- May modify the results of GTF.
- For each drive:

- Call GTF.
- Execute task file (possibly modified).

9.8.2.1 IDE Controller-specific Objects

9.8.2.1.1 _GTM (Get Timing Mode)

This Control Method exists under each channel device object and returns the current settings for the IDE channel.

Arguments:

None

Return Value:

A **Buffer** containing the current IDE channel timing information block as described in <u>Table 9-238</u> below.

_GTM returns a buffer with the following format

Table 9-238 GTM Method Result Codes

Field	Format	Description
PIO Speed 0	DWORD	The PIO bus-cycle timing for drive 0 in nanoseconds. 0xFFFFFFF indicates that this mode is not supported by the channel. If the chipset cannot set timing parameters independently for each drive, this field represents the timing for both drives.
DMA Speed 0	DWORD	The DMA bus-cycle for drive 0 timing in nanoseconds. If Bit 0 of the Flags register is set, this DMA timing is for UltraDMA mode, otherwise the timing is for multi-word DMA mode. 0xFFFFFFF indicates that this mode is not supported by the channel. If the chipset cannot set timing parameters independently for each drive, this field represents the timing for both drives.
PIO Speed 1	DWORD	The PIO bus-cycle timing for drive 1 in nanoseconds. 0xFFFFFFF indicates that this mode is not supported by the channel. If the chipset cannot set timing parameters independently for each drive, this field must be 0xFFFFFFF.
DMA Speed 1	DWORD	The DMA bus-cycle timing for drive 1 in nanoseconds. If Bit 0 of the Flags register is set, this DMA timing is for UltraDMA mode, otherwise the timing is for multi-word DMA mode. 0xFFFFFFFF indicates that this mode is not supported by the channel. If the chipset cannot set timing parameters independently for each drive, this field must be 0xFFFFFFFF.

ACPI-Defined Devices and Device-Specific Objects

Field	Format	Description
Flags	DWORD	Mode flags Bit[0]: 1 indicates using UltraDMA on drive 0 Bit[1]: 1 indicates IOChannelReady is used on drive 0 Bit[2]: 1 indicates using UltraDMA on drive 1 Bit[3]: 1 indicates IOChannelReady is used on drive 1 Bit[4]: 1 indicates chipset can set timing independently for each drive Bits[5-31]: reserved (must be 0)

9.8.2.1.2 _STM (Set Timing Mode)

This Control Method sets the IDE channel's transfer timings to the setting requested. The AML code is required to convert and set the nanoseconds timing to the appropriate transfer mode settings for the IDE controller. _STM may also make adjustments so that _GTF control methods return the correct commands for the current channel settings.

This control method takes three arguments: Channel timing information (as described in Table 9-6), and the ATA drive ID block for each drive on the channel. The channel timing information is not guaranteed to be the same values as returned by _GTM; the OS may tune these values as needed.

Arguments: (3)

Arg0 – A **Buffer** containing a channel timing information block (described in Table 9-6)

Arg1 – A **Buffer** containing the ATA drive ID block for channel 0

Arg2 – A **Buffer** containing the ATA drive ID block for channel 1

Return Value:

None

The ATA drive ID block is the raw data returned by the Identify Drive ATA command, which has the command code "0ECh." The _STM control method is responsible for correcting for drives that misreport their timing information.

9.8.3 Serial ATA (SATA) Controller Device

9.8.3.1 Definitions

HBA Host Bus Adapter

Native SATA aware Refers to system software (BIOS, option ROM, operating system,

etc) that comprehends a particular SATA HBA implementation

and understands its programming interface and power

management behavior.

Non-native SATA aware Refers to system software (BIOS, option ROM, operating system,

etc) that does not comprehend a particular SATA HBA implementation and does not understand its programming interface or power management behavior. Typically, non-native SATA aware software will use a SATA HBA's emulation interface (e.g. task file registers) to control the HBA and access

its devices.

Emulation mode Optional mode supported by a SATA HBA. Allows non-native

SATA aware software to access SATA devices via traditional

task file registers.

Native mode Optional mode supported by a SATA HBA. Allows native SATA

aware software to access SATA devices via registers that are

specific to the HBA.

Hybrid Device Refers to a SATA HBA that implements both an emulation and a

native programming interface.

9.8.3.2 Overview

A SATA HBA differs from an IDE controller in a number of ways. First, it can save its complete device context. Second, it replaces IDE channels, which may support up to 2 attached devices, with ports, which support only a single attached device, unless a port multiplier is present. See the SATA spec at "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "SATA Specification" for more information. Finally, SATA does not require timing information from the platform, allowing a simplification in how SATA controllers are represented in ACPI. (_GTM and _STM are replaced by the simpler _SDD method.)

All ports, even those attached off a port multiplier, are represented as children directly under the SATA controller device. This is practical because the SATA specification does not allow a port multiplier to be attached to a port multiplier. Each port's _ADR indicates to which root port they are connected, as well as the port multiplier location, if applicable. (See Table 6-2 for _ADR format.)

Since this specification only covers the configuration of motherboard devices, it is also the case that the control methods defined in this section cannot be used to send taskfiles to devices attached via either an add-in SATA HBA, or attached via a motherboard SATA HBA, if used with a port multiplier that is not also on the motherboard.

The following shows an example SATA namespace:

```
\ SB
                   - System bus
   PCT0
                   - PCT bus
       SATA
                   - SATA Controller device
           ADR
                          - Indicates address of the controller on the PCI bus
           PR0
                          - Power resources needed for DO power state
                       - Port 0 device
           PRTO
               _ADR
                           - Indicates physical port and port multiplier topology
               _SDD
                           - Identify information for drive attached to this port
                           - Control method to get task file
               _GTF
           PRTn
                       - Port n device
               _ADR
                           - Indicates physical port and port multiplier topology
               _SDD
                           - Identify information for drive attached to this port
               _GTF
                           - Control method to get task file
```

9.8.3.3 SATA controller-specific control methods

In order to ensure proper interaction between OSPM, the firmware, and devices attached to the SATA controller, it is a requirement that OSPM execute the _SDD and _GTF control methods when certain events occur. OSPM's response to events must be as follows:

COMRESET, Initial OS load, device insertion, HBA D3 to D0 transition, asynchronous loss of signal:

- 1. OSPM sends IDENTIFY DEVICE or IDENTIFY PACKET DEVICE command to the attached device.
- 2. OS executes _SDD. _SDD control method requires 1 argument that consists of the data block received from an attached device as a result of a host issued IDENTIFY DEVICE or IDENTIFY PACKET DEVICE command.
- 3. After the _SDD method completes, the OS executes the _GTF method. Using the task file information provided by GTF, the OS then sends the GTF taskfiles to the attached device.

Device removal and HBA D0 to D3 transition:

1. No OSPM action required.

9.8.3.3.1 _SDD (Set Device Data)

This optional object is a control method that conveys to the platform the type of device connected to the port. The _SDD object may exist under a SATA port device object. The platform typically uses the information conveyed by the _SDD object to construct the values returned by the _GTF object.

OSPM conveys to the platform the ATA drive ID block, which is the raw data returned by the Identify (Packet) Device, ATA command (command code "0ech."). Please see the ATA/ATAPI-6 specification for more details.

Arguments: (1)

Arg0 – A **Buffer** containing an ATA drive identify block, contents described by the ATA specification

Return Value:

None

9.9 Floppy Controller Device Objects

9.9.1 _FDE (Floppy Disk Enumerate)

Enumerating devices attached to a floppy disk controller is a time-consuming function. In order to speed up the process of floppy enumeration, ACPI defines an optional enumeration object that is defined directly under the device object for the floppy disk controller. It returns a buffer of five 32-bit values. The first four values are Boolean values indicating the presence or absence of the four floppy drives that are potentially attached to the controller. A non-zero value indicates that the floppy device is present. The fifth value returned indicates the presence or absence of a tape controller. Definitions of the tape presence value can be found in <u>Table 9-239</u>.

Arguments:

None

Return Value:

A **Buffer** containing a floppy drive information block, as decribed below

Table 9-239 Tape Presence

Value	Description
0	Device presence is unknown or unavailable
1	Device is present
2	Device is never present
>2	Reserved

9.9.2 FDI (Floppy Disk Information)

This object returns information about a floppy disk drive. This information is the same as that returned by the INT 13 Function 08H on IA-PCs.

Arguments:

None

Return Value:

A Package containing the floppy disk information as a list of Integers

Table 9-240 ACPI Floppy Drive Information

Package Element	Element Object Type	Actual Valid Data Width	
00 – Drive Number	Integer	BYTE	
01 – Device Type	Integer	BYTE	
02 – Maximum Cylinder Number	Integer	WORD	

Package Element	Element Object Type	Actual Valid Data Width
03 – Maximum Sector Number	Integer	WORD
04 - Maximum Head Number	Integer	WORD
05 - Disk_specify_1	Integer	BYTE
06 - Disk_specify_2	Integer	BYTE
07 – Disk_motor_wait	Integer	BYTE
08 - Disk_sector_siz	Integer	BYTE
09 - Disk_eot	Integer	BYTE
10 – Disk_rw_gap	Integer	BYTE
11 - Disk_dtl	Integer	BYTE
12 - Disk_formt_gap	Integer	BYTE
13 – Disk_fill	Integer	BYTE
14 - Disk_head_sttl	Integer	BYTE
15 – Disk_motor_strt	Integer	BYTE

9.9.3 FDM (Floppy Disk Drive Mode)

This control method switches the mode (300 RPM or 360 RPM) of all floppy disk drives attached to this controller. If this control method is implemented, the platform must reset the mode of all drives to 300RPM mode after a Dx to D0 transition of the controller.

Arguments: (1)

Arg0 – An **Integer** containing the new drive mode

0 – Set the mode of all drives to 300 RPM mode

1 – Set the mode of all drives to 360 RPM mode

Return Value:

None

9.10 GPE Block Device

The GPE Block device is an optional device that allows a system designer to describe GPE blocks beyond the two that are described in the FADT. Control methods associated with the GPE pins of GPE block devices exist as children of the GPE Block device, not within the _GPE namespace. Because GPE block devices are meant as an extension to the GPE blocks defined in the FADT, and that portion of the FADT is to be ignored in hardware-reduced ACPI, GPE block devices are not supported in hardware-reduced ACPI.

A GPE Block device consumes I/O or memory address space, as specified by its _PRS or _CRS child objects. The interrupt vector used by the GPE block does not need to be the same as the SCI_INT field. The interrupt used by the GPE block device is specified in the _CRS and _PRS methods associated with the GPE block. The _CRS of a GPE Block device may only specify a single register address range, either I/O or memory. This range contains two registers: the GPE status and enable registers. Each register's length is defined as half of the length of the _CRS-defined register address range.

A GPE Block device must have a HID or a CID of "ACPI0006."

Note: A system designer must describe the GPE block necessary to bootstrap the system in the FADT as a GPE0/GPE1 block. GPE Block devices cannot be used to implement these GPE inputs.

A GPE Block Device must contain the _Lxx, _Exx, _Wxx, _CRS, _PRS, and _SRS methods required to use and program that block.

To represent the GPE block associated with the FADT, the system designer shouldinclude in the namespace a Device object with the ACPI0006 _HID that contains **no** _CRS, _PRS, _SRS, _Lxx, _Exx, or _Wxx methods. OSPM assumes that the first such ACPI0006 device is the GPE Block Device that is associated with the FADT GPEs. (See the example below).

```
// ASL example of a standard GPE block device
Device(\_SB.PCI0.GPE1) {
    Name(_HID, "ACPI0006")
    Name(_UID, 2)
    Name(_CRS, Buffer () {
        IO(Decode16, FC00, FC03, 4, 4,)
        IRQ( Level, ActiveHigh, Shared,) { 5 }
    })

    Method(_L02) { ... }
    Method(_E07) { ... }
    Method(_W04) { ... }
}

// ASL example of a GPE block device that refers to the FADT GPEs.
// Cannot contain any _Lxx, _Exx, _Wxx, _CRS, _PRS, or. _SRS methods.
Device(\_SB.PCI0.GPE0) {
    Name(_HID, "ACPI0006")
    Name(_UID,1)
}
```

Notice that it is legal to replace the I/O descriptors with Memory descriptors if the register is memory mapped.

If the system must run any GPEs to bootstrap the system (for example, when Embedded Controller events are required), the associated block of GPEs must be described in the FADT. This register block is not relocatable and will always be available for the life of the operating system boot.

A GPE block associated with the ACPI0006 _HID can be stopped, ejected, reprogrammed, and so on. The system can also have multiple such GPE blocks.

9.10.1 Matching Control Methods for Events in a GPE Block Device

When a GPE Device raises an interrupt, OSPM executes a corresponding control method (as described in <u>Section 5.6.4.1.1</u>, "Queuing the Matching Control Method for Execution"). These control methods (of the form _Lxx, _Exx, and _Wxx) for GPE Devices are not within the _GPE namespace. They are children of the GPE Block device.

For example:

```
Device(GPE5) {
    Name(_HID, "ACPI0006")

    Method(_L02) { ... }
    Method(_E07) { ... }
    Method(_W04) { ... }
}
```

9.11 Module Device

This optional device is a container object that acts as a bus node in a namespace. It may contain child objects that are devices or buses. The module device is declared using the ACPI0004 hardware identifier (HID).

If the module device contains a _CRS object, the "bus" described by this object is assumed to have these resources available for consumption by its child devices. If a _CRS object is present, any resources not produced in the module device's _CRS object may not be allocated to child devices.

Providing a _CRS object is undesirable in some module devices. For example, consider a module device used to describe an add-in board containing multiple host bridges without any shared resource decoding logic. In this case the resource ranges available to the host bridges are not controlled by any entity residing on the add-in board, implying that a _CRS object in the associated module device would not describe any real feature of the underlying hardware. A module device must contain a _CRS object if the device contains any PCI host bridge devices.

To account for cases like this, the system designer may optionally omit the module device's _CRS object. If no _CRS object is present, OSPM will assume that the module device is a simple container object that does not produce the resources consumed by its child devices. In this case, OSPM will assign resources to the child devices as if they were direct children of the module device's parent object.

For an example with a module device _CRS object present, consider a Module Device containing three child memory devices. If the _CRS object for the Module Device contains memory from 2 GB through 6 GB, then the child memory devices may only be assigned addresses within this range.

Example:

```
Device (\_SB.NOD0) {
                                            // Module device
   Name (_HID, "ACPI0004")
   Name (_UID, 0)
   Name (_PRS, ResourceTemplate() {
       WordIO (
           ResourceProducer,
                                    // _MIF
// _MAF
           MinFixed,
           MaxFixed,,,
                                    // _GRA
           0x0000,
                                    // _MIN
           0x0000,
           0x7FFF,
                                   // _MAX
           0x0,
                                   // _TRA
           0x8000)
                                   // _LEN
       DWordMemory (
           ResourceProducer,, // For Main Memory + PCI
                        // _MIF
// _MAF
// _MEM
           MinNotFixed,
           MaxNotFixed,
           Cacheable,
                                   // _RW
           ReadWrite,
                                // _GRA
// _MIN
// _MAX
           0x0FFFFFFF,
           0x40000000,
           0x7FFFFFFF,
                                   // _TRA
           0x0.
           0x00000000)
                                    // _LEN
   })
   Method (_SRS, 1) { ... }
   Method (_CRS, 0) { ... }
   Device (MEM0) {
                                    // Main Memory (256MB module)
      Name (_HID, EISAID("PNP0C80"))
       Name (_UID, 0)
       Method (_STA, 0) {
                                    // If memory not present --> Return(0x00)
                                     // Else if memory is disabled --> Return(0x0D)
                                     // Else --> Return(0x0F)
       Name (_PRS, ResourceTemplate () {
           DWordMemory (,,,,
                                   // _MEM
               Cacheable,
               ReadWrite,
                                   // _RW
               0x0FFFFFFF,
                                   // _GRA
               0x40000000,
                                   // _MIN
                                 // _MAX
               0x7FFFFFFF,
                                   // _TRA
               0x0,
               0x10000000)
                                    // _LEN
       Method (_CRS, 0) { ... }
       Method (_SRS, 1) { ... }
       Method (_DIS, 0) { ... }
                                      // Main Memory (512MB module)
   Device (MEM1) {
       Name (_HID, EISAID("PNP0C80"))
       Name (_UID, 1)
       Method (_STA, 0) {
                                      // If memory not present --> Return(0x00)
                                      // Else if memory is disabled --> Return(0x0D)
                                      // Else --> Return(0x0F)
       Name ( PRS, ResourceTemplate () {
           DWordMemory (,,,,
```

```
Cacheable,
                                  // _MEM
             ReadWrite,
                                  // _RW
            })
    Method (_CRS, 0) { ... }
    Method (_SRS, 1) { ... }
    Method (_DIS, 0) { ... }
Device (PCI0) {
                                     // PCI Root Bridge
    Name (_HID, EISAID("PNP0A03"))
    Name (_UID, 0)
    Name (\_BBN, 0x00)
    Name (_PRS, ResourceTemplate () {
       WordBusNumber (
           ResourceProducer,
            MinFixed,
                                  // _MIF
            MaxFixed, // _MAF

0x00, // _GRA

0x00, // _MIN

0x7F, // _MAX

0x0, // _TRA

0x80) // _LEN
        WordIO (
            ResourceProducer,
            WordIO (
            ResourceProducer,
MinFixed, // _MIF
MaxFixed,,, // _MAF
0x0000, // _GRA
0x0D00, // _MIN
0x7FFF, // _MAX
0x0, // _TRA
0x7300) // _LEN
        DWordMemory (
             ResourceProducer,,
            Method (_CRS, 0) { ... }
    Method (_SRS, 1) { ... }
}
```

9.12 Memory Devices

Memory devices allow a platform to convey dynamic properties of memory to OSPM and are required when a platform supports the addition or removal of memory while the system is active or when the platform supports memory bandwidth monitoring and reporting (see Section 9.12.2, "Memory Bandwidth Monitoring and Reporting). Memory devices may describe exactly the same physical memory that the System Address Map interfaces describe (see section 14, "System Address Map Interfaces"). They do not describe how that memory is, or has been, used. If a region of physical memory is marked in the System Address Map interface as AddressRangeReserved or AddressRangeNVS and it is also described in a memory device, then it is the responsibility of the OS to guarantee that the memory device is never disabled.

It is not necessary to describe all memory in the system with memory devices if there is some memory in the system that is static in nature. If, for instance, the memory that is used for the first 16 MB of system RAM cannot be ejected, inserted, or disabled, that memory may only be represented by the System Address Map interfaces. But if memory can be ejected, inserted, or disabled, or if the platform supports memory bandwidth monitoring and reporting, the memory must be represented by a memory device.

9.12.1 Address Decoding

Memory devices must provide a _CRS object that describes the physical address space that the memory decodes. If the memory can decode alternative ranges in physical address space, the devices may also provide _PRS, _SRS and _DIS objects. Other device objects may also apply if the device can be ejected.

9.12.2 Memory Bandwidth Monitoring and Reporting

During platform operation, an adverse condition external to the platform may arise whose remedy requires a reduction in the platform's available memory bandwidth. For example, a server management controller's detection of an adverse thermal condition or the need to reduce the total power consumption of platforms in the data center to stay within acceptable limits. Providing OSPM with knowledge of a platform induced reduction of memory bandwidth enables OSPM to provide more robust handling of the condition. The following sections describe objects OSPM uses to configure platform-based memory bandwidth monitoring and to ascertain available memory bandwidth when the platform performs memory bandwidth throttling.

9.12.2.1 _MBM (Memory Bandwidth Monitoring Data)

The optional _MBM object provides memory bandwidth monitoring information for the memory device.

Arguments:

None

Return Value:

A **Package** containing memory device status information as described in <u>Table 9-241</u> below

Return Value Information:

MBM evaluation returns a package of the following format:

Table 9-241 MBM Package Details

Field	Format	Description
Revision	Integer	Current revision is: 0
Window Size	Integer (DWORD)	This field indicates the size of the averaging window (in seconds) that the platform uses to report average bandwidth.
Sampling Interval	Integer (DWORD)	This field indicates the sampling interval (in seconds) that the platform uses to record bandwidth during the averaging window.
Maximum Bandwidth	Integer (DWORD)	This field indicates the maximum memory bandwidth (in megabytes per second) for the memory described by this memory device.
Average Bandwidth	Integer (DWORD)	This field indicates the moving average memory bandwidth (in percent) for the averaging window.
Low Bandwidth	Integer (DWORD)	This field indicates the lowest memory bandwidth (in percent) recorded for the averaging window.
Low Notification Threshold	Integer (DWORD)	The platform to issues a Notify (0x80) on the memory device when the moving average memory bandwidth value (in percent) falls below the value indicated by this field.
High Notification Threshold	Integer (DWORD)	The platform to issues a Notify (0x81) on the memory device when the moving average memory bandwidth value (in percent) increases to or exceeds the value indicated by this field.

9.12.2.2 _MSM (Memory Set Monitoring)

This optional object sets the memory bandwidth monitoring parameters described in <u>Table 9-241</u>.

Arguments: (4)

Arg0 – WindowSize (Integer(DWORD)): indicates the window size in seconds.

Arg1 – SamplingInterval (Integer(DWORD)): indicates the sampling interval in seconds.

Arg2 – LowNotificationThreshold (**Integer**(DWORD)): indicates the low notification threshold in percent. Must be <= HighNotificationThreshold.

Arg3 – HighNotificationThreshold (**Integer**(DWORD)): indicates the high notification threshold in percent. Must be >= LowNotificationThreshold.

Return Value:

An Integer (DWORD) containing a bit encoded result code as follows:

0x00000000 - Succeeded to set all memory bandwidth monitoring parameters.

Non-Zero – At least one memory bandwith monitoring parameter value could not be set as follows:

Table 9-242 MSM Result Encoding

Bits	Definition
0	If clear indicates WindowSize was set successfully. If set, indicates invalid WindowSize argument.
1	If clear indicates SamplingInterval was set successfully. If set, indicates invalid SamplingInterval argument.
2	If clear indicates LowNotificationThreshold was set successfully. If set, indicates invalid LowNotificationThreshold argument.
3	If clear indicates HighNotificationThreshold was set successfully. If set, indicates invalid HighNotificationThreshold argument.
31:4	Reserved (must be 0)

9.12.3 OSC Definition for Memory Device

OSPM evaluates _OSC under the Memory Device to convey OSPM capabilities to the platform. Argument definitions are as follows:

Arguments: (4)

 $Arg0-UUID\ (Buffer):\ 03B19910-F473-11DD-87AF-0800200C9A66$

Arg1 – Revision ID (Integer): 1

Arg2 – Count of Entries in Arg3 (Integer): 2

Arg3 – DWORD capabilities (**Buffer**): First DWORD: as described in <u>Section 6.2.10</u>, Second DWORD: See Table 6-197.

Return Value:

A **Buffer** containing platform capabilities

Table 9-243 Memory Device OSC Capabilities DWORD number 2

Bits	Field Name	Definition
0	Memory Bandwidth Change Notifications	This bit is set if OSPM supports the processing of memory bandwidth change notifications. If the platform supports the ability to issue a notification when Memory Bandwidth changes, it may only do so after _OSC has been evaluated with this bit setOSC evaluation with this bit clear will cause the platform to cease issuing notifications if previously enabled.
31:1		Reserved (must be 0)

Return Value Information

Capabilities Buffer (Buffer) – The platform acknowledges the Capabilities Buffer by returning a buffer of DWORDs of the same length. Set bits indicate acknowledgement and cleared bits indicate that the platform does not support the capability.

9.12.4 Example: Memory Device

```
Scope (\_SB){
    Device (MEM0) {
       Name (_HID, EISAID ("PNP0C80"))
       Name (_CRS, ResourceTemplate () {
           QWordMemory
                ResourceConsumer,
                MinFixed.
                MaxFixed,
                Cacheable,
                ReadWrite,
                0xFFFFFFF,
                0x10000000,
                0x30000000,
                ,,)
        }
    }
}
```

9.13 _UPC (USB Port Capabilities)

This optional object is a method that allows the platform to communicate to the operating system, certain USB port capabilities that are not provided for through current USB host bus adaptor specifications (e.g. UHCI, OHCI and EHCI). If implemented by the platform, this object will be present for each USB port (child) on a given USB host bus adaptor; operating system software can examine these characteristics at boot time in order to gain knowledge about the system's USB topology, available USB ports, etc. This method is applicable to USB root hub ports as well as ports that are implemented through integrated USB hubs.

Arguments:

None

Return Value:

A **Package** as described below

Return Value Information:

Table 9-244 UPC Return Package Values

Element	Object Type	Description	
Connectable	Integer	If this value is non-zero, then the port is connectable. If this value is zero, then	
	(BYTE)	the port is not connectable.	

Element	Object Type	Description	
Туре	Integer	Specifies the host connector type. It is ignored by OSPM if the port is not user	
	(BYTE)	visible:	
		0x00:	Type 'A' connector
		0x01:	Mini-AB connector
		0x02:	ExpressCard
		0x03:	USB 3 Standard-A connector
		0x04:	USB 3 Standard-B connector
		0x05:	USB 3 Micro-B connector
		0x06:	USB 3 Micro-AB connector
		0x07:	USB 3 Power-B connector
		0x08 – 0xFE:	Reserved
		0xFF:	Proprietary connector
Reserved0	Integer	This value is reserved for future use and must be zero.	
Reserved1	Integer	This value is reserved for future use and must be zero.	

Additional Notes:

The definition of a 'connectable' port is dependent upon the implementation of the USB port within a particular platform. For example,

- If a USB port is user visible (as indicated by the _PLD object) and connectable, then an end user can freely connect and disconnect USB devices to the USB port.
- If a USB port is not user visible and is connectable, then an end user cannot freely connect and disconnect USB devices to the USB port. A USB device that is directly "hard-wired" to a USB port is an example of a USB port that is not user visible and is connectable.
- If a USB port is not user visible and is not connectable, then the USB port is physically implemented by the USB host controller, but is not being used by the platform and therefore cannot be accessed by an end user.

A USB port cannot be specified as both visible and not connectable.

Example

The following is an example of a port characteristics object implemented for a USB host controller's root hub where:

- Three Ports are implemented; Port 1 is not user visible/not connectable and Ports 2 and 3 are user visible and connectable.
- Port 2 is located on the back panel
- Port 3 has an integrated 2 port hub. Note that because this port hosts an integrated hub, it is therefore not sharable with another host controller (e.g. If the integrated hub is a USB2.0 hub, the port can never be shared with a USB1.1 companion controller).
- The ports available through the embedded hub are located on the front panel and are adjacent to one another.

ACPI-Defined Devices and Device-Specific Objects




Figure 9-49 USB ports

```
// Root hub device for this host controller. This controller implements 3 root hub ports.
11
Device( RHUB) {
        Name( _ADR, 0x0000000)
                                        // Value of 0 is reserved for root HUB
        // Root hub, port 1
        Device( PRT1) {
            // Address object for port 1. This value must be 1
            Name( _ADR, 0x0000001)
            \ensuremath{//} USB port capabilities object. This object returns the system
            // specific USB port configuration information for port number 1
            // Because this port is not connectable it is assumed to be not visible.
            // Therefore a _PLD descriptor is not required.
            Name( _UPC, Package(){
                0x00,
                                           // Port is not connectable
                0xFF,
                                           // Connector type (N/A for non-visible ports)
                0x00000000,
                                           // Reserved 0 - must be zero
                0x00000000)
                                           // Reserved 1 - must be zero
    }
                                           // Device( PRT1)
                                           11
                                           // Root Hub, Port 2
                                           11
    Device( PRT2) {
                                           // Address object for port 2. This value must be 2
            \texttt{Name(\_ADR, 0x00000002)}
            Name( _UPC, Package(){
                0xFF,
                                           // Port is connectable
                0x00,
                                           // Connector type - Type 'A'
                0x00000000,
                                           // Reserved 0 - must be zero
                0x00000000)
                                           // Reserved 1 - must be zero
                                            // provide physical port location info
            Name( _PLD, Package(1) {
                Buffer(0x14) {
                    0x82,0x00,0x00,0x00,
                                            // Revision 2, Ignore color
                                            // Color (ignored), width and height not
                    0x00,0x00,0x00,0x00,
                                            // required as this is a standard USB 'A' type
                                            // connector
```

```
// User visible, Back panel, Vertical
                    0x69,0x0c,0x00,0x00,
                                             // Center, shape = vert. rectangle
                    0x03,0x00,0x00,0x00,
                                             // ejectable, requires OPSM eject assistance
                    0xFF,0xFF,0xFF,0xFF\})\} // Vert. and Horiz. Offsets not supplied
}
                                             // Device( PRT2)
                                             // Root Hub, Port 3
                                             //
   Device( PRT3) {
                                             // This device is the integrated USB hub.
                                             // Address object for port 3. This value must be 3
        Name(_{ADR}, 0x00000003)
        // Because this port is not connectable it is assumed to be not visible.
        // Therefore a _PLD descriptor is not required.
        Name( _UPC, Package(){
            0xFF,
                                            // Port is connectable
                                            // Connector type (N/A for non-visible ports)
            0xFF,
            0x00000000,
                                            // Reserved 0 - must be zero
            0x00000000)
                                            // Reserved 1 - must be zero
                                            11
                                            // Integrated hub, port 1
                                            11
            Device( PRT1) {
            // Address object for the port. Because the port is implemented on
            // integrated hub port #1, this value must be 1
            Name( _ADR, 0x0000001)
            // USB port characteristics object. This object returns the system
            // specific USB port configuration information for integrated hub port
            // number 1
            Name( _UPC, Package(){
                0xFF,
                                            // Port is connectable
                0x00,
                                            // Connector type - Type 'A'
                0x00000000,
                                            // Reserved 0 - must be zero
0x00000000)
                                            // Reserved 1 - must be zero
                                            // provide physical port location info
            Name( _PLD, Package(1) {
                Buffer(0x14) {
                0x82,0x00,0x00,0x00,,
                                            // Revision 2, Ignore color
                                            // Color (ignored), width and height not
                0 \times 00, 0 \times 00, 0 \times 00, 0 \times 00,
                                            // required as this is a standard USB 'A' type
                                            // connector
    0xa1,0x10,0x00,0x00,
                                            // User visible, front panel, Vertical
                                            // lower, horz. Left, shape = horz. rectangle
                0 \times 03, 0 \times 00, 0 \times 00, 0 \times 00,
                                            // ejectable, requires OPSM eject assistance
                0xFF,0xFF,0xFF,0xFF})}
                                            // Vert. and Horiz. Offsets not supplied
                                            // Device( PRT1)
                                            11
                                            // Integrated hub, port 2
            Device( PRT2) {
                // Address object for the port. Because the port is implemented on
                // integrated hub port #2, this value must be 2
                Name( _ADR, 0x00000002)
                // USB port characteristics object. This object returns the system
                // specific USB port configuration information for integrated hub port
                // number 2
```

ACPI-Defined Devices and Device-Specific Objects

```
Name( _UPC, Package(){
            0xFF,
                                     // Port is connectable
            0x00,
                                     // Connector type - Type 'A'
            0x00000000,
                                     // Reserved 0 - must be zero
            0x00000000)
                                     // Reserved 1 - must be zero
        Name( _PLD, Package(1) {
            Buffer(0x14) {
            0x82,0x00,0x00,0x00,
                                     // Revision 2, Ignore color
                                     // Color (ignored), width and height not
            0 \times 00, 0 \times 00, 0 \times 00, 0 \times 00,
                                     // required as this is a standard USB 'A' type
                                     // connector
            0xa1,0x12,0x00,0x00,
                                     // User visible, front panel, Vertical
                                     // lower, horz. right, shape = horz. rectangle
            0x03,0x00,0x00,0x00,
                                     // ejectable, requires OPSM eject assistance
            0xFF,0xFF,0xFF,0xFF})
                                     // Vert. and Horiz. Offsets not supplied
                                     // Device( PRT2)
}
                                     // Device( PRT3)
                                     // Device( RHUB)
```

9.13.1 USB 2.0 Host Controllers and _UPC and _PLD

Platforms implementing USB2.0 host controllers that consist of one or more USB1.1 compliant companion controllers (e.g. UHCI or OHCI) must implement a _UPC and a _PLD object for each port USB port that can be routed between the EHCI host controller and its associated companion controller. This is required because a USB Port Capabilities object implemented for a port that is a child of an EHCI host controller may not be available if the OSPM disables the parent host controller. For example, if root port 1 on an EHCI host controller is routable to root port 1 on its companion controller, then the namespace must provide a _UPC and a _PLD object under each host controller's associated port 1 child object.

Example

```
Scope(\_SB) {
Device(PCI0) {
                             // Host controller (EHCI)
Device( USB0) {
                             // PCI device#/Function# for this HC. Encoded as specified in the ACPI
                             // specification
Name(_ADR, 0xyyyyzzzz)
                             // Root hub device for this HC #1.
Device(RHUB) {
Name(\_ADR, 0x00000000)
                             // must be zero for USB root hub
                             // Root hub, port 1
Device(PRT1) {
Name(_ADR, 0x0000001)
           \ensuremath{//} USB port configuration object. This object returns the system
\ensuremath{//} specific USB port configuration information for port number 1
// Must match the _UPC declaration for USB1.RHUB.PRT1 as it is this
// host controller's companion
Name( _UPC, Package(){
0xFF,
                              // Port is connectable
0x00,
                              // Connector type - Type 'A'
0x00000000,
                              // Reserved 0 - must be zero
                              // Reserved 1 - must be zero
0x00000000)
// provide physical port location info for port 1
// Must match the _UPC declaration for USB1.RHUB.PRT1 as it is this
// host controller's companion
Name( _PLD, Package(1) {
    Buffer(0x14)
    0x82,0x00,0x00,0x00,
                             // Revision 2, Ignore color
                             // Color (ignored), width and height not
    0 \times 00, 0 \times 00, 0 \times 00, 0 \times 00,
                             // required as this is a standard USB 'A'
                             // type connector
    0xa1,0x10,0x00,0x00,
                             // User visible, front panel, Vertical
                             // lower, horz. Left, shape = horz. Rect.
    0x03,0x00,0x00,0x00,
                             // ejectable, needs OPSM eject assistance
                    0xFF,0xFF,0xFF,0xFF})}
                                                   // Vert. and Horiz. Offsets not supplied
}
                             // Device( PRT1)
                             11
                             // Define other ports, control methods, etc
                             // Device( RHUB)
                             // Device( USB0)
                             // Companion Host controller (OHCI or UHCI)
Device( USB1) {
                             // PCI device#/Function# for this HC. Encoded as specified in the ACPI
                             // specification
Name(_ADR, 0xyyyyzzzz)
                             // Root hub device for this HC #1.
Device(RHUB) {
Name(\_ADR, 0x00000000)
                             // must be zero for USB root hub
                             // Root hub, port 1
```

```
Device(PRT1) {
Name(_{ADR}, 0x00000001)
// USB port configuration object. This object returns the system
// specific USB port configuration information for port number 1
// Must match the \_{\tt UPC} declaration for USB0.RHUB.PRT1 as this host
// controller is a companion to the EHCI host controller
// provide physical port location info for port 1
Name( _UPC, Package(){
0xFF.
                           // Port is connectable
0x00,
                           // Connector type - Type 'A'
0x00000000,
                           // Reserved 0 - must be zero
                           // Reserved 1 - must be zero
0x00000000)
// Must match the _PLD declaration for USB0.RHUB.PRT1 as this host
// controller is a companion to the EHCI host controller
Name( _PLD, Package(1) {
   Buffer( 0x14) {
    0x82,0x00,0x00,0x00, // Revision 2, Ignore color
                           // Color (ignored), width and height not
    0x00,0x00,0x00,0x00, // required as this is a standard USB 'A'
                           // type connector
    0xa1,0x10,0x00,0x00, // User visible, front panel, Vertical
                          // lower, horz. Left, shape = horz. Rect.
    0x03,0x00,0x00,0x00,
                          // ejectable, requires OPSM eject assistance
                    0xFF,0xFF,0xFF,0xFF})}
                                              // Vert. and Horiz. Offsets not supplied
}
                           // Device( PRT1)
                            11
                           // Define other ports, control methods, etc
                           // Device( RHUB)
                           // Device( USB1)
                           // Device( PCI0)
                            // Scope( _\SB)
```

9.14 Device Object Name Collision

Devices containing both _HID and _CID may have device specific control methods pertaining to both the device ID in the _HID and the device ID in the _CID. These device specific control methods are defined by the device owner (a standard body or a vendor or a group of vendor partners). Since these object names are not controlled by a central authority, there is a likelihood that the names of objects will conflict between two defining parties. The _DSM object described in the next section solves this conflict.

9.14.1 DSM (Device Specific Method)

This optional object is a control method that enables devices to provide device specific control functions that are consumed by the device driver.

Arguments: (4)

```
Arg0 – A Buffer containing a UUID
```

Arg1 – An **Integer** containing the Revision ID

Arg2 – An Integer containing the Function Index

Arg3 – A **Package** that contains function-specific arguments

Return Value:

If Function Index = 0, a **Buffer** containing a function index bitfield. Otherwise, the return value and type depends on the UUID and revision ID (see below).

Argument Information:

Arg0: UUID – A Buffer containing the Universal Unique Identifier (16 Bytes)

Arg1: Revision ID – the function's revision. This revision is specific to the UUID.

Arg2: Function Index – Represents a specific function whose meaning is specific to the UUID and Revision ID. Function indices should start with 1. Function number zero is a query function (see the special return code defined below).

Arg3: Arguments – a package containing the parameters for the function specified by the *UUID*, *Revision ID* and *Function Index*. Successive revisions of *Function Arguments* must be backward compatible with earlier revisions. See Section 9 "ACPI Devices and Device Specific Objects", for any _DSM definitions for ACPI devices. New UUIDs may also be created by OEMs and IHVs for custom devices and other interface or device governing bodies (e.g. the PCI SIG), as long as the UUID is different from other published UUIDs. Only the issuer of a UUID can authorize a new *Function Index*, *Revision ID* or *Function Argument* for that UUID.

Return Value Information:

If Function Index is zero, the return is a buffer containing one bit for each function index, starting with zero. Bit 0 indicates whether there is support for any functions other than function 0 for the specified UUID and Revision ID. If set to zero, no functions are supported (other than function zero) for the specified UUID and Revision ID. If set to one, at least one additional function is supported. For all other bits in the buffer, a bit is set to zero to indicate if that function index is not supported for the specific UUID and Revision ID. (For example, bit 1 set to 0 indicates that function index 1 is not supported for the specific UUID and Revision ID.)

If the bit representing a particular function index would lie outside of the buffer, it should be assumed to be 0 (that is, not supported).

If *Function index* is non-zero, the return is any data object. The type and meaning of the returned data object depends on the *UUID* and *Revision ID*.

Note: For backward compatibility _DSM requires that each Revision ID support all of the functions defined by all previous Revision IDs for the same UUID.

Implementation Note

Since the purpose of the _DSM method is to avoid the namespace collision, the implementation of this method shall not use any other method or data object which is not defined in this specification unless its driver and usage is completely under the control of the platform vendor.

Example:

```
// _DSM - Device Specific Method
// Arg0: UUID
                       Unique function identifier
// Arg1: Integer
                        Revision Level
         Integer
Package
// Arg2:
                           Function Index (0 = Return Supported Functions)
                           Parameters
Function(_DSM,{IntObj,BuffObj},{BuffObj, IntObj, IntObj, PkgObj})
    // Switch based on which unique function identifier was passed in
    switch(Arg0)
    {
        // First function identifier
        case(ToUUID("893f00a6-660c-494e-bcfd-3043f4fb67c0"))
            switch(Arg2)
                // Function 0: Return supported functions, based on revision
                case(0)
                    switch(Arg1)
                        // revision 0: functions 1-4 are supported
                        case(0) {return (Buffer() {0x1F})}
                        // revision 1: functions 1-5 are supported
                        case(1) {return (Buffer() {0x3F})}
                    // revision 2+: functions 1-7 are supported
                    return (Buffer() {0xFF})
                }
                11
                // Function 1:
                //
                case(1)
                    ... function 1 code ...
                   Return(Zero)
                }
                // Function 2:
                11
                case(2)
                    ... function 2 code ...
                    Return(Buffer(){0x00})
                case(3) { ... function 3 code ...}
                case(4) { ... function 4 code ...}
                case(5) { if (LLess(Arg1,1) BreakPoint; ... function 5 code ... }
                case(6) { if (LLess(Arg1,2) BreakPoint; ... function 6 code ... )
                case(7) { if (LLess(Arg1,3) BreakPoint; ... function 7 code ... )
                default {BreakPoint }
```

```
}
    // Second function identifier
    11
    case(ToUUID("107ededd-d381-4fd7-8da9-08e9a6c79644"))
        // Function 0: Return supported functions (there is only one revision)
        //
        if (LEqual(Arg2,Zero))
            return (Buffer() {0x3}) // only one function supported
        // Function 1
        11
        if (LEqual(Arg2,One))
            ... function 1 code ...
            Return(Unicode("text"))
        11
        // Function 2+: Runtime Error
        //
        else
           BreakPoint;
}
11
// If not one of the UUIDs we recognize, then return a buffer
// with bit 0 set to 0 indicating no functions supported.
return(Buffer(){0})
```

9.15 PC/AT RTC/CMOS Devices

Most computers contain an RTC device which also contains battery-backed RAM represented as a linear array of bytes. There is a standard mechanism for accessing the first 64 bytes of non-volatile RAM in devices that are compatible with the Motorola RTC/CMOS device that was in the IBM PC/AT. Newer devices usually contain at least 128 bytes of battery-backed RAM. New PNP IDs were assigned for these devices.

Certain bytes within the battery-backed RAM have pre-defined values. In particular, the time, date, month, year, century, alarm time and RTC periodic interrupt are read-only.

9.15.1 PC/AT-compatible RTC/CMOS Devices (PNP0B00)

The standard PC/AT-compatible RTC/CMOS device is denoted by the PnP ID PNP0B00. If an ACPI platform uses a device that is compatible with this device, it may describe this in its ACPI namespace. ASL may then read and write this as a linear 64-byte array. If PNP0B00 is used, ASL and ACPI operating systems may not assume that any extensions to the CMOS exist.

Note: This means that the CENTURY field in the Fixed ACPI Description Table may only contain values between 0 and 63.

Example:

This is an example of how this device could be described:

```
Device (RTC0) {
   Name(_HID, EISAID("PNP0B00"))
Name
      (_FIX, Package(1) {
EISAID("PNP0B00") }
Name(_CRS, ResourceTemplate() {
   IO(Decode16, 0x70, 0x70, 0x1, 0x2)
   OperationRegion(CMS1, SystemCMOS, 0, 0x40)
   Field(CMS1, ByteAcc, NoLock, Preserve) {
       AccessAs(ByteAcc, 0),
       CM00, 8,
        ,256,
       CM01, 8,
       CM02, 16,
        , 216,
       CM03, 8
    }
```

9.15.2Intel PIIX4-compatible RTC/CMOS Devices (PNP0B01)

The Intel PIIX4 contains an RTC/CMOS device that is compatible with the one in the PC/AT. But it contains 256 bytes of non-volatile RAM. The first 64 bytes are accessed via the same mechanism as the 64 bytes in the PC/AT. The upper 192 bytes are accessed through an interface that is only used on Intel chips. (See <u>82371AB PCI-TO-ISA / IDEXCELERATOR (PIIX4)</u> for details.)

Any platform containing this device or one that is compatible with it may use the PNP ID PNP0B01. This will allow an ACPI-compatible OS to recognize the RTC/CMOS device as using the programming interface of the PIIX4. Thus, the array of bytes that ASL can read and write with this device is 256 bytes long.

Note: This also means that the CENTURY field in the Fixed ACPI Description Table may contain values between 0 and 255.

Example:

This is an example of how this device could be described:

```
Device (RTC0) {
   Name(_HID, EISAID("PNP0B01"))
      (_FIX, Package(1) {
Name
EISAID("PNP0B01") }
   Name(_CRS, ResourceTemplate() {
       IO(Decode16, 0x70, 0x70, 0x1, 0x2)
       IO(Decode16, 0x72, 0x72, 0x1, 0x2)
   }
   OperationRegion(CMS1, SystemCMOS, 0, 0x100)
   Field(CMS1, ByteAcc, NoLock, Preserve) {
       AccessAs(ByteAcc, 0),
       CM00, 8,
        ,256,
       CM01, 8,
       CM02, 16,
        , 224,
       CM03, 8,
        , 184,
       CENT, 8
```

9.15.3 Dallas Semiconductor-compatible RTC/CMOS Devices (PNP0B02)

Dallas Semiconductor RTC/CMOS devices are compatible with the one in the PC/AT, but they contain 256 bytes of non-volatile RAM or more. The first 64 bytes are accessed via the same mechanism as the 64 bytes in the PC/AT. The upper bytes are accessed through an interface that is only used on Dallas Semiconductor chips.

Any platform containing this device or one that is compatible with it may use the PNP ID PNP0B02. This will allow an ACPI-compatible OS to recognize the RTC/CMOS device as using the Dallas Semiconductor programming interface. Thus, the array of bytes that ASL can read and write with this device is 256 bytes long.

Description of these devices is similar to the PIIX4 example above, and the CENTURY field of the FADT may also contain values between 0 and 255.

9.16 User Presence Detection Device

The following section illustrates the operation and definition of the control method-based User Presence Detection (UPD) device.

The user presence detection device can optionally support power management objects (e.g. _PS0, _PS3) to allow the OS to manage the device's power consumption.

The Plug and Play ID of an ACPI control method user presence detection device is ACPI000F.

Table 9-245 User Presence Detection Device

Object	Description
_UPD	The current user presence detection reading. [Required]
_UPP	User presence detection polling frequency in tenths of seconds. [Optional]

9.16.1 _UPD (User Presence Detect)

This control method returns the user presence detection reading, indicating whether or not the user is currently present from the perspective of this sensor. Three states are currently defined for UPD sensor readings: *absent*, *present*, and *unknown*, represented by the values 0x00, 0x01, and 0xFF respectively. The unknown state is used to convey that the sensor is currently unable to determine user presence due to some environmental or other transient factor. All other values are reserved.

Arguments:

None

Return Value:

An **Integer** containing the user presence code:

0x00 – Absent: A user is not currently detected by this sensor.

0x01 -Present: A user is currently detected by this sensor.

0xFF - *Unknown*: The sensor is currently unable to determine if a user is present or absent.

9.16.2 UPP (User Presence Polling)

This optional object evaluates to a *recommended* polling frequency (in tenths of seconds) for this user presence sensor. A value of zero – or the absence of this object when other UPD objects are defined – indicates that the OS does not need to poll the sensor in order to detect meaningful changes in user presence (the hardware is capable of generating asynchronous notifications).

Arguments:

None

Return Value:

An **Integer** containing the recommended polling frequency in tenths of seconds. A value of zero indicates that polling is not required.

The use of polling is allowed but strongly discouraged by this specification. OEMs should design systems that asynchronously notify OSPM whenever a meaningful change in user presence occurs—relieving the OS of the overhead associated with polling.

This value is specified as tenths of seconds. For example, a value of 10 would be used to indicate a 1 second polling frequency. As this is a recommended value, OSPM will consider other factors when determining the actual polling frequency to use.

9.16.3 User Presence Sensor Events

To communicate changes in user presence to OSPM, AML code should issue a **Notify**(upd_device, 0x80) whenever a change in user presence has occurred. The OS receives this notification and calls the _UPD control method to determine the current user presence status.

UPD notifications should be generated whenever a transition occurs between one of the user presence states (absent, present, or unknown) – but at a level of granularity that provides an appropriate response without overly taxing the system with unnecessary interrupts.

9.17 I/O APIC Device

This optional device describes a discrete I/O APIC device that is not bus enumerated (e.g., as a PCI device). Describing such a device in the ACPI namespace is only necessary if hot plug of this device is supported. If hot plug of this device is not supported, an MADT I/O APIC (Section 5.2.12.3,"I/O APIC Structure") entry or I/O SAPIC (Section 5.2.12.9, "I/O SAPIC Structure") entry is sufficient to describe this device.

An I/O APIC device is an I/O unit that complies with either of the APIC interrupt models supported by ACPI. These interrupt models are described Section 5.2.12.3, "I/O APIC Structure" and Section 5.2.12.9, "I/O SAPIC Structure". If the device is an I/O unit that complies with the APIC interrupt model, it is declared using the ACPI000A identifier. If this device is an I/O unit that complies with the SAPIC interrupt model, it is declared using the ACPI000B identifier. If this device complies with both the APIC and SAPIC interrupt models (I/OxAPIC), it is declared using the ACPI0009 identifier.

An I/O APIC device declared using any of the above identifiers must contain a _GSB object as defined in Section 6.2.7, "_GSB (Global System Interrupt Base)" to report its Global System Interrupt Base. It must also contain a _CRS object that reports the base address of the I/O APIC device. The _CRS object is required to contain only one resource, a memory resource pointing to the I/O APIC register base.

Note: Because the _CRS and _GSB methods provide sufficient information, it is not necessary to provide _MAT under an I/O APIC device.

For an I/O APIC device that is described both in the MADT and in the namespace, the base address described in the MADT entry must be the same as the base address in the IO APIC device _CRS at boot time. OSPM must use the information from the MADT until such a time as the _CRS and _GSB methods in the namespace device can be processed. At this point OSPM must ignore the MADT entry.

9.18 Time and Alarm Device

The following sections define the operation and definition of the optional control method-based Time and Alarm device, which provides a hardware independent abstraction and a more robust alternative to the Real Time Clock (RTC), See Section 9.15, "PC/AT RTC/CMOS Devices".

The time capabilities of the time and alarm device maintain the time of day information across platform power transitions, and keep track of time even when the platform is turned off. It is

ACPI-Defined Devices and Device-Specific Objects

expected that the time on the platform will be consistent when different firmware interfaces are used to query the platform time. For example, a UEFI call to get the time should return the same time as if the OSPM used the time and alarm device at the same point in time.

The Time and Alarm device can optionally support power management objects (e.g. _PS0, _PS3) to allow the OS to manage the device's power consumption.

The Time andAlarm device must support control method _PRW for being enabled to wake up the system. It might support _DSW or _PSW to provide the functionality to enable or disable the device's ability to wake a sleep system. On Hardware-reduced ACPI platforms, _PRW is only required if the device depends on ACPI-defined power resources. _PRW's GPEInfo structure is ignored by OSPM. For enabling Wakeup, _DSW and _SxW are used, and the wakeup event is signaled by the GPIO-signaled ACPI event mechanism (Section 5.6.5).

The Plug and Play ID of the Time and Wake Alarm device is ACPI000E.

Table 9-246	lime and A	Alarm L	Jevice
-------------	------------	---------	--------

Object	Description
_GCP	Get the capabilities of the time and alarm device
_GRT	Get the Real time
_SRT	Set the Real time
_GWS	Get Wake status
_CWS	Clear Wake Status
_STP	Sets expired timer wake policy for the specified timer.
_STV	Sets the value in the specified timer.
_TIP	Returns the current expired timer policy setting of the specified timer.
_TIV	Returns the remaining time of the specified timer.

9.18.10verview

The Time and Alarm device provides an alternative to the real time clock (RTC), which is defined as a fixed feature hardware device. The wake timers allow the system to transition from the S3 (or optionally S4/S5) state to S0 state after a time period elapses. In comparison with the Real Time Clock (RTC) Alarm, the Time and Alarm device provides a larger scale of flexibility in the operation of the wake timers, and allows the implementation of the time source to be abstracted from the OSPM.

Time and Alarm device provides the OSPM with a firmware abstraction of time and alarm services that can be applicable to a variety of hardware designs. The methods for setting and getting real time provide an alternative to the (RTC). In addition the device provides two different levels of wake services, depending on the platform capabilities, AC/DC wake or AC wake.

Time and Alarm devices that implement AC/DC wake service contain two programmable timers that can be configured to wake the system depending on the platform's current power source (AC or DC) when the timers expire. The two timers, which are referred to as the AC timer and the DC timer, are independent in that they are individually programmable and applicable without interfering each other. Each of the timers can be programmed with the number of seconds to elapse from the time the timer is programmed until a wake is requested. When a timer expires, the Time and Alarm device

decides whether to wake the system based on the current power source. If the current power source is consistent with the timer type that expired, a wake signal will be asserted. Otherwise, the wake signal will not be asserted.

Time and Alarm devices that implement the AC only (power independent) wake contain one programmable timer that can be configured to wake up the system regardless of the platform's power source when the timer expires. To simplify the programming interface the AC wake will use the AC timer portion of the AC/DC wake; writes to the DC timer when AC only wake is supported will be ignored.

To simplify the programming interface for the time and alarm device, timer expiration events will persist. This means that if the OSPM programs a wake timer that expires before the OSPM completes the transition into S3 (or S4/S5 if supported) the time and alarm device will wake the system immediately after the OSPM completes the transition. Figure 9-51 illustrates this behavior.




Figure 9-50 Persistence of expired timer events

The time and alarm device will provide the OSPM with an interface to query the status of the wake timers and discover what timers have expired. This interface enables the OSPM to discover the wake source. The status of wake timers can be reset by setting the wake alarm; the OSPM may clear the alarm status using the clear wake status method. All expired wake timer must be cleared if the OSPM requires the platform to stay in S3 (S4/S5), otherwise the expired timers will immediately wake up the system.

For the AC/DC wake services, and in case the current power source is inconsistent with the timer type that expires, an expired timer wake policy value, in units of seconds, is defined that enables the time and alarm device to wake the system when the power source corresponding to the expired timer becomes active (wake either immediately, after some time period, or never). The expired timer wake policy is applicable only on devices that support AC/DC wake and only when the timer expires and

ACPI-Defined Devices and Device-Specific Objects

the power source is not consistent with the timer type. The expired timer policy is applied in conjunction with expired timer persistence described earlier.

For example, if a mobile platform programs the AC timer to be 2 hours long and DC timer to be 4 hours long and then transitions from the S0 state to S3 state at 1:00 AM, the AC timer is set to expire at 3:00 AM and the DC timer is set to expire at 5:00 AM. For the AC Timer, a expired timer wake policy value is programmed as 60 seconds.

If the platform is unplugged from AC power at 1:40 AM and remains unplugged, the Time and Alarm Device will not wake up the system at 3:00 AM. If the platform remains on DC power until 5:00 AM when the DC timer expires, a wake signal will then be asserted. The following graph illustrates the above example.




Figure 9-51 System transitions with WakeAlarm -- Timer

If the AC power is plugged in again at 4:00 AM, then the system will be woken up at 4:01 AM due to the AC expired timer wake policy value setting. The following graph illustrates this.




Figure 9-52 System transitions with WakeAlarm -- Policy

The Time and Alarm device can support a range of services, the OSPM evaluates the _GCP object to get the supported capabilities of the device. If the capabilities indicate that the device supports time services, the OSPM evaluates the _GRT and _SRT objects to get and set time respectively.

If alarm services are supported by the device, the OSPM evaluates the _STV object to program both the AC and DC timer values. The values, which are in units of seconds, indicate the elapsed time before the timer expires. OSPM evaluates the _TIV object to read the current AC and DC timer values (seconds remaining until expiration).

OSPM evaluates the _STP object to set timer policies for both the AC and DC timers OSPM reads the current timer policy by evaluating the _TIP object, which return policy settings for both the AC and DC timer.

The OSPM evaluates the _GWS object to identify expired timers that may have waked the platform. The OSPM must evaluate the _CWS object to clear any expired timer events that can prevent the system from performing a sleep transition according the expired timer wake policy, and the expired timer persistence described above.

The Time and Alarm device, if implemented with wake support, must support waking up the system from S3. Waking from S4/S5 support is optional. If the Time and Alarm device support AC/DC wake, Wake support for any power state must be made available on both AC and DC power sources.

9.18.2 _GCP (Get Capability)

This object is required and provides the OSPM with a bit mask of the device capabilities. The device can implement the time function in addition to the wake function. The capabilities bitmask will indicate to the OSPM what support is implemented. If the platform implements both AC and DC timers then it is capable of waking up based on the power source

Arguments: (0)

Return Value:

A 32-bit integer containing a result bitmask as follows:

```
Bit 0 - 1 = AC wake implemented, 0 = not supported
Bit 1 - 1 = DC wake implemented, 0 = not supported
Bit 2 - 1 = Get/Set real time features implemented, 0 = not supported
```

Bit 3 - 1 = Real time accuracy in milliseconds, 0 = Real time accuracy in seconds

Bit 4 to 31 are reserved and must be 0.

9.18.3 _GRT (Get Real Time)

This object is required if the capabilities bit 2 is set to 1. The OSPM can use this object to get time. The return value is a buffer containing the time information as described below.

Arguments: (0)

Return Value:

A buffer containing the time information, in the following format

9.18.4 _SRT (Set Real Time)

This object is required if the capabilities bit 2 is set to 1. The OSPM can use this object to set the time. The argument is a buffer containing the time information, as defined above.

Arguments: (1)

A buffer containing the time information, in the following format:

```
Buffer(){
WORD Year;
                 // 1900 - 9999
BYTE Month;
                 // 1 - 12
                 // 1 - 31
BYTE Day;
                 // 0 - 23
BYTE Hour;
                // 0 - 59
BYTE Minute;
BYTE Second;
                  // 0 - 59
BYTE Pad1;
WORD milliseconds, // 1-1000
WORD TimeZone; // -1440 to 1440 or 2047 (unspecified)
BYTE Daylight;
BYTE Pad2[3]; // Reserved, must be zero
```

Return Value:

An Integer:

0 - success

0xFFFFFFFF Failed

Note: Time is maintained using a battery backed time device (e.g. a real time clock)

Note: The time will always be local time; the time zone value can be used to determine the offset from UTC.

Note: Time zone field is the number of minutes that the local time lags behind the UTC time. (i.e. time zone = UTC - local time). The time zone is in 2's complement format.

Note: Time zone value of 2047, means that time zone value is not specified, and no relation to UTC can be inferred.

Note: Daylight is a bitmask containing the daylight savings time information for the time, as follows:

Bit0: 1 = the time is affected by daylight savings time, 0= time is not affected by daylight savings. This value does not indicate that the time has been adjusted for daylight savings time. It indicates only that it should be adjusted when the time enters daylight savings time.

Bit1: 1= the time has been adjusted for daylight savings time, 0= the time hasn't been adjusted for daylight savings.

All other bits must be zero.

When entering daylight saving time, if the time is affected, but hasn't been adjusted (DST = 1), use the new calculation:

- The date/time should be increased by the appropriate amount.
- The TimeZone should be decreased by the appropriate amount (EX: +480 changes to +420 when moving from PST to PDT).
- The Daylight value changes to 3.

When exiting daylight saving time, if the time is affected and has been adjusted (DST = 3), use the new calculation:

- The date/time should be decreased by the appropriate amount.
- The TimeZone should be increased by the appropriate amount.
- The Daylight value changes to 1.

9.18.5 _GWS (Get Wake alarm status)

This object is required and enables the OSPM to read the status of wake alarms. Expired wake timers will wake the platform even if the transition to a sleep state was completed after the wake timer has expired. This method enables the OSPM to retrieve the status of wake timers and clear any of them if needed.

Arguments: (1)

```
Arg0 - Timer Identifier (Integer (DWORD)): indicates the timer to be cleared: 0x00000000 - AC Timer 0x00000001 - DC Timer
```

Return Value:

An Integer (DWORD) containing current expired timers in bit field

```
Bit 0- 1 = timer expired, 0 = \text{timer did not expired}
```

Bit 1- 1= timer caused a platform wake, 0 = timer did not cause a platform wake

Bit 2-31 reserved and should be 0.

9.18.6 _CWS (Clear Wake alarm status)

This object is required and enables the OSPM to clear the status of wake alarms. Expired wake timers will wake the platform even if the transition to a sleep state was completed after the wake timer has expired. This method enables the OSPM to clear the status of expired wake timers.

Arguments: (1)

```
Arg0 - Timer Identifier (Integer (DWORD)): indicates the timer to be cleared: 0x00000000 - AC Timer 0x00000001 - DC Timer
```

Return Value:

An Integer (DWORD) containing current expired timer wake policy:

```
0x00000000 - Success
0x00000001 - Failure
```

9.18.7 STP (Set Expired Timer Wake Policy)

This object is required and sets the expired timer wake policy. The policy is applied when a corresponding timer expired but the wake signal was not asserted as a result of the power source. The platform accumulates elapsed time on the power source and asserts the wake signal when the elapsed timer on the power source exceeds the expired timer wake policy value. Power source transitions do not reset the expired timer wake policy values. When the Wake Alarm device asserts the wake, the expired timer wake policy values of both the AC timer and DC timer are reset to 0xFFFFFFFF automatically by hardware.

Arguments: (2)

Arg0 – TimerIdentifier (**Integer**(DWORD)): indicates the timer to be set:

```
0x00000000 – AC Timer
0x00000001 – DC Timer
```

Arg1 – ExpiredTimerWakePolicy (**Integer**(DWORD)): indicates the expired timer wake policy:

0x00000000 – The timer will wake up the system instantly after the power source changes.

0x00000001 - 0xFFFFFFE: time between the power source changes and the timer wakes up the system (in units of second).

0xFFFFFFF – The timer will never wake up the system after the power source changes.

Return Value:

An **Integer** containing a result code as follows:

0x00000000 – Succeeded to set the expired timer wake policy.

0x00000001 – Failed to set the timer policy. Actual timer policy unknown.

9.18.8 _STV (Set Timer Value)

This object is required and sets the timer to the specified value. As defined in _TIV, the value indicates the number of seconds between the time when the timer is programmed and the time when it expires. When the Wake Alarm device asserts the wake signal, the timer value is automatically reset to 0xFFFFFFFF (disabled).

Arguments: (2)

Arg0 – TimerIdentifier (**Integer** (DWORD)): indicates the timer to be set:

0x00000000 - AC Timer

0x00000001 - DC Timer

Arg1 – TimerValue (Integer): indicates the value to be set.

Return Value:

An Integer containing a result code as follows:

0x00000000 - Succeeded to set timer value.

0x00000001 – Failed to set timer value. Actual timer value unknown.

9.18.9 _TIP (Expired Timer Wake Policy)

This object is required and returns the current expired timer wake policy setting of the specified timer.

Arguments: (1)

Arg0 – TimerIdentifier (**Integer** (DWORD)): indicates the timer to be read:

0x00000000 - AC Timer

0x00000001 - DC Timer

Return Value:

An **Integer** (DWORD) containing current expired timer wake policy:

0x00000000 – The timer will wake up the system instantly after the power source changes

ACPI-Defined Devices and Device-Specific Objects

0x00000001 – 0xFFFFFFE: Time between the power source changes and the timer wakes up the system (in units of seconds)

0xFFFFFFF - The timer will never wake up the system after the power source changes

9.18.10 _TIV (Timer Values)

This object is required and returns the remaining time of the specified timer before it expires.

Arguments: (1)

Arg0 – TimerIdentifier (**Integer**(DWORD)): indicates the timer to be read:

0x00000000 - AC Timer

0x00000001 - DC Timer

Return Value:

An **Integer** containing the current timer value. A value of 0xFFFFFFF indicates that the timer is disabled.

9.18.11 ACPI Wakeup Alarm Events

The Wake Alarm, device as a generic hardware, supports control methods _PSW and _PRW to wake up the system and issues a Notify(<device>, 0x2) on the wakeup alarm device.

9.18.12 Relationship to Real Time Clock Alarm

Though both of the devices support wakeup timers to wake up system from sleeping state, they work independently. The Real Time Clock Alarm is defined as a fixed feature hardware whereas Time and Alarm device is defined as a generic hardware and can replace or coexist with the real time clock. OSPM may choose which device to utilize to provide timed wake capability.

9.18.13 Time and Alarm device as a replacement to the RTC

The Time and Alarm device can be an alternative to the RTC on some platforms where the legacy RTC hardware is not available, on these platforms the OSPM can use the Time and Alarm device to obtain time and set wake alarms. For platforms that don't require AC/DC wake service (e.g. a platform that have one power source only) the AC timer can be used to provide all the functions that were traditionally provided by the RTC. Using the capabilities object the Time and Alarm device can provide a scalable range of services to the OSPM.

9.18.14 Relationship to UEFI time source

The Time and Alarm device must be driven from the same time source as UEFI time services. This ensures that the platform has a consistent value of real time (time of day) and wake alarms. The OSPM can interact with this value using either ACPI or UEFI.

• OSPM must use only one runtime interface to configure/query the platform alarm(s); undefined behavior may occur if the two wakeup interfaces are used on the same hardware.

• If OSPM is trying to set an alarm using EFI runtime services, the alarm should be honored regardless of the power source (i.e. if the platform has an independent timer for each power source, they should both be configured with that alarm).

9.18.15 Example ASL code

The following ASL code serves as an example of how the Time and Alarm Device could be implemented. It is beyond the capability and the scope of this specification to provide a complete hardware implementation example.

Example 1: Define an ACPI Wake Alarm device

```
Device(\_SB.AWAK){
Name(_HID, "ACPI000E") //device ID
Name(PRW, Package(){...})//enable or disable to wake up the system
OperationRegion(CMOP, EmbeddedControl, ...)
Field(CMOP, ByteAcc, ...){
...... //timer status and policies
Method(_GCP) {
Return (0x03)
                      //Both AC and DC alarms are implemented; Time capability is NOT supported
Method(_STP, 2){
If(LEqual(Arg0, 0) {
Store(Arg1, ...)
                     //Set AC timer policy
Else {
Store(Arg1, ...) //Set DC timer policy
Return(0)
Method(_TIP, 1){
If(LEqual(Arg0, 1) {
Store(..., Local0) //Get DC timer policy
Else {
Store(..., Local0) //Get AC timer policy
Return (Local0)
Method(_STV, 2){
If(LEqual(Arg0, 0) {
Store(Arg1, ...)
                     //Set AC timer value
Else {
Store(Arg1, ...) //Set DC timer value
Return(0)
Method(_TIV, 1){
If(LEqual(Arg0, 1) {
Store(..., Local0) //Get DC timer value
Else {
Store(..., Local0)
                    //Get AC timer value
Return (Local0)
```

```
Method(_GWS, 1){
If(LEqual(Arg0, 1) {
Store(..., Local0)
                      //Get DC timer wake status
Else {
Store(..., Local0) //Get AC timer wake status
Return (Local0)
Method(_CWS, 2){
If(LEqual(Arg0, 0) {
Store(0, ...)
                      //Clear AC Wake status
Else {
Store(0, ...)
                      //Clear DC Wake status
Return(0)
                      // end of ACPI Wake Alarm device object
                     // Root level event handlers
Scope(\_GPE) {
Method(_Lxx){
Store(One, ...)
Notify(\LSB.AWA, 0x2) //notify the OSPM of device wake
                      // end of \_GPE scope
```

Example 2: Define an ACPI Real Time device on a HW-Reduced ACPI platform

```
Device(\_SB.I2C1)
                      //The controller used to access the RTC hardware
    Name (_HID, ...)
    \ldots // Other objects required for this I2C controller
    // Track status of SPB OpRegion availability for this controller
    Name(AVBL, 0)
    Method(_REG,2)
        /* 9 is the OpRegion type for SPB. (8 == GPIO, etc) */
       If (Lequal(Arg0, 9))
 {
           Store(Arg1, ^AVBL)
    }
Device(\_SB.TAAD) //The Time and Alarm Device
    Name (_HID, "ACPI000E")
    Scope(\_SB.I2C1)
                      //OpRegion declaration must appear under the controller
        OperationRegion(TOP1, GenericSerialBus, 254, 0x100)
       Field(TOP1, BufferAcc, NoLock, Preserve)
           Connection(I2CSerialBus(0x4a,,400000,,"\LSB.I2Cl",,,,)), //Connection to the
controller for the following field accesses
           AccessAs(BufferAcc, AttribWord),
                                                  //AccessProtocol for the following field(s)
           Y, 8,
           AccessAs(BufferAcc, AttribByte),
           M, 8,
           D, 8,
```

ACPI-Defined Devices and Device-Specific Objects

```
н, 8,
            Mi,8,
            S, 8,
            P, 8,
            AccessAs(BufferAcc, AttribWord),
            Ms, 8,
            Tz, 8,
            AccessAs(BufferAcc, AttribByte),
            D1, 8,
            P2, 8
        }
    Method (_GCP, 0x0, NotSerialized)
                                               //Implements Real Time interface, but no alarms
        Return(0x4)
    Method(_GRT, 0x0, NotSerialized)
        If(LNotEqual(\_SB.TC1.AVBL, 1))
                                              // Verify that SPB OpRegion is available for this
access
 {
            Return(0)
        Name(BUFF, Buffer(4){})
                                              // Create SerialBus data buffer as BUFF
        CreateByteField(BUFF, 0x00, STAT)  // STAT = Status (Byte)
CreateWordField(BUFF, 0x02, DATA)  // DATA = Data (Byte)
        \label{eq:name_bulk} Name(BUF2,Buffer(0x10)\{\}) \qquad // \mbox{ Create buffer to hold the Real Time structure as BUF2 CreateWordField(BUF2, 0x0,Y)} \qquad // \mbox{ year}
        CreateByteField(BUF2,0x2,M)
                                               //Month
                                          //Dl
        CreateByteField(BUF2,0xc,Dl)
        CreateByteField(BUF2,0xd,P2)
                                             //Pad2
        Store(\S B.I2C1.Y, BUFF) //Get each member from the OpRegion and store in the structure
        Store(DATA,Y)
        Store(\_SB.I2C1.M, BUFF)
        Store(DATA,M)
        Store(\_SB.I2C1.Dl, BUFF)
        Store(DATA,Dl)
        Store(\_SB.I2C1.P2, BUFF)
        Store(DATA, P2)
                                             // Success -> return what was last in buffer
        Return(BUF2)
    Method(_SRT,0x1, NotSerialized)
        Name(BUFF, Buffer(4){})
                                              // Create SerialBus data buffer as BUFF
        CreateByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)
        CreateWordField(BUFF, 0x02, DATA) // DATA = Data (Byte)
 // Verify that SPB OpRegion is available for this access
        If(LNotEqual(\_SB.I2C1.AVBL, 1))
 {
            Return(0)
        CreateWordField(Arg0,0x0,Y) //Create Fields to access each member of the input data
 . . .
        CreateByteField(Arg0,0xd,P2)
 Store(Store(Y, \_SB.I2C1.Y), BUFF)
                                            //Store each input member into the hardware, and
                                             //set the transaction status into BUFF
        If(LEqual(STAT, 0x00))
                                             //Transaction was _NOT_successful
 {
```

ACPI-Defined Devices and Device-Specific Objects

10

Power Source and Power Meter Devices

This section specifies the battery, AC adapter, and power source device objects OSPM uses to manage power resources, as well as the power meter device objects OSPM uses to measure power consumption.

A battery device is required to either have a Smart Battery subsystem or a Control Method Battery interface as described in this section. OSPM is required to be able to connect and manage a battery on either of these interfaces. This section describes these interfaces.

In the case of a compatible ACPI Smart Battery Table, the Definition Block needs to include a Bus/Device package for the SMB-HC. This will install an OS-specific driver for the SMBus, which in turn will locate the components of the Smart Battery subsystem. In addition to the battery or batteries, the Smart Battery subsystem includes a charger and a manager device to handle subsystems with multiple batteries.

The Smart Battery System Manager is one implementation of a manager device that is capable of arbitrating among the available power sources (AC power and batteries) for a system. It provides a superset of the Smart Battery Selector functionality, such as safely responding to power events (AC versus battery power), inserting and removing batteries and notifying the OS of all such changes. Additionally, the Smart Battery System Manager is capable of handling configurations including simultaneous charging and discharging of multiple batteries. Unlike the Smart Battery Selector that shares responsibility for configuring the battery system with OSPM, the Smart Battery System Manager alone controls the safe configuration of the battery system and simply issues status changes to OSPM when the configuration changes. Smart Battery System Manager is the recommended solution for handling multiple-battery systems.

A Power Meter device is the logical representation of a platform sensor that measures the power consumption of one or more devices in the system. A basic platform implementation implements interfaces that query the current power consumption and get the currently configured power consumption hardware limit, while more advance power meter device implementations provide interfaces that support OSPM configurable power consumption trip points that trigger SCI events, or enable configuration of the underlying hardware to enforce a hard limit on the maximum amount of power that can be consumed.

10.1 Smart Battery Subsystems

The Smart Battery subsystem is defined by the:

- System Management Bus Specification (SMBS)
- Smart Battery Data Specification (SBDS)
- Smart Battery Charger Specification (SBCS)
- Smart Battery System Manager Specification (SBSM)
- Smart Battery Selector Specification (SBSS)

Power Source and Power Meter Devices

An ACPI-compatible Smart Battery subsystem consists of:

- An SMB-HC (CPU to SMB-HC) interface
- At least one Smart Battery
- A Smart Battery Charger
- Either a Smart Battery System Manager or a Smart Battery Selector if more than one Smart Battery is supported

In such a subsystem, a standard way of communicating with a Smart Battery and Smart Battery Charger is through the SMBus physical protocols. The Smart Battery System Manager or Smart Battery Selector provides event notification (battery insertion/removal, and so on) and charger SMBus routing capability for any Smart Battery subsystem. A typical Smart Battery subsystem is illustrated below:




Figure 10-53 Typical Smart Battery Subsystem (SBS)

SMBus defines a fixed 7-bit slave address per device. This means that all batteries in the system have the same address (defined to be 0xB). The slave addresses associated with Smart Battery subsystem components are shown in the following table.

Table 10-247 Example SMBus Device Slave Addresses

SMBus Device Description	SMBus Slave Address (A0-A6)
SMBus Host Slave Interface	0x8
Smart Battery Charger/Charger Selector or Charger System Manager	0x9
Smart Battery System Manager or Smart Battery Selector	0xA
Smart Battery	0xB

Each SMBus device has up to 256 registers that are addressed through the SMBus protocol's *Command* value. SMBus devices are addressed by providing the slave address with the desired register's *Command* value. Each SMBus register can have non-linear registers; that is, command register 1 can have a 32-byte string, while command register 2 can have a byte, and command register 3 can have a word.

The SMBus host slave interface provides a standard mechanism for the host CPU to generate SMBus protocol commands that are required to communicate with SMBus devices (in other words, the Smart Battery components). ACPI defines such an SMB-HC that resides in embedded controller address space; however, an OS can support any SMB-HC that has a native SMB-HC device driver.

- Event notification for battery insertion and removal
- Event notification for AC power connected or disconnected
- Status of which Smart Battery is communicating with the SMB-HC
- Status of which Smart Battery(s) are powering the system
- Status of which Smart Battery(s) are connected to the charger
- Status of which Smart Batteries are present in the system

- Event notification when the Smart Battery System Manager switches from one power source to another
- Hardware-switching to an alternate Smart Battery when the Smart Battery supplying power runs low
- Hardware switching between battery-powered and AC-powered powered operation

•

The Smart Battery System Manager function can reside in a standalone SMBus slave device (Smart Battery System Manager that responds to the 0xA slave address), may be present within a smart charger device (Smart Battery Charger that responds to the 0x9 slave address), or may be combined within the embedded controller (that responds to the 0xA slave address). If both a Smart Battery Charger and a standalone Smart Battery System Manager are present in the same Smart Battery subsystem, then the driver assumes that the standalone Smart Battery System Manager is wired to the batteries.

The Smart Battery charger is an SMBus device that provides a standard programming model to control the charging of Smart Batteries present in a Smart Battery subsystem. For single battery systems, the Smart Battery Charger is also responsible for notifying the system of the battery and AC status.

The Smart Battery provides intelligent chemistry-independent power to the system. The Smart Battery is capable of informing the Smart Battery charger of its charging requirements (which provides chemistry independence) and providing battery status and alarm features needed for platform battery management.

10.1.1 ACPI Smart Battery Status Change Notification Requirements

The Smart Battery System Manager, the Smart Battery Selector, and the Smart Battery Charger each have an optional mechanism for notifying the system that the battery configuration or AC status has changed. ACPI requires that this interrupt mechanism be through the SMBus Alarm Notify mechanism.

For systems using an embedded controller as the SMBus host, a battery system device issues a status change notification by either mastering the SMBus to send the notification directly to the SMBus host, or by emulating it in the embedded controller. In either case, the process is the same. After the notification is received or emulated, the embedded controller asserts an SCI. The source of the SCI is identified by a GPE that indicates the SCI was caused by the embedded controller. The embedded controller's status register alarm bit is set, indicating that the SMBus host received an alarm message. The Alarm Address Register contains the address of the SMBus device that originated the alarm and the Alarm Data Registers contain the contents of that device's status register.

10.1.1.1 Smart Battery Charger

This requires a Smart Battery Charger, on a battery or AC status change, to generate an SMBus Alarm Notify. The contents of the Smart Battery Charger's ChargerStatus() command register (0x13) is placed in the embedded controller's Alarm Data Registers, the Smart Battery Charger's

slave address 1 (0x09) is placed in the embedded controller's Alarm Address Register and the EC's Status Register's Alarm bit is set. The embedded controller then asserts an SCI.

10.1.1.2 Smart Battery Charger with optional System Manager or Selector

A Smart Battery Charger that contains the optional System Manager or Selector function (as indicated by the ChargerSpecInfo() command register, 0x11, bit 4) is required to generate an SMBus Alarm Notify on a battery or AC status change. The content of the Smart Battery Charger with an optional System Manager, the BatterySystemState() command register (0x21) (or in the case of an optional Selector, the SelectorState() (0x01)), is placed in the EC's Alarm Data Registers, the Smart Battery Charger's slave address (0x09) is placed in the embedded controller's Alarm Address Register, and the embedded controller's Status Register's Alarm bit is set. The embedded controller then asserts an SCI.

10.1.1.3 Smart Battery System Manager

The Smart Battery System Manager is required to generate an SMBus Alarm Notify on a battery or AC status change. The content of the Smart Battery System Manager's BatterySystemState() command register (0x01) is placed in the EC's Alarm Data Registers, the Smart Battery System Manager's slave address (0x0A) is placed in the EC's Alarm Address Register, and the embedded controller's Status Register's Alarm bit is set. The embedded controller then asserts an SCI.

10.1.1.4 Smart Battery Selector

The requirements for the Smart Battery Selector are the same as the requirements for the Smart Battery System Manager, with the exception that the contents of the SelectorState() command register (0x01) are used instead of BatterySystemState(). The Smart Battery Selector is a subset of the Smart Battery System Manager and does not have the added support for simultaneous charge/discharge of multiple batteries. The System Manager is the preferred implementation.

10.1.2 Smart Battery Objects

The Smart Battery subsystem requires a number of objects to define its interface. These are summarized below:

Table 10-248 Smart Battery Objects

Object	Description
_HID	This is the hardware ID named object that contains a string. For Smart Battery subsystems, this object returns the value of "ACPI0002." This identifies the Smart Battery subsystem to the Smart Battery driver.
_SBS	This is the Smart Battery named object that contains a DWORD. This named object returns the configuration of the Smart Battery.

^{1.} Notice that the 1.0 SMBus protocol specification is ambiguous about the definition of the "slave address" written into the command field of the host controller. In this case, the slave address is actually the combination of the 7-bit slave address and the Write protocol bit. Therefore, bit 0 of the initiating device's slave address is aligned to bit 1 of the host controller's slave command register, bit 1 of the slave address is aligned to bit 2 of the controller's slave command register, and so on.

10.1.3 _SBS (Smart Battery Subsystem)

The _SBS control method returns the configuration of the Smart Battery subsystem. This named object returns a DWORD value with a number from 0 to 4. If the number of batteries is greater than 0, then the Smart Battery driver assumes that a Smart Battery System Manager or Smart Battery Selector is present. If 0, then the Smart Battery driver assumes a single Smart Battery and neither a Smart Battery System Manager nor Smart Battery Selector is present.

The DWORD returned by SBS is encoded as follows:

- 0 Maximum of one Smart Battery and no Smart Battery System Manager or Smart Battery Selector.
- 1 Maximum of one Smart Battery and a Smart Battery System Manager or Smart Battery Selector
- 2 Maximum of two Smart Batteries and a Smart Battery System Manager or Smart Battery Selector.
- 3 Maximum of three Smart Batteries and a Smart Battery System Manager or Smart Battery Selector.
- 4 Maximum of four Smart Batteries and a Smart Battery System Manager or Smart Battery Selector.

Arguments:

None

Return Value:

An **Integer** containing the Smart Battery subsystem configuration:

- 0 Maximum 1 Smart Battery, system manager/selector not present
- 1 Maximum 1 Smart Battery, system manager/selector present
- 2 Maximum 2 Smart Batteries, system manager/selector present
- 3 Maximum 3 Smart Batteries, system manager/selector present
- 4 Maximum 4 Smart Batteries, system manager/selector present

The maximum number of batteries is for the entire system. Therefore, if the platform is capable of supporting four batteries, but only two are normally present in the system, then this field should return 4. Notice that a value of 0 indicates a maximum support of one battery and there is no Smart Battery System Manager or Smart Battery Selector present in the system

As the SMBus is not an enumerable bus, all devices on the bus must be declared in the ACPI name-space. As the Smart Battery driver understands Smart Battery, Smart Battery Charger, and Smart Battery System Manager or Smart Battery Selector; only a single device needs to be declared per Smart Battery subsystem. The driver gets information about the subsystem through the hardware ID (which defines a Smart Battery subsystem) and the number of Smart Batteries supported on this subsystem (_SBS named object). The ACPI Smart Battery table indicates the energy levels of the platform at which the system should warn the user and then enter a sleeping state. The Smart Battery driver then reflects these as threshold alarms for the Smart Batteries.

A Smart Battery device declaration in the ACPI namespace requires the _GLK object if potentially contentious accesses to device resources are performed by non-OS code. See <u>Section 6.5.7</u> "_GLK (Global Lock)," for details about the GLK object.

10.1.3.1 Example: Single Smart Battery Subsystem

This section illustrates how to define a Smart Battery subsystem containing a single Smart Battery and charger. The platform implementation is illustrated below:




Figure 10-54 Single Smart Battery Subsystem

In this example, the platform is using an SMB-HC that resides within the embedded controller and meets the ACPI standard for an embedded controller interface and SMB-HC interface. The embedded controller interface sits at system I/O port addresses 0x62 and 0x66. The SMB-HC is at base address 0x80 within embedded controller address space (as defined by the ACPI embedded controller specification) and responds to events on query value 0x30.

In this example the Smart Battery subsystem only supports a single Smart Battery. The ASL code for describing this interface is shown below:

```
Device (ECO) {
   Name (_HID, EISAID("PNP0C09"))
   Name (_CRS,
       ResourceTemplate () {
                                         // port 0x62 and 0x66
           IO (Decode16, 0x62, 0x62, 0, 1),
           IO (Decode16, 0x66, 0x66, 0, 1)
   Name (_GPE, 0)
   Device (SMB0) {
       Name (_HID, "ACPI0001")
                                          // Smart Battery Host Controller
       Name (_EC, 0x8030)
                                          // EC offset (0x80), Ouery (0x30)
       Device (SBS0){
                                          // Smart Battery Subsystem
           Name (_HID, "ACPI0002")
                                         // Smart Battery Subsystem ID
           Name(\_SBS, 0x1)
                                          // Indicates support for one battery
        } // end of SBS0
    } // end of SMB0
} // end of EC
```

10.1.3.2 Multiple Smart Battery Subsystem: Example

This section illustrates how to define a Smart Battery subsystem that contains three Smart Batteries, a Smart Battery System Manager, and a Smart Battery Charger. The platform implementation is illustrated below:




Figure 10-55 Smart Battery Subsystem

In this example, the platform is using an SMB-HC that resides within the embedded controller and meets the ACPI standard for an embedded controller interface and SMB-HC interface. The embedded controller interface sits at system I/O port addresses 0x100 and 0x101. The SMB-HC resides at base address 0x90 within embedded controller address space (as defined by the ACPI embedded controller specification) and responds to events on query value 0x31.

In this example the Smart Battery subsystem supports three Smart Batteries. The Smart Battery Charger and Smart Battery System Manager reside within the embedded controller, meet the Smart Battery System Manager and Smart Battery Charger interface specification, and respond to their 7-bit addresses (0xA and 0x9 respectively). The ASL code for describing this interface is shown below:

```
Device (EC1) {
Name (_HID, EISAID("PNP0C09"))
   Name (_CRS,
       ResourceTemplate () {
                                          // port 0x100 and 0x101
           IO(Decode16, 0x100, 0x100, 0, 2)
   Name (_GPE, 1)
   Device (SMB1) {
       Name (_HID, "ACPI0001")
                                         // Smart Battery Host Controller
       Name (_EC, 0x9031)
Device (SBS1){
                                         // EC offset (0x90), Query (0x31)
                                         // Smart Battery Subsystem
           Name (_HID, "ACPI0002")
                                        // Smart Battery Subsystem ID
           Name (_SBS, 0x3)
                                         // Indicates support for three batteries
       } // end of SBS1
   } // end of SMB1
} // end of EC
```

10.2 Control Method Batteries

The following section illustrates the operation and definition of the Control Method Battery.

10.2.1 Battery Events

The AML code handling an SCI for a battery event notifies the system of which battery's status may have changed. The OS uses the _BST control method to determine the current status of the batteries and what action, if any, should be taken (for more information about the _BST control method, see Section 10.2.2, "Battery Control Methods"). The typical action is to notify applications monitoring the battery status to provide the user with an up-to-date display of the system battery state. But in some cases, the action may involve generating an alert or even forcing a system into a sleeping state. In any case, any changes in battery status should generate an SCI in a timely manner to keep the system power state UI consistent with the actual state of the system battery (or batteries).

Unlike most other devices, when a battery is inserted or removed from the system, the device itself (the battery bay) is still considered to be present in the system. For most systems, the _STA for this device will always return a value with bits 0-3 set and will toggle bit 4 to indicate the actual presence of a battery (see Section 6.3.7, "_STA [Status]"). When this insertion or removal occurs, the AML code handler for this event should issue a **Notify**(battery_device, 0x81) to indicate that the static battery information has changed. For systems that have battery slots in a docking station or batteries that cannot be surprise-removed, it may be beneficial or necessary to indicate that the entire device has been removed. In this case, the standard methods and notifications described in Section 6.3, "Device Insertion, Removal, and Status Objects," should be used.

When the present state of the battery has changed or when the trip point set by the _BTP control method is reached or crossed, the hardware will assert a general purpose event. The AML code handler for this event issues a **Notify**(battery_device, 0x80) on the battery device. This notification is also sent when the Status Flags returned from BMD change.

In the case where the remaining battery capacity becomes critically low, the AML code handler issues a **Notify**(*battery_device*, 0x80) and reports the battery critical flag in the _BST object. The OS performs an emergency shutdown. For a full description of the critical battery state, see <u>Section 3.9.4</u>, "Low Battery Levels."

Sometimes the value to be returned from _BST or _BIF will be temporarily unknown. In this case, the method may return the value 0xFFFFFFFF as a placeholder. When the value becomes known, the appropriate notification (0x80 for _BST or 0x81 for BIF) should be issued, in like manner to any other change in the data returned by these methods. This will cause OSPM to re-evaluate the method—obtaining the correct data value.

When one or more of the status flags returned by the _BMD control method change, AML code issues a **Notify**(*battery_device*, 0x82) on the battery device unless this change occurs during a call to _BMC and the value of the status flags in _BMD match the value passed in to _BMC. If the value of the status bits cannot be set to reflect the action requested by the executing _BMC, the AML code will issue this notification. For example, calling _BMC with bit 0 set to initiate a calibration cycle while AC power is not available will cause AML to issue a **Notify**(*battery_device*, 0x82).

10.2.2 Battery Control Methods

The Control Method Battery is a battery with an AML code interface between the battery and the host PC. The battery interface is completely accessed by AML code control methods, allowing the OEM to use any type of battery and any kind of communication interface supported by ACPI. OSPM requires accurate battery data to perform optimal power management policy and to provide

Power Source and Power Meter Devices

the end user with a meaningful estimation of remaining battery life. As such, control methods that return battery information should calculate this information rather than return hard coded data.

A Control Method Battery is described as a device object. Each device object supporting the Control Method Battery interface contains the following additional control methods. When there are two or more batteries in the system, each battery will have an independent device object in the namespace.

Table 10-249 Battery Control Methods

Object	Description
_BIF	Returns static information about a battery (in other words, model number, serial number, design voltage, and so on).
_BIX	Returns extended static information about a battery (in other words, model number, serial number, design voltage, and so on).
_OSC	OSPM Capabilities conveyance for batteries.
_BMA	Sets the averaging interval of the battery capacity measurement, in milliseconds.
_BMS	Sets the sampling time of the battery capacity measurement, in milliseconds.
_BST	Returns the current battery status (in other words, dynamic information about the battery, such as whether the battery is currently charging or discharging, an estimate of the remaining battery capacity, and so on).
_BTP	Sets the Battery Trip point, which generates an SCI when batterycapacity reaches the specified point.
_PCL	List of pointers to the device objects representing devices powered by the battery.
_STA	Returns general status of the battery (for a description of the _STA control method, see <u>Section 6.3.7</u> , "_STA (Status]").
_BTM	Returns battery estimated runtime at the present average rate of drain, or the runtime at a specified rate.
_BCT	Returns battery estimated charging time.
_BMD	Returns battery information related to battery recalibration and charging control.
_BMC	Control calibration and charging.

A Control Method Battery device declaration in the ACPI namespace requires the _GLK object if potentially contentious accesses to device resources are performed by non-OS code. See <u>Section 6.5.7</u>, "_GLK (Global Lock)," for details about the _GLK object.

10.2.2.1 _BIF (Battery Information)

This object returns the static portion of the Control Method Battery information. This information remains constant until the battery is changed. This object is deprecated in ACPI 4.0. The _BIX object provides expanded battery information and includes all of the information provide by _BIF. See <u>Section 10.2.2.2.</u>, "Battery Information Extended").

Arguments:

None

Return Value:

A **Package** containing the battery information as described below

Return Value Information:

_BIF returns a package in the format below

Table 10-250 BIF Return Package Values

Field	Format	Description
Power Unit	Integer (DWORD)	Indicates the units used by the battery to report its capacity and charge/ discharge rate information to the OS. 0x00000000 – Capacity information is reported in [mWh] and charge/ discharge rate information in [mW]. 0x00000001 – Capacity information is reported in [mAh] and charge/ discharge rate information in [mA].
Design Capacity	Integer (DWORD)	Battery's design capacity. Design Capacity is the nominal capacity of a new battery. The <i>Design Capacity</i> value is expressed as power [mWh] or current [mAh] depending on the <i>Power Unit</i> value. 0x000000000 – 0x7FFFFFFF (in [mWh] or [mAh]) 0xFFFFFFF – Unknown design capacity
Last Full Charge Capacity	Integer (DWORD)	Predicted battery capacity when fully charged. The Last Full Charge Capacity value is expressed as power (mWh) or current (mAh) depending on the Power Unit value. 0x000000000h – 0x7FFFFFFF (in [mWh] or [mAh]) 0xFFFFFFFF – Unknown last full charge capacity
Battery Technology	Integer (DWORD)	0x00000000 - Primary (for example, non-rechargeable) 0x00000001 - Secondary (for example, rechargeable)
Design Voltage	Integer (DWORD)	Nominal voltage of a new battery. 0x000000000 – 0x7FFFFFFF in [mV] 0xFFFFFFF – Unknown design voltage
Design capacity of Warning	Integer (DWORD)	OEM-designed battery warning capacity. See Section 3.9.4, "Low Battery Levels." 0x000000000 - 0x7FFFFFFF in [mWh] or [mAh]
Design Capacity of Low	Integer (DWORD)	OEM-designed low battery capacity. See Section 3.9.4, "Low Battery Levels." 0x000000000 - 0x7FFFFFFF in [mWh] or [mAh]

Field	Format	Description
Battery Capacity Granularity 1	Integer (DWORD)	Battery capacity granularity between low and warning in [mAh] or [mWh]. That is, this is the smallest increment in capacity that the battery is capable of measuring. See note below for more details
Battery Capacity Granularity 2	Integer (DWORD)	Battery capacity granularity between warning and Full in [mAh] or [mWh]. That is, this is the smallest increment in capacity that the battery is capable of measuring. This may be a different value than Battery Capacity Granularity 1 to accommodate systems where the granularity accuracy may change depending on the battery level. See note below for more details.
Model Number	String (ASCIIZ)	OEM-specific Control Method Battery model number
Serial Number	String (ASCIIZ)	OEM-specific Control Method Battery serial number
Battery Type	String (ASCIIZ)	The OEM-specific Control Method Battery type
OEM Information	String (ASCIIZ)	OEM-specific information for the battery that the UI uses to display the OEM information about the Battery. If the OEM does not support this information, this field should contain a NULL string.

Additional Notes:

- A secondary-type battery should report the corresponding capacity (except for Unknown).
- On a multiple-battery system, all batteries in the system should return the same granularity.
- Operating systems prefer these control methods to report data in terms of power (watts).
- On a multiple-battery system, all batteries in the system must use the same power unit.
- The definition of battery capacity granularity has been clarified. For OSPM to determine if systems support the clarified definition of battery capacity granularity, OSPM may evaluate an _OSC method at the battery scope to indicate support for this capability, and for the platform to indicate if it supports these extended capabilities.

10.2.2.2 _BIX (Battery Information Extended)

The _BIX object returns the static portion of the Control Method Battery information. This information remains constant until the battery is changed. The _BIX object returns all information available via the _BIF object plus additional battery information. The _BIF object is deprecated in lieu of _BIX in ACPI 4.0.

Arguments:

None

Return Value:

A Package containing the battery information as described below

Return Value Information:

BIX returns a package in the format below

```
// ASCIIZ is ASCII character string terminated with a 0x00.
 Revision
                                                                     //Integer
 Power Unit
                                                                       //Integer (DWORD)
Design Capacity //Integer (DWORD)
Last Full Charge Capacity //Integer (DWORD)
Battery Technology //Integer (DWORD)
Design Voltage //Integer (DWORD)
Design Capacity of Warning //Integer (DWORD)
Design Capacity of Low //Integer (DWORD)
Cycle Count //Integer (DWORD)
Measurement Accuracy //Integer (DWORD)
Max Sampling Time //Integer (DWORD)
Min Sampling Time //Integer (DWORD)
Max Averaging Interval //Integer (DWORD)
Min Averaging Interval //Integer (DWORD)
 Battery Capacity Granularity 1 //Integer (DWORD)
Battery Capacity Granularity 2 //Integer (DWORD)
 Model Number
                                                                      //String (ASCIIZ)
                                                                     //String (ASCIIZ)
 Serial Number
                                                                      //String (ASCIIZ)
 Battery Type
 OEM Information
                                                                       //String (ASCIIZ)
```

Table 10-251 BIX Return Package Values

Field	Format	Description
Revision	Integer	Current revision is: 0
Power Unit	Integer (DWORD)	 Indicates the units used by the battery to report its capacity and charge/ discharge rate information to the OS. 0x00000000 - Capacity information is reported in [mWh] and charge/ discharge rate information in [mW]. 0x00000001 - Capacity information is reported in [mAh] and charge/ discharge rate information in [mA].
Design Capacity	Integer (DWORD)	Battery's design capacity. Design Capacity is the nominal capacity of a new battery. The <i>Design Capacity</i> value is expressed as power [mWh] or current [mAh] depending on the <i>Power Unit</i> value. • 0x000000000 – 0x7FFFFFFF (in [mWh] or [mAh]) • 0xFFFFFFFF – Unknown design capacity
Last Full Charge Capacity	Integer (DWORD)	Predicted battery capacity when fully charged. The Last Full Charge Capacity value is expressed as power (mWh) or current (mAh) depending on the Power Unit value. • 0x00000000h – 0x7FFFFFFF (in [mWh] or [mAh]) • 0xFFFFFFFF – Unknown last full charge capacity
Battery Technology	Integer (DWORD)	 0x00000000 – Primary (for example, non-rechargeable) 0x00000001 – Secondary (for example, rechargeable)
Design Voltage	Integer (DWORD)	Nominal voltage of a new battery. • 0x000000000 – 0x7FFFFFFF in [mV] • 0xFFFFFFF – Unknown design voltage

Power Source and Power Meter Devices

Field	Format	Description		
Design capacity of Warning	Integer (DWORD)	OEM-designed battery warning capacity. See Section 3.9.4, "Low Battery Levels." • 0x000000000 – 0x7FFFFFFF in [mWh] or [mAh]		
Design Capacity of Low	Integer (DWORD)	OEM-designed low battery capacity. See Section 3.9.4, "Low Battery Levels." • 0x000000000 – 0x7FFFFFFF in [mWh] or [mAh]		
Cycle Count	Integer (DWORD)	The number of cycles the battery has experienced. A cycle is defined as: An amount of discharge approximately equal to the value of Design Capacity. • 0x000000000 – 0xFFFFFFE • 0xFFFFFFF – Unknown cycle count		
Measurement Accuracy	Integer (DWORD)	The accuracy of the battery capacity measurement, in thousandth of a percent. (0% - 100.000%) For example, The value 80000 would mean 80% accuracy.		
Max Sampling Time	Integer (DWORD)	The sampling time is the duration between two consecutive measurements of the battery's capacities specified in _BST, such as present rate and remaining capacity. If the OSPM makes two succeeding readings through _BST beyond the duration, two different results will be returned. The Max Sampling Time is the maximum sampling time the battery can support, in milliseconds. OxFFFFFFF is returned if the information is unavailable.		
Min Sampling Time	Integer (DWORD)	The Min Sampling Time is the minimum sampling time the battery can support, in milliseconds. 0xFFFFFFF is returned if the information is unavailable.		
Max Averaging Interval	Integer (DWORD)	The Average Interval is the length of time (in milliseconds) within which the battery averages the capacity measurements specified in _BST, such as remaining capacity and present rate. The Sampling time specifies the frequency of measurements, and the average interval specifies the width of the time window of every measurement. This field indicates the maximum Average Interval that the battery supports.		
Min Averaging Interval	Integer (DWORD)	This field indicates the minimum Average Interval that the battery supports		
Battery Capacity Granularity 1	Integer (DWORD)	Battery capacity granularity between low and warning in [mAh] or [mWh]. That is, this is the smallest increment in capacity that the battery is capable of measuring. See note below for more details		
Battery Capacity Granularity 2	Integer (DWORD)	Battery capacity granularity between warning and Full in [mAh] or [mWh]. That is, this is the smallest increment in capacity that the battery is capable of measuring. This may be a different value than Battery Capacity Granularity 1 to accommodate systems where the granularity accuracy may change depending on the battery level. See note below for more details.		
Model Number	String (ASCIIZ)	OEM-specific Control Method Battery model number		

Field	Format	Description
Serial Number	String (ASCIIZ)	OEM-specific Control Method Battery serial number
Battery Type	String (ASCIIZ)	The OEM-specific Control Method Battery type
OEM Information	String (ASCIIZ)	OEM-specific information for the battery that the UI uses to display the OEM information about the Battery. If the OEM does not support this information, this field should contain a NULL string.

Note: A secondary-type battery should report the corresponding capacity (except for Unknown).

Note: On a multiple-battery system, all batteries in the system should return the same granularity.

Note: Operating systems prefer these control methods to report data in terms of power (watts).

Note: On a multiple-battery system, all batteries in the system must use the same power unit.

Note: The definition of battery capacity granularity has been clarified. For OSPM to determine if systems support the clarified definition of battery capacity granularity, OSPM may evaluate an _OSC method at the battery scope to indicate support for this capability, and for the platform to indicate if it supports these extended capabilities.

10.2.2.3 OSC Definition for Control Method Battery

OSC for control method battery is uniquely identified by the UUID:

F18FC78B-0F15-4978-B793-53F833A1D35B

The Revision 1 capabilities described under this OSC are defined in Table 10-252.

Table 10-252 Control Method Battery OSC Capabilities DWORD2 Bit Definitions

Capabilities DWORD2 bits	Interpretation
0	 0 – OS does not support revised battery granularity definition. 1 – OS supports revised battery granularity definition.
1	O – OS does not support specifying wake on low battery user preference. 1 – OS supports specifying wake on low battery user preference, See Section 9.1.3, _BLT Battery Level Threshold) for more information.
2-31	Reserved

Bits defined in Capabilities DWORD2 provide information regarding OS supported features. Contents in DWORD2 are passed one-way; the OS will disregard the corresponding bits of DWORD2 in the Return Code.

10.2.2.4 _BMA (Battery Measurement Averaging Interval)

This object is used to set the averaging interval of the battery capacity measurement, in milliseconds. The Battery Measurement Averaging Interval is the length of time within which the battery averages the capacity measurements specified in BST, such as remaining capacity and present rate.

The OSPM may read the Max Average Interval and Min Average Interval with _BIX during boot time, and set a specific average interval within the range with BMA.

Arguments: (1)

Arg0 – AveragingInterval (**Integer**(DWORD)) the averaging interval of battery capacity measurement:

0x00000001 – 0xFFFFFFF (in units of millisecond)

Return Value:

An **Integer** (DWORD) containing a result code as follows:

0x00000000 - Success.

0x00000001 – Failure to set Battery Measurement Averaging Interval because it is out of the battery's measurement capability.

0x00000002 - 0xFFFFFFFF - Reserved.

10.2.2.5 BMS (Battery Measurement Sampling Time)

This object is used to set the sampling time of the battery capacity measurement, in milliseconds.

The Sampling Time is the duration between two consecutive measurements of the battery's capacities specified in _BST, such as present rate and remaining capacity. If the OSPM makes two succeeding readings through BST beyond the duration, two different results will be returned.

The OSPM may read the Max Sampling Time and Min Sampling Time with _BIX during boot time, and set a specific sampling time within the range with BMS.

Arguments: (1)

 $Arg0-SamplingTime\ (\textbf{Integer}(DWORD))\ the\ sampling\ time\ of\ battery\ capacity\ measurement:$

0x00000001 – 0xFFFFFFF (in units of millisecond)

Return Value:

An Integer (DWORD) containing a result code as follows:

0x00000000 - Success.

0x00000001 – Failure to set Battery Measurement Sampling Time because it is out of the battery's measurement capability.

0x00000002 - 0xFFFFFFFF - Reserved.

10.2.2.6 BST (Battery Status)

This object returns the present battery status. Whenever the *Battery State* value changes, the system will generate an SCI to notify the OS.

Arguments:

None

Return Value:

A **Package** containing the battery status as described below

Return Value Information:

BST returns a package in the format below

Table 10-253 BST Return Package Values

Element	Format	Description
Battery State	Integer (DWORD)	Bit values. Notice that the <i>Charging</i> bit and the <i>Discharging</i> bit are mutually exclusive and must not both be set at the same time. Even in critical state, hardware should report the corresponding charging/discharging state. • Bit0 – 1 indicates the battery is discharging. • Bit1 – 1 indicates the battery is charging. • Bit2 – 1 indicates the battery is in the critical energy state (see Section 3.9.4, "Low Battery Levels"). This does not mean battery failure.
Battery Present Rate	Integer (DWORD)	Returns the power or current being supplied or accepted through the battery's terminals (direction depends on the <i>Battery State</i> value). The <i>Battery Present Rate</i> value is expressed as power [mWh] or current [mAh] depending on the <i>Power Unit</i> value. Batteries that are rechargeable and are in the discharging state are required to return a valid <i>Battery Present Rate</i> value. • 0x00000000 – 0x7FFFFFFF in [mW] or [mA] 0xFFFFFFF – Unknown rate
Battery Remaining Capacity	Integer (DWORD)	Returns the estimated remaining battery capacity. The <i>Battery Remaining Capacity</i> value is expressed as power [mWh] or current [mAh] depending on the <i>Power Unit</i> value. Batteries that are rechargeable are required to return a valid <i>Battery Remaining Capacity</i> value. • 0x00000000 – 0x7FFFFFFF in [mWh] or [mAh] • 0xFFFFFFFF – Unknown capacity
Battery Present Voltage	Integer (DWORD)	Returns the voltage across the battery's terminals. Batteries that are rechargeable must report <i>Battery Present Voltage</i> . • 0x000000000 – 0x7FFFFFFF in [mV] • 0xFFFFFFF – Unknown voltage Note: Only a primary battery can report unknown voltage.

Notice that when the battery is a primary battery (a non-rechargeable battery such as an Alkaline-Manganese battery) and cannot provide accurate information about the battery to use in the calculation of the remaining battery life, the Control Method Battery can report the percentage directly to OS. It does so by reporting the Last Full Charged Capacity =100 and BatteryPresentRate=0xFFFFFFF. This means that Battery Remaining Capacity directly reports the battery's remaining capacity [%] as a value in the range 0 through 100 as follows:

Figure 10-56 Remaining Battery Percent Formula

Figure 10-57 Remaining Battery Life Formula

10.2.2.7 _BTP (Battery Trip Point)

This object is used to set a trip point to generate an SCI whenever the *Battery Remaining Capacity* reaches or crosses the value specified in the _BTP object. Specifically, if *Battery Remaining Capacity* is less than the last argument passed to _BTP, a notification must be issued when the value of *Battery Remaining Capacity* rises to be greater than or equal to this trip-point value. Similarly, if *Battery Remaining Capacity* is greater than the last argument passed to _BTP, a notification must be issued when the value of *Battery Remaining Capacity* falls to be less than or equal to this trip-point value. The last argument passed to _BTP will be kept by the system.

If the battery does not support this function, the _BTP control method is not located in the namespace. In this case, the OS must poll the *Battery Remaining Capacity* value.

Arguments: (1)

Arg0 – An **Integer** containing the new battery trip point

0 – Clear the trip point

1 - 0x7FFFFFFF - New trip point, in units of**mWh**or**mAh**depending on the*Power Units*value

Return Value:

None

10.2.2.8 BTM (Battery Time)

This optional object returns the estimated runtime of the battery while it is discharging.

Arguments: (1)

Arg0 – An **Integer** containing the rate at which the battery is expected to discharge

- 0 Indicates that the battery will continue discharging at the current rate. The rate should be based on the average rate of drain, not the current rate of drain.
- 1 0x7FFFFFFFFThe discharge rate (in mA or mW)

Return Value:

An **Integer** containing the estimated remaining runtime

- 0 The input discharge rate (Arg0) is too large for the battery or batteries to supply. If the input argument was 0, this value indicates that the battery is critical.
- 1 0xFFFFFFE –Estimated runtime in seconds

0xFFFFFFFF -Runtime is unknown

10.2.2.9 BCT (Battery Charge Time)

When the battery is charging, this optional object returns the estimated time from present to when it is charged to a given percentage of Last Full Charge Capacity.

Arguments:

Arg0 – ChargeLevel (Integer (DWORD)): The queried charge level in units of percent of Last Full Charge Capacity. For example: 96 refers to 96% of Last Full Charge Capacity. Valid values are 1 – 100 (0x00000001 – 0x00000064).

Return Value:

An **Integer** (DWORD) containing a result code as follows:

0x00000000 – Specified targeted charging capacity is smaller than the current remaining capacity or larger than 100% of Last Full Charge Capacity.

0x00000001 -0xFFFFFFE - Estimated charging time in seconds

0xFFFFFFF - Charging time is unknown

10.2.2.10 BMD (Battery Maintenance Data)

This optional object returns information about the battery's capabilities and current state in relation to battery calibration and charger control features. If the _BMC object (defined below) is present under a battery device, this object must also be present. Whenever the *Status Flags* value changes, AML code will issue a **Notify**(*battery_device*, 0x82). In addition, AML will issue a **Notify**(*battery_device*, 0x82) if evaluating _BMC did not result in causing the *Status Flags* to be set as indicated in that argument to _BMC. AML is not required to issue **Notify**(*battery_device*, 0x82) if the *Status Flags* change while evaluating _BMC unless the change does not correspond to the argument passed to _BMC.

Arguments:

None

Return Value:

A **Package** containing the battery maintenance data as described below

Return Value Information:

BMD returns a package in the format below:

```
Package {
Status Flags // Integer (DWORD)
Capability Flags // Integer (DWORD)
Recalibrate Count // Integer (DWORD)
Quick Recalibrate Time // Integer (DWORD)
Slow Recalibrate Time // Integer (DWORD)
}
```

Power Source and Power Meter Devices

Table 10-254 BMD Return Package Values

Field	Format	Description
Status Flags	Integer (DWORD)	Bit values. Bit0 is mutually exclusive with Bit1 and Bit2. If the charger is being manually controlled, there cannot be an AML controlled calibration cycle. Bit0 – 1 indicates the battery is running an AML controlled calibration cycle Bit1 – 1 indicates that charging has been disabled. Bit2 – 1 indicates the battery is configured to discharge while AC power is available. Bit3 – 1 indicates that the battery should be recalibrated. Bit4 – 1 indicates that the OS should put the system into standby to speed charging during a calibration cycle. This is optional (based on user preference) if "Slow Recalibrate Time" is not equal to 0x00000000.
Capability Flags	Integer (DWORD)	 Bit values that describe the capabilities of the battery system. These bits allows a battery system with more limited capabilities to still be calibrated by OSPM. Bit0 – 1 indicates that an AML controlled calibration cycle is supported. Bit1 – 1 indicates that disabling the charger is supported. Bit2 – 1 indicates that discharging while running on AC is supported. Bit3 – 1 indicates that calling _BMC for one battery will affect the state of all batteries in the system. This is for battery systems that cannot control batteries individually. Bit4 – 1 indicates that calibration should be done by first fully charging the battery and then discharging it. Not setting this bit will indicate that calibration can be done by simply discharging the battery. Bit4 – Bit31 – reserved.
Recalibrate Count	Integer (DWORD)	This is used by battery systems that can't detect when calibration is required, but wish to recommend that the battery should be calibrated after a certain number of cycles. Counting the number of cycles and partial cycles is done by the OS. • 0x00000000 – Only calibrate when Status Flag bit 3 is set. • 0x00000000 – 0xFFFFFFFF – calibrate battery after detecting this many battery cycles.
Quick Recalibrate Time	Integer (DWORD)	Returns the estimated time it will take to calibrate the battery if the system is put into standby whenever <i>Status Flags</i> Bit4 is set. While the AML controlled calibration cycle is in progress, this returns the remaining time in the calibration cycle. • 0x000000000 – indicates that standby while calibrating the battery is not supported. The system should remain in S0 until calibration is completed. • 0x00000001 – 0xFFFFFFF – estimated recalibration time in seconds. • 0xFFFFFFF – indicates that the estimated time to recalibrate the battery is unknown.
Slow Recalibrate Time	Integer (DWORD)	Returns the estimated time it will take to calibrate the battery if <i>Status Flag</i> Bit4 is ignored. While the AML controlled calibration cycle is in progress, this returns the remaining time in the calibration cycle. • 0x000000000 – indicates that battery calibration may not be successful if <i>Status Flags</i> Bit4 is ignored. • 0x00000001 – 0xFFFFFFF – estimated recalibration time in seconds. • 0xFFFFFFF – indicates that the estimated time to recalibrate the battery is unknown.

See Section 3.9.5, "Battery Calibration" for an overview of Battery Calibration.

The *Capability Flags* and *Recalibration Count* are used to indicate what functions are controlled by AML and what functions are controlled by OSPM as described in section 3.9.5, "Battery Calibration". If the system does not implement an AML controlled calibration cycle (bit 0), it may indicate using bit 1 and bit 2 that the OS can control a generic calibration cycle without prompting the user to remove the power cord. *Recalibration Count* may be used to indicate that the BIOS cannot determine when calibration should be preformed so bit 3 of the *Status Flags* will never be set. In that case, OSPM will attempt to count the number of cycles.

Bit3 is used by systems that do not have individual control over the batteries and can only perform calibration on all batteries in the system at once. On such a system, if one battery requests calibration and another battery does not, the OS may suggest that the user remove the battery that doesn't need calibration, before initiating the calibration cycle. When this bit is set, reading the Recalibrate Time from either battery should give the time to recalibrate all batteries present in the system.

10.2.2.11 BMC (Battery Maintenance Control)

This object is used to initiate calibration cycles or to control the charger and whether or not a battery is powering the system. This object is only present under a battery device if the _BMD *Capabilities Flags* field has bit 0, 1, or 2 set.

Arguments: (1)

Arg0 – An **Integer** containing feature control flags

Bit0 – Set to initiate an AML controlled calibration cycle. Clear to end the calibration cycle

Bit1 – Set to disable charging. Clear to enable charging

Bit2 – Set to allow the battery to discharge while AC power is available. Clear to prevent discharging while AC power is available

Return Value:

None

See Section 3.9.5 for an overview of Battery Calibration.

Evaluating this object with bit0 set will initiate an AML controlled recalibration cycle if _BMD indicates that this is supported. The calibration cycle is controlled by the platform and will typically include disabling the AC adapter and discharging the battery, then charging the battery. While the battery is charging, the BIOS should set Bit4 of the Status flags returned by _BMD if it is possible to put the system into standby during calibration to speed up charging. Evaluating this with Bit0 equal to 0 will abort the calibration cycle if one is in process. If the BIOS determines that the calibration cycle must be aborted (for example AC power is lost), or the calibration completes successfully, the BIOS will end the cycle automatically, clear the _BMD *Status Flag* Bit0, and send a notify 0x82. While the calibration cycle is in process, the battery will report data normally, so the OS must disable battery alarms.

Bit1 and Bit2 may not be used in conjunction with the AML controlled calibration cycle. Having Bit0 set will override Bit1 and Bit2. Bit1 will prevent the battery from charging even though AC power is connected. Bit2 will allow the system to draw its power from the battery even though AC power is available. When the battery is no longer capable of delivering current, this setting is automatically cleared, and the system will continue running off AC power without interruption. In addition, if AC power is lost this bit will be cleared. When AC power comes back, the OS must set

the bit again if the user wants to continue discharging. When the system clears this bit automatically, it will result in a change in the *Status Flags* returned by _BMD. This will cause a notify 0x82. Bit1 is only cleared automatically if an AML controlled calibration cycle is initiated.

When a battery is discharging because Bit2 is set, the _PSR method of the AC adapter device will report that AC is offline because the system is not running off of the AC adapter. If the batteries are controlled individually (Bit3 of the _BMD *Capabilities Flags*), setting either battery to discharge will cause _PSR to report AC offline. If more than one battery in the system has Bit2 set to discharge the battery, it is up to the system to decide which battery to discharge, so only on a system that discharges the batteries one at a time, a battery with Bit2 set may not be discharging if another battery in the system is being discharged.

If Batteries are not controlled individually, calling _BMC will initiate calibration, disable charge, and/or allow discharge on all batteries in the system. The state of these batteries will be reflected in the BMD *Status Flags* for all batteries.

10.3 AC Adapters and Power Source Objects

The Power Source objects describe the system's power source. These objects may be defined under a Power Source device which is declared using a hardware identifier (_HID) of "ACPI0003". Typically there will be a power source device for each physical power supply contained within the system. However, in cases where the power supply is shared, as in a blade server configuration, this may not be possible. Instead the firmware can choose to expose a virtual power supply that represents one or more of the physical power supplies.

Table 10-255	Power	Source	Objec	ts
--------------	-------	--------	-------	----

Object	Description
_PSR	Returns whether this power source device is currently online.
_PCL	List of pointers to devices this power source is powering.
_PIF	Returns static information about a power source.
_PRL	List of pointers to all the other power source devices that belong in the same redundancy group of which the power supply device is a member.

10.3.1 PSR (Power Source)

Returns whether the power source device is currently in use. This can be used to determine if system is running off this power supply or adapter. On mobile systes this will report that the system is not running on the AC adapter if any of the batteries in the system is being forced to discharge. In systems that contains multiple power sources, this object reports the power source's online or offline status.

Arguments:

None

Return Value:

An **Integer** containing the power source status

0 – Off-line (not on AC power)

1 – On-line

10.3.2 PCL (Power Consumer List)

This object evaluates to a list of pointers, each pointing to a device or a bus powered by the power source device. Pointing to a bus indicates that all devices under the bus are powered by the power source device.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to devices or buses

10.3.3 PIF (Power Source Information)

This object returns information about the Power Source, which remains constant until the Power Source is changed. When the power source changes, the platform issues a Notify(0x0) (Bus Check) to the Power Source device to indicate that OSPM must re-evaluate the PIF object.

Arguments:

None

Return Value:

A **Package** with the following format:

Table 10-256 PIF Method Result Codes

Element	Object Type	Description
Power Source State	Integer (DWORD)	Bit values that describe the type of this Power Source. These bits are especially useful in server scenarios. Bit0 – indicates the power source is a redundant one. If this bit is set, this Power Source device should have a _PRL object. Bit1 – indicates the power source is being shared across multiple machines. Bit2 – Bit31 – Reserved.
Maximum Output Power	Integer (DWORD)	The maximum rated output wattage of the power source device. [mW] 0xFFFFFFF is returned if the information is unavailable.
Maximum Input Power	Integer (DWORD)	The maximum rated input wattage of the power source device. [mW] 0xFFFFFFF is returned if the information is unavailable.

Model Number	String (ASCIIZ)	OEM-specific Power Source model number. This element is optional and an empty string (a null character) should be used if this is not supported.
Serial Number	String (ASCIIZ)	OEM-specific Power Source serial number. This element is optional and an empty string (a null character) should be used if this is not supported.
OEM Information	String (ASCIIZ)	OEM-specific information that the UI uses to display about the Power Source device. This element is optional and a NULL string should be used if this is not supported.

10.3.4 PRL (Power Source Redundancy List)

This optional object evaluates to a list of Power Source devices that are in the same redundancy grouping as Power Source device under which this object is defined. A redundancy grouping is a group of power supplies that together provide redundancy. For example, on a system that contains two power supplies that each could independently power the system, both power supplies would be part of the same redundancy group. This is used in conjunction with the *Power Source State* values specified by the PIF object.

The entries should be in the format of a fully qualified ACPI namespace path.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to power source devices. It has the following format:

10.4 Power Meters

The following section describes Power Metering objects. These objects may be defined under a Power Meter device which is declared using the ACPI000D hardware identifier (_HID).

Table 10-257 Power Meter Objects

Object	Description
_GAI	Gets the averaging interval used by the power meter.
_GHL	Gets the hardware power consumption limit that is enforced by the Power Meter.
_PAI	Sets the power averaging interval used by the Power Meter.
_PMC	Returns Power Meter capabilities.
_PMD	Returns a list of devices whose power consumption is measured by the Power Meter.
_PMM	Returns the power consumption measured by the Power Meter.

Object	Description
_PTP	Sets Power Meter device trip points.
_SHL	Sets the hardware power consumption limit that is enforced by the Power Meter.

10.4.1 _PMC (Power Meter Capabilities)

This object returns the capabilities of a power meter. This information remains constant unless either the power meter's firmware or the BMC hardware changes, at which time the platform is required to send Notify(power meter, 0x80) for the OSPM to re-evaluate PMC.

Arguments:

None

Return Value:

A **Package** with the following format:

Table 10-258 PMC Method Result Codes

Element	Object Type	Description
Supported Capabilities	Integer (DWORD)	A bitmask that represents the capability flags: Bit0 – indicates the power meter supports measurement. Bit1 – indicates the power meter supports trip points. Bit2 – indicates the power meter supports hardware enforced limit. Bit3 – indicates that the power meter supports notifications when the hardware limit is enforced. Bit4 – Bit7 – reserved. Bit8 – indicates the power meter only reports data when discharging. This applies to power meters that are battery-type devices.
Measurement Unit	Integer (DWORD)	The units used by the power meter to report measurement and configure trip points and hardware enforced limits. 0x00000000 – indicates measurements are reported in [mW].
Measurement Type	Integer (DWORD)	The type of measurement the power meter is measuring. A power meter may measure either input or output power, not both. 0x00000000 – indicates the power meter is measuring input power. 0x00000001 – indicates the power meter is measuring output power.

Element	Object Type	Description
Measurement Accuracy	Integer (DWORD)	The accuracy of the power meter device, in thousandth of a percent. (0% - 100.000%) For example, The value 80000 would mean 80% accuracy.
Measurement Sampling Time	Integer (DWORD)	The sampling time of the power meter device, in milliseconds. This is the minimum amount of time at which the measurement value will change. In other words, the same reading will be returned by _PMM if OSPM makes 2 consecutive reads within a measurement sampling time. 0xFFFFFFF is returned if the information is unavailable.
Minimum Averaging Interval	Integer (DWORD)	This is the minimum length of time (in milliseconds) within which the power meter firmware is capable of averaging the measurements within it.
Maximum Averaging Interval	Integer (DWORD)	This is the maximum length of time (in milliseconds) within which the power meter firmware is capable of averaging the measurements within it.
Hysteresis Margin	Integer (DWORD)	The margin used by the BMC for hysteresis, in the unit of [Measurement Unit / Measurement Sampling Time]. This indicates the margin built around the trip points and hardware limit notifications. This margin prevents unnecessary notifies to the OSPM when the reading is fluctuating very close to one of the trip points or the hardware limit. 0xFFFFFFF is returned if the information is unavailable.
Hardware Limit Is Configurable	Integer (DWORD)	This boolean value represents whether hardware enforced limit is configurable by the OSPM. 0x00000000 (zeros) – indicates the limit is read-only. 0xFFFFFFF (ones) – indicates the limit is writable.
Minimum Configurable Hardware Limit	Integer (DWORD)	The minimum value that can be configured into the hardware enforced limit, expressed in the units as specified by Measurement Unit.
Maximum Configurable Hardware Limit	Integer (DWORD)	The maximum value that can be configured into the hardware enforced limit, expressed in the units as specified by Measurement Unit.
Model Number	String (ASCIIZ)	OEM-specific Power meter model number. This element is optional and an empty string (a null character) should be used if this is not supported.
Serial Number	String (ASCIIZ)	OEM-specific Power meter serial number. This element is optional and an empty string (a null character) should be used if this is not supported.
OEM Information	String (ASCIIZ)	OEM-specific information that the UI uses to display about the Power meter device. This element is optional and a NULL string should be used if this is not supported.

10.4.2 PTP (Power Trip Points)

This object sets the upper and lower trip points for the power meter device. These 2 trip points define a hysteresis range for which the OSPM can tolerate without re-reading the current measurement via _PMM. When the power meter draw goes outside the range, a **Notify**(power_meter, 0x81) should be sent to notify the OSPM, at which time the OSPM should re-evaluate _PMM and also set a pair of

trip points around the newest reading. If the latest value measured by the power meter is outside of the range defined by the trip points by the time _PTP is called, a result code is returned.

Arguments: (2)

Arg0 (**Integer**): Upper Trip Point Arg1 (**Integer**): Lower Trip Point

Return Value:

An **Integer** containing the status of the operation:

0x00000000 - Success

0x00000001 – Failure to set trip points because latest measurement is out of range

0x00000002 – Failure to set trip points due to hardware timeout

0x00000003 – Failure to set trip points due to unknown hardware error

0x00000004 - 0xFFFFFFF - Reserved

10.4.3 PMM (Power Meter Measurement)

This object returns the latest measurement reading from the power meter device. The value returned represents real power (i.e. power factor is included in the value). In most cases this is a rolling average value that is computed by the firmware over an averaging interval. On systems where this interval can be configured, the PAI object should be present under the power meter device (see Section 10.4.4).

Arguments:

None

Return Value:

An **Integer** is returned to represent the latest measurement reading from the power meter device. This value should be in the unit specified in the power meter capabilities (typically in milliwatts), and is required to be the RMS value if the power meter is measuring in AC. If an error occurs while obtaining the meter reading or if the value is not available then an Integer with all bits set is returned.

10.4.4 PAI (Power Averaging Interval)

This object sets the averaging interval used by the power meter. The averaging interval is the total time the power meter will take instantaneous measurement samples for, before averaging them to produce the average power measurement as returned by _PMM. If the platform changes the averaging interval independently from OSPM, the platform must issue a Notify(power_meter, 0x84) to indicate the change to the OSPM. Upon receiving the notification, OSPM evaluates the _GAI object to read the new averaging interval.

Arguments: (1)

Arg0 – An **Integer** that represents the desired value OSPM chose to be the power averaging interval, in milliseconds. This value needs to be within the minimum and maximum averaging interval as specified by PMC. Otherwise, a failure result code is returned.

Return Value:

An **Integer** containing the status of the operation:

0x00000000 - Success

0x00000001 – Failure to set power averaging interval because it is out of range

0x00000002 – Failure to set power averaging interval due to hardware timeout

0x00000003 – Failure to set power averaging interval due to unknown hardware error

0x00000004 - 0xFFFFFFF - Reserved

10.4.5 _GAI (Get Averaging Interval)

This object gets the averaging interval used by the power meter. The averaging interval is the total time the power meter will take instantaneous measurement samples for, before averaging them to produce the average power measurement as returned by _PMM. If the platform changes the averaging interval independently from OSPM, the platform must issue a Notify(power_meter, 0x84) to indicate the change to the OSPM. Upon receiving the notification, OSPM evaluates the _GAI object to read the new averaging interval.

Arguments:

None

Return Value:

An **Integer** containing the currently configured power averaging interval, in milliseconds. If an error occurs while obtaining the averaging interval or if the value is not available then an Integer with all bits set is returned.

10.4.6 _SHL (Set Hardware Limit)

This object sets the hardware limit enforced by the power meter. This limit, if supported, will be enforced by the circuitry on the platform hardware, to the best of its effort. This value is typically also configurable via other out-of-band management mechanism. When the enforcement happens, the platform should send a **Notify**(power meter, 0x83) to the OSPM.

Arguments: (1)

Arg0 – An **Integer** value that represent the desired value OSPM chose as the hardware enforced limit of this power meter, in the unit specified in _PMC. This value needs to be within the minimum and maximum hardware limit as specified by _PMC. Otherwise, a failure result code is returned.

Return Value:

An **Integer** containing the status of the operation:

0x00000000 - Success

0x00000001 – Failure to set hardware limit because it is out of range

0x00000002 – Failure to set hardware limit due to the hardware timeout

0x00000003 – Failure to set hardware limit due to unknown hardware error

0x00000004 - 0xFFFFFFFF - Reserved

10.4.7 _GHL (Get Hardware Limit)

This object gets the hardware limit enforced by the power meter. This limit can be changed by either the OSPM or by the platform through some out-of-band mechanism. When this value is changed, a **Notify**(*power_meter*, 0x82) should be sent to notify the OSPM to re-read the hardware limit. If an error occurs while obtaining the hardware limit or if the value is not available then an Integer with all bits set is returned.

Arguments:

None

Return Value:

An **Integer** is returned to represent the currently configured hardware enforced limit of the power meter, in the unit specified in PMC.

10.4.8 PMD (Power Metered Devices)

This object evaluates to a package of device names. Each name corresponds to a device in the ACPI namespace that is being measured by the power meter device. The measurement reported by the power meter is roughly correspondent to the total power draw of all the devices returned.

If this control method is present, the package needs to contain at least 1 device. On a system that supports power metering, a system power meter that measures the power draw of the entire system should always be present and have a PMD that contains \ SB as its sole entry.

Arguments:

None

Return Value:

A variable-length **Package** consisting of references to devices being measured by the power meter.

10.5 Example: Power Source and Power Meter Namespace

<u>Figure 10-58</u> below shows the ACPI namespace for a computer with a power meter, AC adapter and two batteries associated with a docking station which itself has an AC adapter.

d




Figure 10-58 Power Meter and Power Source/Docking Namespace Example

11

Thermal Management

This section describes the ACPI thermal model and specifies the ACPI Namespace objects OSPM uses for thermal management of the platform.

11.1 Thermal Control

ACPI defines interfaces that allow OSPM to be proactive in its system cooling policies. With OSPM in control of the operating environment, cooling decisions can be made based on the system's application load, the user's preference towards performance or energy conservation, and thermal heuristics. Graceful shutdown of devices or the entire system at critical heat levels becomes possible as well. The following sections describe the ACPI thermal model and the ACPI Namespace objects available to OSPM to apply platform thermal management policy.

The ACPI thermal model is based around conceptual platform regions called *thermal zones* that physically contain devices, thermal sensors, and cooling controls. Generally speaking, the entire platform is one large thermal zone, but the platform can be partitioned into several ACPI thermal zones if necessary to enable optimal thermal management.

ACPI Thermal zones are a logical collection of interfaces to temperature sensors, trip points, thermal property information, and thermal controls. Thermal zone interfaces apply either thermal zone wide or to specific devices, including processors, contained within the thermal zone. ACPI defines namespace objects that provide the thermal zone-wide interfaces in Section 11.3, "Thermal Objects". A subset of these objects may also be defined under devices. OS implementations compatible with the ACPI 3.0 thermal model, interface with these objects but also support OS native device driver interfaces that perform similar functions at the device level. This allows the integration of devices with embedded thermal sensors and controls, perhaps not accessible by AML, to participate in the ACPI thermal model through their inclusion in the ACPI thermal zone. OSPM is responsible for applying an appropriate thermal policy when a thermal zone contains both thermal objects and native OS device driver interfaces for thermal control.

Some devices in a thermal zone may be comparatively large producers of thermal load in relation to other devices in the thermal zone. Devices may also have varying degrees of thermal sensitivity. For example, some devices may tolerate operation at a significantly higher temperature than other devices. As such, the platform can provide OSPM with information about the platform's device topology and the resulting influence of one device's thermal load generation on another device. This information must be comprehended by OSPM for it to achieve optimal thermal management through the application of cooling controls.

ACPI expects all temperatures to be represented in tenths of degrees. This resolution is deemed sufficient to enable OSPM to perform robust platform thermal management.




Figure 11-59 ACPI Thermal Zone

11.1.1 Active, Passive, and Critical Policies

There are three cooling policies that OSPM uses to control the thermal state of the hardware. The policies are *active*, *passive* and *critical*.

- Active Cooling. OSPM takes a direct action such as turning on one or more fans. Applying
 active cooling controls typically consume power and produce some amount of noise, but are able
 to cool a thermal zone without limiting system performance. Active cooling temperature trip
 points declare the temperature thresholds OSPM uses to decide when to start or stop different
 active cooling devices.
- Passive Cooling. OSPM reduces the power consumption of devices to reduce the temperature of a thermal zone, such as slowing (throttling) the processor clock. Applying passive cooling controls typically produces no user-noticeable noise. Passive cooling temperature trip points specify the temperature thresholds where OSPM will start or stop passive cooling.
- Critical Trip Points. These are threshold temperatures at which OSPM performs an orderly, but critical, shutdown of a device or the entire system. The _HOT object declares the critical temperature at which OSPM may choose to transition the system into the S4 sleeping state, if supported, The _CRT object declares the critical temperature at which OSPM must perform a critical shutdown.

When a thermal zone appears in the ACPI Namespace or when a new device becomes a member of a thermal zone, OSPM retrieves the temperature thresholds (trip points) at which it executes a cooling policy. When OSPM receives a temperature change notification, it evaluates the thermal zone's temperature interfaces to retrieve current temperature values. OSPM compares the current temperature values against the temperature thresholds. If any temperature is greater than or equal to a corresponding active trip point then OSPM will perform active cooling. If any temperature is greater than or equal to a corresponding passive trip point then OSPM will perform passive cooling. If the TMP object returns a value greater than or equal to the value returned by the HOT object then OSPM may choose to transition the system into the S4 sleeping state, if supported. If the TMP object returns a value greater than or equal to the value returned by the CRT object then OSPM must shut the system down. Embedded Hot and Critical trip points may also be exposed by individual devices within a thermal zone. Upon passing of these trip points, OSPM must decide whether to shut down the device or the entire system based upon device criticality to system operation. OSPM must also evaluate the thermal zone's temperature interfaces when any thermal zone appears in the namespace (for example, during system initialization) and must initiate a cooling policy as warranted independent of receipt of a temperature change notification. This allows OSPM to cool systems containing a thermal zone whose temperature has already exceeded temperature thresholds at initialization time.

An optimally designed system that uses several thresholds can notify OSPM of thermal increase or decrease by raising an event every several degrees. This enables OSPM to anticipate thermal trends and incorporate heuristics to better manage the system's temperature.

To implement a preference towards performance or energy conservation, OSPM can request that the platform change the priority of active cooling (performance) versus passive cooling (energy conservation/silence) by evaluating the _SCP (Set Cooling Policy) object for the thermal zone or a corresponding OS-specific interface to individual devices within a thermal zone.

11.1.2 Dynamically Changing Cooling Temperature Trip Points

The platform or its devices can change the active and passive cooling temperature trip points and notify OSPM to reevaluate the trip point interfaces to establish the new policy threshold settings. The following are the primary uses for this type of thermal notification:

- When OSPM changes the platform's cooling policy from one cooling mode to another.
- When a swappable bay device is inserted or removed. A swappable bay is a slot that can accommodate several different devices that have identical form factors, such as a CD-ROM drive, disk drive, and so on. Many mobile PCs have this concept already in place.
- After the crossing of an active or passive trip point is signaled to implement hysteresis.

In each situation, OSPM must be notified to re-evaluate the thermal zone's trip points via the AML code execution of a **Notify**(*thermal_zone*, 0x81) statement or via an OS specific interface invoked by device drivers for zone devices participating in the thermal model.

11.1.2.1 OSPM Change of Cooling Policy

When OSPM changes the platform's cooling policy from one cooling mode to the other, the following occurs:

- 1. OSPM notifies the platform of the new cooling mode by running the Set Cooling Policy (_SCP) control method in all thermal zones and invoking the OS-specific Set Cooling Policy interface to all participating devices in each thermal zone.
- 2. Thresholds are updated in the hardware and OSPM is notified of the change.
- 3. OSPM re-evaluates the active and passive cooling temperature trip points for the zone and all devices in the zone to obtain the new temperature thresholds.

11.1.2.2 Resetting Cooling Temperatures to Adjust to Bay Device Insertion or Removal

The platform can adjust the thermal zone temperature to accommodate the maximum operating temperature of a bay device as necessary. For example:

- 1. Hardware detects that a device was inserted into or removed from the bay, updates the temperature thresholds, and then notifies OSPM of the thermal policy change and device insertion events.
- 2. OSPM re-enumerates the devices and re-evaluates the active and passive cooling temperature trip points.

11.1.2.3 Resetting Cooling Temperatures to Implement Hysteresis

An OEM can build hysteresis into platform thermal design by dynamically resetting cooling temperature thresholds. For example:

- 1. When the temperature increases to the designated threshold, OSPM will turn on the associated active cooling device or perform passive cooling.
- 2. The platform resets the threshold value to a lower temperature (to implement hysteresis) and notifies OSPM of the change. Because of this new threshold value, the fan will be turned off at a lower temperature than when it was turned on (therefore implementing a negative hysteresis).
- 3. When the temperature hits the lower threshold value, OSPM will turn off the associated active cooling device or cease passive cooling. The hardware will reset _ACx to its original value and notify OSPM that the trip points have once again been altered.

11.1.3 Detecting Temperature Changes

The ability of the platform and its devices to asynchronously notify an ACPI-compatible OS of meaningful changes in the thermal zone's temperature is a highly desirable capability that relieves OSPM from implementing a poll-based policy and generally results in a much more responsive and optimal thermal policy implementation. Each notification instructs OSPM to evaluate whether a trip point has been crossed and allows OSPM to anticipate temperature trends for the thermal zone.

It is recognized that much of the hardware used to implement thermal zone functionality today is not capable of generating ACPI-visible notifications (SCIs) or only can do so with wide granularity (for example, only when the temperature crosses the critical threshold). In these environments, OSPM must poll the thermal zone's temperature periodically to implement an effective policy.

While ACPI specifies a mechanism that enables OSPM to poll thermal zone temperature, platform reliance on thermal zone polling is strongly discouraged by this specification. OEMs should design systems that asynchronously notify OSPM whenever a meaningful change in the zone's temperature occurs – relieving OSPM of the overhead associated with polling. In some cases, embedded

controller firmware can overcome limitations of existing thermal sensor capabilities to provide the desired asynchronous notification.

Notice that the _TZP (thermal zone polling) object is used to indicate whether a thermal zone must be polled by OSPM, and if so, a recommended polling frequency. See <u>Section 11.4.21</u>, "_TZP," for more information.

11.1.3.1 Temperature Change Notifications

Thermal zone-wide temperature sensor hardware that supports asynchronous temperature change notifications does so using an SCI. The AML code that responds to this SCI must execute a **Notify**(*thermal_zone*, 0x80) statement to inform OSPM that a meaningful change in temperature has occurred. Alternatively, devices with embedded temperature sensors may signal their associated device drivers and the drivers may use an OS-specific interface to signal OSPM's thermal policy driver. A device driver may also invoke a device specific control method that executes a **Notify**(*thermal_zone*, 0x80) statement. When OSPM receives this thermal notification, it will evaluate the thermal zone's temperature interfaces to evaluate the current temperature values. OSPM will then compare the values to the corresponding cooling policy trip point values (either zone-wide or device-specific). If the temperature has crossed over any of the policy thresholds, then OSPM will actively or passively cool (or stop cooling) the system, or shut the system down entirely.

Both the number and granularity of thermal zone trip points are OEM-specific. However, it is important to notice that since OSPM can use heuristic knowledge to help cool the system, the more events OSPM receives the better understanding it will have of the system's thermal characteristic.




Figure 11-60 Thermal Events

For example, the simple thermal zone illustrated above includes hardware that will generate a temperature change notification using a 5° Celsius granularity. All thresholds (_PSV, _AC1, _AC0, and _CRT) exist within the monitored range and fall on 5 boundaries. This granularity is appropriate for this system as it provides sufficient opportunity for OSPM to detect when a threshold is crossed as well as to understand the thermal zone's basic characteristics (temperature trends).

Note: The ACPI specification defines Kelvin as the standard unit for absolute temperature values. All thermal zone objects must report temperatures in Kelvin when reporting absolute temperature

values. All figures and examples in this section of the specification use Celsius for reasons of clarity. ACPI allows Kelvin to be declared in precision of $1/10^{th}$ of a degree (for example, 310.5). Kelvin is expressed as $\theta/K = T/^{\circ}C + 273.2$.

11.1.3.2 Polling

Temperature sensor hardware that is incapable of generating thermal change events, or that can do so for only a few thresholds should inform OSPM to implement a poll-based policy. OSPM does this to ensure that temperature changes across threshold boundaries are always detectable.

Polling can be done in conjunction with hardware notifications. For example, thermal zone hardware that only supports a single threshold might be configured to use this threshold as the critical temperature trip point. Assuming that hardware monitors the temperature at a finer granularity than OSPM would, this environment has the benefit of being more responsive when the system is overheating.

A thermal zone advertises the need to be polled by OSPM via the _TZP object. See <u>Section 11.4.21</u>, "_TZP," for more information.

11.1.4 Active Cooling

Active cooling devices typically consume power and produce some amount of noise when enabled. These devices attempt to cool a thermal zone through the removal of heat rather than limiting the performance of a device to address an adverse thermal condition.

The active cooling interfaces in conjunction with the active cooling lists or the active cooling relationship table (_ART) allow the platform to use an active device that offers varying degrees of cooling capability or multiple cooling devices. The active cooling temperature trip points designate the temperature where Active cooling is engaged or disengaged (depending upon the direction in which the temperature is changing). For thermal zone-wide active cooling controls, the _ALx object evaluates to a list of devices that actively cool the zone or the _ART object evaluates to describe the entire active cooling relationship of various devices. For example:

- If a standard single-speed fan is the Active cooling device, then _AC0 evaluates to the temperature where active cooling is engaged and the fan is listed in _AL0.
- If the zone uses two independently controlled single-speed fans to regulate the temperature, then _AC0 will evaluate to the maximum cooling temperature using two fans, and _AC1 will evaluate to the standard cooling temperature using one fan.
- If a zone has a single fan with a low speed and a high speed, the _AC0 will evaluate to the temperature associated with running the fan at high-speed, and _AC1 will evaluate to the temperature associated with running the fan at low speed. _AL0 and _AL1 will both point to different device objects associated with the same physical fan, but control the fan at different speeds.
- If the zone uses two independently controlled multiple-speed fans to regulate the temperature, _AC0 of the target devices evaluates to the temperature at which OSPM will engage fan devices described by the _ART object as needed up to a maximum capability level.

For ASL coding examples that illustrate these points, see <u>Section 11.6</u>, "Thermal Zone Interface Requirements," and <u>Section 11.7</u>, "Thermal Zone Examples."

11.1.5 Passive Cooling

Passive cooling controls are able to cool a thermal zone without creating noise and without consuming additional power (actually saving power), but do so by decreasing the performance of the devices in the zone.

11.1.5.1 Processor Clock Throttling

The processor passive cooling threshold (_PSV) in conjunction with the processor list (_PSL) allows the platform to indicate the temperature at which a passive control, for example clock throttling, will be applied to the processor(s) residing in a given thermal zone. Unlike other cooling policies, during passive cooling of processors OSPM may take the initiative to actively monitor the temperature in order to cool the platform.

On an ACPI-compatible platform that properly implements CPU throttling, the temperature transitions will be similar to the following figure, in a coolable environment, running a coolable workload:




Figure 11-61 Temperature and CPU Performance Versus Time

The following equation should be used by OSPM to assess the optimum CPU performance change necessary to lower the thermal zone's temperature:

Equation #1:

$$\Delta P [\%] = _TC1 * (Tn - Tn-1) + _TC2 * (Tn - Tt)$$

Where:

Tn = current temperature

Tt = target temperature (PSV)

The two coefficients _TC1 and _TC2 and the sampling period _TSP are hardware-dependent constants the OEM must supply to OSPM (for more information, see Section 11.4, "Thermal

Objects"). The _TSP object contains a time interval that OSPM uses to poll the hardware to sample the temperature. Whenever the time value returned by _TSP has elapsed, OSPM will evaluate _TMP to sample the current temperature (shown as Tn in the above equation). Then OSPM will use the sampled temperature and the passive cooling temperature trip point (_PSV) (which is the target temperature Tt) to evaluate the equation for ΔP . The granularity of ΔP is determined by the CPU duty width of the system.

Note: Equation #1 has an implied formula.

Equation #2:

```
Pn = Pn-1 + HW[-\Delta P] where 0\% \le Pn \le 100\%
```

For Equation #2, whenever Pn-1 + Δ P lies outside the range 0-100%, then Pn will be truncated to 0-100%. For hardware that cannot assume all possible values of Pn between 0 and 100%, a hardware-specific mapping function HW is used.

In addition, the hardware mapping function in Equation #2 should be interpreted as follows:

For absolute temperatures:

- 1. If the right hand side of Equation #1 is negative, $HW[\Delta P]$ is rounded to the next available higher setting of frequency.
- 2. If the right hand side of Equation #1 is positive, $HW[\Delta P]$ is rounded to the next available lower setting of frequency.

For relative temperatures:

- 1. If the right hand side of Equation #1 is positive, HW[ΔP] is rounded to the next available higher setting of frequency.
- 2. If the right hand side of Equation #1 is negative, $HW[\Delta P]$ is rounded to the next available lower setting of frequency.
- The calculated Pn becomes Pn-1 during the next sampling period.
- For more information about CPU throttling, see <u>Section 8.1.1</u>, Processor Power State C0." A detailed explanation of this thermal feedback equation is beyond the scope of this specification.

11.1.6 Critical Shutdown

When the thermal zone-wide temperature sensor value reaches the threshold indicated by _CRT, OSPM must immediately shut the system down. The system must disable the power either after the temperature reaches some hardware-determined level above _CRT or after a predetermined time has passed. Before disabling power, platform designers should incorporate some time that allows OSPM to run its critical shutdown operation. There is no requirement for a minimum shutdown operation window that commences immediately after the temperature reaches _CRT. This is because:

- Temperature might rise rapidly in some systems and slowly on others, depending on casing design and environmental factors.
- Shutdown can take several minutes on a server and only a few seconds on a hand-held device.

Because of this indistinct discrepancy and the fact that a critical heat situation is a remarkably rare occurrence, ACPI does not specify a target window for a safe shutdown. It is entirely up to the OEM to build in a safe buffer that it sees fit for the target platform.

11.2 Cooling Preferences

A robust OSPM implementation provides the means for the end user to convey a preference (or a level of preference) for either performance or energy conservation to OSPM. Allowing the end user to choose this preference is most critical to mobile system users where maximizing system run-time on a battery charge often has higher priority over realizing maximum system performance. For example, if a user is taking notes on her PC in a quiet environment, such as a library or a corporate meeting, she may want the system to emphasize passive cooling so that the system operates quietly, even at the cost of system performance.

A user preference towards performance corresponds to the Active cooling mode while a user's preference towards energy conservation or quiet corresponds to the Passive cooling mode. ACPI defines an interface to convey the cooling mode to the platform. Active cooling can be performed with minimal OSPM thermal policy intervention. For example, the platform indicates through thermal zone parameters that crossing a thermal trip point requires a fan to be turned on. Passive cooling requires OSPM thermal policy to manipulate device interfaces that reduce performance to reduce thermal zone temperature.

Either cooling mode will be activated only when the thermal condition requires it. When the thermal zone is at an optimal temperature level where it does not warrant any cooling, both modes result in a system operating at its maximum potential with all fans turned off.

Thermal zones supporting the Set Cooling Policy interface allow the user to switch the system's cooling mode emphasis. See <u>Section 11.4.11</u>, "SCP," for more information.




Figure 11-62 Active and Passive Threshold Values

As illustrated in <u>Figure 11-62</u>, the platform must convey the value for each threshold to instruct OSPM to initiate the cooling policies at the desired target temperatures. The platform can emphasize active or passive cooling modes by assigning different threshold values. Generally, if _ACx is set lower than _PSV, then the system emphasizes active cooling. Conversely, if _PSV is set lower than _ACx, then the emphasis is placed on passive cooling.

For example, a thermal zone that includes a processor and one single-speed fan may use _PSV to indicate the temperature value at which OSPM would enable passive cooling and _AC0 to indicate the temperature at which the fan would be turned on. If the value of _PSV is less than _AC0 then the

system will favor passive cooling (for example, CPU clock throttling). On the other hand, if AC0 is less than PSV the system will favor active cooling (in other words, using the fan). See <u>Figure 11-63</u> below.




Figure 11-63 Cooling Preferences

The example on the left enables active cooling (for example, turn on a fan) when OSPM detects the temperature has risen above 50°. If for some reason the fan does not reduce the system temperature, then at 75° OSPM will initiate passive cooling (for example, CPU throttling) while still running the fan. If the temperature continues to climb, OSPM will quickly shut the system down when the temperature reaches 90°C. The example on the right is similar but the _AC0 and _PSV threshold values have been swapped to emphasize passive cooling.

The ACPI thermal model allows flexibility in the thermal zone design. An OEM that needs a less elaborate thermal implementation may consider using only a single threshold (for example, _CRT). Complex thermal implementations can be modeled using multiple active cooling thresholds and devices, or through the use of additional thermal zones.

11.2.1 Evaluating Thermal Device Lists

The **Notify**(*thermal_zone*, 0x82) statement is used to inform OSPM that a change has been made to the thermal zone device lists. This thermal event instructs OSPM to re-evaluate the _ALx, _PSL, and _TZD objects.

For example, a system that supports the dynamic insertions of processors might issue this notification to inform OSPM of changes to _PSL following the insertion or removal of a processor. OSPM would re-evaluate all thermal device lists and adjust its policy accordingly.

Notice that this notification can be used with the **Notify**(*thermal_zone*, 0x81) statement to inform OSPM to both re-evaluate all device lists and all thresholds.

Alternatively, devices may include the _TZM (Thermal Zone Member) object their device scope to convey their thermal zone association to OSPM. <u>Section 11.4.20</u>, "_TZM (Thermal Zone Member)", for more information.

11.2.2 Evaluating Device Thermal Relationship Information

The **Notify**(*thermal_zone*, 0x83) statement is used to inform OSPM that a change has been made to the thermal relationship information. This thermal event instructs OSPM to re-evaluate the _TRT and _ART objects. The thermal influence between devices may change when active cooling moves air across device packages as compared to when only passive cooling controls are applied. Similarly, the active cooling relationship may change as various fans are engaged to actively cool a platform or if user preferences change.

11.2.3Fan Device Notifications

Notify events of type 0x80 will cause OSPM to evaluate the _FST object to evaluate the fan's current speed.

11.3 Fan Device

ACPI 1.0 defined a simple fan device that is assumed to be in operation when it is in the D0 state. Thermal zones reference fan device(s) as being responsible primarily for cooling within that zone. Notice that multiple fan devices can be present for any one thermal zone. They might be actual different fans, or they might be used to implement one fan of multiple speeds (for example, by turning both "fans" on the one fan will run full speed).

ACPI 4.0 defines additional fan device interface objects enabling OSPM to perform more robust active cooling thermal control. These objects are summarized in <u>Table 11-259</u>. OSPM requires that all of the objects listed in <u>Table 11-259</u> be defined under a fan device to enable advanced active cooling control. The absence of any of these objects causes OSPM to perform ACPI 1.0 style simple fan control.

The Plug and Play ID of a fan device is PNP0C0B.

Table 11-259 Fan Specific Objects

Object	Description
_FIF	Returns fan device information.
_FPS	Returns a list of supported fan performance states.
_FSL	Control method that sets the fan device's speed level (performance state).
_FST	Returns current status information for a fan device.

While the Fan Device and its associated objects are optional, if the Fan Device is implemented by the platform, all objects listed in <u>Table 11-259</u> are required and must be provided.

11.3.1 Fan Objects

11.3.1.1 _FIF (Fan Information)

The optional FIF object provides OSPM with fan device capability information.

Arguments:

None

Return Value:

A **Package** containing the fan device parameters as described in <u>Table 11-260</u> below FIF evaluation returns a package of the following format:

Table 11-260 FIF Package Details

Field	Format	Description
Revision	Integer	Current revision is: 0
Fine Grain Control	Integer (Boolean)	A non zero value in this field indicates OSPM may evaluate the fan device's _FSL object with a Level argument value in the range of 0-100, which represents a percentage of maximum speed. A zero value in this field indicates that OSPM may evaluate the fan device's _FSL object with a Level argument value that is a Control field value from a package in the _FPS object's package list only.
Step Size	Integer (DWORD)	The recommended minimum step size in percentage points to be used when OSPM performs fine-grained fan speed control. OSPM may utilize the value of this field if the FineGrainControl field is non-zero the value in this field is between 1 and 9.
Low Speed Notification Support	Integer (Boolean)	A non zero value in this field indicates that the platform will issue a Notify (0x80) to the fan device if a low (errant) fan speed is detected.

If a fan device supports fine-grained control, OSPM may evaluate a fan device's _FSL object with any Level argument value that is less than or equal to the Control field value specified in the package of the _FPS object's package list that corresponds to the active cooling trip point that has been exceeded. This capability provides OSPM access to one hundred fan speed settings thus enabling fine-grained fan speed control. The platform uses the StepSize field to help OSPM optimize its fan level selection policy by fine-grained fan speed control. The platform uses the StepSize field to help OSPM optimize its fan level selection policy by indicating recommended increments in the fan speed level value that are appropriate for the fan when one percent increments are not optimal. In the event OSPM's incremental selections of Level using the StepSize field value do not sum to 100%, OSPM may select an appropriate ending Level increment to reach 100%. OSPM should use the same residual step value first when reducing Level.

11.3.1.2 FPS (Fan Performance States)

The optional _FPS object evaluates to a variable-length package containing a list of packages that describe the fan device's performance states. A temperature reading above an active cooling trip point defined by an _ACx object in a thermal zone or above a native active cooling trip point of a device within the thermal zone causes OSPM thermal control to engage the appropriate corresponding fan performance state from the list of fan performance states described by the _FPS object if the fan device is present in the corresponding _ALx device list or if an entry exists for the fan and trip point in the active cooling relationship table (ART).

OSPM assumes a linear relationship for the acoustic impact and power consumption values between successive entries in the fan performance state list. Notice that the acoustic impact measurement unit (Decibels) is inherently non-linear. As such, the platform should populate _FPS entries as necessary to enable OSPM to achieve optimal results.

Arguments:

None

Return Value:

A variable-length **Package** containing a Revision ID and a list of **Package**s that describe the fan device's performance states as described in <u>Table 11-261</u> below.

Return Value Information

Each FanPState sub-**Package** contains the elements described below:

```
Package () // Fan P-State {

Control, // Integer DWORD TripPoint, // Integer DWORD Speed, // Integer DWORD NoiseLevel, // Integer DWORD Power // Integer DWORD }
```

Table 11-261 FPS FanPstate Package Details

Field	Format	Description
Control	Integer (DWORD)	Indicates the value to be used to set the fan speed to a specific level using the _FSL object. If the fan device supports fine-grained control as indicated by the _FIF object, this value is a percentage (0-100) of maximum speed level. If the fan device does not support fine-grained control, this field is an opaque value that OSPM must simply use in its evaluation of the _FSL object to set the level to this performance state.

Field	Format	Description
TripPoint	Integer (DWORD)	0-9: The active cooling trip point number that corresponds to this performance state. If the _ART object is defined, OSPM may optionally use information provided by the _ART object and _FPS objects to select alternative fan performance states. Only one entry per unique trip point number is allowed in the _FPS. 0x0A- 0xFFFFFFE: Reserved 0x0FFFFFFFF: Indicates that this performance state does not correspond with a specific active cooling trip point.
Speed	Integer (DWORD)	Indicates the speed of the fan in revolutions per minute in this performance state.
NoiseLevel	Integer (DWORD)	This optional field indicates the audible noise emitted by the fan in this performance state. The value represents the noise in 10ths of decibels. For example, if the fan emits noise at 28.3dB in this performance state, the value of this field would be 283. A value of 0xFFFFFFF indicates that this field is not populated.
Power	Integer (DWORD)	This optional field indicates the power consumption (in milliwatts) of the fan in this performance state. For example, if the fan consumes .5W in this performance state, the value of this field would be 500. A value of 0xFFFFFFF indicates that this field is not populated.

11.3.1.3 FSL (Fan Set Level)

The optional _FSL object is a control method that OSPM evaluates to set a fan device's speed (performance state) to a specific level

Arguments: (1)

Arg0 – Level (**Integer**): conveys to the platform the fan speed level to be set.

Return Value:

None

Argument Information

Arg0: Level. If the fan supports fine-grained control, Level is a percentage of maximum level (0-100) that the platform is to engage the fan. If the fan does not support fine-grained control, Level is a Control field value from a package in the _FPS object's package list. A Level value of zero causes the platform to turn off the fan.

11.3.1.4 _FST (Fan Status)

The optional FST object provides status information for the fan device.

Arguments:

None

Return Value:

A **Package** containing fan device status information as described in <u>Table 11-262</u> below FST evaluation returns a package of the following format:

Table 11-262 FST Package Details

Field	Format	Description
Revision	Integer	Current revision is: 0
Control	Integer (DWORD)	The current control value used to operate the Fan. If the fan is not operating Control will be zero. If the fan is operating, Control is the Level argument passed in the evaluation of the _FSL object.
Speed	Integer (DWORD)	The current fan speed in revolutions per minute at which the fan is rotating. A value of 0xFFFFFFF indicates that the fan does not support speed reporting.

11.4 Thermal Objects

Objects related to thermal management are listed in the following table.

Table 11-263 Thermal Objects

Object	Description
_ACx	Returns active cooling policy threshold values in tenths of degrees.
_ALx	List of active cooling device objects.
_ART	Table of values that convey the Active Cooling Relationship between devices
_CRT	Returns critical trip point in tenths of degrees where OSPM must perform a critical shutdown.
_HOT	Returns critical trip point in tenths of degrees where OSPM may choose to transition the system into S4.
_NTT	Returns the temperature change threshold for devices containing native temperature sensors to cause evaluation of the _TPT object
_PSL	List of processor device objects for clock throttling.
_PSV	Returns the passive cooling policy threshold value in tenths of degrees.
_RTV	Conveys whether temperatures are expressed in terms of absolute or relative values.
_SCP	Sets platform cooling policy (active or passive).
_TC1	Thermal constant for passive cooling.
_TC2	Thermal constant for passive cooling.
_TMP	Returns the thermal zone's current temperature in tenths of degrees.
_TPT	Conveys the temperature of a devices internal temperature sensor to the platform when a temperature trip point is crossed or a meaningful change in temperature occurs.
_TRT	Table of values that convey the Thermal Relationship between devices
_TSP	Thermal sampling period for Passive cooling in tenths of seconds.

Object	Description
_TST	Conveys the minimum separation for a devices' programmable temperature trip points.
_TZD	List of devices whose temperature is measured by this thermal zone.
_TZM	Returns the thermal zone for which a device is a member.
_TZP	Thermal zone polling frequency in tenths of seconds.

With the exception of _TPT, _TST, and the _TZM objects, the objects described in the following sections may exist under a thermal zone. Devices with embedded thermal sensors and controls may contain static cooling temperature trip points or dynamic cooling temperature trip points that must be programmed by the device's driver. In this case, thermal objects defined under a device serve to convey the platform specific values for these settings to the devices driver.

11.4.1 _ACx (Active Cooling)

This optional object, if present under a thermal zone, returns the temperature trip point at which OSPM must start or stop Active cooling, where x is a value between 0 and 9 that designates multiple active cooling levels of the thermal zone. If the Active cooling device has one cooling level (that is, "on") then that cooling level must be defined as _AC0. If the cooling device has two levels of capability, such as a high fan speed and a low fan speed, then they must be defined as _AC0 and _AC1 respectively. The smaller the value of x, the greater the cooling strength _ACx represents. In the above example, _AC0 represents the greater level of cooling (the faster fan speed) and _AC1 represents the lesser level of cooling (the slower fan speed). For every _ACx method, there must be a matching _ALx object or a corresponding entry in an _ART object's active cooling relationship list.

If this object it present under a device, the device's driver evaluates this object to determine the device's corresponding active cooling temperature trip point. This value may then be used by the device's driver to program an internal device temperature sensor trip point. When this object is present under a device, the device must contain a native OS device driver interface supporting a corresponding active cooling control, a matching _ALx object under the thermal zone of which the device is a member must exist, or a corresponding entry in an _ART object's active cooling relationship list must.

Arguments:

None

Return Value:

An **Integer** containing the active cooling temperature threshold in tenths of degrees Kelvin The return value is an integer that represents tenths of degrees Kelvin. For example, 300.0K is represented by the integer 3000.

11.4.2 _ALx (Active List)

This object is defined under a thermal zone and evaluates to a list of Active cooling devices to be turned on when the corresponding _ACx temperature threshold is exceeded. For example, these devices could be fans.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to active cooling devices

The return value is a package consisting of references to all active cooling devices that should be engaged when the associated active cooling threshold (ACx) is exceeded.

When the returned package consists of references to an active cooling device that is a fan device and the fan device implements _FPS and _FSL objects, OSPM activates the identified fan at a capability level matching the level identified by this object. For example, if the system has a fan that implements _FPS object with 5 levels, and if _AL3 is evaluated by the OSPM causing it to return this fan's reference, then the fan is activated by evaluating _FSL with the value from the Control field of an FPS entry whose TripPoint field value equals 3.

If a thermal zone has the _ART object defined, then it is not necessary to have any _ALx objects implemented.

Note: If a thermal zone has _ART object defined as well as _ALx defined, the OSPM ignores _ALx objects and uses _ART exclusively.

11.4.3 _ART (Active Cooling Relationship Table)

The optional _ART object evaluates to a variable-length package containing a list of packages each of which describes the active cooling relationship between a device within a thermal zone and an active cooling device. OSPM uses the combined information about the active cooling relationships of all devices in the thermal zone to make active cooling policy decisions.

If _ART is implemented within a thermal zone, OSPM ignores all _ALx objects as _ART conveys a mapping for each of the ACx trip points to active cooling devices.

The platform can dynamically change the _ART object by notifying the thermal zone object with a Notify code of 0x83, which will cause OSPM to re-evaluate both the _TRT and _ART objects. This allows the platform to change the capability level mapping to various _ACx trip points dynamically at run time.

Arguments:

None

Return Value:

A variable-length **Package** containing a Revision ID and a list of Active Relationship **Packages** as described below:

Return Value Information

Each ActiveRelationship sub-Package contains the elements described below:

```
Package {
                           // Object R
// Object R
// Integer
     SourceDevice,
                                                // Object Reference to a Fan Device Object
     TargetDevice,
                                               // Object Reference to a Device Object
     Weight,
     ACOMaxLevel,
     AC1MaxLevel,
     AC2MaxLevel,
     AC3MaxLevel,
     AC4MaxLevel,
     AC5MaxLevel,
     AC6MaxLevel,
    AC7MaxLevel,
     AC8MaxLevel,
     AC9MaxLevel
```

Table 11-264 Thermal Relationship Package Values

Element	Object Type	Description
SourceDevice	Reference (to a device)	The fan device that has an impact on the cooling of the device indicated by <i>TargetDevice</i> .
TargetDevice	Reference (to a device)	The device that is impacted by the fan device indicated by <i>SourceDevice</i> .
Weight	Integer	Indicates the SourceDevice's contribution to the platform's TargetDevice total cooling capability when the fans of all entries in the _ART with the same target device are engaged at their highest (maximum capability) performance state. This is represented as a percentage value (0-100).
AC0MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC0 trip point value. A value of 0xFFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.
AC1MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC1 trip point value. A value of 0xFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.

Element	Object Type	Description
AC2MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC2 trip point value. A value of 0xFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.
AC3MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC3 trip point value. A value of 0xFFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.
AC4MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC4 trip point value. A value of 0xFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.
AC5MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC5 trip point value. A value of 0xFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.
AC6MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC6 trip point value. A value of 0xFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.
AC7MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC7 trip point value. A value of 0xFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.
AC8MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC8 trip point value. A value of 0xFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.
AC9MaxLevel	Integer (DWORD)	Indicates the maximum fans speed level in percent (0-100) that OSPM may engage on the <i>SourceDevice</i> when a temperature exceeds the _AC9 trip point value. A value of 0xFFFFFFF in this field indicates that the SourceDevice is not to be engaged for the trip point.

In the case multiple active cooling trip points have been exceeded and _ART entries indicate various maximum limits for the same SourceDevice, OSPM may operate the SourceDevice up to the highest ACxMaxLevel value indicated for all exceeded trip points.

11.4.4 _CRT (Critical Temperature)

This object, when defined under a thermal zone, returns the critical temperature at which OSPM must shutdown the system. If this object it present under a device, the device's driver evaluates this object to determine the device's critical cooling temperature trip point. This value may then be used by the device's driver to program an internal device temperature sensor trip point.

Arguments:

None

Return Value:

An Integer containing the critical temperature threshold in tenths of degrees Kelvin

The result is an integer value that represents the critical shutdown threshold in tenths of degrees. For example, 300.0K is represented by the integer 3000.

11.4.5 _DTI (Device Temperature Indication)

This optional object may be present under a device and is evaluated by OSPM when the device's native (driver managed) temperature sensor has crossed a cooling temperature trip point or when a meaningful change in temperature (as indicated by evaluation of the _NTT object) has occurred. OSPM evaluation of the _DTI object enables the platform to take action as a result of these events. For example, the platform may choose to implement fan control hysteresis based on the conveyed value or signal the revaluation of the _TDL or _PDL objects.

Arguments: (1)

Arg0 – An **Integer** containing the current value of the temperature sensor (in tenths Kelvin)

Return Value:

None

11.4.6 _HOT (Hot Temperature)

This optional object, when defined under a thermal zone, returns the critical temperature at which OSPM may choose to transition the system into the S4 sleeping state. The platform vendor should define _HOT to be far enough below _CRT so as to allow OSPM enough time to transition the system into the S4 sleeping state. While dependent on the amount of installed memory, on typical platforms OSPM implementations can transition the system into the S4 sleeping state in tens of seconds. If this object it present under a device, the device's driver evaluates this object to determine the device's hot cooling temperature trip point. This value may then be used by the device's driver to program an internal device temperature sensor trip point.

Arguments:

None

Return Value:

An **Integer** containing the critical temperature threshold in tenths of degrees Kelvin

The return value is an integer that represents the critical sleep threshold tenths of degrees Kelvin. For example, 300.0K is represented by the integer 3000.

11.4.7 NTT (Notification Temperature Threshold)

This optional object may be defined under devices containing native temperature sensors and evaluates to the temperature change threshold for the device where the platform requires notification of the change via evaluation of the TPT object.

Arguments:

None

Return Value:

An **Integer** containing the temperature threshold in tenths of degrees Kelvin.

The return value is an integer that represents the amount of change in device temperature that is meaningful to the platform and for which the platform requires notification via evaluation of the _TPT object.

11.4.8 PSL (Passive List)

This object is defined under a thermal zone and evaluates to a list of processor objects to be used for passive cooling.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to processor objects

The return value is a package consisting of references to all processor objects that will be used for passive cooling when the zone's passive cooling threshold (PSV) is exceeded.

11.4.9 **_PSV** (Passive)

This optional object, if present under a thermal zone, evaluates to the temperature at which OSPM must activate passive cooling policy.

Arguments:

None

Return Value:

An Integer containing the passive cooling temperature threshold in tenths of degrees Kelvin

The return value is an integer that represents tenths of degrees Kelvin. For example, 300.0 Kelvin is represented by 3000.

If this object it present under a device, the device's driver evaluates this object to determine the device's corresponding passive cooling temperature trip point. This value may then be used by the device's driver to program an internal device temperature sensor trip point. When this object is present under a device, the device must contain a native OS device driver interface supporting a passive cooling control.

11.4.10 _RTV (Relative Temperature Values)

This optional object may be present under a device or a thermal zone and is evaluated by OSPM to determine whether the values returned by temperature trip point and current operating temperature interfaces under the corresponding device or thermal zone represent absolute or relative temperature values.

Arguments:

None

Return Value:

An Integer containing a relative versus absolute indicator

0 Temperatures are absolute
Other Temperatures are relative

The return value is an integer that indicates whether values returned by temperature trip point and current operating temperature interfaces represent absolute or relative temperature values.

If the _RTV object is not present or is present and evaluates to zero then OSPM assumes that all values returned by temperature trip point and current operating temperature interfaces under the device or thermal zone represent absolute temperature values expressed in tenths of degrees Kelvin.

If the _RTV object is present and evaluates to a non zero value then all values returned by temperature trip point and current operating temperature interfaces under the corresponding device or thermal zone represent temperature values relative to a zero point that is defined as the maximum value of the device's or thermal zone's critical cooling temperature trip point. In this case, temperature trip point and current operating temperature interfaces return values in units that are tenths of degrees **below** the zero point.

OSPM evaluates the _RTV object before evaluating any other temperature trip point or current operating temperature interfaces.

11.4.11 _SCP (Set Cooling Policy)

This optional object is a control method that OSPM invokes to set the platform's cooling mode policy setting. The platform may use the evaluation of _SCP to reassign _ACx and _PSV temperature trip points according to the mode or limits conveyed by OSPM. OSPM will automatically evaluate _ACx and _PSV objects after executing _SCP. This object may exist under a thermal zone or a device.

Arguments: (3)

Arg0 – *Mode* An **Integer** containing the cooling mode policy code

Arg1 – *AcousticLimit* An **Integer** containing the acoustic limit

Arg2 – *PowerLimit* An **Integer** containing the power limit

Return Value:

None

Argument Information:

Mode - 0 = Active, 1 = Passive

Acoustic Limit – Specifies the maximum acceptable acoustic level that active cooling devices may generate. Values are 1 to 5 where 1 means no acoustic tolerance and 5 means maximum acoustic tolerance.

Power Limit – Specifies the maximum acceptable power level that active cooling devices may consume. Values are from 1 to 5 where 1 means no power may be used to cool and 5 means maximum power may be used to cool.

Example:

```
// Fan Control is defined as follows:
      Speed 1 (Fan is Off): Acoustic Limit 1, Power Limit 1, <= 64C
11
11
      Speed 2: Acoustic Limit 2, Power Limit 2, 65C - 74C
      Speed 3:
//
                     Acoustic Limit 3, Power Limit 3, 75C - 84C
                    Acoustic Limit 4, Power Limit 4, 85C - 94C
      Speed 4:
11
                    Acoustic Limit 5, Power Limit 5, >= 95C
11
      Speed 5:
// _SCP Notifies the platform the current cooling mode.
   Arg0 = Mode
//
        0 - Active cooling
        1 - Passive cooling
//
   Arg1 = Acoustic Limit
11
      1 = No acoustic tolerance
//
//
       5 = maximum acoustic tolerance
11
   Arg2 = Power Limit
11
11
      1 = No power may be used to cool
11
         5 = maximum power may be used to cool
Method(_SCP,3,Serialized)
    // Store the Cooling Mode in NVS and use as needed in
   // the rest of the ASL Code.
   Store(Arg0, CTYP)
   // Set PSVT to account for a Legacy OS that does not pass
    // in either the acoustic limit or Power Limit.
   If(Arg0)
    {
       Store(60, PSVT)
   Else
       Store(97, PSVT)
   If (CondRefOf (_OSI,Local0))
     If (\_OSI ("3.0 _SCP Extensions"))
       // Determine Power Limit.
       // NOTE1: PSVT = Passive Cooling Trip Point stored
       // in NVS in Celsius.
       11
       // NOTE2: 4 Active Cooling Trips Points correspond to 5
       // unique Power Limit regions and 5 unique acoustic limit
       // regions.
```

```
11
// NOTE3: This code will define Passive cooling so that
// CPU throttling will be initiated within the Power Limit
// Region passed in such that the next higher Power Limit
// Region will not be reached.
Switch(Arg2)
                     // Power Limit = 1.
    Case(1)
        // Stay in Acoustic Limit 1.
       Store(60,PSVT) // Passive = 60C.
    }
                     // Power Limit = 2.
    Case(2)
        // Store Highest supported Acoustic Level
        // at this Power Limit (1 or 2).
        Store(70, PSVT)
        If(Lequal(Arg1,1))
            // Stay in Acoustic Level 1.
           Store(60,PSVT)
        }
    Case(3)
                     // Power Limit = 3.
        // Store Highest supported Acoustic Level
        // at this Power Limit (1, 2, or 3).
        Store(80, PSVT)
        If(Lequal(Arg1,2))
            // Stay in Acoustic Level 1 or 2.
           Store(70,PSVT)
        If(Lequal(Arg1,1))
            // Stay in Acoustic Level 1.
           Store(60,PSVT)
    Case(4)
                     // Power Limit = 4.
        // Store Highest supported Acoustic Level
        // at this Power Limit (1, 2, 3, or 4).
        Store(90, PSVT)
        If(Lequal(Arg1,3))
            // Stay in Acoustic Level 1 or 2.
           Store(80,PSVT)
        If(Lequal(Arg1,2))
            // Stay in Acoustic Level 1 or 2.
            Store(70,PSVT)
        If(Lequal(Arg1,1))
            // Stay in Acoustic Level 1.
            Store(60,PSVT)
```

```
Case(5)
                               // Power Limit = 5.
                // Store Highest supported Acoustic Level
                // at this Power Limit (1, 2, 3, 4, or 5).
                Store(97, PSVT)
                If(Lequal(Arg1,4))
                    // Stay in Acoustic Level 1 or 2.
                    Store(90, PSVT)
                If(Lequal(Arg1,3))
                    // Stay in Acoustic Level 1 or 2.
                    Store(80,PSVT)
                If(Lequal(Arg1,2))
                    // Stay in Acoustic Level 1 or 2.
                    Store(70,PSVT)
                If(Lequal(Arg1,1))
                    // Stay in Acoustic Level 1.
                    Store(60, PSVT)
            } // Case 5
        } // Switch Arg 2
    } // _OSI - Extended _SCP
 } // CondRefOf _OSI
} // Method _SCP
```

11.4.12 _TC1 (Thermal Constant 1)

This object evaluates to the constant _TC1 for use in the Passive cooling formula:

$$\Delta$$
Performance [%]= TC1 * (Tn - Tn-1) + TC2 * (Tn. - Tt)

Arguments:

None

Return Value:

An Integer containing Thermal Constant #1

11.4.13 _TC2 (Thermal Constant 2)

This object evaluates to the constant TC2 for use in the Passive cooling formula:

```
\DeltaPerformance [%]= TC1 * (Tn - Tn-1) + TC2 *(Tn - Tt)
```

Arguments:

None

Return Value:

An **Integer** containing Thermal Constant #2

11.4.14 _TMP (Temperature)

This control method returns the thermal zone's current operating temperature.

Arguments:

None

Return Value:

An **Integer** containing the current temperature of the thermal zone (in tenths of degrees Kelvin) The return value is the current temperature of the thermal zone in tenths of degrees Kelvin. For example, 300.0K is represented by the integer 3000.

11.4.15 _TPT (Trip Point Temperature)

This optional object may be present under a device and is invoked by OSPM to indicate to the platform that the devices' embedded temperature sensor has crossed a cooling temperature trip point. After invocation, OSPM immediately evaluates the devices' Active and Passive cooling temperature trip point values. This enables the platform to implement hysteresis.

Arguments: (1)

Arg0 – An **Integer** containing the current value of the temperature sensor (in tenths Kelvin)

Return Value:

None

The _TPT object is deprecated in ACPI 4.0. The _DTI object , <u>Section 11.4.5</u> "_DTI (Device Temperature Indication)", should be used instead.

11.4.16 _TRT (Thermal Relationship Table)

This object evaluates to a package of packages each of which describes the thermal relationship between devices within a thermal zone. OSPM uses the combined information about the thermal relationships of all devices in the thermal zone to make thermal policy decisions.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of Thermal Relationship **Packages** as described below

Return Value Information

Each ThermalRelationship sub-Package contains the elements described below:

```
Package {
                                // Object Reference to a Device Object
   SourceDevice,
   TargetDevice,
                               // Object Reference to a Device Object
   Influence,
                               // Integer
   SamplingPeriod,
                                // Integer
   Reserved1,
                                // Integer
   Reserved2,
                                // Integer
   Reserved3,
                                // Integer
                                // Integer
   Reserved4
},
```

Table 11-265 Thermal Relationship Package Values

Element	Object Type	Description
Source Device	Reference (to a device)	The device that is influencing the device indicated by <i>TargetDevice</i> .
Target Device	Reference (to a device)	The device that is influenced by the device indicated by SourceDevice.
Influence	Integer	The thermal influence of <i>SourceDevice</i> on <i>TargetDevice</i> - represented as tenths of degrees Kelvin that the device indicated by <i>SourceDevice</i> raises the temperature of the device indicated by <i>TargetDevice</i> per watt of thermal load that <i>SourceDevice</i> generates.
Sampling Period	Integer	The minimum period of time in tenths of seconds that OSPM should wait after applying a passive control to the device indicated by <i>SourceDevice</i> to detect its impact on the device indicated by <i>TargetDevice</i> .
Reserved (1-4)	Integer	Reserved for future use.

11.4.17 _TSP (Thermal Sampling Period)

This object evaluates to a thermal sampling period (in tenths of seconds) used by OSPM to implement the Passive cooling equation. This value, along with _TC1 and _TC2, will enable OSPM to provide the proper hysteresis required by the system to accomplish an effective passive cooling policy.

Arguments:

None

Return Value:

An **Integer** containing the sampling period in tenths of seconds

The granularity of the sampling period is 0.1 seconds. For example, if the sampling period is 30.0 seconds, then _TSP needs to report 300; if the sampling period is 0.5 seconds, then it will report 5. OSPM can normalize the sampling over a longer period if necessary.

11.4.18 _TST (Temperature Sensor Threshold)

This optional object may be present under a device and is evaluated by OSPM to determine the minimum separation for a devices' programmable temperature trip points. When a device contains multiple programmable temperature trip points, it may not be necessary for OSPM to poll the

device's temperature after crossing a temperature trip point when performing passive cooling control policy.

Arguments:

None

Return Value:

An **Integer** containing the sensor threshold (in tenths of degrees Kelvin)

To eliminate polling, the device can program intermediate trip points of interest (higher or lower than the current temperature) and signal the crossing of the intermediate trip points to OSPM. The distance between the current temperature and these intermediate trip points may be platform specific and must be set far enough away from the current temperature so as to not to miss the crossing of a meaningful temperature point. The _TST object conveys the recommended minimum separation between the current temperature and an intermediate temperature trip point to OSPM.

11.4.19 _TZD (Thermal Zone Devices)

This optional object evaluates to a package of device names. Each name corresponds to a device in the ACPI namespace that is associated with the thermal zone. The temperature reported by the thermal zone is roughly correspondent to that of each of the devices.

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **References** to thermal zone devices

The list of devices returned by the control method need not be a complete and absolute list of devices affected by the thermal zone. However, the package should at least contain the devices that would uniquely identify where this thermal zone is located in the machine. For example, a thermal zone in a docking station should include a device in the docking station, a thermal zone for the CD-ROM bay, should include the CD-ROM.

11.4.20 _TZM (Thermal Zone Member)

This optional object may exist under any device definition and evaluates to a reference to the thermal zone of which the device is a member.

Arguments:

None

Return Value:

A Reference to the parent device

11.4.21 _TZP (Thermal Zone Polling)

This optional object evaluates to a *recommended* polling frequency (in tenths of seconds) for this thermal zone. A value of zero indicates that OSPM does not need to poll the temperature of this

thermal zone in order to detect temperature changes (the hardware is capable of generating asynchronous notifications).

Arguments:

None

Return Value:

An **Integer** containing the recommended polling frequency in tenths of seconds

The return value contains the recommended polling frequency, in tenths of seconds. A value of zero indicates that polling is not necessary.

The use of polling is allowed but strongly discouraged by this specification. OEMs should design systems that asynchronously notify OSPM whenever a meaningful change in the zone's temperature occurs—relieving the OS of the overhead associated with polling. See <u>Section 11.1.3</u>, "Detecting Temperature Changes," for more information.

This value is specified as tenths of seconds with a 1 second granularity. A minimum value of 30 seconds (_TZP evaluates to 300) and a maximum value of 300 seconds (in other words, 5 minutes) (_TZP evaluates to 3000) may be specified. As this is a *recommended* value, OSPM will consider other factors when determining the actual polling frequency to use.

11.5 Native OS Device Driver Thermal Interfaces

OS implementations compatible with the ACPI 3.0 thermal model, interface with the thermal objects of a thermal zone but also comprehend the thermal zone devices' OS native device driver interfaces that perform similar functions to the thermal objects at the device level.

The recommended native OS device driver thermal interfaces that enable OSPM to perform optimal performance / thermal management include:

- Reading a value from a device's embedded thermal sensor
- Reading a value that indicates whether temperature and trip point values are reported in absolute or relative temperatures
- Setting the platform's cooling mode policy setting
- Reading the embedded thermal sensor's threshold
- Reading the device's active and passive cooling temperature trip points
- Reading the device's association to a thermal zone
- Signaling the crossing of a thermal trip point
- Reading the desired polling frequency at which to check the devices temperature if the device cannot signal OSPM or signal OSPM optimally (both before and after a temperature trip point is crossed)
- Setting / limiting a device's performance / throttling states
- Engaging / disengaging a device's active cooling controls

These interfaces are OS specific and as such the OS vendor defines the exact interface definition for each target operating system.

11.6 Thermal Zone Interface Requirements

While not all thermal zone interfaces are required to be present in each thermal zone, OSPM levies conditional requirements for the presence of specific thermal zone interfaces based on the existence of other related thermal zone interfaces. These interfaces may be implemented by thermal zone-wide objects or by OS-specific device driver exposed thermal interfaces. The requirements are outlined below:

- A thermal zone must contain at least one temperature interface; either the _TMP object or a member device temperature interface.
- A thermal zone must contain at least one trip point (critical, near critical, active, or passive).
- If _ACx is defined then an associated _ALx must be defined (e.g. defining _AC0 requires _AL0 also be defined).
- If _PSV is defined then either the _PSL or _TZD objects must exist. The _PSL and _TZD objects may both exist.
- If PSL is defined then:
 - If a linear performance control register is defined (via either P_BLK or the _PTC, _TSS, _TPC objects) for a processor defined in _PSL or for a processor device in the zone as indicated by _TZM then the _TC1, _TC2, and objects must exist. The _TSP object must also be defined if the device requires polling.
 - If a linear performance control register is not defined (via either P_BLK or the _PTC, _TSS, _TPC objects) for a processor defined in _PSL or for a processor device in the zone as indicated by _TZM then the processor must support processor performance states (in other words, the processor's processor object must include _PCT, _PSS, and _PPC).
- If _PSV is defined and _PSL is not defined then at least one device in thermal zone, as indicated
 by either the _TZD device list or devices' _TZM objects, must support device performance
 states.
- SCP is optional.
- TZD is optional outside of the PSV requirement outlined above.
- If HOT is defined then the system must support the S4 sleeping state.

11.7 Thermal Zone Examples

11.7.1 Example: The Basic Thermal Zone

The following ASL describes a basic configuration where the entire system is treated as a single thermal zone. Cooling devices for this thermal zone consist of a processor and one single-speed fan. This is an example only.

Notice that this thermal zone object (TZ0) is defined in the \SB scope. Thermal zone objects should appear in the namespace under the portion of the system that comprises the thermal zone. For example, a thermal zone that is isolated to a docking station should be defined within the scope of the docking station device. Besides providing for a well-organized namespace, this configuration allows OSPM to dynamically adjust its thermal policy as devices are added or removed from the system.

```
Scope(\_SB) {
    Processor(
       CPU0,
                                                // unique number for this processor
        1,
                                                // system IO address of Pblk Registers
        0x110.
        0x06
                                                // length in bytes of PBlk
    ) {}
Scope(\_SB.PCI0.ISA0) {
    Device(EC0) {
        Name(_HID, EISAID("PNP0C09"))
                                                // ID for this EC
                                                 // current resource description for this EC
        Name(_CRS, ResourceTemplate() {
            IO(Decode16,0x62,0x62,0,1)
            IO(Decode16,0x66,0x66,0,1)
        })
        Name(_GPE, 0)
                                                 // GPE index for this EC
        // create EC's region and field for thermal support
        OperationRegion(ECO, EmbeddedControl, 0, 0xFF)
        Field(ECO, ByteAcc, Lock, Preserve) {
            MODE,
                    1,
                                                 // thermal policy (quiet/perform)
            FAN,
                                                 // fan power (on/off)
                    1,
                                                 // reserved
                     6.
            TMP.
                    16,
                                                 // current temp
            ACO,
                                                 // active cooling temp (fan high)
                    16,
                     16,
                                                 // reserved
            PSV.
                                                // passive cooling temp
                    16,
            HOT
                                                // critical S4 temp
                    16.
                                                 // critical temp
            CRT,
                    16
        \ensuremath{//} following is a method that OSPM will schedule after
        // it receives an SCI and queries the EC to receive value 7
        Method(_Q07) {
            Notify (\_SB.PCIO.ISAO.ECO.TZO, 0x80)
            // end of Notify method
    // fan cooling on/off - engaged at ACO temp
    PowerResource(PFAN, 0, 0) {
        \label{lem:method(STA) { Return (\SB.PCI0.ISA0.EC0.FAN) } // \ check power state Method(ON) { Store (One, \SB.PCI0.ISA0.EC0.FAN) } // \ turn on fan
        Method(_OFF) { Store ( Zero, \_SB.PCIO.ISAO.ECO.FAN) } // turn off fan
    // Create FAN device object
    Device (FAN) {
        // Device ID for the FAN
        Name(_HID, EISAID("PNP0C0B"))
        // list power resource for the fan
        Name(_PR0, Package(){PFAN})
    // create a thermal zone
    ThermalZone (TZ0) {
        Method(_TMP) { Return (\_SB.PCI0.ISA0.EC0.TMP )}
                                                              // get current temp
                                                              // fan high temp
        Method(_AC0) { Return (\_SB.PCI0.ISA0.EC0.AC0) }
        Name(_AL0, Package(){\_SB.PCI0.ISA0.EC0.FAN})
                                                              // fan is act cool dev
        Method(_PSV) { Return (\_SB.PCI0.ISA0.EC0.PSV) }
                                                              // passive cooling temp
        Name(_PSL, Package (){\_SB.CPU0})
                                                              // passive cooling devices
        Method(_HOT) { Return (\_SB.PCI0.ISA0.EC0.HOT) }
                                                              // get critical S4 temp
```

```
Method(_CRT) { Return (\_SB.PCI0.ISA0.EC0.CRT) }
                                                                   // get critical temp
       Method(_SCP, 1) { Store (Arg1, \_SB.PCIO.ISAO.ECO.MODE) } // set cooling mode
       Name(_TC1, 4)
                                                                   // bogus example constant
       Name(_TC2, 3)
                                                                   // bogus example constant
       Name(_TSP, 150)
                                                                   // passive sampling = 15 sec
       Name(_TZP, 0)
                                                                   // polling not required
        } // end of TZ0
                                                                   // end of ECO
}
                                                                   // end of \_SB.PCIO.ISAO scope-
                                                                   // end of \_SB scope
```

11.7.2 Example: Multiple-Speed Fans

The following ASL describes a thermal zone consisting of a processor and one dual-speed fan. As with the previous example, this thermal zone object (TZ0) is defined in the _SB scope and represents the entire system. This is an example only.

```
Scope(\_SB) {
   Processor(
       CPU0,
       1.
                   // unique number for this processor
                  // system IO address of Pblk Registers
                   // length in bytes of PBlk
    ) {}
Scope(\_SB.PCI0.ISA0) {
   Device(EC0) {
       Name(_HID, EISAID("PNP0C09"))
                                            // ID for this EC
        // current resource description for this EC
       Name(_CRS, ResourceTemplate() {
           IO(Decode16,0x62,0x62,0,1)
           IO(Decode16,0x66,0x66,0,1)
        })
                            // GPE index for this EC
       Name(_GPE, 0)
       // create EC's region and field for thermal support
       OperationRegion(ECO, EmbeddedControl, O, OxFF)
       Field(EC0, ByteAcc, Lock, Preserve) {
           MODE,
                  1,  // thermal policy (quiet/perform)
                            // fan strength high/off
                    1,
           FANO,
                             // fan strength low/off
           FAN1,
                    1,
                             // reserved
                    5,
                             // current temp
           TMP.
                   16,
           ACO,
                   16,
                             // active cooling temp (high)
           AC1,
                   16,
                             // active cooling temp (low)
                             // passive cooling temp
                   16,
           HOT
                    18,
                             // critical S4 temp
           CRT,
                 16
                             // critical temp
       // following is a method that OSPM will schedule after it
        // receives an SCI and queries the EC to receive value 7
       Method(_Q07) {
           Notify (\_SB.PCIO.ISAO.ECO.TZO, 0x80)
        } end of Notify method
```

```
// fan cooling mode high/off - engaged at ACO temp
        PowerResource(FN10, 0, 0) {
           Method(_STA) { Return (\_SB.PCI0.ISA0.EC0.FAN0) }
           \label{lem:method(STA) { Return (\SB.PCIO.ISAO.ECO.FANO) } // check power state Method(ON) { Store (One, \SB.PCIO.ISAO.ECO.FANO) } // turn on fan at high
           Method(_OFF) { Store (Zero, \_SB.PCI0.ISA0.EC0.FAN0) } // turn off fan
       // fan cooling mode low/off
                                      - engaged at AC1 temp
       PowerResource(FN11, 0, 0) {
           Method(_OFF) { Store (Zero, \_SB.PCIO.ISAO.ECO.FAN1) } // turn off fan
}
    \ensuremath{//} Following is a single fan with two speeds. This is represented
    // by creating two logical fan devices. When FN2 is turned on then
    // the fan is at a low speed. When FN1 and FN2 are both on then
    // the fan is at high speed.
   11
    // Create FAN device object FN1
   Device (FN1) {
       // Device ID for the FAN
       Name(_HID, EISAID("PNP0C0B"))
       Name(_UID, 0)
       Name(_PR0, Package(){FN10, FN11})
    // Create FAN device object FN2
   Device (FN2) {
       // Device ID for the FAN
       Name(_HID, EISAID("PNP0C0B"))
       Name(_UID, 1)
       Name(_PR0, Package(){FN10})
    // create a thermal zone
   ThermalZone (TZ0) {
       Method(_TMP) { Return (\_SB.PCI0.ISA0.EC0.TMP )}
                                                               // get current temp
       Method(_AC0) { Return (\_SB.PCI0.ISA0.EC0.AC0) }
                                                                // fan high temp
       Method(_AC1) { Return (\_SB.PCI0.ISA0.EC0.AC1) }
                                                                // fan low temp
                                                                // active cooling (high)
       Name(_AL0, Package() {\_SB.PCI0.ISA0.EC0.FN1})
                                                                // active cooling (low)
       Name(_AL1, Package() {\_SB.PCI0.ISA0.EC0.FN2})
       Method(_PSV) { Return (\_SB.PCI0.ISA0.EC0.PSV) }
                                                                 // passive cooling temp
       Name(_PSL, Package() {\_SB.CPU0})
                                                                 // passive cooling devices
       Method(_HOT) { Return (\_SB.PCI0.ISA0.EC0.HOT) }
                                                                 // get critical S4 temp
       Method(_CRT) { Return (\_SB.PCI0.ISA0.EC0.CRT) }
                                                                 // get crit. temp
       Method(_SCP, 1) { Store (Arg1, \_SB.PCIO.ISAO.ECO.MODE) } // set cooling mode
       Name(_TC1, 4)
                                                                 // bogus example constant
       Name(_TC2, 3)
                                                                  // bogus example constant
       Name(_TSP, 150)
                                                                  // passive sampling = 15 sec
       Name(_TZP, 0)
                                                                  // polling not required
        } // end of TZ0
    } // end of ECO
    // end of \_SB.PCIO.ISAO scope
} // end of \_SB scope
```

11.7.3 Example: Thermal Zone with Multiple Devices

```
Scope(\_SB) {
   Device(CPU0) {
       Name(_HID, "ACPI0007")
       Name(_UID, 0)
       // Load additional objects if 3.0 Thermal model support is available
       11
       Method(_INI, 0) {
           If (\_OSI("3.0 Thermal Model")) {
               LoadTable("OEM1", "PmRef", "Cpu0", "\\_SB.CPU0") // 3.0 Thermal Model
        // For brevity, most processor objects have been excluded
        // from this example (such as _PSS, _CST, _PCT, _PPC, etc.)
       // Processor Throttle Control object
       Name(_PTC, ResourceTemplate() {
           Register(SystemIO, 32, 0, 0x120)
                                              // Processor Control
           Register(SystemIO, 32, 0, 0x120)
                                             // Processor Status
       })
       // Throttling Supported States
        // The values shown are for exemplary purposes only
       Name(_TSS, Package() {
       // Read: freq percentage, power, latency, control, status
           Package() \{0x64, 1000, 0x0, 0x7, 0x0\}, // Throttle off (100%)
           Package() {0x58, 800, 0x0, 0xF, 0x0},
                                                    // 87.5%
           Package() {0x4B, 600, 0x0, 0xE, 0x0},
                                                    // 75%
           Package() {0x3F, 400, 0x0, 0xD, 0x0}
                                                    // 62.5%
       })
       // Throttling Present Capabilities
        // The values shown are for exemplary purposes only
       Method(_TPC) {
           If(\_SB.AC) {
                            // All throttle states available
               Return(0)
           } Else {
                          // Throttle states >= 2 are available
               Return(2)
    } // end of CPU0 scope
   Device(CPU1) {
       Name(_HID, "ACPI0007")
       Name(_UID, 1)
       // Load additional objects if 3.0 Thermal model support is available
       11
       Method(_INI, 0) {
           If (\_OSI("3.0 Thermal Model")) {
               LoadTable("OEM1", "PmRef", "Cpu1", "\\_SB.CPU1") // 3.0 Thermal Model
        }
```

```
// For brevity, most processor objects have been excluded
        // from this example (such as _PSS, _CST, _PCT, _PPC, _PTC, etc.)
        // Processor Throttle Control object
       Name(_PTC, ResourceTemplate() {
           Register(SystemIO, 32, 0, 0x120)
                                                  // Processor Control
                                                  // Processor Status
           Register(SystemIO, 32, 0, 0x120)
       })
       // Throttling Supported States
        // The values shown are for exemplary purposes only
       Name(_TSS, Package() {
       // Read: freq percentage, power, latency, control, status
           Package() \{0x64, 1000, 0x0, 0x7, 0x0\}, // Throttle off (100%)
                                                  // 87.5%
// 75%
// 62.5%
           Package() {0x58, 800, 0x0, 0xF, 0x0},
           Package() {0x4B, 600, 0x0, 0xE, 0x0},
           Package() {0x3F, 400, 0x0, 0xD, 0x0}
       })
       // Throttling Present Capabilities
        // The values shown are for exemplary purposes only
       Method(_TPC) {
           If(\_SB.AC) {
               Return(0)
                                                      // All throttle states available
            } Else {
               Return(2)
                                                      // Throttle states >= 2 are available
       }
    }
                                                      // end of CPU1 scope
Scope(\_SB.PCI0.ISA0) {
   Device(EC0) {
       Name(_HID, EISAID("PNP0C09"))
                                                    // ID for this EC
       // Load additional objects if 3.0 Thermal model support is available
       11
       Method(_INI, 0) {
           If (\_OSI("3.0 Thermal Model")) {
               LoadTable("OEM1", "PmRef", "Tz3", "\\_SB.PCI0.ISA0.EC0") // 3.0 Tz
       }
        // Current resource description for this EC
       Name(_CRS,
               ResourceTemplate() {
                   IO(Decode16,0x62,0x62,0,1)
                   IO(Decode16,0x66,0x66,0,1)
           })
       Name(_GPE, 0)
                           // GPE index for this EC
        // Create EC's region and field for thermal support
        OperationRegion(EC0, EmbeddedControl, 0, 0xFF)
        Field(EC0, ByteAcc, Lock, Preserve) {
           MODE, 1, // thermal policy (quiet/perform)
                   1,
                             // fan strength high/off
           FANO,
                   6,
                            // reserved
           TMP,
                  16,
                            // current temp
                         // active cooling temp
           ACO, 16,
```

```
PSV, 16,
                            // passive cooling temp
           HOT, 16,
                             // critical S4 temp
           CRT,
                 16
                             // critical temp
       }
       // Following is a method that OSPM will schedule after it
    // fan cooling mode high/off - engaged at ACO temp
    PowerResource(FN10, 0, 0) {
       Method(_STA) { Return (\_SB.PCI0.ISA0.EC0.FAN0) }
                                                              // check power state
       Method(_ON) { Store (One, \_SB.PCIO.ISAO.ECO.FANO) } // turn on fan at high
       Method(_OFF) { Store (Zero, \_SB.PCIO.ISAO.ECO.FANO) } // turn off fan
    }
    // Following is a single fan with one speed.
    // Create FAN device object FN1
   Device (FN1) {
       // Device ID for the FAN
       Name(_HID, EISAID("PNP0C0B"))
       Name(_UID, 0)
       Name(_PR0, Package(){FN10})
       \ensuremath{//} Receives an SCI and queries the EC to receive value 7
       Method(_Q07) {
           Notify (\_SB.PCIO.ISAO.ECO.TZO, 0x80)
        } // end of Notify method
    // Create standard specific thermal zone
   ThermalZone (TZ0) {
                                                             // get current temp
       Method(_TMP) { Return (\_SB.PCIO.ISAO.ECO.TMP )}
       Name(_PSL, Package() {\_SB.CPU0, \_SB.CPU1})
                                                               // passive cooling devices
                                                               // active cooling
       Name(_AL0, Package() {\_SB.PCI0.ISA0.EC0.FN1})
       Method(_AC0) { Return (\_SB.PCI0.ISA0.EC0.AC0) }
                                                               // fan temp (high)
                                                                // fan temp (low)
       Method(_AC1) { Return (\_SB.PCI0.ISA0.EC0.AC1) }
                                                                // passive cooling temp
       Method(_PSV) { Return (\_SB.PCI0.ISA0.EC0.PSV) }
                                                                // get critical S4 temp
       Method(_HOT) { Return (\_SB.PCI0.ISA0.EC0.HOT) }
       Method(_CRT) { Return (\_SB.PCI0.ISA0.EC0.CRT) }
                                                                 // get crit. temp
                                                                 // bogus example constant
       Name(_TC1, 4)
       Name(_TC2, 3)
                                                                 // bogus example constant
       Method(_SCP, 1) { Store (Arg0, \_SB.PCI0.ISA0.EC0.MODE) } // set cooling mode
       Name(_TSP, 150)
                                                                 // passive sampling = 15 sec
       } // end of TZ0
    } // end of ECO
    // end of \_SB.PCIO.ISAO scope
) // end of \_SB scope
// ACPI 3.0 Thermal Model SSDT
DefinitionBlock (
   "TZASSDT.aml",
    "OEM1",
   0x01,
   "PmRef",
   "Tz3",
   0x3000
   External(\_SB.PCI0.ISA0.EC0, DeviceObj)
   External(\_SB.CPU0, DeviceObj)
```

```
External(\_SB.CPU1, DeviceObj)
   Scope(\_SB.PCI0.ISA0.EC0)
    // Create an ACPI 3.0 specific thermal zone
   ThermalZone (TZ0) {
       // This TRT is for exemplary purposes only
       Name(_TRT, Package() {
           // Thermal relationship package data. A package is generated for
           // each permutation of device sets. 2 devices = 4 entries.
           // Read: source, target, thermal influence, sampling period, 4 reserved
           Package () {\_SB.CPU0, \_SB.CPU0,
                                                20, 1, 0, 0, 0, 0},
                                  \_SB.CPU1, 10, 15, 0, 0, 0, 0},
           Package () {\_SB.CPU0,
           Package () {\_SB.CPU1,
                                  \_SB.CPU0, 10, 15, 0, 0, 0, 0},
           Package () {\_SB.CPU1, \_SB.CPU1, 20, 1, 0, 0, 0}
       }) // end of TRT
   } // end of TZ0
    } // end of ECO Scope
} // end of SSDT
// CPU0 3.0 Thermal Model SSDT
11
DefinitionBlock (
   "CPU0SSDT.aml",
   "OEM1",
   0x01,
   "PmRef",
   "CPUO",
   0x3000
   )
   External(\_SB.CPU0, DeviceObj)
   External(\_SB.PCI0.ISA0.TZ0, ThermalZoneObj)
   Scope(\_SB.CPU0)
       // Add the objects required for 3.0 extended thermal support
       // Create a region and fields for thermal support; the platform
       // fills in the values and traps on writes to enable hysteresis.
       // The Operation Region location is invalid
       OperationRegion(CP00, SystemMemory, 0x00000000, 0xA)
       Field(CP00, ByteAcc, Lock, Preserve) {
           SCP, 1,
                            // thermal policy (passive/active)
           RTV,
                            // absolute or relative temperature
                  1.
                   6,
                            // reserved
           ACO,
                  16,
                            // active cooling temp
                   16,
           PSV,
                            // passive cooling temp
                   16,
           CRT,
                             // critical temp
                            // Temp trip point crossed
                   16,
           TPT,
                             // Temp sensor threshold
           TST.
       }
       Method(_TZM, 0) { Return(\_SB.PCI0.ISA0.TZ0) } // thermal zone member
       // Some thermal zone methods are now located under the
       // thermal device participating in the 3.0 thermal model.
       // These methods provide device specific thermal information
```

```
Method(_SCP, 1) { Store (Arg0, \_SB.CPU0.SCP) } // set cooling mode
    Method(_RTV) { Return (\_SB.CPU0.RTV) }
                                                          // absolute or relative temp
    Method(_AC0) { Return (\_SB.CPU0.AC0) }
                                                        // active cooling (fan) temp
    Method(_PSV) { Return (\_SB.CPU0.PSV) }
                                                        // passive cooling temp
                                                        // critical temp
    Method(_CRT) { Return (\_SB.CPU0.CRT) }
    Name(_TC1, 4)
                                                          // thermal constant 1 (INVALID)
    Name(_TC2, 3)
                                                          // thermal constant 2 (INVALID)
    Method(_TPT, 1) { Store (Arg0, \_SB.CPU0.TPT)}
                                                         // trip point temp
    Method(_TST) { Return (\_SB.CPU0.TST) }
                                                          // temp sensor threshold
    } // end of CPU0 scope
} // end of SSDT
// CPU1 3.0 Thermal Model SSDT
DefinitionBlock (
   "CPU1SSDT.aml",
    "OEM1",
    0x01,
    "PmRef",
    "CPU1",
    0x3000
    )
    External(\_SB.CPU1, DeviceObj)
    External(\_SB.PCI0.ISA0.TZ0, ThermalZoneObj)
    Scope(\_SB.CPU1)
        // Add the objects required for 3.0 extended thermal support
        // Create a region and fields for thermal support; the platform
        // fills in the values and traps on writes to enable hysteresis.
        // The Operation Region location is invalid
        OperationRegion(CP01, SystemIO, 0x00000008, 0xA)
        Field(CP01, ByteAcc, Lock, Preserve) {
            SCP,
                  1,  // thermal policy (passive/active)
            RTV,
                     1,
                               // absolute or relative temperature
                              // reserved
                    6,
                               // active cooling temp
                    16,
            ACO,
                               // passive cooling temp
            PSV,
                    16,
                               // critical temp
// Temp trip point crossed
// Temp sensor threshold
                    16,
            CRT.
            TPT,
                    16,
            TST.
                   8
        Method(_TZM, 0) { Return(\_SB.PCI0.ISA0.TZ0) } // thermal zone member
        // Some thermal zone methods are now located under the
        // thermal device participating in the 3.0 thermal model.
        // These methods provide device specific thermal information
    \label{eq:method} \texttt{Method}(\_SCP, \ 1) \ \left\{ \ \texttt{Store} \ (\texttt{Arg0}, \ \backslash\_\texttt{SB.CPU1.SCP}) \ \right\} \\ \hspace*{0.5cm} // \ \texttt{set cooling mode}
    Method(_RTV) { Return (\_SB.CPU1.RTV) }
                                                           // absolute or relative temp
    Method(_AC0) { Return (\_SB.CPU1.AC0) }
                                                           // active cooling (fan) temp
    Method(_PSV) { Return (\_SB.CPU1.PSV) }
                                                           // passive cooling temp
    Method(_CRT) { Return (\_SB.CPU1.CRT) }
                                                            // critical temp
    Name(_TC1, 4)
                                                            // thermal constant 1 (INVALID)
    Name(_TC2, 3)
                                                            // thermal constant 2 (INVALID)
```

12

ACPI Embedded Controller Interface Specification

ACPI defines a standard hardware and software communications interface between an OS driver and an embedded controller. This allows any OS to provide a standard driver that can directly communicate with an embedded controller in the system, thus allowing other drivers within the system to communicate with and use the resources of system embedded controllers. This in turn enables the OEM to provide platform features that the OS OSPM and applications can take advantage of.

ACPI also defines a standard hardware and software communications interface between an OS driver and an Embedded Controller-based SMB-HC (EC-SMB-HC).

The ACPI standard supports multiple embedded controllers in a system, each with its own resources. Each embedded controller has a flat byte-addressable I/O space, currently defined as 256 bytes. Features implemented in the embedded controller have an event "query" mechanism that allows feature hardware implemented by the embedded controller to gain the attention of an OS driver or ASL/AML code handler. The interface has been specified to work on the most popular embedded controllers on the market today, only requiring changes in the way the embedded controller is "wired" to the host interface.

Two interfaces are specified:

- A private interface, exclusively owned by the embedded controller driver.
- A shared interface, used by the embedded controller driver and some other driver.

This interface is separate from the traditional PC keyboard controller. Some OEMs might choose to implement the ACPI Embedded Controller Interface (ECI) within the same embedded controller as the keyboard controller function, but the ECI requires its own unique host resources (interrupt event and access registers).

This interface does support sharing the ECI with an inter-environment interface (such as SMI) and relies on the ACPI-defined "Global Lock" protocol. Note, however, that HW-reduced ACPI platforms, which do not support the Global Lock, cannot share the EC interface. For information about the Global Lock interface, see <u>Section 5.2.10.1</u>, "Global Lock." Both the shared and private EC interfaces are described in the following sections.

The ECI has been designed such that a platform can use it in either the legacy or ACPI modes with minimal changes between the two operating environments. This is to encourage standardization for this interface to enable faster development of platforms as well as opening up features within these controllers to higher levels of software.

12.1 Embedded Controller Interface Description

Embedded controllers are the general class of microcontrollers used to support OEM-specific implementations. The ACPI specification supports embedded controllers in any platform design, as

long as the microcontroller conforms to one of the models described in this section. The embedded controller is a unique feature in that it can perform complex low-level functions through a simple interface to the host microprocessor(s).

Although there is a large variety of microcontrollers in the market today, the most commonly used embedded controllers include a host interface that connects the embedded controller to the host data bus, allowing bi-directional communications. A bi-directional interrupt scheme reduces the host processor latency in communicating with the embedded controller.

Currently, the most common host interface architecture incorporated into microcontrollers is modeled after the standard IA-PC architecture keyboard controller. This keyboard controller is accessed at 0x60 and 0x64 in system I/O space. Port 0x60 is termed the data register, and allows bidirectional data transfers to and from the host and embedded controller. Port 0x64 is termed the command/status register; it returns port status information upon a read, and generates a command sequence to the embedded controller upon a write. This same class of controllers also includes a second decode range that shares the same properties as the keyboard interface by having a command/status register and a data register. The following diagram graphically depicts this interface.




Figure 12-64 Shared Interface

The diagram above depicts the general register model supported by the ACPI Embedded Controller Interface.

Advanced Configuration and Power Interface Specification

The first method uses an embedded controller interface shared between OSPM and the system management code, which requires the Global Lock semaphore overhead to arbitrate ownership. The second method is a dedicated embedded controller decode range for sole use by OSPM driver. The following diagram illustrates the embedded controller architecture that includes a dedicated ACPI interface.




Figure 12-65 Private Interface

The private interface allows OSPM to communicate with the embedded controller without the additional software overhead associated with using the Global Lock. Several common system configurations can provide the additional embedded controller interfaces:

- Non-shared embedded controller. This will be the most common case where there is no need for
 the system management handler to communicate with the embedded controller when the system
 transitions to ACPI mode. OSPM processes all normal types of system management events, and
 the system management handler does not need to take any actions.
- Integrated keyboard controller and embedded controller. This provides three host interfaces as described earlier by including the standard keyboard controller in an existing component (chip set, I/O controller) and adding a discrete, standard embedded controller with two interfaces for system management activities.
- Standard keyboard controller and embedded controller. This provides three host interfaces by providing a keyboard controller as a distinct component, and two host interfaces are provided in the embedded controller for system management activities.
- Two embedded controllers. This provides up to four host interfaces by using two embedded controllers; one controller for system management activities providing up to two host interfaces, and one controller for keyboard controller functions providing up to two host interfaces.
- Embedded controller and no keyboard controller. Future platforms might provide keyboard functionality through an entirely different mechanism, which would allow for two host interfaces in an embedded controller for system management activities.

To handle the general embedded controller interface (as opposed to a dedicated interface) model, a method is available to make the embedded controller a shareable resource between multiple tasks running under the operating system's control and the system management interrupt handler. This method, as described in this section, requires several changes:

- Additional external hardware
- Embedded controller firmware changes
- System management interrupt handler firmware changes
- Operating software changes

Access to the shared embedded controller interface requires additional software to arbitrate between the operating system's use of the interface and the system management handler's use of the interface. This is done using the Global Lock as described in <u>Section 5.2.10.1</u>, "Global Lock", but is not supported on HW-reduced ACPI platforms.

This interface sharing protocol also requires embedded controller firmware changes, in order to ensure that collisions do not occur at the interface. A collision could occur if a byte is placed in the system output buffer and an interrupt is then generated. There is a small window of time when the incorrect recipient could receive the data. This problem is resolved by ensuring that the firmware in the embedded controller does not place any data in the output buffer until it is requested by OSPM or the system management handler.

More detailed algorithms and descriptions are provided in the following sections.

12.2 Embedded Controller Register Descriptions

The embedded controller contains three registers at two address locations: EC_SC and EC_DATA. The EC_SC, or Embedded Controller Status/Command register, acts as two registers: a status register for reads to this port and a command register for writes to this port. The EC_DATA (Embedded Controller Data register) acts as a port for transferring data between the host CPU and the embedded controller.

12.2.1 Embedded Controller Status, EC_SC (R)

This is a read-only register that indicates the current status of the embedded controller interface.

Table 12-266 Read only register table

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
IGN	SMI_EVT	SCI_EVT	BURST	CMD	IGN	IBF	OBF

Where:

Table 12-267 Register details

IGN:	Ignored			
SMI_EVT:	1 – Indicates SMI event is pending (requesting SMI query).			
	0 – No SMI events are pending.			
SCI_EVT:	1 – Indicates SCI event is pending (requesting SCI query).			
	0 – No SCI events are pending.			
BURST:	1 – Controller is in burst mode for polled command processing.			
	0 – Controller is in normal mode for interrupt-driven command processing.			
CMD:	1 – Byte in data register is a command byte (only used by controller).			
	0 – Byte in data register is a data byte (only used by controller).			
IBF:	1 – Input buffer is full (data ready for embedded controller).			
	0 – Input buffer is empty.			
OBF:	1 – Output buffer is full (data ready for host).			
	0 – Output buffer is empty.			

The Output Buffer Full (OBF) flag is set when the embedded controller has written a byte of data into the command or data port but the host has not yet read it. After the host reads the status byte and sees the OBF flag set, the host reads the data port to get the byte of data that the embedded controller has written. After the host reads the data byte, the OBF flag is cleared automatically by hardware. This signals the embedded controller that the data has been read by the host and the embedded controller is free to write more data to the host.

The Input Buffer Full (IBF) flag is set when the host has written a byte of data to the command or data port, but the embedded controller has not yet read it. After the embedded controller reads the status byte and sees the IBF flag set, the embedded controller reads the data port to get the byte of data that the host has written. After the embedded controller reads the data byte, the IBF flag is

automatically cleared by hardware. This is the signal to the host that the data has been read by the embedded controller and that the host is free to write more data to the embedded controller.

The SCI event (SCI_EVT) flag is set when the embedded controller has detected an internal event that requires the operating system's attention. The embedded controller sets this bit in the status register, and generates an SCI to OSPM. OSPM needs this bit to differentiate command-complete SCIs from notification SCIs. OSPM uses the query command to request the cause of the SCI_EVT and take action. For more information, see Section 12.3, "Embedded Controller Command Set.")

The SMI event (SMI_EVT) flag is set when the embedded controller has detected an internal event that requires the system management interrupt handler's attention. The embedded controller sets this bit in the status register before generating an SMI.

The Burst (BURST) flag indicates that the embedded controller has received the burst enable command from the host, has halted normal processing, and is waiting for a series of commands to be sent from the host. This allows OSPM or system management handler to quickly read and write several bytes of data at a time without the overhead of SCIs between the commands.

12.2.2 Embedded Controller Command, EC_SC (W)

This is a write-only register that allows commands to be issued to the embedded controller. Writes to this port are latched in the input data register and the input buffer full flag is set in the status register. Writes to this location also cause the command bit to be set in the status register. This allows the embedded controller to differentiate the start of a command sequence from a data byte write operation.

12.2.3 Embedded Controller Data, EC_DATA (R/W)

This is a read/write register that allows additional command bytes to be issued to the embedded controller, and allows OSPM to read data returned by the embedded controller. Writes to this port by the host are latched in the input data register, and the input buffer full flag is set in the status register. Reads from this register return data from the output data register and clear the output buffer full flag in the status register.

12.3 Embedded Controller Command Set

The embedded controller command set allows OSPM to communicate with the embedded controllers. ACPI defines the commands and their byte encodings for use with the embedded controller that are shown in the following table.

Table 12-268	B Embedded	Controller	Commands
--------------	------------	------------	----------

Embedded Controller Command	Command Byte Encoding
Read Embedded Controller (RD_EC)	0x80
Write Embedded Controller (WR_EC)	0x81
Burst Enable Embedded Controller (BE_EC)	0x82
Burst Disable Embedded Controller (BD_EC)	0x83
Query Embedded Controller (QR_EC)	0x84

12.3.1 Read Embedded Controller, RD_EC (0x80)

This command byte allows OSPM to read a byte in the address space of the embedded controller. This command byte is reserved for exclusive use by OSPM, and it indicates to the embedded controller to generate SCIs in response to related transactions (that is, IBF=0 or OBF=1 in the EC Status Register), rather than SMIs. This command consists of a command byte written to the Embedded Controller Command register (EC_SC), followed by an address byte written to the Embedded Controller Data register (EC_DATA). The embedded controller then returns the byte at the addressed location. The data is read at the data port after the OBF flag is set.

12.3.2 Write Embedded Controller, WR_EC (0x81)

This command byte allows OSPM to write a byte in the address space of the embedded controller. This command byte is reserved for exclusive use by OSPM, and it indicates to the embedded controller to generate SCIs in response to related transactions (that is, IBF=0 or OBF=1 in the EC Status Register), rather than SMIs. This command allows OSPM to write a byte in the address space of the embedded controller. It consists of a command byte written to the Embedded Controller Command register (EC_SC), followed by an address byte written to the Embedded Controller Data register (EC_DATA), followed by a data byte written to the Embedded Controller Data Register (EC_DATA); this is the data byte written at the addressed location.

12.3.3 Burst Enable Embedded Controller, BE_EC (0x82)

This command byte allows OSPM to request dedicated attention from the embedded controller and (except for critical events) prevents the embedded controller from doing tasks other than receiving command and data from the host processor (either the system management interrupt handler or OSPM). This command is an optimization that allows the host processor to issue several commands back to back, in order to reduce latency at the embedded controller interface. When the controller is in the burst mode, it should transition to the burst disable state if the host does not issue a command within the following guidelines:

- First Access 400 microseconds
- Subsequent Accesses 50 microseconds each
- Total Burst Time 1 millisecond

In addition, the embedded controller can disengage the burst mode at any time to process a critical event. If the embedded controller disables burst mode for any reason other than the burst disable command, it should generate an SCI to OSPM to indicate the change.

While in burst mode, the embedded controller follows these guidelines for OSPM driver:

SCIs are generated as normal, including IBF=0 and OBF=1.

Accesses should be responded to within 50 microseconds.

Burst mode is entered in the following manner:

OSPM driver writes the Burst Enable Embedded Controller, BE_EC (0x82) command byte and then the Embedded Controller will prepare to enter the Burst mode. This includes processing any routine activities such that it should be able to remain dedicated to OSPM interface for ~ 1 microsecond.

The Embedded Controller sets the Burst bit of the Embedded Controller Status Register, puts the Burst Acknowledge byte (0x90) into the SCI output buffer, sets the OBF bit, and generates an SCI to signal OSPM that it is in Burst mode.

Burst mode is exited the following manner:

OSPM driver writes the Burst Disable Embedded Controller, BD_EC (0x83) command byte and then the Embedded Controller will exit Burst mode by clearing the Burst bit in the Embedded Controller Status register and generating an SCI signal (due to IBF=0).

The Embedded Controller clears the Burst bit of the Embedded Controller Status Register.

12.3.4 Burst Disable Embedded Controller, BD_EC (0x83)

This command byte releases the embedded controller from a previous burst enable command and allows it to resume normal processing. This command is sent by OSPM or system management interrupt handler after it has completed its entire queued command sequence to the embedded controller.

12.3.5 Query Embedded Controller, QR_EC (0x84)

OSPM driver sends this command when the SCI_EVT flag in the EC_SC register is set. When the embedded controller has detected a system event that must be communicated to OSPM, it first sets the SCI_EVT flag in the EC_SC register, generates an SCI, and then waits for OSPM to send the query (QR_EC) command. OSPM detects the embedded controller SCI, sees the SCI_EVT flag set, and sends the query command to the embedded controller. Upon receipt of the QR_EC command byte, the embedded controller places a notification byte with a value between 0-255, indicating the cause of the notification. The notification byte indicates which interrupt handler operation should be executed by OSPM to process the embedded controller SCI. The query value of zero is reserved for a spurious query result and indicates "no outstanding event."

12.4 SMBus Host Controller Notification Header (Optional), OS SMB EVT

This query command notification header is the special return code that indicates events with an SMBus controller implemented within an embedded controller. These events include:

- Command completion
- Command error
- Alarm reception

The actual notification value is declared in the EC-SMB-HC device object in the ACPI Namespace.

12.5 Embedded Controller Firmware

The embedded controller firmware must obey the following rules in order to be ACPI-compatible:

• **SMI Processing**. Although it is not explicitly stated in the command specification section, a shared embedded controller interface has a separate command set for communicating with each environment it plans to support. In other words, the embedded controller knows which

environment is generating the command request, as well as which environment is to be notified upon event detection, and can then generate the correct interrupts and notification values. This implies that a system management handler uses commands that parallel the functionality of all the commands for ACPI including query, read, write, and any other implemented specific commands

- SCI/SMI Task Queuing. If the system design is sharing the interface between both a system management interrupt handler and OSPM, the embedded controller should always be prepared to queue a notification if it receives a command. The embedded controller only sets the appropriate event flag in the status (EC_SC) register if the controller has detected an event that should be communicated to the OS or system management handler. The embedded controller must be able to field commands from either environment without loss of the notification event. At some later time, the OS or system management handler issues a query command to the embedded controller to request the cause of the notification event.
- Notification Management. The use of the embedded controller means using the query (QR_EC) command to notify OSPM of system events requiring action. If the embedded controller is shared with the operating system, the SMI handler uses the SMI_EVT flag and an SMI query command (not defined in this document) to receive the event notifications. The embedded controller doesn't place event notifications into the output buffer of a shared interface unless it receives a query command from OSPM or the system management interrupt handler.

12.6 Interrupt Model

The EC Interrupt Model uses pulsed interrupts to speed the clearing process. The Interrupt is firmware generated using an EC general-purpose output and has the waveform shown in <u>Figure 12-66</u>. The embedded controller SCI is always wired directly to a GPE input or a GPIO pin, and OSPM driver treats this as an edge event (the EC SCI cannot be shared).




Figure 12-66 Interrupt Model

12.6.1 Event Interrupt Model

The embedded controller must generate SCIs for the events listed in the following table.

Table 12-269 Events for Which Embedded Controller Must Generate SCIs

Event	Description
IBF=0	Signals that the embedded controller has read the last command or data from the input buffer and the host is free to send more data.
OBF=1	Signals that the embedded controller has written a byte of data into the output buffer and the host is free to read the returned data.
SCI_EVT=1	Signals that the embedded controller has detected an event that requires OS attention. OSPM should issue a query (QR_EC) command to find the cause of the event.

12.6.2 Command Interrupt Model

The embedded controller must generate SCIs for commands as follows:

Table 12-270 Read Command (3 Bytes)

Byte #1	(Command byte Header)	Interrupt on IBF=0
Byte #2	(Address byte to read)	No Interrupt
Byte #3	(Data read to host)	Interrupt on OBF=1

Table 12-271 Write Command (3 Bytes)

Byte #1	(Command byte Header)	Interrupt on IBF=0
Byte #2	(Address byte to write)	Interrupt on IBF=0
Byte #3	(Data to read)	Interrupt on IBF=0

Table 12-272 Query Command (2 Bytes

Byte #1	(Command byte Header)	No Interrupt
Byte #2	(Query value to host)	Interrupt on OBF=1

Table 12-273 Burst Enable Command (2 Bytes)

Byte #1	(Command byte Header)	No Interrupt
Byte #2	(Burst acknowledge byte)	Interrupt on OBF=1

Table 12-274 Burst Disable Command (1 Byte)

Byte #1	(Command byte Header)	Interrupt on IBF=0

12.7 Embedded Controller Interfacing Algorithms

To initiate communications with the embedded controller, OSPM or system management handler acquires ownership of the interface. This ownership is acquired through the use of the Global Lock (described in <u>Section 5.2.10.1</u>, "Global Lock"), or is owned by default by OSPM as a non-shared resource (and the Global Lock is not required for accessibility).

Advanced Configuration and Power Interface Specification

After ownership is acquired, the protocol always consists of the passing of a command byte. The command byte will indicate the type of action to be taken. Following the command byte, zero or more data bytes can be exchanged in either direction. The data bytes are defined according to the command byte that is transferred.

The embedded controller also has two status bits that indicate whether the registers have been read. This is used to ensure that the host or embedded controller has received data from the embedded controller or host. When the host writes data to the command or data register of the embedded controller, the input buffer flag (IBF) in the status register is set within 1 microsecond. When the embedded controller reads this data from the input buffer, the input buffer flag is reset. When the embedded controller writes data into the output buffer, the output buffer flag (OBF) in the status register is set. When the host processor reads this data from the output buffer, the output buffer flag is reset.

12.8 Embedded Controller Description Information

Certain aspects of the embedded controller's operation have OEM-definable values associated with them. The following is a list of values that are defined in the software layers of the ACPI specification:

- Status flag indicating whether the interface requires the use of the Global Lock.
- Bit position of embedded controller interrupt in general-purpose status register.
- Decode address for command/status register.
- Decode address for data register.
- Base address and guery value of any EC-SMBus controller.

For implementation details of the above listed information, see <u>Section 12.11</u>, "Defining an Embedded Controller Device in ACPI Namespace," and <u>Section 12.12</u>, "Defining an EC SMBus Host Controller in ACPI Namespace."

An embedded controller will require the inclusion of the GLK method in its ACPI namespace if potentially contentious accesses to device resources are performed by non-OS code. See Section 6.5.7, "_GLK (Global Lock)" for details about the _GLK method.

12.9 SMBus Host Controller Interface via Embedded Controller

This section specifies a standard interface that an ACPI-compatible OS can use to communicate with embedded controller-based SMBus host controllers (EC-SMB-HC). This interface allows the host processor (under control of OSPM) to manage devices on the SMBus. Typical devices residing on the SMBus include Smart Batteries, Smart Battery Chargers, contrast/backlight control, and temperature sensors.

The EC-SMB-HC interface consists of a block of registers that reside in embedded controller space. These registers are used by software to initiate SMBus transactions and receive SMBus notifications. By using a well-defined register set, OS software can be written to operate with any vendor's embedded controller hardware.

Certain SMBus segments have special requirements that the host controller filters certain SMBus commands (for example, to prevent an errant application or virus from potentially damaging the battery subsystem). This is most easily accomplished by implementing the host interface controller through an embedded controller—as embedded controller can easily filter out potentially problematic commands.

Notice that an EC-SMB-HC interface will require the inclusion of the GLK method in its ACPI namespace if potentially contentious accesses to device resources are performed by non-OS code. See Section 6.5.7, "GLK (Global Lock)" for details on using the GLK method.

12.9.1 Register Description

The EC-SMBus host interface is a flat array of registers that are arranged sequentially in the embedded controller address space.

12.9.1.1 Status Register, SMB_STS

This register indicates general status on the SMBus. This includes SMB-HC command completion status, alarm received status, and error detection status (the error codes are defined later in this section). This register is cleared to zeroes (except for the ALRM bit) whenever a new command is issued using a write to the protocol (SMB_PRTCL) register. This register is always written with the error code before clearing the protocol register. The SMB-HC query event (that is, an SMB-HC interrupt) is raised after the clearing of the protocol register.

Note: OSPM must ensure the ALRM bit is cleared after it has been serviced by writing '00' to the SMB_STS register.

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
DONE	ALRM	RES			STATUS		

Where:

DONE:	Indicates the last command has completed and no error.
ALRM:	Indicates an SMBus alarm message has been received.
RES:	Reserved
STATUS:	Indicates SMBus communication status for one of the reasons listed in the following table.

Table 12-275 SMBus Status Codes

Status Code	Name	Description
00h	SMBus OK	Indicates the transaction has been successfully completed.
07h	SMBus Unknown Failure	Indicates failure because of an unknown SMBus error.
10h	SMBus Device Address Not Acknowledged	Indicates the transaction failed because the slave device address was not acknowledged.
11h	SMBus Device Error Detected	Indicates the transaction failed because the slave device signaled an error condition.

Advanced Configuration and Power Interface Specification

Status Code	Name	Description
12h	SMBus Device Command Access Denied	Indicates the transaction failed because the SMBus host does not allow the specific command for the device being addressed. For example, the SMBus host might not allow a caller to adjust the Smart Battery Charger's output.
13h	SMBus Unknown Error	Indicates the transaction failed because the SMBus host encountered an unknown error.
17h	SMBus Device Access Denied	Indicates the transaction failed because the SMBus host does not allow access to the device addressed. For example, the SMBus host might not allow a caller to directly communicate with an SMBus device that controls the system's power planes.
18h	SMBus Timeout	Indicates the transaction failed because the SMBus host detected a timeout on the bus.
19h	SMBus Host Unsupported Protocol	Indicates the transaction failed because the SMBus host does not support the requested protocol.
1Ah	SMBus Busy	Indicates that the transaction failed because the SMBus host reports that the SMBus is presently busy with some other transaction. For example, the Smart Battery might be sending charging information to the Smart Battery Charger.
1Fh	SMBus PEC (CRC-8) Error	Indicates that a Packet Error Checking (PEC) error occurred during the last transaction.

All other error codes are reserved.

12.9.1.2 Protocol Register, SMB_PRTCL

This register determines the type of SMBus transaction generated on the SMBus. In addition to indicating the protocol type to the SMB-HC, a write to this register initiates the transaction on the SMBus. Notice that bit 7 of the protocol value is used to indicate whether packet error checking should be employed. A value of 1 (one) in this bit indicates that PEC format should be used for the specified protocol, and a value of 0 (zero) indicates the standard (non-PEC) format should be used.

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0	
PEC	PROTOCO	PROTOCOL						

Where:

PROTOCOL:	0x00 – Controller Not In Use
	0x01 – Reserved
	0x02 – Write Quick Command
	0x03 – Read Quick Command
	0x04 – Send Byte
	0x05 – Receive Byte
	0x06 – Write Byte

PROTOCOL:	0x00 – Controller Not In Use
	0x07 – Read Byte
	0x08 – Write Word
	0x09 – Read Word
	0x0A – Write Block
	0x0B – Read Block
	0x0C – Process Call
	0x0D -
	Block Write-Block Read Process Call

For example, the protocol value of 0x09 would be used to communicate to a device that supported the standard *read word* protocol. If this device also supported packet error checking for this protocol, a value of 0x89 (*read word with PEC*) could optionally be used. See the SMBus specification for more information on packet error checking.

When OSPM initiates a new command such as write to the SMB_PRTCL register, the SMBus controller first updates the SMB_STS register and then clears the SMB_PRTCL register. After the SMB_PRTCL register is cleared, the host controller query value is raised.

All other protocol values are reserved.

12.9.1.3 Address Register, SMB_ADDR

This register contains the 7-bit address to be generated on the SMBus. This is the first byte to be sent on the SMBus for all of the different protocols.

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
ADDRESS (A6:A0)							RES

Where:

RES:	Reserved
ADDRESS:	7-bit SMBus address. This address is not zero aligned (in other words, it is only a 7-bit address (A6:A0) that is aligned from bit 1-7).

12.9.1.4 Command Register, SMB_CMD

This register contains the command byte that will be sent to the target device on the SMBus and is used for the following protocols: send byte, write byte, write word, read byte, read word, process call, block read and block write. It is not used for the quick commands or the receive byte protocol, and as such, its value is a "don't care" for those commands.

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
COMMAND							

Where:

12.9.1.5 Data Register Array, SMB_DATA[i], i=0-31

COMMAND:	Command byte to be sent to SMBus device.	
----------	--	--

This bank of registers contains the remaining bytes to be sent or received in any of the different protocols that can be run on the SMBus. The SMB_DATA[i] registers are defined on a per-protocol basis and, as such, provide efficient use of register space.

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
DATA							

Where:

DATA:	One byte of data to be sent or received (depending upon protocol).
-------	--

12.9.1.6 Block Count Register, SMB_BCNT

This register contains the number of bytes of data present in the SMB_DATA[i] registers preceding any write block and following any read block transaction. The data size is defined on a per protocol basis.

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
RES	RES		BCNT				

12.9.1.7 Alarm Address Register, SMB_ALRM_ADDR

This register contains the address of an alarm message received by the host controller, at slave address 0x8, from the SMBus master that initiated the alarm. The address indicates the slave address of the device on the SMBus that initiated the alarm message. The status of the alarm message is contained in the SMB_ALRM_DATAx registers. Once an alarm message has been received, the SMB-HC will not receive additional alarm messages until the ALRM status bit is cleared.

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
ADDRESS ((A6:A0)						RES

Where:

RES:	Reserved	ĺ
ADDRESS:	Slave address (A6:A0) of the SMBus device that initiated the SMBus alarm message.	

12.9.1.8 Alarm Data Registers, SMB_ALRM_DATA[0], SMB_ALRM_DATA[1]

These registers contain the two data bytes of an alarm message received by the host controller, at slave address 0x8, from the SMBus master that initiated the alarm. These data bytes indicate the

specific reason for the alarm message, such that OSPM can take actions. Once an alarm message has been received, the SMB-HC will not receive additional alarm messages until the ALRM status bit is cleared.

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
DATA (D7:D0)							

Where:

DATA:	Data byte received in alarm message.
-------	--------------------------------------

The alarm address and alarm data registers are not read by OSPM until the alarm status bit is set. OSPM driver then reads the 3 bytes, and clears the alarm status bit to indicate that the alarm registers are now available for the next event.

12.9.2 Protocol Description

This section describes how to initiate the different protocols on the SMBus through the interface described in <u>Section 12.9.1</u>, "Register Descriptions." The registers should all be written with the appropriate values before writing the protocol value that starts the SMBus transaction. All transactions can be completed in one pass.

12.9.2.1 Write Quick

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_PRTCL:	Write 0x02 to initiate the write quick protocol.

Data Returned:

SMB_STS:	Status code for transaction.
SMB_PRTCL:	0x00 to indicate command completion.

12.9.2.2Read Quick

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_PRTCL:	Write 0x03 to initiate the read quick protocol.

Data Returned:

SMB_STS:	Status code for transaction.
SMB_PRTCL:	0x00 to indicate command completion.

12.9.2.3 Send Byte

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_CMD:	Command byte to be sent.
SMB_PRTCL:	Write 0x04 to initiate the send byte protocol, or 0x84 to initiate the send byte protocol with PEC.

Data Returned:

SMB_STS:	Status code for transaction.	
SMB_PRTCL:	0x00 to indicate command completion.	

12.9.2.4 Receive Byte

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_PRTCL:	Write 0x05 to initiate the receive byte protocol, or 0x85 to initiate the receive byte protocol with PEC.

Data Returned:

SMB_DATA[0]:	Data byte received.
SMB_STS:	Status code for transaction.
SMB_PRTCL:	0x00 to indicate command completion.

12.9.2.5 Write Byte

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_CMD:	Command byte to be sent.
SMB_DATA[0]:	Data byte to be sent.
SMB_PRTCL:	Write 0x06 to initiate the write byte protocol, or 0x86 to initiate the write byte protocol with PEC.

Data Returned:

SMB_STS:	Status code for transaction.

SMB_PRTCL:	0x00 to indicate command completion.
------------	--------------------------------------

12.9.2.6 Read Byte

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_CMD:	Command byte to be sent.
SMB_PRTCL:	Write 0x07 to initiate the read byte protocol, or 0x87 to initiate the read byte protocol with PEC.

Data Returned:

SMB_DATA[0]:	Data byte received.
SMB_STS:	Status code for transaction.
SMB_PRTCL:	0x00 to indicate command completion.

12.9.2.7 Write Word

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_CMD:	Command byte to be sent.
SMB_DATA[0]:	Low data byte to be sent.
SMB_DATA[1]:	High data byte to be sent.
SMB_PRTCL:	Write 0x08 to initiate the write word protocol, or 0x88 to initiate the write word protocol with PEC.

Data Returned:

SMB_STS:	Status code for transaction.
SMB_PRTCL:	0x00 to indicate command completion.

12.9.2.8 Read Word

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_CMD:	Command byte to be sent.
SMB_PRTCL:	Write 0x09 to initiate the read word protocol, or 0x89 to initiate the read word protocol with PEC.

Data Returned:

SMB_DATA[0]:	Low data byte received.
SMB_DATA[1]:	High data byte received.
SMB_STS:	Status code for transaction.
SMB_PRTCL:	0x00 to indicate command completion.

12.9.2.9 Write Block

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_CMD:	Command byte to be sent.
SMB_DATA[0-31]:	Data bytes to write (1-32).
SMB_BCNT:	Number of data bytes (1-32) to be sent.
SMB_PRTCL:	Write 0x0A to initiate the write block protocol, or 0x8A to initiate the write block protocol with PEC.

Data Returned:

SMB_PRTCL:	0x00 to indicate command completion.
SMB_STS:	Status code for transaction.

12.9.2.10 Read Block

Data Sent:

SMB_ADDR:	Address of SMBus device.
SMB_CMD:	Command byte to be sent.
SMB_PRTCL:	Write 0x0B to initiate the read block protocol, or 0x8B to initiate the read block protocol with PEC.

Data Returned:

SMB_BCNT:	Number of data bytes (1-32) received.	
SMB_DATA[0-31]:	Data bytes received (1-32).	
SMB_STS:	Status code for transaction.	
SMB_PRTCL:	0x00 to indicate command completion.	

12.9.2.11 Process Call

Data Sent:

SMB_ADDR:	Address of SMBus device.	
SMB_CMD:	Command byte to be sent.	

SMB_DATA[0]:	Low data byte to be sent.	
SMB_DATA[1]:	High data byte to be sent.	
SMB_PRTCL:	Write 0x0C to initiate the process call protocol, or 0x8C to initiate the process call protocol with PEC.	

Data Returned:

SMB_DATA[0]:	Low data byte received.	
SMB_DATA[1]:	High data byte received.	
SMB_STS:	Status code for transaction.	
SMB_PRTCL:	0x00 to indicate command completion.	

12.9.2.12 Block Write-Block Read Process Call

Data Sent:

SMB_ADDR:	Address of SMBus device.	
SMB_CMD:	Command byte to be sent.	
SMB_DATA[0-31]:	Data bytes to write (1-31).	
SMB_BCNT:	Number of data bytes (1-31) to be sent.	
SMB_PRTCL:	Write 0x0D to initiate the write block-read block process call protocol, or 0x8D to initiate the write block-read block process call protocol with PEC.	

Data Returned:

SMB_BCNT:	Number of data bytes (1-31) received.	
SMB_DATA[0-31]:	Oata bytes received (1-31).	
SMB_STS:	Status code for transaction.	
SMB_PRTCL:	0x00 to indicate command completion.	

Note: The following restrictions apply: The aggregate data length of the write and read blocks must not exceed 32 bytes and each block (write and read) must contain at least 1 byte of data.

12.9.2.13 SMBus Register Set

The register set for the SMB-HC has the following format. All registers are 8 bit.

Table 12-276 SMB EC Interface

Location	Register Name	Description
BASE+0	SMB_PRTCL	Protocol register
BASE+1	SMB_STS	Status register
BASE+2	SMB_ADDR	Address register
BASE+3	SMB_CMD	Command register
BASE+4	SMB_DATA[0]	Data register zero

Advanced Configuration and Power Interface Specification

Location	Register Name	Description
BASE+5	SMB_DATA[1]	Data register one
BASE+6	SMB_DATA[2]	Data register two
BASE+7	SMB_DATA[3]	Data register three
BASE+8	SMB_DATA[4]	Data register four
BASE+9	SMB_DATA[5]	Data register five
BASE+10	SMB_DATA[6]	Data register six
BASE+11	SMB_DATA[7]	Data register seven
BASE+12	SMB_DATA[8]	Data register eight
BASE+13	SMB_DATA[9]	Data register nine
BASE+14	SMB_DATA[10]	Data register ten
BASE+15	SMB_DATA[11]	Data register eleven
BASE+16	SMB_DATA[12]	Data register twelve
BASE+17	SMB_DATA[13]	Data register thirteen
BASE+18	SMB_DATA[14]	Data register fourteen
BASE+19	SMB_DATA[15]	Data register fifteen
BASE+20	SMB_DATA[16]	Data register sixteen
BASE+21	SMB_DATA[17]	Data register seventeen
BASE+22	SMB_DATA[18]	Data register eighteen
BASE+23	SMB_DATA[19]	Data register nineteen
BASE+24	SMB_DATA[20]	Data register twenty
BASE+25	SMB_DATA[21]	Data register twenty-one
BASE+26	SMB_DATA[22]	Data register twenty-two
BASE+27	SMB_DATA[23]	Data register twenty-three
BASE+28	SMB_DATA[24]	Data register twenty-four
BASE+29	SMB_DATA[25]	Data register twenty-five
BASE+30	SMB_DATA[26]	Data register twenty-six
BASE+31	SMB_DATA[27]	Data register twenty-seven
BASE+32	SMB_DATA[28]	Data register twenty-eight
BASE+33	SMB_DATA[29]	Data register twenty-nine
BASE+34	SMB_DATA[30]	Data register thirty
BASE+35	SMB_DATA[31]	Data register thirty-one
BASE+36	SMB_BCNT	Block Count Register
BASE+37	SMB_ALRM_ADDR	Alarm address
BASE+38	SMB_ALRM_DATA[0]	Alarm data register zero
BASE+39	SMB_ALRM_DATA[1]	Alarm data register one

12.10 SMBus Devices

The embedded controller interface provides the system with a standard method to access devices on the SMBus. It does not define the data and/or access protocol(s) used by any particular SMBus

device. Further, the embedded controller can (and probably will) serve as a gatekeeper to prevent accidental or malicious access to devices on the SMBus.

Some SMBus devices are defined by their address and a specification that describes the data and the protocol used to access that data. For example, the Smart Battery System devices are defined by a series of specifications including:

- Smart Battery Data specification
- Smart Battery Charger specification
- Smart Battery Selector specification
- Smart Battery System Manager specification

The embedded controller can also be used to emulate (in part or totally) any SMBus device.

12.10.1 SMBus Device Access Restrictions

In some cases, the embedded controller interface will not allow access to a particular SMBus device. Some SMBus devices can and do communicate directly between themselves. Unexpected accesses can interfere with their normal operation and cause unpredictable results.

12.10.2 SMBus Device Command Access Restriction

There are cases where part of an SMBus device's commands are public while others are private. Extraneous attempts to access these commands might cause interference with the SMBus device's normal operation.

The Smart Battery and the Smart Battery Charger are good examples of devices that should not have their entire command set exposed. The Smart Battery commands the Smart Battery Charger to supply a specific charging voltage and charging current. Attempts by anyone to alter these values can cause damage to the battery or the mobile system. To protect the system's integrity, the embedded controller interface can restrict access to these commands by returning one of the following error codes: Device Command Access Denied (0x12) or Device Access Denied (0x17).

12.11 Defining an Embedded Controller Device in ACPI Namespace

An embedded controller device is created using the named device object. The embedded controller's device object requires the following elements:

Table 12-277 Embedded Controller Device Object Control Methods

Object	Description		
_CRS	Named object that returns the Embedded Controller's current resource settings. Embedded Controllers are considered static resources; hence only return their defined resources. The embedded controller resides only in system I/O or memory space. The first address region returned is the data port, and the second address region returned is the status/command port for the embedded controller. If the EC is used on a HW-Reduced ACPI platform, a third resource is required, which is the GPIO Interrupt Connection resource for the EC's SCI Interrupt. CRS is a standard device configuration control method defined in Section 6.2.2, "_CRS (Current Resource Outlines)."		
_HID	Resource Settings)." Named object that provides the Embedded Controller's Plug and Play identifier. This value is set to PNP0C09HID is a standard device configuration control method defined in Section 6.1.5, "_HID (Hardware ID)."		
_GPE	Named Object that evaluates to either an integer or a package. If _GPE evaluates to an integer the value is the bit assignment of the SCI interrupt within the GPEx_STS register of a GPE block described in the FADT that the embedded controller will trigger. If _GPE evaluates to a package, then that package contains two elements. The first is an object reference to the GPE Block device that contains the GPE register that will be triggered by the embedded controller. The second element is numeric (integer) that specifies the bit assignment of the SCI interrupt within the GPEx_STS register of the GPE Block device referenced by the first element in the package. This control method is specific to the embedded controller.		
	This method is not required on Hardware-reduced ACPI platforms.		

12.11.1 Example: EC Definition ASL Code

Example ASL code that defines an embedded controller device is shown below:

12.12 Defining an EC SMBus Host Controller in ACPI Namespace

An EC-SMB-HC device is defined using the named device object. The EC-SMB- HC's device object requires the following elements:

Table 12-278 EC SMBus HC Device Objects

Object	Description
_HID	Named object that provides the EC-SMB- HC's Plug and Play identifier. This value is be set to ACPI0001HID is a standard device configuration control method defined in Section 6.1.5, "_HID (Hardware ID)."
_EC	Named object that evaluates to a WORD that defines the SMBus attributes needed by the SMBus driverEC is the Embedded Controller Offset Query Control Method. The most significant byte is the address offset in embedded controller space of the SMBus controller; the least significant byte is the query value for all SMBus events.

12.12.1 Example: EC SMBus Host Controller ASL-Code

Example ASL code that defines an SMB-HC from within an embedded controller device is shown below:

```
Device(EC0)
{
    Name(_HID, EISAID("PNPOC09"))
    Name(_CRS, ResourceTemplate())
    {
        IO(Decode16, 0x62, 0x62, 0, 1), // Status port
        IO(Decode16, 0x66, 0x66, 0, 1) // command port
    })
    Name(_GPE, 0)

Device (SMB0)
    {
        Name(_HID, "ACPI0001") // EC-SMB-HC
        Name(_UID, 0) // Unique device identifier
        Name(_EC, 0x2030) // EC offset 0x20, query bit 0x30
        :
}
```

Advanced Configuration and Power Interface Specification

ACPI System Management Bus Interface Specification

This section describes the System Management Bus (SMBus) generic address space and the use of this address space to access SMBus devices from AML.

Unlike other address spaces, SMBus operation regions are inherently *non-linear*, where each offset within an SMBus address space represents a variable-sized (from 0 to 32 bytes) field. Given this uniqueness, SMBus operation regions include restrictions on their field definitions and require the use of an SMBus-specific data buffer for all transactions.

The SMBus interface presented in this section is intended for use with any hardware implementation compatible with the SMBus specification. SMBus hardware is broadly classified as either non-EC-based or EC-based. EC-based SMBus implementations comply with the standard register set defined in Section 12, ACPI Embedded Controller Interface Specification."

Non-EC SMBus implementations can employ any hardware interface and are typically used for their cost savings when SMBus security is not required. Non–EC-based SMBus implementations require the development of hardware specific drivers for each OS implementation. See <u>Section 13.2.1</u>, "Declaring SMBus Host Controller Objects," for more information.

Support of the SMBus generic address space by ACPI-compatible operating systems is optional. As such, the Smart Battery System Implementer's Forum (SBS-IF) has defined an SMBus interface based on a standard set of control methods. This interface is documented in the *SMBus Control Method Interface Specification*, available at "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Smart Battery System Components and SMBus Specification"...

13.1 SMBus Overview

SMBus is a two-wire interface based upon the I²C protocol. The SMBus is a low-speed bus that provides positive addressing for devices, as well as bus arbitration. For more information, refer to the complete set of SMBus specifications published by the SBS-IF.

13.1.1 SMBus Slave Addresses

Slave addresses are specified using a 7-bit non-shifted notation. For example, the slave address of the Smart Battery Selector device would be specified as 0x0A (1010b), not 0x14 (10100b) as might be found in other documents. These two different forms of addresses result from the format in which addresses are transmitted on the SMBus.

During transmission over the physical SMBus, the slave address is formatted in an 8-bit block with bits 7-1 containing the address and bit 0 containing the read/write bit. ASL code, on the other hand, presents the slave address simply as a 7-bit value making it the responsibility of the OS (driver) to shift the value if needed. For example, the ASL value would have to be shifted left 1 bit before being

written to the SMB_ADDR register in the EC based SMBus as described in <u>Section 12.9.1.3</u>, "Address Register, SMB_ADDR."

13.1.2 SMBus Protocols

There are seven possible *command protocols* for any given SMBus slave device, and a device may use any or all of the protocols to communicate. The protocols and associated access type indicators are listed below. Notice that the protocols values are similar to those defined for the EC-based SMBus in <u>Section 12.9.1.2</u>, "Protocol Register, SMB_PRTCL," except that protocol pairs (for example, Read Byte, Write Byte) have been joined.

Table 13-279	SMBus	Protocol	Types
---------------------	-------	----------	-------

Value	Туре	Description
0x02	SMBQuick	SMBus Read/Write Quick Protocol
0x04	SMBSendReceive	SMBus Send/Receive Byte Protocol
0x06	SMBByte	SMBus Read/Write Byte Protocol
0x08	SMBWord	SMBus Read/Write Word Protocol
0x0A	SMBBlock	SMBus Read/Write Block Protocol
0x0C	SMBProcessCall	SMBus Process Call Protocol
0x0D	SMBBlockProcessCall	SMBus Write Block-Read Block Process Call Protocol

All other protocol values are reserved.

Notice that bit 7 of the protocol value is used by this interface to indicate to the SMB-HC whether or not packet error checking (PEC) should be employed for a transaction. Packet error checking is described in section 7.4 of the *System Management Bus Specification, Version 1.1*. This highly desirable capability improves the reliability and robustness of SMBus communications.

The bit encoding of the protocol value is shown below. For example, the value 0x86 would be used to specify the PEC version of the SMBus Read/Write Byte protocol.




Figure 13-67 Bit Encoding Example

Notice that bit 0 of the protocol value is always zero (even number hexadecimal values). In a manner similar to the slave address, software that implements the SMBus interface is responsible for setting this bit to indicate whether the transaction is a read (for example, Read Byte) or write (for example, Write Byte) operation.

For example, software implanting this interface for EC-SMBus segments would set bit 0 for read transactions. For the SMBByte protocol (0x06), this would result in the value 0x07 being placed into the SMB_PRTCL register (or 0x87 if PEC is requested) for write transactions.

13.1.3 SMBus Status Codes

The use of status codes helps AML determine whether an SMBus transaction was successful. In general, a status code of zero indicates success, while a non-zero value indicates failure. The SMBus interface uses the same status codes defined for the EC-SMBus (see <u>Section 12.9.1.1</u>, "Status Register, SMB_STS").

13.1.4 SMBus Command Values

SMBus devices may optionally support up to 256 device-specific commands. For these devices, each *command value* supported by the device is modeled by this interface as a separate *virtual register*. Protocols that do not transmit a command value (for example, Read/Write Quick and Send/Receive Byte) are modeled using a single virtual register (with a command value = 0x00).

13.2 Accessing the SMBus from ASL Code

The following sections demonstrate how to access and use the SMBus from ASL code.

13.2.1 Declaring SMBus Host Controller Objects

EC-based SMBus 1.0-compatible HCs should be modeled in the ACPI namespace as described in Section 12.11, "Defining an Embedded Controller SMBus Host Controller in ACPI Namespace." An example definition is given below. Using the HID value "ACPI0001" identifies that this SMB-HC is implemented on an embedded controller using the standard SMBus register set defined in Section 12.9, SMBus Host Controller Interface via Embedded Controller."

EC-based SMBus 2.0-compatible host controllers should be defined similarly in the namespace as follows:

Non–EC-based SMB-HCs should be modeled in a manner similar to the EC-based SMBus HC. An example definition is given below. These devices use a vendor-specific hardware identifier (HID) to specify the type of SMB-HC (do not use "ACPI0001" or "ACPI0005"). Using a vendor-specific HID allows the correct software to be loaded to service this segment's SMBus address space.

```
Device(SMB0)
{
    Name(_HID, "<Vendor-Specific HID>") // Vendor-Specific HID
    :
}
```

Regardless of the type of hardware, some OS software element (for example, the SMBus HC driver) must register with OSPM to support all SMBus operation regions defined for the segment. This software allows the generic SMBus interface defined in this section to be used on a specific hardware implementation by translating between the conceptual (for example, SMBus address space) and physical (for example, process of writing/reading registers) models. Because of this linkage, SMBus operation regions must be defined immediately within the scope of the corresponding SMBus device.

13.2.2 Declaring SMBus Devices

The SMBus, as defined by the SMBus 1.0 Specification, is not an enumerable bus. As a result, an SMBus 1.0-compatible SMB-HC driver cannot discover child devices on the SMBus and load the appropriate corresponding device drivers. As such, SMBus 1.0-compatible devices are declared in the ACPI namespace, in like manner to other motherboard devices, and enumerated by OSPM.

The SMBus 2.0 specification adds mechanisms enabling device enumeration on the bus while providing compatibility with existing devices. ACPI defines and associates the "ACPI0005" HID value with an EC-based SMBus 2.0-compatible host controller. OSPM will enumerate SMBus 1.0-compatible devices when declared in the namespace under an SMBus 2.0-compatible host controller.

The responsibility for the definition of ACPI namespace objects, required by an SMBus 2.0-compatible host controller driver to enumerate non–bus-enumerable devices, is relegated to the Smart Battery System Implementers Forum. See "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Smart Battery System Components and SMBus Specification"...

Starting in ACPI 2.0, _ADR is used to associate SMBus devices with their lowest SMBus slave address.

13.2.3 Declaring SMBus Operation Regions

Each SMBus operation region definition identifies a single SMBus slave address. Operation regions are defined only for those SMBus devices that need to be accessed from AML. As with other regions, SMBus operation regions are only accessible via the **Field** term (see Section 13.2.2, "Declaring SMBus Fields").

This interface models each SMBus device as having a 256-byte linear address range. Each byte offset within this range corresponds to a single command value (for example, byte offset 0x12 equates to command value 0x12), with a maximum of 256 command values. By doing this, SMBus address spaces appear linear and can be processed in a manner similar to the other address space types.

The syntax for the **OperationRegion** term (from <u>Section 19.5.96</u>, "OperationRegion (Declare Operation Region]") is described below.

Advanced Configuration and Power Interface Specification

Where:

- RegionName specifies a name for this slave device (for example, "SBD0").
- RegionSpace must be set to **SMBus** (operation region type value 0x04).
- Offset is a word-sized value specifying the slave address and initial command value offset for the target device. The slave address is stored in the high byte and the command value offset is stored in the low byte. For example, the value 0x4200 would be used for an SMBus device residing at slave address 0x42 with an initial command value offset of zero (0).
- Length is set to the 0x100 (256), representing the maximum number of possible command values, for regions with an initial command value offset of zero (0). The difference of these two values is used for regions with non-zero offsets. For example, a region with an Offset value of 0x4210 would have a corresponding Length of 0xF0 (0x100 minus 0x10).

For example, the Smart Battery Subsystem (illustrated below) consists of the Smart Battery Charger at slave address 0x09, the Smart Battery System Manager at slave address 0x0A, and one or more batteries (multiplexed) at slave address 0x0B. (Notice that Figure 13-2 represents the logical connection of a Smart Battery Subsystem. The actual physical connections of the Smart Battery(s) and the Smart Battery Charger are made through the Smart Battery System Manager.) All devices support the Read/Write Word protocol. Batteries also support the Read/Write Block protocol.




Figure 13-68 Smart Battery Subsystem Devices

The following ASL code shows the use of the OperationRegion term to describe these SMBus devices:

Notice that these operation regions in this example are defined within the immediate context of the 'owning' EC-SMBus device. Each definition corresponds to a separate slave address (device), and happens to use an initial command value offset of zero (0).

13.2.4 Declaring SMBus Fields

As with other regions, SMBus operation regions are only accessible via the Field term. Each field element is assigned a unique command value and represents a virtual register on the targeted SMBus device.

The syntax for the **Field** term (from <u>Section 19.5.40</u>, "Event (Declare Event Synchronization Object]") is described below.

Where:

- RegionName specifies the operation region name previously defined for the device.
- AccessType must be set to **BufferAcc**. This indicates that access to field elements will be done using a region-specific data buffer. For this access type, the field handler is not aware of the data buffer's contents which may be of any size. When a field of this type is used as the source argument in an operation it simply evaluates to a buffer. When used as the destination, however, the buffer is passed bi-directionally to allow data to be returned from write operations. The modified buffer then becomes the execution result of that operation. This is slightly different than the normal case in which the execution result is the same as the value written to the destination. Note that the source is never changed, since it could be a read only object (see Section 13.2.5, "Declaring an SMBus Data Buffer" and Section 19.1.5, "Opcode Terms").
- LockRule indicates if access to this operation region requires acquisition of the Global Lock for synchronization. This field should be set to Lock on system with firmware that may access the SMBus, and NoLock otherwise.
- *UpdateRule* is not applicable to SMBus operation regions since each virtual register is accessed in its entirety. This field is ignored for all SMBus field definitions.

Advanced Configuration and Power Interface Specification

SMBus operation regions require that all field elements be declared at command value granularity. This means that each virtual register cannot be broken down to its individual bits within the field definition.

Access to sub-portions of virtual registers can be done only outside of the field definition. This limitation is imposed both to simplify the SMBus interface and to maintain consistency with the physical model defined by the SMBus specification.

SMBus protocols are assigned to field elements using the AccessAs term within the field definition. The syntax for this term (from Section 19.1.3, "ASL Root and SecondaryTerms") is described below.

Where:

- *AccessType* must be set to **BufferAcc**.
- AccessAttribute indicates the SMBus protocol to assign to command values that follow this
 term. See <u>Section 13.1.2</u>, "SMBus Protocols," for a listing of the SMBus protocol types and
 values.

An AccessAs term must appear as the first entry in a field definition to set the initial SMBus protocol for the field elements that follow. A maximum of one SMBus protocol may be defined for each field element. Devices supporting multiple protocols for a single command value can be modeled by specifying multiple field elements with the same offset (command value), where each field element is preceded by an AccessAs term specifying an alternate protocol.

For example, the register at command value 0x08 for a Smart Battery device (illustrated below) represents a word value specifying the battery temperature (in degrees Kelvin), while the register at command value 0x20 represents a variable-length (0 to 32 bytes) character string specifying the name of the company that manufactured the battery.




Figure 13-69 Smart Battery Device Virtual Registers

The following ASL code shows the use of the OperationRegion, Field, AccessAs, and Offset terms to represent these Smart Battery device virtual registers:

```
OperationRegion(SBD0, SMBus, 0x0B00, 0x0100)
Field(SBD0, BufferAcc, NoLock, Preserve)
   AccessAs(BufferAcc, SMBWord) // Use the SMBWord protocol for the following...
   MFGA. 8.
                                   // ManufacturerAccess() [command value 0x00]
   RCAP, 8,
                                   // RemainingCapacityAlarm() [command value 0x01]
   Offset(0x08)
                                   // Skip to command value 0x08...
                                  // Temperature() [command value 0x08]
   BTMP. 8.
   Offset(0x20)
                                   // Skip to command value 0x20...
   AccessAs(BufferAcc, SMBBlock) // Use the SMBBlock protocol for the following...
   MFGN, 8,
                                 // ManufacturerName() [command value 0x20]
   DEVN, 8
                                  // DeviceName() [command value 0x21]
```

Notice that command values are equivalent to the field element's byte offset (for example, MFGA=0, RCAP=1, BTMP=8). The **AccessAs** term indicates which SMBus protocol to use for each command value.

13.2.5 Declaring and Using an SMBus Data Buffer

The use of a data buffer for SMBus transactions allows AML to receive status and data length values, as well as making it possible to implement the Process Call protocol. As previously mentioned, the **BufferAcc** access type is used to indicate to the field handler that a region-specific data buffer will be used.

For SMBus operation regions, this data buffer is defined as a fixed-length 34-byte buffer that, if represented using a 'C'-styled declaration, would be modeled as follows:

Where:

- *Status* (byte 0) indicates the status code of a given SMBus transaction. See <u>Section 13.1.3</u>, "SMBus Status Code," for more information.
- *Length* (byte 1) specifies the number of bytes of valid data that exists in the data buffer. Use of this field is only defined for the Read/Write Block protocol, where valid *Length* values are 0 through 32. For other protocols—where the data length is implied by the protocol—this field is reserved.
- Data (bytes 2-33) represents a 32-byte buffer, and is the location where actual data is stored.

For example, the following ASL shows the use of the SMBus data buffer for performing transactions to a Smart Battery device. This code is based on the example ASL presented in <u>Section 13.2.4</u>, "Declaring SMBus Fields," which lists the operation region and field definitions for the Smart Battery device.

```
/* Create the SMBus data buffer */
Name(BUFF, Buffer(34){})
                                              // Create SMBus data buffer as BUFF
                                           // OB1 = Status (Byte)
CreateByteField(BUFF, 0x00, OB1)
CreateByteField(BUFF, 0x01, OB2) // OB2 = Length (Byte)
CreateWordField(BUFF, 0x02, OB3) // OB3 = Data (Word - Bytes 2 & 3)
CreateField(BUFF, 0x10, 256, OB4) // OB4 = Data (Block - Bytes 2-33)
/* Read the battery temperature */
                                               // Invoke Read Word transaction
Store(BTMP, BUFF)
If(LEqual(OB1, 0x00))
                                               // Successful?
                                               // OB3 = Battery temperature in 1/10<sup>th</sup> degrees Kelvin
/* Read the battery manufacturer name */
Store(MFGN, BUFF)
                                               // Invoke Read Block transaction
If(LEqual(OB1, 0x00))
                                               // Successful?
                                               // OB2 = Length of the manufacturer name
                                               // OB4 = Manufacturer name (as a counted string)
```

Notice the use of the **CreateField** primitives to access the data buffer's sub-elements (*Status*, *Length*, and *Data*), where *Data* (bytes 2-33) is 'typecast' as both word (OB3) and block (OB4) data.

The example above demonstrates the use of the Store() operator to invoke a Read Block transaction to obtain the name of the battery manufacturer. Evaluation of the *source* operand (MFGN) results in a 34-byte buffer that gets copied by Store() to the *destination* buffer (BUFF).

Capturing the results of a write operation, for example to check the status code, requires an additional Store() operator, as shown below.

```
Store(Store(BUFF, MFGN), BUFF) // Invoke Write Block transaction If(LEqual(OB1, 0x00)) {...} // Transaction successful?
```

Note that the outer Store() copies the results of the Write Block transaction back into BUFF. This is the nature of BufferAcc's bi-directionality described in <u>Section 13.2.4</u>, "Declaring SMBus Fields" It should be noted that storing (or parsing) the result of an SMBus Write transaction is not required although useful for ascertaining the outcome of a transaction.

SMBus Process Call protocols require similar semantics due to the fact that only destination operands are passed bi-directionally. These transactions require the use of the double-Store() semantics to properly capture the return results.

13.3 Using the SMBus Protocols

This section provides information and examples on how each of the SMBus protocols can be used to access SMBus devices from AML.

13.3.1 Read/Write Quick (SMBQuick)

The SMBus Read/Write Quick protocol (SMBQuick) is typically used to control simple devices using a device-specific binary command (for example, ON and OFF). Command values are not used

ACPI System Management Bus Interface Specification

by this protocol and thus only a single element (at offset 0) can be specified in the field definition. This protocol transfers no data.

The following ASL code illustrates how a device supporting the Read/Write Quick protocol should be accessed:

```
OperationRegion(SMBD, SMBus, 0x4200, 0x100)
                                              // SMBus device at slave address 0x42
Field(SMBD, BufferAcc, NoLock, Preserve)
   AccessAs(BufferAcc, SMBOuick)
                                              // Use the SMBus Read/Write Ouick protocol
                                              // Virtual register at command value 0.
   FLD0, 8
/* Create the SMBus data buffer */
                                             // Create SMBus data buffer as BUFF
Name(BUFF, Buffer(34){})
CreateByteField(BUFF, 0x00, OB1)
                                             // OB1 = Status (Byte)
/* Signal device (e.g. OFF) */
Store(FLD0, BUFF)
                                             // Invoke Read Quick transaction
If(LEqual(OB1, 0x00)) {...}
                                              // Successful?
/* Signal device (e.g. ON) */
Store(BUFF, FLD0)
                                              // Invoke Write Quick transaction
```

In this example, a single field element (FLD0) at offset 0 is defined to represent the protocol's read/write bit. Access to FLD0 will cause an SMBus transaction to occur to the device. Reading the field results in a Read Quick, and writing to the field results in a Write Quick. In either case data is not transferred—access to the register is simply used as a mechanism to invoke the transaction.

13.3.2 Send/Receive Byte (SMBSendReceive)

The SMBus Send/Receive Byte protocol (SMBSendReceive) transfers a single byte of data. Like Read/Write Quick, command values are not used by this protocol and thus only a single element (at offset 0) can be specified in the field definition.

The following ASL code illustrates how a device supporting the Send/Receive Byte protocol should be accessed:

```
OperationRegion(SMBD, SMBus, 0x4200, 0x100) // SMBus device at slave address 0x42
Field(SMBD, BufferAcc, NoLock, Preserve)
{
    AccessAs(BufferAcc, SMBSendReceive) // Use the SMBus Send/Receive Byte protocol
    FLD0, 8 // Virtual register at command value 0.
}

// Create the SMBus data buffer

Name(BUFF, Buffer(34){}) // Create SMBus data buffer as BUFF
CreateByteField(BUFF, 0x00, STAT) // STAT = Status (Byte)
CreateByteField(BUFF, 0x02, DATA) // DATA = Data (Byte)
```

In this example, a single field element (FLD0) at offset 0 is defined to represent the protocol's data byte. Access to FLD0 will cause an SMBus transaction to occur to the device. Reading the field results in a Receive Byte, and writing to the field results in a Send Byte.

13.3.3 Read/Write Byte (SMBByte)

The SMBus Read/Write Byte protocol (SMBByte) also transfers a single byte of data. But unlike Send/Receive Byte, this protocol uses a command value to reference up to 256 byte-sized virtual registers.

The following ASL code illustrates how a device supporting the Read/Write Byte protocol should be accessed:

```
OperationRegion(SMBD, SMBus, 0x4200, 0x100) // SMBus device at slave address 0x42
Field(SMBD, BufferAcc, NoLock, Preserve)
                                       // Use the SMBus Read/Write Byte protocol
   AccessAs(BufferAcc, SMBByte)
   FLD0, 8,
                                       // Virtual register at command value 0.
   FLD1, 8,
                                       // Virtual register at command value 1.
   FLD2, 8
                                       // Virtual register at command value 2.
                                       // Create the SMBus data buffer
// Read a byte of data from the device using command value 1
Store(FLD1, BUFF)
                                       // Invoke a Read Byte transaction
If(LEqual(STAT, 0x00))
                                       // Successful?
                                       // DATA = Byte read from FLD1...
// Write the byte '0x16' to the device using command value 2
Store(0x16, DATA) // Save 0x16 into the data buffer
Store(BUFF, FLD2)
                                       // Invoke a Write Byte transaction
```

In this example, three field elements (FLD0, FLD1, and FLD2) are defined to represent the virtual registers for command values 0, 1, and 2. Access to any of the field elements will cause an SMBus transaction to occur to the device. Reading FLD1 results in a Read Byte with a command value of 1, and writing to FLD2 results in a Write Byte with command value 2.

13.3.4 Read/Write Word (SMBWord)

The SMBus Read/Write Word protocol (SMBWord) transfers 2 bytes of data. This protocol also uses a command value to reference up to 256 word-sized virtual device registers.

The following ASL code illustrates how a device supporting the Read/Write Word protocol should be accessed:

```
OperationRegion(SMBD, SMBus, 0x4200, 0x100) // SMBus device at slave address 0x42
Field(SMBD, BufferAcc, NoLock, Preserve)
                                              // Use the SMBus Read/Write Word protocol
    AccessAs(BufferAcc, SMBWord)
    FLD0, 8,
                                              // Virtual register at command value 0.
    FLD1, 8,
                                               // Virtual register at command value 1.
    FLD2, 8
                                               // Virtual register at command value 2.
// Create the SMBus data buffer
                                              // Create SMBus data buffer as BUFF
Name(BUFF, Buffer(34){})
CreateByteField(BUFF, 0x00, STAT)
CreateWordField(BUFF, 0x02, DATA)
                                              // STAT = Status (Byte)
                                               // DATA = Data (Word)
\ensuremath{//} Read two bytes of data from the device using command value 1
                                       // Invoke a Read Word transaction
Store(FLD1, BUFF)
If(LEqual(STAT, 0x00))
                                               // Successful?
    // DATA = Word read from FLD1...
// Write the word `0x5416' to the device using command value 2
Store(0x5416, DATA)
                                           // Save 0x5416 into the data buffer
Store(BUFF, FLD2)
                                               // Invoke a Write Word transaction
```

In this example, three field elements (FLD0, FLD1, and FLD2) are defined to represent the virtual registers for command values 0, 1, and 2. Access to any of the field elements will cause an SMBus transaction to occur to the device. Reading FLD1 results in a Read Word with a command value of 1, and writing to FLD2 results in a Write Word with command value 2.

Notice that although accessing each field element transmits a word (16 bits) of data, the fields are listed as 8 bits each. The actual data size is determined by the protocol. Every field element is declared with a length of 8 bits so that command values and byte offsets are equivalent.

13.3.5 Read/Write Block (SMBBlock)

The SMBus Read/Write Block protocol (SMBBlock) transfers variable-sized (0-32 bytes) data. This protocol uses a command value to reference up to 256 block-sized virtual registers.

The following ASL code illustrates how a device supporting the Read/Write Block protocol should be accessed:

```
// Create the SMBus data buffer
                                        // Create SMBus data buffer as BUFF
                                        // STAT = Status (Byte)
                                        // SIZE = Length (Byte)
CreateField(BUFF, 0x10, 256, DATA)
                                        // DATA = Data (Block)
// Read block data from the device using command value 1
Store(FLD1, BUFF)
                                         // Invoke a Read Block transaction
                                         // Successful?
If(LEqual(STAT, 0x00))
   // SIZE = Size (number of bytes) of the block data read from FLD1...
   // DATA = Block data read from FLD1...
// Write the block 'TEST' to the device using command value 2
Store("TEST", DATA)
                                         // Save "TEST" into the data buffer
Store(4, SIZE)
                                         // Length of valid data in the data buffer
Store(BUFF, FLD2)
                                         // Invoke a Write Word transaction
```

In this example, three field elements (FLD0, FLD1, and FLD2) are defined to represent the virtual registers for command values 0, 1, and 2. Access to any of the field elements will cause an SMBus transaction to occur to the device. Reading FLD1 results in a Read Block with a command value of 1, and writing to FLD2 results in a Write Block with command value 2.

13.3.6 Word Process Call (SMBProcessCall)

The SMBus Process Call protocol (SMBProcessCall) transfers 2 bytes of data bi-directionally (performs a Write Word followed by a Read Word as an atomic transaction). This protocol uses a command value to reference up to 256 word-sized virtual registers.

The following ASL code illustrates how a device supporting the Process Call protocol should be accessed:

```
OperationRegion(SMBD, SMBus, 0x4200, 0x100)
                                               // SMBus device at slave address 0x42
Field(SMBD, BufferAcc, NoLock, Preserve)
    AccessAs(BufferAcc, SMBProcessCall)
                                              // Use the SMBus Process Call protocol
                                               // Virtual register at command value 0.
    FLD0, 8,
    FLD1, 8,
                                               // Virtual register at command value 1.
    FLD2, 8
                                               // Virtual register at command value 2.
                                              // Create the SMBus data buffer
                                               // Create SMBus data buffer as BUFF
Name(BUFF, Buffer(34){})
CreateByteField(BUFF, 0x00, STAT)
CreateWordField(BUFF, 0x02, DATA)
                                               // STAT = Status (Byte)
                                               // DATA = Data (Word)
// Process Call with input value '0x5416' to the device using command value 1
Store(0x5416, DATA)
                                          // Save 0x5416 into the data buffer
Store(Store(BUFF, FLD1), BUFF)
                                              // Invoke a Process Call transaction
If(LEqual(STAT, 0x00))
                                              // Successful?
                                              // DATA = Word returned from FLD1...
```

In this example, three field elements (FLD0, FLD1, and FLD2) are defined to represent the virtual registers for command values 0, 1, and 2. Access to any of the field elements will cause an SMBus transaction to occur to the device. Reading *or* writing FLD1 results in a Process Call with a

command value of 1. Notice that unlike other protocols, Process Call involves both a write and read operation in a single atomic transaction. This means that the *Data* element of the SMBus data buffer is set with an input value before the transaction is invoked, and holds the output value following the successful completion of the transaction.

13.3.7 Block Process Call (SMBBlockProcessCall)

The SMBus Block Write-Read Block Process Call protocol (SMBBlockProcessCall) transfers a block of data bi-directionally (performs a Write Block followed by a Read Block as an atomic transaction). The maximum aggregate amount of data that may be transferred is limited to 32 bytes. This protocol uses a command value to reference up to 256 block-sized virtual registers.

The following ASL code illustrates how a device supporting the Process Call protocol should be accessed:

```
OperationRegion(SMBD, SMBus, 0x4200, 0x100)
                                                 // SMbus device at slave address 0x42
Field(SMBD, BufferAcc, NoLock, Preserve)
       AccessAs(BufferAcc, SMBBlockProcessCall) // Use the Block Process Call protocol
       FLDO, 8, // Virtual register representing a command value of 0
       FLD1, 8 // Virtual register representing a command value of 1
}
// Create the SMBus data buffer as BUFF
                                               // Create SMBus data buffer as BUFF
Name(BUFF, Buffer(34)())
                                               // STAT = Status (Byte)
CreateByteField(BUFF, 0x00, STAT)
CreateByteField(BUFF, 0x01, SIZE)
                                                // SIZE = Length (Byte)
CreateField(BUFF, 0x10, 256, DATA)
                                                // Data (Block)
// Process Call with input value "ACPI" to the device using command value 1
Store("ACPI", DATA)
                                                 // Fill in outgoing data
Store(8, SIZE)
                                                // Length of the valid data
Store(Store(BUFF, FLD1), BUFF)
                                                // Execute the PC
if (LEqual(STAT, 0x00))
                                                 // Test the status
    // BUFF now contains information returned from PC
    // SIZE now equals size of data returned
```

Platform Communications Channel (PCC)

The platform communication channel is a generic mechanism for OSPM to communicate with an entity in the platform (e.g., a Baseboard Management Controller (BMC)). Neither the entity that OSPM communicates with, nor any aspects of the information passed back and forth is defined in this section. That information is defined by the actual interface that that employs PCC register address space as the communication channel.

PCC defines a new address space type (PCC Space, 0xA), which is implemented as one or more independent communications channels, or subspaces. The interface is described in the following ACPI system description table.

14.1 Platform Communications Channel Table

Table 14-280 Platform Communications Channel Table (PCCT)

Field	Byte Length	Byte Offset	Description
Header			
Signature	4	0	'PCCT' Signature for the Platform Communications Channel Table.
Length	4	4	Length, in bytes, of the entire PCCT.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID
OEM Table ID	8	16	For the PCCT, the table ID is the manufacturer model ID.
OEM Revision	4	24	OEM revision of PCCT for supplied OEM Table ID.
Creator ID	4	28	Vendor ID of utility that created the table. For tables containing Definition Blocks, this is the ID for the ASL Compiler.
Creator Revision	4	32	Revision of utility that created the table. For tables containing Definition Blocks, this is the revision for the ASL Compiler.
Flags	4	36	Platform Communications Channel Global flags, described in Table 14-281.
Reserved	8	40	Reserved
PCC Subspace Structure[n] (n = subspace ID)	_	48	A list of Platform Communications Channel Subspace structures for this platform. This structure is described in the following section. At most 256 subspaces are supported.

14.1.1 Platform Communications Channel Global Flags

Table 14-281 Platform Communications Channel Global Flags

PCC Flags	Bit Length	Bit Offset	Description
Doorbell Interrupt	1	0	If set, the platform is capable of generating a n interrupt to indicate completion of a command.
Reserved	31	1	Must be zero.

14.1.2 Platform Communications Channel Subspace Structures

PCC Subspaces are described by the PCC Subspace structure in the PCCT table. The subspace ID of a PCC subspace is its index in the array of subspace structures, starting with subspace 0. All subspaces have a common header, followed by a set of type-specific fields:

Table 14-282 Generic PCC Subspace Structure

Field	Byte Length	Byte Offset	Description
Туре	1	0	The type of subspace.
Length	1	1	Length of the subspace structure, in bytes. The next subspace structure begins <i>length</i> bytes after the start of this one.
Type specific fields	variable	2	See specific subspace types for more details

This specification defines subspace type 0, the Generic Communications Subspace, and subspace type 1, the HW-Reduced Communications Subspace. All other subspace types are reserved.

14.1.3 Generic Communications Subspace Structure (type 0)

Table 14-283 PCC Subspace Structure type 0 (Generic Communications Subspace)

Field	Byte Length	Byte Offset	Description
Туре	1	0	0 (Generic Communications Subspace)
Length	1	1	62
Reserved	6	2	Reserved
Base Address	8	8	Base Address of the shared memory range, described in Table 14-285.
Length	8	16	Length of the memory range. Must be > 8.
Doorbell Register	12	24	Contains the processor relative address, represented in Generic Address Structure format, of the PCC doorbell. Note: Only System I/O space and System Memory space are valid for values for Address_Space_ID.
Doorbell Preserve	8	36	Contains a mask of bits to preserve when writing the doorbell register.

Field	Byte Length	Byte Offset	Description
Doorbell Write	8	44	Contains a mask of bits to set when writing the doorbell register.
Nominal Latency	4	52	Expected latency to process a command, in microseconds.
Maximum Periodic Access Rate	4	56	The maximum number of periodic requests that the subspace channel can support, reported in commands per minute. 0 indicates no limitation.
Minimum Request Turnaround Time	2	60	The minimum amount of time that OSPM must wait after the completion of a command before issuing the next command, in microseconds.

Note: Inaccurate values for the Maximum Periodic Access Rate and Minimum Request Turnaround Time fields can result in punitive side effects for features that rely on the PCC interface. The Platform should report accurate values that allow for maximum channel efficiency while maintaining maximum channel stability.

Note: The Maximum Periodic Access Rate is used by OSPM to determine the maximum rate for periodic evaluation of commands. Infrequent, event driven commands are not restricted by the maximum periodic access rate.

14.1.4 HW-Reduced Communications Subspace Structure (type 1)

The HW-Reduced Communications Subspace is defined in <u>Table 14-284</u>. It is intended for use on HW-Reduced ACPI Platforms, which do not support the SCI. Aside from the interrupt change, and the allowed use of the Functional Fixed HW address space for the Doorbell Register, this subspace is identical to the Generic Communications Subspace described in <u>Section 14.2</u> and <u>Section 14.3</u>.

Table 14-284 PCC Subspace Structure type 1 (HW-Reduced Communications Subspace)

Field	Byte Length	Byte Offset	Description
Туре	1	0	1 (HW-Reduced Communications Subspace)
Length	1	1	62
Doorbell Interrupt	4	2	GSIV of the interrupt used for the PCC doorbell for this Subspace.
Doorbell Interrupt Flags	1	6	Bit[2-7] Reserved
			Bit[1] Doorbell interrupt mode
			1: Interrupt is Edge triggered
			0: Interrupt is Level triggered
			Bit[0] Doorbell interrupt polarity
			1: Interrupt is Active low
			0: Interrupt is Active high
Reserved	1	7	Reserved

Platform Communications Channel (PCC)

Base Address	8	8	Base Address of the shared memory range, described in <u>Table 14-267</u> .
Length	8	16	Length of the memory range. Must be > 8.
Doorbell Register	12	24	Contains the processor relative address, represented in Generic Address Structure format, of the PCC doorbell. Note: Only the System I/O, System Memory, and Functional Fixed Hardware spaces are valid for values for Address_Space_ID.
Doorbell Preserve	8	36	Contains a mask of bits to preserve when writing the doorbell register.
Doorbell Write	8	44	Contains a mask of bits to set when writing the doorbell register.
Nominal Latency	4	52	Expected latency to process a command, in microseconds.
Maximum Periodic Access Rate	4	56	The maximum number of periodic requests that the subspace channel can support, reported in commands per minute. 0 indicates no limitation.
Minimum Request Turnaround Time	2	60	The minimum amount of time that OSPM must wait after the completion of a command before issuing the next command, in microseconds.

Note: Inaccurate values for the Maximum Periodic Access Rate and Minimum Request Turnaround Time fields can result in punitive side effects for features that rely on the PCC interface. The Platform should report accurate values that allow for maximum channel efficiency while maintaining maximum channel stability.

Note: The Maximum Periodic Access Rate is used by OSPM to determine the maximum rate for periodic evaluation of commands. Infrequent, event driven commands are not restricted by the maximum periodic access rate.

14.2 Generic Communications Channel Shared Memory Region

Table 14-285 Generic Communications Channel Shared Memory Region

Field	Byte Length	Byte Offset	Description
Signature	4	0	The PCC signature. The signature of a subspace is computed by a bitwise-or of the value 0x50434300 with the subspace ID. For example, subspace 3 has the signature 0x50434303.
Command	2	4	PCC command field, described in <u>Table 14-286</u> .
Status	2	4	PCC status field, described in <u>Table 14-287</u> .
Communication Space	_	8	Memory region for reading/writing PCC data. The size of this region is 8 bytes smaller than the size of the shared memory region (specified in the General Communications Subspace structure). The first byte of this field represents PCC address 0.

14.2.1 Generic Communications Channel Command Field

This 16-bit field is used to select one of the defined commands for the platform to perform. OSPM is responsible for populating this field before each command invocation.

Table 14-286 Generic Communications Channel Command Field

Field	Bit Length	Bit Offset	Description
Command	8	0	Command code to execute. Command codes are application specific and defined by the consumer of this interface.
Reserved	7	8	Reserved.
Generate Doorbell Interrupt	1	15	If set, the platform should generate a Doorbell interrupt at the completion of this command.
			If the Doorbell bit is not set in the PCC global flags, this bit must be cleared.

14.2.2 Generic Communications Channel Status Field

Table 14-287 Generic Communications Channel Status Field

Field	Bit Length	Bit Offset	Description
Command Complete	1	0	If set, the platform has completed processing the last command.
SCI Doorbell	1	1	If set, the platform has issued a Doorbell Interrupt to this subspace. OSPM must check the Command Complete and Platform Notification fields to determine the cause of the Interrupt.
Error	1	2	If set, an error occurred executing the last command.
Platform Notification	1	3	If set, indicates the platform is issuing an asynchronous notification to OSPM.
Reserved	12	4	Reserved.

Note: OSPM (either in an Interrupt handler or via polling) is required to detect that the Command Complete bit has been set and to clear it before issuing another command. While waiting for this bit to be set, OSPM must not modify any portion of the shared memory region.

Note: The Doorbell Interrupt bit is required to be cleared in OSPM's Interrupt handler so that a new event can be detected.

14.3 Doorbell Protocol

The doorbell is used by OSPM to notify the platform that the shared memory region contains a valid command that is ready to be processed. A doorbell consists of a hardware register that is accessed via I/O or memory mapped I/O, abstracted in the doorbell field of the PCC subspace structure. OSPM rings the doorbell by performing a read/modify/write cycle on the specified register,

preserving and setting the bits specified in the preserve and write mask of the PCC subspace structure.

To ensure consistency of the shared memory region, the shared memory region is exclusively owned by OSPM or the platform at any point in time. After being initialized by the platform, the region is owned by OSPM. Writing the doorbell register transfers ownership of the memory region to the platform. The platform transfers ownership back by setting the Command Complete bit in the Status field.

Note: All accesses to the Status Field must be made using interlocked operations, by both entities sharing the channel.

14.4 Platform Notification

The doorbell protocol is a synchronous notification from OSPM to the platform to process a command. If the platform wants to notify OSPM of an event asynchronously, it may set the SCI Doorbell Interrupt and Platform Notification status bits and issue a Doorbell Interrupt. OSPM will service the Interrupt, clear the Doorbell Interrupt and Platform Notification bits, and service the platform notification. The meaning of the platform notification and the steps required to service it are defined by the individual components utilizing the PCC interface.

The platform must wait until OSPM has issued a consumer defined command that serves to notify the platform that OSPM is ready to service Platform Notifications. The command is subspace specific and may not be supported by all subspaces. Platform Notifications must be used in conjunction with an interrupt. Polling for Platform Notifications is not supported.

The platform may not modify any portion of the shared memory region other than the status field when issuing a platform notification.

Note: All accesses to the Status Field must be made using interlocked operations, by both entities sharing the channel.

14.5 Referencing the PCC address space

An individual PCC register may be referenced by the Generic Address Structure or in a Generic Register Descriptor by using the address space id PCC (0xA). When using the PCC address space, the Access Size field is redefined to Subspace ID, and identifies which PCC subspace the descriptor refers to.

As an example, the following resource template refers to the field occupying bits 8 through 15 at address 0x30 in PCC subspace 9:

Note that the PCC address space may not be used in any resource template or register unless the register/resource field explicitly allows the use of the PCC address space.

Platform Communications Channel (PCC)

15

System Address Map Interfaces

This section explains how an ACPI-compatible system conveys its memory resources/type mappings to OSPM. There are three ways for the system to convey memory resources /mappings to OSPM. The first is an INT 15 BIOS interface that is used in IA-PC-based systems to convey the system's initial memory map. UEFI enabled systems use the UEFI **GetMemoryMap()** boot services function to convey memory resources to the OS loader. These resources must then be conveyed by the OS loader to OSPM. See the UEFI Specification for more information on UEFI services.

Lastly, if memory resources may be added or removed dynamically, memory devices are defined in the ACPI Namespace conveying the resource information described by the memory device (see Section 9.12, "Memory Devices").

ACPI defines five address range types; AddressRangeMemory, AddressRangeACPI, AddressRangeNVS, AddressRangeUnusable, and AddressRangeReserved as described in the table below:

Value	Mnemonic	Description
1	AddressRangeMemory	This range is available RAM usable by the operating system.
2	AddressRangeReserved	This range of addresses is in use or reserved by the system and is not to be included in the allocatable memory pool of the operating system's memory manager.
3	AddressRangeACPI	ACPI Reclaim Memory. This range is available RAM usable by the OS after it reads the ACPI tables.
4	AddressRangeNVS	ACPI NVS Memory. This range of addresses is in use or reserve by the system and must not be used by the operating system. This range is required to be saved and restored across an NVS sleep.
5	AddressRangeUnusuable	This range of addresses contains memory in which errors have been detected. This range must not be used by OSPM.
6	AddressRangeDisabled	This range of addresses contains memory that is not enabled. This range must not be used by OSPM.
Other	Undefined	Undefined. Reserved for future use. OSPM must treat any range of this type as if the type returned was AddressRangeReserved.

The BIOS can use the *AddressRangeReserved* address range type to block out various addresses as not suitable for use by a programmable device. Some of the reasons a BIOS would do this are:

- The address range contains system ROM.
- The address range contains RAM in use by the ROM.
- The address range is in use by a memory-mapped system device.
- The address range is, for whatever reason, unsuitable for a standard device to use as a device memory space.

• The address range is within an NVRAM device where reads and writes to memory locations are no longer successful, that is, the device was worn out.

Note: OSPM will not save or restore memory reported as AddressRangeReserved, AddressRangeUnusable, or AddressRangeDisabled when transitioning to or from the S4 sleeping state.

15.1 INT 15H, E820H - Query System Address Map

This interface is used in real mode only on IA-PC-based systems and provides a memory map for all of the installed RAM, and of physical memory ranges reserved by the BIOS. The address map is returned through successive invocations of this interface; each returning information on a single range of physical addresses. Each range includes a type that indicates how the range of physical addresses is to be treated by the OSPM.

If the information returned from E820 in some way differs from INT-15 88 or INT-15 E801, the information returned from E820 supersedes the information returned from INT-15 88 or INT-15 E801. This replacement allows the BIOS to return any information that it requires from INT-15 88 or INT-15 E801 for compatibility reasons. For compatibility reasons, if E820 returns any AddressRangeACPI or AddressRangeNVS memory ranges below 16 MB, the INT-15 88 and INT-15 E801 functions must return the top of memory below the AddressRangeACPI and AddressRangeNVS memory ranges.

The memory map conveyed by this interface is not required to reflect any changes in available physical memory that have occurred after the BIOS has initially passed control to the operating system. For example, if memory is added dynamically, this interface is not required to reflect the new system memory configuration.

Table 15-289 Input to the INT 15h E820h Call

Register	Contents	Description
EAX	Function Code	E820h
EBX	Continuation	Contains the continuation value to get the next range of physical memory. This is the value returned by a previous call to this routine. If this is the first call, EBX must contain zero.
ES:DI	Buffer Pointer	Pointer to an Address Range Descriptor structure that the BIOS fills in.
ECX	Buffer Size	The length in bytes of the structure passed to the BIOS. The BIOS fills in the number of bytes of the structure indicated in the ECX register, maximum, or whatever amount of the structure the BIOS implements. The minimum size that must be supported by both the BIOS and the caller is 20 bytes. Future implementations might extend this structure.
EDX	Signature	'SMAP' Used by the BIOS to verify the caller is requesting the system map information to be returned in ES:DI.

Table 15-290 Output from the INT 15h E820h Call

Register	Contents	Description	
CF	Carry Flag	Non-Carry – Indicates No Error	
EAX	Signature	'SMAP.' Signature to verify correct BIOS revision.	
ES:DI	Buffer Pointer	Returned Address Range Descriptor pointer. Same value as on input.	
ECX	Buffer Size	Number of bytes returned by the BIOS in the address range descriptor. The minimum size structure returned by the BIOS is 20 bytes.	
EBX	Continuation	Contains the continuation value to get the next address range descriptor. The actual significance of the continuation value is up to the discretion of the BIOS. The caller must pass the continuation value unchanged as input to the next iteration of the E820 call in order to get the next Address Range Descriptor. A return value of zero means that this is the last descriptor. Note: the BIOS can also indicate that the last descriptor has already been returned during previous iterations by returning the carry flag set. The caller will ignore any other information returned by the BIOS when the carry flag is set.	

Table 15-291 Address Range Descriptor Structure

Offset in Bytes	Name	Description
0	BaseAddrLow	Low 32 Bits of Base Address
4	BaseAddrHigh	High 32 Bits of Base Address
8	LengthLow	Low 32 Bits of Length in Bytes
12	LengthHigh	High 32 Bits of Length in Bytes
16	Туре	Address type of this range
20	Extended Attributes	See Table 14-5

The *BaseAddrLow* and *BaseAddrHigh* together are the 64-bit base address of this range. The base address is the physical address of the start of the range being specified.

The *LengthLow* and *LengthHigh* together are the 64-bit length of this range. The length is the physical contiguous length in bytes of a range being specified.

The *Type* field describes the usage of the described address range as defined in <u>Table 15-288</u>.

Table 15-292 Extended Attributes for Address Range Descriptor Structure

Bit	Mnemonic	Description	
0	Reserved	Reserved, must be set to 1.	
1	AddressRangeNonVolatile	If set, the Address Range Descriptor represents non-volatile memory. Memory reported as non-volatile may require characterization to determine its suitability for use as conventional RAM.	
2	AddressRangeSlowAccess	If set, accesses to the described range may incur considerable latencies	
3	AddressRangeErrorLog	If set, the address range descriptor represents memory used for logging hardware errors.	

Bit	Mnemonic	Description
4-31	Reserved	Reserved for future use.

Note: Bit 1 and 2 are currently not used in the implementations and will be deprecated in the next revision of the specification. Bit 3 is used only on PC-AT BIOS systems to pinpoint the error log in memory. On UEFI-based systems, either UEFI Hardware Error Record HwErrRec#### runtime UEFI variable interface or the Error Record Serialization Actions 0xD, 0xE and 0xF for the APEI ERST interface must be implemented for the error logs.

15.2 E820 Assumptions and Limitations

- The BIOS returns address ranges describing baseboard memory.
- The BIOS does not return a range description for the memory mapping of PCI devices, ISA
 Option ROMs, and ISA Plug and Play cards because the OS has mechanisms available to detect
 them.
- The BIOS returns chip set-defined address holes that are not being used by devices as reserved.
- Address ranges defined for baseboard memory-mapped I/O devices, such as APICs, are returned as reserved.
- All occurrences of the system BIOS are mapped as reserved, including the areas below 1 MB, at 16 MB (if present), and at end of the 4-GB address space.
- Standard PC address ranges are not reported. For example, video memory at A0000 to BFFFF physical addresses are not described by this function. The range from E0000 to EFFFF is specific to the baseboard and is reported as it applies to that baseboard.
- All of lower memory is reported as normal memory. The OS must handle standard RAM locations that are reserved for specific uses, such as the interrupt vector table (0:0) and the BIOS data area (40:0).

15.3 UEFI GetMemoryMap() Boot Services Function

EFI enabled systems use the UEFI GetMemoryMap() boot services function to convey memory resources to the OS loader. These resources must then be conveyed by the OS loader to OSPM.

The GetMemoryMap interface is only available at boot services time. It is not available as a run-time service after OSPM is loaded. The OS or its loader initiates the transition from boot services to run-time services by calling ExitBootServices(). After the call to ExitBootServices() all system memory map information must be derived from objects in the ACPI Namespace.

The GetMemoryMap() interface returns an array of UEFI memory descriptors. These memory descriptors define a system memory map of all the installed RAM, and of physical memory ranges reserved by the firmware. Each descriptor contains a type field that dictates how the physical address range is to be treated by the operating system. The table below describes the memory types returned by the UEFI GetMemoryMap() interface along with a mapping from UEFI memory type to ACPI address range types. See the UEFI Specification for more information on UEFI memory types.

Table 15-293 UEFI Memory Types and mapping to ACPI address range types

Туре	Mnemonic	Description	ACPI Address Range Type
0	EfiReservedMemoryType	Not used.	AddressRangeReserved
1	EfiLoaderCode	The Loader and/or OS may use this memory as they see fit. Note: the OS loader that called ExitBootServices() is executing out of one or more EfiLoaderCode sections.	AddressRangeMemory
2	EfiLoaderData	The Loader and/or OS may use this memory as they see fit. Note: the OS loader that called ExitBootServices() is utilizing out of one or more EfiLoaderData sections.	AddressRangeMemory
3	EfiBootServicesCode	Memory available for general use.	AddressRangeMemory
4	EfiBootServicesData	Memory available for general use.	AddressRangeMemory
5	EfiRuntimeServiceCode	The OS and loader must preserve this memory range in the working and ACPI S1–S3 states.	AddressRangeReserved
6	EfiRuntimeServicesData	The OS and loader must preserve this memory range in the working and ACPI S1–S3 states.	AddressRangeReserved
7	EfiConventionalMemory	Memory available for general use.	AddressRangeMemory
8	EfiUnusableMemory	Memory that should not be used by the OS. For example, memory that failed UEFI memory test.	AddressRangeReserved
9	EfiACPIReclainMemory	The memory is to be preserved by the loader and OS until ACPI in enabled. Once ACPI is enabled, the memory in this range is available for general use.	AddressRangeACPI
10	EfiACPIMemoryNVS	The OS and loader must preserve this memory range in the working and ACPI S1–S3 states.	AddressRangeNVS
11	EfiMemoryMappedIO	The OS does not use this memory. All system memory-mapped I/O port space information should come from ACPI tables.	AddressRangeReserved
12	EfiMemoryMappedIOPort Space	The OS does not use this memory. All system memory-mapped I/O port space information should come from ACPI tables.	AddressRangeReserved
13	EfiPalCode	The OS and loader must preserve this memory range in the working and ACPI S1–S3 states.	AddressRangeReserved

15.4 UEFI Assumptions and Limitations

- The firmware returns address ranges describing the current system memory configuration.
- The firmware does *not* return a range description for the memory mapping of PCI devices, ISA Option ROMs, and ISA Plug and Play cards because the OS has mechanisms available to detect them.
- The firmware returns chip set-defined address holes that are not being used by devices as reserved.
- Address ranges defined for baseboard memory-mapped I/O devices, such as APICs, are returned as reserved.
- All occurrences of the system firmware are mapped as reserved, including the areas below 1
 MB, at 16 MB (if present), and at end of the 4-GB address space. This can include PAL code on
 ItaniumTM Processor Family (IPF)- based platforms.
- Standard PC address ranges are not reported. For example, video memory at A0000 to BFFFF physical addresses are not described by this function. The range from E0000 to EFFFF is specific to the baseboard and is reported as it applies to that baseboard.
- All of lower memory is reported as normal memory. The OS must handle standard RAM locations that are reserved for specific uses, such as the interrupt vector table (0:0) and the BIOS data area (40:0).
- EFI contains descriptors for memory mapped I/O and memory mapped I/O port space to allow for virtual mode calls to UEFI run-time functions. The OS must never use these regions.

15.5 Example Address Map

This sample address map (for an Intel processor-based system) describes a machine that has 128 MB of RAM, 640 KB of base memory and 127 MB of extended memory. The base memory has 639 KB available for the user and 1 KB for an extended BIOS data area. A 4-MB Linear Frame Buffer (LFB) is based at 12 MB. The memory hole created by the chip set is from 8 MB to 16 MB.

Memory-mapped APIC devices are in the system. The I/O Unit is at FEC00000 and the Local Unit is at FEE00000. The system BIOS is remapped to 1 GB–64 KB.

The 639-KB endpoint of the first memory range is also the base memory size reported in the BIOS data segment at 40:13. The following table shows the memory map of a typical system.

Table 15-294	Sample	Memory	/ Map
--------------	--------	--------	-------

Base (Hex)	Length	Туре	Description
0000 0000	639 KB	AddressRangeMemory	Available Base memory. Typically the same value as is returned using the INT 12 function.
0009 FC00	1 KB	AddressRangeReserved	Memory reserved for use by the BIOS(s). This area typically includes the Extended BIOS data area.
000F 0000	64 KB	AddressRangeReserved	System BIOS
0010 0000	7 MB	AddressRangeMemory	Extended memory, which is not limited to the 64-MB address range.

Base (Hex)	Length	Туре	Description
0080 0000	4 MB	AddressRangeReserved	Chip set memory hole required to support the LFB mapping at 12 MB.
0100 0000	120 MB	AddressRangeMemory	Baseboard RAM relocated above a chip set memory hole.
FEC0 0000	4 KB	AddressRangeReserved	I/O APIC memory mapped I/O at FEC00000.
FEE0 0000	4 KB	AddressRangeReserved	Local APIC memory mapped I/O at FEE00000.
FFFF 0000	64 KB	AddressRangeReserved	Remapped System BIOS at end of address space.

15.6 Example: Operating System Usage

The following code segment illustrates the algorithm to be used when calling the Query System Address Map function. It is an implementation example and uses non-standard mechanisms.

```
E820Present = FALSE;
   Reg.ebx = 0;
   do {
       Reg.eax = 0xE820;
       Reg.es = SEGMENT (&Descriptor);
       Reg.di = OFFSET (&Descriptor);
       Reg.ecx = sizeof (Descriptor);
       Reg.edx = 'SMAP';
       _int( 15, regs );
       if ((Regs.eflags & EFLAG_CARRY) || Regs.eax != 'SMAP') {
       if (Regs.ecx < 20 || Reg.ecx > sizeof (Descriptor) ) {
           // bug in bios - all returned descriptors must be
           // at least 20 bytes long, and cannot be larger then
           // the input buffer.
           break;
       E820Present = TRUE;
       Add address range Descriptor.BaseAddress through
       Descriptor.BaseAddress + Descriptor.Length
       as type Descriptor. Type
   } while (Regs.ebx != 0);
   if (!E820Present) {
```

System Address Map Interfaces

```
call INT-15 88 and/or INT-15 E801 to obtain old style memory information
.
.
.
.
```

Waking and Sleeping

ACPI defines a mechanism to transition the system between the working state (G0) and a sleeping state (G1) or the soft-off (G2) state. During transitions between the working and sleeping states, the context of the user's operating environment is maintained. ACPI defines the quality of the G1 sleeping state by defining the system attributes of four types of ACPI sleeping states (S1, S2, S3, and S4). Each sleeping state is defined to allow implementations that can tradeoff cost, power, and wake latencies. Additionally, ACPI defines the sleeping states such that an ACPI platform can support multiple sleeping states, allowing the platform to transition into a particular sleeping state for a predefined period of time and then transition to a lower power/higher wake latency sleeping state (transitioning through the G0 state) ¹.

ACPI defines a programming model that provides a mechanism for OSPM to initiate the entry into a sleeping or soft-off state (S1-S5); this consists of a 3-bit field SLP_TYPx² that indicates the type of sleep state to enter, and a single control bit SLP_EN to start the sleeping process. On HW-reduced ACPI systems, the register described by the SLEEP_CONTROL_REG field in the FADT is used instead of the fixed SLP_TYPx and SLP_EN register bit fields.

Note: Systems containing processors without a hardware mechanism to place the processor in a low-power state may additionally require the execution of appropriate native instructions to place the processor in a low-power state after OSPM sets the SLP_EN bit. The hardware may implement a number of low-power sleeping states and then associate these states with the defined ACPI sleeping states (through the SLP_TYPx fields). The ACPI system firmware creates a sleeping object associated with each supported sleeping state (unsupported sleeping states are identified by the lack of the sleeping object). Each sleeping object contains two constant 3-bit values that OSPM will program into the SLP_TYPa and SLP_TYPb fields (in fixed register space), or, on HW-reduced ACPI platforms, a single 3-bit value that OSPM will write to the register specified by the FADT's SLEEP_CONTROL_REG field.

On systems that are not HW-reduced ACPI platforms, an alternate mechanism for entering and exiting the S4 state is defined. This mechanism passes control to the BIOS to save and restore platform context. Context ownership is similar in definition to the S3 state, but hardware saves and restores the context of memory to non-volatile storage (such as a disk drive), and OSPM treats this as an S4 state with implied latency and power constraints. This alternate mechanism of entering the S4 state is referred to as the S4BIOS transition.

^{1.} OSPM uses the RTC wakeup feature or the Time and Alarm Namespace device to program in the time transition delay. Prior to sleeping, OSPM will program the alarm to the closest (in time) wakeup event: either a transition to a lower power sleeping state, or a calendar event (to run some application).

^{2.} Notice that there can be two fixed PM1x_CNT registers, each pointing to a different system I/O space region. Normally a register grouping only allows a bit or bit field to reside in a single register group instance (a or b); however, each platform can have two instances of the SLP_TYP (one for each grouping register: a and b). The \Sx control method gives a package with two values: the first is the SLP_TYPa value and the second is the SLP_TYPb value.

Waking and Sleeping

Prior to entering a sleeping state (S1-S4), OSPM will execute OEM-specific AML/ASL code contained in the _PTS (Prepare To Sleep) control method. One use of the _PTS control method is that it can indicate to the embedded controller what sleeping state the system will enter. The embedded controller can then respond by executing the proper power-plane sequencing upon sleep state entry.

The _WAK (Wake) control method is then executed. This control method again contains OEM-specific AML/ASL code. One use of the _WAK control method requests OSPM to check the platform for any devices that might have been added or removed from the system while the system was asleep. For example, a PC Card controller might have had a PC Card added or removed, and because the power to this device was off in the sleeping state, the status change event was not generated.

This section discusses the system initialization sequence of an ACPI-enabled platform. This includes the boot sequence, different wake scenarios, and an example to illustrate how to use the system address map reporting interfaces. This sequence is part of the ACPI event programming model.

Note: HW-reduced ACPI platforms do not implement the Legacy Mode nor the S4BIOS state described below.

For detailed information on the power management control methods described above, see <u>Section 7</u>, "Power and Performance Management."

16.1 Sleeping States

The illustration below shows the transitions between the working state, the sleeping states, and the Soft Off state.




Figure 16-70 Example Sleeping States

ACPI defines distinct differences between the G0 and G1 system states.

- In the G0 state, work is being performed by the OS/application software and the hardware. The CPU or any particular hardware device could be in any one of the defined power states (C0-C3 or D0-D3); however, some work will be taking place in the system.
- In the G1 state, the system is assumed to be doing no work. Prior to entering the G1 state, OSPM will place devices in a device power state compatible with the system sleeping state to be entered; if a device is enabled to wake the system, then OSPM will place these devices into the lowest Dx state from which the device supports wake. This is defined in the power resource description of that device object. This definition of the G1 state implies:
- The CPUs execute no instructions in the G1 state.
- Hardware devices are not operating (except possibly to generate a wake event).
- If not HW-reduced, ACPI registers are affected as follows:
- Wake event bits are enabled in the corresponding fixed or general-purpose registers according to enabled wake options.
- PM1 control register is programmed for the desired sleeping state.
- WAK STS is set by hardware in the sleeping state.

Waking and Sleeping

All sleeping states have these specifications. ACPI defines additional attributes that allow an ACPI platform to have up to four different sleeping states, each of which has different attributes. The attributes were chosen to allow differentiation of sleeping states that vary in power, wake latency, and implementation cost tradeoffs.

Running processors at reduced levels of performance is not an ACPI sleeping state (G1); this is a working (G0) state—defined event.

The CPU cannot execute any instructions when in the sleeping state; OSPM relies on this fact. A platform designer might be tempted to support a sleeping system by reducing the clock frequency of the system, which allows the platform to maintain a low-power state while at the same time maintaining communication sessions that require constant interaction (as with some network environments). This is definitely a G0 activity where an OS policy decision has been made to turn off the user interface (screen) and run the processor in a reduced performance mode. This type of reduced performance state as a sleeping state is not defined by the ACPI specification; ACPI assumes no code execution during sleeping states.

ACPI defines attributes for four sleeping states: S1, S2, S3 and S4. (Notice that S4 and S5 are very similar from a hardware standpoint.) ACPI-compatible platforms can support multiple sleeping states. ACPI specifies that a 3-bit binary number be associated with each sleeping state (these numbers are given objects within ACPI's root namespace: $\S0, \S1, \S2, \S3, \S4$ and $\S5$). When entering a system sleeping state, OSPM will do the following:

- 1. Pick the deepest sleeping state supported by the platform and enabled waking devices.
- 2. Execute the _PTS control method (which passes the type of intended sleep state to OEM AML code).
- 3. If OS policy decides to enter the S4 state and chooses to use the S4BIOS mechanism and S4BIOS is supported by the platform, OSPM will pass control to the BIOS software by writing the S4BIOS REQ value to the SMI CMD port.
- 4. If not using the S4BIOS mechanism, OSPM gets the SLP_TYPx value from the associated sleeping object (\S1, \S2, \S3, \S4 or \S5).
- 5. Program the SLP TYPx fields with the values contained in the selected sleeping object.

Note: Compatibility Note: The _GTS method is deprecated in ACPI 5.0A. For earlier versions, execute the _GTS control method, passing an argument that indicates the sleeping state to be entered (1, 2, 3, or 4 representing S1, S2, S3, and S4).

- 6. If entering S1, S2, or S3, flush the processor caches.
- 7. If not entering S4BIOS, set the SLP_EN bit to start the sleeping sequence. (This actually occurs on the same write operation that programs the SLP_TYPx field in the PM1_CNT register.) If entering S4BIOS, write the S4BIOS REQ value into the SMI CMD port.
- 8. If HW-reduced, program the register indicated by the SLEEP_CONTROL_REG FADT field with the HW-reduced ACPI Sleep Type value (retrieved from the sleep state object in step 4 above) and with the SLP EN bit set to one.
- 9. On systems containing processors without a hardware mechanism to place the processor in a low-power state, execute appropriate native instructions to place the processor in a low-power state.

The _PTS control method provides the BIOS a mechanism for performing some housekeeping, such as writing the sleep type value to the embedded controller, before entering the system sleeping state. Control method execution occurs "just prior" to entering the sleeping state and is not an event

synchronized with the write to the PM1_CNT register. Execution can take place several seconds prior to the system actually entering the sleeping state. As such, no hardware power-plane sequencing takes place by execution of the PTS control method.

Note: Compatibility Note: The _BFS method is deprecated in ACPI 5.0A. In earlier versions, on waking, the _BFS control method is executed. OSPM then executes the _WAK control method. This control method executes OEM-specific ASL/AML code that can search for any devices that have been added or removed during the sleeping state.

The following sections describe the sleeping state attributes.

16.1.1 S1 Sleeping State

The S1 state is defined as a low wake-latency sleeping state. In this state, all system context is preserved with the exception of CPU caches. Before entering S1, OSPM will flush the system caches. If the platform supports the WBINVD instruction (as indicated by the WBINVD and WBINVD_FLUSH flags in the FADT), OSPM will execute the WBINVD instruction. The hardware is responsible for maintaining all other system context, which includes the context of the CPU, memory, and chipset.

Examples of S1 sleeping state implementation alternatives follow.

16.1.1.1 Example 1: S1 Sleeping State Implementation

This example references an IA processor that supports the stop grant state through the assertion of the STPCLK# signal. When SLP_TYPx is programmed to the S1 value (the OEM chooses a value, which is then placed in the _S1 object) and the SLP_ENx bit is subsequently set, or when the HW-reduced ACPI Sleep Type value for S1 and the SLP_EN bit are written to the Sleep Control Register, the hardware can implement an S1 state by asserting the STPCLK# signal to the processor, causing it to enter the stop grant state.

In this case, the system clocks (PCI and CPU) are still running. Any enabled wake event causes the hardware to de-assert the STPCLK# signal to the processor whereby OSPM must first invalidate the CPU caches and then transition back into the working state.

16.1.1.2 Example 2: S1 Sleeping State Implementation

When SLP_TYPx is programmed to the S1 value and the SLP_ENx bit is subsequently set, or the HW-reduced ACPI Sleep Type value for S1 and the SLP_EN bit are written to the Sleep Control Register, the hardware will implement an S1 sleeping state transition by doing the following:

- 1. Placing the processor into the stop grant state.
- 2. Stopping the processor's input clock, placing the processor into the stop clock state.
- 3. Placing system memory into a self-refresh or suspend-refresh state. Refresh is maintained by the memory itself or through some other reference clock that is not stopped during the sleeping state.
- 4. Stopping all system clocks (asserts the standby signal to the system PLL chip). Normally the RTC will continue running.

In this case, all clocks in the system have been stopped (except for the RTC). Hardware must reverse the process (restarting system clocks) upon any enabled wake event whereby OSPM must first invalidate the CPU caches and then transition back into the working state.

16.1.2 S2 Sleeping State

The S2 state is defined as a low wake latency sleep state. This state is similar to the S1 sleeping state where any context except for system memory may be lost. Additionally, control starts from the processor's reset vector after the wake event. Before entering S2 the SLP_EN bit, OSPM will flush the system caches. If the platform supports the WBINVD instruction (as indicated by the WBINVD and WBINVD_FLUSH flags in the FADT), OSPM will execute the WBINVD instruction. The hardware is responsible for maintaining chip set and memory context. An example of an S2 sleeping state implementation follows.

16.1.2.1 Example: S2 Sleeping State Implementation

When the SLP_TYPx register(s) are programmed to the S2 value (found in the _S2 object) and the SLP_EN bit is set, or the HW-reduced ACPI Sleep Type value for S2 and the SLP_EN bit are written to the Sleep Control Register, the hardware will implement an S2 sleeping state transition by doing the following:

- 1. Stopping system clocks (the only running clock is the RTC).
- 2. Placing system memory into a self-refresh or suspend-refresh state.
- 3. Powering off the CPU and cache subsystem.

In this case, the CPU is reset upon detection of the wake event; however, core logic and memory maintain their context. Execution control starts from the CPU's boot vector. The BIOS is required to:

- Program the initial boot configuration of the CPU (such as the CPU's MSR and MTRR registers).
- Initialize the cache controller to its initial boot size and configuration.
- Enable the memory controller to accept memory accesses.
- Jump to the waking vector.

16.1.3 S3 Sleeping State

The S3 state is defined as a low wake-latency sleep state. From the software viewpoint, this state is functionally the same as the S2 state. The operational difference is that some Power Resources that may have been left ON in the S2 state may not be available to the S3 state. As such, some devices may be in a lower power state when the system is in S3 state than when the system is in the S2 state. Similarly, some device wake events can function in S2 but not S3. An example of an S3 sleeping state implementation follows.

16.1.3.1 Example: S3 Sleeping State Implementation

When the SLP_TYPx register(s) are programmed to the S3 value (found in the _S3 object) and the SLP_EN bit is set, or the HW-reduced ACPI Sleep Type value for S3 and the SLP_EN bit are written to the Sleep Control Register, the hardware will implement an S3 sleeping state transition by doing the following:

- 1. Placing the memory into a low-power auto-refresh or self-refresh state.
- 2. Devices that are maintaining memory isolating themselves from other devices in the system.

3. Removing power from the system. At this point, only devices supporting memory are powered (possibly partially powered). The only clock running in the system is the RTC clock.

In this case, the wake event repowers the system and resets most devices (depending on the implementation).

Execution control starts from the CPU's boot vector. The BIOS is required to:

- 4. Program the initial boot configuration of the CPU (such as the MSR and MTRR registers).
- 5. Initialize the cache controller to its initial boot size and configuration.
- 6. Enable the memory controller to accept memory accesses.
- 7. Jump to the waking vector.

Notice that if the configuration of cache memory controller is lost while the system is sleeping, the BIOS is required to reconfigure it to either the pre-sleeping state or the initial boot state configuration. The BIOS can store the configuration of the cache memory controller into the reserved memory space, where it can then retrieve the values after waking. OSPM will call the _PTS method once per session (prior to sleeping).

The BIOS is also responsible for restoring the memory controller's configuration. If this configuration data is destroyed during the S3 sleeping state, then the BIOS needs to store the presleeping state or initial boot state configuration in a non-volatile memory area (as with RTC CMOS RAM) to enable it to restore the values during the waking process.

When OSPM re-enumerates buses coming out of the S3 sleeping state, it will discover any devices that have been inserted or removed, and configure devices as they are turned on.

16.1.4 S4 Sleeping State

The S4 sleeping state is the lowest-power, longest wake-latency sleeping state supported by ACPI. In order to reduce power to a minimum, it is assumed that the hardware platform has powered off all devices. Because this is a sleeping state, the platform context is maintained. Depending on how the transition into the S4 sleeping state occurs, the responsibility for maintaining system context changes. S4 supports two entry mechanisms: OS initiated and BIOS-initiated. The OSPM-initiated mechanism is similar to the entry into the S1-S3 sleeping states; OSPM driver writes the SLP_TYPx fields and sets the SLP_EN bit, or writes the HW-reduced ACPI Sleep Type value for S3 and the SLP_EN bit to the Sleep Control Register. The BIOS-initiated mechanism occurs by OSPM transferring control to the BIOS by writing the S4BIOS_REQ value to the SMI_CMD port, and is not supported on HW-reduced ACPI platforms.

In OSPM-initiated S4 sleeping state, OSPM is responsible for saving all system context. Before entering the S4 state, OSPM will save context of all memory with the exception of memory reported as type AddressRangeReserved (see Section 15, "System Address Map Interfaces," for more information). Upon waking, OSPM will then restore the system context. When OSPM reenumerates buses coming out of the S4 sleeping state, it will discover any devices that have come and gone, and configure devices as they are turned on.

In the BIOS-initiated S4 sleeping state, OSPM is responsible for the same system context as described in the S3 sleeping state (BIOS restores the memory and some chip set context). The S4BIOS transition transfers control to the BIOS, allowing it to save context to non-volatile memory (such as a disk partition).

16.1.4.1 Operating System-Initiated S4 Transition

If OSPM supports OSPM-initiated S4 transition, it will not generate a BIOS-initiated S4 transition. Platforms that support the BIOS-initiated S4 transition also support OSPM-initiated S4 transition.

OSPM-initiated S4 transition is initiated by OSPM by saving system context, writing the appropriate values to the SLP_TYPx register(s), and setting the SLP_EN bit, or writes the HW-reduced ACPI Sleep Type value for S4 and the SLP_EN bit to the Sleep Control Register. Upon exiting the S4 sleeping state, the BIOS restores the chipset to its POST condition, updates the hardware signature (described later in this section), and passes control to OSPM through a normal boot process.

When the BIOS builds the ACPI tables, it generates a hardware signature for the system. If the hardware configuration has changed during an OS-initiated S4 transition, the BIOS updates the hardware signature in the FACS table. A change in hardware configuration is defined to be any change in the platform hardware that would cause the platform to fail when trying to restore the S4 context; this hardware is normally limited to boot devices. For example, changing the graphics adapter or hard disk controller while in the S4 state should cause the hardware signature to change. On the other hand, removing or adding a PC Card device from a PC Card slot should not cause the hardware signature to change.

16.1.4.2 The S4BIOS Transition

This transition is not supported on HW-reduced ACPI platforms. On other systems, the BIOS-initiated S4 transition begins with OSPM writing the S4BIOS_REQ value into the SMI_CMD port (as specified in the FADT). Once gaining control, the BIOS then saves the appropriate memory and chip set context, and then places the platform into the S4 state (power off to all devices).

In the FACS memory table, there is the S4BIOS_F bit that indicates hardware support for the BIOS-initiated S4 transition. If the hardware platform supports the S4BIOS state, it sets the S4BIOS_F flag within the FACS memory structure prior to booting the OS. If the S4BIOS_F flag in the FACS table is set, this indicates that OSPM can request the BIOS to transition the platform into the S4BIOS sleeping state by writing the S4BIOS_REQ value (found in the FADT) to the SMI_CMD port (identified by the SMI_CMD value in the FADT).

Upon waking the BIOS, software restores memory context and jumps to the waking vector (similar to wake from an S3 state). Coming out of the S4BIOS state, the BIOS must only configure boot devices (so it can read the disk partition where it saved system context). When OSPM re-enumerates buses coming out of the S4BIOS state, it will discover any devices that have come and gone, and configure devices as they are turned on.

16.1.5 S5 Soft Off State

OSPM places the platform in the S5 soft off state to achieve a logical off. Notice that *the S5 state is not a sleeping state* (it is a G2 state) and no context is saved by OSPM or hardware but power may still be applied to parts of the platform in this state and as such, it is not safe to disassemble. Also notice that from a hardware perspective, the S4 and S5 states are nearly identical. When initiated, the hardware will sequence the system to a state similar to the off state. The hardware has no responsibility for maintaining any system context (memory or I/O); however, it does allow a transition to the S0 state due to a power button press or a Remote Start. Upon start-up, the BIOS performs a normal power-on reset, loads the boot sector, and executes (but not the waking vector, as all ACPI table context is lost when entering the S5 soft off state).

The _TTS control method allows the BIOS a mechanism for performing some housekeeping, such as storing the targeted sleep state in a "global" variable that is accessible by other control methods (such as PS3 and DSW).

16.1.6 Transitioning from the Working to the Sleeping State

On a transition of the system from the working to the sleeping state, the following occurs:

- 1. OSPM decides (through a policy scheme) to place the system into the sleeping state.
- 2. OSPM invokes the _TTS method to indicate the deepest possible system state the system will transition to (1, 2, 3, or 4 representing S1, S2, S3, and S4).
- 3. OSPM examines all devices enabled to wake the system and determines the deepest possible sleeping state the system can enter to support the enabled wake functions. The _PRW named object under each device is examined, as well as the power resource object it points to.
- 4. OSPM places all device drivers into their respective Dx state. If the device is enabled for wake, it enters the Dx state associated with the wake capability. If the device is not enabled to wake the system, it enters the D3 state.
- 5. OSPM executes the _PTS control method, passing an argument that indicates the desired sleeping state (1, 2, 3, or 4 representing S1, S2, S3, and S4).
- 6. OSPM saves any other processor's context (other than the local processor) to memory.
- 7. OSPM writes the waking vector into the FACS table in memory.

Note: Compatibility Note: The _GTS method is deprecated in ACPI 5.0A. For earlier versions, OSPM executes the _GTS control method, passing an argument that indicates the sleeping state to be entered (1, 2, 3, or 4 representing S1, S2, S3, and S4).

- 8. If not a HW-reduced ACPI platform, OSPM clears the WAK_STS in the PM1a_STS and PM1b_STS registers. On HW-reduced ACPI platforms, OSPM clears the WAK_STS bit in the Sleep Status Register.
- 9. OSPM saves the local processor's context to memory.
- 10. OSPM flushes caches (only if entering S1, S2 or S3).
- 11. OSPM sets GPE enable registers or enables wake-capable interrupts to ensure that all appropriate wake signals are armed
- 12. If entering an S4 state using the S4BIOS mechanism, OSPM writes the S4BIOS_REQ value (from the FADT) to the SMI_CMD port. This passes control to the BIOS, which then transitions the platform into the S4BIOS state.
- 13. If not entering an S4BIOS state, and not a HW-reduced ACPI platform, then OSPM writes SLP_TYPa (from the associated sleeping object) with the SLP_ENa bit set to the PM1a_CNT register.
- 14. OSPM writes SLP_TYPb with the SLP_EN bit set to the PM1b_CNT register, or writes the HW-reduced ACPI Sleep Type value and the SLP_EN bit to the Sleep Control Register.
- 15. On systems containing processors without a hardware mechanism to place the processor in a low-power state, OSPM executes appropriate native instructions to place the processor in a low-power state.
- 16. OSPM loops on the WAK_STS bit, either in both the PM1a_CNT and PM1b_CNT registers, or in the SLEEP STATUS REG, in the case of HW-reduced ACPI platforms
- 17. The system enters the specified sleeping state.

Note: This is accomplished after step 14 or 15 above.

16.1.7 Transitioning from the Working to the Soft Off State

On a transition of the system from the working to the soft off state, the following occurs:

- 1. OSPM executes the PTS control method, passing the argument 5.
- 2. OSPM prepares its components to shut down (flushing disk caches).

Note: Compatibility Note: The _GTS method is deprecated in ACPI 5.0A. For earlier versions, OSPM executes the _GTS control method, passing the argument 5.

- 3. If not a HW-reduced ACPI platform, OSPM writes SLP_TYPa (from the _S5 object) with the SLP_ENa bit set to the PM1a_CNT register.
- 4. OSPM writes SLP_TYPb (from the _S5 object) with the SLP_ENb bit set to the PM1b_CNT register, or writes the HW-reduced ACPI Sleep Type value for S5 and the SLP_EN bit to the Sleep Control Register.
- 5. The system enters the Soft Off state.

16.2 Flushing Caches

Before entering the S1, S2 or S3 sleeping states, OSPM is responsible for flushing the system caches. ACPI provides a number of mechanisms to flush system caches. These include:

- Using a native instruction (for example, the IA-32 architecture WBINVD instruction) to flush and invalidate platform caches.
 WBINVD FLUSH flag set (1) in the FADT indicates the system provides this support level.
- Using the IA-32 instruction WBINVD to flush but **not** invalidate the platform caches. WBINVD flag set (1) in the FADT indicates the system provides this support level.

The manual flush mechanism has two caveats:

- Largest cache is 1 MB in size (FLUSH SIZE is a maximum value of 2 MB).
- No victim caches (for which the manual flush algorithm is unreliable).

Processors with built-in victim caches will not support the manual flush mechanism and are therefore required to support the WBINVD mechanism to use the S2 or S3 state.

The manual cache-flushing mechanism relies on the two FADT fields:

- **FLUSH_SIZE.** Indicates twice the size of the largest cache in bytes.
- **FLUSH_STRIDE.** Indicates the smallest line size of the caches in bytes.

The cache flush size value is typically twice the size of the largest cache size, and the cache flush stride value is typically the size of the smallest cache line size in the platform. OSPM will flush the system caches by reading a contiguous block of memory indicated by the cache flush size.

16.3 Initialization

This section covers the initialization sequences for an ACPI platform. After a reset or wake from an S2, S3, or S4 sleeping state (as defined by the ACPI sleeping state definitions), the CPU will start execution from its boot vector. At this point, the initialization software has many options, depending

on what the hardware platform supports. This section describes at a high level what should be done for these different options. Figure 16-71 illustrates the flow of the boot-up software.




Figure 16-71 BIOS Initialization

The processor will start executing at its power-on reset vector when waking from an S2, S3, or S4 sleeping state, during a power-on sequence, or as a result of a hard or soft reset.

Waking and Sleeping

When executing from the power-on reset vector as a result of a power-on sequence, a hard or soft reset, **or waking from an S4 sleep state**, the platform firmware performs complete hardware initialization; placing the system in a boot configuration. The firmware then passes control to the operating system boot loader.

When executing from the power-on reset vector as a result of waking from an S2 or S3 sleep state, the platform firmware performs only the hardware initialization required to restore the system to either the state the platform was in prior to the initial operating system boot, or to the pre-sleep configuration state. In multiprocessor systems, non-boot processors should be placed in the same state as prior to the initial operating system boot. The platform firmware then passes control back to OSPM system by jumping to either the Firmware_Waking_Vector or the X_Firmware_Waking_Vector in the FACS (see <u>Table 5-38</u> for more information). The contents of operating system memory contents may not be changed during the S2 or S3 sleep state.

First, the BIOS determines whether this is a wake from S2 or S3 by examining the SLP_TYP register value, which is preserved between sleeping sessions. If this is an S2 or S3 wake, then the BIOS restores minimum context of the system before jumping to the waking vector. This includes:

- **CPU configuration.** BIOS restores the pre-sleep configuration or initial boot configuration of each CPU (MSR, MTRR, BIOS update, SMBase, and so on). Interrupts must be disabled (for IA-32 processors, disabled by CLI instruction).
- Memory controller configuration. If the configuration is lost during the sleeping state, the BIOS initializes the memory controller to its pre-sleep configuration or initial boot configuration.
- Cache memory configuration. If the configuration is lost during the sleeping state, the BIOS initializes the cache controller to its pre-sleep configuration or initial boot configuration.
- Functional device configuration. The BIOS doesn't need to configure/restore context of functional devices such as a network interface (even if it is physically included in chipset) or interrupt controller. OSPM is responsible for restoring all context of these devices. The only requirement for the hardware and BIOS is to ensure that interrupts are not asserted by devices when the control is passed to OS.
- **ACPI registers.** SCI_EN bit must be set on non-HW-reduced ACPI platforms, and all event status/enable bits (PM1x_STS, PM1x_EN, GPEx_STS and GPEx_EN) must not be changed by BIOS.

Note: The BIOS may reconfigure the CPU, memory controller and cache memory controller to either the pre-sleeping configuration or the initial boot configuration. OSPM must accommodate both configurations.

When waking from an S4BIOS sleeping state, the BIOS initializes a minimum number of devices such as CPU, memory, cache, chipset and boot devices. After initializing these devices, the BIOS restores memory context from non-volatile memory such as hard disk, and jumps to waking vector.

As mentioned previously, waking from an S4 state is treated the same as a cold boot: the BIOS runs POST and then initializes memory to contain the ACPI system description tables. After it has finished this, it can call OSPM loader, and control is passed to OSPM.

When waking from S4 (either S4OS or S4BIOS), the BIOS may optionally set SCI_EN bit before passing control to OSPM. In this case, interrupts must be disabled (for IA-32 processors, disabled

CLI instruction) until the control is passed to OSPM and the chipset must be configured in ACPI mode.

16.3.1 Placing the System in ACPI Mode

When a platform initializes from a cold boot (mechanical off or from an S4 or S5 state), the hardware platform may be configured in a legacy configuration, if not a HW-reduced ACPI platform. From these states, the BIOS software initializes the computer as it would for a legacy operating system. When control is passed to the operating system, OSPM will check the SCI_EN bit and if it is not set will then enable ACPI mode by first finding the ACPI tables, and then by generating a write of the ACPI_ENABLE value to the SMI_CMD port (as described in the FADT). The hardware platform will set the SCI_EN bit to indicate to OSPM that the hardware platform is now configured for ACPI.

Note: Before SCI is enabled, no SCI interrupt can occur. Nor can any SCI interrupt occur immediately after ACPI is on. The SCI interrupt can only be signaled after OSPM has enabled one of the GPE/PM1 enable bits.

When the platform is waking from an S1, S2 or S3 state, and from S4 and S5 on HW-reduced ACPI platforms, OSPM assumes the hardware is already in the ACPI mode and will not issue an ACPI ENABLE command to the SMI CMD port

16.3.2 BIOS Initialization of Memory

During a power-on reset, an exit from an S4 sleeping state, or an exit from an S5 soft-off state, the BIOS needs to initialize memory. This section explains how the BIOS should configure memory for use by a number of features including:

- ACPI tables.
- BIOS memory that wants to be saved across S4 sleeping sessions and should be cached.
- BIOS memory that does not require saving and should be cached.

For example, the configuration of the platform's cache controller requires an area of memory to store the configuration data. During the wake sequence, the BIOS will re-enable the memory controller and can then use its configuration data to reconfigure the cache controllers. To support these three items, IA-PC-based systems contain system address map reporting interfaces that return the following memory range types:

- **ACPI Reclaim Memory.** Memory identified by the BIOS that contains the ACPI tables. This memory can be any place above 8 MB and contains the ACPI tables. When OSPM is finished using the ACPI tables, it is free to reclaim this memory for system software use (application space).
- ACPI Non-Volatile-Sleeping Memory (NVS). Memory identified by the BIOS as being
 reserved by the BIOS for its use. OSPM is required to tag this memory as cacheable, and to save
 and restore its image before entering an S4 state. Except as directed by control methods, OSPM
 is not allowed to use this physical memory. OSPM will call the _PTS control method some time
 before entering a sleeping state, to allow the platform's AML code to update this memory image
 before entering the sleeping state. After the system awakes from an S4 state, OSPM will restore

Waking and Sleeping

this memory area and call the _WAK control method to enable the BIOS to reclaim its memory image.

Note: The memory information returned from the system address map reporting interfaces should be the same before and after an S4 sleep.

When the system is first booting, OSPM will invoke E820 interfaces on IA-PC-based legacy systems or the GetMemoryMap() interface on UEFI-enabled systems to obtain a system memory map (see Section 15, "System Address Map Interfaces," for more information). As an example, the following memory map represents a typical IA-PC-based legacy platform's physical memory map.




Figure 16-72 Example Physical Memory Map

The names and attributes of the different memory regions are listed below:

- **0–640 KB.** Compatibility Memory. Application executable memory for an 8086 system.
- **640 KB–1 MB.** Compatibility Holes. Holes within memory space that allow accesses to be directed to the PC-compatible frame buffer (A0000h-BFFFFh), to adapter ROM space (C0000h-DFFFFh), and to system BIOS space (E0000h-FFFFFh).
- **1 MB–8 MB.** Contiguous RAM. An area of contiguous physical memory addresses. Operating systems may require this memory to be contiguous in order for its loader to load the OS properly on boot up. (No memory-mapped I/O devices should be mapped into this area.)
- **8 MB–Top of Memory1.** This area contains memory to the "top of memory1" boundary. In this area, memory-mapped I/O blocks are possible.
- **Boot Base–4 GB.** This area contains the bootstrap ROM.

The BIOS should decide where the different memory structures belong, and then configure the E820 handler to return the appropriate values.

For this example, the BIOS will report the system memory map by E820 as shown in Figure 15-4. Notice that the memory range from 1 MB to top of memory is marked as system memory, and then a small range is additionally marked as ACPI reclaim memory. A legacy OS that does not support the E820 extensions will ignore the extended memory range calls and correctly mark that memory as system memory.




Figure 16-73 Memory as Configured after Boot

Also, from the Top of Memory1 to the Top of Memory2, the BIOS has set aside some memory for its own use and has marked as reserved both ACPI NVS Memory and Reserved Memory. A legacy OS will throw out the ACPI NVS Memory and correctly mark this as reserved memory (thus preventing this memory range from being allocated to any add-in device).

OSPM will call the _PTS control method prior to initiating a sleep (by programming the sleep type, followed by setting the SLP_EN bit). During a catastrophic failure (where the integrity of the AML code interpreter or driver structure is questionable), if OSPM decides to shut the system off, it will not issue a _PTS, but will immediately issue a SLP_TYP of "soft off" and then set the SLP_EN bit, or directly write the HW-reduced ACPI Sleep Type value and the SLP_EN bit to the Sleep Control Register. Hence, the hardware should not rely solely on the _PTS control method to sequence the system to the "soft off" state. After waking from an S4 state, OSPM will restore the ACPI NVS memory image and then issue the _WAK control method that informs BIOS that its memory image is back.

16.3.3 OS Loading

At this point, the BIOS has passed control to OSPM, either by using OSPM boot loader (a result of waking from an S4/S5 or boot condition) or OSPM waking vector (a result of waking from an S2 or S3 state). For the Boot OS Loader path, OSPM will get the system address map via one of the

Waking and Sleeping

mechanisms describe in <u>Section 15</u>, "System Address Map Interfaces." If OSPM is booting from an S4 state, it will then check the NVS image file's hardware signature with the hardware signature within the FACS table (built by BIOS) to determine whether it has changed since entering the sleeping state (indicating that the platforms fundamental hardware configuration has changed during the current sleeping state). If the signature has changed, OSPM will not restore the system context and can boot from scratch (from the S4 state). Next, for an S4 wake, OSPM will check the NVS file to see whether it is valid. If valid, then OSPM will load the NVS image into system memory. Next, if not a HW-reduced ACPI platform, OSPM will check the SCI_EN bit and if it is not set, will write the ACPI_ENABLE value to the SMI_CMD register to switch into the system into ACPI mode and will then reload the memory image from the NVS file.




Figure 16-74 OS Initialization

If an NVS image file did not exist, then OSPM loader will load OSPM from scratch. At this point, OSPM will generate a _WAK call that indicates to the BIOS that its ACPI NVS memory image has been successfully and completely updated.

16.3.4 Exiting ACPI Mode

For machines that do not boot in ACPI mode, ACPI provides a mechanism that enables the OS to disable ACPI. The following occurs:

- 1. OSPM unloads all ACPI drivers (including the ACPI driver).
- 2. OSPM disables all ACPI events.
- 3. OSPM finishes using all ACPI registers.
- 4. OSPM issues an I/O access to the port at the address contained in the SMI_CMD field (in the FADT) with the value contained in the ACPI_DISABLE field (in the FADT).
- 5. BIOS then remaps all SCI events to legacy events and resets the SCI EN bit.
- 6. Upon seeing the SCI EN bit cleared, the ACPI OS enters the legacy OS mode.

When and if the legacy OS returns control to the ACPI OS, if the legacy OS has not maintained the ACPI tables (in reserved memory and ACPI NVS memory), the ACPI OS will reboot the system to allow the BIOS to re-initialize the tables.

Waking and Sleeping

Non-Uniform Memory Access (NUMA) Architecture Platforms

Systems employing a Non Uniform Memory Access (NUMA) architecture contain collections of hardware resources including processors, memory, and I/O buses, that comprise what is commonly known as a "NUMA node". Two or more NUMA nodes are linked to each other via a high-speed interconnect. Processor accesses to memory or I/O resources within the local NUMA node are generally faster than processor accesses to memory or I/O resources outside of the local NUMA node, accessed via the node interconnect. ACPI defines interfaces that allow the platform to convey NUMA node topology information to OSPM both statically at boot time and dynamically at run time as resources are added or removed from the system.

17.1 NUMA Node

A conceptual model for a node in a NUMA configuration may contain one or more of the following components:

- Processor
- Memory
- I/O Resources
- Networking, Storage
- Chipset

The components defined as part of the model are intended to represent all possible components of a NUMA node. A specific node in an implementation of a NUMA platform may not provide all of these components. At a minimum, each node must have a chipset with an interface to the interconnect between nodes.

The defining characteristic of a NUMA system is a coherent global memory and / or I/O address space that can be accessed by all of the processors. Hence, at least one node must have memory, at least one node must have I/O resources and at least one node must have processors. Other than the chipset, which must have components present on every node, each is implementation dependent. In the ACPI namespace, NUMA nodes are described as module devices. See Section 9.11,"Module Device".

17.2 System Locality

A collection of components that are presented to OSPM as a Symmetrical Multi-Processing (SMP) unit belong to the same System Locality, also known as a Proximity Domain. The granularity of a System Locality is typically at the NUMA Node level although the granularity can also be at the sub-NUMA node level or the processor, memory and host bridge level. A System Locality is reported to

the OSPM using the _PXM method. If OSPM only needs to know a near/far distinction among the System Localities, the PXM method is sufficient.

OSPM makes no assumptions about the proximity or nearness of different proximity domains. The difference between two integers representing separate proximity domains does not imply distance between the proximity domains (in other words, proximity domain 1 is not assumed to be closer to proximity domain 0 than proximity domain 6).

17.2.1 System Resource Affinity Table Definition

This optional System Resource Affinity Table (SRAT) provides the boot time description of the processor and memory ranges belonging to a system locality. OSPM will consume the SRAT only at boot time. OSPM should use _PXM for any devices that are hot-added into the system after boot up.

The SRAT describes the system locality that all processors and memory present in a system belong to at system boot. This includes memory that can be hot-added (that is memory that can be added to the system while it is running, without requiring a reboot). OSPM can use this information to optimize the performance of NUMA architecture systems. For example, OSPM could utilize this information to optimize allocation of memory resources and the scheduling of software threads.

17.2.2 System Resource Affinity Update

Dynamic migration of the devices may cause the relative system resource affinity information (if the optional SRAT is present) to change. If this occurs, The System Resource Affinity Update notification (Notify event of type 0x0D) may be generated by the platform to a device at a point on the device tree that represents a System Resource Affinity. This indicates to OSPM to invoke the _PXM object of the notified device to update the resource affinity.

17.3 System Locality Distance Information

Optionally, OSPM may further optimize a NUMA architecture system using information about the relative memory latency distances among the System Localities. This may be useful if the distance between multiple system localities is significantly different. In this case, a simple near/far distinction may be insufficient. This information is contained in the optional System Locality Information Table (SLIT) and is returned from the evaluation of the _SLI object.

The SLIT is a matrix that describes the relative distances between all System Localities. Support for the _PXM object is required for SLIT. The System Locality as returned by the _PXM object is used as the row and column indices of the matrix.

Note: (Implementation Note) The size of the SLIT table is determined by the largest _PXM value used in the system. Hence, to minimize the size of the SLIT table, the _PXM values assigned by the system firmware should be in the range 0, ..., N-1, where N is the number of System Localities. If _PXM values are not packed into this range, the SLIT will still work, but more memory will have to be allocated to store the "Entries" portion of the SLIT for the matrix.

The static SLIT table provides the boot time description of the relative distances among all System Localities. For hot-added devices and dynamic reconfiguration of the system localities, the _SLI object must be used for runtime update.

The _SLI method is an optional object that provides the runtime update of the relative distances from the System Locality i to all other System Localities in the system. Since _SLI method is providing additional relative distance information among System Localities, if implemented, it is provided alongside with the _PXM method.

17.3.1 Online Hot Plug

In the case of online addition, the Bus Check notification (0x0) is performed on a device object to indicate to OSPM that it needs to perform the Plug and Play re-enumeration operation on the device tree starting from the point where it has been notified. OSPM needs to evaluate all _PXM objects associated with the added System Localities, or SLI objects if the SLIT is present.

In the case of online deletion, OSPM needs to perform the Plug and Play ejection operation when it receives the Eject Request notification (0x03). OSPM needs to remove the relative distance information from its internal data structure for the removed System Localities.

17.3.2 Impact to Existing Localities

Dynamic reconfiguration of the system may cause the relative distance information (if the optional SLIT is present) to become stale. If this occurs, the System Locality Information Update notification may be generated by the platform to a device at a point on the device tree that represents a System Locality. This indicates to OSPM that it needs to invoke the _SLI objects associated with the System Localities on the device tree starting from the point where it has been notified..

Non-Uniform Memory Access (NUMA) Architecture Platforms

This section describes the ACPI Platform Error Interfaces (APEI), which provide a means for the platform to convey error information to OSPM. APEI extends existing hardware error reporting mechanisms and brings them together as components of a coherent hardware error infrastructure. APEI takes advantage of the additional hardware error information available in today's hardware devices and integrates much more closely with the system firmware.

As a result, APEI provides the following benefits:

- Allows for more extensive error data to be made available in a standard error record format for determining the root cause of hardware errors.
- Is extensible, so that as hardware vendors add new and better hardware error reporting mechanisms to their devices, APEI allows the platform and the OSPM to gracefully accommodate the new mechanisms.

This provides information to help system designers understand basic issues about hardware errors, the relationship between the firmware and OSPM, and information about error handling and the APEI architecture components.

APEI consists of four separate tables:

- Error Record Serialization Table (ERST)
- BOOT Error Record Table (BERT)
- Hardware Error Source Table (HEST)
- Error Injection Table (EINJ)

18.1Hardware Errors and Error Sources

A hardware error is a recorded event related to a malfunction of a hardware component in a computer platform. The hardware components contain error detection mechanisms that detect when a hardware error condition exists. Hardware errors can be classified as either corrected errors or uncorrected errors as follows:

- A corrected error is a hardware error condition that has been corrected by the hardware or by the firmware by the time the OSPM is notified about the existence of the error condition.
- An uncorrected error is a hardware error condition that cannot be corrected by the hardware or by the firmware. Uncorrected errors are either fatal or non-fatal.
 - A fatal hardware error is an uncorrected or uncontained error condition that is determined to be unrecoverable by the hardware. When a fatal uncorrected error occurs, the system is restarted to prevent propagation of the error.
 - A non-fatal hardware error is an uncorrected error condition from which OSPM can attempt recovery by trying to correct the error. These are also referred to as correctable or recoverable errors.

Central to APEI is the concept of a hardware error source. A hardware error source is any hardware unit that alerts OSPM to the presence of an error condition. Examples of hardware error sources include the following:

- Processor machine check exception (for example, MC#)
- Chipset error message signals (for example, SCI, SMI, SERR#, MCERR#)
- I/O bus error reporting (for example, PCI Express root port error interrupt)
- I/O device errors

A single hardware error source might handle aggregate error reporting for more than one type of hardware error condition. For example, a processor's machine check exception typically reports processor errors, cache and memory errors, and system bus errors.

A hardware error source is typically represented by the following:

- One or more hardware error status registers.
- One or more hardware error configuration or control registers.
- A signaling mechanism to alert OSPM to the existence of an error condition.

In some situations, there is not an explicit signaling mechanism and OSPM must poll the error status registers to test for an error condition. However, polling can only be used for corrected error conditions since uncorrected errors require immediate attention by OSPM.

18.2 Relationship between OSPM and System Firmware

Both OSPM and system firmware play important roles in hardware error handling. APEI improves the methods by which both of these can contribute to the task of hardware error handling in a complementary fashion. APEI allows the hardware platform vendor to determine whether the firmware or OSPM will own key hardware error resources. APEI also allows the firmware to pass control of hardware error resources to OSPM when appropriate.

18.3 Error Source Discovery

Platforms enumerate error sources to OSPM via a set of tables that describe the error sources. OSPM may also support non-ACPI enumerated error sources such as: Machine Check Exception, Corrected Machine Check, NMI, PCI Express AER, and on ItaniumTM Processor Family (IPF) platforms the INIT error source. Non-ACPI error sources are not described by this specification.

During initialization, OSPM examines the tables and uses this information to establish the necessary error handlers that are responsible for processing error notifications from the platform.

18.3.1 Boot Error Source

Under normal circumstances, when a hardware error occurs, the error handler receives control and processes the error. This gives OSPM a chance to process the error condition, report it, and optionally attempt recovery. In some cases, the system is unable to process an error. For example, system firmware or a management controller may choose to reset the system or the system might experience an uncontrolled crash or reset.

The boot error source is used to report unhandled errors that occurred in a previous boot. This mechanism is described in the BERT table. The boot error source is reported as a 'one-time polled' type error source. OSPM queries the boot error source during boot for any existing boot error records. The platform will report the error condition to OSPM via a Common Platform Error Record (CPER) compliant error record. The CPER format is described in appendix N of the UEFI 2.1 specification.

The Boot Error Record Table (BERT) format is shown in <u>Table 18-295</u>.

Table 18-295 Boot Error Record Table (BERT) Table

Field	Byte length	Byte offset	Description
Header Signature	4	0	'BERT'. Signature for the Boot Error Record Table.
Length	4	4	Length, in bytes, of BERT.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID.
OEM Table ID	8	16	The manufacturer model ID.
OEM Revision	4	24	OEM revision of the BERT for the supplied OEM table ID.
Creator ID	4	28	Vendor ID of the utility that created the table.
Creator Revision	4	32	Revision of the utility that created the table.
Boot Error Region Length	4	36	The length in bytes of the boot error region.
Boot Error Region	8	40	64-bit physical address of the Boot Error Region.

The Boot Error Region is a range of addressable memory OSPM can access during initialization to determine if an unhandled error condition occurred. System firmware must report this memory range as firmware reserved. The format of the Boot Error Region is shown in following table.

Table 18-296 Boot Error Region

Field	Byte length	Byte offset	Description
Block Status	4	0	Indicates the type of error information reported in the error packet: Bit 0 – Uncorrectable Error Valid: If set to one, indicates that an uncorrectable error condition exists. Bit 1 – Correctable Error Valid: If set to one, indicates that a correctable error condition exists. Bit 2 – Multiple Uncorrectable Errors: If set to one, indicates that more than one uncorrectable errors have been detected. Bit 3 – Multiple Correctable Errors: If set to one, indicates that more than one correctable errors have been detected. Bit 4–13 – Error Data Entry Count: This value indicates the number of Error Data Entries found in the <i>Data</i> section. Bit 14–31 – Reserved.
Raw Data Offset	4	4	Offset in bytes from the beginning of the Error Status Block to raw error data. The raw data must follow any <i>Generic Error Data Entries</i> .

Raw Data Length	4	8	Length in bytes of the raw data.	
Data Length	4	12	Length in bytes of the generic error data.	
Error Severity	4	16	Identifies the error severity of the reported error: 0 - Correctable 1 - Fatal 2 - Corrected 3 - None Note: This is the error severity of the entire event. Each Generic Error Data Entry also includes its own Error Severity field.	
Generic Error Data	Data Length	20	The information contained in this field is a collection of zero or more Generic Error Data Entries.	

One or more *Generic Error Data Entry* structures may be recorded in the *Generic Error Data Entries* field of the *Generic Error Status Block* structure. This allows the platform to accumulate information for multiple hardware components related to a given error event. For example, if the generic error source represents an error that occurs on a device on the secondary side of a PCI Express / PCI-X Bridge, it is useful to record error information from the PCI Express Bridge and from the PCI Express device. Utilizing two *Generic Error Data Entry* structures enables this. Table 18-307 defines the layout of a Generic Error Data Entry.

For details of some of the fields defined in <u>Table 18-307</u>. See also Table 3 in section N2.2 of Appendix N of the UEFI 2.1 specification.

18.3.2 ACPI Error Source

The hardware error source describes a standardized mechanism platforms may use to describe their error sources. Use of this interface is the preferred way for platforms to describe their error sources as it is platform and processor-architecture independent and allows the platform to describe the operational parameters associated with error sources.

This mechanism allows for the platform to describe error sources in detail; communicating operational parameters (i.e. severity levels, masking bits, and threshold values) to OSPM as necessary. It also allows the platform to report error sources for which OSPM would typically not implement support (for example, chipset-specific error registers).

The Hardware Error Source Table provides the platform firmware a way to describe a system's hardware error sources to OSPM. The format of the Hardware Error Source Table is shown in Table 18-297.

Table 18-297 Hardware Error Source Table (HEST)

Field	Byte length	Byte offset	Description
Header Signature	4	0	"HEST". Signature for the Hardware Error Source Table.
Length	4	4	Length, in bytes, of entire HEST. Entire table must be contiguous.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID.

Field	Byte length	Byte offset	Description
OEM Table ID	8	16	The manufacturer model ID.
OEM Revision	4	24	OEM revision of the HEST for the supplied OEM table ID.
Creator ID	4	28	Vendor ID of the utility that created the table.
Creator Revision	4	32	Revision of the utility that created the table.
Error Source Count	4	36	The number of error source descriptors.
Error Source Structure[n]	-	40	A series of Error Source Descriptor Entries.

The following sections detail each of the specific error source descriptors.

Note: Error source types 3, 4, and 5 are reserved for legacy reasons and must not be used.

18.3.2.1 IA-32 Architecture Machine Check Exception

Processors implementing the IA-32 Instruction Set Architecture employ a machine check exception mechanism to alert OSPM to the presence of an uncorrected hardware error condition. The information in this table is used by OSPM to configure the machine check exception mechanism for each processor in the system.

Only one entry of this type is permitted in the HEST. OSPM applies the information specified in this entry to all processors.

Table 18-298 IA-32 Architecture Machine Check Exception Structure

Field	Byte Length	Byte Offset	Description
Туре	2	0	0 – IA-32 Architecture Machine Check Exception Structure.
Source Id	2	2	This value serves to uniquely identify this error source against other error sources reported by the platform.
Reserved	2	4	Reserved.
Flags	1	6	Bit 0 - FIRMWARE_FIRST: If set, this bit indicates to the OSPM that system firmware will handle errors from this source first. All other bits are reserved.
Enabled	1	7	Specifies whether MCE is to be enabled. If set to 1, this field indicates this error source is to be enabled. If set to 0, this field indicates that the error source is not to be enabled.
Number of Records To Pre-allocate	4	8	Indicates the number of error records to pre-allocate for this error source.
Max Sections Per Record	4	12	Indicates the maximum number of error sections included in an error record created as a result of an error reported by this error source.
Global Capability Init Data	8	16	Indicates the value of the machine check global capability register.
Global Control Init Data	8	24	Indicates the value to be written to the machine check global control register.

Field	Byte Length	Byte Offset	Description
Number Of Hardware Banks	1	32	Indicates the number of hardware error reporting banks.
Reserved	7	33	Reserved.
Machine Check Bank Structure[n]	-	40	A list of Machine Check Bank structures defined in section 17.3.2.1.1

18.3.2.1.1 IA-32 Architecture Machine Check Bank Structure

This table describes the attributes of a specific IA-32 architecture machine check hardware error bank.

Table 18-299 IA-32 Architecture Machine Check Error Bank Structure

Field	Byte Length	Byte Offset	Description
Bank Number	1	0	Zero-based index identifies the machine check error bank.
Clear Status On Initialization	1	1	If set, indicates the status information in this machine check bank is to be cleared during system initialization as follows: 0 – Clear 1 – Don't clear
Status Data Format	1	2	Identifies the format of the data in the status register: 0 – IA-32 MCA 1 – Intel® 64 MCA 2 – AMD64MCA All other values are reserved
Reserved	1	3	Reserved.
Control Register MSR Address	4	4	Address of the hardware bank's control MSR. Ignored if zero.
Control Init Data	8	8	This is the value the OSPM will program into the machine check bank's control register.
Status Register MSR Address	4	16	Address of the hardware bank's MCi_STAT MSR. Ignored if zero.
Address Register MSR Address	4	20	Address of the hardware bank's MCi_ADDR MSR. Ignored if zero.
Misc Register MSR Address	4	24	Address of the hardware bank's MCi_MISC MSR. Ignored if zero.

18.3.2.2 IA-32 Architecture Corrected Machine Check

Processors implementing the IA-32 Instruction Set Architecture may report corrected processor errors to OSPM. The information in this table allows platform firmware to communicate key parameters of the corrected processor error reporting mechanism to OSPM, including whether CMC processing should be enabled.

Only one entry of this type is permitted in the HEST. OSPM applies the information specified in this entry to all processors.

Table 18-300 IA-32 Architecture Corrected Machine Check Structure

Field	Byte Length	Byte Offset	Description
Туре	2	0	1 – IA-32 Architecture Corrected Machine Check Structure.
Source Id	2	2	Uniquely identifies the error source.
Reserved	2	4	Reserved
Flags	1	6	Bit 0 - FIRMWARE_FIRST: If set, this bit indicates that system firmware will handle errors from this source first. All other bits must be set to zero.
Enabled	1	7	If the field value is 1, indicates this error source is to be enabled. If the field value is 0, indicates that the error source is not to be enabled. If FIRMWARE_FIRST is set in the flags field, the Enabled field is ignored by OSPM.
Number of Records To Pre- allocate	4	8	Indicates the number of error records to pre-allocate for this error source. Must be >= 1.
Max Sections Per Record	4	12	Indicates the maximum number of error sections included in an error record created as a result of an error reported by this error source. Must be >= 1.
Notification Structure	28	16	Hardware Error Notification Structure as defined in Table 17-14.
Number Of Hardware Banks	1	44	The number of hardware error reporting banks.
Reserved	3	45	Reserved.
Machine Check Bank Structure[n]	-	48	A list of Machine Check Bank structures defined in section 17.3.2.1.1.

18.3.2.2.1 IA-32 Architecture Non-Maskable Interrupt

Uncorrected platform errors are typically reported using the Non-Maskable Interrupt (NMI) vector (for example, INT 2). This table allows platform firmware to communicate parameters regarding the configuration and handling of NMI error conditions.

Only one entry of this type is permitted in the HEST.

Table 18-301 IA-32 Architecture NMI Error Structure

Field	Byte Length	Byte Offset	Description
Туре	2	0	2 – IA-32 Architecture NMI Structure.
Source Id	2	2	Uniquely identifies this error source.
Reserved	4	4	Must be zero.
Number of Records To Pre-allocate	4	8	Indicates number of error records to pre-allocate for this error source. Must be >= 1.

Field	Byte Length	Byte Offset	Description
Max Sections Per Record	4	12	Indicates maximum number of error sections included in an error record created as a result of an error reported by this error source. Must be >= 1.
Max Raw Data Length	4	16	The size in bytes of the NMI error data.

18.3.2.3 PCI Express Root Port AER Structure

PCI Express (PCIe) root ports may implement PCIe Advanced Error Reporting (AER) support. This table contains information platform firmware supplies to OSPM for configuring AER support on a given root port.

The HEST may contain one entry of this type for each PCI Express root port if none of the entries has the GLOBAL flag set. If the GLOBAL flag is set, there may only be one entry of this type and the information contained in that entry is applied to all PCIe root ports.

Table 18-302 PCI Express Root Port AER Structure

Field	Byte Length	Byte Offset	Description
Туре	2	0	6 – AER Root Port.
Source Id	2	2	Uniquely identifies the error source.
Reserved	2	4	Reserved.
Flags	1	6	Bit 0 - FIRMWARE_FIRST: If set, this bit indicates to the OSPM that system firmware will handle errors from this source first. Bit 1 - GLOBAL: If set, indicates that the settings contained in this structure apply globally to all PCI Express Devices. All other bits must be set to zero.
Enabled	1	7	If the field value is 1, indicates this error source is to be enabled. If the field value is 0, indicates that the error source is not to be enabled. If FIRMWARE_FIRST is set in the flags field, the Enabled field is ignored by the OSPM.
Number of Records To Pre-allocate	4	8	Indicates the number error records to pre-allocate for this error source. Must be >= 1.
Max Sections Per Record	4	12	Indicates the maximum number of error sections included in an error record created as a result of an error reported by this error source. Must be >= 1.
Bus	4	16	Identifies the PCI Bus and Segment of the root port. The Bus is encoded in bits 0-7. For systems that expose multiple PCI segment groups, the segment number is encoded in bits 8-23 and bits 24-31 must be zero. For systems that do not expose multiple PCI segment groups, bits 8-31 must be zero. If the GLOBAL flag is specified, this field is ignored.
Device	2	20	Identifies the PCI Device Number of the root port. If the GLOBAL flag is specified, this field is ignored.

Field	Byte Length	Byte Offset	Description
Function	2	22	Identifies the PCI Function number of the root port. If the GLOBAL flag is specified, this field is ignored.
Device Control	2	24	Device control bits with which to initialize the device.
Reserved	2	26	Must be zero.
Uncorrectable Error Mask	4	28	Value to write to the root port's Uncorrectable Error Mask register.
Uncorrectable Error Severity	4	32	Value to write to the root port's Uncorrectable Error Severity register.
Correctable Error Mask	4	36	Value to write to the root port's Correctable Error Mask register.
Advanced Error Capabilities and Control	4	40	Value to write to the root port's Advanced Error Capabilities and Control Register.
Root Error Command	4	44	Value to write to the root port's Root Error Command Register.

18.3.2.4 PCI Express Device AER Structure

PCI Express devices may implement AER support. This table contains information platform firmware supplies to OSPM for configuring AER support on a given PCI Express device.

The HEST may contain one entry of this type for each PCI Express endpoint device if none of the entries has the GLOBAL flag set. If the GLOBAL flag is set, there may only be one entry of this type and the information contained in that entry will be applied to all PCI Express endpoint devices.

Table 18-303 PCI Express Device AER Structure

Field	Byte Length	Byte Offset	Description
Туре	2	0	7 – AER Endpoint.
Source Id	2	2	Uniquely identifies the error source.
Reserved	2	4	Reserved.
Flags	1	6	Bit 0 - FIRMWARE_FIRST: If set, indicates that system firmware will handle errors from this source first. Bit 1 - GLOBAL: If set, indicates that the settings contained in this structure apply globally to all PCI Express Devices. All other bits must be set to zero.
Enabled	1	7	If the field value is 1, indicates this error source is to be enabled. If the field value is 0, indicates that the error source is not to be enabled. If FIRMWARE_FIRST is set in the flags field, the Enabled field is ignored by the OSPM.
Number of Records To Pre-allocate	4	8	Indicates the number of error records to pre-allocate for this error source. Must be >= 1.

Field	Byte Length	Byte Offset	Description
Max Sections Per Record	4	12	Indicates the maximum number of error sections included in an error record created as a result of an error reported by this error source. Must be >= 1.
Bus	4	16	Identifies the PCI Bus and Segment of the device. The Bus is encoded in bits 0-7. For systems that expose multiple PCI segment groups, the segment number is encoded in bits 8-23 and bits 24-31 must be zero. For systems that do not expose multiple PCI segment groups, bits 8-31 must be zero. If the GLOBAL flag is specified, this field is ignored.
Device	2	20	Identifies the PCI Device Number of the device. If the GLOBAL flag is specified, this field is ignored.
Function	2	22	Identifies the PCI Function Number of the device. If the GLOBAL flag is specified, this field is ignored.
Device Control	2	24	Device control bits with which to initialize the device.
Reserved	2	26	Must be zero.
Uncorrectable Error Mask	4	28	Value to write to the root port's Uncorrectable Error Mask register.
Uncorrectable Error Severity	4	32	Value to write to the root port's Uncorrectable Error Severity register.
Correctable Error Mask	4	36	Value to write to the root port's Correctable Error Mask register.
Advanced Error Capabilities and Control	4	40	Value to write to the root port's Advanced Error Capabilities and Control Register.

18.3.2.5 PCI Express/PCI-X Bridge AER Structure

PCI Express/PCI-X bridges that implement AER support implement fields that control the behavior how errors are reported across the bridge.

The HEST may contain one entry of this type for each PCI Express/PCI-X bridges if none of the entries has the GLOBAL flag set. If the GLOBAL flag is set, there may only be one entry of this type and the information contained in that entry will be applied to all PCI Express/ PCI-X bridges.

Table 18-304 PCI Express Bridge AER Structure

Field	Byte Length	Byte Offset	Description
Туре	2	0	8 – AER Bridge.
Source Id	2	2	Uniquely identifies the error source.
Reserved	2	4	Reserved.

Field	Byte Length	Byte Offset	Description
Flags	1	6	Bit 0 - FIRMWARE_FIRST: If set, indicates that system firmware will handle errors from this source first. Bit 1 - GLOBAL: If set, indicates that the settings contained in this structure apply globally to all PCI Express Bridges. All other bits must be set to zero.
Enabled	1	7	If the field value is 1, indicates this error source is to be enabled. If the field value is 0, indicates that the error source is not to be enabled. If FIRMWARE_FIRST is set in the flags field, the Enabled field is ignored by the OSPM.
Number of Records To Pre-allocate	4	8	Indicates the number of error records to pre-allocate for this error source. Must be >= 1.
Max Sections Per Record	4	12	Indicates the maximum number of error sections included in an error record created as a result of an error reported by this error source. Must be >= 1.
Bus	4	16	Identifies the PCI Bus and Segment of the bridge. The Bus is encoded in bits 0-7. For systems that expose multiple PCI segment groups, the segment number is encoded in bits 8-23 and bits 24-31 must be zero. For systems that do not expose multiple PCI segment groups, bits 8-31 must be zero. If the GLOBAL flag is specified, this field is ignored.
Device	2	20	Identifies the PCI device number of the bridge. If the GLOBAL flag is specified, this field is ignored.
Function	2	22	Identifies the PCI function number of the bridge. If the GLOBAL flag is specified, this field is ignored.
Device Control	2	24	Device control bits with which to initialize the device.
Reserved	2	26	This value must be zero.
Uncorrectable Error Mask	4	28	Value to write to the bridge's Uncorrectable Error Mask register.
Uncorrectable Error Severity	4	32	Value to write to the bridge's Uncorrectable Error Severity register.
Correctable Error Mask	4	36	Value to write to the bridge's Correctable Error Mask register.
Advanced Error Capabilities and Control	4	40	Value to write to the bridge's Advanced Error Capabilities and Control Register.
Secondary Uncorrectable Error Mask	4	44	Value to write to the bridge's secondary uncorrectable error mask register.
Secondary Uncorrectable Error Severity	4	48	Value to write to the bridge's secondary uncorrectable error severity register.

Field	Byte Length	Byte Offset	Description
Secondary Advanced Capabilities and Control	4	52	Value to write to the bridge's secondary advanced capabilities and control register.

18.3.2.6 Generic Hardware Error Source

The platform may describe a generic hardware error source to OSPM using the Generic Hardware Error Source structure. A generic hardware error source is an error source that either notifies OSPM of the presence of an error using a non-standard notification mechanism or reports error information that is encoded in a non-standard format.

Using the information in a Generic Hardware Error Source structure, OSPM configures an error handler to read the error data from an error status block – a range of memory set aside by the platform for recording error status information.

As the generic hardware error source is non-standard, OSPM does not implement built-in support for configuration and control operations. The error source must be configured by system firmware during boot.

Table 18-305 Generic Hardware Error Source Structure

Field	Byte Length	Byte Offset	Description
Туре	2	0	9 – Generic Hardware Error Source Structure.
Source Id	2	2	Uniquely identify the error source.
Related Source Id	2	4	If this generic error source represents an alternate source to a separate source that the platform has specified that it requires firmware-first handling (See Section 18.4,"Firmware First Error Handling"), this field identifies the error source for which this error source is the alternate. If this generic error source does not represent an alternate source, this field must be set to 0xFFFF.
Flags	1	6	Reserved.
Enabled	1	7	If the field value is 1, indicates this error source is to be enabled. If the field value is 0, indicates that the error source is not to be enabled.
Number of Records To Pre-allocate	4	8	Indicates the number of error records to pre-allocate for this error source. Must be >= 1.
Max Sections Per Record	4	12	Indicates the maximum number of error sections included in an error record created as a result of an error reported by this error source. Must be >= 1.
Max Raw Data Length	4	16	Indicates the size in bytes of the error data recorded by this error source.

Error Status Address	12	20	Generic Address Structure as defined in Section 5.2.3.2 of the ACPI Specification. This field specifies the location of a register that contains the physical address of a block of memory that holds the error status data for this error source. This range of memory must reside in firmware reserved memory. OSPM maps this range into system address space and reads the error status information from the mapped address.
Notification Structure	28	32	Hardware Error Notification Structure as defined in Table 17-14. This structure specifies how this error source notifies OSPM that an error has occurred.
Error Status Block Length	4	60	Identifies the length in bytes of the error status data block.

The *Error Status Address* field specifies the location of an 8-byte memory-mapped register that holds the physical address of the error status block. This error status block must reside in a range of memory reported to OSPM as firmware reserved. OSPM maps the error status buffer into system address space in order to read the error data.

18.3.2.6.1 Generic Error Data

The *Error Status Block* contains the error status information for a given generic error source. OSPM provides an error handler that formats one or more of these blocks as necessary for the specific operating system.

The generic error status block includes two levels of information. The top level is a *Generic Error Status Block* structure and is defined in <u>Table 18-306</u>. Following the Generic Error Status Block structure are one or more *Generic Error Data Entry* structures, defined in <u>Table 18-307</u>.

Table 18-306 Generic Error Status Block

Field	Byte Length	Byte Offset	Description
Block Status	4	0	Indicates the type of error information reported in the error packet. Bit 0 - Uncorrectable Error Valid: If set to one, indicates that an uncorrectable error condition exists. Bit 1 - Correctable Error Valid: If set to one, indicates that a correctable error condition exists. Bit 2 - Multiple Uncorrectable Errors: If set to one, indicates that more than one uncorrectable errors have been detected. Bit 3 - Multiple Correctable Errors: If set to one, indicates that more than one correctable errors have been detected. Bit 4-13 - Error Data Entry Count: This value indicates the number of Error Data Entries found in the <i>Data</i> section. Bit 14-31 - Reserved
Raw Data Offset	4	4	Offset in bytes from the beginning of the Error Status Block to raw error data. The raw data must follow any <i>Generic Error Data Entries</i> .
Raw Data Length	4	8	Length in bytes of the raw data.

Data Length	4	12	Length in bytes of the generic error data.
Error Severity	4	16	Identifies the error severity of the reported error: 0 – Recoverable 1 – Fatal 2 – Corrected 3 – None Note: This is the error severity of the entire event. Each Generic Error Data Entry also includes its own Error Severity field.
Generic Error Data Entries	Data Length	20	The information contained in this field is a collection of zero or more Generic Error Data Entries (see <u>Table 18-307</u>).

One or more *Generic Error Data Entry* structures may be recorded in the *Generic Error Data Entries* field of the *Generic Error Status Block* structure. This allows the platform to accumulate information for multiple hardware components related to a given error event. For example, if the generic error source represents an error that occurs on a device on the secondary side of a PCI Express / PCI-X Bridge, it is useful to record error information from the PCI Express Bridge and from the PCI-X device. Utilizing two *Generic Error Data Entry* structures enables this. <u>Table 18-307</u> defines the layout of a Generic Error Data Entry.

For details of some of the fields defined in <u>Table 18-307</u>. See also Table 3 in section N2.2 of Appendix N of the UEFI 2.1 specification.

Table 18-307 Generic Error Data Entry

Field	Byte Length	Byte Offset	Description
Section Type	16	0	Identifies the type of error data in this entry. See the Section Type field of the Section Descriptor in the UEFI 2.1 specification.
Error Severity	4	16	Identifies the severity of the reported error. 0 – Recoverable 1 – Fatal 2 – Corrected 3 – None
Revision	2	20	The revision number of the error data. The revision number is 0x0201. See the <i>Revision</i> field of the Section Descriptor in the UEFI 2.1 specification.
Validation Bits	1	22	Identifies whether certain fields are populated with valid data. See the <i>Validation Bits</i> field of the Section Descriptor in the UEFI 2.1 specification.
Flags	1	23	Flags describing the error data. See the <i>Flags</i> field of the Section Descriptor in the UEFI 2.1 specification.
Error Data Length	4	24	Length in bytes of the generic error data. It is valid to have a <i>Data Length</i> of zero. This would be used for instance in firmware-first error handling where the platform reports errors to the OSPM using NMI.

FRU Id	16	28	Identifies the Field Replaceable Unit. See the FRU Id field of the Section Descriptor in the UEFI 2.1 specification.
FRU Text	20	44	Text field describing the Field Replaceable Unit. See the <i>FRU Text</i> field of the Section Descriptor in the UEFI 2.1 specification.
Data	Error Data Length	64	Generic error data. The information contained in this field must match one of the error record section types defined in Appendix N of the UEFI 2.1 specification.

18.3.2.6.2 Event Notification For Generic Error Sources

An event notification is recommended for corrected errors where latency in processing error reports is not critical to proper system operation. The implementation of Event notification requires the platform to define a device with PNP ID PNP0C33 in the ACPI namespace, referred to as the error device. This device is used to notify the OSPM that a generic error source is reporting an error. Since multiple generic error sources can use event notification, it is the responsibility of the OSPM to scan the list of these generic error sources and check the block status field (<u>Table 18-306</u>) to identify the source that reported the error.

The platform is responsible for providing a control method that issues a NOTIFY on the error device (PNP0C33), with a notification code of type 0x80.

For traditional ACPI platforms the event signaling follows the model describedin <u>Section 5.6.4.1.1</u>. The platform implements a general purpose event (GPE) for the error notification, and the GPE has an associated control method.

An example of a GPE control method for error notification is the following:

```
Method (\_GPE._L08) { // GPE 8 level error notification
  Notify (error_device, 0x80)
}
```

For HW-reduced ACPI platforms, the event signaling follows the model described in Section 5.6.5. The platform implements a GPIO pin for the error notification, and the GPIO pin has an associated _AEI object and control method.

An example of an EVT control method for error notification is the following:

```
Method (\_EVT) { // GPIO pin 300 error notification
    Switch (Arg1) {
        Case (300) {
            Notify (error_device, 0x80)
        }
    }
}
```

The overall flow when the platform uses the event notification is:

The platform enumerates the error source with event as the notification method using the format in Table 18-305 and Table 18-306

The platform surfaces an error device, PNP ID PNP0C33, to the OSPM

When the platform is ready to report an error, the platform populates the error status block including the block status field (<u>Table 18-306</u>)

Traditional ACPI platforms signal the error using an SCI, on the appropriate GPE:

- The OSPM evaluates the GPE control method associated with this event as indicated on Section 5.6.4.1.1
- OSPM responds to this notification by checking the error status block of all generic error sources with the SCI Generic notification type to identify the source reporting the error

HW-reduced ACPI platforms signal the error using a GPIO interrupt on a pin designated as an ACPI event, as declared by the associated AEI object:

- The OSPM evaluates the control method associated with this event as indicated in Section 5.6.5.3
- OSPM responds to this notification by checking the error status block of all generic error sources with the GPIO-Signal notification type to identify the source reporting the error.

18.3.2.7 Hardware Error Notification

This table describes the notification mechanism associated with a hardware error source.

Table 18-308 Hardware Error Notification Structure

Field	Byte Length	Byte Offset	Description	
Туре	1	0	Identifies the notification type: 0 - Polled 1 - External Interrupt 2 - Local Interrupt 3 - SCI 4 - NMI 5 - CMCI 6 - MCE 7 - GPIO-Signal All other values are reserved	
Length	1	1	Total length of the structure in bytes.	
Configuration Write Enable	2	2	This field indicates whether configuration parameters may be modified by OSPM. If the bit for the associated parameter is set, the parameter is writeable by OSPM: Bit 0: Type Bit 1: Poll Interval Bit 2: Switch To Polling Threshold Value Bit 3: Switch To Polling Threshold Window Bit 4: Error Threshold Value Bit 5: Error Threshold Window All other bits are reserved.	

Field	Byte Length	Byte Offset	Description	
Poll Interval	4	4	Indicates the poll interval in milliseconds OSPM should use to periodically check the error source for the presence of an error condition.	
Vector	4	8	Interrupt vector.	
Switch To Polling Threshold Value	4	12	The number of error interrupts that must occur within <i>Switch To Polling Threshold Interval</i> before OSPM switches the error source to polled mode.	
Switch To Polling Threshold Window	4	16	Indicates the time interval in milliseconds that <i>Switch To Polling Threshold Value</i> interrupts must occur within before OSPM switches the error source to polled mode.	
Error Threshold Value	4	20	Indicates the number of error events that must occur within <i>Error Threshold Interval</i> before OSPM processes the event as an error condition.	
Error Threshold Window	4	24	Indicates the time interval in milliseconds that <i>Error Threshold Value</i> errors must occur within before OSPM processes the eve as an error condition.	

18.4 Firmware First Error Handling

It may be necessary for the platform to process certain classes of errors in firmware before relinquishing control to OSPM for further error handling. Errata management and error containment are two examples where firmware-first error handling is beneficial. Generic hardware error sources support this model through the related source ID.

The platform reports the original error source to OSPM via the hardware error source table (HEST) and sets the FIRMWAREFIRST flag for this error source. In addition, the platform must report a generic error source with a related source ID set to the original source ID. This generic error source is used to notify OSPM of the errors on the original source and their status after the firmware first handling.

There are different notification strategies that can be used in firmware first handling; the following options are available to the platform:

- Traditional ACPI platforms may use NMI to notify the OSPM of both corrected and uncorrected errors for a given error source
- Traditional ACPI platforms may use NMI to report uncorrected errors and the SCI to report corrected errors
- Traditional ACPI platforms may use NMI to report uncorrected errors and polling to notify the OSPM of corrected errors
- HW-reduced ACPI platforms may use GPIO-signaled events or polling to report corrected errors.

18.4.1 Example: Firmware First Handling Using NMI Notification

If the platform chooses to use NMI to report errors, which is the recommended method for uncorrected errors, the platform follows these steps:

- 1. System firmware configures the platform to trigger a firmware handler when the error occurs
- 2. System firmware identifies the error source for which it will handle errors via the error source enumeration interface by setting the FIRMWARE FIRST flag
- 3. System firmware describes the generic error source, and the associated error status block, as described in <u>Section 18.3.2.6</u>. System firmware identifies the relation between the generic error source and the original error source by using the original source ID in the related source ID of <u>Table 18-305</u>.
- 4. When a hardware error reported by the error source occurs, system firmware gains control and handles the error condition as required. Upon completion system firmware should do the following:
 - a Extract the error information from the error source and fill in the error information in the data block of the generic error source it identified as an alternate in step 3. The error information format follows the specification in <u>Section 18.3.2.6.1</u>
 - b Set the appropriate bit in the block status field (<u>Table 18-306</u>) to indicate to the OSPM that a valid error condition is present.
 - c Clears error state from the hardware.
 - d Generates an NMI.

At this point, the OSPM NMI handler scans the list of generic error sources to find the error source that reported the error and processes the error report

18.5 Error Serialization

- The error record serialization feature is used to save and retrieve hardware error information to
 and from a persistent store. OSPM interacts with the platform through a platform interface. On
 UEFI-based platforms, the UEFI runtime variable services can be used to carry out error record
 persistence operations. On non-UEFI based platforms, the ACPI solution described below is
 used.
- For error persistence across boots, the platform must implement some form of non-volatile store to save error records. The amount of space required depends on the platform's processor architecture. Typically, this store will be flash memory or some other form of non-volatile RAM.
- Serialized errors are encoded according to the Common Platform Error Record (CPER) format, which is described in appendix N of the UEFI 2.1 specification. These entries are referred to as *error records*.
- The Error Record Serialization Interface is designed to be sufficiently abstract to allow hardware vendors flexibility in how they implement their error record serialization hardware. The platform provides details necessary to communicate with its serialization hardware by populating the ERST with a set of Serialization Instruction Entries. One or more serialization instruction entries comprise a Serialization Action. OSPM carries out serialization operations by

executing a series of Serialization Actions. Serialization Actions and Serialization Instructions are described in detail in the following sections.

<u>Table 18-309</u> details the layout of the ERST which system firmware is responsible for building.

Table 18-309 Error Record Serialization Table (ERST)

Field	Byte Length	Byte Offset	Description
ACPI Standard Header			
Header Signature	4	0	"ERST". Signature for the Error Record Serialization Table.
Length	4	4	Length, in bytes, of entire ERST. Entire table must be contiguous.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID.
OEM Table ID	8	16	The manufacturer model ID.
OEM Revision	4	24	OEM revision of the ERST for the supplied OEM table ID.
Creator ID	4	28	Vendor ID of the utility that created the table.
Creator Revision	4	32	Revision of the utility that created the table.
Serialization Header			
Serialization Header Size	4	36	Length in bytes of the serialization header.
Reserved	4	40	Must be zero.
Instruction Entry Count	4	44	The number of Serialization Instruction Entries in the Serialization Action Table.
Serialization Action Table			
Serialization Instruction Entries		48	A series of error logging instruction entries.

18.5.1 Serialization Action Table

A Serialization Action is defined as a series of Serialization Instructions on registers that result in a well known action. A Serialization Instruction is a Serialization Action primitive and consists of either reading or writing an abstracted hardware register. The Serialization Action Table contains Serialization Instruction Entries for all the Serialization Actions the platform supports.

In most cases, a Serialization Action comprises only one Serialization Instruction, but it is conceivable that a more complex device will require more than one Serialization Instruction. When an action does comprise more than one instruction, the instructions must be listed consecutively and they will consequently be performed sequentially, according to their placement in the Serialization Action Table.

18.5.1.1 Serialization Actions

This section identifies the Serialization Actions that comprise the Error Record Serialization interface. <u>Table 18-310</u> identifies the supported error record Serialization Actions.

Table 18-310 Error Record Serialization Actions

Value	Name	Description
0x0	BEGIN_WRITE_OPERATION	Indicates to the platform that an error record write operation is beginning. This allows the platform to set its operational context.
0x1	BEGIN_READ_OPERATION	Indicates to the platform that an error record read operation is beginning. This allows the platform to set its operational context.
0x2	BEGIN_CLEAR_OPERATION	Indicates to the platform that an error record clear operation is beginning. This allows the platform to set its operation context.
0x3	END_OPERATION	Indicates to the platform that the current error record operation has ended. This allows the platform to clear its operational context.
0x4	SET_RECORD_OFFSET	Sets the offset from the base of the <i>Error Log Address Range</i> to or from which the platform is to transfer an error record.
0x5	EXECUTE_OPERATION	Instructs the platform to carry out the current operation based on the current operational context.
0x6	CHECK_BUSY_STATUS	Returns the state of the current operation. Once an operation has been executed through the EXECUTE_OPERATION action, the platform is required to return an indication that the operation is in progress until the operation completes. This allows the OS to poll for completion by repeatedly executing the CHECK_BUSY_STATUS action until the platform indicates that the operation not busy.
0x7	GET_COMMAND_STATUS	Returns the status of the current operation. The platform is expected to maintain a status code for each operation. See Table 17-17 for a list of valid command status codes.
0x8	GET_RECORD_IDENTIFIER	Returns the record identifier of an existing error record on the persistent store. The error record identifier is a 64-bit unsigned value as defined in Appendix N of version 2.1 of the UEFI specification. If the record store is empty, this action must return 0xFFFFFFFFFFFFFFF.
0x9	SET_RECORD_IDENTIFIER	Sets the record identifier. The error record identifier is a 64-bit unsigned value as defined in Appendix N of version 2.1 of the UEFI specification.
0xA	GET_RECORD_COUNT	Retrieves the number of error records currently stored on the platforms persistent store. The platform is expected to maintain a count of the number of error records resident in its persistent store.
0xB	BEGIN_DUMMY_WRITE_OPE RATION	Indicates to the platform that a dummy error record write operation is beginning. This allows the platform to set its operational context. A dummy error record write operation performs no actual transfer of information from the <i>Error Log Address Range</i> to the persistent store.

Value	Name	Description
0xC	RESERVED	Reserved.
0xD	GET_ERROR_LOG_ADDRESS _RANGE	Returns the 64-bit physical address OSPM uses as the buffer for reading/writing error records.
0xE	GET_ERROR_LOG_ADDRESS _RANGE_LENGTH	Returns the length in bytes of the Error Log Address Range
0xF	GET_ERROR_LOG_ADDRESS _RANGE_ATTRIBUTES	Returns attributes that describe the behavior of the error log address range. Bit 0 (0x1) – Reserved. Bit 1 (0x2) – Non-Volatile: Indicates that the error log address range is in non-volatile RAM. Bit 2 (0x4) – Slow: Indicates that the memory in which the error log address range is locates has slow access times. All other bits reserved.

<u>Table 18-311</u> below defines the serialization action status codes returned from GET COMMAND STATUS.

Table 18-311 Command Status Definition

Value	Description	
0x00	Success	
0x01	Not Enough Space	
0x02	Hardware Not Available	
0x03	Failed	
0x04	Record Store Empty	
0x05	Record Not Found	

18.5.1.2 Serialization Instruction Entries

Each Serialization Action consists of a series of one or more Serialization Instructions. A Serialization Instruction represents a primitive operation on an abstracted hardware register represented by the register region as defined in a Serialization Instruction Entry.

A Serialization Instruction Entry describes a region in a serialization hardware register and the serialization instruction to be performed on that region. <u>Table 18-312</u> details the layout of a Serialization Instruction Entry.

Table 18-312 Serialization Instruction Entry

Field	Byte Length	Byte Offset	Description
Serialization Action	1	N+0	The serialization action that this serialization instruction is a part of.
Instruction	1	N+1	Identifies the instruction to execute. See Table 17-19 for a list of valid instructions.
Flags	1	N+2	Flags that qualify the instruction.

Field	Byte Length	Byte Offset	Description
Reserved	1	N+3	Must be zero.
Register Region	12	N+4	Generic address structure as defined in <u>Section 5.2.3.2</u> to describe the address and bit.
Value	8	N+16	Value used with READ_REGISTER_VALUE and WRITE_REGISTER_VALUE instructions.
Mask	8	N+24	The bit mask required to obtain the bits corresponding to the serialization instruction in a given bit range defined by the register region.

Register region is described as a generic address structure. This structure describes the physical address of a register as well as the bit range that corresponds to a desired region of the register. The bit range is defined as the smallest set of consecutive bits that contains every bit in the register that is associated with the Serialization Instruction. If bits [6:5] and bits [3:2] all correspond to a Serialization Instruction, the bit range for that instruction would be [6:2].

Because a bit range could contain bits that do not pertain to a particular Serialization Instruction (i.e. bit 4 in the example above), a bit mask is required to distinguish all the bits in the region that correspond to the instruction. The Mask field is defined to be this bit mask with a bit set to '1' for each bit in the bit range (defined by the register region) corresponding to the Serialization Instruction. Note that bit 0 of the bit mask corresponds to the lowest bit in the bit range. In the example used above, the mask would be 11011b or 0x1B.

The Instruction field identifies the operation to be performed on the register region by the instruction entry. <u>Table 18-313</u> identifies the instructions that are supported.

Table 18-313 Serialization Instructions

Value	Name	Description
0x00	READ_REGISTER	A READ_REGISTER instruction reads the designated information from the specified Register Region.
0x01	READ_REGISTER_VALUE	A READ_REGISTER_VALUE instruction reads the designated information from the specified Register Region and compares the results with the contents of the Value field. If the information read matches the contents of the Value field, TRUE is returned, else FALSE is returned.
0x02	WRITE_REGISTER	A WRITE_REGISTER instruction writes a value to the specified Register Region. The Value field is ignored.
0x03	WRITE_REGISTER_VALUE	A WRITE_REGISTER_VALUE instruction writes the contents of the Value field to the specified Register Region.
0x04	NOOP	This instruction is a NOOP.
0x05	LOAD_VAR1	Loads the VAR1 variable from the register region.
0x06	LOAD_VAR2	Loads the VAR2 variable from the register region.
0x07	STORE_VAR1	Stores the value in VAR1 to the indicate register region.
0x08	ADD	Adds VAR1 and VAR2 and stores the result in VAR1.
0x09	SUBTRACT	Subtracts VAR1 from VAR2 and stores the result in VAR1.

Value	Name	Description
0x0A	ADD_VALUE	Adds the contents of the specified register region to Value and stores the result in the register region.
0x0B	SUBTRACT_VALUE	Subtracts Value from the contents of the specified register region and stores the result in the register region.
0x0C	STALL	Stall for the number of microseconds specified in Value.
0x0D	STALL_WHILE_TRUE	OSPM continually compares the contents of the specified register region to Value until the values are not equal. OSPM stalls between each successive comparison. The amount of time to stall is specified by VAR1 and is expressed in microseconds.
0x0E	SKIP_NEXT_INSTRUCTION_I F_TRUE	This is a control instruction which compares the contents of the register region with Value. If the values match, OSPM skips the next instruction in the sequence for the current action.
0x0F	GOTO	OSPM will go to the instruction specified by Value. The instruction is specified as the zero-based index. Each instruction for a given action has an index based on its relative position in the array of instructions for the action.
0x10	SET_SRC_ADDRESS_BASE	Sets the SRC_BASE variable used by the MOVE_DATA instruction to the contents of the register region.
0x11	SET_DST_ADDRESS_BASE	Sets the DST_BASE variable used by the MOVE_DATA instruction to the contents of the register region.
0x12	MOVE_DATA	Moves VAR2 bytes of data from SRC_BASE + Offset to DST_BASE + Offset, where Offset is the contents of the register region.

The Flags field allows qualifying flags to be associated with the instruction. <u>Table 18-314</u> identifies the flags that can be associated with Serialization Instructions.

Table 18-314 Instruction Flags

Value	Name	Description
0x01	PRESERVE_REGISTER	For WRITE_REGISTER and WRITE_REGISTER_VALUE instructions, this flag indicates that bits within the register that are not being written must be preserved rather than destroyed.
		For READ_REGISTER instructions, this flag is ignored.

18.5.1.2.1 READ_REGISTER_VALUE

A read register value instruction reads the register region and compares the result with the specified value. If the values are not equal, the instruction failed. This can be described in pseudo code as follows:

```
X = Read(register)
X = X >> Bit Offset described in Register Region
X = X & Mask
If (X != Value) FAIL
SUCCEED
```

18.5.1.2.2 READ_REGISTER

A read register instruction reads the register region. The result is a generic value and should not be compared with Value. Value will be ignored. This can be described in pseudo code as follows:

```
X = Read(register)
X = X >> Bit Offset described in Register Region
X = X & Mask
Return X
```

18.5.1.2.3 WRITE REGISTER VALUE

A write register value instruction writes the specified value to the register region. If PRESERVE_REGISTER is set in Instruction Flags, then the bits not corresponding to the write value instruction are preserved. If the register is preserved, the write value instruction requires a read of the register. This can be described in pseudo code as follows:

```
X = Value & Mask
X = X << Bit Offset described in Register Region
If (Preserve Register)
    Y = Read(register)
    Y = Y & ~(Mask << Bit Offset)
    X = X | Y
Write(X, Register)</pre>
```

18.5.1.2.4 WRITE REGISTER

A write register instruction writes a value to the register region. Value will be ignored. If PRESERVE_REGISTER is set in Instruction Flags, then the bits not corresponding to the write instruction are preserved. If the register is preserved, the write value instruction requires a read of the register. This can be described in pseudo code as follows:

```
X = supplied value
X = X & Mask
X = X << Bit Offset described in Register Region
If (Preserve Register)
    Y = Read(register)
    Y = Y & ~(Mask << Bit Offset)
    X = X | Y
Write(X, Register)</pre>
```

18.5.1.3 Error Record Serialization Information

The APEI error record includes an 8 byte field called OSPM Reserved. <u>Table 18-315</u> defines the layout of this field. The error record serialization information is a small buffer the platform can use for serialization bookkeeping. The platform is free to use the 48 bits starting at bit offset 16 for its

own purposes. It may use these bits to indicate the busy/free status of an error record, to record an internal identifier, etc.

Table 18-315 Error Record Serialization Info

Field	Bit Length	Bit Offset	Description
Signature	16	0	16-bit signature ('ER') identifying the start of the error record serialization data.
Platform Serialization Data	48	16	Platform private error record serialization information.

18.5.2 Operations

The error record serialization interface comprises three operations: Write, Read, and Clear. OSPM uses the Write operation to write a single error record to the persistent store. The Read operation is used to retrieve a single error record previously recorded to the persistent store using the write operation. The Clear operation allows OSPM to notify the platform that a given error record has been fully processed and is no longer needed, allowing the platform to recover the storage associated with a cleared error record.

Where the *Error Log Address Range* is NVRAM, significant optimizations are possible since transfer from the *Error Log Address Range* to a separate storage device is unnecessary. The platform may still, however, copy the record from NVRAM to another device, should it choose to. This allows, for example, the platform to copy error records to private log files. In order to give the platform the opportunity to do this, OSPM must use the Write operation to persist error records even when the *Error Log Address Range* is NVRAM. The Read and Clear operations, however, are unnecessary in this case as OSPM is capable of reading and clearing error records without assistance from the platform.

18.5.2.1 Writing

To write a single HW error record, OSPM executes the following steps:

- 1. Initializes the error record's serialization info. OSPM must fill in the *Signature*.
- 2. Writes the error record to be persisted into the
- 3. Error Log Address Range.
- 4. Executes the BEGIN_WRITE_OPERATION action to notify the platform that a record write operation is beginning.
- 5. Executes the SET RECORD OFFSET action to inform the platform where in the
- 6. Error Log Address Range the error record resides.
- 7. Executes the EXECUTE_OPERATION action to instruct the platform to begin the write operation.
- 8. Busy waits by continually executing CHECK BUSY STATUS action until FALSE is returned.
- 9. Executes a GET_COMMAND_STATUS action to determine the status of the write operation. If an error is indicated, the OS
- 10. PM may retry the operation.

11. Executes an END_OPERATION action to notify the platform that the record write operation is complete.

When OSPM performs the EXECUTE_OPERATION action in the context of a record write operation, the platform attempts to transfer the error record from the designated offset in the *Error Log Address Range* is non-volatile RAM, no transfer is required.

Where the platform is required to transfer the error record from the *Error Log Address Range* to a persistent store, it performs the following steps in response to receiving a write command:

- 1. Sets some internal state to indicate that it is busy. OSPM polls by executing a CHECK BUSY STATUS action until the operation is completed.
- 2 Reads the error record's
- 3. *Record ID* field to determine where on the storage medium the supplied error record is to be written. The platform attempts to locate the specified error record on the persistent store.
 - a If the specified error record does not exist, the platform attempts to write a new record to the persistent store.
 - b If the specified error record does exists, then if the existing error record is large enough to be overwritten by the supplied error record, the platform can do an in-place replacement. If the existing record is not large enough to be overwritten, the platform must attempt to locate space in
 - which to write the new record. It may mark the existing record as Free and coalesce adjacent free records in order to create the necessary space.
- 4. Transfers the error record to the selected location on the persistent store.
- 5. Updates an internal
- 6. Record Count if a new record was written.
- 7. Records the s
- 8. tatus of the operation so OSPM can retrieve the status by executing a GET COMMAND STATUS action.
- 9. Modifies internal busy state as necessary so when OS
- 10. PM executes CHECK BUSY STATUS, the result indicates that the operation is complete.

If the *Error Log Address Range* resides in NVRAM, the minimum steps required of the platform are:

- 1. Sets some internal state to indication that it is busy. OSPM polls by executing a CHECK BUSY STATUS action until the operation is completed.
- 2. Records the status of the o
- 3. peration so OSPM can retrieve the status by executing a GET COMMAND STATUS action.
- 4. Clear internal busy state so when OS
- 5. PM executes CHECK BUSY STATUS, the result indicates that the operation is complete.

18.5.2.2 Reading

During boot, OSPM attempts to retrieve all serialized error records from the persistent store. If the *Error Log Address Range* does not reside in NVRAM, the following steps are executed by OSPM to retrieve all error records:

- 1. Executes the BEGIN_READ_OPERATION action to notify the platform that a record read operation is beginning.
- 2. Executes the SET_RECORD_OFFSET action to inform the platform at what offset in the *Error Log Address Range* the error record is to be transferred.
- 3. Executes the SET_RECORD_IDENTIFER action to inform the platform which error record is to be read from its persistent store.
- 4. Executes the EXECUTE_OPERATION action to instruct the platform to begin the read operation.
- 5. Busy waits by continually executing CHECK BUSY STATUS action until FALSE is returned.
- 6. Executes a GET_COMMAND_STATUS action to determine the status of the read operation.
 - a If the status is *Record Store Empty (0x04)*, continue to step 7.
 - b If an error occurred reading a valid error record, the status will be Failed(0x03), continue to step 7.
 - c If the status is $Record\ Not\ Found\ (0x05)$, indicating that the specified error record does not exist, OSPM retrieves a valid identifier by executing a GET_RECORD_IDENTIFIER action. The platform will return a valid record identifier.
 - d If the status is *Success*, OSPM transfers the retrieved record from the *Error Log Address Range* to a private buffer and then executes the GET_RECORD_IDENTIFIER action to determine the identifier of the next record in the persistent store.
- 7. Execute an END_OPERATION to notify the platform that the record read operation is complete.

The steps performed by the platform to carry out a read request are as follows:

- 1. Sets some internal state to indicate that it is busy. OSPM polls by executing a CHECK BUSY STATUS action until the operation is completed.
- 2. Using the record identifier supplied by OSPM through the SET_RECORD_IDENTIFIER operation, determine which error record to read:
 - a If the identifier is 0x0 (unspecified), the platform reads the 'first' error record from its persistent store. First, in this is implementation specific.
 - b If the identifier is non-zero, the platform attempts to locate the specified error record on the persistent store.
 - c If the specified error record does not exist, set the status register's
 - d Status to Record Not Found (0x05), and update the status register's Identifier field with the identifier of the 'first' error record.
- 3. Transfer the record from the persistent store to the offset specified by OSPM from the base of the *Error Log Address Range*.
- 4. Record the *Identifier* of the 'next' valid error record that resides on the persistent store. This allows OSPM to retrieve a valid record identifier by executing a GET_RECORD_IDENTIFIER operation.
- 5. Record the status of the operation so OSPM can retrieve the status by executing a GET COMMAND STATUS action.
- 6. Clear internal busy state so when OSPM executes CHECK_BUSY_STATUS, the result indicates that the operation is complete.

Where the *Error Log Address Range* does reside in NVRAM, OSPM requires no platform support to read persisted error records. OSPM can scan the *Error Log Address Range* on its own and retrieve the error records it previously persisted.

18.5.2.3 Clearing

After OSPM has finished processing an error record, it will notify the platform by clearing the record. This allows the platform to delete the record from the persistent store or mark it such that the space is free and can be reused. The following steps are executed by OSPM to clear an error record:

- 1. Executes a BEGIN_ CLEAR_OPERATION action to notify the platform that a record clear operation is beginning.
- 2. Executes a SET_RECORD_IDENTIFER action to inform the platform which error record is to be cleared. This value must not be set to 0x0 (unspecified).
- 3. Executes an EXECUTE_OPERATION action to instruct the platform to begin the clear operation.
- 4. Busy waits by continually executing CHECK BUSY STATUS action until FALSE is returned.
- 5. Executes a GET_COMMAND_STATUS action to determine the status of the clear operation.
- 6. Execute an END_OPERATION to notify the platform that the record read operation is complete.

The platform carries out a clear request by performing the following steps:

- 1. Sets some internal state to indication that it is busy. OSPM polls by executing a CHECK BUSY STATUS action until the operation is completed.
- 2. Using the record identifier supplied by OSPM through the SET_RECORD_IDENTIFIER operation, determine which error record to clear. This value may not be 0x0 (unspecified).
- 3. Locate the specified error record on the persistent store.
- 4. Mark the record as free by updating the Attributes in its serialization header.
- 5. Update internal record count.
- 6. Clear internal busy state so when OS
- 7. PM executes CHECK BUSY STATUS, the result indicates that the operation is complete.

When the *Error Log Address Range* resides in NVRAM, the OS requires no platform support to Clear error records.

18.5.2.4 Usage

This section describes several possible ways the error record serialization mechanism might be implemented.

18.5.2.4.1 Error Log Address Range Resides in NVRAM

If the *Error Log Address Range* resides in NVRAM, then when OSPM writes a record into the logging range, the record is automatically persistent and the busy bit can be cleared immediately. On a subsequent boot, OSPM can read any persisted error records directly from the persistent store range. The size of the persistent store, in this case, is expected to be enough for several error records.

18.5.2.4.2 Error Log Address Range Resides in (volatile) RAM

In this implementation, the *Error Log Address Range* describes an intermediate location for error records. To persist a record, OSPM copies the record into the *Error Log Address Range* and sets the *Execute*, at which time the platform runs necessary code (SMM code on non-UEFI based systems and UEFI runtime code on UEFI-enabled systems) to transfer the error record from main memory to some persistent store. To read a record, OSPM asks the platform to copy a record from the persistent store to a specified offset within the *Error Log Address Range*. The size of the *Error Log Address Range* is at least large enough for one error record.

18.5.2.4.3 Error Log Address Range Resides on Service Processor

In this type of implementation, the *Error Log Address Range* is really MMIO. When OSPM writes an error record to the *Error Log Address Range*, it is really writing to memory on a service processor. When the OSPM sets the *Execute* control bit, the platform knows that the OSPM is done writing the record and can do something with it, like move it into a permanent location (i.e. hard disk) on the service processor. The size of the persistent store in this type of implementation is typically large enough for one error record.

18.5.2.4.4 Error Log Address Range is Copied Across Network

In this type of implementation, the *Error Log Address Range* is an intermediate cache for error records. To persist an error record, OSPM copies the record into the *Error Log Address Range* and set the *Execute* control bit, and the platform runs code to transmit this error record over the wire. The size of the *Error Log Address Range* in this type of implementation is typically large enough for one error record.

18.6 Error Injection

This section outlines an ACPI table mechanism, called EINJ, which allows for a generic interface mechanism through which OSPM can inject hardware errors to the platform without requiring platform specific OSPM level software. The primary goal of this mechanism is to support testing of OSPM error handling stack by enabling the injection of hardware errors. Through this capability OSPM is able to implement a simple interface for diagnostic and validation of errors handling on the system.

18.6.1 Error Injection Table (EINJ)

The Error Injection Table provides a generic interface mechanism through which OSPM can inject hardware errors to the platform without requiring platform specific OSPM software. System firmware is responsible for building this table, which is made up of Injection Instruction entries. Table 18-316 details the layout of the table.

Table 18-316 Error Injection Table (EINJ)

Field	Byte length	Byte offset	Description
ACPI Standard Header			
Header Signature	4	0	EINJ. Signature for the Error Record Injection Table.

Field	Byte length	Byte offset	Description
Length	4	4	Length, in bytes, of entire EINJ. Entire table must be contiguous.
Revision	1	8	1
Checksum	1	9	Entire table must sum to zero.
OEMID	6	10	OEM ID.
OEM Table ID	8	16	The manufacturer model ID.
OEM Revision	4	24	OEM revision of EINJ.
Creator ID	4	28	Vendor ID of the utility that created the table.
Creator Revision	4	32	Revision of the utility that created the table.
Injection Header			
Injection Header Size	4	36	Length in bytes of the Injection Interface header.
Injection Flags	1	40	Reserved. Must be zero
Reserved	3	41	Must be zero.
Injection Entry Count	4	44	The number of Instruction Entries in the Injection Action Table
Injection Action Table			
Injection Instruction Entries		48	A series of error injection instruction entries

<u>Table 18-317</u> identifies the supported error injection actions.

Table 18-317 Error Injection Actions

Value	Name	Description
0x0	BEGIN_INJECTION_OPERATION	Indicates to the platform that an error injection is beginning. This allows the platform to set its operational context.
0x1	GET_TRIGGER_ERROR_ACTION_T ABLE	Returns a 64-bit physical memory pointer to the TRIGGER_ERROR action table. The TRIGGER_ERROR action instructions when executed by software trigger the error that was injected by the immediately prior SET_ERROR_TYPE action.
0x2	SET_ERROR_TYPE	Type of error to Inject. Only one ERROR_TYPE can be injected at any given time. If there is request for multiple injections at the same time, then the platform will return an error condition.
0x3	GET_ERROR_TYPE	Returns the error injection capabilities of the platform.
0x4	END_OPERATION	Indicates to the platform that the current injection operation has ended. This allows the platform to clear its operational context.
0x5	EXECUTE_OPERATION	Instructs the platform to carry out the current operation based on the current operational context.

Value	Name	Description
0x6	CHECK_BUSY_STATUS	Returns the state of the current operation. Once an operation has been executed through the EXECUTE_OPERATION action, the platform is required to return an indication that the operation is busy until the operation is completed. This allows software to poll for completion by repeatedly executing the CHECK_BUSY_STATUS action until the platform indicates that the operation is complete by setting not busy. The lower most bit (bit0) of the returned value indicates the busy status by setting it to 1 and not busy status by setting it to 0.
0x7	GET_COMMAND_STATUS	Returns the status of the current operation. The platform is expected to maintain a status code for each operation. Bits 1:8 of the returned value indicate the command status. See Table 18-311 for a list of valid command status codes.
0x8	SET_ERROR_TYPE_WITH_ADDRE SS	Type of error to Inject, and the address to inject. Only one Error type can be injected at any given time. If there is request for multiple injections at the same time, then the platform will return an error condition. Both this Action and the SET_ERROR_TYPE action will be present as part of this EINJ action table. OSPM is free to choose either of these two actions to inject an error. The platform will give precedence to SET_ERROR_TYPE_WITH_ADDRESS. In other words, if a non-zero value is set using SET_ERROR_TYPE_WITH_ADDRESS, then any error type value set by SET_ERROR_TYPE will be ignored. If, on the other hand, if no error type is specified using SET_ERROR_TYPE_WITH_ADDRESS, then the platform will use SET_ERROR_TYPE to identify the error type to inject. The RegisterRegion field (SeeTable 18-318) in SET_ERROR_TYPE_WITH_ADDRESS points to a data structure whose format is defined in Table 18-308. Note that calling set error type with address without specifying address has the same behavior as calling SET_ERROR_TYPE.
0xFF	TRIGGER_ERROR	This is not a true error injection action. In response to error injection, the platform returns a trigger error action table. This table consists of a series of injection instruction entries where the injection action is set to TRIGGER_ERROR to distinguish such entries.

18.6.2 Injection Instruction Entries

An Injection action consists of a series of one or more Injection Instructions. An Injection Instruction represents a primitive operation on an abstracted hardware register, represented by the register region as defined in an Injection Instruction Entry.

An Injection Instruction Entry describes a region in an injection hardware register and the injection instruction to be performed on that region.

<u>Table 18-318</u> details the layout of an Injection Instruction Entry.

Table 18-318 Injection Instruction Entry

Field	Byte length	Byte offset	Description	
Injection Action	1	N+0	The injection action that this instruction is a part of. See Table 17-23 for supported injection actions.	
Instruction	1	N+1	Identifies the instruction to execute. See Table 17-26 for a list of valid instructions.	
Flags	1	N+2	Flags that qualify the instruction.	
Reserved	1	N+3	Must be zero.	
Register Region	12	N+4	Generic address structure as defined in <u>Section 5.2.3.2</u> to describe the address and bit. Address_Space_ID must be 0 (System Memory) or 1 (System IO). This constraint is an attempt to ensure that the registers are accessible in the presence of hardware error conditions.	
Value	8	N+16	This is the value field that is used by the instruction READ or WRITE_REGISTER_VALUE.	
Mask	8	N+24	The bit mask required to obtain the bits corresponding to the injection instruction in a given bit range defined by the register region.	

Register region is described as a generic address structure. This structure describes the physical address of a register as well as the bit range that corresponds to a desired region of the register. The bit range is defined as the smallest set of consecutive bits that contains every bit in the register that is associated with the injection Instruction. If bits [6:5] and bits [3:2] all correspond to an Injection Instruction, the bit range for that instruction would be [6:2].

Because a bit range could contain bits that do not pertain to a particular injection Instruction (i.e. bit 4 in the example above), a bit mask is required to distinguish all the bits in the region that correspond to the instruction. The Mask field is defined to be this bit mask with a bit set to a '1' for each bit in the bit range (defined by the register region) corresponding to the Injection Instruction. Note that bit 0 of the bit mask corresponds to the lowest bit in the bit range. In the example used above, the mask would be 11011b or 0x1B.

Table 18-319 Instruction Flags

Value	Name	Description
0x01	PRESERVE_REGISTER	For WRITE_REGISTER and WRITE_REGISTER_VALUE instructions, this flag indicates that bits within the register that are not being written must be preserved rather than destroyed. For READ_REGISTER instructions, this flag is ignored.

18.6.3 Injection Instructions

<u>Table 18-320</u> lists the supported Injection Instructions for Injection Instruction Entries.

Table 18-320 Injection Instructions

Opcode	Instruction name	Description
0x00	READ_REGISTER	A READ_REGISTER instruction reads the value from the specified register region.
0x01	READ_REGISTER_VALUE	A READ_REGISTER_VALUE instruction reads the designated information from the specified Register Region and compares the results with the contents of the Value field. If the information read matches the contents of the Value field, TRUE is returned, else FALSE is returned.
0x02	WRITE_REGISTER	A WRITE_REGISTER instruction writes a value to the specified Register Region. The Value field is ignored.
0x03	WRITE_REGISTER_VALUE	A WRITE_REGISTER_VALUE instruction writes the contents of the Value field to the specified Register Region.
0x04	NOOP	No operation.

<u>Table 18-321</u> below defines the error injection status codes returned from GET_COMMAND_STATUS.

Table 18-321 Command Status Definition

Value	Description
0x0	Success
0x1	Unknown Failure
0x2	Invalid Access

<u>Table 18-322</u> below defines the error type codes returned from GET_ERROR_TYPE.

Table 18-322 Error Type Definition

Bit	Description
0	Processor Correctable
1	Processor Uncorrectable non-fatal
2	Processor Uncorrectable fatal

ACPI Platform Error Interfaces (APEI)

Bit	Description	
3	Memory Correctable	
4	Memory Uncorrectable non-fatal	
5	Memory Uncorrectable fatal	
6	PCI Express Correctable	
7	PCI Express Uncorrectable non-fatal	
8	PCI Express Uncorrectable fatal	
9	Platform Correctable	
10	Platform Uncorrectable non-fatal	
11	Platform Uncorrectable fatal	
12:30	RESERVED	
31	Vendor Defined Error Type. If this bit is set, then the Error types and related data structures are defined by the Vendor, as shown in Table 18-324 .	

Table 18-323 SET_ERROR_TYPE_WITH_ADDRESS Data Structure

Field	Byte Length	Byte Offset	Description	
Error Type	4	0x0	Bit map of error types to inject. Refer <u>Table 18-322</u> . This field is cleared by the platform once it is consumed.	
Vendor Error Type Extension Structure Offset	4	4	Specifies the offset from the beginning of the table to the vendor error type extension structure. If no vendor error type extension is present, bit31 in error type must be clear and this field must be set to 0.	
Flags	4	0x8	BIT 0 – Processor APIC Field Valid BIT 1 – Memory Address and Memory address Mask Field Valid BIT 2 – PCIe SBDF field valid BIT3:BIT31 – RESERVED This field is cleared by the platform once it is consumed.	
Processor Error				
APIC ID	4	0x0C	Optional field which specifies the physical APIC ID or the X2APIC ID of the processor which is a target for the injection.	
Memory Error		•		
Memory Address	8	0x10	Optional field which specifies the physical address of the memory which is the target for the injection. Valid if BIT 1 of the <i>Flags</i> field is set.	
Memory Address Range	8	0x18	Optional field which provided a range mask for the address field. Valid if BIT 1 of the <i>Flags</i> field is set. If the OSPM doesn't want to provide a range of address, then this field should be zero.	

Field	Byte Length	Byte Offset	Description
PCIe SBDF	4	0x20	BYTE 3 – PCIe Segment BYTE 2 – Bus Number BYTE 1 – Device Number[BITs 7:3], Function Number BITs[2:0] BYTE 0 – RESERVED

Table 18-324 Vendor Error Type Extension Structure

Field	Byte Length	Byte Offset	Attribute	Description
Length	4	0x0	Set by software. RO for Platform	
SBDF	4	0x04	Set by Platform. RO for Software	This provides a PCIe Segment, Bus, Device and Function number which can be used to read the Vendor ID, Device ID and Rev ID, so that software can identify the system for error injection purposes. The platform sets this field and is RO for Software
Vendor ID	2	0x08	Set by Platform. RO for Software	Vendor ID which identifies the device manufacturer. This is same as the PCI SIG defined Vendor ID The platform sets this field and is RO for Software
Device ID	2	0x0A	Set by Platform. RO for Software	This 16-bit ID is assigned by the manufacturer that identifies this device. The platform sets this field and is RO for Software
Rev ID	1	0x0C	Set by Platform. RO for Software	This 8-bit value is assigned by the manufacturer and identifies the revision number of the device. The platform sets this field and is RO for Software
Reserved	3	0x0D	Set by Platform. RO for Software	Reserved
OEM Defined structure	N	0x10		The rest of the fields are defined by the OEM.

18.6.4 Trigger Action Table

Error injection operation is a two step process where the error is injected into the platform and subsequently triggered. After software injects an error into the platform using SET_ERROR_TYPE action, it needs to trigger the error. In order to trigger the error, the software invokes GET_TRIGGER_ERROR_ACTION_TABLE action which returns a pointer to a Trigger Error

ACPI Platform Error Interfaces (APEI)

Action table. The format of the table is as shown in <u>Table 18-325</u>. Software executes the instruction entries specified in the Trigger Error Action Table in order to trigger the injected error.

Table 18-325 Trigger Error Action

TRIGGER_ERROR Header	Byte Length	Byte Offset	Description
Header Size	4	0	Length in bytes of this header.
Revision	4	4	
Table Size	4	8	Size in Bytes of the entire table.
Entry Count	4	12	The number of Instruction Entries in the TRIGGER_ERROR Action Sequence (See Note 1)
Action Table			
TRIGGER_ERROR Instruction Entries (See Note 2)		16	A series of error injection instruction entries as defined in Table 17-26.

Note: If the "Entry Count" field above is ZERO, then there are no action structures in the TRIGGER_ERROR action table. The platform may make this field ZERO in situations where there is no need for a TRIGGER_ERROR action (for example, in cases where the **error** injection action seeds as well as consumes the error).

Note: The format of TRIGGER_ERROR Instructions Entries is the same as Injection Instruction entries as described in <u>Table 18-320</u>.

18.6.5Error Injection Operation

Before OSPM can use this mechanism to inject errors, it must discover the error injection capabilities of the platform by executing a GET_ERROR_TYPE. See <u>Table 18-322</u> for definition of error types.

After discovering the error injection capabilities, OSPM can inject and trigger an error according to the sequence described below.

Note that injecting an error into the platform does not automatically consume the error. In response to an error injection, the platform returns a trigger error action table. The software that injected the error must execute the actions in the trigger error action table in order to consume the error. If a specific error type is such that it is automatically consumed on injection, the platform will return a trigger error action table consisting of NO OP.

- 1. Executes a BEGIN_INJECTION_OPERATION action to notify the platform that an error injection operation is beginning.
- 2. Executes a GET_ERROR_TYPE action to determine the error injection capabilities of the system. This action returns a DWORD bit map of the error types supported by the platform. See <u>Table 18-322</u> for definition of error types.
- 3. If GET_ERROR_TYPE returns the DWORD with BIT31 set, it means that vendor defined error types are present, apart from the standard error types defined in Table 18-322.
- 4. OSPM chooses the type of error to inject.
 - a If the OSPM chooses to inject one of the supported standard error types, then it sets the corresponding bit in the "Error Type" field (see <u>Table 18-323</u>), by executing a

- SET_ERROR_TYPE_WITH_ADDRESS command. For example, if OSPM chooses to inject "Memory Correctable" error, then the OSPM executes SET_ERROR_TYPE_WITH_ADDRESS with an "Error Type" value of 0x0000_0080.
- Optionally, the OSPM can choose the target of the injection, such as a memory range, PCIe Segment/Device/Function or Processor APIC ID, depending on the type of error. The OSPM does this by filling in the appropriate fields of the "SET ERROR TYPE WITH ADDRESS Data structure". See Table 18-323 for details.
- b If the OSPM chooses to inject one of the vendor defined error types, then it executes SET ERROR TYPE WITH ADDRESS with BIT31 of "Error Type" field set.
- OSPM gets of the location of the "Vendor Error Type Extension Structure", by reading the "Vendor Error Type Extension Structure Offset" (see <u>Table 18-324</u>).
- OSPM reads the Vendor ID, Device ID and Rev ID from the PCI config space whose path (PCIe Segment/Device/Function) is provided in the "SBDF" field of the Vendor Error Type Extension Structure.
- If the Vendor ID/Device ID and Rev IDs match, then the OSPM can identify the platform it is running on and would know the Vendor error types that are supported by this platform
- The OSPM writes the vendor error type to inject in the "OEM Defined Structure" field. (see <u>Table 18-324</u>)
- Optionally, the OSPM can choose the target of the injection, such as a memory range, PCIe Segment/Device/Function or Processor APIC ID, depending on the type of error. The OSPM does this by filling in the appropriate fields of the "SET ERROR TYPE WITH ADDRESS Data structure". See <u>Table 18-323</u> for details
- 5. Executes an EXECUTE_OPERATION action to instruct the platform to begin the injection operation.
- 6. Busy waits by continually executing CHECK_BUSY_STATUS action until the platform indicates that the operation is complete by clearing the abstracted *Busy* bit.
- 7. Executes a GET COMMAND STATUS action to determine the status of the read operation.
- 8. If the status indicates that the platform cannot inject errors, stop.
- 9. Executes a GET_TRIGGER_ERROR_ACTION_TABLE operation to get the physical pointer to the TRIGGER_ERROR action table. This provides the flexibility in systems where injecting an error is a two (or more) step process.
- 10. Executes the actions specified in the TRIGGER ERROR action table.
- 11. Execute an END_OPERATION to notify the platform that the error injection operation is complete.

ACPI Platform Error Interfaces (APEI)

19

ACPI Source Language (ASL)Reference

This section formally defines the ACPI Source Language (ASL). ASL is a source language for defining ACPI objects including writing ACPI control methods. OEMs and BIOS developers define objects and write control methods in ASL and then use a translator tool (compiler) to generate ACPI Machine Language (AML) versions of the control methods. For a formal definition of AML, see the ACPI Machine Language (AML) Specification, Section 20, "ACPI Machine Language Specification."

AML and ASL are *different languages* though they are closely related.

Every ACPI-compatible OS must support AML. A given user can define some arbitrary source language (to replace ASL) and write a tool to translate it to AML.

An OEM or BIOS vendor needs to write ASL and be able to single-step AML for debugging. (Debuggers and similar tools are expected to be AML-level tools, not source-level tools.) An ASL translator implementer must understand how to read ASL and generate AML. An AML interpreter author must understand how to execute AML.

This section has two parts:

- The ASL grammar, which is the formal ASL specification and also serves as a quick reference.
- A full ASL reference, which includes for each ASL operator: the operator invocation syntax, the type of each argument, and a description of the action and use of the operator.

19.1 ASL Language Grammar

The purpose of this section is to state unambiguously the grammar rules used by the syntax checker of an ASL compiler.

ASL statements declare objects. Each object has three parts, two of which might not be present.

Object := ObjectType FixedList VariableList

FixedList refers to a list, of known length, that supplies data that all instances of a given **ObjectType** must have. A fixed list is written as (a, b, c, ...) where the number of arguments depends on the specific **ObjectType**, and some elements can be nested objects, that is (a, b, (q, r, s, t), d). Arguments to a **FixedList** can have default values, in which case they can be skipped. Thus, (a,c) will cause the default value for the second argument to be used. Some **ObjectTypes** can have a null **FixedList**, which is simply omitted. Trailing arguments of some object types can be left out of a fixed list, in which case the default value is used.

VariableList refers to a list, not of predetermined length, of child objects that help define the parent. It is written as { x, y, z, aa, bb, cc } where any argument can be a nested object. ObjectType determines what terms are legal elements of the VariableList. Some ObjectTypes may have a null variable list, which is simply omitted.

Other rules for writing ASL statements are the following:

- Multiple blanks are the same as one. Blank, (,), ',' and newline are all token separators.
- // marks the beginning of a comment, which continues from the // to the end of the line.
- /* marks the beginning of a comment, which continues from the /* to the next */.
- "" (quotes) surround an ASCII string.
- Numeric constants can be written in three ways: ordinary decimal, octal (using 0ddd) or hexadecimal, using the notation 0xdd.
- **Nothing** indicates an empty item. For example, { **Nothing** } is equivalent to {}.

19.1.1 ASL Grammar Notation

The notation used to express the ASL grammar is specified in the following table.

Table 19-326 ASL Grammar Notation

Notation Convention	Description	Example
Term := Term Term	The term to the left of := can be expanded into the sequence of terms on the right.	aterm := bterm cterm means that aterm can be expanded into the two-term sequence of bterm followed by cterm.
Angle brackets (< >)	Used to group items.	 <c d=""> means either a b or c d.</c>
Arrow (=>)	Indicates required run-time reduction of an ASL argument to an AML data type. Means "reduces to" or "evaluates to" at run-time.	"TermArg => Integer" means that the argument must be an ASL TermArg that must resolve to an Integer data type when it is evaluated by an AML interpreter.
Bar symbol ()	Separates alternatives.	aterm := bterm <cterm dterm=""> means the following constructs are possible: • bterm • cterm dterm aterm := <bterm cterm="" =""> dterm means the following constructs are possible: • bterm dterm • cterm dterm</bterm></cterm>
Term Term Term	Terms separated from each other by spaces form an ordered list.	N/A
Word in bold	Denotes the name of a term in the ASL grammar, representing any instance of such a term. ASL terms are not case-sensitive.	In the following ASL term definition: ThermalZone (ZoneName) {ObjectList} the item in bold is the name of the term.
Word in italics	Names of arguments to objects that are replaced for a given instance.	In the following ASL term definition: ThermalZone (ZoneName) {ObjectList} the italicized item is an argument. The item that is not bolded or italicized is defined elsewhere in the ASL grammar.

Notation Convention	Description	Example
Single quotes (' ')	Indicate constant characters.	'A'
Oxdd	Refers to a byte value expressed as two hexadecimal digits.	0x21 means a value of hexadecimal 21, or decimal 37. Notice that a value expressed in hexadecimal must start with a leading zero (0).
Dash character (-)	Indicates a range.	1-9 means a single digit in the range 1 to 9 inclusive.

19.1.2 ASL Name and Pathname Terms

```
// Name and path characters supported
LeadNameChar :=
   `A'-`Z' | `a'-`z' | `_'
DigitChar :=
   10'-19'
NameChar :=
   DigitChar | LeadNameChar
RootChar :=
ParentPrefixChar :=
PathSeparatorChar :=
CommaChar :=
SemicolonDelimiter :=
Nothing | ';'
// Names and paths
NameSeg :=
   <LeadNameChar> |
   <LeadNameChar NameChar> |
    <LeadNameChar NameChar> |
   <LeadNameChar NameChar NameChar>
NameString :=
   <RootChar NamePath> | <ParentPrefixChar PrefixPath NamePath> | NonEmptyNamePath
NamePath :=
   Nothing | <NameSeg NamePathTail>
NamePathTail :=
   Nothing | <PathSeparatorChar NameSeg NamePathTail>
NonEmptyNamePath :=
   NameSeg | <NameSeg NamePathTail>
PrefixPath :=
   Nothing | <ParentPrefixChar PrefixPath>
```

19.1.3 ASL Root and Secondary Terms

```
// Root Term
ASLCode :=
   DefinitionBlockTerm
// Major Terms
SuperName :=
   NameString | ArgTerm | LocalTerm | DebugTerm | Type6Opcode | MethodInvocationTerm
Target :=
   Nothing | SuperName
TermArg :=
   Type2Opcode | DataObject | ArgTerm | LocalTerm | NameString
MethodInvocationTerm :=
   NameString( // NameString => Method
      ArgList
    ) => Nothing | DataRefObject
// List Terms
ArgList :=
   Nothing | <TermArg ArgListTail>
ArgListTail :=
   Nothing | <CommaChar TermArg ArgListTail>
ByteList :=
   Nothing | <ByteConstExpr ByteListTail>
ByteListTail :=
   Nothing | <CommaChar ByteConstExpr ByteListTail>
DWordList :=
  Nothing | <DWordConstExpr DWordListTail>
DWordListTail :=
   Nothing | <CommaChar DWordConstExpr DWordListTail>
ExtendedAccessAttribTerm :=
   ExtendedAccessAttribKeyword (
         AccessLength //ByteConst
FieldUnitList :=
   Nothing | <FieldUnit FieldUnitListTail>
FieldUnitListTail :=
   Nothing | <CommaChar FieldUnit FieldUnitListTail>
FieldUnit :=
   FieldUnitEntry | OffsetTerm | AccessAsTerm | ConnectionTerm
FieldUnitEntry :=
   <Nothing | NameSeg> CommaChar Integer
ObjectList :=
   Nothing | <Object ObjectList>
Object :=
CompilerDirective | NamedObject | NameSpaceModifier
PackageList :=
  Nothing | <PackageElement PackageListTail>
PackageListTail :=
  Nothing | <CommaChar PackageElement PackageListTail>
PackageElement :=
   DataObject | NameString
```

```
ParameterTypePackage :=
   ObjectTypeKeyword | {Nothing | ParameterTypePackageList}
ParameterTypePackageList :=
   ObjectTypeKeyword | <ObjectTypeKeyword CommaChar ParameterTypePackageList>
ParameterTypesPackage :=
   ObjectTypeKeyword | {Nothing | ParameterTypesPackageList}
ParameterTypesPackageList :=
   ParameterTypePackage | <ParameterTypePackage CommaChar ParameterTypesPackageList>
TermList :=
   Nothing | <Term SemicolonDelimiter TermList>
Term :=
   Object | Type1Opcode | Type2Opcode
// Conditional Execution List Terms
CaseTermList :=
   Nothing | CaseTerm | DefaultTerm DefaultTermList | CaseTerm CaseTermList
DefaultTermList :=
   Nothing | CaseTerm | CaseTerm DefaultTermList
IfElseTerm :=
   IfTerm ElseTerm
```

19.1.4 ASL Data and Constant Terms

```
// Numeric Value Terms
LeadDigitChar :=
    11/-19/
HexDigitChar :=
   DigitChar | 'A'-'F' | 'a'-'f'
OctalDigitChar :=
    `0'-`7'
NullChar :=
    0 \times 0.0
// Data Terms
DataObject :=
   BufferData | PackageData | IntegerData | StringData
DataRefObject :=
   DataObject | ObjectReference | DDBHandle
ComputationalData :=
    BufferData | IntegerData | StringData
BufferData :=
    Type5Opcode | BufferTerm
IntegerData :=
   Type3Opcode | Integer | ConstTerm
PackageData :=
   PackageTerm
StringData :=
   Type40pcode | String
// Integer Terms
Integer :=
   DecimalConst | OctalConst | HexConst
DecimalConst :=
```

```
LeadDigitChar | <DecimalConst DigitChar>
OctalConst :=
   '0' | <OctalConst OctalDigitChar>
HexConst :=
   <0x HexDigitChar> | <0X HexDigitChar> | <HexConst HexDigitChar>
ByteConst :=
   Integer => 0x00-0xFF
WordConst :=
   Integer => 0x0000-0xFFFF
DWordConst :=
   Integer => 0x00000000-0xFFFFFFFF
QWordConst :=
   ByteConstExpr :=
   <Type3Opcode | ConstExprTerm | Integer> => ByteConst
WordConstExpr :=
   <Type3Opcode | ConstExprTerm | Integer> => WordConst
DWordConstExpr :=
   <Type3Opcode | ConstExprTerm | Integer> => DWordConst
QWordConstExpr :=
   <Type3Opcode | ConstExprTerm | Integer> => QWordConst
ConstTerm :=
   ConstExprTerm | Revision
ConstExprTerm :=
   Zero | One | Ones
// String Terms
String :=
   `"' Utf8CharList `"'
Utf8CharList :=
   Nothing | <EscapeSequence Utf8CharList> | <Utf8Char Utf8CharList>
Utf8Char :=
   0x01 - 0x21
   0x23 - 0x5B
   0x5D-0x7F
   0xC2-0xDF 0x80-0xBF |
   0xE0 0xA0-0xBF 0x80-0xBF |
   0xE1-0xEC 0x80-0xBF 0x80-0xBF
   0xED 0x80-0x9F 0x80-0xBF
   0xEE-0xEF 0x80-0xBF 0x80-0xBF |
   0xF0 0x90-0xBF 0x80-0xBF 0x80-0xBF
   0xF1-0xF3 0x80-0xBF 0x80-0xBF 0x80-0xBF
// Escape sequences
EscapeSequence :=
   SimpleEscapeSequence | OctalEscapeSequence | HexEscapeSequence
HexEscapeSequence :=
   \x HexDigitChar |
   \x HexDigitChar HexDigitChar
SimpleEscapeSequence :=
   \' | \" | \a | \b | \f | \n | \r | \t | \v | \\
OctalEscapeSequence :=
   \ OctalDigitChar |
```

19.1.5 ASL Opcode Terms

```
CompilerDirective :=
   IncludeTerm | ExternalTerm
NamedObject :=
   BankFieldTerm | CreateBitFieldTerm | CreateByteFieldTerm | CreateDWordFieldTerm |
   CreateFieldTerm | CreateQWordFieldTerm | CreateWordFieldTerm | DataRegionTerm |
   DeviceTerm | EventTerm | FieldTerm | FunctionTerm | IndexFieldTerm | MethodTerm |
   MutexTerm | OpRegionTerm | PowerResTerm | ProcessorTerm | ThermalZoneTerm
NameSpaceModifier :=
   AliasTerm | NameTerm | ScopeTerm
Type10pcode :=
BreakTerm | BreakPointTerm | ContinueTerm | FatalTerm | IfElseTerm | LoadTerm |
   NoOpTerm | NotifyTerm | ReleaseTerm | ResetTerm | ReturnTerm | SignalTerm |
   SleepTerm | StallTerm | SwitchTerm | UnloadTerm | WhileTerm
A Type 1 opcode term does not return a value and can only be used standalone on a line of ASL code.
Since these opcodes do not return a value they cannot be used as a term in an expression.
Type20pcode :=
   AcquireTerm | AddTerm | AndTerm | ConcatTerm | ConcatResTerm | CondRefOfTerm |
   CopyObjectTerm | DecTerm | DerefOfTerm | DivideTerm | FindSetLeftBitTerm |
   FindSetRightBitTerm | FromBCDTerm | IncTerm | IndexTerm | LAndTerm | LEqualTerm |
   LGreaterTerm | LGreaterEqualTerm | LLessTerm | LLessEqualTerm | LNotTerm |
   LNotEqualTerm | LoadTableTerm | LOrTerm | MatchTerm | MidTerm | ModTerm | MultiplyTerm |
   NAndTerm | NOrTerm | NotTerm | ObjectTypeTerm | OrTerm | RefOfTerm | ShiftLeftTerm |
   ShiftRightTerm | SizeOfTerm | StoreTerm | SubtractTerm | TimerTerm | ToBCDTerm |
   ToBufferTerm | ToDecimalStringTerm | ToHexStringTerm | ToIntegerTerm | ToStringTerm |
   WaitTerm | XorTerm | MethodInvocationTerm
A Type 2 opcode returns a value and can be used in an expression.
Type30pcode :=
   AddTerm | AndTerm | DecTerm | DerefOfTerm | DivideTerm | EISAIDTerm |
   FindSetLeftBitTerm | FindSetRightBitTerm | FromBCDTerm | IncTerm | LAndTerm |
   LEqualTerm | LGreaterTerm | LGreaterEqualTerm | LLessEqualTerm | LNotTerm |
   LNotEqualTerm | LOrTerm | MatchTerm | ModTerm | MultiplyTerm | NAndTerm | NOrTerm |
   NotTerm | OrTerm | ShiftLeftTerm | ShiftRightTerm | SubtractTerm | ToBCDTerm |
   ToIntegerTerm | XorTerm
```

The Type 3 opcodes are a subset of Type 2 opcodes that return an Integer value and can be used in an expression that evaluates to a constant. These opcodes may be evaluated at ASL compile-time. To ensure that these opcodes will evaluate to a constant, the following rules apply: The term cannot have a destination (target) operand, and must have either a Type3Opcode, Type4Opcode, Type5Opcode, ConstExprTerm, Integer, BufferTerm, Package, or String for all arguments.

The Type 4 opcodes are a subset of Type 2 opcodes that return a String value and can be used in an expression that evaluates to a constant. These opcodes may be evaluated at ASL compile-time. To ensure that these opcodes will evaluate to a constant, the following rules apply: The term cannot have a destination (target) operand, and must have either a Type3Opcode, Type4Opcode, Type5Opcode, ConstExprTerm, Integer, BufferTerm, Package, or String for all arguments.

```
Type5Opcode :=
   ConcatTerm | ConcatResTerm | DerefOfTerm | MidTerm | ResourceTemplateTerm |
   ToBufferTerm | ToUUIDTerm | UnicodeTerm
```

The Type 5 opcodes are a subset of Type 2 opcodes that return a Buffer value and can be used in an expression that evaluates to a constant. These opcodes may be evaluated at ASL compile-time. To ensure that these opcodes will evaluate to a constant, the following rules apply: The term cannot have a destination (target) operand, and must have either a Type3Opcode, Type4Opcode, Type5Opcode, ConstExprTerm, Integer, BufferTerm, Package, or String for all arguments.

```
Type60pcode :=
    RefOfTerm | DerefOfTerm | IndexTerm | MethodInvocationTerm
```

The Type 6 opcodes are a subset of Type 2 opcodes that return a Reference value and can be used in an expression. They cannot be evaluated at compile time. Type 6 also includes the UserTerm, which is a control method invocation.

19.1.6 ASL Primary (Terminal) Terms

```
AccessAsTerm :=
   AccessAs (
                        // AccessTypeKeyword
       AccessType,
       AccessAttribute // Nothing | ByteConstExpr |
                         // AccessAttribKeyword | ExtendedAccessAttribTerm
   )
AcquireTerm :=
   Acquire (
       SyncObject,
                       // SuperName => Mutex
       TimeoutValue
                        // WordConstExpr
    ) => Boolean
                        // True means the operation timed out and the Mutex was not acquired
AddTerm :=
   Add (
                      // TermArg => Integer
       Addend1,
                         // TermArg => Integer
       Addend2.
       Result
                         // Target
    ) => Integer
AliasTerm :=
   Alias (
       SourceObject, // NameString
```

```
AliasObject
                                // NameString
AndTerm :=
    And (
         Source1, // TermArg => Integer
Source2, // TermArg => Integer
         Source2,
         Result
                                 // Target
     ) => Integer
ArgTerm :=
     Arg0 | Arg1 | Arg2 | Arg3 | Arg4 | Arg5 | Arg6
BankFieldTerm :=
    BankField (
         RegionName, // NameString => OperationRegion
BankName, // NameString => FieldUnit
BankValue, // TermArg => Integer
AccessType, // AccessTypeKeyword
LockRule, // LockRuleKeyword
UpdateRule // UpdateRuleKeyword
     ) {FieldUnitList}
BreakPointTerm :=
     BreakPoint
BreakTerm :=
    Break
BufferTerm :=
    Buffer (
         BuffSize // Nothing | TermArg => Integer
     ) {StringData | ByteList} => Buffer
CaseTerm :=
    Case (
                              // DataObject
        Value
     ) {TermList}
ConcatResTerm :=
    ConcatenateResTemplate (
         Source1, // TermArg => Buffer
Source2, // TermArg => Buffer
Result // Target
> Buffer
     ) => Buffer
ConcatTerm :=
     Concatenate (
         Source1, // TermArg => ComputationalData
Source2, // TermArg => ComputationalData
Result // Target
         Source1,
     ) => ComputationalData
ConnectionTerm :=
    Connection (
         ConnectionResource // NameString | ResourceMacroTerm
CondRefOfTerm :=
    CondRefOf (
                           // SuperName
         Source,
```

```
// Target
          Destination
     ) => Boolean
ContinueTerm :=
     Continue
CopyObjectTerm :=
     CopyObject (
                                   // TermArg => DataRefObject
          Source,
                                   // NameString | LocalTerm | ArgTerm
          Result,
     ) => DataRefObject
CreateBitFieldTerm :=
     CreateBitField (
          SourceBuffer, // TermArg => Buffer
BitIndex, // TermArg => Integer
BitFieldName // NameString
CreateByteFieldTerm :=
     CreateByteField (
         SourceBuffer, // TermArg => Buffer

ByteIndex, // TermArg => Integer

ByteFieldName // NameString
         SourceBuffer,
CreateDWordFieldTerm :=
     CreateDWordField (
         SourceBuffer, // TermArg => Buffer
ByteIndex, // TermArg => Integer
DWordFieldName // NameString
     )
CreateFieldTerm :=
     CreateField (
         SourceBuffer, // TermArg => Buffer
BitIndex, // TermArg => Integer
NumBits, // TermArg => Integer
          FieldName
                                   // NameString
CreateQWordFieldTerm :=
     CreateQWordField (
          SourceBuffer, // TermArg => Buffer
ByteIndex, // TermArg => Integer
QWordFieldName // NameString
     )
CreateWordFieldTerm :=
         sourceBuffer, // TermArg => Buffer
ByteIndex, // TermArg => Integer
WordFieldName // NameString
     CreateWordField (
DataRegionTerm :=
     DataTableRegion (
          RegionName,
                                  // NameString
          SignatureString, // TermArg => String
                                  // TermArg => String
          OemIDString,
```

```
DebugTerm :=
   Debug
DecTerm :=
   Decrement (
                // SuperName
     Minuend
    => Integer
DefaultTerm :=
   Default {TermList}
DefinitionBlockTerm :=
   DefinitionBlock (
      AMLFileName, // String
TableSignature, // String
      ComplianceRevision, // ByteConst
      OEMID, // String
      TableID, // String

OEMRevision // DWordConst
   ) {TermList}
DerefOfTerm :=
   DerefOf (
                        // TermArg => ObjectReference
      Source
                         // ObjectReference is an object produced by terms such
                         // as Index, RefOf or CondRefOf.
   ) => DataRefObject
DeviceTerm :=
   Device (
                 // NameString
      DeviceName
   ) {ObjectList}
DivideTerm :=
   Divide (
   EISAIDTerm :=
   EISAID (
                  // StringData
     EisaIdString
   ) => DWordConst
ElseIfTerm :=
   ElseIf (
      Predicate
                       // TermArg => Integer
   ) {TermList} ElseTerm
   Else {TermList} | ElseIfTerm | Nothing
EventTerm :=
  Event (
```

```
// NameString
        EventName
ExternalTerm :=
   External (
        ObjName, // NameString
ObjType, // Nothing | ObjectTypeKeyword
ResultType, // Nothing | ParameterTypePackage
ParameterTypes // Nothing | ParameterTypesPackage
FatalTerm :=
   Fatal (
       Type, // ByteConstExpr
Code, // DWordConstExpr
Arg // TermArg => Integer
    )
FieldTerm :=
   Field (
    FindSetLeftBitTerm :=
    FindSetLeftBit (
                           // TermArg => Integer
        Source,
        Result
                              // Target
    ) => Integer
FindSetRightBitTerm :=
    FindSetRightBit (
                             // TermArg => Integer
        Source,
        Result
                               // Target
    ) => Integer
FromBCDTerm :=
    FromBCD (
       BCDValue, // TermArg => Integer
                              // Target
        Result
    ) => Integer
FunctionTerm :=
    Function (
       FunctionName, // NameString
ReturnType, // Nothing | ParameterTypePackage
ParameterTypes // Nothing | ParameterTypesPackage
    ) {TermList}
IfTerm :=
    If (
                    // TermArg => Integer
        Predicate
    ) {TermList}
IncludeTerm :=
   Include (
```

```
FilePathName
                           // StringData
IncTerm :=
   Increment (
       Addend
                           // SuperName
    ) => Integer
IndexFieldTerm :=
    IndexField (
       opaateRule
) {FieldUnitList}
                           // UpdateRuleKeyword
IndexTerm :=
   Index (
                           // TermArg => <String | Buffer | PackageTerm>
       Source,
       Destination
       Index,
                           // TermArg => Integer
                           // Target
    ) => ObjectReference
LAndTerm :=
   LAnd (
       Source1, // TermArg => Integer
Source2 // TermArg => Integer
    ) => Boolean
LEqualTerm :=
   LEqual (
       Source1, // TermArg => ComputationalData
Source2 // TermArg => ComputationalData
    ) => Boolean
LGreaterEqualTerm :=
   LGreaterEqual (
                           // TermArg => ComputationalData
       Source1,
       Source2
                           // TermArg => ComputationalData
    ) => Boolean
LGreaterTerm :=
   LGreater (
                        // TermArg => ComputationalData
       Source1,
       Source2
                            // TermArg => ComputationalData
    ) => Boolean
LLessEqualTerm :=
   LLessEqual (
       Source1,
                           // TermArg => ComputationalData
       Source2
                           // TermArg => ComputationalData
    ) => Boolean
LLessTerm :=
   LLess (
       Source1, // TermArg => ComputationalData
Source2 // TermArg => ComputationalData
    ) => Boolean
LNotEqualTerm :=
   LNotEqual (
```

```
Source1,
                                // TermArg => ComputationalData
         Source2
                                 // TermArg => ComputationalData
     ) => Boolean
LNotTerm :=
    LNot (
        Source,
                         // TermArg => Integer
     ) => Boolean
LoadTableTerm :=
    LoadTable (
        SignatureString, // TermArg => String
OemIDString, // TermArg => String
OemTableIDString, // TermArg => String
         RootPathString,
                                 // Nothing | TermArg => String
         ParameterPathString, // Nothing | TermArg => String
         ParameterData // Nothing | TermArg => DataRefObject
     ) => DDBHandle
LoadTerm :=
    Load (
                             // NameString
// SuperName
         Object,
         DDBHandle
    )
LocalTerm :=
    Local0 | Local1 | Local2 | Local3 | Local4 | Local5 | Local6 | Local7
LOrTerm :=
    LOr (
                               // TermArg => Integer
         Source1,
         Source2
                                // TermArg => Integer
    ) => Boolean
MatchTerm :=
    Match (
        SearchPackage, // TermArg => Package
        Op2, // MatchOpKeyword

MatchObject2, // TermArg => ComputationalData

StartIndex // TermArg
                                 // TermArg => Integer
         StartIndex
     ) => <Ones | Integer>
MethodTerm :=
    Method (
        MethodName, // NameString
NumArgs, // Nothing | ByteConstExpr
SerializeRule, // Nothing | SerializeRuleKeyword
SyncLevel, // Nothing | ByteConstExpr
ReturnType, // Nothing | ParameterTypePackage
ParameterTypes // Nothing | ParameterTypesPackage
     ) {TermList}
MidTerm :=
    Mid (
         Source,
                                // TermArg => <Buffer | String>
         Index,
                                // TermArg => Integer
         Length,
                                // TermArg => Integer
```

```
Result
                                    // Target
     ) => <Buffer | String>
ModTerm :=
    Mod (
     Dividend, // TermArg => Integer
Divisor, // TermArg => Integer
Result // Target
) => Integer // Returns Result
MultiplyTerm :=
    Multiply (
        Multiplicand, // TermArg => Integer
Multiplier, // TermArg => Integer
Result // Target
     ) => Integer
MutexTerm :=
    Mutex (
        MutexName, // NameString
SyncLevel // ByteConstExpr
     )
NameTerm :=
    Name (
        ObjectName, // NameString
Object // DataObject
NAndTerm :=
    NAnd (
       Source1, // TermArg => Integer
Source2, // TermArg => Integer
Result // Target
     ) => Integer
NoOpTerm :=
    q0oM
NOrTerm :=
    NOr (
         Source1, // TermArg => Integer
Source2, // TermArg => Integer
Result // Target
         Result
                                   // Target
     ) => Integer
NotifyTerm :=
    Notify (
                        // SuperName => <ThermalZone | Processor | Device>
         NotificationValue // TermArg => Integer
     )
NotTerm :=
    Not (
         Source, // TermArg => Integer
```

```
// Target
         Result
    ) => Integer
ObjectTypeTerm :=
    ObjectType (
                                  // NameString | ArgTerm | LocalTerm | DebugTerm |
         0bject
                                   // RefOfTerm | DerefOfTerm | IndexTerm |
     ) => Integer
OffsetTerm :=
    Offset (
        ByteOffset // IntegerData
OpRegionTerm :=
    OperationRegion (
        RegionName, // NameString
RegionSpace, // RegionSpaceKeyword
Offset, // TermArg => Integer
Length // TermArg => Integer
OrTerm :=
    Or (
        Source1, // TermArg => Integer
Source2, // TermArg => Integer
Result // Target
                                 // TermArg => Integer
     ) => Integer
PackageTerm :=
    Package (
                           // Nothing | ByteConstExpr | TermArg => Integer
         NumElements
     ) {PackageList} => Package
PowerResTerm :=
    PowerResource (
       ResourceName, // NameString
SystemLevel, // ByteConstExpr
ResourceOrder // WordConstExpr
     ) {ObjectList}
ProcessorTerm :=
    Processor (
         ProcessorName, // NameString
ProcessorID, // ByteConstExpr
PBlockAdress, // DWordConstExpr | Nothing (=0)
PblockLength // ByteConstExpr | Nothing (=0)
     ) {ObjectList}
RawDataBufferTerm :=
    RawDataBuffer (
        BuffSize
                                     // Nothing | WordConst
     ) { ByteList} => RawDataBuffer
RefOfTerm :=
    RefOf (
        Object
                                     // SuperName
     ) => ObjectReference
ReleaseTerm :=
    Release (
```

```
SyncObject
                             // SuperName
ResetTerm :=
  Reset (
      SyncObject // SuperName
ReturnTerm :=
   Return (
                    // Nothing | TermArg => DataRefObject
      Arg
ScopeTerm :=
   Location // NameString
) {ObjectList}
   Scope (
ShiftLeftTerm :=
   ShiftLeft (
       Source, // TermArg => Integer
ShiftCount, // TermArg => Integer
Result // Target
       Source,
       Result
   ) => Integer
ShiftRightTerm :=
   ShiftRight (
      Source, // TermArg => Integer
ShiftCount, // TermArg => Integer
Result // Target
      Source,
   ) => Integer
SignalTerm :=
   Signal (
      SyncObject
                             // SuperName
SizeOfTerm :=
   SizeOf (
                       // SuperName => <String | Buffer | Package>
      DataObject
   ) => Integer
SleepTerm :=
   Sleep (
      MilliSeconds // TermArg => Integer
StallTerm :=
   Stall (
      MicroSeconds // TermArg => Integer
   )
StoreTerm :=
   Store (
   Source, // TermArg => DataRefObject

Destination // SuperName
) => DataRefObject
SubtractTerm :=
   Subtract (
                    // TermArg => Integer
      Minuend,
```

```
Subtrahend,
                               // TermArg => Integer
       Result
                               // Target
    ) => Integer
SwitchTerm :=
   Switch (
   .redicate
) {CaseTermList}
                               // TermArg => ComputationalData
ThermalZoneTerm :=
   ThermalZone (
       ThermalZoneName // NameString
   ) {ObjectList}
TimerTerm :=
   Timer => Integer
ToBCDTerm :=
   ToBCD (
      Value,
Result
                            // TermArg => Integer
                               // Target
   ) => Integer
ToBufferTerm :=
   ToBuffer (
      Data,
                               // TermArg => ComputationalData
                                // Target
       Result
   ) => ComputationalData
ToDecimalStringTerm :=
   ToDecimalString (
                               // TermArg => ComputationalData
      Data,
       Result
                               // Target
   ) => String
ToHexStringTerm :=
   ToHexString (
                               // TermArg => ComputationalData
      Data.
       Result
                                // Target
   ) => String
ToIntegerTerm :=
   ToInteger (
       Data,
                               // TermArg => ComputationalData
       Result
                                // Target
    ) => Integer
ToStringTerm :=
   ToString (
                       // TermArg => Buffer
// Nothing | TermArg
// Termary
       Length,
Result
       Source,
                               // Nothing | TermArg => Integer
                                // Target
   ) => String
ToUUIDTerm :=
   ToUUID (
      String
                              // StringData
    ) => Buffer
UnicodeTerm :=
   Unicode (
```

```
String
                                  // StringData
    ) => Buffer
UnloadTerm :=
   Unload (
       DDBHandle
                                  // SuperName
WaitTerm :=
   Wait (
       SyncObject, // SuperName => Event
TimeoutValue // TermArg => Integer
> Boolean
    ) => Boolean
                                  // True means timed-out
WhileTerm :=
    While (
       Predicate
                                  // TermArg => Integer
) {TermList}
XOrTerm :=
   XOr (
       Source1,
                                // TermArg => Integer
                                // TermArg => Integer
       Source2,
       Result
                                  // Target
    ) => Integer
```

19.1.7 ASL Parameter Keyword Terms

```
AccessAttribKeyword :=
   AttribQuick | AttribSendReceive | AttribByte | AttribBytes (n) | AttribRawBytes (n) |
   AttribRawProcessBytes (n) | AttribWord | AttribBlock | AttribProcessCall |
   AttribBlockProcessCall // Note: Used for SMBus and GenericSerialBus BufferAcc only
AccessTypeKeyword :=
   AnyAcc | ByteAcc | WordAcc | DWordAcc | QWordAcc | BufferAcc
AddressKevword :=
   AddressRangeMemory | AddressRangeReserved | AddressRangeNVS | AddressRangeACPI
AddressSpaceKeyword :=
   RegionSpaceKeyword | FFixedHW | PCC
AddressingModeKeyword :=
   AddressingMode7Bit | AddressingMode10Bit
ByteLengthKeyword :=
   DataBitsFive | DataBitsSix | DataBitsSeven | DataBitsEight | DataBitsNine
BusMasterKeyword :=
   BusMaster | NotBusMaster
ClockPhaseKeyword :=
   ClockPhaseFirst | ClockPhaseSecond
ClockPolarityKeyword :=
   ClockPolarityLow | ClockPolarityHigh
DecodeKeyword :=
   SubDecode | PosDecode
EndianKeyword :=
   BigEndianing | LittleEndian
ExtendedAccessAttribKeyword :=
   AttribBytes | AttribRawBytes | AttribRawProcessBytes
    // Note: Used for GenericSerialBus BufferAcc only.
```

```
FlowControlKeyword :=
   FlowControlNone | FlowControlXon | FlowControlHardware
InterruptTypeKeyword :=
   Edge | Level
InterruptLevel :=
   ActiveHigh | ActiveLow
InterruptLevelKeyword :=
   ActiveHigh | ActiveLow | ActiveBoth
IODecodeKeyword :=
   Decode16 | Decode10
IoRestrictionKeyword :=
   IORestrictionNone | IoRestrictionInputOnly | IoRestrictionOutputOnly |
   IoRestrictionNoneAndPreserve
LockRuleKeyword :=
   Lock | NoLock
MatchOpKeyword :=
   MTR | MEQ | MLE | MLT | MGE | MGT
MaxKeyword :=
   MaxFixed | MaxNotFixed
MemTypeKeyword :=
   Cacheable | WriteCombining | Prefetchable | NonCacheable
MinKeyword :=
   MinFixed | MinNotFixed
ObjectTypeKeyword :=
   UnknownObj | IntObj | StrObj | BuffObj | PkgObj | FieldUnitObj | DeviceObj
   EventObj | MethodObj | MutexObj | OpRegionObj | PowerResObj | ProcessorObj |
   ThermalZoneObj | BuffFieldObj | DDBHandleObj
ParityKeyword :=
   ParityTypeNone | ParityTypeSpace | ParityTypeMark | ParityTypeOdd | ParityTypeEven
PinConfigKeyword :=
   PullDefault | PullUp | PullDown | PullNone
PolarityKeyword :=
   PolarityHigh | PolarityLow
RangeTypeKeyword :=
   ISAOnlyRanges | NonISAOnlyRanges | EntireRange
ReadWriteKeyword :=
   ReadWrite | ReadOnly
RegionSpaceKeyword :=
   UserDefRegionSpace | SystemIO | SystemMemory | PCI_Config | EmbeddedControl |
   SMBus | SystemCMOS | PciBarTarget | IPMI | GeneralPurposeIO | GenericSerialBus
ResourceTypeKeyword :=
   ResourceConsumer | ResourceProducer
SerializeRuleKeyword :=
   Serialized | NotSerialized
ShareTypeKeyword :=
   Shared | Exclusive | SharedAndWake | ExclusiveAndWake
SlaveModeKeyword :=
   ControllerInitiated | DeviceInitiated
StopBitsKeyword :=
   StopBitsZero | StopBitsOne | StopBitsOnePlusHalf | StopBitsTwo
TransferWidthKeyword :=
   Width8Bit | Width16Bit | Width32Bit | Width64Bit | Width128Bit | Width256Bit
TranslationKeyword :=
   SparseTranslation | DenseTranslation
TypeKeyword :=
   TypeTranslation | TypeStatic
UpdateRuleKeyword :=
   Preserve | WriteAsOnes | WriteAsZeros
UserDefRegionSpace :=
   IntegerData => 0x80 - 0xFF
XferTypeKeyword :=
```

```
Transfer8 | Transfer16 | Transfer8_16
WireModeKeyword :=
   ThreeWireMode | FourWireMode
```

19.1.8 ASL Resource Template Terms

```
ResourceTemplateTerm :=
    ResourceTemplate () {ResourceMacroList} => Buffer
ResourceMacroList :=
   Nothing | <ResourceMacroTerm ResourceMacroList>
ResourceMacroTerm :=
   DMATerm | DWordIOTerm | DWordMemoryTerm | DWordSpaceTerm | EndDependentFnTerm |
    ExtendedIOTerm | ExtendedMemoryTerm | ExtendedSpaceTerm | FixedIOTerm |
    GpioIntTerm | GpioIOTerm | I2CSerialBusTerm | InterruptTerm | IOTerm | IRQNoFlagsTerm |
    IRQTerm | Memory24Term | Memory32FixedTerm | Memory32Term | QWordIOTerm | QWordMemoryTerm |
    QWordSpaceTerm | RegisterTerm | SPISerialBusTerm | StartDependentFnTerm |
    StartDependentFnNoPriTerm | UARTSerialBusTerm | VendorLongTerm | VendorShortTerm |
    WordBusNumberTerm | WordIOTerm | WordSpaceTerm
DMATerm :=
   DMA (
       DMAType,
                                           // DMATypeKeyword (_TYP)
        BusMaster,
                                           // BusMasterKeyword (_BM)
                                          // XferTypeKeyword (_SIZ)
        XferType,
        DescriptorName
                                         // Nothing | NameString
    ) {ByteList}
                                          // List of channels (0-7 bytes)
DWordIOTerm :=
   DWordIO (
                                       // Nothing (ResourceConsumer) | ResourceTypeKeyword
        ResourceUsage,
       {\it MinType},
                                          // Nothing (MinNotFixed) | MinKeyword (_MIF)
       MaxType,
                                          // Nothing (MaxNotFixed) | MaxKeyword ( MAF)
                                          // Nothing (PosDecode) | DecodeKeyword (_DEC)
        Decode,
        RangeType,
                                          // Nothing (EntireRange) | RangeTypeKeyword (_RNG)
        AddressGranularity, // DWordConstExpr (_GRA)
        MinAddress,
                                          // DWordConstExpr (_MIN)
                                          // DWordConstExpr (_MAX)
        MaxAddress,
                                 // DWordConstExpr (_TRA)
// DWordConstExpr (_LEN)
// Nothing | ByteConstExpr
// Nothing | StringData
// Nothing | NameString
// Nothing | TypeKeyword (
        AddressTranslation,
        AddressLength,
        ResourceSourceIndex,
        ResourceSource,
        DescriptorName,
        TranslationType,
                                         // Nothing | TypeKeyword (_TTP)
        TranslationDensity
                                          // Nothing | TranslationKeyword (_TRS)
DWordMemoryTerm :=
    DWordMemory (
                                          // Nothing (ResourceConsumer) | ResourceTypeKeyword
        ResourceUsage,
                                          // Nothing (PosDecode) | DecodeKeyword (_DEC)
        Decode.
        MinType,
                                          // Nothing (MinNotFixed) | MinKeyword (_MIF)
                                          // Nothing (MaxNotFixed) | MaxKeyword (_MAF)
        MaxType,
        MemType,
                                          // Nothing (NonCacheable) | MemTypeKeyword (_MEM)
        ReadWriteType,
                                          // ReadWriteKeyword (_RW)
                                          // DWordConstExpr (_GRA)
        AddressGranularity,
                                          // DWordConstExpr (_MIN)
        MinAddress,
                                          // DWordConstExpr (_MAX)
        MaxAddress,
                                  // DWordConstExpr (_MAX)
// DWordConstExpr (_TRA)
// DWordConstExpr (_LEN)
// Nothing | ByteConstEx
        AddressTranslation,
        AddressLength,
                                          // Nothing | ByteConstExpr
        ResourceSourceIndex.
```

```
// Nothing | StringData
          ResourceSource,
          DescriptorName,
                                                     // Nothing | NameString
          MemoryRangeType,
                                                    // Nothing | AddressKeyword (_MTP)
          TranslationType
                                                    // Nothing | TypeKeyword (_TTP)
DWordSpaceTerm :=
      DWordSpace (
                                                    // ByteConstExpr (_RT), 0xC0 - 0xFF
         ResourceType,
         ResourceUsage,
                                                    // Nothing (ResourceConsumer) | ResourceTypeKeyword
                                                    // Nothing (PosDecode) | DecodeKeyword (_DEC)
         Decode,
         MinType,
                                                    // Nothing (MinNotFixed) | MinKeyword (_MIF)
         MaxType,
                                                    // Nothing (MaxNotFixed) | MaxKeyword (_MAF)
         TypeSpecificFlags,
AddressGranularity,
                                                    // ByteConstExpr (_TSF)
                                                   // DWordConstExpr (_GRA)
                                                    // DWordConstExpr (_MIN)
          MinAddress,
                                                    // DWordConstExpr (_MAX)
          MaxAddress,
                                           // DWordConstExpr (_MAX)

// DWordConstExpr (_TRA)

// DWordConstExpr (_LEN)

// Nothing | ByteConstExpr

// Nothing | StringData

// Nothing | NameString
         MaxAddress,
AddressTranslation,
AddressLength,
ResourceSourceIndex,
          ResourceSource,
          DescriptorName
                                                   // Nothing | NameString
EndDependentFnTerm :=
     EndDependentFn ()
ExtendedIOTerm :=
     ExtendedIO (
         ResourceUsage,
                                                   // Nothing (ResourceConsumer) | ResourceTypeKeyword
         MinType,
                                                    // Nothing (MinNotFixed) | MinKeyword (_MIF)
                                                    // Nothing (MaxNotFixed) | MaxKeyword (_MAF)
         MaxType,
                                                    // Nothing (PosDecode) | DecodeKeyword (_DEC)
         Decode,
                                                    // Nothing (EntireRange) | RangeTypeKeyword (_RNG)
          RangeType,
                                                    // QWordConstExpr (_GRA)
          AddressGranularity,
                                                     // QWordConstExpr (_MIN)
          MinAddress,
                                                    // QWordConstExpr (_MAX)
         MaxAddress.

      maxAdaress,
      // QWordConstExpr (_MAX)

      AddressTranslation,
      // QWordConstExpr (_TRA)

      AddressLength,
      // QWordConstExpr (_LEN)

      TypeSpecificAttributes,
      // Nothing | QWordConstExpr

      DescriptorName,
      // Nothing | NameString

          TranslationType,
                                                   // Nothing | TypeKeyword (_TTP)
          TranslationDensity
                                                    // Nothing | TranslationKeyword (_TRS)
ExtendedMemoryTerm :=
     ExtendedMemory (
                                             // Nothing (ResourceConsumer) | ResourceTypeKeyword
         ResourceUsage,
         Decode,
                                                  // Nothing (PosDecode) | DecodeKeyword (_DEC)
         MinType,
                                                  // Nothing (MinNotFixed) | MinKeyword (_MIF)
                                                   // Nothing (MaxNotFixed) | MaxKeyword (_MAF)
         MaxType,
          MemType,
                                                   // Nothing (NonCacheable) | MemTypeKeyword (_MEM)
                                                   // ReadWriteKeyword (_RW)
          ReadWriteType,
          AddressGranularity,
                                                   // QWordConstExpr (_GRA)
          MinAddress,
                                                   // QWordConstExpr (_MIN)
         AddressTranslation, // QWordConstExpr (_MAX)
AddressTranslation, // QWordConstExpr (_TRA)
AddressLength, // QWordConstExpr (_LEN)
TypeSpecificAttributes, // Nothing | QWordConstExpr
DescriptorName, // Nothing | NameString
MemoryRangeType, // Nothing | AddressKeyword
                                                  // Nothing | AddressKeyword (_MTP)
```

```
TranslationType
                                                                                                                          // Nothing | TypeKeyword (_TTP)
ExtendedSpaceTerm :=
            ExtendedSpace (
                                                                                                               // ByteConstExpr (_RT), 0xC0 - 0xFF
                        ResourceType,
                                                                                                                         // Nothing (ResourceConsumer) | ResourceTypeKeyword
// Nothing (PosDecode) | DecodeKeyword (_DEC)
                        ResourceUsage,
                       Decode,
                                                                                                                          // Nothing (MinNotFixed) | MinKeyword (_MIF)
                       MinType,
                      Minitype,

MaxType,

TypeSpecificFlags,

AddressGranularity,

// QWordConstExpr (_GRA)

// QWordConstExpr (_MIN)

// OWordConstExpr (_MAX)
                                                                                                                         // Nothing (MaxNotFixed) | MaxKeyword (_MAF)
                       MaxAddress, // QWordConstExpr (_MIN)

MaxAddress, // QWordConstExpr (_MAX)

AddressTranslation, // QWordConstExpr (_TRA)

AddressLength, // QWordConstExpr (_LEN)

TypeSpecificAttributes, // Nothing | QWordConstExpr (_ATT)

DescriptorName // Nothing | NameString
FixedDMATerm :=
           FixedDMA (
                        DMAReq,
                                                                                                                         //WordConstExpr (_DMA)
                                                                                                                          //WordConstExpr (_TYP)
                        Channel,
                        XferWidth,
                                                                                                                            //Nothing (Width32Bit) | TransferWidthKeyword (_SIZ)
                        DescriptorName,
                                                                                                                            //Nothing | NameString
FixedIOTerm :=
           FixedIO (
                                                                      // WordConstExpr (_BAS)
// ByteConstExpr (_LEN)
// Nothing | Variable | Varia
                       AddressBase,
                       RangeLength,
                       DescriptorName
                                                                                                                         // Nothing | NameString
GpioIntTerm :=
           GpioInt(
                       InterruptType, // InterruptTypeKeyword (_MOD)
InterruptLevel, // InterruptLevelKeyword (_POL)
ShareType, // Nothing (Exclusive) | ShareTypeKeyword (_SHR)
PinConfig, // PinConfigKeyword | ByteConstExpr (_PPI)
DeBounceTime // Nothing | WordConstExpr (_DBT)
                      InterruptType,
                      ) {DWordList}
GpioIOTerm :=
           GpioIO (
                                                                                    // Nothing (Exclusive) | ShareTypeKeyword (_SHR)
// PinConfigKeyword | ByteConstExpr (_PPIC)
// Nothing | WordConstExpr (_DBT)
// Nothing | WordConstExpr (_DRS)
// Nothing (None) | IORestrictionKeyword (_IOR)
                        ShareType,
                        PinConfig,
```

```
) {DWordList}
                                                                // List of GPIO pins (_PIN)
I2CSerialBusTerm :=
      I2CSerialBus (
           )
           ResourceType, // Nothing (ResourceConsumer) | ResourceTypeKeyword
InterruptType, // InterruptTypeKeyword (_LL, _HE)
InterruptLevel, // InterruptLevelKeyword (_LL, _HE)
ShareType, // Nothing (Exclusive) ShareTypeKeyword (_SHR)
ResourceSourceIndex, // Nothing | ByteConstExpr
ResourceSource, // Nothing | StringData
DescriptorName // Nothing | NameString
DWordList } // list of interrupts / INTERVALLED
InterruptTerm :=
      Interrupt (
      ) {DWordList}
IOTerm :=
                                        // IODecodeKeyword (_DEC)
// WordConstExpr (_MIN)
// WordConstExpr (_MAX)
// ByteConstExpr (_ALN)
// ByteConstExpr (_LEN)
// Nothing | NameCtries
      IO (
           TODecode.
           MinAddress,
           MaxAddress,
            Alignment,
            RangeLength,
            DescriptorName
      )
IRQNoFlagsTerm :=
      IRQNoFlags (
            DescriptorName
                                                                // Nothing | NameString
      ) {ByteList}
                                                                 // list of interrupts (0-15 bytes)
IRQTerm :=
      IRO (
            InterruptType,
InterruptLevel,
ShareType,
DescriptorName
                                                                // InterruptTypeKeyword (_LL, _HE)
                                                               // InterruptLevelKeyword (_LL, _HE)
// Nothing (Exclusive) | ShareTypeKeyword (_SHR)
// Nothing | NameString
      ) {ByteList}
                                                                 // list of interrupts (0-15 bytes)
Memory24Term :=
      Memory24 (
           ReadWriteType, // ReadWriteKeyword (_RW)
MinAddress[23:8], // WordConstExpr (_MIN)
MaxAddress[23:8], // WordConstExpr (_MAX)
Alignment, // WordConstExpr (_ALN)
RangeLength, // WordConstExpr (_LEN)
DescriptorName // Nothing | NameString
Memory32FixedTerm :=
     Memory32Fixed (
            ReadWriteType,
                                                                // ReadWriteKeyword (_RW)
```

```
AddressBase,
                                        // DWordConstExpr (_BAS)
       RangeLength,
                                        // DWordConstExpr (_LEN)
       DescriptorName
                                       // Nothing | NameString
Memory32Term :=
   Memory32 (
      ReadWriteType, // ReadWriteKeyword (_RW)
MinAddress, // DWordConstExpr (_MIN)
MaxAddress, // DWordConstExpr (_MAX)
Alignment, // DWordConstExpr (_ALN)
RangeLength, // DWordConstExpr (_LEN)
DescriptorName // Nothing | NameString
       DescriptorName
                                       // Nothing | NameString
    )
QWordIOTerm :=
      QWordIO (
QWordMemoryTerm :=
       QWordMemory (
                                       // Nothing (ResourceConsumer) | ResourceTypeKeyword
QWordSpaceTerm :=
    OWordSpace (
       ResourceType,
                                       // ByteConstExpr (_RT), 0xC0 - 0xFF
       ResourceUsage,
                                       // Nothing (ResourceConsumer) | ResourceTypeKeyword
                                        // Nothing (PosDecode) | DecodeKeyword (_DEC)
       Decode,
                                        // Nothing (MinNotFixed) | MinKeyword (_MIF)
       MinType,
       MaxType,
                                        // Nothing (MaxNotFixed) | MaxKeyword (_MAF)
```

```
TypeSpecificFlags,
                                               // ByteConstExpr (_TSF)
         AddressGranularity,
        AddressGranularity,
MinAddress, // QWordConstExpr (_Min,
MaxAddress, // QWordConstExpr (_MAX)
AddressTranslation, // QWordConstExpr (_TRA)
AddressLength, // QWordConstExpr (_TRA)
ResourceSourceIndex, // Nothing | ByteConstExpr
ResourceSource, // Nothing | StringData
DescriptorName // Nothing | NameString
                                               // QWordConstExpr (_GRA)
RawDataBufferTerm :=
    RawDataBuffer (
       (BuffSize)
                                          // Nothing | Integer
) {ByteList} => ByteList
RegisterTerm :=
     Register (
                                          // AddressSpaceKeyword (_ASI)
        AddressSpaceID,
        RegisterBitWidth, // ByteConstExpr (_RBW)
RegisterOffset, // ByteConstExpr (_RBO)
RegisterAddress, // QWordConstExpr (_ADR)
         AccessSize,
                                          // ByteConstExpr (_ASZ)
         Accesssize, // Byteconstexpr (_ASZ)

DescriptorName // Nothing | NameString
SPISerialBusTerm :=
    SPISerialBus (
        DeviceSelection, // WordConstExpr (_ADR)
DeviceSelectionPolarity, // Nothing (PolarityLow) | DevicePolarityKeyword (_DPL)
         WireMode,
                                          // Nothing (FourWireMode) | WireModeKeyword (_MOD)
         DataBitLength,
                                          // ByteConstExpr (_LEN)
         SlaveMode,
                                          // Nothing (ControllerInitiated) | SlaveModeKeyword (_SLV)
         ConnectionSpeed, // DWordConstExpr (_SPE)
ClockPolarity, // ClockPolarityKeyword (_POL)
ClockPhase, // ClockPhaseKeyword (_PHA)
        VendorData
                                          // Nothing | RawDataBuffer (_VEN)
     )
StartDependentFnNoPriTerm :=
    StartDependentFnNoPri () {ResourceMacroList}
StartDependentFnTerm :=
    StartDependentFn (
         CompatPriority,
                                          // ByteConstExpr (0-2)
         PerfRobustPriority
                                          // ByteConstExpr (0-2)
     ) {ResourceMacroList}
UARTSerialBusTerm :=
    UARTSerialBus(
         Initial BaudRate,
                                        // DwordConstExpr (_SPE)
                                            // Nothing (DataBitsEight) | DataBitsKeyword (_LEN)
         BitsPerByte,
                                           // Nothing (StopBitsOne) | StopBitsKeyword (_STB)
         StopBits,
                                          // ByteConstExpr (_LIN)
         LinesInUse,
         IsBigEndian,
                                          // Nothing (LittleEndian) | EndianessKeyword (_END)
         Parity,
                                          // Nothing (ParityTypeNone) | ParityTypeKeyword (_PAR)
         FlowControl,
                                          // Nothing (FlowControlNone) | FlowControlKeyword (_FLC)
```

```
// WordConstExpr (_RXL)
        ReceiveBufferSize,
       VendorLongTerm :=
   VendorLong (
       DescriptorName // Nothing | NameString
    ) {ByteList}
VendorShortTerm :=
    VendorShort (
                                      // Nothing | NameString
       DescriptorName
    ) {ByteList}
                                      // Up to 7 bytes
WordBusNumberTerm :=
    WordBusNumber (
                                    // Nothing (ResourceConsumer) | ResourceTypeKeyword
       ResourceUsage,
       // Nothing (MinNotFixed) | MinKeyword (_MIF)
       MinType,
      WordIOTerm :=
    WordIO (
                            // Nothing (ResourceConsumer) | ResourceTypeKeyword
       ResourceUsage,
       MinType,
                                     // Nothing (MinNotFixed) | MinKeyword (_MIF)
       MaxType,
                                    // Nothing (MaxNotFixed) | MaxKeyword (_MAF)
                                 Decode,
       MinAddress,
       MinAddress, // WordConstExpr (_MIN)
MaxAddress, // WordConstExpr (_MAX)
AddressTranslation, // WordConstExpr (_TRA)
AddressLength, // WordConstExpr (_LEN)
ResourceSourceIndex, // Nothing | ByteConstExpr
ResourceSource, // Nothing | StringData
DescriptorName, // Nothing | NameString
TranslationType, // Nothing | TypeKeyword (_TTP)
TranslationDensity // Nothing | TranslationKeyword (_TRS)
WordSpaceTerm :=
    WordSpace (
       ResourceType,
                                    // ByteConstExpr (_RT), 0xC0 - 0xFF
                                // Nothing (ResourceConsumer) | ResourceTypeKe
// Nothing (PosDecode) | DecodeKeyword (_DEC
// Nothing (MinNotFixed) | MinKeyword (_MIF)
// Nothing (MaxNotFixed) | MaxKeyword (_MAF)
        ResourceUsage,
                                    // Nothing (ResourceConsumer) | ResourceTypeKeyword
                                   // Nothing (PosDecode) | DecodeKeyword (_DEC)
       Decode,
        MinType,
        MaxType,
                                    // Nothing (MaxNotFixed) | MaxKeyword (_MAF)
```

```
TypeSpecificFlags, // ByteConstExpr (_TSF)
AddressGranularity, // WordConstExpr (_GRA)
MinAddress, // WordConstExpr (_MIN)
MaxAddress, // WordConstExpr (_MAX)
AddressTranslation, // WordConstExpr (_TRA)
AddressLength, // WordConstExpr (_LEN)
ResourceSourceIndex, // Nothing | ByteConstExpr
ResourceSource, // Nothing | StringData
DescriptorName // Nothing | NameString
```

19.2 ASL Concepts

This reference section is for developers who are writing ASL code while developing definition blocks for platforms.

19.2.1 ASL Names

This section describes how to encode object names using ASL.

The following table lists the characters legal in any position in an ASL object name. ASL names are not case-sensitive and will be converted to upper case.

Table 19-327 Named Object Reference Encodings

Value	Description	Title
0x41-0x5A, 0x5F, 0x61-0x7A	Lead character of name ('A'-'Z', '_', 'a'-'z')	LeadNameChar
0x30-0x39, 0x41-0x5A, 0x5F, 0x61- 0x7A	Non-lead (trailing) character of name ('A'-'Z', '_', 'a'-'z', '0'-'9')	NameChar

The following table lists the name modifiers that can be prefixed to an ASL name.

Table 19-328 Definition Block Name Modifier Encodings

Value	Description	NamePrefix :=	Followed by
0x5C	Namespace root ('\')	RootPrefix	Name
0x5E	Parent namespace ('^')	ParentPrefix	ParentPrefix or Name

19.2.1.1 T x Reserved Object Names

The ACPI specification reserves object names with the prefix _T_ for internal use by the ASL compiler. The ASL compiler may, for example, use these objects to store temporary values when implementing translation of complicated control structures into AML. The ASL compiler must declare _T_x objects normally (using Name) and must not define them more than once within the same scope.

19.2.2 ASL Literal Constants

This section describes how to encode integer and string constants using ASL.

19.2.2.1 Integers

Numeric constants can be specified in decimal, octal, or hexadecimal. Octal constants are preceded by a leading zero (0), and hexadecimal constants are preceded by a leading zero and either a lower or upper case 'x'. In some cases, the grammar specifies that the number must evaluate to an integer within a limited range, such as 0x00-0xFF, and so on.

19.2.2.2 Strings

```
String
              := \"' Utf8CharList \"'
             := Nothing | <EscapeSequence Utf8CharList> | <Utf8Char Utf8CharList>
Utf8CharList
Utf8Char
              = 0x01-0x21
              0x23 - 0x5B
               0x5D-0x7F
               0xC2-0xDF 0x80-0xBF
               0xE0 0xA0-0xBF 0x80-0xBF
               0xE1-0xEC 0x80-0xBF 0x80-0xBF |
               0xED 0x80-0x9F 0x80-0xBF |
               0xEE-0xEF 0x80-0xBF 0x80-0xBF |
               0xF0 0x90-0xBF 0x80-0xBF 0x80-0xBF
               0xF1-0xF3 0x80-0xBF 0x80-0xBF 0x80-0xBF |
              0xF4 0x80-0x8F 0x80-0xBF 0x80-0xBF
               := SimpleEscapeSeq | OctalEscapeSeq | HexEscapeSeq
EscapeSeq
:= \ OctalDigitChar |
OctalEscapeSeq
          \ OctalDigitChar OctalDigitChar |
          \ OctalDigitChar OctalDigitChar OctalDigitChar
HexEscapeSeg
              := \x HexDigitChar |
          \x HexDigitChar HexDigitChar
NullChar
              = 0x00
```

String literals consist of zero or more ASCII characters surrounded by double quotation marks ("). A string literal represents a sequence of characters that, taken together, form a null-terminated string. After all adjacent strings in the constant have been concatenated, a null character is appended.

Strings in the source file may be encoded using the UTF-8 encoding scheme as defined in the Unicode 4.0 specification. UTF-8 is a byte-oriented encoding scheme, where some characters take a single byte and others take multiple bytes. The ASCII character values 0x01-0x7F take up exactly one byte.

However, only one operator currently supports UTF-8 strings: Unicode. Since string literals are defined to contain only non-null character values, both Hex and Octal escape sequence values must be non-null values in the ASCII range 0x01 through 0xFF. For arbitrary byte data (outside the range of ASCII values), the **Buffer** object should be used instead.

ACPI Source Language (ASL)Reference

Since the backslash is used as the escape character and also the namespace root prefix, any string literals that are to contain a fully qualified namepath from the root of the namespace must use the double backslash to indicate this:

```
Name (_EJD, "\\_SB.PCI0.DOCK1")
```

The double backslash is only required within quoted string literals.

Since double quotation marks are used close a string, a special escape sequence (\") is used to allow quotation marks within strings. Other escape sequences are listed in the table below:

Table 19-329 ASL Escape Sequences

Escape Sequence	ASCII Character
\a	0x07 (BEL)
\psi	0x08 (BS)
\f	0x0C (FF)
\n	0x0A (LF)
\r	0x0D (CR)
\t	0x09 (TAB)
\v	0x0B (VT)
\"	0x22 (")
\\'	0x27 (')
	0x5C (\)

Since literal strings are read-only constants, the following ASL statement (for example) is not supported:

```
Store ("ABC", "DEF")
```

However, the following sequence of statements is supported:

```
Name (STR, "DEF")
...
Store ("ABC", STR)
```

19.2.3 ASL Resource Templates

ASL includes some macros for creating resource descriptors. The ResourceTemplate macro creates a Buffer in which resource descriptor macros can be listed. The ResourceTemplate macro automatically generates an End descriptor and calculates the checksum for the resource template. The format for the ResourceTemplate macro is as follows:

```
ResourceTemplate ()
    {
            // List of resource macros
}
```

The following is an example of how these macros can be used to create a resource template that can be returned from a PRS control method:

```
Name (PRS0, ResourceTemplate ()
{
    StartDependentFn (1, 1)
    {
        IRQ (Level, ActiveLow, Shared) {10, 11}
        DMA (TypeF, NotBusMaster, Transfer16) {4}
        IO (Decode16, 0x1000, 0x2000, 0, 0x100)
        IO (Decode16, 0x5000, 0x6000, 0, 0x100, IO1)
    }
    StartDependentFn (1, 1)
    {
        IRQ (Level, ActiveLow, Shared) {}
        DMA (TypeF, NotBusMaster, Transfer16){5}
        IO (Decode16, 0x3000, 0x4000, 0, 0x100)
        IO (Decode16, 0x5000, 0x6000, 0, 0x100, IO2)
    }
    EndDependentFn ()
}
```

Occasionally, it is necessary to change a parameter of a descriptor in an existing resource template at run-time (i.e., during a method execution.) To facilitate this, the descriptor macros optionally include a name declaration that can be used later to refer to the descriptor. When a name is declared with a descriptor, the ASL compiler will automatically create field names under the given name to refer to individual fields in the descriptor.

The offset returned by a reference to a resource descriptor field name is either in units of bytes (for 8-, 16-, 32-, and 64-bit field widths) or in bits (for all other field widths). In all cases, the returned offset is the integer offset (in either bytes or bits) of the name from the first byte (offset 0) of the parent resource template.

For example, given the above resource template, the following code changes the minimum and maximum addresses for the I/O descriptor named IO2:

```
CreateWordField (PRS0, IO2._MIN, IMIN)
Store (0xA000, IMIN)
CreateWordField (PRS0, IO2._MAX, IMAX)
Store (0xB000, IMAX)
```

The resource template macros for each of the resource descriptors are listed below, after the table that defines the resource descriptor. The resource template macros are formally defined in Section 6.4.1, "ASL Macros for Resource Descriptors."

The reserved names (such as _MIN and _MAX) for the fields of each resource descriptor are defined in the appropriate table entry of the table that defines that resource descriptor.

19.2.4 ASL Macros

The ASL compiler supports some built in macros to assist in various ASL coding operations. The following table lists some of the supported directives and an explanation of their function.

Table 19-330 Example ASL Built-in Macros

ASL Statement	Description
EISAID (TextID)	Converts the 7-character text argument into its corresponding 4-byte numeric EISA ID encoding. This can be used when declaring IDs for devices that are EISA IDs.
ResourceTemplate ()	Used to supply Plug and Play resource descriptor information in human readable form, which is then translated into the appropriate binary Plug and Play resource descriptor encodings. For more information about resource descriptor encodings, see Section 6.4 , "Resource Data Types for ACPI."
ToUUID (AsciiString)	Converts an ASCII string to a 128-bit buffer.
Unicode (StringData)	Converts an ASCII string to a Unicode string contained in a buffer.

19.2.5 ASL Data Types

ASL provides a wide variety of data types and operators that manipulate data. It also provides mechanisms for both explicit and implicit conversion between the data types when used with ASL operators.

The table below describes each of the available data types.

Table 19-331 Summary of ASL Data Types

ASL Data Type	Description
[Uninitialized]	No assigned type or value. This is the type of all control method LocalX variables and unused ArgX variables at the beginning of method execution, as well as all uninitialized Package elements. Uninitialized objects must be initialized (via Store or CopyObject) before they may be used as source operands in ASL expressions.
Buffer	An array of bytes. Uninitialized elements are zero by default.
Buffer Field	Portion of a buffer created using CreateBitField, CreateByteField, CreateWordField, CreateQWordField, CreateField, or returned by the Index operator.
DDB Handle	Definition block handle returned by the Load operator
Debug Object	Debug output object. Formats an object and prints it to the system debug port. Has no effect if debugging is not active.
Device	Device or bus object
Event	Event synchronization object
Field Unit (within an Operation Region)	Portion of an address space, bit-aligned and of one-bit granularity. Created using Field, BankField, or IndexField.
Integer	An <i>n</i> -bit little-endian unsigned integer. In ACPI 1.0 this was 32 bits. In ACPI 2.0 and later, this is 64 bits. The Integer (DWORD) designation indicates that only the lower 32 bits have meaning and the upper 32 bits of 64-bit integers must be zero (masking of upper bits is not required).

ASL Data Type	Description	
Integer Constant	Created by the ASL terms "Zero", "One", "Ones", and "Revision".	
Method	Control Method (Executable AML function)	
Mutex	Mutex synchronization object	
Object Reference	Reference to an object created using the RefOf, Index, or CondRefOf operators	
Operation Region	Operation Region (A region within an Address Space)	
Package	Collection of ASL objects with a fixed number of elements (up to 255).	
Power Resource	Power Resource description object	
Processor	Processor description object	
RawDataBuffer	An array of bytes. Uninitialized elements are zero by default. RawDataBuffer does not contain any AML encoding bytes, only the raw bytes.	
String	Null-terminated ASCII string.	
Thermal Zone	Thermal Zone description object	

Note: (Compatibility Note) The ability to store and manipulate object references was first introduced in ACPI 2.0. In ACPI 1.0 references could not be stored in variables, passed as parameters or returned from functions.

19.2.5.1 Data Type Conversion Overview

ASL provides two mechanisms to convert objects from one data type to another data type at run-time (during execution of the AML interpreter). The first mechanism, *Explicit Data Type Conversion*, allows the use of explicit ASL operators to convert an object to a different data type. The second mechanism, *Implicit Data Type Conversion*, is invoked by the AML interpreter when it is necessary to convert a data object to an expected data type before it is used or stored.

The following general rules apply to data type conversions:

- Input parameters are always subject to implicit data type conversion (also known as implicit source operand conversion) whenever the operand type does not match the expected input type.
- Output (target) parameters for all operators except the explicit data conversion operators are subject to implicit data type conversion (also known as implicit result object conversion) whenever the target is an existing named object or named field that is of a different type than the object to be stored.
- Output parameters for the explicit data conversion operators, as well as output parameters that
 refer to a method local or argument (LocalX or ArgX) are not subject to implicit type
 conversion.

Both of these mechanisms (explicit and implicit conversion) are described in detail in the sections that follow.

19.2.5.2 Explicit Data Type Conversions

The following ASL operators are provided to *explicitly* convert an object from one data type to another:

ACPI Source Language (ASL)Reference

EISAID

Converts a 7-character text argument into its corresponding 4-byte numeric EISA ID encoding.

FromBCD

Convert an Integer to a BCD Integer

ToBCD

Convert a BCD Integer to a standard binary Integer.

ToBuffer

Convert an Integer, String, or Buffer to an object of type Buffer

ToDecimalString

Convert an Integer, String, or Buffer to an object of type String. The string contains the ASCII representation of the decimal value of the source operand.

ToHexString

Convert an Integer, String, or Buffer to an object of type String. The string contains the ASCII representation of the hexadecimal value of the source operand.

ToInteger

Convert an Integer, String, or Buffer to an object of type Integer.

ToString

Copy directly and convert a Buffer to an object of type String.

ToUUID

Convert an ASCII string to a UUID Buffer.

The following ASL operators are provided to copy and transfer objects:

CopyObject

Explicitly store a copy of the operand object to the target name. No implicit type conversion is performed. (This operator is used to avoid the implicit conversion inherent in the ASL Store operator.)

Store

Store a copy of the operand object to the target name. Implicit conversion is performed if the target name is of a fixed data type (see below). However, Stores to method locals and arguments do not perform implicit conversion and are therefore the same as using CopyObject.

19.2.5.3 Implicit Data Type Conversions

Automatic or *Implicit* type conversions can take place at two different times during the execution of an ASL operator. First, it may be necessary to convert one or more of the source operands to the data type(s) expected by the ASL operator. Second, the result of the operation may require conversion before it is stored into the destination. (Many of the ASL operators can store their result optionally

into an object specified by the last parameter. In these operators, if the destination is specified, the action is exactly as if a Store operator had been used to place the result in the destination.)

Such data conversions are performed by an AML interpreter during execution of AML code and are known collectively as *Implicit Operand Conversions*. As described briefly above, there are two different types of implicit operand conversion:

- Conversion of a source operand from a mismatched data type to the correct data type required by an ASL operator, called *Implicit Source Conversion*. This conversion occurs when a source operand must be converted to the operand type expected by the operator. Any or all of the source operands may be converted in this manner before the execution of the ASL operator can proceed.
- 2. Conversion of the result of an operation to the existing type of a target operand before it is stored into the target operand, called *Implicit Result Conversion*. This conversion occurs when the target is a fixed type such as a named object or a field. When storing to a method Local or Arg, no conversion is required because these data types are of variable type (the store simply overwrites any existing object and the existing type).

19.2.5.4 Implicit Source Operand Conversion

During the execution of an ASL operator, each source operand is processed by the AML interpreter as follows:

- If the operand is of the type expected by the operator, no conversion is necessary.
- If the operand type is incorrect, attempt to convert it to the proper type.
- For the Concatenate operator and logical operators (LEqual, LGreater, LGreaterEqual, LLess, LLessEqual, and LNotEqual), the data type of the first operand dictates the required type of the second operand, and for Concatenate only, the type of the result object. (The second operator is implicitly converted, if necessary, to match the type of the first operand.)
- If conversion is impossible, abort the running control method and issue a fatal error.

An implicit source conversion will be attempted anytime a source operand contains a data type that is different that the type expected by the operator. For example:

```
Store ("5678", Local1)
Add (0x1234, Local1, BUF1)
```

In the Add statement above, *Local1* contains a String object and must undergo conversion to an Integer object before the Add operation can proceed.

In some cases, the operator may take more than one type of operand (such as Integer and String). In this case, depending on the type of the operand, the highest priority conversion is applied. The table below describes the source operand conversions available. For example:

```
Store (Buffer (1) {}, Local0)
Name (ABCD, Buffer (10) {1, 2, 3, 4, 5, 6, 7, 8, 9, 0})
CreateDWordField (ABCD, 2, XYZ)
Name (MNOP, "1234")
Concatenate (XYZ, MNOP, Local0)
```

The Concatenate operator can take an Integer, Buffer or String for its first two parameters and the type of the first parameter determines how the second parameter will be converted. In this example, the first parameter is of type Buffer Field (from the CreateDWordField operator). What should it be

ACPI Source Language (ASL)Reference

converted to: Integer, Buffer or String? According to <u>Table 19-333</u>, the highest priority conversion is to Integer. Therefore, both of the following objects will be converted to Integers:

```
XYZ (0x05040302)
MNOP (0x31, 0x32, 0x33, 0x34)
```

And will then be joined together and the resulting type and value will be:

```
Buffer (0x02, 0x03, 0x04, 0x05, 0x31, 0x32, 0x33, 0x34)
```

19.2.5.5 Implicit Result Object Conversion

For all ASL operators that generate and store a result value (including the Store operator), the result object is processed and stored by the AML interpreter as follows:

- If the ASL operator is one of the *explicit* conversion operators (ToString, ToInteger, etc., and the CopyObject operator), no conversion is performed. (In other words, the result object is stored directly to the target and completely overwrites any existing object already stored at the target.)
- If the target is a method local or argument (LocalX or ArgX), no conversion is performed and the result is stored directly to the target.
- If the target is a fixed type such as a named object or field object, an attempt is made to convert the source to the existing target type before storing.
- If conversion is impossible, abort the running control method and issue a fatal error.

An implicit result conversion can occur anytime the result of an operator is stored into an object that is of a fixed type. For example:

```
Name (BUF1, Buffer (10))
Add (0x1234, 0x789A, BUF1)
```

Since BUF1 is a named object of fixed type *Buffer*, the Integer result of the Add operation must be converted to a Buffer before it is stored into BUF1.

19.2.5.6 Data Types and Type Conversions

The following table lists the available ASL data types and the available data type conversions (if any) for each. The entry for each data type is fully cross-referenced, showing both the types to which the object may be converted as well as all other types that may be converted to the data type.

The allowable conversions apply to both explicit and implicit conversions.

Table 19-332 Data Types and Type Conversions			
ASL Data Type	Can be implicitly or explicitly converted <u>to</u> these Data Types: (In priority order) Can be implicitly or explicitly converted <u>from</u> these Data Types		
[Uninitialized]	None. Causes a fatal error when used as a source operand in any ASL statement.	Integer, String, Buffer, Package, DDB Handle, Object Reference	
Buffer	Integer, String, Debug Object	g, Debug Object Integer, String	
Buffer Field	Integer, Buffer, String, Debug Object	Integer, Buffer, String	
DDB Handle	Integer, Debug Object	Integer	

Debug Object	None. Causes a fatal error when used as a source operand in any ASL statement.	Integer, String, Buffer, Package, Field Unit, Buffer Field, DDB Handle	
Device	None	None	
Event	None	None	
Field Unit (within an Operation Region)	Integer, Buffer, String, Debug Object	Integer, Buffer, String	
Integer	Buffer, Buffer Field, DDB Handle, Field Unit, String, Debug Object	Buffer, String	
Integer Constant	Integer, Debug Object	None. Also, storing any object to a constant is a no-op, not an error.	
Method	None	None	
Mutex	None	None	
Object Reference	None	None	
Operation Region	None	None	
Package	Debug Object	None	
String	Integer, Buffer, Debug Object	Integer, Buffer	
Power Resource	None	None	
Processor	None	None	
RawDataBuffer	None	None	
Thermal Zone	None	None	

19.2.5.7 Data Type Conversion Rules

The following table presents the detailed data conversion rules for each of the allowable data type conversions. These conversion rules are implemented by the AML Interpreter and apply to all conversion types — explicit conversions, implicit source conversions, and implicit result conversions.

ACPI Source Language (ASL)Reference

Table 19-333 Object Conversion Rules

To convert from an object of this Data Type	To an object of this Data	This action is performed by the AML Interpreter:
Buffer	Buffer Field	The contents of the buffer are copied to the Buffer Field. If the buffer is smaller than the size of the buffer field, it is zero extended. If the buffer is larger than the size of the buffer field, the upper bits are truncated. Compatibility Note: This conversion was first introduced in ACPI 2.0. The behavior in ACPI 1.0 was undefined.
	Debug Object	Each buffer byte is displayed as a hexadecimal integer, delimited by spaces and/or commas.
	Field Unit	The entire contents of the buffer are copied to the Field Unit. If the buffer is larger (in bits) than the size of the Field Unit, it is broken into pieces and completely written to the Field Unit, lower chunks first. If the buffer (or the last piece of the buffer, if broken up) is smaller than the size of the Field Unit, it is zero extended before being written.
	Integer	If no integer object exists, a new integer is created. The contents of the buffer are copied to the Integer, starting with the least-significant bit and continuing until the buffer has been completely copied — up to the maximum number of bits in an Integer. The size of an Integer is indicated by the Definition Block table header's Revision field. A Revision field value less than 2 indicates that the size of an Integer is 32 bits. A value greater than or equal to 2 signifies that the size of an Integer is 64 bits. If the buffer is smaller than the size of an integer, it is zero extended. If the buffer is larger than the size of an integer, it is truncated. Conversion of a zero-length buffer to an integer is not allowed.
	String	If no string object exists, a new string is created. If the string already exists, it is completely overwritten and truncated or extended to accommodate the converted buffer exactly. The entire contents of the buffer are converted to a string of two-character hexadecimal numbers, each separated by a space. A zero-length buffer will be converted to a null (zero-length) string.
Buffer Field	[See the Integer and Buffer Rules]	If the Buffer Field is smaller than or equal to the size of an Integer (in bits), it will be treated as an Integer. Otherwise, it will be treated as a Buffer. The size of an Integer is indicated by the Definition Block table header's Revision field. A Revision field value less than 2 indicates that the size of an Integer is 32 bits. A value greater than or equal to 2 signifies that the size of an Integer is 64 bits. (See the conversion rules for the Integer and Buffer data types.)
DDB Handle	[See the Integer Rule]	The object is treated as an Integer (See conversion rules for the Integer data type.)
Field Unit	[See the Integer and Buffer Rules]	If the Field Unit is smaller than or equal to the size of an Integer (in bits), it will be treated as an Integer. If the Field Unit is larger than the size of an Integer, it will be treated as a Buffer. The size of an Integer is indicated by the Definition Block table header's Revision field. A Revision field value less than 2 indicates that the size of an Integer is 32 bits. A value greater than or equal to 2 signifies that the size of an Integer is 64 bits. (See the conversion rules for the Integer and Buffer data types.)

To convert from an object of this Data Type	To an object of this Data Type	This action is performed by the AML Interpreter:
Integer	Buffer	If no buffer object exists, a new buffer object is created based on the size of the integer (4 bytes for 32-bit integers and 8 bytes for 64-bit integers). If a buffer object already exists, the Integer overwrites the entire Buffer object. If the integer requires more bits than the size of the Buffer, then the integer is truncated before being copied to the Buffer. If the integer contains fewer bits than the size of the buffer, the Integer is zero-extended to fill the entire buffer.
	Buffer Field	The Integer overwrites the entire Buffer Field. If the integer is smaller than the size of the buffer field, it is zero-extended. If the integer is larger than the size of the buffer field, the upper bits are truncated. Compatibility Note: This conversion was first introduced in ACPI 2.0. The behavior in ACPI 1.0 was undefined.
	Debug Object	The integer is displayed as a hexadecimal value.
	Field Unit	The Integer overwrites the entire Field Unit. If the integer is smaller than the size of the buffer field, it is zero-extended. If the integer is larger than the size of the buffer field, the upper bits are truncated.
	String	If no string object exists, a new string object is created based on the size of the integer (8 characters for 32-bit integers and 16 characters for 64-bit integers). If the string already exists, it is completely overwritten and truncated or extended to accommodate the converted integer exactly. In either case, the entire integer is converted to a string of hexadecimal ASCII characters.
Package	Package	If no package object exists, a new package object is created. If the package already exists, it is completely overwritten and truncated or extended to accommodate the source package exactly. Any and all existing valid (non-null) package elements of the target package are deleted, and the entire contents of the source package are copied into the target package.
	Debug Object	Each element of the package is displayed based on its type.

To convert from an object of this Data Type	To an object of this Data	This action is performed by the AML Interpreter:
String	Buffer	If no buffer object exists, a new buffer object is created. If a buffer object already exists, it is completely overwritten. If the string is longer than the buffer, the string is truncated before copying. If the string is shorter than the buffer, the remaining buffer bytes are set to zero. In either case, the string is treated as a buffer, with each ASCII string character copied to one buffer byte, including the null terminator. A null (zero-length) string will be converted to a zero-length buffer.
	Buffer Field	The string is treated as a buffer. If this buffer is smaller than the size of the buffer field, it is zero extended. If the buffer is larger than the size of the buffer field, the upper bits are truncated. Compatibility Note: This conversion was first introduced in ACPI 2.0. The behavior in ACPI 1.0 was undefined.
	Debug Object	Each string character is displayed as an ASCII character.
	Field Unit	Each character of the string is written, starting with the first, to the Field Unit. If the Field Unit is less than eight bits, then the upper bits of each character are lost. If the Field Unit is greater than eight bits, then the additional bits are zeroed.
	Integer	If no integer object exists, a new integer is created. The integer is initialized to the value zero and the ASCII string is interpreted as a hexadecimal constant. Each string character is interpreted as a hexadecimal value ('0'-'9', 'A'-'F', 'a'-'f'), starting with the first character as the most significant digit, and ending with the first non-hexadecimal character, end-of-string, or when the size of an integer is reached (8 characters for 32-bit integers and 16 characters for 64-bit integers). Note: the first non-hex character terminates the conversion without error, and a "0x" prefix is not allowed. Conversion of a null (zero-length) string to an integer is not allowed.

19.2.5.8 Rules for Storing and Copying Objects

The table below lists the actions performed when storing objects to different types of named targets. ASL provides the following types of "store" operations:

- The Store operator is used to explicitly store an object to a location, with implicit conversion support of the source object.
- Many of the ASL operators can store their result optionally into an object specified by the last parameter. In these operators, if the destination is specified, the action is exactly as if a Store operator had been used to place the result in the destination.
- The CopyObject operator is used to explicitly store a copy of an object to a location, with no implicit conversion support.

Table 19-334 Object Storing and Copying Rules

When Storing an object of any data type to this type of Target location	This action is performed by the Store operator or any ASL operator with a Target operand:	This action is performed by the CopyObject operator:	
Method ArgX variable	The object is copied to the destination with no conversion applied, with one exception. If the ArgX contains an Object Reference, an automatic de-reference occurs and the object is copied to the target of the Object Reference instead of overwriting the contents of ArgX		
Method LocalX variable	The object is copied to the destination with no conversion applied. Even if LocalX contains an Object Reference, it is overwritten.		
Field Unit or Buffer Field	he object is copied to the destination fter implicit result conversion is applied cannot be changed. Therefore, CopyObject can only be used to copy an object of type Integer or Buffer to fields.		
Named data object	The object is copied to the destination after implicit result conversion is applied to match the existing type of the named location	The object and type are copied to the named location.	

19.2.5.9 Rules for Reading and Writing Objects

In the descriptions below, read operations always return the actual object, not a copy of the object in order that constructs of the form:

```
Add (Local1, Local2, Local3)
```

do not create unnecessary copies of Local1 or Local2. Also, this behavior enables the call-by-reference semantics of control method invocation.

19.2.5.9.1 ArgX Objects

- 1. Read from ArgX parameters
 - **ObjectReference** Automatic dereference, return the target of the reference. Use of DeRefOf returns the same.
 - **Buffer** Return the Buffer. Can create an Index, Field, or Reference to the buffer.
 - Package Return the Package. Can create an Index or Reference to the package.
 - **All other object types** Return the object.

Example method invocation for the table below:

```
MTHD (RefOf (Obj), Buf, Pkg, Obj)
```

Table 19-335 Reading from ArgX Objects

Parameter	MTHD ArgX Type	Read operation on ArgX	Result of read
RefOf (Obj),	Reference to object Obj	Store (Arg0,)	Obj
		CopyObject (Arg0,)	Obj
		DeRefOf (Arg0)	Obj

ACPI Source Language (ASL)Reference

Parameter	MTHD ArgX Type	Read operation on ArgX	Result of read
Buf,	Buffer	Store (Arg1,) CopyObject (Arg1,) Index (Arg1,) Field (Arg1,)	Buf Buf Index (<i>Buf</i>) Field (<i>Buf</i>)
Pkg	Package	Store (Arg2,) CopyObject (Arg2,) Index (Arg2,)	Pkg Pkg Index (<i>Pkg</i>)
Obj	All other object types	Store (Arg3,) CopyObject (Arg3,)	Obj Obj

2. Store to ArgX parameters

- **ObjectReference** objects Automatic dereference, copy the object and overwrite the final target.
- All other object types- Copy the object and overwrite the ArgX variable. (Direct writes to buffer or package ArgX parameters will also simply overwrite ArgX)

Table 19-336 Writing to ArgX Objects

Current type of ArgX	Object to be written	Write operation on ArgX	Result of write (in ArgX)
RefOf (OldObj)	Obj (Any type)	Store (, ArgX) CopyObject (, ArgX)	RefOf (copy of Obj) RefOf (copy of Obj)
All other object types	Obj (Any type)	Store (, ArgX) CopyObject (, ArgX)	Copy of <i>Obj</i> Copy of <i>Obj</i>

Note: RefOf (ArgX) returns a reference to ArgX.

19.2.5.9.2 LocalX Objects

- 1. Read from LocalX variables
 - **ObjectReference** If performing a DeRefOf return the target of the reference. Otherwise, return the reference.
 - All other object types Return a the object

Table 19-337 Reading from LocalX Objects

Current LocalX Type	Read operation on LocalX	Result of read
RefOf (Obj)	Store (LocalX,)	RefOf (Obj)
	CopyObject (LocalX,)	RefOf (Obj)
	DeRefOf (LocalX)	Obj
Obj (All other types)	Store (LocalX,)	Obj
	CopyObject (LocalX,)	Obj

2. Store to LocalX variables

• All object types - Delete any existing object in LocalX first, then store a copy of the object.

Table 19-338 Writing to LocalX Objects

Current LocalX Type	Object to be written	Write operation on LocalX	Result of write (in LocalX)
All object types	Obj (Any type)	Store (, LocalX) CopyObject (, LocalX)	Copy of <i>Obj</i> Copy of <i>Obj</i>

19.2.5.9.3 Named Objects

- 1. Read from Named object
 - **ObjectReference** If performing a DeRefOf return the target of the reference. Otherwise, return the reference.
 - All other object types Return the object

Table 19-339 Reading from Named Objects

Current NAME Type	Read operation on NAME	Result of read
RefOf (Obj)	Store (NAME,)	RefOf (Obj)
	CopyObject (NAME,)	RefOf (Obj)
	DeRefOf (NAME)	Obj
Obj (All other types)	Store (NAME,)	Obj
	CopyObject (NAME,)	Obj

2. Store to Named object

• **All object types** - Delete any existing object in NAME first, then store a copy of the object. The Store operator will perform an implicit conversion to the existing type in NAME. CopyObject does not perform an implicit store.

Table 19-340 Writing to Named Objects

Current NAME Type	Object to be written	Write operation on NAME	Result of write (in NAME)
Any (Any Type)	Obj (Any type)	Store (, NAME) CopyObject (, NAME)	Copy of <i>Obj</i> (converted to match existing type of NAME) Copy of <i>Obj</i> (No conversion)

19.3 ASL Operator Summary

Operator Name	Location	Description
AccessAs	page 740	Change Field Access
Acquire	page 741	Acquire a mutex
Add	page 741	Integer Add
Alias	page 741	Define a name alias
And	page 742	Integer Bitwise And
ArgX	page 742	Method argument data objects
BankField	page 742	Declare fields in a banked configuration object
Break	page 744	Continue following the innermost enclosing While
BreakPoint	page 744	Used for debugging, stops execution in the debugger
Buffer	page 744	Declare Buffer object
Case	page 745	Expression for conditional execution
Concatenate	page 745	Concatenate two strings, integers or buffers
ConcatenateResTemplate	page 746	Concatenate two resource templates
CondRefOf	page 746	Conditional reference to an object
Connection	page 746	Declare Field Connection Attributes
Continue	page 747	Continue innermost enclosing While loop
CopyObject	page 747	Copy and existing object
CreateBitField	page 748	Declare a bit field object of a buffer object
CreateByteField	page 748	Declare a byte field object of a buffer object
CreateDWordField	page 748	Declare a DWord field object of a buffer object
CreateField	page 749	Declare an arbitrary length bit field of a buffer object
CreateQWordField	page 749	Declare a QWord field object of a buffer object
CreateWordField	page 749	Declare a Word field object of a buffer object
DataTableRegion	page 749	Declare a Data Table Region
Debug	page 750	Debugger output
Decrement	page 750	Decrement an Integer
Default	page 751	Default execution path in Switch()
DefinitionBlock	page 751	Declare a Definition Block
DerefOf	page 752	Dereference an object reference
Device	page 752	Declare a bus/device object
Divide	page 753	Integer Divide
DMA	page 754	DMA Resource Descriptor macro
DWordIO	page 754	DWord IO Resource Descriptor macro
DWordMemory	page 756	DWord Memory Resource Descriptor macro
DWordSpace	page 758	DWord Space Resource Descriptor macro
Eisald	page 759	EISA ID String to Integer conversion macro
Else	page 760	Alternate conditional execution
Elself	page 760	Conditional execution

Operator Name	Location	Description
EndDependentFn	page 761	End Dependent Function
Event	page 762	Resource Descriptor macro
ExtendedIO	page 762	Declare an event synchronization object
ExtendedMemory	page 764	Extended IO Resource Descriptor macro
ExtendedSpace	page 765	Extended Space Resource Descriptor macro
External	page 767	Declare external objects
Fatal	page 768	Fatal error check
Field	page 768	Declare fields of an operation region object
FindSetLeftBit	page 771	Index of first least significant bit set
FindSetRightBit	page 771	Index of first most significant bit set
FixedDMA	page 774	Fixed DMA Resource Descriptor macro
FixedIO	page 772	Fixed I/O Resource Descriptor macro
FromBCD	page 772	Convert from BCD to numeric
Function	page 772	Declare control method
GpioInt	page 774	GPIO Interrupt Connection Resource Descriptor macro
Gpiolo	page 775	GPIO I0 Connection Resource Descriptor macro
I2CSerialBus	page 776	I2C Serialbus Connection Resource Descriptor macro
If	page 777	Conditional execution
Include	page 777	Include another ASL file
Increment	page 778	Increment a Integer
Index	page 780	Indexed Reference to member object
IndexField	page 781	Declare Index/Data Fields
Interrupt	page 781	Interrupt Resource Descriptor macro
10	page 783	IO Resource Descriptor macro
IRQ	page 784	Interrupt Resource Descriptor macro
IRQNoFlags	page 784	Short Interrupt Resource Descriptor macro
LAnd	page 784	Logical And
LEqual	page 785	Logical Equal
LGreater	page 785	Logical Greater
LGreaterEqual	page 785	Logical Not less
LLess	page 786	Logical Less
LLessEqual	page 786	Logical Not greater
LNot	page 786	Logical Not
LNotEqual	page 786	Logical Not equal
Load	page 787	Load differentiating definition block
LoadTable	page 787	Load Table from RSDT/XSDT
LocalX	page 788	Method local data objects
LOr	page 789	Logical Or
Match	1	I .

ACPI Source Language (ASL)Reference

Operator Name	Location	Description
Memory24	page 790	Memory Resource Descriptor macro
Memory32	page 791	Memory Resource Descriptor macro
Memory32Fixed	page 792	Memory Resource Descriptor macro
Method	page 792	Declare a control method
Mid	page 794	Return a portion of buffer or string
Mod	page 794	Integer Modulo
Multiply	page 795	Integer Multiply
Mutex	page 795	Declare a mutex synchronization object
Name	page 796	Declare a Named object
NAnd	page 796	Integer Bitwise Nand
NoOp	page 796	No operation
NOr	page 797	Integer Bitwise Nor
Not	page 797	Integer Bitwise Not
Notify	page 797	Notify Object of event
ObjectType	page 798	Type of object
Offset	page 797	Set Field Offset within operation range
One	page 799	Constant One Object (1)
Ones	page 799	Constant Ones Object (-1)
OperationRegion	page 799	Declare an operational region
Or	page 801	Integer Bitwise Or
Package	page 801	Declare a package object
PowerResource	page 802	Declare a power resource object
Processor	page 803	Declare a processor package
QWordIO	page 803	QWord IO Resource Descriptor macro
QWordMemory	page 805	QWord Memory Resource Descriptor macro
QWordSpace	page 807	Qword Space Resource Descriptor macro
RawDataBuffer	page 809	Declare a RawDataBuffer
RefOf	page 809	Create Reference to an object
Register	page 809	Generic register Resource Descriptor macro
Release	page 810	Release a synchronization object
Reset	page 811	Reset a synchronization object
ResourceTemplate	page 811	Resource to buffer conversion macro
Return	page 811	Return from method execution
Revision	page 810	Constant revision object
Scope	page 812	Open named scope
ShiftLeft	page 813	Integer shift value left
ShiftRight	page 813	Integer shift value right
Signal	page 814	Signal a synchronization object
SizeOf	page 814	Get the size of a buffer, string, or package

Operator Name	Location	Description
Sleep	page 814	Sleep n milliseconds (yields the processor)
SPISerialbus	page 815	SPI Serialbus Connection Resource
Stall	page 816	Delay n microseconds (does not yield the processor)
StartDependentFn	page 816	Start Dependent Function Resource Descriptor macro
StartDependentFnNoPri	page 817	Start Dependent Function Resource Descriptor macro
Store	page 817	Store object Integer
Subtract	page 818	Subtract
Switch	page 818	Select code to execute based on expression value
ThermalZone	page 820	Declare a thermal zone package.
Timer	page 820	Get 64-bit timer value
ToBCD	page 821	Convert Integer to BCD
ToBuffer	page 821	Convert data type to buffer
ToDecimalString	page 822	Convert data type to decimal string
ToHexString	page 822	Convert data type to hexadecimal string
Tolnteger	page 821	Convert data type to integer
ToString	page 823	Copy ASCII string from buffer
ToUUID	page 823	Convert Ascii string to UUID
Unicode	page 825	String to Unicode conversion macro
Unload	page 826	Unload definition block
UARTSerialBus	page 824	UART SerialBus Connection Resource Descriptor macro
VendorLong	page 826	Vendor Resource Descriptor
VendorShort	page 826	Vendor Resource Descriptor
Wait	page 827	Wait on an Event
While	page 827	Conditional loop
WordBusNumber	page 828	Word Bus number Resource Descriptor macro
WordIO	page 829	Word IO Resource Descriptor macro
WordSpace	page 831	Word Space Resource Descriptor macro
Xor	page 832	Integer Bitwise Xor
Zero	page 832	Constant Zero object 0

19.4 ASL Operator Summary By Type

// ASL compiler controls		
External	page 767	Declare external objects
Include	page 777	Include another ASL file
// ACPI table management		
DefinitionBlock	page 751	Declare a Definition Block
Load	page 787	Load definition block
LoadTable	page 788	Load Table from RSDT/XSDT
Unload	page 826	Unload definition block
// Miscellaneous named ob	ject creation	1
Alias	page 742	Define a name alias
Buffer	page 744	Declare Buffer object
Device	page 752	Declare a bus/device object
Function	page 772	Declare a control method
Method	page 792	Declare a control method
Name	page 796	Declare a Named object
Package	page 801	Declare a package object
PowerResource	page 802	Declare a power resource object
Processor	page 803	Declare a processor package
RawDataBuffer	page 809	Declare a RawDataBuffer
Scope	page 812	Open named scope
ThermalZone	page 820	Declare a thermal zone package.
// Operation Regions and F	ields	
AccessAs	page 740	Change Field Access
BankField	page 743	Declare fields in a banked configuration object
Connection	page 746	Declare Field Connection Attributes
DataTableRegion	page 749	Declare a Data Table Region
Field	page 768	Declare fields of an operation region object
IndexField	page 780	Declare Index/Data Fields
Offset	page 797	Set Field offset within operation region
OperationRegion	page 799	Declare an operational region
// Buffer Fields		
CreateBitField	page 748	Declare a bit field object of a buffer object
CreateByteField	page 748	Declare a byte field object of a buffer object
CreateDWordField	page 748	Declare a DWord field object of a buffer object
CreateField	page 749	Declare an arbitrary length bit field of a buffer object
CreateQWordField	page 749	Declare a QWord field object of a buffer object
CreateWordField	page 749	Declare a Word field object of a buffer object
// Synchronization		

Acquire page 741 Acquire a mutex	
Event page 762 Declare an event synchronization objection	
Mutex page 795 Declare a mutex synchronization obje	ect
Notify page 797 Notify Object of event	
Release page 810 Release a synchronization object	
Reset page 811 Reset a synchronization object	
Signal page 814 Signal a synchronization object	
Wait page 827 Wait on an Event	
// Object references	
CondRefOf page 746 Conditional reference to an object	
DerefOf page 752 Dereference an object reference	
RefOf page 809 Create Reference to an ob ect	
// Integer arithmetic	
Add page 741 Integer Add	
And page 741 Integer Add And page 742 Integer Bitwise And	
11 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	
13 11 13	
FindSetRightBit page 771 Index of first most significant bit set	
Increment page 778 Increment a Integer	
Mod page 794 Integer Modulo	
Multiply page 795 Integer Multiply	
NAnd page 796 Integer Bitwise Nand NOr page 797 Integer Bitwise Nor	
Not page 797 Integer Bitwise Not	
Or page 801 Integer Bitwise Or	
ShiftLeft page 813 Integer shift value left	
ShiftRight page 813 Integer shift value right I	
Subtract page 818 Integer Subtract	
Xor page 832 Integer Bitwise Xor	
// Logical operators	
LAnd page 784 Logical And	
LEqual page 785 Logical Equal	
LGreater page 785 Logical Greater	
LGreaterEqual page 785 Logical Not less	
LLess page 786 Logical Less	
LLessEqual page 786 Logical Not greater	
LNot page 786 Logical Not	
LNotEqual page 786 Logical Not equal	
LOr page 789 Logical Or	
// Method execution control	

ACPI Source Language (ASL)Reference

Break	page 744	Continue following the innermost enclosingWhile
BreakPoint	page 744	Used for debugging, stops execution in the debugger
Case	page 745	Expression for conditional execution
Continue	page 747	Continue innermost enclosing While loop
Default	page 751	Default execution path in Switch()
Else	page 760	Alternate conditional execution
Elself	page 760	Conditional execution
Fatal	page 768	Fatal error check
lf .	page 777	Conditional execution
NoOp	page 796	No operation
Return	page 811	Return from method execution
Sleep	page 814	Sleep n milliseconds (yields the processor)
Stall	page 816	Delay in microseconds (does not yield the processor)
Switch	page 818	Select code to execute based on expression value
While	page 827	Conditional loop
// Data type conversion an	d manipulat	ion
Concatenate	page 745	Concatenate two strings,integers or buffers
CopyObject	page 747	Copy and existing object
Debug	page 750	Debugger output
Eisald	page 759	EISA ID String to Integer conversion macro
FromBCD	page 772	Convert from BCD to numeric
Index	page 780	Indexed Reference to member object
Match	page 789	Search for match in package array
Mid	page 794	Return a portion of buffer or string
ObjectType	page 798	Type of object
SizeOf	page 814	Get the size of a buffer, string, or package
Store	page 817	Store object
Timer	page 820	Get 64-bit timer value
ToBCD	page 821	Convert Integer to BCD
ToBuffer	page 821	Convert data type to buffer
ToDecimalString	page 822	Convert data type to decimal string
ToHexString	page 822	Convert data type to hexadecimal string
ToInteger	page 821	Convert data type to integer
ToString	page 823	Copy ASCII string from buffer
ToUUID	page 823	Convert Ascii strin to UUID
Unicode	page 825	String to Unicode conversion macro
// Resource Descriptor ma	cros	

ConcatenateResTemplate	page 746	Concatenate two resource templates		
DMA	page 740 page 754	Concatenate two resource templates DMA Resource Descriptor macro		
DWordIO	page 754	DWord IO Resource Descriptor macro		
DWordMemory	page 754 page 756	DWord Memory Resource Descriptor macro		
DWordSpace		DWord Space Resource Descriptor macro		
EndDependentFn	page 758	End Dependent Function Resource Descriptor macro Extended I/O		
ExtendedIO	page 761			
	page 762	Resource Descriptor macro		
ExtendedMemory	page 764	Extended Memory Resource Descriptor macro		
ExtendedSpace FixedDMA	page 765	Extended Space Resource Descriptor macro		
	page 774	Fixed DMA resource Descriptor macro		
FixedIO	page 772	Fixed I/O Resource Descriptor macro		
GpioInt	page 774	GPIO Interrupt Connection Resource Descriptor macro		
GpiolO	page 775	GPIO IO Connection Resource Descriptor macro		
I2CSerialBus	page 776	I2CSerialBus Connection Resource Descriptor macro		
Interrupt	page 781	Interrupt Resource Descriptor macro		
10	page 783	IO Resource Descriptor macro		
IRQ	page 784	Interrupt Resource Descriptor macro		
IRQNoFlags	page 784	Short Interrupt Resource Descriptor macro		
Memory24	page 790	Memory Resource Descriptor macro		
Memory32	page 791	Memory Resource Descriptor macro		
Memory32Fixed	page 792	Memory Resource Descriptor macro		
QWordIO	page 803	QWord IO Resource Descriptor macro		
QWordMemory	page 805	QWord Memory Resource Descriptor macro		
QWordSpace	page 807	Qword Space Resource Descriptor macro		
Register	page 809	Generic register Resource Descriptor macro		
ResourceTemplate	page 811	Resource to buffer conversion macro		
SPISerialBus	page 815	SPI SerialBus Connection Resource Descriptor macro		
StartDependentFn	page 816	Start Dependent Function Resource Descriptor macro		
StartDependentFnNoPri	page 817	Start Dependent Function Resource Descriptor macro		
UARTSerialBus	page 824	UART SerialBus Connection Resource Descriptor macro		
VendorLong	page 826	Vendor Resource Descriptor		
VendorShort	page 826	Vendor Resource Descriptor		
WordBusNumber	page 828	Word Bus number Resource Descriptor macro		
WordIO	page 829	Word IO Resource Descriptor macro		
WordSpace	page 831	Word Space Resource Descriptor macro		
// Constants				
One	page 799	Constant One Object (1)		
Ones	page 799	Constant Ones Object (-1)		
Revision	page 810	Constant revision object		
Zero	page 832	Constant Zero object (0)		
// Control method objects				
ArgX	page 742	Method argument data objects		
LocalX	page 788	Method local data ob ects		
	. •			

19.5 ASL Operator Reference

This section describes each of the ASL operators. The syntax for each operator is given, with a description of each argument and an overall description of the operator behavior. Example ASL code is provided for the more complex operators.

ASL operators can be categorized as follows:

- Named Object creation
- Method execution control (If, Else, While, etc.)
- Integer math
- Logical operators
- Resource Descriptor macros
- Object conversion
- Utility/Miscellaneous

19.5.1 AccessAs (Change Field Unit Access)

Syntax

AccessAs (AccessType, AccessAttribute)
AccessAs (AccessType, AccessAttribute (AccessLength))

Arguments

AccessType is an AccessTypeKeyword that specifies the type of access desired (ByteAcc, WordAcc, etc.). AccessAttribute is an optional argument of type AccessAttributeKeyword that specifies additional protocols to be used, such as AttribQuick, AttribSendReceive, etc. AccessLength is a required argument for some of the Access Attributes.

Description

The **AccessAs** operator is used within a *FieldList* to specify the Access Type, Access Attributes, and Access Length for the remaining *FieldUnits* within the list (or until another **AccessAs** operator is encountered.) It allows FieldUnits to have different access types within a single Field definition.

Supported *AccessTypes*:

- AnyAcc
- ByteAcc
- WordAcc
- DwordAcc
- QWordAcc
- BufferAcc

Supported simple *AccessAttributes* (with SMBus synonyms):

- AttribQuick (SMBQuick)
- AttribSendReceive (SMBSendReceive)

- AttribByte (*SMBByte*)
- AttribWord (*SMBWord*)
- AttribBlock (SMBBlock)
- AttribProcessCall (SMBProcessCall)
- AttribBlockProcessCall (SMBBlockProcessCall)

Access Attributes that require an AccessLength argument:

- AttribBytes (*AccessLength*)
- AttribRawBytes (*AccessLength*)
- AttribRawProcessBytes (*AccessLength*)

19.5.2 Acquire (Acquire a Mutex)

Syntax

Acquire (*SyncObject*, *TimeoutValue*) => Boolean

Arguments

SynchObject must be a mutex synchronization object. *TimeoutValue* is evaluated as an Integer.

Description

Ownership of the Mutex is obtained. If the Mutex is already owned by a different invocation, the current execution thread is suspended until the owner of the Mutex releases it or until at least *TimeoutValue* milliseconds have elapsed. A Mutex can be acquired more than once by the same invocation.

Note: For Mutex objects referenced by a _DLM object, the host OS may also contend for ownership.

This operation returns **True** if a timeout occurred and the mutex ownership was not acquired. A *TimeoutValue* of 0xFFFF (or greater) indicates that there is no timeout and the operation will wait indefinitely.

19.5.3 Add (Integer Add)

Syntax

Add (*Addend1*, *Addend2*, *Result*) => Integer

Arguments

Addend1 and Addend2 are evaluated as Integers.

Description

The operands are added and the result is optionally stored into *Result*. Overflow conditions are ignored and the result of overflows simply loses the most significant bits.

19.5.4 Alias (Declare Name Alias)

Syntax

Alias (SourceObject, AliasObject)

Arguments

SourceObject is any named object. AliasObject is a NameString.

Description

Creates a new object named AliasObject that refers to and acts exactly the same as SourceObject.

AliasObject is created as an alias of SourceObject in the namespace. The SourceObject name must already exist in the namespace. If the alias is to a name within the same definition block, the SourceObject name must be logically ahead of this definition in the block.

Example

The following example shows the use of an **Alias** term:

Alias (\SUS.SET.EVEN, SSE)

19.5.5 And (Integer Bitwise And)

Syntax

And (Source1, Source2, Result) => Integer

Arguments

Source1 and Source2 are evaluated as Integers.

Description

A bitwise AND is performed and the result is optionally stored into *Result*.

19.5.6 Argx (Method Argument Data Objects)

Syntax

Arg0 | Arg1 | Arg2 | Arg3 | Arg4 | Arg5 | Arg6

Description

Up to 7 argument-object references can be passed to a control method. On entry to a control method, only the argument objects that are passed are usable.

19.5.7 BankField (Declare Bank/Data Field)

Syntax

BankField (*RegionName*, *BankName*, *BankValue*, *AccessType*, *LockRule*, *UpdateRule*) {FieldUnitList}

Arguments

RegionName is the name of the host Operation Region. *BankName* is the name of the bank selection register.

Accessing the contents of a banked field data object will occur automatically through the proper bank setting, with synchronization occurring on the operation region that contains the *BankName* data variable, and on the Global Lock if specified by the *LockRule*.

The AccessType, LockRule, UpdateRule, and FieldUnitList are the same format as the **Field** operator.

Description

This operator creates data field objects. The contents of the created objects are obtained by a reference to a bank selection register.

This encoding is used to define named data field objects whose data values are fields within a larger object selected by a bank-selected register.

Example

The following is a block of ASL sample code using *BankField*:

- Creates a 4-bit bank-selected register in system I/O space.
- Creates overlapping fields in the same system I/O space that are selected via the bank register.

```
// Create BLVL & BAC in bank 1 at the same offset
BankField (GIO0, BNK1, 1, ByteAcc, NoLock, Preserve) {
   Offset (0x30),
   BLVL, 7,
   BAC, 1
}
```

19.5.8 Break (Break from While)

Syntax

Break

Description

Break causes execution to continue immediately following the innermost enclosing **While** or **Switch** scope, in the current Method. If there is no enclosing **While** or **Switch** within the current Method, a fatal error is generated.

Compatibility Note: In ACPI 1.0, the Break operator continued immediately following the innermost "code package." Starting in ACPI 2.0, the Break operator was changed to exit the innermost "While" or "Switch" package. This should have no impact on existing code, since the ACPI 1.0 definition was, in practice, useless.

19.5.9 BreakPoint (Execution Break Point)

Syntax

BreakPoint

Description

Used for debugging, the **Breakpoint** opcode stops the execution and enters the AML debugger. In the non-debug version of the AML interpreter, **BreakPoint** is equivalent to **Noop**.

19.5.10 Buffer (Declare Buffer Object)

Syntax

Buffer (*BufferSize*) {*String* or *ByteList*} => Buffer

Arguments

Declares a Buffer of size BufferSize and optional initial value of String or ByteList.

Description

The optional *BufferSize* parameter specifies the size of the buffer and the initial value is specified in *Initializer* ByteList. If *BufferSize* is not specified, it defaults to the size of initializer. If the count is too small to hold the value specified by initializer, the initializer size is used. For example, all four of the following examples generate the same data in namespace, although they have different ASL encodings:

```
Buffer (10) {"P00.00A"}
Buffer (Arg0) {0x50, 0x30, 0x30, 0x2e, 0x30, 0x30, 0x41}
Buffer (10) {0x50, 0x30, 0x30, 0x2e, 0x30, 0x30, 0x41, 0x00, 0x00, 0x00}
Buffer () {0x50, 0x30, 0x30, 0x2e, 0x30, 0x30, 0x41, 0x00, 0x00, 0x00}
```

19.5.11 Case (Expression for Conditional Execution)

Syntax

Case (Value) {TermList}

Arguments

Value specifies an Integer, Buffer, String or Package object. *TermList* is a sequence of executable ASL expressions.

Description

Execute code based upon the value of a **Switch** statement.

If the **Case** *Value* is an Integer, Buffer or String, then control passes to the statement that matches the value of the enclosing **Switch** (*Value*). If the **Case** value is a Package, then control passes if any member of the package matches the **Switch** (*Value*). The **Switch** *CaseTermList* can include any number of **Case** instances, but no two **Case** *Value*s (or members of a *Value*, if *Value* is a Package) within the same **Switch** statement can contain the same value.

Execution of the statement body begins at the start of the *TermList* and proceeds until the end of the TermList body or until a **Break** or **Continue** operator transfers control out of the body.

19.5.12 Concatenate (Concatenate Data)

Syntax

Concatenate (*Source1*, *Source2*, *Result*) => ComputationalData

Arguments

Source1 and Source2 must each evaluate to an integer, a string, or a buffer. The data type of Source1 dictates the required type of Source2 and the type of the result object. Source2 is implicitly converted if necessary to match the type of Source1.

Description

Source2 is concatenated to Source1 and the result data is optionally stored into Result.

Table 19-341 Concatenate Data Types

Source1 Data Type	Source2 Data Type (→ Converted Type)	Result Data Type
Integer	Integer/String/Buffer → Integer	Buffer
String	Integer/String/Buffer → String	String
Buffer	Integer/String/Buffer → Buffer	Buffer

19.5.13 ConcatenateResTemplate (Concatenate Resource Templates)

Syntax

ConcatenateResTemplate (*Source1*, *Source2*, *Result*) => Buffer

Arguments

Source1 and Source2 are evaluated as Resource Template buffers.

Description

The resource descriptors from *Source2* are appended to the resource descriptors from *Source1*. Then a new end tag and checksum are appended and the result is stored in *Result*, if specified. If either *Source1* or *Source2* is exactly 1 byte in length, a run-time error occurs. An empty buffer is treated as a resource template with only an end tag.

19.5.14 CondRefOf (Create Object Reference Conditionally)

Syntax

CondRefOf (Source, Result) => Boolean

Arguments

Attempts to create a reference to the *Source* object. The *Source* of this operation can be any object type (for example, data package, device object, and so on), and the result data is optionally stored into *Result*.

Description

On success, the *Destination* object is set to refer to *Source* and the execution result of this operation is the value **True**. On failure, *Destination* is unchanged and the execution result of this operation is the value **False**. This can be used to reference items in the namespace that may appear dynamically (for example, from a dynamically loaded definition block).

CondRefOf is equivalent to **RefOf** except that if the *Source* object does not exist, it is fatal for **RefOf** but not for **CondRefOf**

19.5.15 Connection (Declare Field Connection Attributes)

Syntax

Connection (ConnectionResourceObj)

Arguments

ConnectionResourceObj is a GPIO or Serial Bus Connection Descriptor depending on the Operation Region type, or a named object containing the Descriptor

See <u>Section 6.4.3.8.2</u>, "Connection Resource Descriptors" and <u>Section 19.5.46</u> "Field (Declare Field Objects)" for more information.

Examples

```
OperationRegion(TOP1, GenericSerialBus, 0x00, 0x100)// GenericSerialBus device at command value
Name (I2C, ResourceTemplate(){
    I2CSerialBus(0x5a,,100000,, "\_SB.I2C",,,,RawDataBuffer(){1,6})
Field(TOP1, BufferAcc, NoLock, Preserve)
                                                        // Specify connection resource information
    Connection(I2C)
    AccessAs(BufferAcc, AttribWord)
                                                        // Use the GenericSerialBus
                                                        // Read/Write Word protocol
    FLD0, 8,
                                                        // Virtual register at command value 0.
    FLD1, 8,
                                                         // Virtual register at command value 1.
Field(TOP1, BufferAcc, NoLock, Preserve)
    \texttt{Connection}(\texttt{I2CSerialBus}(\texttt{0x5b},\texttt{,100000},\texttt{,"} \setminus \texttt{SB.I2C"},\texttt{,,,,RawDataBuffer}() \{3,9\}))
    AccessAs(BufferAcc, AttribBytes (16))
    FLD2, 8
                                                        // Virtual register at command value 0.
// Create the GenericSerialBus data buffer
                                                       // Create GenericSerialBus data buffer as BUFF
Name(BUFF, Buffer(34){})
                                                     // Create GenericSerial
// STAT = Status (Byte)
CreateByteField(BUFF, 0x00, STAT)
CreateWordField(BUFF, 0x02, DATA)
                                                       // DATA = Data (Word)
```

Description

The Connection macro declares the connection attributes for subsequent fields defined within the Field declaration.

19.5.16 Continue (Continue Innermost Enclosing While)

Syntax

Continue

Description

Continue causes execution to continue at the start of the innermost enclosing **While** scope, in the currently executing Control Method, at the point where the condition is evaluated. If there is no enclosing **While** within the current Method, a fatal error is generated.

19.5.17 CopyObject (Copy and Store Object)

Syntax

CopyObject (Source, Destination) => DataRefObject

Arguments

Converts the contents of the *Source* to a DataRefObject using the conversion rules in 18.2.5 and then copies the results without conversion to the object referred to by *Destination*.

Description

If Destination is already an initialized object of type DataRefObject, the original contents of Destination are discarded and replaced with Source. Otherwise, a fatal error is generated.

Note: (Compatibility Note) The CopyObject operator was first introduced new in ACPI 2.0.

19.5.18 CreateBitField (Create 1-Bit Buffer Field)

Syntax

CreateBitField (SourceBuffer, BitIndex, BitFieldName)

Arguments

SourceBuffer is evaluated as a buffer. BitIndex is evaluated as an integer. BitFieldName is a NameString.

Description

A new buffer field object named *BitFieldName* is created for the bit of *SourceBuffer* at the bit index of *BitIndex*. The bit-defined field within *SourceBuffer* must exist. *BitFieldName* is created for the bit of *SourceBuffer* at the bit index of *BitIndex*. The bit-defined field within *SourceBuffer* must exist.

19.5.19 CreateByteField (Create 8-Bit Buffer Field)

Syntax

CreateByteField (SourceBuffer, ByteIndex, ByteFieldName)

Arguments

SourceBuffer is evaluated as a buffer. ByteIndex is evaluated as an integer. ByteFieldName is a NameString.

Description

A new buffer field object named *ByteFieldName* is created for the byte of *SourceBuffer* at the byte index of *ByteIndex*. The byte-defined field within *SourceBuffer* must exist.

19.5.20 CreateDWordField (Create 32-Bit Buffer Field)

Syntax

CreateDWordField (SourceBuffer, ByteIndex, DWordFieldName)

Arguments

SourceBuffer is evaluated as a buffer. ByteIndex is evaluated as an integer. DWordFieldName is a NameString.

Description

A new buffer field object named *DWordFieldName* is created for the DWord of *SourceBuffer* at the byte index of *ByteIndex*. The DWord-defined field within *SourceBuffer* must exist.

19.5.21 CreateField (Create Arbitrary Length Buffer Field)

Syntax

CreateField (SourceBuffer, BitIndex, NumBits, FieldName)

Arguments

SourceBuffer is evaluated as a buffer. BitIndex and NumBits are evaluated as integers. FieldName is a NameString.

Description

A new buffer field object named *FieldName* is created for the bits of *SourceBuffer* at *BitIndex* for *NumBits*. The entire bit range of the defined field within *SourceBuffer* must exist. If *NumBits* evaluates to zero, a fatal exception is generated.

19.5.22 CreateQWordField (Create 64-Bit Buffer Field)

Syntax

CreateQWordField (SourceBuffer, ByteIndex, QWordFieldName)

Arguments

SourceBuffer is evaluated as a buffer. ByteIndex is evaluated as an integer. QWordFieldName is a NameString.

Description

A new buffer field object named *QWordFieldName* is created for the QWord of *SourceBuffer* at the byte index of *ByteIndex*. The QWord-defined field within *SourceBuffer* must exist.

19.5.23 CreateWordField (Create 16-Bit Buffer Field)

Syntax

CreateWordField (SourceBuffer, ByteIndex, WordFieldName)

Arguments

SourceBuffer is evaluated as a buffer. ByteIndex is evaluated as an integer. WordFieldName is a NameString.

Description

A new bufferfield object named *WordFieldName* is created for the word of *SourceBuffer* at the byte index of *ByteIndex*. The word-defined field within *SourceBuffer* must exist.

19.5.24 DataTableRegion (Create Data Table Operation Region)

Syntax

DataTableRegion (RegionName, SignatureString, OemIDString, OemTableIDString)

Arguments

Creates a new region named *RegionName*. *SignatureString*, *OemIDString* and *OemTableIDString* are evaluated as strings.

Description

A Data Table Region is a special Operation Region whose RegionSpace is SystemMemory . Any table referenced by a Data Table Region must be in memory marked by AddressRangeReserved or AddressRangeNVS.

The memory referred to by the Data Table Region is the memory that is occupied by the table referenced in XSDT that is identified by *SignatureString*, *OemIDString* and *OemTableIDString*. Any Field object can reference RegionName

The base address of a Data Table region is the address of the first byte of the header of the table identified by *SignatureString*, *OemIDString* and *OemTableIDString*. The length of the region is the length of the table.

19.5.25 Debug (Debugger Output)

Syntax

Debug

Description

The debug data object is a virtual data object. Writes to this object provide debugging information. On at least debug versions of the interpreter, any writes into this object are appropriately displayed on the system's native kernel debugger. All writes to the debug object are otherwise benign. If the system is in use without a kernel debugger, then writes to the debug object are ignored. The following table relates the ASL term types that can be written to the Debug object to the format of the information on the kernel debugger display.

Table 19-342 Debug Object Display Formats

ASL Term Type	Display Format
Numeric data object	All digits displayed in hexadecimal format.
String data object	String is displayed.
Object reference	Information about the object is displayed (for example, object type and object name), but the object is not evaluated.

The Debug object is a write-only object; attempting to read from the debug object is not supported.

19.5.26 Decrement (Integer Decrement)

Syntax

Decrement (*Minuend*) => Integer

Arguments

Minuend is evaluated as an Integer.

Description

This operation decrements the *Minuend* by one and the result is stored back to *Minuend*. Equivalent to **Subtract** (*Minuend*, 1, *Minuend*). Underflow conditions are ignored and the result is Ones.

19.5.27 Default (Default Execution Path in Switch)

Syntax

Default {TermList}

Arguments

TermList is a sequence of executable ASL expressions.

Description

Within the body of a **Switch** (page 818) statement, the statements specified by *TermList* will be executed if no **Case** (page 745) statement value matches the Switch statement value. If **Default** is omitted and no **Case** match is found, none of the statements in the Switch body are executed. There can be at most one **Default** statement in the immediate scope of the parent Switch statement. The **Default** statement can appear anywhere in the body of the **Switch** statement.

19.5.28 DefinitionBlock (Declare Definition Block)

Syntax

DefinitionBlock (AMLFileName, TableSignature, ComplianceRevision, OEMID, TableID, OEMRevision) {TermList}

Arguments

AMLFileName is a string that specifies the desired name of the translated output AML file. TableSignature is a string that contains the 4-character ACPI signature. ComplianceRevision is an 8-bit value. OEMID is a 6-character string, TableId is an 8-character string, and OEMRevision is a 32-bit value. TermList is a sequence of executable ASL expressions.

Description

The **DefinitionBlock** term specifies the unit of data and/or AML code that the OS will load as part of the Differentiated Definition Block or as part of an additional Definition Block.

This unit of data and/or AML code describes either the base system or some large extension (such as a docking station). The entire DefinitionBlock will be loaded and compiled by the OS as a single unit, and can be unloaded by the OS as a single unit.

Note: For compatibility with ACPI versions before ACPI 2.0, the bit width of Integer objects is dependent on the *ComplianceRevision* of the DSDT. If the *ComplianceRevision* is less than 2, all integers are restricted to 32 bits. Otherwise, full 64-bit integers are used. The version of the DSDT sets the global integer width for all integers, including integers in SSDTs.

19.5.29 DerefOf (Dereference an Object Reference)

Syntax

DerefOf (Source) => Object

Arguments

Returns the object referred by the *Source* object reference.

Description

If the *Source* evaluates to an object reference, the actual contents of the object referred to are returned. If the *Source* evaluates to a string, the string is evaluated as an ASL name (relative to the current scope) and the contents of that object are returned. If the object specified by *Source* does not exist then a fatal error is generated. If the object specified is a reference generated by the Index() operator and refers to an uninitialized package element, then a fatal error is generated.

Note: (Compatibility Note) The use of a String with DerefOf was first introduced in ACPI 2.0.

19.5.30 Device (Declare Bus/Device Package)

Syntax

Device (*DeviceName*) {ObjectList}

Arguments

Creates a Device object of name *DeviceName*, which represents either a bus or a device or any other similar hardware. Device opens a name scope.

Description

A Bus/Device Package is one of the basic ways the Differentiated Definition Block describes the hardware devices in the system to the operating software. Each Bus/Device Package is defined somewhere in the hierarchical namespace corresponding to that device's location in the system. Within the namespace of the device are other names that provide information and control of the device, along with any sub-devices that in turn describe sub-devices, and so on.

For any device, the BIOS provides only information that is added to the device in a non-hardware standard manner. This type of value-added function is expressible in the ACPI Definition Block such that operating software can use the function.

The BIOS supplies Device Objects only for devices that are obtaining some system-added function outside the device's normal capabilities and for any Device Object required to fill in the tree for such a device. For example, if the system includes a PCI device (integrated or otherwise) with no additional functions such as power management, the BIOS would not report such a device; however, if the system included an integrated ISA device below the integrated PCI device (device is an ISA bridge), then the system would include a Device Package for the ISA device with the minimum feature being added being the ISA device's ID and configuration information and the parent PCI device, because it is required to get the ISA Device Package placement in the namespace correct.

Example

The following block of ASL sample code shows a nested use of Device objects to describe an IDE controller connected to the root PCI bus.

```
Device (IDE0) {
                                    // primary controller
    Name (_ADR, 0)
                                    // put PCI Address (device/function) here
    // define region for IDE mode register
    OperationRegion (PCIC, PCI_Config, 0x50, 0x10)
    Field (PCIC, AnyAcc, NoLock, Preserve) {
       ice (PRIM) { // Primary adapter Name (_ADR, 0) // Primary adapter = 0
    Device (PRIM) {
        Method (_STM, 2) {
        Method (_GTM) {
        Device (MSTR) {
                             // master channel
            Name (_ADR, 0)
            Name (_PR0, Package () {0, PIDE})
            Name (_GTF) {
        Device (SLAV) {
            Name (_ADR, 1)
            Name (_PR0, Package () {0, PIDE})
            Name (_GTF) {
    }
}
```

19.5.31 Divide (Integer Divide)

Syntax

Divide (*Dividend, Divisor, Remainder, Result*) => Integer

Arguments

Dividend and Divisor are evaluated as Integers.

Description

Dividend is divided by *Divisor*, then the resulting remainder is optionally stored into *Remainder* and the resulting quotient is optionally stored into *Result*. Divide-by-zero exceptions are fatal.

The function return value is the *Result (quotient)*.

19.5.32 DMA (DMA Resource Descriptor Macro)

Syntax

DMA (*DmaType*, *IsBusMaster*, *DmaTransferSize*, *DescriptorName*) {*DmaChannelList*} => Buffer

Arguments

DmaType specifies the type of DMA cycle: ISA compatible (**Compatibility**), EISA Type A (**TypeA**), EISA Type B (**TypeB**) or EISA Type F (**TypeF**). The 2-bit field *DescriptorName*._TYP is automatically created to refer to this portion of the resource descriptor, where '0' is Compatibility, '1' is TypeA, '2' is TypeB and '3' is TypeF.

IsBusMaster specifies whether this device can generate DMA bus master cycles (**BusMaster**) or not (**NotBusMaster**). If nothing is specified, then BusMaster is assumed. The 1-bit field *DescriptorName*._BM is automatically created to refer to this portion of the resource descriptor, where '0' is NotBusMaster and '1' is BusMaster.

DmaTransferSize specifies the size of DMA cycles the device is capable of generating: 8-bit (**Transfer8**), 16-bit (**Transfer16**) or both 8 and 16-bit (**Transfer8_16**). The 2-bit field *DescriptorName*._SIZ is automatically created to refer to this portion of the resource descriptor, where '0' is Transfer8, '1' is Transfer8 16 and '2' is Transfer16.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

DmaChannelList is a comma-delimited list of integers in the range 0 through 7 that specify the DMA channels used by the device. There may be no duplicates in the list.

Description

The **DMA** macro evaluates to a buffer which contains a DMA resource descriptor. The format of the DMA resource descriptor can be found in "DMA Descriptor" (page 326). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.33 DWordIO (DWord IO Resource Descriptor Macro)

Syntax

DWordIO (ResourceUsage, IsMinFixed, IsMaxFixed, Decode, ISARanges, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, ResourceSourceIndex, ResourceSource, DescriptorName, TranslationType, TranslationDensity)

Arguments

ResourceUsage specifies whether the I/O range is consumed by this device (**ResourceConsumer**) or passed on to child devices (**ResourceProducer**). If nothing is specified, then ResourceConsumer is assumed.

IsMinFixed specifies whether the minimum address of this I/O range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field

DescriptorName._MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this I/O range is fixed (MaxFixed) or can be changed (MaxNotFixed). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field DescriptorName._MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

Decode specifies whether or not the device decodes the I/O range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field DescriptorName._DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

ISARanges specifies whether the I/O ranges specifies are limited to valid ISA I/O ranges (ISAOnly), valid non-ISA I/O ranges (NonISAOnly) or encompass the whole range without limitation (EntireRange). The 2-bit field DescriptorName._RNG is automatically created to refer to this portion of the resource descriptor, where '1' is NonISAOnly, '2' is ISAOnly and '0' is EntireRange.

AddressGranularity evaluates to a 32-bit integer that specifies the power-of-two boundary (- 1) on which the I/O range must be aligned. The 32-bit field *DescriptorName*._GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 32-bit integer that specifies the lowest possible base address of the I/O range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 32-bit field DescriptorName._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 32-bit integer that specifies the highest possible base address of the I/O range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 32-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 32-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 32-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 32-bit integer that specifies the total number of bytes decoded in the I/O range. The 32-bit field *DescriptorName*._LEN is automatically created to refer to this portion of the resource descriptor.

ResourceSourceIndex is an optional argument which evaluates to an 8-bit integer that specifies the resource descriptor within the object specified by ResourceSource. If this argument is specified, the ResourceSource argument must also be specified.

ResourceSource is an optional argument which evaluates to a string containing the path of a device which produces the pool of resources from which this I/O range is allocated. If this argument is specified, but the ResourceSourceIndex argument is not specified, a value of zero is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current

ACPI Source Language (ASL)Reference

resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

TranslationType is an optional argument that specifies whether the resource type on the secondary side of the bus is different (**TypeTranslation**) from that on the primary side of the bus or the same (**TypeStatic**). If TypeTranslation is specified, then the secondary side of the bus is Memory. If TypeStatic is specified, then the secondary side of the bus is I/O. If nothing is specified, then TypeStatic is assumed. The 1-bit field *DescriptorName*._TTP is automatically created to refer to this portion of the resource descriptor, where '1' is TypeTranslation and '0' is TypeStatic. See _TTP (page 348) for more information

TranslationDensity is an optional argument that specifies whether or not the translation from the primary to secondary bus is sparse (**SparseTranslation**) or dense (**DenseTranslation**). It is only used when *TranslationType* is **TypeTranslation**. If nothing is specified, then DenseTranslation is assumed. The 1-bit field *DescriptorName*._TRS is automatically created to refer to this portion of the resource descriptor, where '1' is SparseTranslation and '0' is DenseTranslation. See _TRS (page 348) for more information.

Description

The **DWordIO** macro evaluates to a buffer which contains a 32-bit I/O range resource descriptor. The format of the 32-bit I/O range resource descriptor can be found in "DWord Address Space Descriptor" (page 340). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.34 DWordMemory (DWord Memory Resource Descriptor Macro)

Syntax

DWordMemory (ResourceUsage, Decode, IsMinFixed, IsMaxFixed, Cacheable, ReadAndWrite, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, ResourceSourceIndex, ResourceSource, DescriptorName, MemoryRangeType, TranslationType)

Arguments

ResourceUsage specifies whether the Memory range is consumed by this device (ResourceConsumer) or passed on to child devices (ResourceProducer). If nothing is specified, then ResourceConsumer is assumed.

Decode specifies whether or not the device decodes the Memory range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field *DescriptorName*. DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

IsMinFixed specifies whether the minimum address of this Memory range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*. MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this Memory range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*._MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

Cacheable specifies whether or not the memory region is cacheable (Cacheable), cacheable and write-combining (WriteCombining), cacheable and prefetchable (Prefetchable) or uncacheable (NonCacheable). If nothing is specified, then NonCacheable is assumed. The 2-bit field DescriptorName. MEM is automatically created to refer to this portion of the resource descriptor, where '1' is Cacheable, '2' is WriteCombining, '3' is Prefetchable and '0' is NonCacheable.

ReadAndWrite specifies whether or not the memory region is read-only (**ReadOnly**) or read/write (**ReadWrite**). If nothing is specified, then ReadWrite is assumed. The 1-bit field DescriptorName._RW is automatically created to refer to this portion of the resource descriptor, where '1' is ReadWrite and '0' is ReadOnly.

AddressGranularity evaluates to a 32-bit integer that specifies the power-of-two boundary (- 1) on which the Memory range must be aligned. The 32-bit field *DescriptorName*._GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 32-bit integer that specifies the lowest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 32-bit field DescriptorName._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 32-bit integer that specifies the highest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 32-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 32-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 32-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 32-bit integer that specifies the total number of bytes decoded in the Memory range. The 32-bit field *DescriptorName*. LEN is automatically created to refer to this portion of the resource descriptor.

ResourceSourceIndex is an optional argument which evaluates to an 8-bit integer that specifies the resource descriptor within the object specified by ResourceSource. If this argument is specified, the ResourceSource argument must also be specified.

ResourceSource is an optional argument which evaluates to a string containing the path of a device which produces the pool of resources from which this Memory range is allocated. If this argument is specified, but the *ResourceSourceIndex* argument is not specified, a zero value is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

MemoryRangeType is an optional argument that specifies the memory usage. The memory can be marked as normal (**AddressRangeMemory**), used as ACPI NVS space (**AddressRangeNVS**), used as ACPI reclaimable space (**AddressRangeACPI**) or as system reserved (**AddressRangeReserved**). If nothing is specified, then AddressRangeMemory is assumed. The 2-bit field *DescriptorName*. MTP is automatically created in order to refer to this portion of the

ACPI Source Language (ASL)Reference

resource descriptor, where '0' is AddressRangeMemory, '1' is AddressRangeReserved, '2' is AddressRangeACPI and '3' is AddressRangeNVS.

TranslationType is an optional argument that specifies whether the resource type on the secondary side of the bus is different (**TypeTranslation**) from that on the primary side of the bus or the same (**TypeStatic**). If TypeTranslation is specified, then the secondary side of the bus is I/O. If TypeStatic is specified, then the secondary side of the bus is I/O. If nothing is specified, then TypeStatic is assumed. The 1-bit field *DescriptorName*._TTP is automatically created to refer to this portion of the resource descriptor, where '1' is TypeTranslation and '0' is TypeStatic. See _TTP (page 348) for more information.

Description

The **DWordMemory** macro evaluates to a buffer which contains a 32-bit memory resource descriptor. The format of the 32-bit memory resource descriptor can be found in "DWord Address Space Descriptor" (page 340). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.35 DWordSpace (DWord Space Resource Descriptor Macro)

Syntax

DWordSpace (ResourceType, ResourceUsage, Decode, IsMinFixed, IsMaxFixed, TypeSpecificFlags, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, ResourceSourceIndex, ResourceSource, DescriptorName)

Arguments

ResourceType evaluates to an 8-bit integer that specifies the type of this resource. Acceptable values are 0xC0 through 0xFF.

ResourceUsage specifies whether the Memory range is consumed by this device (**ResourceConsumer**) or passed on to child devices (**ResourceProducer**). If nothing is specified, then ResourceConsumer is assumed.

Decode specifies whether or not the device decodes the Memory range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field *DescriptorName*._DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

IsMinFixed specifies whether the minimum address of this Memory range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*._MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this Memory range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*. MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

TypeSpecificFlags evaluates to an 8-bit integer. The flags are specific to the *ResourceType*.

AddressGranularity evaluates to a 32-bit integer that specifies the power-of-two boundary (- 1) on which the Memory range must be aligned. The 32-bit field *DescriptorName*._GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 32-bit integer that specifies the lowest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 32-bit field DescriptorName. MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 32-bit integer that specifies the highest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 32-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 32-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 32-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 32-bit integer that specifies the total number of bytes decoded in the Memory range. The 32-bit field *DescriptorName*. LEN is automatically created to refer to this portion of the resource descriptor.

ResourceSourceIndex is an optional argument which evaluates to an 8-bit integer that specifies the resource descriptor within the object specified by ResourceSource. If this argument is specified, the ResourceSource argument must also be specified.

ResourceSource is an optional argument which evaluates to a string containing the path of a device which produces the pool of resources from which this Memory range is allocated. If this argument is specified, but the ResourceSourceIndex argument is not specified, a zero value is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **DWordSpace** macro evaluates to a buffer which contains a 32-bit Address Space resource descriptor. The format of the 32-bit Address Space resource descriptor can be found in "DWord Address Space Descriptor" (page 340). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.36 EISAID (EISA ID String To Integer Conversion Macro)

Syntax

EISAID (*EisaldString*) => DWordConst

Arguments

The *EisaldString* must be a String object of the form "UUUNNNN", where "U" is an uppercase letter and "N" is a hexadecimal digit. No asterisks or other characters are allowed in the string.

Description

Converts *EisaldString*, a 7-character text string argument, into its corresponding 4-byte numeric EISA ID encoding. It can be used when declaring IDs for devices that have EISA IDs.

Example

```
EISAID ("PNPOCO9") // This is a valid invocation of the macro.
```

19.5.37 Else (Alternate Execution)

Syntax

Else {TermList}

Arguments

TermList is a sequence of executable ASL statements.

Description

If *Predicate* evaluates to 0 in an **If** statement, then control is transferred to the Else portion, which can consist of zero or more **ElseIf** statements followed by zero or one **Else** statements. If the *Predicate* of any **ElseIf** statement evaluates to non-zero, the statements in its term list are executed and then control is transferred past the end of the final Else term. If no *Predicate* evaluates to non-zero, then the statements in the **Else** term list are executed.

Example

The following example checks Local0 to be zero or non-zero. On non-zero, CNT is incremented; otherwise, CNT is decremented.

```
If (LGreater (Local0, 5)
{
        Increment (CNT)
} Else If (Local0) {
        Add (CNT, 5, CNT)
}
Else
{
        Decrement (CNT)
}
```

19.5.38 Elself (Alternate/Conditional Execution)

Syntax

ElseIf (*Predicate*)

Arguments

Predicate is evaluated as an Integer.

Description

If the *Predicate* of any **ElseIf** statement evaluates to non-zero, the statements in its term list are executed and then control is transferred past the end of the final **Else**. If no *Predicate* evaluates to non-zero, then the statements in the **Else** term list are executed.

Note: (Compatibility Note) The Elself operator was first introduced in ACPI 2.0, but is backward compatible with the ACPI 1.0 specification. An ACPI 2.0 and later ASL compiler must synthesize Elself from the If. and Else opcodes available in 1.0. For example:

19.5.39 EndDependentFn (End Dependent Function Resource Descriptor Macro)

Syntax

EndDependentFn () => Buffer

Description

The **EndDependentFn** macro generates an end-of-dependent-function resource descriptor buffer inside of an ResourceTemplate (page 811). It must be matched with a StartDependentFn (page 816) or StartDependentFnNoPri (page 817) macro.

19.5.40 Event (Declare Event Synchronization Object)

Syntax

Event (EventName)

Arguments

Creates an event synchronization object named *EventName*.

Description

For more information about the uses of an event synchronization object, see the ASL definitions for the Wait, Signal, and Reset function operators.

19.5.41 ExtendedIO (Extended IO Resource Descriptor Macro)

Syntax

ExtendedIO (ResourceUsage, IsMinFixed, IsMaxFixed, Decode, ISARanges, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, TypeSpecificAttributes, DescriptorName, TranslationType, TranslationDensity)

Arguments

ResourceUsage specifies whether the Memory range is consumed by this device (**ResourceConsumer**) or passed on to child devices (**ResourceProducer**). If nothing is specified, then ResourceConsumer is assumed.

IsMinFixed specifies whether the minimum address of this I/O range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*._MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this I/O range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*._MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

Decode specifies whether or not the device decodes the I/O range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field *DescriptorName*._DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

ISARanges specifies whether the I/O ranges specifies are limited to valid ISA I/O ranges (ISAOnly), valid non-ISA I/O ranges (NonISAOnly) or encompass the whole range without limitation (EntireRange). The 2-bit field DescriptorName._RNG is automatically created to refer to this portion of the resource descriptor, where '1' is NonISAOnly, '2' is ISAOnly and '0' is EntireRange.

AddressGranularity evaluates to a 64-bit integer that specifies the power-of-two boundary (- 1) on which the I/O range must be aligned. The 64-bit field *DescriptorName*._GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 64-bit integer that specifies the lowest possible base address of the I/O range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is

'1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field *DescriptorName*._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 64-bit integer that specifies the highest possible base address of the I/O range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 64-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 64-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 64-bit integer that specifies the total number of bytes decoded in the I/O range. The 64-bit field *DescriptorName*._LEN is automatically created to refer to this portion of the resource descriptor.

TypeSpecificAttributes is an optional argument that specifies attributes specific to this resource type. See <u>Section 6.4.3.5.4.1</u>,"Type Specific Attributes".

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operatorsDescription

The **ExtendedIO** macro evaluates to a buffer which contains a 64-bit I/O resource descriptor, which describes a range of I/O addresses. The format of the 64-bit I/O resource descriptor can be found in "Extended Address Space Descriptor" (page 331). The macro is designed to be used inside of a ResourceTemplate (page 811).

TranslationType is an optional argument that specifies whether the resource type on the secondary side of the bus is different (**TypeTranslation**) from that on the primary side of the bus or the same (**TypeStatic**). If TypeTranslation is specified, then the secondary side of the bus is Memory. If TypeStatic is specified, then the secondary side of the bus is I/O. If nothing is specified, then TypeStatic is assumed. The 1-bit field *DescriptorName*. _TTP is automatically created to refer to this portion of the resource descriptor, where '1' is TypeTranslation and '0' is TypeStatic. See _TTP (page 348) for more information

TranslationDensity is an optional argument that specifies whether or not the translation from the primary to secondary bus is sparse (**SparseTranslation**) or dense (**DenseTranslation**). It is only used when TranslationType is **TypeTranslation**. If nothing is specified, then DenseTranslation is assumed. The 1-bit field DescriptorName._TRS is automatically created to refer to this portion of the resource descriptor, where '1' is SparseTranslation and '0' is DenseTranslation. See _TRS (page 348) for more information.

19.5.42 ExtendedMemory (Extended Memory Resource Descriptor Macro)

Syntax

ExtendedMemory (ResourceUsage, Decode, IsMinFixed, IsMaxFixed, Cacheable, ReadAndWrite, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, TypeSpecificAttributes, DescriptorName, MemoryRangeType, TranslationType)

Arguments

ResourceUsage specifies whether the Memory range is consumed by this device (ResourceConsumer) or passed on to child devices (ResourceProducer). If nothing is specified, then ResourceConsumer is assumed.

Decode specifies whether or not the device decodes the Memory range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field *DescriptorName*._DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

IsMinFixed specifies whether the minimum address of this Memory range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*. _MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this Memory range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*. _MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

Cacheable specifies whether or not the memory region is cacheable (Cacheable), cacheable and write-combining (WriteCombining), cacheable and prefetchable (Prefetchable) or uncacheable (NonCacheable). If nothing is specified, then NonCacheable is assumed. The 2-bit field DescriptorName._MEM is automatically created to refer to this portion of the resource descriptor, where '1' is Cacheable, '2' is WriteCombining, '3' is Prefetchable and '0' is NonCacheable.

ReadAndWrite specifies whether or not the memory region is read-only (**ReadOnly**) or read/write (**ReadWrite**). If nothing is specified, then ReadWrite is assumed. The 1-bit field DescriptorName._RW is automatically created to refer to this portion of the resource descriptor, where '1' is ReadWrite and '0' is ReadOnly.

AddressGranularity evaluates to a 64-bit integer that specifies the power-of-two boundary (- 1) on which the Memory range must be aligned. The 64-bit field *DescriptorName*._GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 64-bit integer that specifies the lowest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName ._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 64-bit integer that specifies the highest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the

secondary bus. The 64-bit field *DescriptorName* ._MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 64-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 64-bit field *DescriptorName*. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 64-bit integer that specifies the total number of bytes decoded in the Memory range. The 64-bit field *DescriptorName*. LEN is automatically created to refer to this portion of the resource descriptor.

TypeSpecificAttributes is an optional argument that specifies attributes specific to this resource type. See Section 6.4.3.5.4.1,"Type Specific Attributes".

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

MemoryRangeType is an optional argument that specifies the memory usage. The memory can be marked as normal (**AddressRangeMemory**), used as ACPI NVS space (**AddressRangeNVS**), used as ACPI reclaimable space (**AddressRangeACPI**) or as system reserved

(**AddressRangeReserved**). If nothing is specified, then AddressRangeMemory is assumed. The 2-bit field *DescriptorName*. _MTP is automatically created in order to refer to this portion of the resource descriptor, where '0' is AddressRangeMemory, '1' is AddressRangeReserved, '2' is AddressRangeACPI and '3' is AddressRangeNVS.

TranslationType is an optional argument that specifies whether the resource type on the secondary side of the bus is different (**TypeTranslation**) from that on the primary side of the bus or the same (**TypeStatic**). If TypeTranslation is specified, then the secondary side of the bus is I/O. If TypeStatic is specified, then the secondary side of the bus is I/O. If nothing is specified, then TypeStatic is assumed. The 1-bit field *DescriptorName*. _TTP is automatically created to refer to this portion of the resource descriptor, where '1' is TypeTranslation and '0' is TypeStatic. See _TTP (page 348) for more information.

Description

The **ExtendedMemory** macro evaluates to a buffer which contains a 64-bit memory resource descriptor, which describes a range of memory addresses. The format of the 64-bit memory resource descriptor can be found in "Extended Address Space Descriptor" (page 343). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.43 ExtendedSpace (Extended Address Space Resource Descriptor Macro)

Syntax

ExtendedSpace (ResourceType, ResourceUsage, Decode, IsMinFixed, IsMaxFixed, TypeSpecificFlags, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, TypeSpecificAttributes, DescriptorName)

ACPI Source Language (ASL)Reference

Arguments

ResourceType evaluates to an 8-bit integer that specifies the type of this resource. Acceptable values are 0xC0 through 0xFF.

ResourceUsage specifies whether the Memory range is consumed by this device (**ResourceConsumer**) or passed on to child devices (**ResourceProducer**). If nothing is specified, then ResourceConsumer is assumed.

Decode specifies whether or not the device decodes the Memory range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field *DescriptorName*. _DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

IsMinFixed specifies whether the minimum address of this Memory range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*. _MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this Memory range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*. _MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

TypeSpecificFlags evaluates to an 8-bit integer. The flags are specific to the *ResourceType*.

Address Granularity evaluates to a 64-bit integer that specifies the power-of-two boundary (- 1) on which the Memory range must be aligned. The 64-bit field *DescriptorName*. _GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 64-bit integer that specifies the lowest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName. MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 64-bit integer that specifies the highest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 64-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 64-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 64-bit integer that specifies the total number of bytes decoded in the Memory range. The 64-bit field *DescriptorName*. LEN is automatically created to refer to this portion of the resource descriptor.

TypeSpecificAttributes is an optional argument that specifies attributes specific to this resource type. See <u>Section 6.4.3.5.4.1</u>,"Type Specific Attributes".

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current

resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **ExtendedSpace** macro evaluates to a buffer which contains a 64-bit Address Space resource descriptor, which describes a range of addresses. The format of the 64-bit AddressSpace descriptor can be found in "Extended Address Space Descriptor" (page 343). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.44 External (Declare External Objects)

Syntax

External (ObjectName, ObjectType, ReturnType, ParameterTypes)

Arguments

ObjectName is a NameString.

ObjectType is an optional ObjectTypeKeyword (e.g. IntObj, PkgObj, etc.). If not specified, "UnknownObj" type is assumed.

ReturnType is optional. If the specified ObjectType is **MethodObj**, then this specifies the type or types of object returned by the method. If the method does not return an object, then nothing is specified or **UnknownObj** is specified. To specify a single return type, simply use the ObjectTypeKeyword. To specify multiple possible return types, enclose the comma-separated ObjectTypeKeywords with braces. For example: {IntObj, BuffObj}.

ParameterTypes is optional. If the specified ObjectType is **MethodObj**, this specifies both the number and type of the method parameters. It is a comma-separated, variable-length list of the expected object type or types for each of the method parameters, enclosed in braces. For each parameter, the parameter type consists of either an ObjectTypeKeyword or a comma-separated sublist of ObjectTypeKeywords enclosed in braces. There can be no more than seven parameters in total.Description

The External directive informs the ASL compiler that the object is declared external to this table so that no errors will be generated for an undeclared object. The ASL compiler will create the external object at the specified place in the namespace (if a full path of the object is specified), or the object will be created at the current scope of the External term.

External is especially useful for use in secondary SSDTs, when the required scopes and objects are declared in the main DSDT.

Example

This example shows the use of **External** in conjunction with **Scope** within an SSDT:

```
DefinitionBlock ("ssdt.aml", "SSDT", 2, "X", "Y", 0x00000001)
{
    External (\_SB.PCI0, DeviceObj)

    Scope (\_SB.PCI0)
    {
     }
}
```

19.5.45 Fatal (Fatal Error Check)

Syntax

Fatal (Type, Code, Arg)

Arguments

This operation is used to inform the OS that there has been an OEM-defined fatal error.

Description

In response, the OS must log the fatal event and perform a controlled OS shutdown in a timely fashion.

19.5.46 Field (Declare Field Objects)

Syntax

Field (RegionName, AccessType, LockRule, UpdateRule) {FieldUnitList}

Arguments

RegionName is a namestring that refers to the host operation region.

AccessType defines the default access width of the field definition and is any one of the following: AnyAcc, ByteAcc, WordAcc, DWordAcc, or QWordAcc. In general, accesses within the parent object are performed naturally aligned. If desired, AccessType set to a value other than AnyAcc can be used to force minimum access width. Notice that the parent object must be able to accommodate the AccessType width. For example, an access type of WordAcc cannot read the last byte of an odd-length operation region. The exceptions to natural alignment are the access types used for a non-linear SMBus device. These will be discussed in detail below. Not all access types are meaningful for every type of operational region.

LockRule is a flag that indicates whether the Global Lock is to be used when accessing this field and is one of the following: Lock or NoLock. If LockRule is set to Lock, accesses to modify the component data objects will acquire and release the Global Lock. If both types of locking occur, the Global Lock is acquired after the parent object Mutex.

On Hardware-reduced ACPI platforms, Lock is not supported.

UpdateRule is used to specify how the unmodified bits of a field are treated and is any one of the following: **Preserve**, **WriteAsOnes**, or **WriteAsZeros**. For example, if a field defines a component data object of 4 bits in the middle of a **WordAcc** region, when those 4 bits are modified the *UpdateRule* specifies how the other 12 bits are treated.

FieldUnitList is a variable-length list of individual field unit definitions, separated by commas. Each entry in the field unit list is one of the following:

Table 19-343 Field Unit list entires

FieldUnitName, BitLength		
Offset (ByteOffset)		
AccessAs (AccessType, AccessAttribute)		
Connection (ConnectionResourceObj)		

FieldUnitName is the ACPI name for the field unit (1 to 4 characters), and BitLength is the length of the field unit in bits. **Offset** is used to specify the byte offset of the next defined field unit. This can be used instead of defining the bit lengths that need to be skipped. **AccessAs** is used to define the access type and attributes for the remaining field units within the list. **Connection** is used to identify the connection resource of the field access. This is necessary for GenericSerialBus and GeneralPurposeIO operation region types only.

Description

Declares a series of named data objects whose data values are fields within a larger object. The fields are parts of the object named by *RegionName*, but their names appear in the same scope as the **Field** term.

For example, the field operator allows a larger operation region that represents a hardware register to be broken down into individual bit fields that can then be accessed by the bit field names. Extracting and combining the component field from its parent is done automatically when the field is accessed.

When reading from a *FieldUnit*, returned values are normalized (shifted and masked to the proper length.) The data type of an individual FieldUnit can be either a **Buffer** or an **Integer**, depending on the bit length of the FieldUnit. If the FieldUnit is smaller than or equal to the size of an Integer (in bits), it will be treated as an Integer. If the FieldUnit is larger than the size of an Integer, it will be treated as a Buffer. The size of an Integer is indicated by the DSDT header's *Revision* field. A revision less than 2 indicates that the size of an Integer is 32 bits. A value greater than or equal to 2 signifies that the size of an Integer is 64 bits. For more information about data types and FieldUnit type conversion rules, see <u>Section 19.2.5.7</u>, "Data Type Conversion Rules".

Accessing the contents of a field data object provides access to the corresponding field within the parent object. If the parent object supports Mutex synchronization, accesses to modify the component data objects will acquire and release ownership of the parent object around the modification.

The following table relates region types declared with an OperationRegion term to the different access types supported for each region.

Table 19-344 OperationRegion Region Types and Access Types

Region Type	Permitted Access Type(s)	Description
SystemMemory	ByteAcc, WordAcc, DWordAcc,	All access allowed
	QWordAcc, or AnyAcc	

ACPI Source Language (ASL)Reference

Region Type	Permitted Access Type(s)	Description
SystemIO	ByteAcc, WordAcc, DWordAcc, QWordAcc, or AnyAcc	All access allowed
PCI_Config	ByteAcc, WordAcc, DWordAcc, QWordAcc, or AnyAcc	All access allowed
EmbeddedControl	ByteAcc	Byte access only
SMBus	BufferAcc	Reads and writes to this operation region involve the use of a region specific data buffer. (See below.)
SystemCMOS	ByteAcc	Byte access only
PciBarTarget	ByteAcc, WordAcc, DWordAcc, QWordAcc, or AnyAcc	All access allowed
IPMI	BufferAcc	Reads and writes to this operation region involve the use of a region specific data buffer. (See below.)
GeneralPurposeIO	ByteAcc	Byte access only
GenericSerialBus	BufferAcc	Reads and writes to this operation region involve the use of a region-specific data buffer. (See below.)

The named FieldUnit data objects are provided in the FieldList as a series of names and bit widths. Bits assigned no name (or NULL) are skipped. The ASL compiler supports the **Offset** (ByteOffset) macro within a FieldList to skip to the bit position of the supplied byte offset, and the **AccessAs** macro to change access within the field list.

GenericSerialBus, SMBus and IPMI regions are inherently non-linear, where each offset within the respective address space represents a variable sized (0 to 32 bytes) field. Given this uniqueness, these operation regions include restrictions on their field definitions and require the use of a region-specific data buffer when initiating transactions. For more information on the SMBus data buffer format, see Section 13, "ACPI System Management Bus Interface Specification,". For more information on the IPMI data buffer format, see Section 5.5.2.4.3, "Declaring IPMI Operation Regions". For more information on the Generic Serial Bus data buffer format, see Section 5.5.2.4.5 "Declaring Generic Serial Bus Operation Regions."

For restrictions on the use of Fields with GeneralPurposeIO OpRegions, see <u>Section 5.5.2.4.4</u>, "Declaring General PurposeIO Operation Regions".

Example

```
OperationRegion (MIOC, PCI_Config, Zero, 0xFF)
Field (MIOC, AnyAcc, NoLock, Preserve)
{
     Offset (0x58),
     HXGB, 32,
     HXGT, 32,
     GAPE, 8,
```

```
MROA, 4,
MROB, 4
```

19.5.47 FindSetLeftBit (Find First Set Left Bit)

Syntax

FindSetLeftBit (Source, Result) => Integer

Arguments

Source is evaluated as an Integer.

Description

The one-based bit location of the first MSb (most significant set bit) is optionally stored into *Result*. The result of 0 means no bit was set, 1 means the left-most bit set is the first bit, 2 means the left-most bit set is the second bit, and so on.

19.5.48 FindSetRightBit (Find First Set Right Bit)

Syntax

FindSetRightBit (Source, Result) => Integer

Arguments

Source is evaluated as an Integer.

Description

The one-based bit location of the most LSb (least significant set bit) is optionally stored in *Result*. The result of 0 means no bit was set, 32 means the first bit set is the thirty-second bit, 31 means the first bit set is the thirty-first bit, and so on.

19.5.49 FixedDMA (DMA Resource Descriptor Macro)

Syntax

FixedDMA (DmaRequestLine, Channel, DmaTransferWidth, DescriptorName) => Buffer

Arguments

DmaRequestLine is a system-relative number uniquely identifying the request line statically assigned to the device. The bit field name _DMA is automatically created to refer to this portion of the resource descriptor.

Channel is a controller-relative number uniquely identifying the channel statically assigned to this *DMARequestLine*. Channels can be shared by reusing Channel numbers across descriptors. The bit field name _TYP is automatically created to refer to this portion of the resource descriptor.

DmaTransferWidth is an optional argument specifying the width of data transfer for which the device is configured. Valid values are Width8Bit, Width16Bit, Width32Bit, Width64Bit, Width

128Bit or **Width256Bit.** If not specified, **Width32Bit** is assumed. The bit field name _SIZ is automatically created to refer to this portion of the resource descriptor.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The FixedDMA macro evaluates to a buffer that contains a Fixed DMA Descriptor (Section 6.4.3).

19.5.50 FixedIO (Fixed IO Resource Descriptor Macro)

Syntax

FixedIO (*AddressBase*, *RangeLength*, *DescriptorName*) => Buffer

Arguments

AddressBase evaluates to a 16-bit integer. It describes the starting address of the fixed I/O range. The field *DescriptorName*. BAS is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to an 8-bit integer. It describes the length of the fixed I/O range. The field DescriptorName. _LEN is automatically created to refer to this portion of the resource descriptor.

DescriptorName evaluates to a name string which refers to the entire resource descriptor.

Description

The **FixedIO** macro evaluates to a buffer which contains a fixed I/O resource descriptor. The format of the fixed I/O resource descriptor can be found in "Fixed Location I/O Port Descriptor" (page 329). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.51 FromBCD (Convert BCD To Integer)

Syntax

FromBCD (*BCDValue*, *Result*) => Integer

Arguments

BCDValue is evaluated as an Integer.

Description

The **FromBCD** operation is used to convert BCDValue to a numeric format and store the numeric value into Result.

19.5.52 Function (Declare Control Method)

Syntax

Function (FunctionName, ReturnType, ParameterTypes) {TermList}

Arguments

ReturnType is optional and specifies the type(s) of the object(s) returned by the method. If the method does not return an object, then nothing is specified or **UnknownObj** is specified. To specify a single return type, simply use the *ObjectTypeKeyword* (e.g. **IntObj**, **PkgObj**, etc.). To specify multiple possible return types, enclose the comma-separated *ObjectTypeKeywords* with braces. For example: {IntObj, BuffObj}.

ParameterTypes specifies both the number and type of the method parameters. It is a commaseparated, variable-length list of the expected object type or types for each of the method parameters, enclosed in braces. For each parameter, the parameter type consists of either an ObjectTypeKeyword or a comma-separated sub-list of ObjectTypeKeywords enclosed in braces. There can be no more than seven parameters in total.

Description

Function declares a named package containing a series of terms that collectively represent a control method. A control method is a procedure that can be invoked to perform computation. **Function** opens a name scope.

System software executes a control method by executing the terms in the package in order. For more information on method execution, see <u>Section 5.5.2</u>, "Control Method Execution."

The current namespace location used during name creation is adjusted to be the current location on the namespace tree. Any names created within this scope are "below" the name of this package. The current namespace location is assigned to the method package, and all namespace references that occur during control method execution for this package are relative to that location.

Functions are equivalent to a **Method** that specifies **NotSerialized**. As such, a function should not create any named objects, since a second thread that might re-enter the function will cause a fatal error if an attempt is made to create the same named object twice.

Note: (Compatibility Note) New for ACPI 3.0

Example

The following block of ASL sample code shows the use of **Function** for defining a control method: Function (EXAM, IntObj, {StrObj, {IntObj, StrObj}})

```
Name (Temp,"")
Store (Arg0, Temp) // could have used Arg1
Return (SizeOf (Concatenate (Arg1, Temp)))
}
```

This declaration is equivalent to:

```
Method (EXAM, 2, NotSerialized, 0, IntObj, {StrObj, {IntObj, StrObj}})
{
...
}
```

19.5.53 GpioInt (GPIO Interrupt Connection Resource Descriptor Macro)

GpioInt (EdgeLevel, ActiveLevel, Shared, PinConfig, DebounceTimeout, ResourceSource, ResourceSourceIndex, ResourceUsage, DescriptorName, VendorData) {PinList}

Arguments

EdgeLevel can be either **Edge** or **Level**. The bit field name _MOD is automatically created to refer to this portion of the resource descriptor.

ActiveLevel can be one of **ActiveHigh**, **ActiveLow** or **ActiveBoth**. **ActiveBoth** can be specified only if *EdgeLevel* is **Edge**. The bit field name _POL is automatically created to refer to this portion of the resource descriptor.

Shared is an optional argument and can be one of **Shared**, **Exclusive**, **SharedAndWake or ExclusiveAndWake**. If not specified, **Exclusive** is assumed. The "Wake" designation indicates that the interrupt is capable of waking the system from a low-power idle state or a system sleep state. The bit field name _SHR is automatically created to refer to this portion of the resource descriptor.

PinConfig can be one of **PullDefault**, **PullUp**, **PullDown**, **PullNone** or a vendor-supplied value in the range 128-255. The bit field name _PPI is automatically created to refer to this portion of the resource descriptor.

DebounceTimeout is an optional argument specifying the **debounce wait time**, in hundredths of milliseconds. The bit field name _DBT is automatically created to refer to this portion of the resource descriptor.

ResourceSource is a string which uniquely identifies the **GPIO controller** referred to by this descriptor. ResourceSource can be a fully-qualified name, a relative name or a name segment that utilizes the namespace search rules.

ResourceSourceIndex is an optional argument and is assumed to be 0 for this revision.

ResourceUsage is an optional argument and is assumed to be **ResourceConsumer** for this revision.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

VendorData is an optional argument that specifies a RawDataBuffer containing vendor-defined byte data to be decoded by the OS driver. The bit field name _VEN is automatically created to refer to this portion of the resource descriptor.

PinList is a list of (zero-based) pin numbers on the ResourceSource that are described by this descriptor. For interrupt pin descriptors, only one pin is allowed. The bit field name _PIN is automatically created to refer to this portion of the resource descriptor.

Description

The **GpioInt** macro evaluates to a buffer that contains a GPIO Interrupt Connection resource descriptor. The format of the GPIO Interrupt Connection resource descriptor can be found in "GPIO Connection Descriptor" (Section 6.4.3.8.1). The macro is designed to be used inside of a Resource Template (Section 19.2.3).

19.5.54 Gpiolo (GPIO Connection IO Resource Descriptor Macro)

GpioIo (Shared, PinConfig, DebounceTimeout, DriveStrength, IORestriction, ResourceSource, ResourceSourceIndex, ResourceUsage, DescriptorName, VendorData) {PinList}

Arguments

Shared is an optional argument and can be either **Shared** or **Exclusive**. If not specified, **Exclusive** is assumed. The bit field name _SHR is automatically created to refer to this portion of the resource descriptor.

PinConfig can be one of **PullDefault**, **PullUp**, **PullDown**, **PullNone** or a vendor-supplied value in the range 128-255. The bit field name _PPI is automatically created to refer to this portion of the resource descriptor.

DebounceTimeout is an optional argument specifying the hardware **debounce wait time**, in hundredths of milliseconds. The bit field name _DBT is automatically created to refer to this portion of the resource descriptor.

DriveStrength is an optional argument specifying the **output drive** capability of the pin, in hundredths of milliamperes. The bit field name _DRS is automatically created to refer to this portion of the resource descriptor.

IORestriction is an optional argument and can be **IoRestrictionInputOnly**,

IoRestrictionOutputOnly, IoRestrictionNone, or IORestrictionNoneAndPreserve.

IORestrictions limit the mode in which the pin can be accessed (Input or Output). They also ensure that the pin configuration is preserved during periods when the driver is unloaded or the resource has been disconnected by the driver. If not specified, **IoRestrictionNone** is assumed. The bit field name IOR is automatically created to refer to this portion of the resource descriptor.

ResourceSource is a string which uniquely identifies the **GPIO controller** referred to by this descriptor. **ResourceSource** can be a fully-qualified name, a relative name or a name segment that utilizes the namespace search rules.

ResourceSourceIndex is an optional argument and is always **0** for this revision.

ResourceUsage is an optional argument and is always ResourceConsumer for this revision.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

VendorData is an optional argument that specifies a RawDataBuffer containing vendor-defined byte data to be decoded by the OS driver. The bit field name _VEN is automatically created to refer to this portion of the resource descriptor.

PinList is a list of **pin numbers** on the ResourceSource that are described by this descriptor. The bit field name _PIN is automatically created to refer to this portion of the resource descriptor.

Description

The **GpioIo** macro evaluates to a buffer that contains a GPIO IO Connection resource descriptor. The format of the GPIO IO Connection resource descriptor can be found in "GPIO Connection Descriptor" (Section 6.4.3.8.1). The macro is designed to be used inside of a Resource Template (Section 19.2.3).

19.5.55 I2CSerialBus (I2C Serial Bus Connection Resource Descriptor Macro)

Syntax

I2CSerialBus (SlaveAddress, SlaveMode, ConnectionSpeed, AddressingMode, ResourceSource, ResourceSourceIndex, ResourceUsage, DescriptorName, VendorData)

Arguments

SlaveAddress is the I2C bus address for this connection. The bit field name _ADR is automatically created to refer to this portion of the resource descriptor.

SlaveMode is an optional argument and can be either **ControllerInitiated** or **DeviceInitiated**. ControllerInitiated is the default. The bit field name _SLV is automatically created to refer to this portion of the resource descriptor.

ConnectionSpeed is the maximum connection speed supported by this connection, in hertz. The bit field name SPE is automatically created to refer to this portion of the resource descriptor.

AddressingMode is an optional argument and can be either AddressingMode7Bit or AddressingMode10Bit. AddressingMode7Bit is the default. The bit field name _MOD is automatically created to refer to this portion of the resource descriptor.

ResourceSource is a string which uniquely identifies the **I2C** bus controller referred to by this descriptor. *ResourceSource* can be a fully-qualified name, a relative name or a name segment that utilizes the namespace search rules.

ResourceSourceIndex is an optional argument and is assumed to be 0 for this revision.

ResourceUsage is an optional argument and is assumed to be ResourceConsumer for this revision.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

VendorData is an optional argument that specifies an object to be decoded by the OS driver. It is a RawDataBuffer. The bit field name _VEN is automatically created to refer to this portion of the resource descriptor.

Description

The **I2CSerialBus** macro evaluates to a buffer that contains an I2C Serial Bus resource descriptor. The macro is designed to be used inside of a ResourceTemplate (see <u>Section 19.2.3</u>).

19.5.56 If (Conditional Execution)

Syntax

If (Predicate) {TermList}

Arguments

Predicate is evaluated as an Integer.

Description

If the *Predicate* is non-zero, the term list of the **If** term is executed.

Example

The following examples all check for bit 3 in Local0 being set, and clear it if set.

```
// example 1

If (And (Local0, 4))
{
      XOr (Local0, 4, Local0)
}

// example 2

Store (4, Local2)

If (And (Local0, Local2))
{
      XOr (Local0, Local2, Local0)
}
```

19.5.57 Include (Include Additional ASL File)

Syntax

Include (*FilePathName*)

Arguments

FilePathname is a StringData data type that contains the full OS file system path.

Description

Include another file that contains ASL terms to be inserted in the current file of ASL terms. The file must contain elements that are grammatically correct in the current scope.

Example

```
Include ("dataobj.asl")
```

19.5.58 Increment (Integer Increment)

Syntax

```
Increment (Addend) => Integer
```

ACPI Source Language (ASL)Reference

Arguments

Addend is evaluated as an Integer.

Description

Add one to the Addend and place the result back in Addend. Equivalent to **Add** (*Addend*, 1, *Addend*). Overflow conditions are ignored and the result of an overflow is zero.

19.5.59 Index (Indexed Reference To Member Object)

Syntax

Index (Source, Index, Destination) => ObjectReference

Arguments

Source is evaluated to a buffer, string, or package data type. Index is evaluated to an integer. The reference to the nth object (where n = Index) within Source is optionally stored as a reference into Destination.

Description

When *Source* evaluates to a Buffer, Index returns a reference to a Buffer Field containing the nth byte in the buffer. When *Source* evaluates to a String, Index returns a reference to a Buffer Field containing the nth character in the string. When *Source* evaluates to a Package, Index returns a reference to the nth object in the package.

19.5.59.1 Index with Packages

The following example ASL code shows a way to use the **Index** term to store into a local variable the sixth element of the first package of a set of nested packages:

Note: DeRefOf is necessary in the first operand of the **Store** operator in order to get the actual object, rather than just a reference to the object. If **DeRefOf** were not used, then Local0 would contain an object reference to the sixth element in the first package rather than the number 1.

19.5.59.2 Index with Buffers

The following example ASL code shows a way to store into the third byte of a buffer:

```
Name (BUFF, Buffer () \{0x01, 0x02, 0x03, 0x04, 0x05\})

// Store 0x55 into the third byte of the buffer

Store (0x55, Index (BUFF, 2))
```

The **Index** operator returns a reference to an 8-bit Buffer Field (similar to that created using **CreateByteField**).

If *Source* is evaluated to a buffer data type, the *ObjectReference* refers to the byte at *Index* within *Source*. If *Source* is evaluated to a buffer data type, a **Store** operation will only change the byte at *Index* within *Source*.

The following example ASL code shows the results of a series of **Store** operations:

```
Name (SRCB, Buffer () \{0x10, 0x20, 0x30, 0x40\})
Name (BUFF, Buffer () \{0x1, 0x2, 0x3, 0x4\})
```

The following will store 0x78 into the 3^{rd} byte of the destination buffer:

```
Store (0x12345678, Index (BUFF, 2))
```

The following will store 0x10 into the 2^{nd} byte of the destination buffer:

```
Store (SRCB, Index (BUFF, 1))
```

The following will store 0x41 (an 'A') into the 4th byte of the destination buffer:

```
Store ("ABCDEFGH", Index (BUFF, 3))
```

Note: (Compatibility Note) First introduced in ACPI 2.0. In ACPI 1.0, the behavior of storing data larger than 8-bits into a buffer using Index was undefined.

19.5.59.3 Index with Strings

The following example ASL code shows a way to store into the 3rd character in a string:

```
Name (STR, "ABCDEFGHIJKL")

// Store 'H' (0x48) into the third character to the string

Store ("H", Index (STR, 2))
```

The **Index** operator returns a reference to an 8-bit Buffer Field (similar to that created using **CreateByteField**).

Note: (Compatibility Note) First introduced in ACPI 2.0.

19.5.60 IndexField (Declare Index/Data Fields)

Syntax

IndexField (IndexName, DataName, AccessType, LockRule, UpdateRule) {FieldUnitList}

Arguments

IndexName and *DataName* refer to field unit objects. *AccessType*, *LockRule*, *UpdateRule*, and *FieldList* are the same format as the **Field** term.

Description

Creates a series of named data objects whose data values are fields within a larger object accessed by an index/data-style reference to *IndexName* and *DataName*.

This encoding is used to define named data objects whose data values are fields within an index/data register pair. This provides a simple way to declare register variables that occur behind a typical index and data register pair.

Accessing the contents of an indexed field data object will automatically occur through the *DataName* object by using an *IndexName* object aligned on an *AccessType* boundary, with synchronization occurring on the operation region that contains the index data variable, and on the Global Lock if specified by *LockRule*.

The value written to the *IndexName* register is defined to be a byte offset that is aligned on an *AccessType* boundary. For example, if *AccessType* is **DWordAcc**, valid index values are 0, 4, 8, etc. This value is always a byte offset and is independent of the width or access type of the *DataName* register.

Example

The following is a block of ASL sample code using **IndexField**:

Creates an index/data register in system I/O space made up of 8-bit registers.

Creates a FET0 field within the indexed range.

```
Method (EX1) {
   // Define a 256-byte operational region in SystemIO space
   // and name it GIOO
   OperationRegion (GIO0, 1, 0x125, 0x100)
   // Create a field named Preserve structured as a sequence
   // of index and data bytes
   Field (GIO0, ByteAcc, NoLock, WriteAsZeros) {
       IDX0, 8,
       DAT0, 8,
    // Create an IndexField within IDX0 & DAT0 which has
   // FETs in the first two bits of indexed offset 0,
   // and another 2 FETs in the high bit on indexed
   // 2F and the low bit of indexed offset 30
   IndexField (IDX0, DAT0, ByteAcc, NoLock, Preserve) {
       FET0, 1,
       FET1, 1,
       Offset (0x2f), // skip to byte offset 2f
                            // skip another 7 bits
       , 7,
       FET3, 1,
       FET4, 1
    }
   // Clear FET3 (index 2F, bit 7)
   Store (Zero, FET3)
} // End EX1
```

19.5.61 Interrupt (Interrupt Resource Descriptor Macro)

Syntax

Interrupt (*ResourceUsage*, *EdgeLevel*, *ActiveLevel*, *Shared*, *ResourceSourceIndex*, *ResourceSource*, *DescriptorName*) {InterruptList} => Buffer

Arguments

ResourceUsage describes whether the device consumes the specified interrupt (ResourceConsumer) or produces it for use by a child device (ResourceProducer). If nothing is specified, then ResourceConsumer is assumed.

EdgeLevel describes whether the interrupt is edge triggered (**Edge**) or level triggered (**Level**). The field *DescriptorName*. _HE is automatically created to refer to this portion of the resource descriptor, where '1' is Edge and '0' is Level.

ACPI Source Language (ASL)Reference

ActiveLevel describes whether the interrupt is active-high (**ActiveHigh**) or active-low (**ActiveLow**). The field *DescriptorName*. _LL is automatically created to refer to this portion of the resource descriptor, where '1' is ActiveHigh and '0' is ActiveLow.

Shared describes whether the interrupt can be shared with other devices (**Shared**) or not (**Exclusive**), and whether it is capable of waking the system from a low-power idle or system sleep state (**SharedAndWake** or **ExclusiveAndWake**). The field *DescriptorName*. SHR is automatically created to refer to this portion of the resource descriptor, where '1' is Shared and '0' is Exclusive. If nothing is specified, then Exclusive is assumed.

ResourceSourceIndex evaluates to an integer between 0x00 and 0xFF and describes the resource source index. If it is not specified, then it is not generated. If this argument is specified, the ResourceSource argument must also be specified.

ResourceSource evaluates to a string which uniquely identifies the resource source. If it is not specified, it is not generated. If this argument is specified, but the *ResourceSourceIndex* argument is not specified, a zero value is assumed.

DescriptorName evaluates to a name string which refers to the entire resource descriptor.

InterruptList is a comma-delimited list on integers, at least one value is required. Each integer represents a 32-bit interrupt number. At least one interrupt must be defined, and there may be no duplicates in the list. The field "DescriptorName. _INT" is automatically created to refer to this portion of the resource descriptor.

Description

The **Interrupt** macro evaluates to a buffer that contains an interrupt resource descriptor. The format of the interrupt resource descriptor can be found in "Extended Interrupt Descriptor" (page 325). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.62 IO (IO Resource Descriptor Macro)

Syntax

IO (Decode, AddressMin, AddressMax, AddressAlignment, RangeLength, DescriptorName) => Buffer

Argument

Decode describes whether the I/O range uses 10-bit decode (**Decode10**) or 16-bit decode (**Decode16**). The field *DescriptorName*. _DEC is automatically created to refer to this portion of the resource descriptor, where '1' is **Decode16** and '0' is **Decode10**.

AddressMin evaluates to a 16-bit integer that specifies the minimum acceptable starting address for the I/O range. It must be an even multiple of AddressAlignment. The field DescriptorName._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMax evaluates to a 16-bit integer that specifies the maximum acceptable starting address for the I/O range. It must be an even multiple of AddressAlignment. The field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

AddressAlignment evaluates to an 8-bit integer that specifies the alignment granularity for the I/O address assigned. The field *DescriptorName*. _ALN is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to an 8-bit integer that specifies the number of bytes in the I/O range. The field *DescriptorName*. _LEN is automatically created to refer to this portion of the resource descriptor.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **IO** macro evaluates to a buffer which contains an IO resource descriptor. The format of the IO descriptor can be found in "I/O Port Descriptor" (page 325). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.63 IRQ (Interrupt Resource Descriptor Macro)

Syntax

IRO (EdgeLevel, ActiveLevel, Shared, DescriptorName) {InterruptList} => Buffer

Arguments

EdgeLevel describes whether the interrupt is edge triggered (**Edge**) or level triggered (**Level**). The field *DescriptorName*. _HE is automatically created to refer to this portion of the resource descriptor, where '1' is **Edge** and **ActiveHigh** and '0' is **Level** and **ActiveLow**.

ActiveLevel describes whether the interrupt is active-high (**ActiveHigh**) or active-low (**ActiveLow**). The field *DescriptorName*. _LL is automatically created to refer to this portion of the resource descriptor, where '1' is **Edge** and **ActiveHigh** and '0' is **Level** and **ActiveLow**.

Shared describes whether the interrupt can be shared with other devices (Shared) or not (Exclusive), and whether it is capable of waking the system from a low-power idle or system sleep state (SharedAndWake or ExclusiveAndWake). The field DescriptorName. SHR is automatically created to refer to this portion of the resource descriptor, where '1' is Shared and '0' is Exclusive. If nothing is specified, then Exclusive is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

InterruptList is a comma-delimited list of integers in the range 0 through 15, at least one value is required. There may be no duplicates in the list.

Description

The **IRQ** macro evaluates to a buffer that contains an IRQ resource descriptor. The format of the IRQ descriptor can be found in "IRQ Descriptor" ((page 325). The macro produces the three-byte form of the descriptor. The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.64 IRQNoFlags (Interrupt Resource Descriptor Macro)

Syntax

IRQNoFlags (DescriptorName) {InterruptList} => Buffer

Arguments

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer.

InterruptList is a comma-delimited list of integers in the range 0 through 15, at least one value is required. There may be no duplicates in the list Description

The **IRQNoFlags** macro evaluates to a buffer which contains an active-high, edge-triggered IRQ resource descriptor. The format of the IRQ descriptor can be found in IRQ Descriptor (page 325). The macro produces the two-byte form of the descriptor. The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.65 LAnd (Logical And)

Syntax

LAnd (Source1, Source2) => Boolean

Arguments

Source1 and source2 are evaluated as integers.

Description

If both values are non-zero, True is returned: otherwise, False is returned.

19.5.66 LEqual (Logical Equal)

Syntax

LEqual (*Source1*, *Source2*) => Boolean

Arguments

Source1 and Source2 must each evaluate to an integer, a string, or a buffer. The data type of Source1 dictates the required type of Source2. Source2 is implicitly converted if necessary to match the type of Source1.

Description

If the values are equal, True is returned; otherwise, False is returned. For integers, a numeric compare is performed. For strings and buffers, True is returned only if both lengths are the same and the result of a byte-wise compare indicates exact equality.

19.5.67 LGreater (Logical Greater)

Syntax

LGreater (*Source1*, *Source2*) => Boolean

Arguments

Source1 and Source2 must each evaluate to an integer, a string, or a buffer. The data type of Source1 dictates the required type of Source2. Source2 is implicitly converted if necessary to match the type of Source1.

Description

If *Source1* is greater than *Source2*, True is returned; otherwise, False is returned. For integers, a numeric comparison is performed. For strings and buffers, a lexicographic comparison is performed. **True** is returned if a byte-wise (unsigned) compare discovers at least one byte in *Source1* that is numerically greater than the corresponding byte in *Source2*. **False** is returned if at least one byte in *Source1* is numerically less than the corresponding byte in *Source2*. In the case of byte-wise equality, **True** is returned if the length of *Source1* is greater than *Source2*, **False** is returned if the length of *Source1* is less than or equal to *Source2*.

19.5.68 LGreaterEqual (Logical Greater Than Or Equal)

Syntax

LGreaterEqual (*Source1*, *Source2*) => Boolean

Arguments

Source1 and Source2 must each evaluate to an integer, a string, or a buffer. The data type of Source1 dictates the required type of Source2. Source2 is implicitly converted if necessary to match the type of Source1.

Description

If *Source1* is greater than or equal to *Source2*, True is returned; otherwise, False is returned. Equivalent to LNot (LLess ()). See the description of the LLess operator.

19.5.69 LLess (Logical Less)

Syntax

LLess (Source1, Source2) => Boolean

Arguments

Source1 and Source2 must each evaluate to an integer, a string, or a buffer. The data type of Source1 dictates the required type of Source2. Source2 is implicitly converted if necessary to match the type of Source1.

Description

If *Source1* is less than *Source2*, True is returned; otherwise, False is returned. For integers, a numeric comparison is performed. For strings and buffers, a lexicographic comparison is performed. **True** is returned if a byte-wise (unsigned) compare discovers at least one byte in *Source1* that is numerically less than the corresponding byte in *Source2*. **False** is returned if at least one byte in *Source1* is numerically greater than the corresponding byte in *Source2*. In the case of byte-wise equality, **True** is returned if the length of *Source1* is less than *Source2*, **False** is returned if the length of *Source1* is greater than or equal to *Source2*.

19.5.70 LLessEqual (Logical Less Than Or Equal)

Syntax

LLessEqual (*Source1*, *Source2*) => Boolean

Arguments

Source1 and Source2 must each evaluate to an integer, a string, or a buffer. The data type of Source1 dictates the required type of Source2. Source2 is implicitly converted if necessary to match the type of Source1.

Description

If *Source1* is less than or equal to *Source2*, True is returned; otherwise False is returned. Equivalent to LNot (LGreater()). See the description of the LGreater operator.

19.5.71 LNot (Logical Not)

Syntax

LNot (*Source*) => Boolean

Arguments

Source is evaluated as an integer.

Description

If the value is zero True is returned; otherwise, False is returned.

19.5.72 LNotEqual (Logical Not Equal))

Syntax

LNotEqual (*Source1*, *Source2*) => Boolean

Arguments

Source1 and Source2 must each evaluate to an integer, a string, or a buffer. The data type of Source1 dictates the required type of Source2. Source2 is implicitly converted if necessary to match the type of Source1.

Description

If *Source1* is not equal to *Source2*, True is returned; otherwise False is returned. Equivalent to LNot (LEqual ()). See the description of the LEqual operator.

19.5.73 Load (Load Definition Block)

Syntax

Load (Object, DDBHandle)

Arguments

The *Object* parameter can either refer to an operation region field or an operation region directly. If the object is an operation region, the operation region must be in SystemMemory space. The Definition Block should contain an ACPI DESCRIPTION_HEADER of type SSDT. The Definition Block must be totally contained within the supplied operation region or operation region field. OSPM reads this table into memory, the checksum is verified, and then it is loaded into the ACPI namespace. The *DDBHandle* parameter is the handle to the Definition Block that can be used to unload the Definition Block at a future time via the Unload operator.

Description

Performs a run-time load of a Definition Block. Any table referenced by **Load** must be in memory marked as AddressRangeReserved or AddressRangeNVS.

The OS can also check the OEM Table ID and Revision ID against a database for a newer revision Definition Block of the same OEM Table ID and load it instead.

The default namespace location to load the Definition Block is relative to the root of the namespace. The new Definition Block can override this by specifying absolute names or by adjusting the namespace location using the **Scope** operator.

Loading a Definition Block is a synchronous operation. Upon completion of the operation, the Definition Block has been loaded. The control methods defined in the Definition Block are not executed during load time.

19.5.74 LoadTable (Load Definition Block From XSDT)

Syntax

LoadTable (SignatureString, OEMIDString, OEMTableIDString, RootPathString, ParameterPathString, ParameterData) => DDBHandle

Arguments

The XSDT is searched for a table where the Signature field matches SignatureString, the OEM ID field matches OEMIDString, and the OEM Table ID matches OEMTableIDString. All comparisons are case sensitive. If the SignatureString is greater than four characters, the OEMIDString is greater than six characters, or the OEMTableID is greater than eight characters, a run-time error is generated. The OS can also check the OEM Table ID and Revision ID against a database for a newer revision Definition Block of the same OEM Table ID and load it instead.

ACPI Source Language (ASL)Reference

The *RootPathString* specifies the root of the Definition Block. It is evaluated using normal scoping rules, assuming that the scope of the **LoadTable** instruction is the current scope. The new Definition Block can override this by specifying absolute names or by adjusting the namespace location using the **Scope** operator. If *RootPathString* is not specified, "\" is assumed

If ParameterPathString and ParameterData are specified, the data object specified by ParameterData is stored into the object specified by ParameterPathString after the table has been added into the namespace. If the first character of ParameterPathString is a backslash ('\') or caret ('^') character, then the path of the object is ParameterPathString. Otherwise, it is RootPathString.ParameterPathString. If the specified object does not exist, a run-time error is generated.

The handle of the loaded table is returned. If no table matches the specified signature, then 0 is returned.

Description

Performs a run-time load of a Definition Block from the XSDT. Any table referenced by **LoadTable** must be in memory marked by AddressRangeReserved or AddressRangeNVS.

Note: OSPM loads the DSDT and all SSDTs during initialization. As such, Definition Blocks to be conditionally loaded via **LoadTable** must contain signatures other than "SSDT".

Loading a Definition Block is a synchronous operation. Upon completion of the operation, the Definition Block has been loaded. The control methods defined in the Definition Block are not executed during load time.

Example

This operation would search through the RSDT or XSDT for a table with the signature "OEM1," the OEM ID of "MYOEM," and the table ID of "TABLE1." If not found, it would store **Zero** in Local0. Otherwise, it will store a package containing 0 and "_SB.PCI0" into the variable at \SB.PCI0.MYD.

19.5.75 Local x (Method Local Data Objects)

Syntax

Local0 | Local1 | Local2 | Local3 | Local4 | Local5 | Local6 | Local7

Description

Up to 8 local objects can be referenced in a control method. On entry to a control method, these objects are uninitialized and cannot be used until some value or reference is stored into the object. Once initialized, these objects are preserved in the scope of execution for that control method.

19.5.76 LOr (Logical Or)

Syntax

LOr (*Source1*, *Source2*) => Boolean

Arguments

Source1 and Source2 are evaluated as integers.

Description

If either value is non-zero, True is returned; otherwise, False is returned.

19.5.77 Match (Find Object Match)

Syntax

Match (SearchPackage, Op1, MatchObject1, Op2, MatchObject2, StartIndex) => **Ones** | Integer

Arguments

SearchPackage is evaluated to a package object and is treated as a one-dimension array. Each package element must evaluate to either an integer, a string, or a buffer. Uninitialized package elements and elements that do not evaluate to integers, strings, or buffers are ignored. Op1 and Op2 are match operators. MatchObject1 and MatchObject2 are the objects to be matched and must each evaluate to either an integer, a string, or a buffer. StartIndex is the starting index within the SearchPackage.

Description

A comparison is performed for each element of the package, starting with the index value indicated by *StartIndex* (0 is the first element). If the element of *SearchPackage* being compared against is called *P[i]*, then the comparison is:

If (P[i] Op1 MatchObject1) and (P[i] Op2 MatchObject2) then Match => i is returned.

If the comparison succeeds, the index of the element that succeeded is returned; otherwise, the constant object **Ones** is returned. The data type of the MatchObject dictates the required type of the package element. If necessary, the package element is implicitly converted to match the type of the MatchObject. If the implicit conversion fails for any reason, the package element is ignored (no match.)

Op1 and *Op2* have the values and meanings listed in the following table.

Table 19-345 Match Term Operator Meanings

Operator	Encoding	Macro
TRUE – A don't care, always returns TRUE	0	MTR
EQ - Returns TRUE if P[i] == MatchObject	1	MEQ
LE – Returns TRUE if P[i] <= MatchObject	2	MLE
LT – Returns TRUE if P[i] < MatchObject	3	MLT
GE – Returns TRUE if P[i] >= MatchObject	4	MGE

Operator	Encoding	Macro
GT – Returns TRUE if P[i] > MatchObject	5	MGT

Example

Following are some example uses of **Match**:

19.5.78 Memory24 (Memory Resource Descriptor Macro)

Syntax

Memory24 (ReadAndWrite, AddressMinimum, AddressMaximum, AddressAlignment, RangeLength, DescriptorName)

Arguments

ReadAndWrite specifies whether or not the memory region is read-only (**ReadOnly**) or read/write (**ReadWrite**). If nothing is specified, then ReadWrite is assumed. The 1-bit field DescriptorName._RW is automatically created to refer to this portion of the resource descriptor, where '1' is ReadWrite and '0' is ReadOnly.

AddressMinimum evaluates to a 16-bit integer that specifies bits [8:23] of the lowest possible base address of the memory range. All other bits are assumed to be zero. The value must be an even multiple of *AddressAlignment*. The 16-bit field *DescriptorName*._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 16-bit integer that specifies bits [8:23] of the highest possible base address of the memory range. All other bits are assumed to be zero. The value must be an even multiple of AddressAlignment. The 16-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

Address Alignment evaluates to a 16-bit integer that specifies bits [0:15] of the required alignment for the memory range. All other bits are assumed to be zero. The address selected must be an even multiple of this value. The 16-bit field *DescriptorName*. _ALN is automatically created to refer to this portion of the resource descriptor.

Advanced Configuration and Power Interface Specification

RangeLength evaluates to a 16-bit integer that specifies the total number of bytes decoded in the memory range. The 16-bit field *DescriptorName*. _LEN is automatically created to refer to this portion of the resource descriptor. The range length provides the length of the memory range in 256 byte blocks.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **Memory24** macro evaluates to a buffer which contains an 24-bit memory descriptor. The format of the 24-bit memory descriptor can be found in "24-Bit Memory Range Descriptor" (page 332). The macro is designed to be used inside of a ResourceTemplate (page 811).

Note: The use of **Memory24** is deprecated and should not be used in new designs.

19.5.79 Memory32 (Memory Resource Descriptor Macro)

Syntax

Memory32 (ReadAndWrite, AddressMinimum, AddressMaximum, AddressAlignment, RangeLength, DescriptorName)

Arguments

ReadAndWrite specifies whether or not the memory region is read-only (**ReadOnly**) or read/write (**ReadWrite**). If nothing is specified, then ReadWrite is assumed. The 1-bit field DescriptorName._RW is automatically created to refer to this portion of the resource descriptor, where '1' is ReadWrite and '0' is ReadOnly.

AddressMinimum evaluates to a 32-bit integer that specifies the lowest possible base address of the memory range. The value must be an even multiple of AddressAlignment. The 32-bit field DescriptorName. MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 32-bit integer that specifies the highest possible base address of the memory range. The value must be an even multiple of AddressAlignment. The 32-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

Address Alignment evaluates to a 32-bit integer that specifies the required alignment for the memory range. The address selected must be an even multiple of this value. The 32-bit field *DescriptorName*. _ALN is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 32-bit integer that specifies the total number of bytes decoded in the memory range. The 32-bit field *DescriptorName*. _LEN is automatically created to refer to this portion of the resource descriptor. The range length provides the length of the memory range in 1 byte blocks.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **Memory32** macro evaluates to a buffer which contains a 32-bit memory descriptor, which describes a memory range with a minimum, a maximum and an alignment. The format of the 32-bit memory descriptor can be found in "32-Bit Memory Range Descriptor" (page 333). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.80 Memory32Fixed (Memory Resource Descriptor Macro)

Syntax

Memory32Fixed (ReadAndWrite, AddressBase, RangeLength, DescriptorName)

Arguments

ReadAndWrite specifies whether or not the memory region is read-only (**ReadOnly**) or read/write (**ReadWrite**). If nothing is specified, then ReadWrite is assumed. The 1-bit field DescriptorName._RW is automatically created to refer to this portion of the resource descriptor, where '1' is ReadWrite and '0' is ReadOnly.

AddressBase evaluates to a 32-bit integer that specifies the base address of the memory range. The 32-bit field *DescriptorName*. BAS is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 32-bit integer that specifies the total number of bytes decoded in the memory range. The 32-bit field *DescriptorName*. LEN is automatically created to refer to this portion of the resource descriptor.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **Memory32Fixed** macro evaluates to a buffer which contains a 32-bit memory descriptor, which describes a fixed range of memory addresses. The format of the fixed 32-bit memory descriptor can be found in 32-Bit Fixed Memory Range Descriptor (page 335). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.81 Method (Declare Control Method)

Syntax

Method (MethodName, NumArgs, SerializeRule, SyncLevel, ReturnType, ParameterTypes) {TermList}

Arguments

MethodName is evaluated as a Namestring data type.

NumArgs is optional and is the required number of arguments to be passed to the method, evaluated as an Integer data type. If not specified, the default value is zero arguments. Up to 7 arguments may

Advanced Configuration and Power Interface Specification

be passed to a method. These arguments may be referenced from within the method as **Arg0** through **Arg6**.

SerializeRule is optional and is a flag that defines whether the method is serialized or not and is one of the following: **Serialized** or **NotSerialized**. A method that is serialized cannot be reentered by additional threads. If not specified, the default is **NotSerialized**.

SyncLevel is optional and specifies the synchronization level for the method (0-15). If not specified, the default sync level is zero.

ReturnType is optional and specifies the type(s) of the object(s) returned by the method. If the method does not return an object, then nothing is specified or **UnknownObj** is specified. To specify a single return type, simply use the *ObjectTypeKeyword* (e.g. **IntObj**, **PkgObj**, etc.). To specify multiple possible return types, enclose the comma-separated *ObjectTypeKeywords* with braces. For example: {IntObj, BuffObj}.

Parameter Types is optional and specifies the type of the method parameters. It is a commaseparated, variable-length list of the expected object type or types for each of the method parameters, enclosed in braces. For each parameter, the parameter type consists of either an Object Type Keyword or a comma-separated sub-list of Object Type Keywords enclosed in braces. If Parameter Types is specified, the number of parameters must match NumArgs.

TermList is a variable-length list of executable ASL statements representing the body of the control method.

Description

Creates a new control method of name *MethodName*. This is a named package containing a series of object references that collectively represent a control method, which is a procedure that can be invoked to perform computation. **Method** opens a name scope.

System software executes a control method by referencing the objects in the package in order. For more information on method execution, see <u>Section 5.5.2</u>, "Control Method Execution."

The current namespace location used during name creation is adjusted to be the current location on the namespace tree. Any names created within this scope are "below" the name of this package. The current namespace location is assigned to the method package, and all namespace references that occur during control method execution for this package are relative to that location.

If a method is declared as **Serialized**, an implicit mutex associated with the method object is acquired at the specified *SyncLevel*. If no *SyncLevel* is specified, *SyncLevel* 0 is assumed. The serialize rule can be used to prevent reentering of a method. This is especially useful if the method creates namespace objects. Without the serialize rule, the reentering of a method will fail when it attempts to create the same namespace object.

There are eight local variables automatically available for each method, referenced as **Local0** through **Local7**. These locals may be used to store any type of ASL object.

Also notice that all namespace objects created by a method have temporary lifetime. When method execution exits, the created objects will be destroyed.

Examples

The following block of ASL sample code shows a use of **Method** for defining a control method that turns on a power resource.

This method is an implementation of _SRS (Set Resources). It shows the use of a method argument and two method locals.

```
Method (_SRS, 1, NotSerialized)
{
    CreateWordField (Arg0, One, IRQW)
    Store (\_SB.PCI0.PID1.IENA, Local1)
    Or (IRQW, Local1, Local1)
    Store (Local1, \_SB.PCI0.PID1.IENA)
    FindSetRightBit (IRQW, Local0)
    If (Local0)
    {
        Decrement (Local0)
        Store (Local0, \_SB.PCI0.PID1.IN01)
    }
}
```

19.5.82 Mid (Extract Portion of Buffer or String)

Syntax

Mid (Source, Index, Length, Result) => Buffer or String

Arguments

Source is evaluated as either a Buffer or String. Index and Length are evaluated as Integers.

Description

If *Source* is a buffer, then *Length* bytes, starting with the *Index*th byte (zero-based) are optionally copied into *Result*. If *Index* is greater than or equal to the length of the buffer, then the result is an empty buffer. Otherwise, if *Index* + *Length* is greater than or equal to the length of the buffer, then only bytes up to and including the last byte are included in the result.

If *Source* is a string, then *Length* characters, starting with the *Index*th character (zero-based) are optionally copied into *Result*. If *Index* is greater than or equal to the length of the buffer, then the result is an empty string. Otherwise, if *Index* + *Length* is greater than or equal to the length of the string, then only bytes up to an including the last character are included in the result.

19.5.83 Mod (Integer Modulo)

Syntax

Mod (*Dividend*, *Divisor*, *Result*) => Integer

Arguments

Dividend and Divisor are evaluated as Integers.

Description

The *Dividend* is divided by *Divisor*, and then the resulting remainder is optionally stored into *Result*. If *Divisor* evaluates to zero, a fatal exception is generated.

19.5.84 Multiply (Integer Multiply)

Syntax

Multiply (*Multiplicand*, *Multiplier*, *Result*) => Integer

Arguments

Multiplicand and Multiplier are evaluated as Integers.

Description

The *Multiplicand* is multiplied by *Multiplier* and the result is optionally stored into *Result*. Overflow conditions are ignored and results are undefined.

19.5.85 Mutex (Declare Synchronization/Mutex Object)

Syntax

Mutex (MutexName, SyncLevel)

Arguments

Creates a data mutex synchronization object named *MutexName*, with a synchronization level from 0 to 15 as specified by the Integer *SyncLevel*.

Description

A synchronization object provides a control method with a mechanism for waiting for certain events. To prevent deadlocks, wherever more than one synchronization object must be owned, the synchronization objects must always be released in the order opposite the order in which they were acquired.

The *SyncLevel* parameter declares the logical nesting level of the synchronization object. The *current sync level* is maintained internally for a thread, and represents the greatest *SyncLevel* among mutex objects that are currently acquired by the thread. The *SyncLevel* of a thread before acquiring any mutexes is zero. The *SyncLevel* of the Global Lock (\ GL) is zero.

All **Acquire** terms must refer to a synchronization object with a *SyncLevel* that is equal or greater than the current level, and all **Release** terms must refer to a synchronization object with a *SyncLevel* that is equal to the current level.

Mutex synchronization provides the means for mutually exclusive ownership. Ownership is acquired using an **Acquire** term and is released using a **Release** term. Ownership of a Mutex must be relinquished before completion of any invocation. For example, the top-level control method cannot exit while still holding ownership of a Mutex. Acquiring ownership of a Mutex can be nested (can be acquired multiple times by the same thread).

19.5.86 Name (Declare Named Object)

Syntax

Name (ObjectName, Object)

Arguments

Creates a new object named *ObjectName*. Attaches *Object* to *ObjectName* in the Global ACPI namespace.

Description

Creates ObjectName in the namespace, which references the Object.

Example

The following example creates the name PTTX in the root of the namespace that references a package.

```
Name (\PTTX, // Port to Port Translate Table Package () {Package () \{0x43, 0x59\}, Package) \{0x90, 0xFF\}}
```

The following example creates the name CNT in the root of the namespace that references an integer data object with the value 5.

```
Name (\CNT, 5)
```

19.5.87 NAnd (Integer Bitwise Nand)

Syntax

NAnd (Source1, Source2, Result) => Integer

Arguments

Source1 and Source2 are evaluated as Integers.

Description

A bitwise **NAND** is performed and the result is optionally stored in *Result*.

19.5.88 NoOp Code (No Operation)

Syntax

NoOp

Description

This operation has no effect.

19.5.89 NOr (Integer Bitwise Nor)

Syntax

NOr (*Source1*, *Source2*, *Result*) => Integer

Arguments

Source1 and Source2 are evaluated as Integers.

Description

A bitwise **NOR** is performed and the result is optionally stored in *Result*.

19.5.90 Not (Integer Bitwise Not)

Syntax

Not (*Source*, *Result*) => Integer

Arguments

Source is evaluated as an integer data type.

Description

A bitwise **NOT** is performed and the result is optionally stored in *Result*.

19.5.91 Notify (Notify Object of Event)

Syntax

Notify (Object, Notification Value)

Arguments

Notifies the OS that the *NotificationValue* for the *Object* has occurred. *Object* must be a reference to a device, processor, or thermal zone object.

Description

Object type determines the notification values. For example, the notification values for a thermal zone object are different from the notification values used for a device object. Undefined notification values are treated as reserved and are ignored by the OS.

For lists of defined Notification values, see Section 5.6.6, "Device Object Notifications."

19.5.92 Offset (Change Current Field Unit Offset)

Syntax

Offset (ByteOffset)

Arguments

ByteOffset is the new offset (in bytes) for the next FieldUnit within a FieldList.

Description

The **Offset** operator is used within a *FieldList* to specify the *byteOffset* of the next defined field within its parent operation region. This can be used instead of defining the bit lengths that need to be skipped. All offsets are defined starting from zero, based at the starting address of the parent region.

19.5.93 ObjectType (Get Object Type)

Syntax

ObjectType (*Object*) => Integer

Arguments

Object is any valid object.

Description

The execution result of this operation is an integer that has the numeric value of the object type for *Object*.

The object type codes are listed in Table 18-20. Notice that if this operation is performed on an object reference such as one produced by the **Alias**, **Index**, or **RefOf** statements, the object type of the base object is returned. For typeless objects such as predefined scope names (in other words, _SB, _GPE, etc.), the type value 0 (**Uninitialized**) is returned.

Table 19-346 TValues Returned By the ObjectType Operator

Value	Object
0	Uninitialized
1	Integer
2	String
3	Buffer
4	Package
5	Field Unit
6	Device
7	Event
8	Method
9	Mutex
10	Operation Region
11	Power Resource
12	Processor
13	Thermal Zone
14	Buffer Field
15	DDB Handle
16	Debug Object
>16	Reserved

19.5.94 One (Constant One Integer)

Syntax

One=> Integer

Description

The **One** operator returns an Integer with the value 1. Writes to this object are not allowed. The use of this operator can reduce AML code size, since it is represented by a one-byte AML opcode.

19.5.95 Ones (Constant Ones Integer)

Syntax

Ones=> Integer

Description

Description

The **Ones** operator returns an Integer with all bits set to 1. Writes to this object are not allowed. The use of this operator can reduce AML code size, since it is represented by a one-byte AML opcode.

Note: The actual value of the integer returned by the **Ones** operator depends on the integer width of the DSDT. If the revision of the DSDT is 1 or less, the integer width is 32 bits and **Ones** returns 0xFFFFFFF. If the revision of the DSDT is 2 or greater, the integer width is 64 bits and **Ones** returns 0xFFFFFFFFFFFFFFFFFF. This difference must be considered when performing comparisons against the **Ones** Integer.

19.5.96 OperationRegion (Declare Operation Region)

Syntax

OperationRegion (RegionName, RegionSpace, Offset, Length)

Arguments

Declares an operation region named *RegionName*. *Offset* is the offset within the selected *RegionSpace* at which the region starts (byte-granular), and *Length* is the length of the region in bytes.

Description

An Operation Region is a type of data object where read or write operations to the data object are performed in some hardware space. For example, the Definition Block can define an Operation Region within a bus, or system I/O space. Any reads or writes to the named object will result in accesses to the I/O space.

Operation regions are regions in some space that contain hardware registers for *exclusive* use by ACPI control methods. In general, no hardware register (at least byte-granular) within the operation region accessed by an ACPI control method can be shared with any accesses from any other source, with the exception of using the Global Lock to share a region with the firmware. The entire Operation Region can be allocated for exclusive use to the ACPI subsystem in the host OS.

ACPI Source Language (ASL)Reference

Operation Regions that are defined within the scope of a method are the exception to this rule. These Operation Regions are known as "Dynamic" since the OS has no idea that they exist or what registers they use until the control method is executed. Using a Dynamic SystemIO or SystemMemory Operation Region is not recommended since the OS cannot *guarantee* exclusive access. All other types of Operation Regions may be Dynamic.

Operation Regions define the overall base address and length of a hardware region, but they cannot be accessed directly by AML code. A **Field** object containing one or more **FieldUnits** is used to overlay the Operation Region in order to access individual areas of the Region. An individual FieldUnit within an Operation Region may be as small as one bit, or as large as the length of the entire Region. FieldUnit values are normalized (shifted and masked to the proper length.) The data type of a FieldUnit can be either a **Buffer** or an **Integer**, depending on the bit length of the FieldUnit. If the FieldUnit is smaller than or equal to the size of an Integer (in bits), it will be treated as an Integer. If the FieldUnit is larger than the size of an Integer, it will be treated as a Buffer. The size of an Integer is indicated by the DSDT header's *Revision* field. A revision less than 2 indicates that the size of an Integer is 32 bits. A value greater than or equal to 2 signifies that the size of an Integer is 64 bits. For more information about data types and FieldUnit type conversion rules, see Section 19.2.5.7, "Data Type Conversion Rules".

An Operation Region object implicitly supports Mutex synchronization. Updates to the object, or a **Field** data object for the region, will automatically synchronize on the Operation Region object; however, a control method may also explicitly synchronize to a region to prevent other accesses to the region (from other control methods). Notice that according to the control method execution model, control method execution is non-preemptive. Because of this, explicit synchronization to an Operation Region needs to be done only in cases where a control method blocks or yields execution and where the type of register usage requires such synchronization.

The predefined Operation Region types specified in ACPI are shown in the table below:

Table 19-347 Predefined Operation Region types

Name (RegionSpace Keyword)	Value
SystemMemory	0
SystemIO	1
PCI_Config	2
EmbeddedControl	3
SMBus	4
SystemCMOS	5
PCIBARTarget	6
IPMI	7
GeneralPurposeIO	8
GenericSerialbus	9
Reserved	0x0A-0x7F

In addition, OEMs may define Operation Regions types **0x80** to **0xFF**.

Example

The following example ASL code shows the use of **OperationRegion** combined with **Field** to describe IDE 0 and 1 controlled through general I/O space, using one FET.

19.5.97 Or (Integer Bitwise Or)

Syntax

Or (Source1, Source2, Result) => Integer

Arguments

Source1 and Source2 are evaluated as Integers.

Description

A bitwise **OR** is performed and the result is optionally stored in *Result*.

19.5.98 Package (Declare Package Object)

Syntax

Package (NumElements) {PackageList} => Package

Arguments

NumElements is evaluated as an Integer. *PackageList* is an initializer list of objects.

Description

Declares an unnamed aggregation of data items, constants, and/or references to control methods. The size of the package is *NumElements*. *PackageList* contains the list data items, constants, and/or control method references used to initialize the package.

If *NumElements* is absent, it is set to match the number of elements in the PackageList. If *NumElements* is present and greater than the number of elements in the PackageList, the default entry of type Uninitialized (see **ObjectType**) is used to initialize the package elements beyond those initialized from the PackageList. There are two types of package elements allowed in the PackageList: Data Objects (Integers, Strings, Buffers, and Packages) and references to control methods.

Evaluating an undefined element will yield an error, but elements can be assigned values at runtime to make them defined (via the Index operator). It is an error for *NumElements* to be less than the number of elements in the PackageList..

The ASL compiler can emit two different AML opcodes for a Package declaration, either *PackageOp* or *VarPackageOp*. For small, fixed-length packages, the *PackageOp* is used and this

opcode is compatible with ACPI 1.0. A *VarPackageOp* will be emitted if any of the following conditions are true:

- The NumElements argument is a TermArg that can only be resolved at runtime.
- At compile time, *NumElements* resolves to a constant that is larger than 255.
- The *PackageList* contains more than 255 initializer elements.

Note: The ability to create variable-sized packages was first introduced in ACPI 2.0. ACPI 1.0 only allowed fixed-size packages with up to 255 elements.

Examples

Example 1:

```
Package () {
    3,
    9,
    "ACPI 1.0 COMPLIANT",
    Package () {
        "CheckSum=>",
            Package () {7, 9}
    },
    0
}
```

Example 2: This example defines and initializes a two-dimensional array.

```
Package () {
    Package () {11, 12, 13},
         Package () {21, 22, 23}
}
```

Example 3: This code allocates space for ten objects to be defined at runtime (see the **Name** and **Index** term definitions).

```
Package (10) {}
```

Example 4: These package declarations will cause the compiler to emit a *VarPackageOp* AML opcode.

```
Name (SIZE, 4)
Package (SIZE) {}
Package (1024) {}
Package (256) {}
```

19.5.99 PowerResource (Declare Power Resource)

Syntax

PowerResource (ResourceName, SystemLevel, ResourceOrder) {ObjectList}

Arguments

Declares a power resource named *ResourceName*. **PowerResource** opens a name scope.

Description

For a definition of the **PowerResource** term, see <u>Section 7.1</u>, "Declaring a Power Resource Object."

19.5.100 Processor (Declare Processor)

Syntax

Processor (ProcessorName, ProcessorID, PBlockAddress, PblockLength) {ObjectList}

Arguments

Declares a named processor object named *ProcessorName*. **Processor** opens a name scope. Each processor is required to have a unique *ProcessorID* value that is unique from any other *ProcessorID* value.

For each processor in the system, the ACPI BIOS declares one processor object in the namespace anywhere within the \SB scope. For compatibility with operating systems implementing ACPI 1.0, the processor object may also be declared under the \PR scope. An ACPI-compatible namespace may define Processor objects in either the \SB or \PR scope but not both.

PBlockAddress provides the system I/O address for the processors register block. Each processor can supply a different such address. PBlockLength is the length of the processor register block, in bytes and is either 0 (for no P_BLK) or 6. With one exception, all processors are required to have the same PBlockLength. The exception is that the boot processor can have a non-zero PBlockLength when all other processors have a zero PBlockLength. It is valid for every processor to have a PBlockLength of 0.

Description

The following block of ASL sample code shows a use of the **Processor** term.

The ObjectList is an optional list that may contain an arbitrary number of ASL Objects. Processor-specific objects that may be included in the ObjectList include _PTC, _CST, _PCT, _PSS, _PPC, _PSD, _TSD, _CSD, _PDC, _TPC, _TSS, and _OSC. These processor-specific objects can only be specified when the processor object is declared within the _SB scope. For a full definition of these objects, see <u>Section 8</u>, "Processor Configuration and Control."

19.5.101 QWordIO (QWord IO Resource Descriptor Macro)

Syntax

QWordIO (Resource Usage, IsMinFixed, IsMaxFixed, Decode, ISARanges, Address Granularity, Address Minimum, Address Maximum, Address Translation, Range Length, Resource Source Index, Resource Source, Descriptor Name, Translation Type, Translation Density)

ACPI Source Language (ASL)Reference

Arguments

ResourceUsage specifies whether the I/O range is consumed by this device (**ResourceConsumer**) or passed on to child devices (**ResourceProducer**). If nothing is specified, then ResourceConsumer is assumed.

IsMinFixed specifies whether the minimum address of this I/O range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*. _MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this I/O range is fixed (MaxFixed) or can be changed (MaxNotFixed). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field DescriptorName. _MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

Decode specifies whether or not the device decodes the I/O range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field DescriptorName. _DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

ISARanges specifies whether the I/O ranges specifies are limited to valid ISA I/O ranges (**ISAOnly**), valid non-ISA I/O ranges (**NonISAOnly**) or encompass the whole range without limitation (**EntireRange**). The 2-bit field *DescriptorName*._RNG is automatically created to refer to this portion of the resource descriptor, where '1' is NonISAOnly, '2' is ISAOnly and '0' is EntireRange.

AddressGranularity evaluates to a 64-bit integer that specifies the power-of-two boundary (- 1) on which the I/O range must be aligned. The 64-bit field *DescriptorName*. _GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 64-bit integer that specifies the lowest possible base address of the I/O range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 64-bit integer that specifies the highest possible base address of the I/O range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName. MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 64-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 64-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 64-bit integer that specifies the total number of bytes decoded in the I/O range. The 64-bit field *DescriptorName*. _LEN is automatically created to refer to this portion of the resource descriptor.

ResourceSourceIndex is an optional argument which evaluates to an 8-bit integer that specifies the resource descriptor within the object specified by ResourceSource. If this argument is specified, the ResourceSource argument must also be specified.

Advanced Configuration and Power Interface Specification

ResourceSource is an optional argument which evaluates to a string containing the path of a device which produces the pool of resources from which this I/O range is allocated. If this argument is specified, but the ResourceSourceIndex argument is not specified, a zero value is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

TranslationType is an optional argument that specifies whether the resource type on the secondary side of the bus is different (**TypeTranslation**) from that on the primary side of the bus or the same (**TypeStatic**). If TypeTranslation is specified, then the secondary side of the bus is Memory. If TypeStatic is specified, then the secondary side of the bus is I/O. If nothing is specified, then TypeStatic is assumed. The 1-bit field *DescriptorName*. _TTP is automatically created to refer to this portion of the resource descriptor, where '1' is TypeTranslation and '0' is TypeStatic. See _TTP (page 347) for more information

TranslationDensity is an optional argument that specifies whether or not the translation from the primary to secondary bus is sparse (**SparseTranslation**) or dense (**DenseTranslation**). It is only used when *TranslationType* is **TypeTranslation**. If nothing is specified, then DenseTranslation is assumed. The 1-bit field *DescriptorName*. _TRS is automatically created to refer to this portion of the resource descriptor, where '1' is SparseTranslation and '0' is DenseTranslation. See _TRS (page 348) for more information.

Description

The **QWordIO** macro evaluates to a buffer which contains a 64-bit I/O resource descriptor, which describes a range of I/O addresses. The format of the 64-bit I/O resource descriptor can be found in QWord Address Space Descriptor (page 336). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.102 QWordMemory (QWord Memory Resource Descriptor Macro)

Syntax

QWordMemory (ResourceUsage, Decode, IsMinFixed, IsMaxFixed, Cacheable, ReadAndWrite, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, ResourceSourceIndex, ResourceSource, DescriptorName, MemoryRangeType, TranslationType)

Arguments

ResourceUsage specifies whether the Memory range is consumed by this device (**ResourceConsumer**) or passed on to child devices (**ResourceProducer**). If nothing is specified, then ResourceConsumer is assumed.

Decode specifies whether or not the device decodes the Memory range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field *DescriptorName*. _DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

IsMinFixed specifies whether the minimum address of this Memory range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit

ACPI Source Language (ASL)Reference

field *DescriptorName*. _MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this Memory range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*. _MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

Cacheable specifies whether or not the memory region is cacheable (Cacheable), cacheable and write-combining (WriteCombining), cacheable and prefetchable (Prefetchable) or uncacheable (NonCacheable). If nothing is specified, then NonCacheable is assumed. The 2-bit field DescriptorName. _MEM is automatically created to refer to this portion of the resource descriptor, where '1' is Cacheable, '2' is WriteCombining, '3' is Prefetchable and '0' is NonCacheable.

ReadAndWrite specifies whether or not the memory region is read-only (**ReadOnly**) or read/write (**ReadWrite**). If nothing is specified, then ReadWrite is assumed. The 1-bit field DescriptorName._RW is automatically created to refer to this portion of the resource descriptor, where '1' is ReadWrite and '0' is ReadOnly.

AddressGranularity evaluates to a 64-bit integer that specifies the power-of-two boundary (- 1) on which the Memory range must be aligned. The 64-bit field *DescriptorName*. _GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 64-bit integer that specifies the lowest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 64-bit integer that specifies the highest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 64-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 64-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 64-bit integer that specifies the total number of bytes decoded in the Memory range. The 64-bit field *DescriptorName*. _LEN is automatically created to refer to this portion of the resource descriptor.

ResourceSourceIndex is an optional argument which evaluates to an 8-bit integer that specifies the resource descriptor within the object specified by *ResourceSource*. If this argument is specified, the *ResourceSource* argument must also be specified.

ResourceSource is an optional argument which evaluates to a string containing the path of a device which produces the pool of resources from which this Memory range is allocated. If this argument is specified, but the *ResourceSourceIndex* argument is not specified, a zero value is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current

Advanced Configuration and Power Interface Specification

resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

MemoryRangeType is an optional argument that specifies the memory usage. The memory can be marked as normal (**AddressRangeMemory**), used as ACPI NVS space (**AddressRangeNVS**), used as ACPI reclaimable space (**AddressRangeACPI**) or as system reserved

(**AddressRangeReserved**). If nothing is specified, then AddressRangeMemory is assumed. The 2-bit field *DescriptorName*. _MTP is automatically created in order to refer to this portion of the resource descriptor, where '0' is AddressRangeMemory, '1' is AddressRangeReserved, '2' is AddressRangeACPI and '3' is AddressRangeNVS.

TranslationType is an optional argument that specifies whether the resource type on the secondary side of the bus is different (**TypeTranslation**) from that on the primary side of the bus or the same (**TypeStatic**). If TypeTranslation is specified, then the secondary side of the bus is I/O. If TypeStatic is specified, then the secondary side of the bus is I/O. If nothing is specified, then TypeStatic is assumed. The 1-bit field *DescriptorName*. _TTP is automatically created to refer to this portion of the resource descriptor, where '1' is TypeTranslation and '0' is TypeStatic. See _TTP (page 347) for more information.

Description

The **QWordMemory** macro evaluates to a buffer which contains a 64-bit memory resource descriptor, which describes a range of memory addresses. The format of the 64-bit memory resource descriptor can be found in "QWord Address Space Descriptor" (page 336). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.103 QWordSpace (QWord Space Resource Descriptor Macro)

Syntax

QWordSpace (ResourceType, ResourceUsage, Decode, IsMinFixed, IsMaxFixed, TypeSpecificFlags, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, ResourceSourceIndex, ResourceSource, DescriptorName)

Arguments

ResourceType evaluates to an 8-bit integer that specifies the type of this resource. Acceptable values are 0xC0 through 0xFF.

ResourceUsage specifies whether the Memory range is consumed by this device (ResourceConsumer) or passed on to child devices (ResourceProducer). If nothing is specified, then ResourceConsumer is assumed.

Decode specifies whether or not the device decodes the Memory range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field *DescriptorName*. _DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

IsMinFixed specifies whether the minimum address of this Memory range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*. _MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

ACPI Source Language (ASL)Reference

IsMaxFixed specifies whether the maximum address of this Memory range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*. _MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

TypeSpecificFlags evaluates to an 8-bit integer. The flags are specific to the *ResourceType*.

Address Granularity evaluates to a 64-bit integer that specifies the power-of-two boundary (- 1) on which the Memory range must be aligned. The 64-bit field *DescriptorName*. _GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 64-bit integer that specifies the lowest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 64-bit integer that specifies the highest possible base address of the Memory range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 64-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 64-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 64-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 64-bit integer that specifies the total number of bytes decoded in the Memory range. The 64-bit field *DescriptorName*. LEN is automatically created to refer to this portion of the resource descriptor.

ResourceSourceIndex is an optional argument which evaluates to an 8-bit integer that specifies the resource descriptor within the object specified by *ResourceSource*. If this argument is specified, the *ResourceSource* argument must also be specified.

ResourceSource is an optional argument which evaluates to a string containing the path of a device which produces the pool of resources from which this Memory range is allocated. If this argument is specified, but the ResourceSourceIndex argument is not specified, a zero value is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **QWordSpace** macro evaluates to a buffer which contains a 64-bit Address Space resource descriptor, which describes a range of addresses. The format of the 64-bit AddressSpace descriptor can be found in "QWord Address Space Descriptor" (page 336). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.104 RawDataBuffer

Syntax

RawDataBuffer (*RDBufferSize*) {*ByteList*} => RawDataBuffer

Arguments

Declares a **RawDataBuffer** of size *RDBufferSize* and optional initial value of *ByteList*.

Description

The optional *RDBufferSize* parameter specifies the size of the buffer and must be a word constant. The initial value is specified in *Initializer* ByteList. If *RDBufferSize* is not specified, it defaults to the size of initializer. If the count is too small to hold the value specified by initializer, the initializer size is used.

Note that a RawDataBuffer is not encoded as a Buffer (Opcode, Package length bytes, etc), but rather contains only the raw bytes specified.

19.5.105 RefOf (Create Object Reference)

Syntax

RefOf (*Object*) => ObjectReference

Arguments

Object can be any object type (for example, a package, a device object, and so on).

Description

Returns an object reference to *Object*. If the *Object* does not exist, the result of a **RefOf** operation is fatal. Use the **CondRefOf** term in cases where the *Object* might not exist.

The primary purpose of **RefOf()** is to allow an object to be passed to a method as an argument to the method without the object being evaluated at the time the method was loaded.

19.5.106 Register (Generic Register Resource Descriptor Macro)

Syntax

Register (AddressSpaceKeyword, RegisterBitWidth, RegisterBitOffset, RegisterAddress, AccessSize, DescriptorName)

Arguments

AddressSpaceKeyword specifies the address space where the register exists. The register can exist in I/O space (**SystemIO**), memory (**SystemMemory**), PCI configuration space (**PCI_Config**), embedded controller space (**EmbeddedControl**), SMBus (**SMBus**), Platform Communications Channel (**PCC**), or fixed-feature hardware (**FFixedHW**). The 8-bit field *DescriptorName*. _ASI is automatically created in order to refer to this portion of the resource descriptor. See Address Space Id (page 351) for more information, including a list of valid values and their meanings.

ACPI Source Language (ASL)Reference

RegisterBitWidth evaluates to an 8-bit integer that specifies the number of bits in the register. The 8-bit field DescriptorName. _RBW is automatically created in order to refer to this portion of the resource descriptor. See _RBW (page 351) for more information.

RegisterBitOffset evaluates to an 8-bit integer that specifies the offset in bits from the start of the register indicated by RegisterAddress. The 8-bit field DescriptorName. _RBO is automatically created in order to refer to this portion of the resource descriptor. See _RBO (page 351) for more information.

RegisterAddress evaluates to a 64-bit integer that specifies the register address. The 64-bit field *DescriptorName*. _ADR is automatically created in order to refer to this portion of the resource descriptor. See ADR (page 351) for more information.

AccessSize evaluates to an 8-bit integer that specifies the size of data values used when accessing the address space as follows:

- 0 Undefined (legacy)
- 1 Byte access
- 2 Word access
- 3 DWord access
- 4 QWord access

The 8-bit field *DescriptorName*. _ASZ is automatically created in order to refer to this portion of the resource descriptor. See _ASZ (page 351) for more information. For backwards compatibility, the *AccesSize* parameter is optional when invoking the Register macro. If the *AccessSize* parameter is not supplied then the *AccessSize* field will be set to zero. In this case, OSPM will assume the access size.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **Register** macro evaluates to a buffer which contains a generic register resource descriptor. The format of the generic register resource descriptor can be found in "Generic Register Descriptor" (page 351). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.107 Release (Release a Mutex Synchronization Object)

Syntax

Release (SyncObject)

Arguments

SynchObject must be a mutex synchronization object.

Description

If the mutex object is owned by the current invocation, ownership for the Mutex is released once. It is fatal to release ownership on a Mutex unless it is currently owned. A Mutex must be totally released before an invocation completes.

19.5.108 Reset (Reset an Event Synchronization Object)

Syntax

Reset (SyncObject)

Arguments

SynchObject must be an Event synchronization object.

Description

This operator is used to reset an event synchronization object to a non-signaled state. See also the Wait and Signal function operator definitions.

19.5.109 ResourceTemplate (Resource To Buffer Conversion Macro)

Syntax

ResourceTemplate () {*ResourceMacroList*} => Buffer

Description

For a full definition of the ResourceTemplateTerm macro, see <u>Section 19.2.3</u>, "ASL Resource Templates".

19.5.110 Return (Return from Method Execution)

Syntax

Return

Return ()

Return (Arg)

Arguments

Arg is optional and can be any valid object or reference.

Description

Returns control to the invoking control method, optionally returning a copy of the object named in Arg. If no Arg object is specified, a Return(**Zero**) is generated by the ASL compiler.

Note: In the absence of an explicit **Return** () statement, the return value to the caller is undefined.

19.5.111 Revision (Constant Revision Integer)

Syntax

Revision => Integer

Description

The **Revision** operator returns an Integer containing the current revision of the AML interpreter. Writes to this object are not allowed.

19.5.112 Scope (Open Named Scope)

Syntax

Scope (Location) {ObjectList}

Arguments

Opens and assigns a base namespace scope to a collection of objects. All object names defined within the scope are created relative to *Location*. Note that *Location* does not have to be below the surrounding scope, but can refer to any location within the namespace. The **Scope** term itself does not create objects, but only locates objects within the namespace; the actual objects are created by other ASL terms.

Description

The object referred to by *Location* must already exist in the namespace and be one of the following object types that has a namespace scope associated with it:

- A predefined scope such as: \ (root), _SB, \GPE, _PR, _TZ, etc.
- Device
- Processor
- Thermal Zone
- Power Resource

The **Scope** term alters the current namespace location to the existing *Location*. This causes the defined objects within *ObjectList* to be created relative to this new location in the namespace.

Note: When creating secondary SSDTs, it is often required to use the **Scope** operator to change the namespace location in order create objects within some part of the namespace that has been defined by the main DSDT. Use the **External** operator to declare the scope location so that the ASL compiler will not issue an error for an undefined *Location*.

Examples

The following example ASL code uses the **Scope** operator and creates several objects:

```
Scope (\PCI0)
{
    Name (X, 3)
    Scope (\)
    {
        Method (RQ) {Return (0)}
    }
    Name (^Y, 4)
}
```

The created objects are placed in the ACPI namespace as shown:

```
\PCI0.X
\RQ
\Y
```

This example shows the use of **External** in conjunction with **Scope** within an SSDT:

```
DefinitionBlock ("ssdt.aml", "SSDT", 2, "X", "Y", 0x00000001)
{
    External (\_SB.PCI0, DeviceObj)

    Scope (\_SB.PCI0)
    {
     }
}
```

19.5.113 ShiftLeft (Integer Shift Left)

Syntax

ShiftLeft (*Source*, *ShiftCount*, *Result*) => Integer

Arguments

Source and ShiftCount are evaluated as Integers.

Description

Source is shifted left with the least significant bit zeroed *ShiftCount* times. The result is optionally stored into *Result*.

19.5.114 ShiftRight (Integer Shift Right)

Syntax

ShiftRight (*Source, ShiftCount, Result*) => Integer

Arguments

Source and ShiftCount are evaluated as Integers.

Description

Source is shifted right with the most significant bit zeroed *ShiftCount* times. The result is optionally stored into *Result*.

19.5.115 Signal (Signal a Synchronization Event)

Syntax

Signal (SyncObject)

Arguments

SynchObject must be an Event synchronization object.

Description

The Event object is signaled once, allowing one invocation to acquire the event.

19.5.116 SizeOf (Get Data Object Size)

Syntax

SizeOf (*ObjectName*) => Integer

Arguments

ObjectName must be a buffer, string or package object.

Description

Returns the size of a buffer, string, or package data object.

For a buffer, it returns the size in bytes of the data. For a string, it returns the size in bytes of the string, not counting the trailing NULL. For a package, it returns the number of elements. For an object reference, the size of the referenced object is returned. Other data types cause a fatal run-time error.

19.5.117 Sleep (Milliseconds Sleep)

Syntax

Sleep (MilliSeconds)

Arguments

The **Sleep** term is used to implement long-term timing requirements. Execution is delayed for at least the required number of milliseconds.

Description

The implementation of **Sleep** is to round the request up to the closest sleep time supported by the OS and relinquish the processor.

19.5.118 SPISerialBus (SPI Serial Bus Connection Resource Descriptor Macro)

Syntax

SPISerialBus (DeviceSelection, DeviceSelectionPolarity, WireMode, DataBitLength, SlaveMode, ConnectionSpeed, ClockPolarity, ClockPhase, ResourceSource, ResourceSourceIndex, ResourceUsage, DescriptorName, VendorData)

Arguments

DeviceSelection is the device selection value. This value may refer to a chip-select line, GPIO line or other line selection mechanism. _ADR is automatically created to refer to this portion of the resource descriptor.

DeviceSelectionPolarity is an optional argument and can be either PolarityHigh or PolarityLow to indicate that the device is active. PolarityLow is the default. The bit field _DPL is automatically created to refer to this portion of the resource descriptor.

WireMode is an optional argument and can be either ThreeWireMode or FourWireMode. FourWireMode is the default. The bit field name _MOD is automatically created to refer to this portion of the resource descriptor.

DataBitLength is the size, in bits, of the smallest transfer unit for this connection. _LEN is automatically created to refer to this portion of the resource descriptor.

SlaveMode is an optional argument and can be either ControllerInitiated or DeviceInitiated. ControllerInitiated is the default. The bit field name _SLV is automatically created to refer to this portion of the resource descriptor.

ConnectionSpeed is the maximum connection speed supported by this connection, in hertz. The bit field name SPE is automatically created to refer to this portion of the resource descriptor.

ClockPolarity can be either ClockPolarityLow or ClockPolarityHigh. _POL is automatically created to refer to this portion of the resource descriptor.

ClockPhase can be either ClockPhaseFirst or ClockPhaseSecond. _PHA is automatically created to refer to this portion of the resource descriptor.

ResourceSource is a string which uniquely identifies the SPI bus controller referred to by this descriptor. ResourceSource can be a fully-qualified name, a relative name or a name segment that utilizes the namespace search rules.

ResourceSourceIndex is an optional argument and is assumed to be 0 for this revision.

ResourceUsage is an optional argument and is assumed to be ResourceConsumer for this revision. DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

VendorData is an optional argument that specifies an object to be decoded by the OS driver. It is a RawDataBuffer. The bit field name _VEN is automatically created to refer to this portion of the resource descriptor.

Description

The **SPISerialBus** macro evaluates to a buffer that contains a SPI Serial Bus resource descriptor. The macro is designed to be used inside of a ResourceTemplate (see <u>Section 19.2.3</u>).

19.5.119 Stall (Stall for a Short Time)

Syntax

Stall (*MicroSeconds*)

Arguments

The **Stall** term is used to implement short-term timing requirements. Execution is delayed for at least the required number of microseconds.

Description

The implementation of **Stall** is OS-specific, but must not relinquish control of the processor. Because of this, delays longer than 100 microseconds must use **Sleep** instead of **Stall**.

19.5.120 StartDependentFn (Start Dependent Function Resource Descriptor Macro)

Syntax

StartDependentFn (CompatibilityPriority, PerformancePriority) {ResourceList}

Arguments

CompatibilityPriority indicates the relative compatibility of the configuration specified by *ResourceList* relative to the PC/AT. 0 = Good, 1 = Acceptable, 2 = Sub-optimal.

PerformancePriority indicates the relative performance of the configuration specified by *ResourceList* relative to the other configurations. 0 = Good, 1 = Acceptable, 2 = Sub-optimal.

ResourceList is a list of resources descriptors which must be selected together for this configuration.

Description

The **StartDependentFn** macro evaluates to a buffer which contains a start dependent function resource descriptor, which describes a group of resources which must be selected together. Each subsequent StartDependentFn or StartDependentFnNoPri resource descriptor introduces a new choice of resources for configuring the device, with the last choice terminated with an EndDependentFn resource descriptor. The format of the start dependent function resource descriptor can be found in "Start Dependent Functions Descriptor" (page 327). This macro generates the two-byte form of the resource descriptor. The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.121 StartDependentFnNoPri (Start Dependent Function Resource Descriptor Macro)

Syntax

StartDependentFnNoPri () {ResourceList}

Description

The **StartDependentFnNoPri** macro evaluates to a buffer which contains a start dependent function resource descriptor, which describes a group of resources which must be selected together. Each subsequent StartDependentFn or StartDependentFnNoPri resource descriptor introduces a new choice of resources for configuring the device, with the last choice terminated with an EndDependentFn resource descriptor. The format of the start dependent function resource descriptor can be found in "Start Dependent Functions Descriptor" (page 327). This macro generates the one-byte form of the resource descriptor. The macro is designed to be used inside of a ResourceTemplate (page 811).

This is similar to StartDependentFn (page 816) with both *CompatibilityPriority* and *PerformancePriority* set to 1, but is one byte shorter.

19.5.122 Store (Store an Object)

Syntax

Store (*Source*, *Destination*) => DataRefObject

Arguments

This operation evaluates *Source*, converts it to the data type of *Destination*, and writes the result into *Destination*. For information on automatic data-type conversion, see <u>Section 19.2.5</u>, "ASL Data Types."

Description

Stores to OperationRegion Field data types may relinquish the processor depending on the region type.

All stores (of any type) to the constant **Zero**, constant **One**, or constant **Ones** object are not allowed. Stores to read-only objects are fatal. The execution result of the operation depends on the type of *Destination*. For any type other than an operation region field, the execution result is the same as the data written to *Destination*. For operation region fields with an *AccessType* of **ByteAcc**, **WordAcc**, **DWordAcc**, **QWordAcc** or **AnyAcc**, the execution result is the same as the data written to *Destination* as in the normal case, but when the *AccessType* is **BufferAcc**, the operation region handler may modify the data when it is written to the *Destination* so that the execution result contains modified data.

Example

The following example creates the name CNT that references an integer data object with the value 5 and then stores CNT to Local0. After the Store operation, Local0 is an integer object with the value 5.

```
Name (CNT, 5)
Store (CNT, Local0)
```

19.5.123 Subtract (Integer Subtract)

Syntax

Subtract (*Minuend*, *Subtrahend*, *Result*) => Integer

Arguments

Minuend and Subtrahend are evaluated as Integers.

Description

Subtrahend is subtracted from *Minuend*, and the result is optionally stored into *Result*. Underflow conditions are ignored and the result simply loses the most significant bits.

19.5.124 Switch (Select Code To Execute Based On Expression)

Syntax

Switch (Expression) {CaseTermList}

Arguments

Expression is an ASL expression that evaluates to an Integer, String or Buffer.

Description

The **Switch**, **Case** and **Default** statements help simplify the creation of conditional and branching code. The **Switch** statement transfers control to a statement within the enclosed body of executable ASL code

If the **Case** *Value* is an Integer, Buffer or String, then control passes to the statement that matches the value of **Switch** (*Expression*). If the **Case** value is a Package, then control passes if any member of the package matches the **Switch** (*Value*) The **Switch** *CaseTermList* can include any number of **Case** instances, but no two **Case** *Value*s (or members of a *Value*, if *Value* is a Package) within the same **Switch** statement can have the same value.

Execution of the statement body begins at the selected TermList and proceeds until the TermList end of body or until a **Break** or **Continue** statement transfers control out of the body.

The **Default** statement is executed if no **Case** *Value* matches the value of **Switch** (*expression*). If the **Default** statement is omitted, and no **Case** match is found, none of the statements in the **Switch** body are executed. There can be at most one **Default** statement. The **Default** statement can appear anywhere in the body of the **Switch** statement.

A Case or Default term can only appear inside a Switch statement. Switch statements can be nested. (Compatibility Note) The Switch, Case, and Default terms were first introduced in ACPI 2.0. However, their implementation is backward compatible with ACPI 1.0 AML interpreters.

Example

Use of the **Switch** statement usually looks something like this:

```
Switch (expression)
{
    Case (value) {
        Statements executed if Lequal (expression, value)
    }
    Case (Package () {value, value, value}) {
        Statements executed if Lequal (expression, any value in package)
    }
    Default {
        Statements executed if expression does not equal
        any case constant-expression
}
```

Note: (Compiler Note) The following example demonstrates how the Switch statement should be translated into ACPI 1.0-compatible AML:

```
Switch (Add (ABCD(),1)
    Case (1) {
        ...statements1...
    Case (Package () {4,5,6}) {
       ...statements2...
    Default {
       ...statements3...
}
     is translated as:
Name (_T_I, 0)
                                   // Create Integer temporary variable for result
While (One)
    Store (Add (ABCD (), 1), _T_I)
    If (LEqual (_T_I, 1)) {
        ...statements1...
    Else {
    If (LNotEqual (Match (Package () {4, 5, 6}, MEQ, _T_I, MTR, 0, 0), Ones)) {
        ...statements2...
    Else {
        ...statements3...
    Break
```

The **While (One)** is emitted to enable the use of **Break** and **Continue** within the Switch statement. Temporary names emitted by the ASL compiler should appear at the top level of the method, since the Switch statement could appear within a loop and thus attempt to create the name more than once.

Note: If the ASL compiler is unable to determine the type of the expression, then it will generate a warning and assume a type of Integer. The warning will indicate that the code should use one of the type conversion operators (Such as ToInteger, ToBuffer, ToDecimalString or ToHexString).

Caution: Some of these operators are defined starting with ACPI 2.0 and as such may not be supported by ACPI 1.0b compatible interpreters.

For example:

19.5.125 ThermalZone (Declare Thermal Zone)

Syntax

ThermalZone (*ThermalZoneName*) {ObjectList}

Arguments

Declares a Thermal Zone object named *ThermalZoneName*. **ThermalZone** opens a name scope.

Each use of a **ThermalZone** term declares one thermal zone in the system. Each thermal zone in a system is required to have a unique *ThermalZoneName*.

Description

A thermal zone may be declared in the namespace anywhere within the _SB scope. For compatibility with operating systems implementing ACPI 1.0, a thermal zone may also be declared under the _TZ scope. An ACPI-compatible namespace may define Thermal Zone objects in either the \ SB or \ TZ scope but not both.

For example ASL code that uses a ThermalZone statement, see <u>Section 11</u>, "Thermal Management."

19.5.126 Timer (Get 64-Bit Timer Value)

Syntax

Timer => Integer

Description

The timer opcode returns a monotonically increasing value that can be used by ACPI methods to measure time passing, this enables speed optimization by allowing AML code to mark the passage of time independent of OS ACPI interpreter implementation.

The **Sleep** opcode can only indicate waiting for longer than the time specified.

Advanced Configuration and Power Interface Specification

The value resulting from this opcode is 64 bits. It is monotonically increasing, but it is not guaranteed that every result will be unique, i.e. two subsequent instructions may return the same value. The only guarantee is that each subsequent evaluation will be greater-than or equal to the previous ones.

The period of this timer is 100 nanoseconds. While the underlying hardware may not support this granularity, the interpreter will do the conversion from the actual timer hardware frequency into 100 nanosecond units.

Users of this opcode should realize that a value returned only represents the time at which the opcode itself executed. There is no guarantee that the next opcode in the instruction stream will execute in any particular time bound.

The OSPM can implement this using the ACPI Timer and keep track of overrun. Other implementations are possible. This provides abstraction away from chipset differences

Note: (Compatibility Note) New for ACPI 3.0

19.5.127 ToBCD (Convert Integer to BCD)

Syntax

ToBCD (*Value, Result*) => Integer

Arguments

Value is evaluated as an integer

Description

The **ToBCD** operator is used to convert *Value* from a numeric (Integer) format to a BCD format and optionally store the numeric value into *Result*.

19.5.128 ToBuffer (Convert Data to Buffer)

Syntax

ToBuffer (*Data*, *Result*) => Buffer

Arguments

Data must be an Integer, String, or Buffer data type.

Description

Data is converted to buffer type and the result is optionally stored into *Result*. If *Data* is an integer, it is converted into n bytes of buffer (where n is 4 if the definition block has defined integers as 32 bits or 8 if the definition block has defined integers as 64 bits as indicated by the Definition Block table header's Revision field), taking the least significant byte of integer as the first byte of buffer. If *Data* is a buffer, no conversion is performed. If *Data* is a string, each ASCII string character is copied to one buffer byte, including the string null terminator. A null (zero-length) string will be converted to a zero-length buffer.

19.5.129 ToDecimalString (Convert Data to Decimal String)

Syntax

ToDecimalString (*Data, Result*) => String

Arguments

Data must be an Integer, String, or Buffer data type.

Description

Data is converted to a decimal string, and the result is optionally stored into Result. If Data is already a string, no action is performed. If Data is a buffer, it is converted to a string of decimal values separated by commas. (Each byte of the buffer is converted to a single decimal value.) A zero-length buffer will be converted to a null (zero-length) string.

19.5.130 ToHexString (Convert Data to Hexadecimal String)

Syntax

ToHexString (*Data, Result*) => String

Arguments

Data must be an Integer, String, or Buffer data type.

Description

Data is converted to a hexadecimal string, and the result is optionally stored into *Result*. If *Data* is already a string, no action is performed. If *Data* is a buffer, it is converted to a string of hexadecimal values separated by commas. A zero-length buffer will be converted to a null (zero-length) string.

19.5.131 Tolnteger (Convert Data to Integer)

Syntax

ToInteger (*Data*, *Result*) => Integer

Arguments

Data must be an Integer, String, or Buffer data type.

Description

Data is converted to integer type and the result is optionally stored into Result. If Data is a string, it must be either a decimal or hexadecimal numeric string (in other words, prefixed by "0x") and the value must not exceed the maximum of an integer value. If the value is exceeding the maximum, the result of the conversion is unpredictable. A null (zero-length) string is illegal. If Data is a Buffer, the first 8 bytes of the buffer are converted to an integer, taking the first byte as the least significant byte of the integer. A zero-length buffer is illegal. If Data is an integer, no action is performed.

19.5.132 ToString (Convert Buffer To String)

Syntax

ToString (Source, Length, Result) => String

Arguments

Source is evaluated as a buffer. Length is evaluated as an integer data type.

Description

Starting with the first byte, the contents of the buffer are copied into the string until the number of characters specified by *Length* is reached or a null (0) character is found. If *Length* is not specified or is **Ones**, then the contents of the buffer are copied until a null (0) character is found. If the source buffer has a length of zero, a zero length (null terminator only) string will be created. The result is copied into the *Result*.

19.5.133 ToUUID (Convert String to UUID Macro)

Syntax

ToUUID (*AsciiString*) => Buffer

Arguments

AsciiString is evaluated as a String data type.

Description

This macro will convert an ASCII string to a 128-bit buffer. The string must have the following format:

aabbccdd-eeff-gghh-iijj-kkllmmnnoopp

where aa - pp are one byte hexadecimal numbers, made up of hexadecimal digits. The resulting buffer has the following format:

Table 19-348 UUID Buffer Format

String	Offset In Buffer
aa	3
bb	2
СС	1
dd	0
ее	5
ff	4
99	7
hh	6
ii	8
jj	9
kk	10

ACPI Source Language (ASL)Reference

String	Offset In Buffer
II	11
mm	12
nn	13
00	14
рр	15

Note: (Compatibility Note) New for ACPI 3.0

19.5.134 UARTSerialBus (UART Serial Bus Connection Resource Descriptor Macro)

Syntax

UARTSerialBus (InitialBaudRate, BitsPerByte, StopBits, LinesInUse, IsBigEndian, Parity, FlowControl, ReceiveBufferSize, TransmitBufferSize, ResourceSource, ResourceSourceIndex, ResourceUsage, DescriptorName, VendorData)

Arguments

InitialBaudRate evaluates to a 32-bit integer that specifies the default or initial connection speed in bytes per second that the device supports. The bit field _SPE is automatically created to refer to this portion of the resource descriptor.

BitsPerByte is an optional argument that specifies whether five bits (**DataBitsFive**), six bits (**DataBitsSix**), seven bits (**DataBitsSeven**), eight bits (**DataBitsEight**) or nine bits (**DataBitsNine**) contain data during transfer of a single packet or character. DataBitsEight is the default. The bit field DescriptorName._LEN is automatically created to refer to this portion of the resource descriptor.

StopBits is an optional argument that specifies whether there are two bits (**StopBitsTwo**), one and a half bits (**StopBitsOnePlusHalf**), one bit (**StopBitsOne**) or no bits (**StopBitsZero**) used to signal the end of a packet or character. StopBitsOne is the default. The bit field _STB is automatically created to refer to this portion of the resource descriptor.

LinesInUse evaluates to an integer representing 8 1-bit flags representing the presence ('1') or absence ('0') of a particular line. The bit field _LIN is automatically created to refer to this portion of the resource descriptor.

Bit Mask	UART Line
Bit 7 (0x80)	Request To Send (RTS)
Bit 6 (0x40)	Clear To Send (CTS)
Bit 5 (0x20)	Data Terminal Ready (DTR)
Bit 4 (0x10)	Data Set Ready (DSR)
Bit 3 (0x08)	Ring Indicator (RI)
Bit 2 (0x04)	Data Carrier Detect (DTD)
Bit 1 (0x02)	Reserved. Must be 0.
Bit 0 (0x01)	Reserved. Must be 0.

IsBigEndian is an optional argument that specifies whether the device is expecting big endian(BigEndian) or little endian (LittleEndian) data formats. LittleEndian is the default. The bit field _END is automatically created to refer to this portion of the resource descriptor.

Parity is an optional argument that specifies whether the type of parity bits included after the data in a packet are to be interpreted as space parity (ParityTypeSpace), mark parity (ParityTypeMark), odd parity (ParityTypeOdd), even parity (ParityTypeEven) or no parity (ParityTypeNone). ParityTypeNone is the default. The bit field PAR is automatically created to refer to this portion of the resource descriptor.

FlowControl is an optional argument that specifies whether there is hardware-based flow control (FlowControlHardware), software-based flow control (FlowControlXON) or no flow control (FlowControlNone) used when communicating with the device. FlowControlNone is the default. The bit field FLC is automatically created to refer to this portion of the resource descriptor.

ReceiveBufferSize evaluates to a 16-bit integer that specifies the upper limit in bytes of the receive buffer that can be optimally utilized while communicating with this device. The bit field_RXL is automatically created to refer to this portion of the resource descriptor.

TransmitBufferSize evaluates to a 16-bit integer that specifies the upper limit in bytes of the transmit buffer that can be optimally utilized while communicating with this device. The bit field _TXL is automatically created to refer to this portion of the resource descriptor.

ResourceSource is a string which uniquely identifies the **UART bus controller** referred to by this descriptor. *ResourceSource* can be a fully-qualified name, a relative name or a name segment that utilizes the namespace search rules.

ResourceSourceIndex is an optional argument and is assumed to be **0** for this revision.

ResourceUsage is an optional argument and is assumed to be **ResourceConsumer** for this revision.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

VendorData is an optional argument that specifies an object to be decoded by the OS driver. It is a RawDataBuffer. The bit field name _VEN is automatically created to refer to this portion of the resource descriptor.

Description

The **UARTSerialBus** macro evaluates to a buffer that contains a UART Serial Bus resource descriptor. The macro is designed to be used inside of a ResourceTemplate (see<u>Section 19.2.3</u>).

19.5.135 Unicode (String To Unicode Conversion Macro)

Syntax

Unicode (*String*) => Buffer

Arguments

This macro will convert a string to a Unicode (UTF-16) string contained in a buffer. The format of the Unicode string is 16 bits per character, with a 16-bit null terminator.

19.5.136 Unload (Unload Definition Block)

Syntax

Unload (Handle)

Arguments

Handle is evaluated as a DDBHandle data type.

Description

Performs a run-time unload of a Definition Block that was loaded using a **Load** term or **LoadTable** term. Loading or unloading a Definition Block is a synchronous operation, and no control method execution occurs during the function. On completion of the **Unload** operation, the Definition Block has been unloaded (all the namespace objects created as a result of the corresponding **Load** operation will be removed from the namespace).

19.5.137 VendorLong (Long Vendor Resource Descriptor)

Syntax

VendorLong (DescriptorName) {VendorByteList}

Arguments

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer.

VendorByteList evaluates to a comma-separated list of 8-bit integer constants, where each byte is added verbatim to the body of the VendorLong resource descriptor. A maximum of n bytes can be specified. UUID and UUID specific descriptor subtype are part of the *VendorByteList*.

Description

The **VendorLong** macro evaluates to a buffer which contains a vendor-defined resource descriptor. The format of the long form of the vendor-defined resource descriptor can be found in Vendor-Defined Descriptor (page 330). The macro is designed to be used inside of a ResourceTemplate (page 811).

This is similar to VendorShort (page 826), except that the number of allowed bytes in *VendorByteList* is 65,533 (instead of 7).

19.5.138 VendorShort (Short Vendor Resource Descriptor)

Syntax

VendorShort (DescriptorName) {VendorByteList}

Arguments

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer.

Description

The **VendorShort** macro evaluates to a buffer which contains a vendor-defined resource descriptor. The format of the short form of the vendor-defined resource descriptor can be found in "Vendor-Defined Descriptor" (page 330). The macro is designed to be used inside of a ResourceTemplate (page 811).

This is similar to VendorLong (page 826), except that the number of allowed bytes in *VendorByteList* is 7 (instead of 65,533).

19.5.139 Wait (Wait for a Synchronization Event)

Syntax

Wait (*SyncObject*, *TimeoutValue*) => Boolean

Arguments

SynchObject must be an event synchronization object. *TimeoutValue* is evaluated as an Integer. The calling method blocks while waiting for the event to be signaled.

Description

The pending signal count is decremented. If there is no pending signal count, the processor is relinquished until a signal count is posted to the Event or until at least *TimeoutValue* milliseconds have elapsed.

This operation returns a non-zero value if a timeout occurred and a signal was not acquired. A *TimeoutValue* of 0xFFFF (or greater) indicates that there is no time out and the operation will wait indefinitely.

19.5.140 While (Conditional Loop)

Syntax

While (*Predicate*) {TermList}

Arguments

Predicate is evaluated as an integer.

Description

If the *Predicate* is non-zero, the list of terms in TermList is executed. The operation repeats until the *Predicate* evaluates to zero.

Note: Creation of a named object more than once in a given scope is not allowed. As such, unconditionally creating named objects within a **While** loop must be avoided. A fatal error will be

generated on the second iteration of the loop, during the attempt to create the same named object a second time.

19.5.141 WordBusNumber (Word Bus Number Resource Descriptor Macro)

Syntax

WordBusNumber (ResourceUsage, IsMinFixed, IsMaxFixed, Decode, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, ResourceSourceIndex, ResourceSource, DescriptorName)

Arguments

ResourceUsage specifies whether the bus range is consumed by this device (**ResourceConsumer**) or passed on to child devices (**ResourceProducer**). If nothing is specified, then ResourceConsumer is assumed.

IsMinFixed specifies whether the minimum address of this bus number range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*. _MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this bus number range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*. _MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

Decode specifies whether or not the device decodes the bus number range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field *DescriptorName*. _DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

AddressGranularity evaluates to a 16-bit integer that specifies the power-of-two boundary (- 1) on which the bus number range must be aligned. The 16-bit field *DescriptorName*. _GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 16-bit integer that specifies the lowest possible bus number for the bus number range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 16-bit field DescriptorName._MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 16-bit integer that specifies the highest possible bus number for the bus number range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 16-bit field DescriptorName. MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 16-bit integer that specifies the offset to be added to a secondary bus bus number which results in the corresponding primary bus bus number. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 16-bit field DescriptorName._TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 16-bit integer that specifies the total number of bus numbers decoded in the bus number range. The 16-bit field *DescriptorName*. _LEN is automatically created to refer to this portion of the resource descriptor.

ResourceSourceIndex is an optional argument which evaluates to an 8-bit integer that specifies the resource descriptor within the object specified by *ResourceSource*. If this argument is specified, the *ResourceSource* argument must also be specified.

ResourceSource is an optional argument which evaluates to a string containing the path of a device which produces the pool of resources from which this I/O range is allocated. If this argument is specified, but the ResourceSourceIndex argument is not specified, a zero value is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **WordBusNumber** macro evaluates to a buffer which contains a 16-bit bus-number resource descriptor. The format of the 16-bit bus number resource descriptor can be found in "Word Address Space Descriptor" (page 342). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.142 WordIO (Word IO Resource Descriptor Macro)

Syntax

WordIO (Resource Usage, IsMinFixed, IsMaxFixed, Decode, ISARanges, Address Granularity, Address Minimum, Address Maximum, Address Translation, Range Length, Resource Source Index, Resource Source, Descriptor Name, Translation Type, Translation Density)

Arguments

ResourceUsage specifies whether the I/O range is consumed by this device (**ResourceConsumer**) or passed on to child devices (**ResourceProducer**). If nothing is specified, then ResourceConsumer is assumed.

IsMinFixed specifies whether the minimum address of this I/O range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*. _MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this I/O range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*. _MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

Decode specifies whether or not the device decodes the I/O range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field DescriptorName. _DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

ACPI Source Language (ASL)Reference

ISARanges specifies whether the I/O ranges specifies are limited to valid ISA I/O ranges (ISAOnly), valid non-ISA I/O ranges (NonISAOnly) or encompass the whole range without limitation (EntireRange). The 2-bit field DescriptorName._RNG is automatically created to refer to this portion of the resource descriptor, where '1' is NonISAOnly, '2' is ISAOnly and '0' is EntireRange.

AddressGranularity evaluates to a 16-bit integer that specifies the power-of-two boundary (- 1) on which the I/O range must be aligned. The 16-bit field *DescriptorName*. _GRA is automatically created to refer to this portion of the resource descriptor.

Address Minimum evaluates to a 16-bit integer that specifies the lowest possible base address of the I/O range. The value must have '0' in all bits where the corresponding bit in Address Granularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 16-bit field DescriptorName. MIN is automatically created to refer to this portion of the resource descriptor.

AddressMaximum evaluates to a 16-bit integer that specifies the highest possible base address of the I/O range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 16-bit field DescriptorName._MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 16-bit integer that specifies the offset to be added to a secondary bus I/O address which results in the corresponding primary bus I/O address. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 16-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 16-bit integer that specifies the total number of bytes decoded in the I/O range. The 16-bit field *DescriptorName*. LEN is automatically created to refer to this portion of the resource descriptor.

ResourceSourceIndex is an optional argument which evaluates to an 8-bit integer that specifies the resource descriptor within the object specified by *ResourceSource*. If this argument is specified, the *ResourceSource* argument must also be specified.

ResourceSource is an optional argument which evaluates to a string containing the path of a device which produces the pool of resources from which this I/O range is allocated. If this argument is specified, but the ResourceSourceIndex argument is not specified, a zero value is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

TranslationType is an optional argument that specifies whether the resource type on the secondary side of the bus is different (**TypeTranslation**) from that on the primary side of the bus or the same (**TypeStatic**). If TypeTranslation is specified, then the secondary side of the bus is Memory. If TypeStatic is specified, then the secondary side of the bus is I/O. If nothing is specified, then TypeStatic is assumed. The 1-bit field *DescriptorName*. _TTP is automatically created to refer to this portion of the resource descriptor, where '1' is TypeTranslation and '0' is TypeStatic. See _TTP (page 348) for more information

TranslationDensity is an optional argument that specifies whether or not the translation from the primary to secondary bus is sparse (**SparseTranslation**) or dense (**DenseTranslation**). It is only used when *TranslationType* is **TypeTranslation**. If nothing is specified, then DenseTranslation is

assumed. The 1-bit field *DescriptorName*. _TRS is automatically created to refer to this portion of the resource descriptor, where '1' is SparseTranslation and '0' is DenseTranslation. See _TRS (page 348) for more information.

Description

The **WordIO** macro evaluates to a buffer which contains a 16-bit I/O range resource descriptor. The format of the 16-bit I/O range resource descriptor can be found in "Word Address Space Descriptor" (page 342). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.143 WordSpace (Word Space Resource Descriptor Macro))

Syntax

WordSpace (ResourceType, ResourceUsage, Decode, IsMinFixed, IsMaxFixed, TypeSpecificFlags, AddressGranularity, AddressMinimum, AddressMaximum, AddressTranslation, RangeLength, ResourceSourceIndex, ResourceSource, DescriptorName)

Arguments

ResourceType evaluates to an 8-bit integer that specifies the type of this resource. Acceptable values are 0xC0 through 0xFF.

ResourceUsage specifies whether the bus range is consumed by this device (**ResourceConsumer**) or passed on to child devices (**ResourceProducer**). If nothing is specified, then ResourceConsumer is assumed.

Decode specifies whether or not the device decodes the bus number range using positive (**PosDecode**) or subtractive (**SubDecode**) decode. If nothing is specified, then PosDecode is assumed. The 1-bit field *DescriptorName*. _DEC is automatically created to refer to this portion of the resource descriptor, where '1' is SubDecode and '0' is PosDecode.

IsMinFixed specifies whether the minimum address of this bus number range is fixed (**MinFixed**) or can be changed (**MinNotFixed**). If nothing is specified, then MinNotFixed is assumed. The 1-bit field *DescriptorName*. _MIF is automatically created to refer to this portion of the resource descriptor, where '1' is MinFixed and '0' is MinNotFixed.

IsMaxFixed specifies whether the maximum address of this bus number range is fixed (**MaxFixed**) or can be changed (**MaxNotFixed**). If nothing is specified, then MaxNotFixed is assumed. The 1-bit field *DescriptorName*. _MAF is automatically created to refer to this portion of the resource descriptor, where '1' is MaxFixed and '0' is MaxNotFixed.

TypeSpecificFlags evaluates to an 8-bit integer. The flags are specific to the *ResourceType*.

AddressGranularity evaluates to a 16-bit integer that specifies the power-of-two boundary (- 1) on which the bus number range must be aligned. The 16-bit field *DescriptorName*. _GRA is automatically created to refer to this portion of the resource descriptor.

AddressMinimum evaluates to a 16-bit integer that specifies the lowest possible bus number for the bus number range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 16-bit field DescriptorName._MIN is automatically created to refer to this portion of the resource descriptor.

ACPI Source Language (ASL)Reference

AddressMaximum evaluates to a 16-bit integer that specifies the highest possible bus number for the bus number range. The value must have '0' in all bits where the corresponding bit in AddressGranularity is '1'. For bridge devices which translate addresses, this is the address on the secondary bus. The 16-bit field DescriptorName. MAX is automatically created to refer to this portion of the resource descriptor.

AddressTranslation evaluates to a 16-bit integer that specifies the offset to be added to a secondary bus bus number which results in the corresponding primary bus bus number. For all non-bridge devices or bridges which do not perform translation, this must be '0'. The 16-bit field DescriptorName. TRA is automatically created to refer to this portion of the resource descriptor.

RangeLength evaluates to a 16-bit integer that specifies the total number of bus numbers decoded in the bus number range. The 16-bit field *DescriptorName*. _LEN is automatically created to refer to this portion of the resource descriptor.

ResourceSourceIndex is an optional argument which evaluates to an 8-bit integer that specifies the resource descriptor within the object specified by ResourceSource. If this argument is specified, the ResourceSource argument must also be specified.

ResourceSource is an optional argument which evaluates to a string containing the path of a device which produces the pool of resources from which this I/O range is allocated. If this argument is specified, but the ResourceSourceIndex argument is not specified, a zero value is assumed.

DescriptorName is an optional argument that specifies a name for an integer constant that will be created in the current scope that contains the offset of this resource descriptor within the current resource template buffer. The predefined descriptor field names may be appended to this name to access individual fields within the descriptor via the Buffer Field operators.

Description

The **WordSpace** macro evaluates to a buffer which contains a 16-bit Address Space resource descriptor. The format of the 16-bit Address Space resource descriptor can be found in "Word Address Space Descriptor" (page 342). The macro is designed to be used inside of a ResourceTemplate (page 811).

19.5.144 XOr (Integer Bitwise Xor)

Syntax

XOr (*Source1*, *Source2*, *Result*) => Integer

Arguments

Source1 and Source2 are evaluated as Integers.

Description

A bitwise **XOR** is performed and the result is optionally stored into *Result*.

19.5.145 Zero (Constant Zero Integer)

Syntax

Zero => Integer

Description

The **Zero** operator returns an Integer with the value 0. Writes to this object are not allowed. The use of this operator can reduce AML code size, since it is represented by a one-byte AML opcode.

ACPI Source Language (ASL)Reference

20

ACPI Machine Language (AML) Specification

This section formally defines the ACPI Control Method Machine Language (AML) language. AML is the ACPI Control Method virtual machine language, machine code for a virtual machine that is supported by an ACPI-compatible OS. ACPI control methods can be written in AML, but humans ordinarily write control methods in ASL.

AML is the language processed by the ACPI AML interpreter. It is primarily a declarative language. It's best not to think of it as a stream of code, but rather as a set of declarations that the ACPI AML interpreter will compile into the ACPI Namespace at definition block load time. For example, notice that DefByte allocates an anonymous integer variable with a byte-size initial value in ACPI namespace, and passes in an initial value. The byte in the AML stream that defines the initial value is *not* the address of the variable's storage location.

An OEM or BIOS vendor needs to write ASL and be able to single-step AML for debugging. (Debuggers and other ACPI control method language tools are expected to be AML-level tools, not source-level tools.) An ASL translator implementer must understand how to read ASL and generate AML. An AML interpreter author must understand how to execute AML.

AML and ASL are *different languages*, though they are closely related.

All ACPI-compatible operating systems must support AML. A given user can define some arbitrary source language (to replace ASL) and write a tool to translate it to AML. However, the ACPI group will support a single translator for a single language, ASL.

20.1 Notation Conventions

The notation conventions in the table below help the reader to interpret the AML formal grammar.

Table 20-349 AML Grammar Notation Conventions

Notation Convention	Description	Example
0xdd	Refers to a byte value expressed as 2 hexadecimal digits.	0x21
Number in bold.	Denotes the encoding of the AML term.	
Term => Evaluated Type	Shows the resulting type of the evaluation of Term.	
Single quotes (' ')	Indicate constant characters.	'A' => 0x41
Term := Term Term	The term to the left of := can be expanded into the sequence of terms on the right.	aterm := bterm cterm means that aterm can be expanded into the two-term sequence of bterm followed by cterm.
Term Term Term	Terms separated from each other by spaces form an ordered list.	
Angle brackets (< >)	Used to group items.	 <c d=""> means either a b or c d.</c>

Notation Convention	Description	Example
Bar symbol ()	Separates alternatives.	aterm := bterm [cterm dterm] means the following constructs are possible: bterm cterm dterm aterm := [bterm cterm] dterm means the following constructs are possible: bterm dterm cterm dterm
Dash character (-)	Indicates a range.	1-9 means a single digit in the range 1 to 9 inclusive.
Parenthesized term following another term.	The parenthesized term is the repeat count of the previous term.	aterm(3) means aterm aterm aterm. bterm(<i>n</i>) means <i>n</i> number of bterms.

20.2 AML Grammar Definition

This section defines the byte values that make up an AML byte stream.

The AML encoding can be categorized in the following groups:

- Table and Table Header encoding
- Name objects encoding
- Data objects encoding
- Package length encoding
- Term objects encoding
- Miscellaneous objects encoding

20.2.1 Table and Table Header Encoding

```
AMLCode
                    := DefBlockHeader TermList
                 := TableSignature TableLength SpecCompliance CheckSum OemID
DefBlockHeader
                       OemTableID OemRevision CreatorID CreatorRevision
TableSignature := DWordData // As defined in section 5.2.3.
                  := DWordData // Length of the table in bytes including
TableLength
// the block header.

SpecCompliance := ByteData // The revision of the structure.

CheckSum := ByteData // Byte checksum of the entire table.
                := ByteData // Byte Greensum of the life
:= ByteData(6) // OEM ID of up to 6 characters. If the OEM
OemID
                                      // ID is shorter than 6 characters, it
                                      // can be terminated with a NULL
                                      // character.
OemTableID := ByteData(8) // OEM Table ID of up to 8 characters. If
                                      // the OEM Table ID is shorter than 8
```

```
// characters, it can be terminated with
// a NULL character.

OemRevision := DWordData // OEM Table Revision.

CreatorID := DWordData // Vendor ID of the ASL compiler.

CreatorRevision := DWordData // Revision of the ASL compiler.
```

20.2.2 Name Objects Encoding

```
:= 'A'-'Z' | '_'
LeadNameChar
             := '0'-'9'
DigitChar
              := DigitChar | LeadNameChar
NameChar
RootChar := '\'
ParentPrefixChar := \^'
`A'-'Z'
              = 0x41 - 0x5A
              = 0x5F
              = 0x30 - 0x39
= 0x5C
10'-19'
1 . . .
              = 0x5E
             := <LeadNameChar NameChar NameChar NameChar>
NameSeg
// Notice that NameSegs shorter than 4 characters are filled with
              := NameSeg | DualNamePath | MultiNamePath | NullName
DualNamePath := DualNamePrefix NameSeg NameSeg
DualNamePrefix := 0x2E
MultiNamePath := MultiNamePrefix SegCount NameSeg(SegCount)
MultiNamePrefix := 0x2F
SegCount
              := ByteData
```

Note: SegCount can be from 1 to 255. For example: MultiNamePrefix(35) is encoded as 0x2f 0x23 and followed by 35 NameSegs. So, the total encoding length will be 1 + 1 + 35*4 = 142. Notice that: **DualNamePrefix NameSeg NameSeg** has a smaller encoding than the encoding of: **MultiNamePrefix(2) NameSeg NameSeg**

```
SimpleName := NameString | ArgObj | LocalObj

SuperName := SimpleName | DebugObj | Type6Opcode

NullName := 0x00

Target := SuperName | NullName
```

20.2.3 Data Objects Encoding

```
ComputationalData := ByteConst | WordConst | DWordConst | QWordConst | String |
                  ConstObj | RevisionOp | DefBuffer
              := ComputationalData | DefPackage | DefVarPackage
DataObject
DataRefObject := DataObject | ObjectReference | DDBHandle
ByteConst
               := BytePrefix ByteData
ByteConst
BytePrefix
               = 0x0A
               := WordPrefix WordData
WordConst
WordPrefix
              = 0x0B
DWordConst
              := DWordPrefix DWordData
DWordPrefix := 0x0C
QWordConst := QWord
QWordPrefix := 0x0E
              := QWordPrefix QWordData
               := StringPrefix AsciiCharList NullChar
String
StringPrefix
           := ZeroOp | OneOp | OnesOp
:= Nothing | <ByteData ByteList>
ConstObi
ByteList
             := 0x00 - 0xFF
ByteData
              := ByteData[0:7] ByteData[8:15]
                 // 0x0000-0xFFFF
DWordData := WordData[0:15] WordData[16:31] // 0x00000000-0xFFFFFFFFF
                  // 0x00000000-0xFFFFFFF
             := DWordData[0:31] DWordData[32:63]
QWordData
NullChar
              = 0x00
              = 0x00
ZeroOp
= 0x01
```

20.2.4 Package Length Encoding

Note: The high 2 bits of the first byte reveal how many follow bytes are in the PkgLength. If the PkgLength has only one byte, bit 0 through 5 are used to encode the package length (in other words, values 0-63). If the package length value is more than 63, more than one byte must be used for the encoding in which case bit 4 and 5 of the PkgLeadByte are reserved and must be zero. If the multiple bytes encoding is used, bits 0-3 of the PkgLeadByte become the least significant 4 bits of the resulting package length value. The next ByteData will become the next

least significant 8 bits of the resulting value and so on, up to 3 ByteData bytes. Thus, the maximum package length is 2**28.

20.2.5 Term Objects Encoding

```
TermObj := NameSpaceModifierObj | NamedObj | TypelOpcode | Type2Opcode
TermList := Nothing | <TermObj TermList>

TermArg := Type2Opcode | DataObject | ArgObj | LocalObj
MethodInvocation := NameString TermArgList
TermArgList := Nothing | <TermArg TermArgList>

ObjectList := Nothing | <Object ObjectList>
Object := NameSpaceModifierObj | NamedObj
```

20.2.5.1 Namespace Modifier Objects Encoding

```
NameSpaceModifierObj := DefAlias | DefName | DefScope

DefAlias := AliasOp NameString NameString
AliasOp := 0x06

DefName := NameOp NameString DataRefObject
NameOp := 0x08

DefScope := ScopeOp PkgLength NameString TermList
ScopeOp := 0x10
```

20.2.5.2 Named Objects Encoding

```
NamedObj
               := DefBankField | DefCreateBitField | DefCreateByteField | DefCreateDWordField |
                 DefCreateField | DefCreateQWordField | DefCreateWordField | DefDataRegion |
                 DefOpRegion | DefPowerRes | DefProcessor | DefThermalZone
DefBankField := BankFieldOp PkgLength NameString NameString BankValue FieldFlags FieldList
BankFieldOp := ExtOpPrefix 0x87
BankValue
             := TermArg => Integer
FieldFlags
              := ByteData
                            // bit 0-3:
                                              AccessType
                              //
                                                0 AnyAcc
                              11
                                                     ByteAcc
                                                1
                               11
                                                2
                                                    WordAcc
                               11
                                                3
                                                    DWordAcc
                                                4 OWordAcc
                               11
                               11
                                               5 BufferAcc
                               //
                                               7-15 Reserved
                               11
                               // bit 4:
                                               LockRule
                              11
                                                0
                                                    NoLock
                                                1
                              11
                                                    Lock
                               // bit 5-6:
                                               UpdateRule
                              //
                                               0 Preserve
                              //
                                               1
                                                    WriteAsOnes
```

```
11
                                                2 WriteAsZeros
                                // bit 7:
                                               Reserved (must be 0)
:= Nothing | <FieldElement FieldList>
                   := 0x01 AccessType AccessAttrib
                   := ByteData // Bits 0:3 - Same as AccessType bits of FieldFlags.
                               // Bits 4:5 - Reserved
                               // Bits 7:6 - 0 = AccessAttrib = Normal Access Attributes
                              11
                                           1 = AccessAttrib = AttribBytes (x)
                               //
                                           2 = AccessAttrib = AttribRawBytes (x)
                               11
                                           3 = AccessAttrib = AttribRawProcessBytes (x)
                               11
                              11
                                            x' is encoded as bits 0:7 of the AccessAttrib byte.
AccessAttrib
                   := ByteData // If AccessType is BufferAcc for the SMB or
                               // GPIO OpRegions, AccessAttrib can be one of
                               // the following values:
                               11
                                       0x02 AttribOuick
                                      0x04 AttribSendReceive
                               11
                               //
                                      0x06 AttribByte
                                      0x08 AttribWord
                               //
                                      0x0A AttribBlock
0x0C AttribProces
0x0D AttribBlock
                               11
                               11
                                               AttribProcessCall
                               11
                                               AttribBlockProcessCall
                  := <0x02 NameString> | <0x02 BufferData>
ConnectField
DefCreateBitField := CreateBitFieldOp SourceBuff BitIndex NameString
CreateBitFieldOp := 0x8D
SourceBuff
                  := TermArg => Buffer
BitIndex
                   := TermArg => Integer
DefCreateByteField := CreateByteFieldOp SourceBuff ByteIndex NameString
DefCreateByteFieldOp := 0x8C := TermArg => Integer
DefCreateDWordField := CreateDWordFieldOp SourceBuff ByteIndex NameString
CreateDWordFieldOp := 0x8A
DefCreateField
                 := CreateFieldOp SourceBuff BitIndex NumBits NameString
CreateFieldOp
                   := ExtOpPrefix 0x13
NumBits
                    := TermArg => Integer
DefCreateQWordField := CreateQWordFieldOp SourceBuff ByteIndex NameString
CreateQWordFieldOp := 0x8F
DefCreateWordField := CreateWordFieldOp SourceBuff ByteIndex NameString
                  = 0x8B
CreateWordFieldOp
DefDataRegion
                   := DataRegionOp NameString TermArg TermArg TermArg
DataRegionOp
                   := ExOpPrefix 0x88
DefDevice
                   := DeviceOp PkgLength NameString ObjectList
                   := ExtOpPrefix 0x82
DeviceOp
                  := EventOp NameString
DefEvent
Event0p
                   := ExtOpPrefix 0x02
```

```
DefField
                   := FieldOp PkgLength NameString FieldFlags FieldList
FieldOp
                   := ExtOpPrefix 0x81
DefIndexField := IndexFieldOp PkgLength NameString NameString FieldFlags FieldList
IndexFieldOp
                   := ExtOpPrefix 0x86
DefMethod
                   := MethodOp PkgLength NameString MethodFlags TermList
                   = 0x14
MethodOp
                                                  ArgCount (0-7)
MethodFlags
                  := ByteData
                                  // bit 0-2:
                                  // bit 3:
                                                  SerializeFlag
                                  11
                                                   0 NotSerialized
                                                  1 Serialized
                                  // bit 4-7: SyncLevel (0x00-0x0f)
                 := MutexOp NameString SyncFlags
DefMutex
Mutex0p
                   := ExtOpPrefix 0x01
SyncFlags
                  := ByteData // bit 0-3:
                                                   SyncLevel (0x00-0x0f)
                                 // bit 4-7:
                                                  Reserved (must be 0)
DefOpRegion
                 := OpRegionOp NameString RegionSpace RegionOffset RegionLen
                 := ExtOpPrefix 0x80
OpRegionOp
RegionSpace
                  := ByteData // 0x00
                                                  SystemMemory
                                                 SystemIO
PCI_Config
EmbeddedControl
                                 // 0x01
                                 // 0x02
                                 // 0x03
                                 // 0x04
                                                   SMBus
                                                 SystemCMOS
PciBarTarget
                                 // 0x05
                                 // 0x06
                                 // 0x07
                                                  IPMI
                                 // 0x80-0xFF: User Defined
RegionOffset := TermArg => Integer
RegionLen
               := TermArg => Integer
DefPowerRes
               := PowerResOp PkqLength NameString SystemLevel ResourceOrder ObjectList
PowerResOp
               := ExtOpPrefix 0x84
SystemLevel
               := ByteData
ResourceOrder := WordData
DefProcessor := ProcessorOp PkgLength NameString ProcID PblkAddr PblkLen ObjectList ProcessorOp := ExtOpPrefix 0x83
ProcID
              := ByteData
PblkAddr
              := DWordData
PblkLen
               := ByteData
DefThermalZone := ThermalZoneOp PkgLength NameString ObjectList
ThermalZoneOp
               := ExtOpPrefix 0x85
ExtendedAccessField := 0x03 AccessType ExtendedAccessAttrib AccessLength
ExtendedAccessAttrib := ByteData
                                // 0x0B
                                                  AttribBytes
                                 // 0x0E
                                                  AttribRawBytes
                                 // 0x0F
                                                  AttribRawProcess
FieldElement
               := NamedField | ReservedField | AccessField | ExtendedAccessField |
                  ConnectField
                                 // 0x00
               := ByteData
                                                   SystemMemory
RegionSpace
                                 // 0x01
                                                  SystemIO
                                 // 0x02
                                                  PCI_Config
                                 // 0x03
                                                  EmbeddedControl
                                 // 0x04
                                                  SMBus
                                 // 0x05
                                                  SystemCMOS
```

```
// 0x06 PciBarTarget
// 0x07 IPMI
// 0x08 GeneralPurposeIO
// 0x09 GenericSerialBus
// 0x80-0xFF: User Defined
```

20.2.5.3 Type 1 Opcodes Encoding

```
:= DefBreak | DefBreakPoint | DefContinue | DefFatal | DefIfElse |
Type10pcode
                 DefLoad | DefNoop | DefNotify | DefRelease | DefReset | DefReturn |
                 DefSignal | DefSleep | DefStall | DefUnload | DefWhile
DefBreak
              := BreakOp
BreakOp
              = 0xA5
BreakPointOp
DefContinue := ContinueOp
              := 0x9F
ContinueOp
         := Nothing | <ElseOp PkgLength TermList>
DefElse
              = 0xA1
DefFatal := FatalOp FatalType FatalCode FatalArg
FatalOp := ExtOpPrefix 0x32
         := ByteData
:= DWordData
FatalType
FatalCode
              := TermArg => Integer
FatalArg
          := IfOp PkgLength Predicate TermList DefElse
DefIfElse
             = 0xA0
Predicate
              := TermArg => Integer
DefLoad := LoadOp NameString DDBHandleObject
LoadOp := ExtOpPrefix 0x20
DDBHandleObject := SuperName
              := NoopOp
DefNoop
NoopOp
              = 0xA3
DefNotify
          := NotifyOp NotifyObject NotifyValue
:= 0x86
NotifyOp
NotifyObject := SuperName => ThermalZone | Processor | Device
NotifyValue
              := TermArg => Integer
:= ReleaseOp MutexObject
:= ReturnOp ArgObject
:= 0xA4
DefReturn
ArgObject
              := TermArg => DataRefObject
```

```
:= SleepOp MsecTime
DefSleep
             := ExtOpPrefix 0x22
SleepOp
MsecTime
                := TermArg => Integer
DefStall := StallOp UsecTime
StallOp := ExtOpPrefix 0x21
                := TermArg => ByteData
UsecTime
DefUnload := UnloadOp DDBHandleObject
UnloadOp
                := ExtOpPrefix 0x2A
DefWhile
               := WhileOp PkgLength Predicate TermList
WhileOp
                = 0xA2
```

20.2.5.4 Type 2 Opcodes Encoding

```
:= DefAcquire | DefAdd | DefAnd | DefBuffer | DefConcat |
                   DefConcatRes | DefCondRefOf | DefCopyObject | DefDecrement |
                    DefDerefOf | DefDivide | DefFindSetLeftBit | DefFindSetRightBit |
                    DefFromBCD | DefIncrement | DefIndex | DefLAnd | DefLEqual |
                    DefLGreater | DefLGreaterEqual | DefLLess | DefLLessEqual | DefMid |
                    DefLNot | DefLNotEqual | DefLoadTable | DefLOr | DefMatch | DefMod |
                    DefMultiply | DefNAnd | DefNOr | DefNot | DefObjectType | DefOr |
                    DefPackage | DefVarPackage | DefRefOf | DefShiftLeft | DefShiftRight |
                    DefSizeOf | DefStore | DefSubtract | DefTimer | DefToBCD | DefToBuffer |
                    DefToDecimalString | DefToHexString | DefToInteger | DefToString |
                    DefWait | DefXOr | MethodInvocation
Type60pcode
                 := DefRefOf | DefDerefOf | DefIndex | UserTermObj
                 := AcquireOp MutexObject Timeout
DefAcquire
AcquireOp
                 := ExtOpPrefix 0x23
                 := WordData
Timeout
DefAdd
             := AddOp Operand Operand Target
                 = 0x72
Add0p
Operand
                := TermArg => Integer
              := AndOp Operand Operand Target
DefAnd
                 = 0x7B
DefBuffer
                := BufferOp PkgLength BufferSize ByteList
BufferOp
                  := 0x11
BufferSize
                  := TermArg => Integer
DefConcat
                 := ConcatOp Data Data Target
                = 0x73
ConcatOp
                 := TermArg => ComputationalData
Data
DefConcatRes := ConcatResOp BufData BufData Target
ConcatResOp
                = 0x84
BufData
                 := TermArg => Buffer
DefCondRefOf := CondRefOfOp SuperName Target
CondRefOfOp
                  := ExtOpPrefix 0x12
DefCopyObject := CopyObjectOp TermArg SimpleName
CopyObjectOp := 0x9D
```

DefDecrement := DecrementOp SuperName

DecrementOp = 0x76

:= DerefOfOp ObjReference DefDerefOf

Deref0f0p

:= DivideOp Dividend Divisor Remainder Quotient
:= 0x78 DefDivide

DivideOp

Dividend := TermArg => Integer := TermArg => Integer

Divisor Remainder := Target Quotient := Target

DefFindSetLeftBit := FindSetLeftBitOp Operand Target

FindSetLeftBitOp = 0x81

DefFindSetRightBit := FindSetRightBitOp Operand Target

FindSetRightBitOp := 0x82

DefFromBCD

:= FromBCDOp BCDValue Target
:= ExtOpPrefix 0x28
:- mage DefFromECDOp BCDValue := TermArg => Integer

DefIncrement := IncrementOp SuperName
IncrementOp := 0x75

DefIndex := IndexOp BuffPkgStrObj IndexValue Target
IndexOp := 0x88
BuffPkgStrObj := TermArg => Buffer, Package or String
IndexValue := TermArg => Integer

DefLAnd := LandOp Operand Operand

Land0p = 0x90

:= LequalOp Operand Operand DefLEqual

= 0x93LequalOp

DefLGreater := LgreaterOp Operand Operand

Lgreater0p = 0x94

DefLGreaterEqual := LgreaterEqualOp Operand Operand

LgreaterEqualOp := LnotOp LlessOp

:= LlessOp Operand Operand DefLLess

= 0x95LlessOp

:= LnotOp Operand DefLNot

LnotOp = 0x92

DefLNotEqual := LnotEqualOp Operand Operand

LnotEqualOp := LnotOp LequalOp

DefLoadTable := LoadTableOp := ExtOpPrefix 0x1F := LoadTableOp TermArg TermArg TermArg TermArg TermArg

DefLOr := LorOp Operand Operand

Lor0p = 0x91

```
:= MatchOp SearchPkg MatchOpcode Operand MatchOpcode Operand StartIndex
DefMatch
MatchOp
                 = 0x89
SearchPkg
                := TermArg => Package
MatchOpcode
                               // 0
                                        MTR
                := ByteData
                                 // 1
                                 // 2
                                        MLE
                                 // 3
                                        MLT
                                 // 4 MGE
                                 // 5
                                      MGT
StartIndex
                := TermArg => Integer
DefMid
                 := MidOp MidObj TermArg TermArg Target
Mid0p
                  = 0x9E
MidObj
                  := TermArg => Buffer | String
                 := ModOp Dividend Divisor Target
DefMod
Mod0p
                 = 0x85
DefMultiply
                := MultiplyOp Operand Operand Target
MultiplyOp
                 = 0x77
DefNAnd
                 := NandOp Operand Operand Target
Nand0p
                  = 0x7C
               := NorOp Operand Operand Target
DefNOr
NorOp
                 = 0x7E
              := NotOp Operand Target
DefNot
NotOp
                 = 0x80
DefObjectType
                := ObjectTypeOp <SimpleName | DebugObj |
                       DefRefOf | DefDerefOf | DefIndex>
ObjectTypeOp
                 = 0x8E
DefOr
                 := OrOp Operand Operand Target
                  = 0x7D
OrOp
PackageOp PkgLength NumElements PackageElementList

PackageOp := 0x12

DefVarPackage := VarPackageOp PkgLength VarNumElements PackageElementList

VarPackageOp := 0x13

NumElements := 0x13
NumElements := ByteData
VarNumElements := TermArg => Integer
PackageElementList := Nothing | <PackageElement PackageElementList>
PackageElement := DataRefObject | NameString
              := RefOfOp SuperName
DefRefOf
Ref0f0p
                  = 0x71
ShiftCount
                  := TermArg => Integer
                 := ShiftRightOp Operand ShiftCount Target
DefShiftRight
ShiftRightOp
                 = 0x7A
DefSizeOf
                 := SizeOfOp SuperName
SizeOfOp
                 = 0x87
```

```
DefStore := StoreOp TermArg SuperName
StoreOp
                  = 0x70
DefSubtract := SubtractOp Operand Operand Target
SubtractOp
                  = 0x74
DefTimer := TimerOp
TimerOp := 0x5B 0x33
DefToBCD := ToBCDOp Operand Target
ToBCDOn := FytOpPrefix 0v20
                   := ExtOpPrefix 0x29
DefToBuffer := ToBufferOp Operand Target
ToBufferOp
                    = 0x96
DefToDecimalString := ToDecimalStringOp Operand Target
ToDecimalStringOp := 0x97
DefToHexString := ToHexStringOp Operand Target
ToHexStringOp := 0x98
DefToInteger := ToIntegerOp Operand Target
ToIntegerOp := 0x99
DefToString := ToStringOp TermArg LengthArg Target
LengthArg := TermArg => Integer
ToStringOp := 0x9C
DefWait
               := WaitOp EventObject Operand
:= ExtOpPrefix 0x25
DefXOr := XorOp Operand Operand Target
                     = 0x7F
XorOp
```

20.2.6 Miscellaneous Objects Encoding

Miscellaneous objects include:

- Arg objects
- Local objects
- Debug objects

20.2.6.1 Arg Objects Encoding

```
ArgObj := ArgOop | Arglop | Arg2Op | Arg3Op | Arg4Op | Arg5Op | Arg6Op
ArgOop := 0x68
Arg1Op := 0x69
Arg2Op := 0x6A
Arg3Op := 0x6B
Arg4Op := 0x6C
Arg5Op := 0x6D
Arg6Op := 0x6E
```

20.2.6.2 Local Objects Encoding

```
:= Local00p | Local10p | Local20p | Local30p | Local40p | Local50p | Local60p |
Local70p
Local00p
          = 0x60
Local10p
         := 0x61
Local20p
         = 0x62
Local30p
         = 0x63
Local40p
         = 0x64
         := 0x65
Local50p
         = 0x66
= 0x67
Local60p
Local70p
```

20.2.6.3 Debug Objects Encoding

```
DebugObj := DebugOp
DebugOp := ExtOpPrefix 0x31
```

20.3 AML Byte Stream Byte Values

The following table lists all the byte values that can be found in an AML byte stream and the meaning of each byte value. This table is useful for debugging AML code.

Table 20-350 AML Byte Stream Byte Values

Encoding	Encoding Name	Encoding	Fixed List	Variable List Arguments
Value		Group	Arguments	
0x00	ZeroOp	Data Object	_	_
0x01	OneOp	Data Object	_	_
0x02-0x05	_	_	_	_
0x06	AliasOp	Term Object	NameString NameString	_
0x07	_	_	_	_
0x08	NameOp	Term Object	NameString DataRefObject	_
0x09	_	_	_	_
0x0A	BytePrefix	Data Object	ByteData	_
0x0B	WordPrefix	Data Object	WordData	_
0x0C	DWordPrefix	Data Object	DWordData	_
0x0D	StringPrefix	Data Object	AsciiCharList NullChar	_
0x0E	QWordPrefix	Data Object	QWordData	_
0x0F	_	_	_	_
0x10	ScopeOp	Term Object	NameString	TermList
0x11	BufferOp	Term Object	TermArg	ByteList
0x12	PackageOp	Term Object	ByteData	Package TermList
0x13	VarPackageOp	Term Object	TermArg	Package TermList

Encoding Value	Encoding Name	Encoding Group	Fixed List Arguments	Variable List Arguments
0x14	MethodOp	Term Object	NameString ByteData	TermList
0x15-0x2D	_	_	_	_
0x2E ('.')	DualNamePrefix	Name Object	NameSeg NameSeg	_
0x2F ('/')	MultiNamePrefix	Name Object	ByteData NameSeg(N)	_
0x30-0x39 ('0'-'9')	DigitChar—	Name Object—	_	_
0x3A-0x40	_	_	_	_
0x41-0x5A ('A'-'Z')	NameChar	Name Object	_	_
0x5B ('[')	ExtOpPrefix	_	ByteData	_
0x5B 0x00		_	_	_
0x5B 0x01	MutexOp	Term Object	NameString ByteData	_
0x5B 0x02	EventOp	Term Object	NameString	_
0x5B 0x12	CondRefOfOp	Term Object	SuperName SuperName	_
0x5B 0x13	CreateFieldOp	Term Object	TermArg TermArg TermArg NameString	_
0x5B 0x1F	LoadTableOp	Term Object	TermArg TermArg TermArg TermArg TermArg TermArg	_
0x5B 0x20	LoadOp	Term Object	NameString SuperName	_
0x5B 0x21	StallOp	Term Object	TermArg	_
0x5B 0x22	SleepOp	Term Object	TermArg	_
0x5B 0x23	AcquireOp	Term Object	SuperName WordData	_
0x5B 0x24	SignalOp	Term Object	SuperName	_
0x5B 0x25	WaitOp	Term Object	SuperName TermArg	_
0x5B 0x26	ResetOp	Term Object	SuperName	_
0x5B 0x27	ReleaseOp	Term Object	SuperName	_
0x5B 0x28	FromBCDOp	Term Object	TermArg Target	_
0x5B 0x29	ToBCD	Term Object	TermArg Target	_

Encoding Value	Encoding Name	Encoding Group	Fixed List Arguments	Variable List Arguments
0x5B 0x2A	UnloadOp	Term Object	SuperName	_
0x5B 0x30	RevisionOp	Data Object	_	_
0x5B 0x31	DebugOp	Debug Object	_	_
0x5B 0x32	FatalOp	Term Object	ByteData DWordData TermArg	_
0x5B 0x33	TimerOp	Term Object	_	_
0x5B 0x80	OpRegionOp	Term Object	NameString ByteData TermArg TermArg	_
0x5B 0x81	FieldOp	Term Object	NameString ByteData	FieldList
0x5B 0x82	DeviceOp	Term Object	NameString	ObjectList
0x5B 0x83	ProcessorOp	Term Object	NameString ByteData DWordData ByteData	ObjectList
0x5B 0x84	PowerResOp	Term Object	NameString ByteData WordData	ObjectList
0x5B 0x85	ThermalZoneOp	Term Object	NameString	ObjectList
0x5B 0x86	IndexFieldOp	Term Object	NameString NameString ByteData	FieldList
0x5B 0x87	BankFieldOp	Term Object	NameString NameString TermArg ByteData	FieldList
0x5B 0x88	DataRegionOp	Term Object	NameString TermArg TermArg TermArg	_
0x5B 0x80 - 0x5B 0xFF	_	_	_	_
0x5C ('\')	RootChar	Name Object	_	_
0x5D	_	_	_	_
0x5E ('^')	ParentPrefixChar	Name Object	_	_
0x5F('_')	NameChar—	Name Object	_	_
0x60 (``')	Local0Op	Local Object	_	_
0x61 ('a')	Local1Op	Local Object	_	_
0x62 ('b')	Local2Op	Local Object	_	_
0x63 ('c')	Local3Op	Local Object	_	_

Encoding Value	Encoding Name	Encoding Group	Fixed List Arguments	Variable List Arguments
0x64 ('d')	Local4Op	Local Object	_	_
0x65 ('e')	Local5Op	Local Object	_	_
0x66 ('f')	Local6Op	Local Object	_	_
0x67 ('g')	Local7Op	Local Object	_	_
0x68 ('h')	Arg0Op	Arg Object	_	_
0x69 ('i')	Arg1Op	Arg Object	_	_
0x6A ('j')	Arg2Op	Arg Object	_	_
0x6B ('k')	Arg3Op	Arg Object	_	_
0x6C ('l')	Arg4Op	Arg Object	_	_
0x6D ('m')	Arg5Op	Arg Object	_	_
0x6E ('n')	Arg6Op	Arg Object	_	_
0x6F	_	_	_	_
0x70	StoreOp	Term Object	TermArg SuperName	_
0x71	RefOfOp	Term Object	SuperName	_
0x72	AddOp	Term Object	TermArg TermArg Target	_
0x73	ConcatOp	Term Object	TermArg TermArg Target	_
0x74	SubtractOp	Term Object	TermArg TermArg Target	_
0x75	IncrementOp	Term Object	SuperName	_
0x76	DecrementOp	Term Object	SuperName	_
0x77	MultiplyOp	Term Object	TermArg TermArg Target	_
0x78	DivideOp	Term Object	TermArg TermArg Target Target	_
0x79	ShiftLeftOp	Term Object	TermArg TermArg Target	_
0x7A	ShiftRightOp	Term Object	TermArg TermArg Target	_
0x7B	AndOp	Term Object	TermArg TermArg Target	_
0x7C	NandOp	Term Object	TermArg TermArg Target	_
0x7D	OrOp	Term Object	TermArg TermArg Target	_
0x7E	NorOp	Term Object	TermArg TermArg Target	_

Encoding Value	Encoding Name	Encoding Group	Fixed List Arguments	Variable List Arguments
0x7F	XorOp	Term Object	TermArg TermArg Target	_
0x80	NotOp	Term Object	TermArg Target	_
0x81	FindSetLeftBitOp	Term Object	TermArg Target	_
0x82	FindSetRightBitOp	Term Object	TermArg Target	_
0x83	DerefOfOp	Term Object	TermArg	_
0x84	ConcatResOp	Term Object	TermArg TermArg Target	_
0x85	ModOp	Term Object	TermArg TermArg Target	_
0x86	NotifyOp	Term Object	SuperName TermArg	_
0x87	SizeOfOp	Term Object	SuperName	_
0x88	IndexOp	Term Object	TermArg TermArg Target	_
0x89	MatchOp	Term Object	TermArg ByteData TermArg ByteData TermArg TermArg TermArg	_
0x8A	CreateDWordFieldOp	Term Object	TermArg TermArg NameString	_
0x8B	CreateWordFieldOp	Term Object	TermArg TermArg NameString	_
0x8C	CreateByteFieldOp	Term Object	TermArg TermArg NameString	_
0x8D	CreateBitFieldOp	Term Object	TermArg TermArg NameString	_
0x8E	ObjectTypeOp	Term Object	SuperName	_
0x8F	CreateQWordFieldOp	Term Object	TermArg TermArg NameString	_
0x90	LandOp	Term Object	TermArg TermArg	_
0x91	LorOp	Term Object	TermArg TermArg	_
0x92	LnotOp	Term Object	TermArg	_

Encoding Value	Encoding Name	Encoding Group	Fixed List Arguments	Variable List Arguments
0x92 0x93	LNotEqualOp	Term Object	TermArg TermArg	_
0x92 0x94	LLessEqualOp	Term Object	TermArg TermArg	_
0x92 0x95	LGreaterEqualOp	Term Object	TermArg TermArg	_
0x93	LEqualOp	Term Object	TermArg TermArg	_
0x94	LGreaterOp	Term Object	TermArg TermArg	_
0x95	LLessOp	Term Object	TermArg TermArg	_
0x96	ToBufferOp	Term Object	TermArg Target	_
0x97	ToDecimalStringOp	Term Object	TermArg Target	_
0x98	ToHexStringOp	Term Object	TermArg Target	_
0x99	ToIntegerOp	Term Object	TermArg Target	_
0x9A-0x9B	_	_	_	_
0x9C	ToStringOp	Term Object	TermArg TermArg Target	_
0x9D	CopyObjectOp	Term Object	TermArg SimpleName	_
0x9E	MidOp	Term Object	TermArg TermArg TermArg Target	_
0x9F	ContinueOp	Term Object	_	_
0xA0	IfOp	Term Object	TermArg	TermList
0xA1	ElseOp	Term Object	_	TermList
0xA2	WhileOp	Term Object	TermArg	TermList
0xA3	NoopOp	Term Object	_	_
0xA4	ReturnOp	Term Object	TermArg	_
0xA5	BreakOp	Term Object		_
0xA6-0xCB	_	_	_	_
0xCC	BreakPointOp	Term Object	_	_
0xCD-0xFE	_	_	_	_
0xFF	OnesOp	Data Object	_	_

20.4 AML Encoding of Names in the Namespace

Assume the following namespace exists:

```
SO

MEM

SET

GET

S1

MEM

SET

GET

CPU

SET

GET
```

Assume further that a definition block is loaded that creates a node \S0.CPU.SET, and loads a block using it as a root. Assume the loaded block contains the following names:

```
STP1
    ^GET
    ^^PCIO
    ^^PCIO.SBS
    \S2.ISA.COM1
    ^^^S3
    ^^^S2.MEM
    ^^^S2.MEM.SET
    Scope(\S0.CPU.SET.STP1) {
       XYZ
        ^ABC
        ^ABC.DEF
    }
     This will be encoded in AML as:
'STP1'
ParentPrefixChar 'GET_'
ParentPrefixChar ParentPrefixChar 'PCI0'
ParentPrefixChar ParentPrefixChar DualNamePrefix 'PCI0' 'SBS_'
RootChar 'S2__'
RootChar MultiNamePrefix 3 'S2__' 'ISA_' 'COM1'
ParentPrefixChar ParentPrefixChar ParentPrefixChar 'S3__'
ParentPrefixChar ParentPrefixChar ParentPrefixChar DualNamePrefix 'S2__' 'MEM_'
ParentPrefixChar ParentPrefixChar MultiNamePrefix 3 'S2__' 'MEM_'
```

After the block is loaded, the namespace will look like this (names added to the namespace by the loading operation are shown in bold):

```
S0
    MEM
        SET
        GET
    CPU
        SET
            STP1
                 XYZ
            ABC
                 DEF
        GET
    PCI0
        SBS
S1
    MEM
        SET
        GET
    CPU
        SET
        GET
S2
    ISA
        COM1
    MEM
        SET
```

S3

21

ACPI Data Tables and Table Definition Language

There are two fundamental types of ACPI tables:

- Tables that contain AML code produced from the ACPI Source Language (ASL). These include the DSDT, any SSDTs, and sometimes OEM-specific tables (OEMx).
- Tables that contain simple data and no AML byte code. These types of tables are known as ACPI
 Data Tables. They include tables such as the FADT, MADT, ECDT, SRAT, etc. essentially
 any table other than a DSDT or SSDT.
- The first type of table is generated using an ASL compiler and this language is specified in section 18.

The second type of table, the ACPI Data Table, is addressed by this section.

This section describes a simple language (the Table Definition Language or TDL) that can be used to generate any ACPI data table. It simplifies the table generation for BIOS vendors and can automatically generate fields such as table lengths, subtable lengths, checksums, flag fields, etc.

21.1 Types of ACPI Data Tables

In the context of a compiler for the Table Definition Language (TDL), there are two types of ACPI Data Tables:

- ACPI tables that are "known" to the compiler. These would typically include all of the basic ACPI tables defined in the ACPI specification such as the FADT, MADT, ECDT, etc. Since these tables are fully specified (usually via the ACPI specification, but from other sources as well), the TDL compiler knows all details of these tables -- including all required data types, ¹optional or required sub-tables, etc.
- ACPI tables that are unknown to the compiler. These may include tables that are not defined in the ACPI specification such as MCFG, DBGP, etc., or simply new ACPI tables that have not yet been implemented in the compiler.

One of the goals of the ACPI Table Definition Language is to support both cases above. Most ACPI tables will be known to the compiler (and will be the easiest to specify in TDL), but the language is general enough to allow the definition of new ACPI tables that are unknown or unimplemented in the compiler.

An additional goal of TDL is to support the output of a disassembler that formats an existing table into TDL. This enables disassembler/change/compile operations.

1.

21.2 ACPI Table Definition Language Specification

The following section defines the ACPI Table Definition Language (TDL). The grammar notation follows the same rules as the ASL source language (See Section 19.1.1, ASL Grammar Notation.) Full definition of the various data types follows the grammar specification.

21.2.1 Overview of the Table Definition Language (TDL)

Most ACPI tables share the following structure (all except FACS):

- A common, 36 byte header containing the table signature, length, checksum, revision, and other data.
- A table body which contains the specific table data.

The Table Definition Language allows the definition of an ACPI table via a collection of *fields*. Each line of TDL source code is a field, and corresponds to a single data item in the definition of the table.

For example, the C definition of the common ACPI table header is as follows:

```
typedef struct acpi_table_header
   char
                          Signature[4];
                        Length;
   UINT32
                         Revision;
   UINT8
   UINT8
                         Checksum;
   char
                         OemId[6];
                        OemTableId[8];
   char
   UINT32
                        OemRevision;
   char
                        AslCompilerId[4];
   UINT32
                        AslCompilerRevision;
} ACPI_TABLE_HEADER;
```

In the Table Definition Language, an ACPI table header can be described as follows:

```
: "ECDT"
: 00000000
: 01
: 00
: "OEM "
: "MACHINE1"
: 00000001
: ""
```

Additionally and optionally, it can also be described with accompanying field names:

```
Signature : "ECDT" [Embedded Controller Boot Resources Table]
Table Length : 00000000
Revision : 01
Checksum : 00
Oem ID : "OEM "
Oem Table ID : "MACHINE1"
Oem Revision : 00000001
Asl Compiler ID : ""
Asl Compiler Revision : 00000000
```

Note: In the ACPI table header, the TableLength, Checksum, AslCompilerId, and the AslCompilerRevision fields are all output fields that are filled in automatically by the compiler during table generation. Also, the field names are output by a disassembler that formats existing tables into TDL code.

21.2.2 TDL Grammar Specification

```
// Root Term
11
DataTable :=
FieldList
// Field Terms
11
FieldList :=
    Field
     <Field FieldList>
     <FieldDefinition OptionalFieldComment> |
     CommentField
FieldDefinition :=
     // Fields for predefined (known) ACPI tables
     <OptionalFieldName ':' FieldValue> |
     // Generic data types (used for custom or undefined ACPI tables)
     <'UINT8' ':' IntegerExpression> | // 8-bit unsigned integer <'UINT16' ':' IntegerExpression> | // 16-bit unsigned integer
     <'UINT24' ':' IntegerExpression> | // 24-bit unsigned integer
     <'UINT32' ':' IntegerExpression> | // 32-bit unsigned integer
     <'UINT40' ':' IntegerExpression> | // 40-bit unsigned integer
     <'UINT48' ':' IntegerExpression> | // 48-bit unsigned integer
     <'Label' ':' Label>
                                         // ASCII label - unquoted string
OptionalFieldName :=
     Nothing |
     AsciiCharList
                                         // Optional field name/description
FieldValue :=
     IntegerExpression | String | Buffer | Flags | Label
OptionalFieldComment :=
     Nothing
     <'[' AsciiCharList ']'>
```

```
CommentField :=
     <'//' AsciiCharList NewLine> |
     <'/*' AsciiCharList '*/'> |
     <'[' AsciiCharList ']'>
// Data Expressions
11
IntegerExpression :=
     <IntegerExpression IntegerOperator IntegerExpression> |
     <'(' IntegerExpression ')'>
// Operators below are shown in precedence order. The precedence rules
// are the same as the C language. Parentheses have precedence over
// all operators.
11
IntegerOperator :=
     '&&' | ' | | ' |
// Data Types
11
String :=
    <'"' AsciiCharList '"'>
Buffer :=
    ByteConstList
Guid :=
    <DWordConst '-' WordConst '-' WordConst '-' Const48>
Label :=
    AsciiCharList
//
// Data Terms
11
    ByteConst | WordConst | Const24 | DWordConst | Const40 | Const48 | Const56 |
     QWordConst | LabelReference
LabelReference :=
     <'$' Label>
Flags :=
    OneBit | TwoBits
ByteConstList :=
     ByteConst
     <Byte Const ' ' ByteConstList>
AsciiCharList :=
    Nothing
     PrintableAsciiChar
     <PrintableAsciiChar AsciiCharList>
// Terminals
```

```
ByteConst :=
     0x00-0xFF
WordConst :=
     0 \times 00000 - 0 \times FFFF
Const24 :=
     0x000000 - 0xFFFFFF
DWordConst :=
     0x00000000 - 0xFFFFFFF
Const40 :=
     0x000000000 - 0xFFFFFFFFF
Const48 :=
     0x00000000000 - 0xFFFFFFFFFF
Const56 :=
     0x0000000000000 - 0xFFFFFFFFFFFFF
QWordConst :-
     0x000000000000000 - 0xFFFFFFFFFFFFFFF
OneBit :=
    0 - 1
TwoBits :=
     0 - 3
PrintableAsciiChar :=
     0x20 - 0x7E
NewLine :=
     '\n'
```

21.2.3 Data Types

21.2.3.1 Integers

All integers in ACPI are unsigned. Four major types of unsigned integers are supported by the compiler: *Bytes*, *Words*, *DWords* and *QWords*. In addition, for special cases, there are some odd sized integers such as 24-bit and 56-bit. The actual required width of an integer is defined by the ACPI table. If an integer is specified that is numerically larger than the width of the target field within the input source, an error is issued by the compiler. Integers are expected by the data table compiler to be entered in hexadecimal with no "hex" prefix.

Capabilities : 0000000000000 // 56 bits

Examples:

[007]

```
[001] Revision : 04// Byte (8-bit)
[002] C2 Latency : 0000// Word (16-bit)
[004] DSDT Address : 00000001// DWord (32-bit)
[008] Address : 0000000000000001// QWord (64-bit)

Length of non-power-of-two examples:

[003] Reserved : 000000// 24 bits
```

21.2.3.2 Integer Expressions

Expressions are supported in all fields that require an integer value.

Supported operators (Standard C meanings, in precedence order):

ACPI Data Tables and Table Definition Language

```
Parentheses
()
!
         Logical NOT
         Bitwise ones compliment (NOT)
*
         Multiply
/
         Divide
%
         Modulo
         Add
+
         Subtract
<<
         Shift left
>>
         Shift right
<
         Less than
         Greater than
>
<=
         Less than or equal
>=
         Greater than or equal
         Equal
!=
         Not Equal
&
         Bitwise AND
\wedge
         bitwise Exclusive OR
         Bitwise OR
&&
         Logical AND
Logical OR
```

Examples:

```
[001] Revision: 04 * (4 + 7)// Byte (8-bit)
[002] C2 Latency: 0032 + 8// Word (16-bit)
```

21.2.3.3 Flags

Many ACPI tables contain flag fields. For these fields, only the individual flag bits need to be specified to the compiler. The individual bits are aggregated into a single integer of the proper size by the compiler.

Examples:

```
[002] Flags (decoded below) : 0005
Polarity : 1
Trigger Mode : 1
```

In this example, only the Polarity and Trigger Mode fields need to be specified to the compiler (as either zero or one). The compiler then creates the final 16-bit Flags field for the ACPI table.

21.2.3.4 Strings

Strings must always be surrounded by quotes. The actual string that is generated by the compiler may or may not be null-terminated, depending on the table definition in the ACPI specification. For example, the OEM ID and OEM Table ID in the common ACPI table header (shown above) are fixed at six and eight characters, respectively. They are not necessarily null terminated. Most other strings, however, are of variable-length and are automatically null terminated by the compiler. If a string is specified that is too long for a fixed-length string field, an error is issued. String lengths are specified in the definition for each relevant ACPI table.

Escape sequences within a quoted string are not allowed. The backslash character '\' refers to the root of the ACPI namespace.

Examples:

```
[800]
                            Oem Table ID : "TEMPLATE" // Fixed length
[006]
                    Processor UID String : "\CPU0"// Variable length
```

21.2.3.5 Buffers

A buffer is typically used whenever the required binary data is larger than a QWord, or the data does not fit exactly into one of the standard integer widths. Examples include UUIDs and byte data defined by the SLIT table.

Examples:

```
// SLIT entry
[032]
                   Locality 0: 0A 10 16 17 18 19 1A 1B 1C 1D 1E 1F 20 21 22 23 \
                                  24 25 26 27 28 29 2A 2B 2C 2D 2E 2F 30 31 32 33
// DMAR entry
                       PCI Path: 1F 07
[002]
```

Each hexadecimal byte should be entered separately, separated by a space. The continuation character (backslash) may be used to continue the buffer data to more than one line.

21.2.4 Fields Set Automatically by the Compiler

There are several types of ACPI table fields that are set automatically by the compiler. This simplifies the process of ACPI table development by relieving the programmer from these tasks.

Checksums: All ACPI table checksums are computed and inserted

automatically. This includes the main checksum that appears in the standard ACPI table header, as well as any additional checksum fields such as the extended checksum that appears in

the ACPI 2.0 RSDP.

Table and Subtable Lengths: All ACPI table lengths are computed and inserted automatically. This includes the master table length that appears in the common

ACPI Data Tables and Table Definition Language

ACPI table header, and the length of any internal subtables as applicable.

Examples:

[004] Table Length: 000000F4

[001] Subtable Type: 08 <Platform Interrupt Sources>
[001] Length: 10

[001] Subtable Type: 01 <Memory Affinity>
[001] Length: 28

Flags: As described in the previous section, individual flags are

aggregated automatically by the compiler and inserted into the

ACPI table as the correctly sized and valued integer.

Compiler IDs: The data table compiler automatically inserts the ID and current

revision for iASL into the common ACPI table header for each

table during compilation.

21.2.5 Special Fields

Reserved Fields: All fields that are declared as Reserved by the table definition

within the ACPI (or other) specification should be set to zero.

Table Revision: This field in the common ACPI table header is often very

important and defines the structure of the remaining table. The developer should take care to ensure that this value is correct and current. This field is not set automatically by the compiler. It is instead used to indicate which version of the table is being

compiled.

Table Signature: There are several table signatures within ACPI that are either

different from the table name, or have unusual length:

FADT - signature is "FACP".

MADT - signature is "APIC".

RSDP - signature is "RSD PTR" (with trailing space)

21.2.6 TDL Generic Data Types

These data types are used to construct ACPI tables that are not predefined (known) by the TDL compiler.

UINT8 Generates an 8-bit unsigned integer

UINT16 Generates a 16-bit unsigned integer

UINT24 Generates a 24-bit unsigned integer

UINT32 Generates a 32-bit unsigned integer

UINT40 Generates a 40-bit unsigned integer
UINT48 Generates a 48-bit unsigned integer
UINT56 Generates a 56-bit unsigned integer
UINT64 Generates a 64-bit unsigned integer
String Generates a null-terminated ASCII string (ASCIIZ)
Unicode Generates a null terminated Unicode (UTF-16) string
Buffer Generates a buffer of 8-bit unsigned integers
GUID Generates an encoded GUID in a 16-byte buffer
Label Generates a Label at the current location (offset) within the table.
This label can be referenced within integer expressions by prepending the label with a '\$' sign.

21.2.7 Defining a Known ACPI Table in TDL

It is expected that most ACPI tables that will be created via the TDL compiler are ACPI tables that are known to the compiler. This means that the compiler contains the required structure and definition of the table, as per the ACPI specification or other specification for that table.

For these known ACPI tables, specifying the data for the table involves simply defining the value for each field in the table. The compiler automatically types the data, performs range and any value checks, and generates the appropriate output.

The starting point for any of the known ACPI tables is the document that specifies the format of the table (usually the ACPI specification), or a table template file generated by an ASL compiler, or even the output of an AML disassembler. Writing the TDL code involves implementing one line of code for each data item specified in the table definition itself.

For example, the table header for an ACPI table can be defined as simply a sequence of strings and integers. The TDL compiler will format these data items into a 36-byte ACPI header.

```
: "ECDT"
: 00000000
: 01
: 00
: "OEM "
: "MACHINE1"
: 00000001
: ""
```

21.2.8 Defining an Unknown or New ACPI table in TDL

For ACPI tables that are new or whose formats are otherwise unknown to the compiler, "generic" data types are introduced to allow the definition of these tables using explicit data types.

Examples of Generic Data Types:

```
Label : StartRecord
UINT8 : 11
UINT16 : $EndRecord - $StartRecord // Record length
UINT24 : 112233
UINT32 : 11223344
UINT56 : 11223344556677
UINT64 : 1122334455667788

String : "This is a string"

DevicePath : "\PciRoot(0)\Pci(0x1f,1)\Usb(0,0)"
Unicode : "This string will be encoded to Unicode"

Buffer : AA 01 32 4C 77
GUID : 11223344-5566-7788-99aa-bbccddeeff00
Label : EndRecord
```

21.2.9 Table Definition Language Examples

21.2.9.1 21.9.1 ECDT Disassembler Output

The output of the iASL disassembler may be used as direct input to the TDL compiler:

```
[000h 0000 4]
                                 Signature : "ECDT" [Embedded Controller Data Table]
                              Table Length : 0000004E
[004h 0004 4]
[008h 0008
          1]
                                 Revision: 01
[009h 0009
           1]
                                 Checksum : F4
[00Ah 0010
           6]
                                   Oem ID : "INTEL "
[010h 0016
                              Oem Table ID : "TEMPLATE"
           8]
[018h 0024
           4]
                              Oem Revision: 00000001
[01Ch 0028
           4]
                           Asl Compiler ID : "INTL"
[020h 0032 4] Asl Compiler Revision: 20110316
[024h 0036 12]
                   Command/Status Register : [Generic Address Structure]
[024h 0036 1]
                                 Space ID : 01 [SystemIO]
[025h 0037
           1]
                                 Bit Width: 08
           1]
[026h 0038
                                Bit Offset : 00
[027h 0039
           1]
                      Encoded Access Width : 00 [Undefined/Legacy]
          8]
[028h 0040
                                  Address : 0000000000000066
[030h 0048 12]
                             Data Register : [Generic Address Structure]
[030h 0048 1]
                                 Space ID : 01 [SystemIO]
[031h 0049 1]
                                 Bit Width: 08
[032h 0050 1]
                                Bit Offset : 00
[033h 0051
          1]
                     Encoded Access Width : 00 [Undefined/Legacy]
[034h 0052 8]
                                  Address: 00000000000000062
[03Ch 0060
                                      UID: 00000000
[040h 0064
           11
                                GPE Number: 09
[041h 0065 13]
                                 Namepath : "\_SB.PCI0.EC"
Raw Table Data: Length 78 (0x4E)
 0000: 45 43 44 54 4E 00 00 00 01 F4 49 4E 54 45 4C 20 ECDTN.....INTEL
 0010: 54 45 4D 50 4C 41 54 45 01 00 00 00 49 4E 54 4C TEMPLATE....INTL
  0020: 16 03 11 20 01 08 00 00 66 00 00 00 00 00 00
                                                     ... ....f.....
  0030: 01 08 00 00 62 00 00 00 00 00 00 00 00 00 00 ...b......
 0040: 09 5C 5F 53 42 2E 50 43 49 30 2E 45 43 00
                                                      .\_SB.PCIO.EC.
```

21.2.9.2 ECDT Definition with Field Comments

Similar to the disassembler output but simpler:

```
Signature : "ECDT"
                                    [Embedded Controller Data Table]
           Table Length : 0000004E
               Revision: 01
               Checksum : F4
                Oem ID : "INTEL "
           Oem Table ID : "TEMPLATE"
           Oem Revision : 00000001
        Asl Compiler ID : "INTL"
  Asl Compiler Revision : 20110316
Command/Status Register : [Generic Address Structure]
               Space ID : 01 [SystemIO]
              Bit Width: 08
            Bit Offset : 00
   Encoded Access Width : 00 [Undefined/Legacy]
               Address : 0000000000000066
```

ACPI Data Tables and Table Definition Language

21.2.10 Minimal ECDT Definition

An example of a minimal ECDT definition with no Field Names:

```
[Embedded Controller Boot Resources Table]
: 0000004E
: 01
: F4
: "INTEL "
: "TEMPLATE"
: 00000001
: "INTL"
: 20110316
: [Generic Address Structure]
: 01 [SystemIO]
: 08
: 00
: 00 [Undefined/Legacy]
: 0000000000000066
: [Generic Address Structure]
: 01 [SystemIO]
: 08
: 00
: 00 [Undefined/Legacy]
: 0000000000000062
: 00000000
: 09
: "\_SB.PCIO.EC"
```

21.2.10.1 Generic ACPI Table Definition

Tables that are not known to the TDL compiler can be defined by using the generic data types. All ACPI tables are assumed to have the common ACPI header, however:

```
Signature : "OEMZ"
Table Length : 00000052
Revision : 01
Checksum : 6C
Oem ID : "TEST"
Oem Table ID : "CUSTOM "
Oem Revision : 00000001
Asl Compiler ID : "INTL
Asl Compiler Revision : 00000001
```

UINT8 : 01 UINT8 : 08 UINT8 : 08
UINT8 : 00
UINT8 : 00
UINT64 : 000000000000066
UINT32 : 00000000
UINT8 : 12
String : "Hello World!"

ACPI Data Tables and Table Definition Language

Appendix A Device Class Specifications

This section defines the behavior of devices as that behavior relates to power management and, specifically, to the four device power states defined by ACPI. The goal is enabling device vendors to design power-manageable products that meet the basic needs of OSPM and can be utilized by any ACPI-compatible operating system.

A.1 Overview

The power management of individual devices is the responsibility of a *policy owner* in the operating system. This software element will implement a power management policy that is appropriate for the type (or *class*) of device being managed. Device power management policy typically operates in conjunction with a global system power policy implemented in the operating system.

In general, the device-class power management policy strives to reduce power consumption while the system is working by transitioning among various available power states according to device usage. The challenge facing policy owners is to minimize power consumption without adversely impacting the system's usability. This balanced approach provides the user with both power savings and good performance.

Because the policy owner has very specific knowledge about when a device is in use or potentially in use, there is no need for hardware timers or such to determine when to make these transitions. Similarly, this level of understanding of device usage makes it possible to use fewer device power states. Generally, intermediate states attempt to draw a compromise between latency and consumption because of the uncertainty of actual device usage. With the increased knowledge in the OS, good decisions can be made about whether the device is needed at all. With this ability to turn devices off more frequently, the benefit of having intermediate states diminishes.

The policy owner also determines what class-specific events can cause the system to transition from sleeping to working states, and enables this functionality based on application or user requests. Notice that the definition of the wake events that each class supports will influence the system's global power policy in terms of the level of power management a system sleeping state can attain while still meeting wake latency requirements set by applications or the user.

A.2 Device Power States

The following definitions apply to devices of all classes:

- **D0**. State in which device is on and running. It is receiving full power from the system and is delivering full functionality to the user.
- **D1**. Class-specific low-power state (defined in the following section) in which device context may or may not be lost. Buses in D1 cannot do anything to the bus that would force devices on that bus to lose context.
- **D2**. Class-specific low-power state (defined in the following section) in which device context may or may not be lost. Attains greater power savings than D1. Buses in D2 can cause devices

on that bus to lose some context (for example, the bus reduces power supplied to the bus). Devices in D2 must be prepared for the bus to be in D2 or higher.

• **D3**. State in which device is off and not running. Device context is lost. Power can be removed from the device.

Device power-state transitions are typically invoked through bus-specific mechanisms (for example, ATA Standby, USB Suspend, and so on). In some cases, bus-specific mechanisms are not available and device-specific mechanisms must be used. Notice that the explicit command for entering the D3 state might be the removal of power.

It is the responsibility of the policy owner (or other software) to restore any lost device context when returning to the D0 state.

A.2.1 Bus Power Management

Policy owners for bus devices (for example, PCI, USB, Small Computer System Interface [SCSI]) have the additional responsibility of tracking the power states of all devices on the bus and for transitioning the bus itself to only those power states that are consistent with those of its devices. This means that the bus state can be no lower than the highest state of one of its devices. However, enabled wake events can affect this as well. For example, if a particular device is in the D2 state and set to wake the system and the bus can only forward wake requests while in the D1 state, then the bus must remain in the D1 state even if all devices are in a lower state.

Below are summaries of relevant bus power management specifications with references to the sources.

A.2.2 Display Power Management

Refer to the Display Power Management Signaling Specification (DPMS), available from:

Video Electronics Standards Association (VESA) 2150 North First Street Suite 440 San Jose, CA 95131-2029

A DPMS-compliant video controller and DPMS-compliant monitor use the horizontal and vertical sync signals to control the power mode of the monitor. There are 4 modes of operation: normal, standby, suspend and off. DPMS-compliant video controllers toggle the sync lines on or off to select the power mode.

A.2.3 PCMCIA/PCCARD/CardBus Power Management

PCMCIA and PCCARD devices do not have device power states defined. The only power states available are on and off, controlled by the host bus controller. The CardBus specification is a superset of the PCCARD specification, incorporating the power management specification for PCI bus. Power management capabilities query, state transition commands and wake event reporting are identical.

A.2.4 PCI Power Management

Refer to the PCI Special Interest Group (PCISIG) Web site, at "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "PCI Sig".

- **PCI Bus Power Management Capabilities Query**. PCI Bus device capabilities are reported via the optional Capabilities List registers, which are accessed via the Cap Ptr.
- **PCI Bus Power Management State Transition Commands**. PCI Bus device power states are controlled and queried via the standard Power Management Status/Control Register (PMCSR).
- **PCI Bus Wakeup Event Reporting**. PCI wake events are reported on the optional PME# signal, with setting of the Wake_Int bit in the PMCSR. Wake event reporting is controlled by the Wake_En bit in the PMCSR register.

A.2.5 USB Power Management

Refer to the Universal Serial Bus Implementers Forum (USB-IF) Web site, at "Links to ACPI-Related Documents" (http://uefi.org/acpi) under the heading "Universal Serial Bus Power Management".

- **USB Power Management Capabilities Query**. USB device capabilities are reported to the USB Host via the standard Power Descriptors. These address power consumption, latency time, wake support, and battery support and status notification.
- USB Power Management State Transition Commands. USB device power states are controlled by the USB Host via the standard SET_FEATURE command. USB device power states are queried via the standard USB GET_STATUS command.
- USB Wakeup Event Reporting. USB wake event reporting is controlled using the SET_FEATURE command, with value DEVICE_REMOTE_WAKEUP. USB wake events are reported by sending remote wake resume signaling.

A.2.6 Device Classes

Below is a list of the class-specific device power management definitions available in this specification. Notice that there exists a default device class definition that applies to all devices, even if there is a separate, class-specific section that adds additional requirements.

- Audio Device Class. Applies to audio devices.
- **COM Port Device Class.** Applies to COM ports devices.
- **Display Device Class**. Applies to CRT monitors, LCD panels, and video controllers for those devices.
- **Input Device Class**. Applies to standard types of input devices such as keyboards, keypads, mice, pointing devices, joysticks, and game pads, plus new types of input devices such as virtual reality devices.
- Modem Device Class. Applies to modem and modem-like (for example, ISDN terminal adapters) devices.
- **Network Device Class**. Applies specifically to Ethernet and token ring adapters. ATM and ISDN adapters are not supported by this specification.
- PC Card Controller Device Class. Applies to PC Card controllers and slots.
- **Storage Device Class**. Applies specifically to ATA hard disks, floppy disks, ATAPI and SCSI CD-ROMs, and the IDE channel.

A.3 Default Device Class

The requirements expressed in this section apply to all devices, even if there is a separate, class-specific power management definition that identifies additional requirements.

Table A-351 Default Power State Definitions

State	Definition
D0	Device is on and running. It is receiving full power from the system, and is delivering full functionality to the user.
D1	This state is not defined and not used by the default device class.
D2	This state is not defined and not used by the default device class.
D3	Device is off and not running. Device context is assumed lost, and there is no need for any of it to be preserved in hardware. This state should consume the minimum power possible. Its only requirement is to recognize a bus-specific command to re-enter D0. Power can be removed from the device while in D3. If power is removed, the device will receive a bus-specific hardware reset upon reapplication of power, and should initialize itself as in a normal power on.

A.3.1 Default Power Management Policy

Present State	Next State	Cause
D0	D3	Device determined by the OS to not be needed by any applications or the user. System enters a sleeping state.
D3	D0	Device determined by the OS to be needed by some application or the user.

A.3.2 Default Wake Events

There are no default wake events, because knowledge of the device is implicit in servicing such events. Devices can expose wake capabilities to OSPM, and device-specific software can enable these, but there is no generic application-level or OS-wide support for undefined wake events.

A.3.3 Minimum Power Capabilities

All devices must support the D0 and D3 states. Functionality available in D0 must be available after returning to D0 from D3 without requiring a system reboot or any user intervention. This requirement applies whether or not power is removed from the device during D3.

A.4 Audio Device Class

The requirements expressed in this section apply to audio devices

A.4.1 Power State Definitions

State	Status	Definition
D0	Required	Power is on. Device is operating.
D1	Optional	Power consumption is less than D0 state. Device must be able to transition between D0 and D1 states within 100 ms. No audio samples may be lost by entering and leaving this state.
D2	Required	Power consumption is less than D0 state. Device must be able to transition between D0 and D2 states within 100 ms. Audio samples may be lost by entering and leaving this state.
D3	Required	The device is completely off or drawing minimal power. For example, a stereo will be off, but a light-emitting diode (LED) may be on and the stereo may be listening to IR commands.

If a device is in the D1 or D2 state it must resume within 100 ms. A device in the D3 state may take as long as it needs to power up. It is the responsibility of the policy owner to advertise to the system how long a device requires to power up.

All audio devices must be capable of D0, D2 and D3 states. It is desirable that an audio device be capable of D1 state. The difference between D1 and D2 is that a device capable of D1 can maintain complete state information in reduced power mode. The policy owner or other software must save all states for D2-capable devices. Some audio samples may be lost in transitioning into and out of the D2 state.

Notice that the D1 state was added to allow digital signal processor (DSP)-equipped audio hardware to exploit low-power modes in the DSP. For example, a DSP may be used to implement Dolby AC-3 Decode. When paused it stops playing audio, but the DSP may contain thousands of bytes worth of state information. If the DSP supports a low-power state, it can shut down and later resume from exactly the audio sample where it paused without losing state information.

A.4.2 Power Management Policy

For the purpose of the following state transition policy, the following device-specific operational states are defined:

- Playing. Audio is playing.
- Recording:
- **Foreground**. Normal application is recording. Recording is considered foreground unless specifically designated low priority.
- Background. Speech recognition or speech activity detection is running. Recording may be
 preempted by foreground recording or playing. Any audio recording may be designated as
 background.
- **Full Duplex**. Device is simultaneously playing and recording.
- **Paused**. File handle is open. Only devices that are playing, foreground recording or in full duplex operation may be paused. Background recording may not be paused. State is static and never lost. The paused state assumes that a device must transition to the resumed state rapidly.

Playing or recording must be resumed within 100 ms. No audio samples may be lost between the device is paused and later resumed.

• **Closed**. No file handle is open.

Present State	Next State	Cause
State	Otate	
D3	D0	Audio device moves from closed to open state or paused when the device receives the resume command.
D0	D1	Audio device receives pause command. If device is D1 capable, this state is preferred. If not, the device driver will preserve context, and the device will be set to D2.
D2/D1	D0	Audio device receives a resume command.
D0	D2	Audio device is closed. Audio inactivity timer started.
D2	D3	Audio inactivity timer expires.
D0	D3	Audio device is in background record mode and receives power-down command.

When an audio device is in the D0 state it will refuse system requests to transition to D3 state unless it is in background record mode. When an audio device is paused (D1 or D2) and it receives a request to transition to the D3 state, it will save the state of the audio device and transition to the D3 state.

Since multimedia applications often open and close audio files in rapid succession, it is recommended that an inactivity timer be employed by the policy owner to prevent needless shutdowns (D3 transitions) of the audio hardware. For example, frequent power cycling may damage audio devices powered by vacuum tubes.

A.4.3 Wake Events

An audio device may be a wake device. For example, a USB microphone designed for security applications might use the USB wake mechanism to signal an alarm condition.

A.4.4 Minimum Power Capabilities

All audio devices must be capable of D0, D2 and D3 power states. If the device is capable of maintaining context while in a low-power state it should advertise support for D1. Transitional latency for the D2 or D3 states must be less than 100 ms. There are no latency restrictions for D3 transitions, but the policy owner should advertise the amount of time required.

A.5 COM Port Device Class

The requirements expressed in this section apply to Universal Asynchronous Receiver/Transmitters (UARTs) such as the common NS16550 buffered serial port and equivalents.

The two required states for any power-managed COM Port are full on (D0) and full off (D3). This in turn requires that the COM port hardware be power-manageable by ACPI control methods for COM ports that are on system boards, or by standard bus power management controls for COM ports that are on add-in cards (for example, PCI). Because of this, ISA-based COM port add-in cards will not be able to meet this requirement, and therefore cannot be compliant with this specification.

A.5.1 Power State Definitions

State	Status	Definition
D0	Required	Line drivers are on. UART context is preserved.
D1	N/A	This state is not defined for COM Ports. Use the D3 state instead.
D2	N/A	This state is not defined for COM Ports. Use the D3 state instead.
D3	Required	Line drivers are off (unpowered; outputs isolated from devices attached to the port). UART context is lost. Latency to return to D0 is less than 1 second.

A.5.2 Power Management Policy

Present State	Next State	Cause
D3	D0	Power-on reset COM port opened by an application
D0	D3	COM port closed System enters sleeping state while wake is disabled on this device. System enters sleeping state while wake is enabled on this device and the device is capable of generating wake to the system from state D3.

A.5.3 Wake Events

If the COM port is capable of generating wake events, asserting the "ring indicator" line (V.24 circuit 125) will cause the COM port to assert a wake event. There are two common mechanisms that may be employed (either one or both) for performing machine wake using COM ports.

The first provides a solution that is capable of waking the PC whether the UART is powered (D0) or not (D3). Here, the "ring indicator" line (from V.24 circuit 125) is commonly connected directly to the system wake device in addition to being connected to the UART. While this implementation is normative for COM ports located on system motherboards (see the ACPI specification), it could also be done by add-in cards with COM ports that reside on buses supporting system wake from devices in D3 (for example, PME# signal on PCI).

The second mechanism requires that the UART be powered (D0) to use the UART's interrupt output pin to generate the wake event instead. When using this method, the OS COM port policy owner or power management control methods are expected to configure the UART. Although any UART interrupt source (for example, 'data ready') could theoretically be used to wake the system, these methods are beyond the scope of this document.

A.5.4 Minimum Power Capabilities

A COM port conforming to this specification must support the D0 and D3 states.

A.6 Display Device Class

The requirements expressed in this section apply to all devices engaged in the display of program content, which includes full screen display devices, display controllers, and graphics adapters. This

class does not include video capture devices unless they are children of the graphics adapter. This class does not include edge displays or hardware indicators for device states.

While saving power from the display and adapter are primary goals of Display Device Class power management definitions, the definitions are also intended to ensure that the user perceives the system as "off" during system sleeping states, as required above. When the system enters a lower power state, the screen must go black so the user knows the system is idle. This is important because devices that cannot actually save power (standard televisions, for example) can still support the user notice of system idle by going black.

A.6.1 Power State Definitions

A.6.1.1 CRT Monitors (not including other full screen displays)

State	Status	Definition
D0	Required	This state is equivalent to the "On" state defined in the VESA DPMS specification (see Related Documents) and is signaled to the display using the DPMS method. Display is fully on Video image is active
D1	Optional	This state is equivalent to the "Standby" state defined in the VESA DPMS and is signaled to the display using the DPMS method. Display is functional but may be conserving energy Video image is blank Latency to return to D0 must be less than 5 seconds
D2	Required	This state is equivalent to the "Suspend" state defined in the VESA DPMS specification and is signaled to the display using the DPMS method. Display is functional and conserving energy Video image is blank Latency to return to D0 is less than 10 seconds
D3	Required	This state is equivalent to the "Off" state defined in the VESA DPMS specification and is signaled to the display using the DPMS method. Display is non-functional Video image is blank

CRT Monitors are a special case in power management. On the one hand, they support a common defined method (DPMS) for changing power states. On the other hand, that procedure and the CRT support is extremely slow and out of keeping with other faster power control methods used by other forms of display. This definition should not preclude the use of faster and more effective methods of transitioning the CRT if they are available and known to the controller. DPMS is not recommended as solution for new display devices in the future.

A.6.1.2 Internal Flat Panel Devices

State	Status	Definition
D0	Required	This state is equivalent to the "On" state for a DPMS device, but is signaled to the panel by the correct application of power and/or controller specific signaling. Display is fully on Backlight (if present) is fully on(subject to performance state requirements – see below) Video image is active
D1	Optional	This state is not required to be physically different than a D3 state if the device is able to meet the resume requirement and the driver is able to restore state. Display retains internal state but may be conserving energy Backlight(if present) is fully off Video image is blank Latency to return to D0 must be less than 500 milliseconds
D2	Optional	This state is not required to be physically different than a D3 state if the device is able to meet the resume requirement and the driver is able to restore state. Display retains state but is conserving energy Backlight (if present) is fully off; Video image is blank Latency to return to D0 is less than 500 milliseconds
D3	Required	This state is equivalent to the "Off" state defined in the VESA DPMS specification. It is signaled by the removal of power or possibly by controller-specific signaling. Display is non-functional Backlight (if present) is fully off. Video image is blank Latency to return to D0 is less than 500 milliseconds

Internal flat panels (also known as local flat panels or sometimes as LCDs) do not normally support or require DPMS signaling to change power states. Instead, controllers capable of managing such panels tend to provide vendor-specific methods to control internal flat panels, often involving special sequencing of power signals to the panel. Some may be managed only by the application or removal of power.

Backlight control for power management states is likewise controller and even platform specific. Note that on-off backlight control for power management states is often unrelated to backlight intensity or brightness control that is used while in the D0 state.

The 500 milliseconds is only to allow some existing hardware to function. The target for new devices should be 100 milliseconds.

A.6.1.3 DVI Displays (Digital Flat Panels and DVI Monitors)

State	Status	Definition
D0	Required	This state is equivalent to the "On" state for a DPMS device, but is signaled to the
		display by the correct application of power and/or controller specific signaling.
		Display is fully on
		Video image is active

State	Status	Definition
D1	Optional	This state is not required to be physically different than a D3 state if the device is able to meet the resume requirement and the driver is able to restore state. It is signaled by the removal of display output and time expiring. The physical state entered is no different than D2. Display retains internal state but may be conserving energy Video image is blank Latency to return to D0 must be less than 250 milliseconds
D2	Optional	This state is not required to be physically different than a D3 state if the device is able to meet the resume requirement and the driver is able to restore state. It is signaled by the removal of display output and time expiring The physical state entered is no different than D1. Display retains state but is conserving energy Video image is blank Latency to return to D0 is less than 250 milliseconds
D3	Required	This state is equivalent to the "Off" state defined in the VESA DPMS specification. It is signaled by the removal of display output and time expiring Display is non-functional Video image is blank Latency to return to D0 is less than 250 milliseconds

Although 250 milliseconds is shown here because not all devices in this group are fast now, the target resume for a new device should be 100 milliseconds.

A.6.1.4 Standard TV Devices (and Analog HDTVs)

State	Status	Definition
D0	Required	This state is equivalent to the "On" state for a DPMS device. Display is fully on Video image is active
D1	Optional	Video image is blank Latency to return to D0 must be less than 100 milliseconds
D2	Optional	Video image is blank Latency to return to D0 must be less than 100 milliseconds
D3	Required	This state is not equivalent to the "Off" state defined in the VESA DPMS specification because not power is actually saved. Video image is blank Latency to return to D0 is less than 100 milliseconds

A.6.1.5 Other (new) Full Screen Devices

Some devices not specifically defined here already exist, such as projectors that emulate CRTs or HDTVs. Others may be coming. It is important for any device used for full screen display to support

power transitions and power management states, but the primary requirement for the method should be low overhead.

State	Status	Definition
D0	Required	This state is equivalent to the "On" state for a DPMS device, but is signaled to the panel by the correct application of power and/or device specific signaling known to the controller. Display is fully on Video image is active
D1	Optional	This state is not required to be physically different than a D3 state if the device is able to meet the resume requirement and the driver is able to restore state. It is signaled to the panel by the correct application of power and/or device specific signaling known to the controller. Display retains internal state but may be conserving energy Video image is blank Latency to return to D0 must be less than 100 milliseconds
D2	Optional	This state is not required to be physically different than a D3 state if the device is able to meet the resume requirement and the driver is able to restore state. It is signaled to the panel by the correct application of power and/or device specific signaling known to the controller. Display retains state but is conserving energy Video image is blank Latency to return to D0 is less than 100 milliseconds
D3	Required	This state is equivalent to the "Off" state defined in the VESA DPMS specification. It is signaled by the removal of display output and/or device specific methods known to the controller. Display is non-functional Video image is blank Latency to return to D0 is less than 250 milliseconds

Although 250 milliseconds is shown here because not all devices in this group are fast now, the target resume for a new device should be 100 milliseconds.

A.6.1.6 Video Controllers (Graphics Adapters)

State	Status	Definition
D0	Required	Back-end is on Video controller context is preserved Video memory contents are preserved
D1	Optional	Back-end is off, except for CRT control signaling (DPMS) Video controller context is preserved Video memory contents is preserved Latency to return to D0 is less than 100 milliseconds
D2	Optional	Back-end is off, except for CRT control signaling (DPMS) Video controller context is lost Video memory contents is lost Latency to return to D0 is less than 200 milliseconds

State	Status	Definition
D3	Required	Back-end is off
		Video controller context is lost (power removed)
		Video memory contents is lost (power removed)
		Latency to return to D0 is less than 200 milliseconds

A.6.1.7 Display Codecs

Like the displays they control, display codecs are children of the adapter and cannot be in a higher state than the adapter or a lower state than the displays they control. It is generally not helpful to deal with codecs entirely separately from the adapter or the displays they control. While it may vary from device to device, a codec will either be safely powered down when its display is powered down or it may require power as long as the adapter receives power.

A.6.2 Power Management Policy for the Display Class

Present State	Next State	Cause
D0	D1	User inactivity for a period of time (T1)
D1	D2	User inactivity for a period of time (T2 > T1)
D2	D3	User inactivity for a period of time (T3 > T2)
D1/D2/D3	D0	User activity or application UI change (for example, dialog pop-up)

These state transition definitions apply to both the full screen display and the video controller. However, the control of the two devices is independent, except that a video controller will never be put into a lower power state than its full screen display. Also, while full screen displays can transition directly from D1 to D3 or from D2 to D3, the adapters require a transition to D0 from D1 or D2 before entering D3.

Transitions for the video controller are commanded via the bus-specific control mechanism for device states. Monitor/LCD transitions are commanded by signaling from the video controller and are only generated as a result of explicit commands from the policy-owner. Full screen display power control is functionally independent from any other interface the monitor may provide (such as USB). For instance, Hubs and HID devices in the monitor enclosure may be power-managed by their driver over the USB bus, but the Monitor/LCD device itself may not; it must be power-managed from the video controller using the methods above.

A.6.3 Wake Events

Display devices incorporating a system power switch should generate a wake event when the switch is pressed while the system is sleeping.

A.6.4 Minimum Power Capabilities

A CRT monitor conforming to this specification must support the D0, D2, and D3 states. Other full screen displays only need to support D0 and D3. Support for the D1 state is optional in all cases. Transitional latencies for the D1 or D2 state must meet the requirements above.

A video controller conforming to this specification must support the D0 and D3 states. Support for the D1 and D2 states is optional. Transitional latencies for the D1 must be less than 100 milliseconds while D2 and D3 must transition to D0 in less than 200 milliseconds.

A.6.5 Performance States for Display Class Devices

Performance states for display devices and adapters have one clear difference from defined power management states. There is no display in any power management state higher than D0. However, performance states are all applied within D0, which means they save power while continuing to display. Not all display class devices will support performance states, but in all cases, they must allow continued display where they exist.

A.6.5.1 Common Requirements for Display Class Performance States

The definition of each state (up the line toward the OSPM) must include maximum latency information on transitions into the state and transitions out of the state. (For states other than DPS1, it may be necessary to indicate whether the latency is the time from DPS0 to DPSx or only from DPSx-1 to DPSx.)

Each state has to have a relative weight indicator or a relative power savings indicator (i.e., it can make a difference in OSPM policies whether DPS1 saves 2% power and DPS2 save 75% power even if latency is longer.)

While ASL NameSpace structures may provide some of this information, it is recommended that display class performance states be entered and exited by driver and not by control method wherever possible.

A.6.5.2 Performance states for Full Screen Displays

A.6.5.2.1 CRT Performance States

Some CRTs (in theory) have the capability for "reduced on" -- a mode which displays but uses less power than full performance. Even without this capability, a CRT may be able to use reduced refresh or other methods to reduce the total power of displaying.

A.6.5.2.2 Internal Flat Panel

In general, panels consume a fixed amount of power. However, some panels are also capable of supporting reduced refresh. More important, the amount of backlight brightness is a major factor in system power. This clearly needs to be coordinated with direct ASL control methods for brightness and with ambient light sensing when present. However, a performance state may be achieved by offsetting the brightness value computed by other methods, either by a fixed amount or a fixed percentage.

A.6.5.2.3 DVI Full Screen Devices

DVI Devices are normally capable of frequency control and may be able to benefit by frequency control. However, because of sensitivity to signal loss, DVI devices may have limitations on other types of performance control.

A.6.5.2.4 Standard TV and Analog HDTVs

Standard TV and Analog HDTVs do not appear capable of performance states. Codecs controlling them may be capable of power saving, however.

A.6.5.2.5 New Devices

The ability to reduce power while continuing to display will be increasingly important.

A.6.5.3 Performance States for Video Controllers/Display Adapters

Adapters are somewhat limited during performance states because they have to continue to support display on one or more full screen devices. However, they can still do a number of things to support performance states, including

- Changes to basic display and render capabilities, including speed or frequency range supported.
- Feature/Capability/Quality Control limiting specific hardware features, limiting refresh rates, limiting resolutions.

The limiting factor on what can be supported may sometimes be in the OSPM. If the OSPM support dynamic changes in these features during a performance state change (even if no other time), more opportunities arise.

Once again, the latency on transitions and the power saved by specific states have to be made available to the OSPM in order to use these options effectively.

A.7 Input Device Class

The requirements expressed in this section apply to standard types of input devices such as keyboards, keypads, mice, pointing devices, joysticks, game pads, to devices that combine these kinds of input functionality (composite devices, and so on), and to new types of input devices such as virtual reality devices, simulation devices, and so on.

A.7.1 Power State Definitions

State	Status	Definition
D0	Required	Device is receiving full power from its power source, delivering full functionality to the user, and preserving applicable context and state information.
D1	Optional	Input device power consumption is greatly reduced. In general, device is in a power management state and is not delivering any functionality to the user except wake functionality if applicable. Device status, state, or other information indicators (for example, LEDs, LCD displays, and so on) are turned off to save power. The following device context and state information should be preserved by the policy owner or other software: Keyboard. Num, caps, scroll lock states (and Compose and Kana states if applicable) and associated LED/indicator states, repeat delay, and repeat rate. Joystick. Forced feedback effects (if applicable). Any input device. All context and state information that cannot be preserved by the device when it's conserving power.

State	Status	Definition
D2	N/A	This state is not defined for input devices, use D1 as the power management state instead.
D3	Required	Input device is off and not running. In general, the device is not delivering any functionality to the user except wake functionality if applicable. Device context and state information is lost.

A.7.2 Power Management Policy

Present State	Next State	Cause
D3	D0	Requested by the system
D0	D1/D3*	Requested by the system (for example, system goes to sleep with wake enabled)
D0/D1	D3	Requested by the system (for example, system goes to sleep with wake disabled) Power is removed
D1/D3	D0	Device with enabled wake capability requests transition by generating a wake event Requested by the system

Note: *Depends on capability of device (if it features D1 or D3 wake capability or not); device will be put in state with the lowest possible power consumption.

A.7.3 Wake Events

It is recommended, but not required, that input devices implement and support bus-specific wake mechanisms if these are defined for their bus type. This is recommended because a user typically uses an input device of some kind to wake the system when it is in a power management state (for example, when the system is sleeping).

The actual input data (particular button or key pressed) that's associated with a wake event should never be discarded by the device itself, but should always be passed along to the policy owner or other software for further interpretation. This software implements a policy for how this input data should be interpreted, and decides what should be passed along to higher-level software, and so on.

It is recommended that the device button(s) or key(s) used for power management purposes are clearly labeled with text and/or icons. This is recommended for keyboards and other input devices on which all buttons or keys are typically labeled with text and/or icons that identify their usage.

For example, a keyboard could include a special-purpose power management button (for example, "Power") that, when pressed during a system sleeping state, generates a wake event. Alternatively, the button(s) on mice and other pointing devices could be used to trigger a wake event.

Examples of more advanced wake events include keyboard wake signaling when any key is pressed, mouse wake signaling on detection of X/Y motion, joystick wake signaling on X/Y motion, and so on. However, in order to avoid accidental or unintentional wake of the system, and to give the user some control over which input events will result in a system wake, it's suggested that more advanced types of wake events are implemented as features that can be turned on or off by the user (for example, as part of the OSPM user interface).

A.7.4 Minimum Power Capabilities

An input device conforming to this specification must support the D0 and D3 states. Support for the D1 state is optional.

A.8 Modem Device Class

- The requirements expressed in this section apply to modems and similar devices, such as USB controlled ISDN Terminal Adapters ("digital modems") and computer-connected telephone devices ("CT phones"). This specification will refer to these devices as "modems; the same considerations apply to digital modems and CT phones unless explicitly stated otherwise.
- The scope of this section is further restricted to modems that support power management using
 methods defined by the relevant PC-modem connection bus. These include PCI, USB, PCCARD
 (PCMCIA), CardBus, and modems on the system motherboard described by ACPI BIOS control
 methods. The scope does not include bus-specific means for devices to alert the host PC (for
 example, how to deliver a "ringing" message), nor does it address how those alerting operations
 are controlled.

A.8.1 Technology Overview

Modems are traditionally serial devices, but today modems may be attached to a PC by many different means. Further, many new modems expose a software serial interface, where the modem controller function is implemented in software. This specification addresses three different connection types:

- Traditional connections without power-managed connections (for example, COM, LPT, ISA)
- Power managed connections (for example, PCCARD, CardBus, PCI, USB)
- Motherboard modems

For some of the above modem connection types mentioned, there are three different modem architectures possible:

- Traditional modem (DAA, DSP, and controller in hardware)
- Controller-less design (DAA and DSP in hardware)
- "Soft modem" design (DAA and CODEC only in hardware)

The hardware components of the modem shall be controlled by the relevant bus commands, where applicable (USB, PCI, CardBus). The software components are dependent on the power state of the CPU.

A.8.1.1 Traditional Connections

In older methods (COM, LPT, ISA) the modem is controlled primarily by serialized ASCII command strings (for example, V.25ter) and traditional V.24 (RS-232) out-of-band leads. In these legacy devices, there are no common means for power management other than the power switch for the device, or the entire system unit.

An external modem connected to a COM port or LPT port typically has its own power supply. An LPT port modem might run from the current on the LPT port +5V supply. For COM or LPT port modems, power is typically controlled by a user switch.

The most common modem type is an ISA card with an embedded COM port. From a software standpoint, they are logically identical to external modems, but the modems are powered by the PC system unit. Power is drawn from the ISA bus without independent power switching.

A.8.1.2 Power-Managed Connections

PCMCIA, PCCARD and CardBus slots are powered and power-managed by the system, using means defined in the relevant bus specifications. For PCMCIA and PCCARD devices, only D0 and D3 states are available, via Socket Services in the OS and/or ACPI BIOS. CardBus adds intermediate states, using the same mechanisms defined for PCI Bus.

PCI bus slots are powered and power-managed by the system, using means defined in the PCI specification.

USB devices may be powered by the USB itself (100mA or 500mA), or have their own external power supply. All USB devices are power-managed by the USB bus master, using means defined in the USB specification.

A.8.1.3 Motherboard Modems

A modem embedded in the motherboard is powered by controls on the motherboard. It should be power-managed by using control methods exposed via ACPI BIOS tables.

A.8.2 Power State Definitions

State	Status	Definition
D0	Required	Phone interface is on (may be on or off hook)
		Speaker is on
		Controller Context is preserved
D1	N/A	Not defined (do not use)
D2	Optional	Phone interface is not powered by the host (on hook)
		Speaker is off
		Controller context is preserved
		2 seconds maximum restore time
D3	Required	Phone interface is not powered by host (on hook)
		Speaker is off
		Controller context may be lost
		5 seconds maximum restore time

A.8.3 Power Management Policy

Present State	Next State	Cause
D2/D3	D0	System issues a bus command to enter the D0 state (for example, an application is answering or originating a call).
D0	D2	System issues a bus command to enter the D2 state. (for example, an application is listening for an incoming call).
D0	D3	System issues a bus command to enter the D3 state (for example, all applications have closed the Modern device).

A.8.4 Wake Events

For any type of modem device, wake events (if supported and enabled) are only generated in response to detected "ringing" from an incoming call. All other events associated with modems (V.8bis messages, and so on) require that the PC be in the "working" state to capture them. The methods and signals used to generate the wake may vary as a function of the modem connection (bus) type and modem architecture.

Machine wake is allowed from any modem power state (D0, D2, and D3), and is accomplished by methods described in the appropriate bus power management specification (PCI, USB, PCCARD), or by ACPI system board control methods (for Modem on Motherboard implementations).

If the specific modem implementation or connection type does not enable it to assert system wake signaling, these modems will not be able to wake the machine. The OS modem policy owner will have to retain the PC in the "working" state to perform *all* types of event detection (including ringing).

A.8.5 Minimum Power Capabilities

A modem or similar device conforming to this specification must support the D0 and D3 states. Support of the D2 state is optional.

A.9 Network Device Class

The requirements expressed in this section apply to Ethernet and token ring adapters. ATM and ISDN adapters are not supported by this specification.

A.9.1 Power State Definitions

For the purpose of the following state definitions "no bus transmission" means that transmit requests from the host processor are not honored, and "no bus reception" means that received data are not transferred to host memory.

State	Status	Definition
D0	Required	Device is on and running and is delivering full functionality and performance to the
		user
		Device is fully compliant with the requirements of the attached network

State	Status	Definition
D1	Optional	No bus transmission allowed No bus reception allowed
		No interrupts can occur
		Device context may be lost
D2	Optional	No bus transmission allowed No bus reception allowed No interrupts can occur Device context may be lost
D3	Required	Device context is assumed to be lost No bus transmission allowed No bus reception allowed No interrupts can occur

This document does not specify maximum power and maximum latency requirements for the sleeping states because these numbers are very different for different network technologies. The device must meet the requirements of the bus that it attaches to.

Although the descriptions of states D1 and D2 are the same, the choice of whether to implement D1 or D2 or both may depend on bus services required, power requirements, or time required to restore the physical layer. For example, a device designed for a particular bus might include state D1 because it needs a bus service such as a bus clock to support Magic PacketTM wake, and that service is available in the bus device's D1 power state but not in D2. Also, a device might include both state D1 and state D2 to provide a choice between lower power and lower latency.

A.9.2 Power Management Policy

Present State	Next State	Cause
D0	Dx	System enters sleep state. If wake is enabled, Dx is the lowest power state (for example, D1, D2, D3) from which the network device supports system wake. An appropriate time-out has elapsed after a "link down" condition was detected. Dx is the lowest power state in which the network device can detect "link up."
D0	D3	System initiated network shutdown. System enters sleep state and wake is either not enabled or the network device is capable of waking from D3.
D1/D2/D3	D0	System wake (transition to S0), including a wake caused by a network wake event.

A.9.3 Wake Events

Network wake events are generally the result of either a change in the *link status* or the reception of a *wake frame* from the network.

A.9.3.1 Link Status Events

Link status wake events are useful to indicate a change in the network's availability, particularly when this change may impact the level at which the system should re-enter the sleeping state. For example, a transition from "link off" to "link on" may trigger the system to re-enter sleep at a higher

level (for example, S2 versus S3) so that wake frames can be detected. Conversely, a transition from "link on" to "link off" may trigger the system to re-enter sleep at a deeper level (for example, S3 versus S2) since the network is not currently available. The network device should implement an internal delay to avoid unnecessary transitions when the link status toggles on or off momentarily.

A.9.3.2 Wake Frame Events

Wake frame events are used to wake the system whenever *meaningful* data is presented to the system over the network. Examples of meaningful data include the reception of a Magic PacketTM, a management request from a remote administrator, or simply network traffic directly targeted to the local system. In all of these cases the network device was pre-programmed by the policy owner or other software with information on how to identify wake frames from other network traffic. The details of how this information is passed between software and network device depend on the OS and therefore are not described in this specification.

A.9.4 Minimum Power Capabilities

A network device conforming to this specification must support the D0 and D3 states. Support for the D1 and D2 states is optional.

A.10 PC Card Controller Device Class

The requirements expressed in this section apply to PC Card controller devices and the PC Card slots.

Power management of *PC Cards* is not defined by this specification. PC Card power management is defined by the relevant power management specification for the card's device class (for example, network, modem, and so on), in conjunction with the PC Card standard (for 16-bit cards) or the PCI Power Management Specification (for CardBus cards).

A.10.1 Power State Definitions

State	Status	Definition
D0	Required	Card status change interrupts are fully functional. Card functional interrupts are fully functional. Controller context (for example, memory, I/O windows) is fully functional. Controller interface is fully functional (processor can access cards). Power to cards (slots) is available (may be on or off under software control). The controller is at its highest power consumption level. Bus command response time is at its fastest level. PC Cards can be in any Dx power state (D0-D3). Note: In D0 state, CSTSCHG interrupts can be passed to a system from a powered down PC Card (for more detail, refer to section 5.2.11.2 of PC Card Standard, Electrical Specification).
D1	Optional	Card status change interrupts are disabled. CSTSCHG interrupt events are still detectable by the controller and cause the bus-specific wake signal to be asserted if wake is enabled on the controller. Card functional interrupts are disabled. Controller context is preserved (all register contents must be maintained but memory and I/O windows need not be functional). Controller interface is non-functional (processor cannot access cards). Power to cards (slots) is available (may be on or off; retains power setting it had at time of entry to D1). Power-level consumption for the controller is high but less than D0. The time required to restore the function from the D1 state to the D0 state is quicker than resumption from D3. Bus command response time is equal to or slower than in D0. PC Cards can be in the D1, D2, or D3 power states (not D0). Note: In D1 state, CSTSCHG interrupts can be passed to a system from a powered-down PC Card (for more detail, refer to section 5.2.11.2 of PC Card Standard, Electrical Specification).
D2	Optional	Functionally the same as D1 (may be implemented instead of D1 in order to allow bus and/or system to enter a lower-power state).
D3	Required	Card status change interrupt: Disabled and need not be detected. Card functional interrupt: Disabled and need not be detected. Controller context (for example, memory, I/O windows): Lost. Controller interface: Non-functional (processor can not access cards). Clock to controller: Off. Power to cards (slots): Off (card context lost). Note: If Vcc is removed (for example, PCI Bus B3) while the device is in the D3 state, a bus-specific reset (for example, PCI RST#) must be asserted when power is restored and functions will then return to the D0 state with a full power-on reset sequence. Whenever the transition from D3 to D0 is initiated through assertion of a bus-specific reset, the power-on defaults will be restored to the function by hardware just as at initial power up. The function must then be fully initialized and reconfigured by software.

A.10.2 Power Management Policy

The PC Card controller is a bus controller. As such, its power state is dependent on the devices

plugged into the bus (child devices). OSPM will track the state of all devices on the bus and will put the bus into the best possible power state based on the current device requirements on that bus. For example, if the PC Card cards are all in the D1 state, OSPM will put the PC Card controller in the D1 state.

Present State	Next State	Cause
D2/D3	D0	Any card in any slot needing to transition to state D0 due to a wake event or because of system usage.
D0	D1	No card in any slot is in state D0.
D0	D2	No card in any slot is in state D0 or D1.
D0	D3	All cards in all slots are in state D3.

A.10.3 Wake Events

A wake event is any event that would normally assert the controller's status change interrupt (for example, card insertion, card battery state change, card ReqAttn event, and so on) or ring-indicate signal.

A.10.4 Minimum Power Capabilities

A PC Card controller device conforming to this specification must support the D0 and D3 states. Support for the D1 or D2 states is optional.

A.11 Storage Device Class

The requirements expressed in this section apply to ATA hard disks, floppy disks, ATAPI and SCSI CD-ROMs, and the IDE channel.

A.11.1 Power State Definitions

A.11.1.1 Hard Disk, CD-ROM and IDE/ATAPI Removable Storage Devices

State	Status	Definition	
D0	Required	Drive controller (for example, interface and control electronics) is functional. Interface mode context (for example, communications timings) is programmed.	
D1	Optional	Drive controller (for example, interface and control electronics) is functional. Interface mode context (for example, communications timings) is preserved. Drive motor (for example, spindle) is stopped, with fast-start mode enabled, if available. Laser (if any) is off. Recommended latency to return to D0 is less than 5 seconds. Power consumption in D1 should be no more than 80% of power consumed in D0. Note: For ATA devices, this state is invoked by the Standby Immediate command.	
D2	N/A	This state is not defined for storage devices.	
D3	Required	Drive controller (for example, interface and control electronics) is not functional; context is lost. Interface mode (for example, communications timings) is not preserved. Drive motor (for example, spindle) is stopped. Laser (if any) is off. Power consumption in D3 is no more than 10% of power consumed in D0. Note: For ATA devices, this state is invoked by the "sleep" command.	

A.11.1.2 Floppy Disk Devices

State	Status	Definition	
D0	Required	Drive controller (for example, interface and control electronics) is functional.	
		Drive motor (for example, spindle) is turning.	
D1	N/A	This state is not defined for floppy disk drives.	
D2	N/A	This state is not defined for floppy disk drives.	
D3	Required	Drive controller (for example, interface and control electronics) is not functional; context is lost. Drive motor (for example, spindle) is stopped.	

A.11.1.3 IDE Channel Devices

State	Status	Definition	
D0	Required	Adapter is functional. Adapter interface mode (for example, communications timings) is programmed. Power is applied to the bus (and all devices connected to it).	
D1	N/A	This state is not defined for the IDE Channel.	
D2	N/A	This state is not defined for the IDE Channel.	
D3	Required	Adapter is non-functional. Adapter interface mode (for example, communications timings) is not preserved. Power to the bus (and all devices connected to it) may be off.	

A.11.2 Power Management Policy

A.11.2.1 Hard Disk, Floppy Disk, CD-ROM and IDE/ATAPI Removable Storage Devices

Present State	Next State	Cause
D3	D0	Device usage (high-priority I/O).
D0	D1*	Device inactivity (no high-priority I/O) for some period of time (T1).
D0	D3	Device inactivity (no high-priority I/O) for a period of time (T2=>T1). System enters sleeping state.
D1*	D0	Device usage (High-priority I/O).

Note: * If supported.

Note: For ATA, the D3-to-D0 transition requires a reset of the IDE channel. This means that both devices on a channel must be placed into D3 at the same time.

A.11.2.2 IDE Channel Devices

Present State	Next State	Cause
D3	D0	Any device on the channel needing to transition to a state other than state D3.
D0	D3	All devices on the channel in state D3.

A.11.3 Wake Events

Storage devices with removable media can, optionally, signal wake upon insertion of media using their bus-specific notification mechanism. There are no other wake events defined for Storage devices.

A.11.4 Minimum Power Capabilities

A hard disk, CD-ROM or IDE/ATAPI removable storage device conforming to this specification must support the D0 and D3 states. Support for the D1 state is optional.

A floppy disk and IDE channel device conforming to this specification must support the D0 and D3 states.

Appendix B Video Extensions

B.1 ACPI Extensions for Display Adapters: Introduction

This section of the document describes a number of specialized ACPI methods to support motherboard graphics devices.

In many cases, system manufacturers need to add special support to handle multiple output devices such as panels and TV-out capabilities, as well as special power management features. This is particularly true for notebook manufacturers. The methods described here have been designed to enable interaction between the system BIOS, video driver, and OS to smoothly support these features.

Systems containing a built-in display adapter are required to implement the ACPI Extensions for Display Adapters.

Table B-352 Video Extension Object Requirements

Method	Description	Requirement
_DOS	Enable/Disable output switching	Required if system supports display switching or LCD brightness levels
_DOD	Enumerate all devices attached to display adapter	Required if integrated controller supports output switching
_ROM	Get ROM Data	Required if ROM image is stored in proprietary format
_GPD	Get POST Device	Required if _VPO is implemented
_SPD	Set POST Device	Required if _VPO is implemented
_VPO	Video POST Options	Required if system supports changing post VGA device
_ADR	Return the unique ID for this device	Required
_BCL	Query list of brightness control levels supported	Required if embedded LCD supports brightness control
_BCM	Set the brightness level	Required if _BCL is implemented
_DDC	Return the EDID for this device	Required if embedded LCD does not support return of EDID via standard interface
_DCS	Return status of output device	Required if the system supports display switching (via hotkey)
_DGS	Query graphics state	Required if the system supports display switching (via hotkey
_DSS	Device state set	Required if the system supports display switching (via hotkey).

B.2 Definitions

• **Built-in display adapter**. This is a graphics chip that is built into the motherboard and cannot be replaced. ACPI information is valid for such built-in devices.

• Add-in display adapter. This is a graphics chip or board that can be added to or removed from the computer. Because the system BIOS cannot have specific knowledge of add-in boards, ACPI information is not available for add-in devices.

- **Boot-up display adapter**. This is the display adapter programmed by the system BIOS during machine power-on self-test (POST). It is the device upon which the machine will show the initial operating system boot screen, as well as any system BIOS messages.
- The system can change the boot-up display adapter, and it can switch between the built-in adapter and the add-in adapter.
- **Display device**. This is a synonym for the term display adapter discussed above.
- **Output device**. This is a device, which is a recipient of the output of a display device. For example, a CRT or a TV is an output device.

B.3 ACPI Namespace

This is an example of the display-related namespace on an ACPI system:

```
GPE
                // ACPI General-purpose HW event
               // Notify(VGA, 0x80) to tell OSPM of the event, when user presses
// the hot key to switch the output status of the monitor.
// Notify(VGA, 0x81) to tell the event to OSPM, when there are any
// changes on the sub-devices for the VGA controller
SB
- PCI
  - VGA
                // Define the VGA controller in the namespace
     - _PS0 / PR0
     - _PS1 / PR1
    - _PS0
       |- _PS1
|- _PS2
                 - Power methods
                 - for the output device
       - _PS3 /
       - LCD
       - _PS2
                - for the output device
       - TV
```

The LCD device represents the built-in output device. Mobile PCs will always have a built-in LCD display, but desktop systems that have a built-in graphics adapter generally don't have a built-in output device.

B.4Display-specific Methods

The methods described in this section are all associated with specific display devices. This devicespecific association is represented in the namespace example in the previous section by the positioning of these methods in a device tree.

B.3.1 _DOS (Enable/Disable Output Switching)

Many ACPI machines currently reprogram the active display output automatically when the user presses the display toggle switch on the keyboard. This is done because most video device drivers are currently not capable of being notified synchronously of such state changes. However, this behavior violates the ACPI specification, because the system modifies some graphics device registers.

The existence of the _DOS method indicates that the system BIOS is capable of automatically switching the active display output or controlling the brightness of the LCD. If it exists at all, the _DOS method must be present for all display output devices. This method is required if the system supports display switching or LCD brightness control.

Arguments: (1)

Arg0 – An **Integer** containing the encoded switching controls (see below)

Return Value:

None

Additional Argument Information:

Bits 1:0

- 0 The system BIOS should not automatically switch (toggle) the active display output, but instead just save the desired state change for the display output devices in variables associated with each display output, and generate the display switch event. OSPM can query these state changes by calling the DGS method.
- 1 The system BIOS should automatically switch (toggle) the active display output, with no interaction required on the OS part. The display switch event should not be generated in this case.
- 2 The _DGS values should be locked. It's highly recommended that the system BIOS do nothing when hotkey pressed. No switch, no notification.
- 3 The system BIOS should not automatically switch (toggle) the active display output, but instead generate the display switch event notify codes 0x82, 0x83, or 0x84. OSPM will determine what display output state should be set, and change the display output state without further involvement from the system BIOS.

Bit 2

- 0 The system BIOS should automatically control the brightness level of the LCD when the power changes from AC to DC.
- 1 The system BIOS should not automatically control the brightness level of the LCD when the power changes from AC to DC.

The _DOS method controls this automatic switching behavior. This method should do so by saving the parameter passed to this method in a global variable somewhere in the BIOS data segment. The system BIOS then checks the value of this variable when doing display switching. This method is also used to control the generation of the display switching **Notify**(VGA, 0x80/0x81).

The system BIOS, when doing switching of the active display, must verify the state of the variable set by the DOS method. The default value of this variable must be 1.

B.3.2 _DOD (Enumerate All Devices Attached to the Display Adapter)

This method is used to enumerate devices attached to the display adapter. This method is required if integrated controller supports output switching.

On many laptops today, a number of devices can be connected to the graphics adapter in the machine. These devices are on the motherboard and generally are not directly enumerable by the video driver; for this reason, all motherboard VGA attached devices are listed in the ACPI namespace.

These devices fall into two categories:

- **Video output devices**. For example, a machine with a single display device on the motherboard can have three possible output devices attached to it, such as a TV, a CRT, or a panel.
- **Non-video output devices**. For example, TV Tuner, DVD decoder, Video Capture. They just attach to VGA and their power management closely relates to VGA.

Both ACPI and the video driver have the ability to program and configure output devices. This means that both ACPI and the video driver must enumerate the devices using the same IDs. To solve this problem, the _DOD method returns a list of devices attached to the graphics adapter, along with device-specific configuration information. This information will allow the cooperation between ACPI components and the video driver.

Every child device enumerated in the ACPI namespace under the graphics adapter must be specified in this list of devices. Each display device must have its own ID, which is unique with respect to any other attachable devices enumerated.

Arguments:

None

Return Value:

A **Package** containing a variable-length list of **Integers**, each of which contains the 32-bit device attribute of a child device (See <u>Table B-353</u>)

Example:

Table B-353 Video Output Device Attributes

Bits	Definition	
15:0	Device ID . The device ID must match the ID's specified by Video Chip Vendors. They must also be unique under VGA namespace.	
	Bit 3:0	Display Index A zero-based instance of the Display, when multiple displays of the same type are attached, regardless of where it is associated. Starting from the first adapter and its first display of the type on the first integrated internal device and then incrementing per device-function according to its relative port number.
	Bit 7:4	Display Port Attachment This field differentiates displays of the same type attached at different points of one adapter. The zero-based number scheme is specific to each Video Chip Vendors' implementation.
	Bit 11:8	Display Type Describes the specific type of Display Technology in use. 0 – Other 1 – VGA* CRT or VESA* Compatible Analog Monitor 2 – TV/HDTV or other Analog-Video Monitor 3 – External Digital Monitor (See Note 1.) 4 – Internal/Integrated Digital Flat Panel (See Note 2.) 5~15 – Reserved for future use
	Bit 15:12	Chipset Vendor Specific.
16	BIOS can detect the device.	
17	Non-VGA output device whose power is related to the VGA device. This can be used when specifying devices like TV Tuner, DVD decoder, Video Capture etc.	
20:18	Duo-View*,	ultiple-head devices, this specifies head or pipe ID e.g. for Dual-Pipe*, Dual-Display*, TwinView*, Triple-View* etc, beginning with 0 for head 0 or single-head device and or each additional head.
30:21	Reserved (r	must be 0)
31		Scheme e bit-field definitions above (bits 15:0) cheme, contact the Video Chip Vendor

As mentioned in the above table, a "Pipe" or "Head" refers to a unique display content stream e.g. at a particular color-depth, resolution, and refresh-rate. The "Port" refers to the display output device attachment and may include a DAC, encoder or other mechanism required to support a given display end-point. The "Display Type" describes the generalized class of display output technology, and the means of integration. The "Display Index" is then an index that assists in creating a unique identifier display end-points in scenarios where other attributes are the same.




Figure B-1 Example Display Architecture

Table B-354 Example Device Ids

Bits	Definition
0х000хуууу	Bit 31 = 0. Other proprietary scheme - 0x110 Device ID is an exception. (See Note 3)
0x00000110	Integrated LCD Panel #1 using a common, backwards compatible ID
0x80000100	Integrated VGA CRT or VESA compatible Monitor #1 on Port0
0x80000240	Integrated TV #1 on Port4
0x80000410	Integrated Internal LCD Panel #1 on Port1
0x80000421	LVDS Panel #2 Dual-Link using Port2 & 3. (See Note 4)
0x80000131	VGA CRT or VESA compatible Monitor #2 on Port3
0x80000121	Dual-Link VGA CRT or VESA compatible Monitor #2 using Port2 & 3. (See Note 4.)
0x80000320	DVI Monitor #1 on Port2 (shares Port2 with a Dual-Function DVI/TV Encoder). (See Note 5)
0x80000331	DVI Monitor #2 on Port3
0x80000330	Dual-Link DVI Monitor #1 using Port2 & 3
0x80000231	TV #2 on Port2 (shares Port2 with a Dual-Function DVI/TV Encoder). (See Note 5)

Note: An "External Digital Monitor" is an external display device attachable via a user-accessible connector standard (e.g. DFP* or DVI* Compatible Monitors).

Note: An "Internal Flat Panel" is a non-detachable fixed pixel display device, including a backlight, and is internally associated, without user-accessible connectors, to the Video Chip (e.g. TFT LCD via TMDS*, LVDS* interface).

Note: When Bit 31 is 0, no assumptions can be made on which ID will be used for any particular display type. Contact the Video Chip vendor for details of the ID scheme employed.

Note: In certain cases multiple Displays Ports may be combined to increase bandwidth for a particular Display in higher-resolution modes. In this situation, the Display Type and Port Number should remain the same in order to retain a consistent ID for the same device, regardless of the selected display mode.

Note: In certain cases, more than one type of display (and connector) may be supportable on a single Port (e.g. DVI + TV + CRT on a single Display Encoder device), while only one display is selectable at any time. In this case the Port Number field of the ID may be the same as other Display ID's however the other fields (e.g. Display Type) provide uniqueness.

B.3.3 ROM (Get ROM Data)

This method is used to get a copy of the display devices' ROM data. This method is required when the ROM image is stored in a proprietary format such as stored in the system BIOS ROM. This method is not necessary if the ROM image can be read through a standard PCI interface (using ROM BAR). If ROM is present, it is preferred over the image read through the standard PCI interface, in order to allow system BIOS to provide re-configured ROM data via the method.

The video driver can use the data returned by this method to program the device. The format of the data returned by this function is a large linear buffer limited to 4 KB. The content of the buffer is defined by the graphics independent hardware vendor (IHV) that builds this device. The format of this ROM data will traditionally be compatible with the ROM format of the normal PCI video card, which will allow the video driver to program its device, independently of motherboard versus add-in card issues.

The data returned by the _ROM method is implementation-specific data that the video driver needs to program the device. This method is defined to provide this data as motherboard devices typically don't have a dedicated option ROM. This method will allow a video driver to get the key implementation specific data it needs so that it can fully control and program the device without BIOS support.

Arguments: (2)

Arg0 – An **Integer** containing the offset of the display device ROM data

Arg1 – An **Integer** containing the size of the buffer to fill in (up to 4K).

Return Value:

A **Buffer** containing the requested ROM data

B.3.4 _GPD (Get POST Device)

This method is required if the VPO method is implemented.

This method is used as a mechanism for the OS to query a CMOS value that determines which VGA device will be posted at boot. A zero return value indicates the motherboard VGA will be posted on

the next boot, a 1 indicates a PCI VGA device will be posted, and a 2 indicates an AGP VGA device will be posted.

Arguments:

None

Return Value:

An **Integer** containing encoded post information (32 bits valid)

Bits 1:0

00 – Post the motherboard VGA device

01 - Post an add-in PCI VGA device

10 - Post an add-in AGP VGA device

11 – Post an add-in PCI-Express VGA device

Bits 31:2 – Reserved (must be 0)

B.3.5 _SPD (Set POST Device)

This method is required if the _VPO method is implemented.

This method is used as a mechanism for the OS to update a CMOS value that determines which video device will be posted at boot. A zero argument will cause the "motherboard" to be posted on the next boot, a 1 will cause an add-in PCI device to be posted, and a 2 will cause an add-in AGP device to be posted.

Arguments: (1)

Arg0 – An **Integer** containing encode post information (32 bits valid)

Bits 1:0

00 – Post the motherboard VGA device

01 - Post an add-in PCI VGA device

10 - Post an add-in AGP VGA device

11 – Post an add-in PCI-Express VGA device

Bits 31:2 – Reserved (must be 0)

Return Value:

An **Integer** containing the status of the operation

) _

Operation was successful

Non-zero - Operation failed

Example

```
Method (\_SPD, 1)\{ // Make the motherboard device the device to post \}
```

B.3.6 _VPO (Video POST Options)

This method is required for systems with video devices built onto the motherboard and support changing post-VGA device.

This method is used as a mechanism for the OS to determine what options are implemented. This method will be used in conjunction with _GPD and _SPD

Arguments:

None

Return Value:

An **Integer** containing the options that are implemented and available

- Bit 0 Posting the motherboard VGA device is an option. (Bit 0 should always be set)
- Bit 1 Posting a PCI VGA device is an option.
- Bit 2 Posting an AGP VGA device is an option.
- Bit 3 Posting a PCI-Express VGA device is an option.
- Bits 31:4 Reserved (must be zero)

B.4 Notifications for Display Devices

Display devices may need to know about external, asynchronous events. In order to accommodate that, the following notifications are defined.

The event number is standardized because the event will be handled by the OS directly under certain circumstances (see DOS method in this specification).

These notifications are valid for Display Devices

Table B-355 Notifications for Display Devices.

Value	Description
0x80	Cycle Output Device. Used to notify OSPM whenever the state of one of the output devices attached to the VGA controller has been switched or toggled. This event will, for example, be generated when the user presses a hotkey to switch the active display output from the LCD panel to the CRT.
0x81	Output Device Status Change. Used to notify OSPM whenever the state of any output devices attached to the VGA controller has been changed. This event will, for example, be generated when the user plugs-in or remove a CRT from the VGA port. In this case, OSPM will re-enumerate all devices attached to VGA
0x82	Cycle Display Output Hotkey Pressed. Used to notify OSPM whenever the user has pressed the Cycle display hotkey.
0x83	Next Display Output Hotkey Pressed. Used to notify OSPM whenever the user has pressed the Next display hotkey.
0x84	Previous Display Output Hotkey Pressed. Used to notify OSPM whenever the user has pressed the Previous display hotkey.

B.5 Output Device-specific Methods

The methods in this section are methods associated with the display output device.

B.5.1 _ADR (Return the Unique ID for this Device)

This method returns a unique ID representing the display output device. All output devices must have a unique hardware ID. This method is required for all The IDs returned by this method will appear in the list of hardware IDs returned by the DOD method.

Arguments:

None

Return Value:

An Integer containing the device ID (32 bits)

Example:

```
Method (_ADR, 0) {
    return(0x0100) // device ID for this CRT
}
```

This method is required for all output display devices.

B.5.2 _BCL (Query List of Brightness Control Levels Supported)

This method allows the OS to query a list of brightness level supported by built-in display output devices. (This method in not allowed for externally connected displays.) This method is required if an integrated LCD is present and supports brightness levels.

Each brightness level is represented by a number between 0 and 100, and can be thought of as a percentage. For example, 50 can be 50% power consumption or 50% brightness, as defined by the OEM.

The OEM may define the number 0 as "Zero brightness" that can mean to turn off the lighting (e.g. LCD panel backlight) in the device. This may be useful in the case of an output device that can still be viewed using only ambient light, for example, a transflective LCD. If Notify(Output Device, 0x85) for "Zero brightness" is issued, OSPM may be able to turn off the lighting by calling BCM(0).

Arguments:

None

Return Value:

A variable-length **Package** containing a list of **Integers** representing the supported brightness levels. Each integer has 8 bits of significant data.

Example:

The first number in the package is the level of the panel when full power is connected to the machine. The second number in the package is the level of the panel when the machine is on batteries. All other numbers are treated as a list of levels OSPM will cycle through when the user toggles (via a keystroke) the brightness level of the display.

These levels will be set using the BCM method described in the following section.

B.5.3 _BCM (Set the Brightness Level)

This method allows OSPM to set the brightness level of a built-in display output device.

The OS will only set levels that were reported via the _BCL method. This method is required if BCL is implemented.

Arguments: (1)

Arg0 – An Integer containing the new brightness level

Return Value:

None

Example:

```
Method (\_BCM, 1) { // Set the requested level }
```

The method will be called in response to a power source change or at the specific request of the end user, for example, when the user presses a function key that represents brightness control.

B.5.4 _BQC (Brightness Query Current level)

This optional method returns the current brightness level of a built-in display output device. If present, it must be set by the platform for initial brightness.

Arguments:

None

Return Value:

An **Integer** containing the current brightness level (must be one of the values returned from the _BCL method)

B.5.5 _DDC (Return the EDID for this Device)

This method returns an EDID (Extended Display Identification Data) structure that represents the display output device. This method is required for integrated LCDs that do not have another standard mechanism for returning EDID data.

Arguments:

Arg0 – An **Integer** containing a code for the return data length:

- 1 Return 128 bytes of data
- 2 Return 256 bytes of data

Return Value:

Either a **Buffer** containing the requested data (of the length specified in Arg0), or an **Integer** (value 0) if Arg0 was invalid

Example:

```
Method (_DDC, 2) {
    If (LEqual (Arg0, 1)) { Return (Buffer(128){ ,,,, }) }
    If (LEqual (Arg0, 2)) { Return (Buffer(256){ ,,,, }) }
    Return (0)
}
```

The buffer will later be interpreted as an EDID data block. The format of this data is defined by the VESA EDID specification.

B.5.6 _DCS (Return the Status of Output Device)

This method is required if hotkey display switching is supported.

Arguments:

None

Return Value:

An **Integer** containing the device status (32 bits) (See <u>Table B-356</u>)

Table B-356 Device Status

Bits	Definition
0	Output connector exists in the system now
1	Output is activated
2	Output is ready to switch
3	Output is not defective (it is functioning properly)
4	Device is attached (this is optional)
5-31	Reserved (must be zero)

Example:

• If the output signal is activated by DSS, DCS returns 0x1F or 0x0F.

- If the output signal is inactivated by DSS, DCS returns 0x1D or 0x0D.
- If the device is not attached or cannot be detected, _DCS returns 0x0xxxx and should return 0x1xxxx if it is attached.
- If the output signal cannot be activated, DCS returns 0x1B or 0x0B.
- If the output connector does not exist (when undocked), DCS returns 0x00.

B.5.7 _ DGS (Query Graphics State)

This method is used to query the state (active or inactive) of the output device. This method is required if hotkey display switching is supported.

Arguments:

None

Return Value:

An **Integer** containing the device state (32 bits) (See Table B-357)

Table B-357 Device State for DGS

Bits	Definition
0	0 – Next desired state is inactive 1 – Next desired state is active
1-31	Reserved (must be zero)

The desired state represents what the user wants to activate or deactivate, based on the special function keys the user pressed. OSPM will query the desired state when it receives the display toggle event (described earlier).

B.5.8 _DSS (Device Set State)

OSPM will call this method when it determines the outputs can be activated or deactivated. OSPM will manage this to avoid flickering as much as possible. This method is required if hotkey display switching is supported.

Arguments: (1)

Arg0 – An **Integer** containing the new device state (32 bits) (See <u>Table B-358</u>)

Return Value:

None

Table B-358 Device State for _DSS

Bits	Definition
0	0 – Set output device to inactive state 1 – Set output device to active state
30	0 – Do whatever Bit 31 requires
	1 – Don't do actual switching, but need to change _DGS to next state

Bits	Definition	
31	0 – Don't do actual switching, just cache the change	
	1 – If Bit 30 = 0, commit actual switching, including any _DSS with MSB=0 called before	
	If Bit 30 = 1, don't do actual switching, change _DGS to next state	
1-29	Reserved (must be zero)	

Example Usage:

OS may call in such an order to turn off CRT, and turn on LCD

```
CRT._DSS(0);
LCD._DSS(80000001L);
Or
LCD._DSS(1);
CRT._DSS(80000000L);
```

OS may call in such an order to force BIOS to make _DGS jump to next state without actual CRT, LCD switching

```
CRT._DSS(40000000L);
LCD._DSS(C0000001L);
```

B.6 Notifications Specific to Output Devices

Output devices may need to know about external, asynchronous events. In order, each of these events corresponds to accommodate that, pressing a key or button on the following machine. Using these notifications is not appropriate if no physical device exists that is associated with them. OSPM may ignore any of these notifications if, for example the current user does not have permission to change the state of the output device.

These notifications are only valid for Output Devices.

Table B-359 Notification Values for Output Devices

Value	Description
0x85	Cycle Brightness. Used to notify OSPM that the output device brightness should be increased by one level. Used to notify OSPM that the user pressed a button or key that is associated with cycling brightness. A useful response by OSPM would be to increase output device brightness by one or more levels. (Levels are defined in _BCL.) If the brightness level is currently at the maximum value, it should be set to the minimum level.
0x86	Increase Brightness. Used to notify OSPM that the output device brightness should be increased by one or more levels as defined by the _BCL object. Used to notify OSPM that the user pressed a button or key that is associated with increasing brightness. If the brightness level is currently at the maximum value, OSPM may should ignore the notification.
0x87	Decrease Brightness. Used to notify OSPM that the output device brightness should be decreased by one or more levels as defined by the _BCL object. Used to notify OSPM that the user pressed a button or key that is associated with decreasing device brightness. If the brightness level is currently at the minimum value, OSPM may should ignore the notification.

Value	Description
0x88	Zero Brightness. Used to notify OSPM that the output device brightness should be zeroed, effectively turning off any lighting that is associated with the device. Used to notify OSPM that the user pressed a button or key associated with zeroing device brightness. This is not to be confused with putting the device in a D3 state. While the brightness may be decreased to zero, the device may still be displaying, using only ambient light.
0x89	Display Device Off. Used to notify OSPM that the device should be put in an off state, one that is not active or visible to the user, usually D3, but possibly D1 or D2. Used to notify OSPM that the user pressed a low power button or key associated with putting the device in an off state. There is no need for a corresponding "device on" notification, for two reasons. First, OSPM may choose to toggle device state when this event is pressed multiple times. Second, OSPM may (and probably will) choose to turn the monitor on whenever the user types on the keyboard, moves the mouse, or otherwise indicates that he or she is attempting to interact with the machine.

B.7 Notes on State Changes

It is possible to have any number of simultaneous active output devices. It is possible to have 0, 1, 2 ... and so on active output devices. For example, it is possible for both the LCD device and the CRT device to be active simultaneously. It is also possible for all display outputs devices to be inactive (this could happen in a system where multiple graphics cards are present).

The state of the output device is separate from the power state of the device. The "active" state represents whether the image being generated by the graphics adapter would be sent to this particular output device. A device can be powered off or in a low-power mode but still be the active output device. A device can also be in an off state but still be powered on.

Example of the display-switching mechanism:

The laptop has three output devices on the VGA adapter. At this moment in time, the panel and the TV are both active, while the CRT is inactive. The automatic display-switching capability has been disabled by OSPM by calling DOS(0), represented by global variable display switching = 0.

The system BIOS, in order to track the state of these devices, will have three global variable to track the state of these devices. There are currently initialized to:

```
crt_active - 0
panel_active - 1
tv_active - 1
```

The user now presses the display toggle switch, which would switch the TV output to the CRT.

The system BIOS first updates three temporary variables representing the desired state of output devices:

```
want_crt_active - 1
want_panel_active - 1
want_tv_active - 0
```

Then the system BIOS checks the display_switching variable. Because this variable is set to zero, the system BIOS does not do any device reprogramming, but instead generates a **Notify**(VGA, 0x80/0x81) event for the display. This event will be sent to OSPM.

OSPM will call the _DGS method for each enumerated output device to determine which devices should now be active. OSPM will determine whether this is possible, and will reconfigure the

internal data structure of the OS to represent this state change. The graphics modes will be recomputed and reset.

Finally, OSPM will call the DSS method for each output device it has reconfigured.

Note: OSPM may not have called the _DSS routines with the same values and the _DGS routines returned, because the user may be overriding the default behavior of the hardware-switching driver or operating system-provided UI. The data returned by the _DGS method (the want_XXX values) are only a hint to the OS as to what should happen with the output devices.

If the display-switching variable is set to 1, then the BIOS would not send the event, but instead would automatically reprogram the devices to switch outputs. Any legacy display notification mechanism could also be performed at this time.

Symbols	engaging 538
_EJx 316	preferences 51, 541
???????????????????????????????????????	threshold values 541
???????????????????????????????????????	active line printer (LPT) ports 42
??? 147	Active List (_ALx) object 548
A	Add (Integer Add) 741
AC adapter	add-in display adapter, definition 896
device ID 241	Address (ADR) object 262
power source objects 524	address register (SMB_ADDR) 586
AC status notification 506	Address Space Descriptors
access, device 593	DWORD resource descriptor format 339
AccessAs term 216, 605	Extended 343
acoustics See noise	QWORD resource descriptor format 336,
ACPI	805, 807, 808
definition 17	resource specific flags 347
device ID 241, 255	WORD resource descriptor format 342
goals 1	Address Space Resource Descriptors
ACPI Hardware See hardware	valid combinations 336
ACPI Machine Language See AML	addresses
ACPI mode	alarm fields 81
entering 641	BARs (Base Address Registers) 207
exiting 645	blocking, BIOS 621
ACPI Namespace	bus types 262, 266, 272, 308, 309
AML encoding 852	control methods 206
control method access 206	decoding 471
definition 17	FACS 128
display adapters 896	format 104
embedded controller device definition 594	functional fixed hardware 105
generic hardware registers 92	Generic Address Structure (GAS) 105
Modifier Objects encoding, AML 839	generic hardware 57, 64
naming conventions 197	I/O (S)APIC 142, 364
Processor statements 405	map samples 626
root namespaces 199	mixed, preventing 142, 364
SMBus host controller objects 601	registers 70
ACPI Source Language See ASL	reset register 90, 91
ACPI System Description tables See tables	slave 505, 599
ACPI-compatible hardware See hardware	system description tables 100
Acquire (Acquire a Mutex) 741	Advanced Configuration and Power Interface
Acquire terms 795	See ACPI
active cooling	Advanced Programmable Interrupt Controller
_ACx object 535, 548	See APIC
control methods 538	alarm address register (SMB_ALRM_ADDR)
definition 534	587

alarm data register (SMB_ALRM_DATA) 587	NMI 141
alarm events 80	Processor Local 138, 163
Alias (Declare Name Alias) 742	structure types 137
allocation, device resources 310	support 139
Ambient Light Sensor devices 242	APM BIOS 31
AML	appliance PCs 126
Arg Objects encoding 846	ARB DIS 88
battery events 511	architecture, system description tables 99
byte values 847	Arg Objects encoding, AML 846
code event handler 58	arguments, control methods 204
compiling 57	Argx (Method Argument Data Objects) 742
Control Method Battery 512	arrow symbol
data buffers, SMBus 217, 606	ASL notation 690
Data Objects encoding 838	ASL
Debug Objects encoding 847	FIX usage example 285
definition 17	HPP example 288
grammar 836	case sensitivity 716
Local Objects encoding 847	CMOS protocols 206
Name Objects encoding 836, 837	converting to AML 57
Named Objects encoding 839	data and constant terms 693
Namespace encoding 852	data types 720
Namespace Modifier Objects encoding 839	definition 18
notation conventions 835	Definition Block terms 751
Package Length encoding 838	EC-SMB-HC device code 596
purpose of 57	embedded controller device code 595
sleep button code example 78	grammar 689
SMBus device access protocols 218, 607	grammar notation 690
Term Objects encoding 839	index with buffers example code 779
Type 1 Opcodes encoding 842	IPMI data buffer code 211
Type 2 Opcodes encoding 843	IPMI devices 209
And (Integer Bitwise And) 742	lid status code example 97
angle brackets	macros 720
AML 835	modifiers 716
ASL notation 690	multiple Smart Battery subsystem code 510
answering phones	name and pathname terms 691
modem example 40	nested packages sample code 778
waking computer 42	object names 716
APIC	objects, declaring 203
_MAT (Multiple APIC Table Entry) 294	opcode terms 695
definition 17	opcodes 695
I/O 20, 139	operator reference 740
local 21	operator summary 732
multiple description table (MADT) 21	operator summary by type 736

parameter keyword terms 707	Battery Information (BIF) object 512
parameters 723	Battery Information Extended(BIX) object
Power Resource statements 371	514
primary terms 696	Battery Maintenance Control (BMC) object
reserved object names 716	523
resource template terms 709, 824	Battery Maintenance Data (BMD) object 521
root and secondary terms 691	Battery Measurement Averaging Interval
SMBBlock code 221, 224, 610	(BMA) object 517
SMBBlockProcessCall code 223, 225, 612	Battery Measurement Sampling Time (BMS)
SMBByte code 220, 609	object 518
SMBProcessCall code 222, 611	Battery Status (_BST) object 518
SMBQuick code 219, 608	Battery Time (BTM) object 520
SMBSendReceive code 219, 608	Battery Trip Point (_BTP) object 520
SMBus data buffer code 217, 606	bay devices 536
SMBus devices 603	BIOS
SMBWord code 220, 610	address range types 621
storing results 723	configuring boot devices 44
thermal zone examples 562	determining ACPI support 82
virtual register code 210, 213, 214, 606	Device Objects 752
AT interrupt model 152	devices, switching 910
ATA hard disks See storage devices	Dock Name (_BDN) 364
audible output See noise	initialization 639
audio devices, power management 871, 872	legacy functions 31
aware device drivers 231	legacy specifications 15
В	memory initialization 641
BankField (Declare Bank/Data Field) 743	relation to ACPI 5
bar symbol	resetting enable bits 94
AML notation 836	S4 Sleeping state transition 636
ASL notation 690	bits
BARs (Base Address Registers) 207	alarm 81
Base Bus Number (_BBN) object 367	child 64, 92
batteries 510	child status 94
Control Method Batteries 510	control 92
emergency shutdown 48	enable 68
events 511	general-purpose events 94
low-level warnings 47	generic hardware registers 91
management 45	ignored 20, 65
multiple 45	interrupt status 64
power status information 38	lid status 97
remaining capacity 519	parent 64, 92
types supported 39	PM timer 88
batteries See also Smart Batteries Pattery Charge Time (PCT) object 521	PM1 Control registers 87
Battery Charge Time (_BCT) object 521	PM1 Enable registers 86

PM1 Status registers 84, 438	WORD 343
PM2 Control register 88	Brightness Control Levels Supported, Query
processor control register 89	List of (BCL) 905
processor LVL2 89	brightness control, LCDs 895
processor LVL3 90	Brightness Level, Set (BCM) 906
register notation 59	Buffer (Declare Buffer Object) 744
reserved 22, 65, 103	Buffer field data type, ASL 720, 724
reset register 90, 91	buffers, IPMI 210
SMBus protocol encoding 600	buffers, SMBus 217, 606
status 68, 92	built-in display adapter, definition 896
system event signals 44	Burst Disable Embedded Controller (BD EC)
wake enabled 39	580
write-only 65	Burst Enable Embedded Controller (BE_EC)
blanks 689	579
block count register (SMB_BCNT) 587	Burst flags 578
block devices, GPE 466	burst mode 579
Block Write-Read Block Process Call (SMB-	Bus/Device packages 752
BlockProcessCall) protocol 223, 612	buses
blocking, control methods 204	power management standards 870
blocks, register 69	segment locations 367
BM_RLD 87	setting power states 38
BM_STS 84	button control models 74
bold	buttons See power button
AML notation 835	byte values, AML 847
ASL notation 690	C
boot architecture flags, IA-PC 126	C0 processor power state
boot devices 44	definition 28
boot resources, embedded controller 153	implementation 399
bootstrap ROM 642	C1 processor power state
boot-up 638	definition 28
brackets, angle	implementation 401
AML notation 835	C2 processor power state
ASL notation 690	definition 28
Break (Break from While) 744	implementation 401
BreakPoint (Execution Break Point) 744	C3 processor power state
bridges	definition 29
Base Bus Number (_BBN) 367	implementation 401
DWORD 340	cache controller configuration 640
flags 349	caches, flushing 403, 638
ISA bus device 457, 752	capacity, battery
power states 39	calculating 45
purpose 102	low-level warnings 47
QWORD 338, 345	remaining 519

status information 39	definition 23
CardBus mode 364	during emergency shutdown 49
Case (Conditional Execution) 745	S4 sleeping state 635
case sensitivity, ASL 716	sleep states lost in 28
category names 6	contiguous RAM 642
Celsius scale 537	Continue (Continue Innermost Enclosing
centenary value, RTC alarm 81	While) 747
Central Processing Unit See CPU	control bits
CENTURY 81	functions 92
channels, DMA 326, 330	symbol 59
chemistry independence 506	Control Method Battery 45
child bits 64, 92	Control Method placeBattery 240, 241, 510
child objects, ASL statements 689	control methods
child status bits 94	_ADR (Return the Unique ID for this De-
CityplaceEnterprise servers 126	vice) 905
CLK_VAL 89	_BCL (Query List of Brightness Control
clock logic 399	Levels Supported) 905
CMOS protocols 206	BCM (Set the Brightness Level) 906
cold boots 90, 640	BDN (BIOS Dock Name) 364
cold insertion and removal 313	DCK (Dock) 364
COM port devices, power management 40,	DCS (Return the Status of Output Device)
871, 874	907
command protocols, SMBus 600	_DDC (Return the EDID for this Device)
command register (SMB_CMD) 586	907
commands, embedded controller interface 578	_DDS (PlaceNameDevice PlaceNameSet
comments, ASL 690	PlaceTypeState)PlaceName 908
compatibility memory 642	_DGS (PlaceNameQuery PlaceName-
compatibility, compiler 818	Graphics PlaceTypeState)Place-
Compatible ID (_CID) object 263	Name 908
compiling, ASL to AML 57, 818	_DOD (Enumerate All Devices Attached to
composite battery 45	the Display Adapter) 899
Concatenate (Concatenate Data) 745	_DOS (Enable/Disable Output Switching)
ConcatenateResTemplate (Concatenate Re-	898
source Templates) 746	_GPD (Get POST Device) 902
CondRefOf (Conditional Reference Of) 746	_LID (lid device) 449, 450, 451, 456, 486,
configuration objects, device 276	494, 495, 496, 497
configuring	MSG (Message) 447, 448
BIOS initialization 640	OFF 372
boot devices 44	PS0 (PlaceNamePower PlaceTypeState 0)
modem example 44	376
Plug and Play devices 44	_PS0 (Power State 0) 377
context, device 19	_PS1 (PlaceNamePower PlaceTypeState 1)
context, system	376

_PS2 (PlaceNamePower PlaceTypeState 2)	CPU
376	boot configuration 640
PS3 (PlaceNamePower PlaceTypeState 3)	boot-up 638
376	cache flushing 403
PSC (PlaceNamePower PlaceTypeState	clock logic 399
Current) 377	definition 18
PSW 381	fixed hardware control 57, 104
PTS (Prepare To Sleep) 387	multiple performance state control 419
_REG (Region) 365	non-symmetric power state support 399
ROM (Get Rom Data) 902	passive cooling 539
SCP (Set Cooling Policy) 554	performance states 29
SPD (Set POST Device) 903	processor power states 397
STM (Set Timing Mode) 462	thermal management 49
_TMP (Temperature) 535, 558	throttling 399, 412
_VPO (Video POST OPtions) 903	waking operations 39
WAK (System Wake) 394	crashed systems 74, 75
ASL, writing 689	CreateBitField (Create 1-Bit Buffer Field) 748
battery 512	CreateByteField (Create 8-Bit Buffer Field)
device identification 262	748
device removal 313	CreateDWordField (Create 32-Bit Buffer
initialization (_INI) 363	Field) 748
lid device 443, 448, 456, 485	CreateField (Create Arbitrary Length Buffer
OEM-supplied 386	Field) 749
overview 204	CreateQWordField (Create 64-Bit Buffer
power button 75, 457	Field) 749
Power Resource objects 372	CreateWordField (Create 16-Bit Buffer Field)
power source 524, 526	749
reserved names 242	Critical battery state 48
resources 276	Critical Temperature (_CRT) object 540, 552
sleep button 77, 457	critical temperature shutdowns 534, 540
system indicators 447	Cross Device Dependency 65
thermal management 547	CRT monitors, power management 875
video extensions 895	C-States (processor power) 402, 407
control methods See also objects	CT phones See modems
control registers 68	Current Resource Settings (_CRS) objects 278,
controllers, embedded	480
definition 19	D
interface 19	D0-Fully On
conversion, data types 720	control method 376, 377
cooling modes 50, 534	definition 27
cooling preferences 51, 541	In Rush Current (_IRC) object 382
CopyObject (Copy an Object) 747	power resource object 377
core logic, system events 44	transitioning to 378

D1 Device State	requirements for 689
definition 27	decimals, notation 690
transitioning to 378	Decrement (Integer Decrement) 750
D1 PlaceNameDevice PlaceTypeState	Default (Default Execution Path in Switch) 751
control methods 376	Definition Blocks
D1 PlaceNameplaceDevice PlaceTypeState	ASL code 716
power resource objects 378	encoding 200
D2 Device State	loading 101, 133, 787
definition 27	loading from XSDT 787
transitioning to 379	unloading 826
D2 PlaceNameDevice PlaceTypeState	DefinitionBlock (Declare Definition Block)
control methods 376	751
D2 PlaceNameplaceDevice PlaceTypeState	definitions See terminology
power resource objects 378, 379	degrees, Kelvin 537
D3-Off	dependencies, device 65, 327
control methods 376	DerefOf (Dereference an Object Reference)
definition 26	752
transitioning to 373	description tables See tables
dash character	design guides 6, 8
AML notation 836	desktop PCs
ASL notation 691	profile system type 125
data buffers, IPMI 210	Device (Declare Bus/Device Package) 752
data buffers, SMBus 217, 606	device and processor performance states 29, 43
Data Objects encoding, AML 838	Device Class Power Management specifica-
data objects, ASL	tions 37
Buffer 744	Device data type, ASL 720, 724, 725
Package 801	device drivers, ACPI-Aware 231
data register array (SMB_DATA) 587	Device Name (_DDN) object 264
data types	device power
ASL 720	management 36
concatenate 729, 730, 731, 745	modem example 39
data types, resource See resource data types	objects 373
DataTableRegion (Create Data Table Opera-	requirements 872
tion Region) 749	standards 36, 37
day alarm 80	states 26
day mode 35	status 38
DAY_ALRM 81	devices
DDB Handle data type, ASL 720, 724	audio, power management 872
DDT, Plug and Play devices 43	class-specific objects 240
Debug (Debugger Output) 750	COM port, power management 874
Debug Object data type, ASL 720, 725	context, definition 19
Debug Objects encoding, AML 847	definition 18
debugging	graphics 895

identification objects 261	control methods 313, 364
input, power management 882	event signals 45
insertion and removal objects 312	objects 314
interference 65	query events 93
modems, power management 884	documentation
network, power management 886	organization 12
object notification 235	supplemental 15
PC Card controllers, power management	drain rates, battery 47
888	drivers
Plug and Play IDs 240	interference 65
power states 26	restoration 27
resource allocation 310	DSDT
resource control method 276	definition 19, 134
SMBus, declaring 602	purpose 101
storage, power management 890	dual 8259 139
waking system 380	dual-button model 74
Devices Attached to the Display Adapter	duty cycle 399
(_DOD) 899	DVD decoders 899
Differentiated Definition Block	DWORD 89
Bus/Device packages 752	DWORD resource descriptor format 339
determining device power capabilities 37	DWordIO (DWord IO Resource Descriptor
modem example 41	Macro) 754
Differentiated Description Block	DWordMemory (DWord Memory Resource
isolation logic 41	Descriptor Macro) 756
Differentiated System Description Table See	DWordSpace (DWord Space Resource De-
DSDT	scriptor Macro) 758
digital modems See modems	dynamic insertion and removal 313
Direct Memory Access (_DMA) object 278	dynamic objects 205
Disable (_DIS) object 278	dynamic Operation Regions 800
Disable Output Switching (_DOS) 898	dynamic transitioning 61
display adapters	E
ACPI Namespace 896	E_TMR_VAL 88
control methods 895	E820 mapping 622
definitions 896	EC_DATA (embedded controller data register)
switching devices 910	578
display devices, power management 871, 875	EC_SC (R) (embedded controller status regis-
Display Power Management Signaling Specifi-	ter) 577
cation (DPMS) 870	EC_SC (W) (embedded controller command
Divide (Integer Divide) 753	register) 578
DMA resource descriptor format 326, 330	ECDT 153
DMA Resource Descriptor Macro 754, 771	ECI See embedded controller interface
Dock (_DCK) control method 364	EC-SMB-HC 583, 596
docking	EDID control methods (_DDC) 907

EFI	SMBus host controller 583
definition 19	SMBus notification header
GetMemoryMap interface 624	(OS_SMB_EVT) 580
RSDP location 107	SMBus protocol descriptions 588
EISA ID 265	SMBus registers 584
EISAID (EISA ID String To Integer Conver-	specifications 573
sion Macro) 759	emergency shutdown 48
Eject (_EJx) object 316	enable bits
Eject Device List (EDL) object 314	corresponding status bits 94
Ejection Dependent Device (_EJD) object 315	resetting 94
ejection mechanisms 313	symbol 59
Else (Alternate Execution) 760	enable register 44
ElseIf (Alternate/Conditional Execution) 760	Enable/Disable Output Switch (_DOS) 898
embedded controller	encoding
boot resources table 153	AML 836
burst mode 579	Definition Blocks 200
device ID 241	object names, ASL 716
device object 457	tables 103
event control example 92	End Dependent Functions resource descriptor
multiple 573	format 328
operations 97	end tag resource descriptor format 331
queuing events 230	EndDependentFn End Dependent Functions
region control method 365	Descriptor Macro) 761
embedded controller interface	energy conservation See power management
ACPI Namespace objects 594	Enumerate All Devices Attached to the Display
algorithms 582	Adapter (_DOD) 899
ASL code, device 595	enumeration, enabling 602
bi-directional communications 574	errors, fatal 768
Burst flag 578	Ethernet adapters See network devices
command interrupt model 582	Event (Declare Event Synchronization Object)
command register (EC_SC (W)) 578	762
command set 578	Event data type, ASL 720, 725
commands, restricted 594	events
configurations, additional 576	alarm 80
data register (EC_DATA) 578	AML code handler 58
definition 19	battery 511
firmware requirements 580	button 74
Input Buffer Full (IBF) flag 578, 583	enable register 44
objects 594	fixed feature 20
OEM-definable values 583	fixed handling 228
Output Buffer Full (OBF) flag 577, 583	general model 44
registers 577	general-purpose registers 20, 92
shared 574, 576	hardware 62

interrupt 62, 82	fans
link status 887	active cooling 50
OS-transparent 63	device operations 543
power button 75	noise preferences 51
power button override 76	Plug and Play ID 98
programming model 226	thermal zone example 564
query 93	Fatal (Fatal Error Check) 768
shared 64	fatal errors 768
status register 44	features
synchronization objects 814	fixed 20
synchronization, waiting for 827	generic 20
user-initiated 74	generic hardware 94
wake frame 888	Field (Declare Field Objects) 768
exiting ACPI mode 645	fields
extended I/O bus 241	alarm 81
Extended Interrupt resource descriptor format	cache flushing 638
349	declaring objects 768
Extended IO Resource Descriptor Macro 762	embedded controller boot resources 153
Extended Memory Resource Descriptor Macro	FACS 128
764	FADT 114, 284
Extended resource descriptor format 343	I/O APIC 139
Extended Root Systems Description Table See	IPMI 209
XSDT	MADT 136, 162, 187
Extended Space Resource Descriptor Macro	NMI 141
765	Processor Local APIC 138, 145, 188, 189,
Extensible Firmware Interface See EFI	190, 191, 192
External (Declare External Objects) 767	reserved 103
F	RSDT 112
FACS	SBST 152
definition 19	SMBus 212, 215, 604
flags 131	Start Dependent Functions 327
Global Lock 131	FindSetLeftBit (Find First Set Left Bit) 771
table fields 128	FindSetRightBit (Find First Set Right Bit) 771
FADT	firmware
alarm bits 80	ACPI System 6
cache flushing 403, 638	embedded controller requirements 580
definition 19	OSPM controls 33
flags 91	SMM functional fixed hardware implemen-
optional feature bits 83	tation 104
Plug and Play IDs 284	Firmware ACPI Control Structure See FACS
processor power states 398	Fixed ACPI Description Table See FADT
reset register location 90, 91	fixed event handling 228
SCI interrupt mapping 82	fixed features

definition 20	Floppy Disk Enumerate (FDE) object 464
events 20	Floppy Disk Information (FDI) object 465
registers 20	floppy disks See storage devices
fixed hardware	flushing caches 403, 638
definition 55	frequency mismatch 236
feature control bits 87	FromBCD (Convert BCD To Integer) 772
feature enable bits 85	Function (Declare Control Method) 772
feature status bits 83	functional device configuration 640
features 66	functions
functional implementation 57	End Dependent 328
interfaces 104	Start Dependent 327
power button 75	G
programming model 56	G0 Working state
register blocks 69	behavior during 631
registers 68, 83	definition 25
sleep button 77	properties 25
fixed location I/O port descriptor resource de-	transitioning to 60
scriptor format 329	transitioning to Sleeping state 637
Fixed Register Resource Provider (_FIX) 284	transitioning to Soft-Off 638
fixed width registers 351	G1 Sleeping state
FixedIO (Fixed IO Resource Descriptor) 772	definition 24
FixedList 689	properties 25
flags	transitioning to 631
Burst 578	G2 Soft Off
DWORD 340	definition 24
FACS 131	properties 26
FADT 91	transitioning to 61
I/O resource 348	G3 Mechanical Off
IA-PC boot architecture 126	definition 24
Input Buffer Full (IBF) 578, 583	properties 26
interrupt vector 350	transitioning from 60
local APIC 138	transitioning to 34
MADT 137	game pads See input devices
memory resource 347	GAS See Generic Address Structure
MPS INTI 140	GBL EN 86
Output Buffer Full (OBF) 577, 583	GBL RLS 87
QWORD 337, 344	GBL STS 84
SMI event (SMI EVT) 578	general event model 44
system type 126	general-purpose event registers
WORD 342	addresses 71, 92
floppy controller device objects 464	blocks 72, 94
Floppy Disk Drive Mode (FDM) control	definition 20
method 466	event 0 94

event 0 enable 95	block devices 242, 466
event 0 status 95	control method 231
event 1 95	grammar
event 1 enable 96	AML 836
event 1 status 96	ASL 689
grouping 70	grammar notation
general-purpose events	AML 835
Exx, Lxx, and Qxx methods 229	ASL 690
handling 228, 233	graphics devices, requirements for 895
wake 231	Green PCs, power management for 35
generic address space, SMBus 599	groupings, register See register groupings
Generic Address Structure (GAS) 105	guides, design 6, 8
generic events	H
example 93, 396	hardware
top-level 93	ACPI interfaces 4
generic feature, definition 20	definition 17
generic hardware	events 62
definition 55	features 66
features 66, 94	fixed 56
power button control 75	ignored bits 65
registers 57, 68, 91	interfaces 6
sleep button control 77	legacy 64
generic ISA bus device 457	legacy vs. ACPI 3
generic register resource descriptor format 351	OEM implementation 3
Get POST Device (_GPD) 902	OS-independent 57, 104
Get Power Status 38	OSPM model 60
Get ROM Data (_ROM) 902	register definitions 57
Get Task File (_GTF) control method 458	registers 67
Get Timing Mode (_GTM) control method 461	reserved bits 65
GetMemoryMap 624	value-added 57
Global Lock 131	hardware ID (_HID) object 264, 265, 507
Global Lock (_GLK) object 368	headers, long 112
Global Lock Mutex 254	headers, table 100
Global Lock Structure 132	heat management See thermal management
global standby timer 64	hexadecimals, notation 690
global system interrupts 139, 151	holes, compatibility 642
global system states	home PCs, power management for 35
transitioning 33, 62, 267, 268, 272, 901	host controller objects, SMBus 601
goals	hot insertion and removal 316
ACPI 1	Hot Plug Parameters (_HPP) object 287, 291
OSPM 1	292
power management 2	Hot Temperature (_HOT) object 552
GPE	hung systems 74, 75

hysteresis 536	Include (Include Additional ASL File) 777
I	Increment (Integer Increment) 777
I/O APIC	independence, OS
_MAT (Multiple APIC Table Entry 294	functional fixed hardware 104
definition 20	generic hardware 57
Global System Interrupts 152	Index (Indexed Reference To Member Object)
mixed addresses, preventing 142, 364	778
structure 139	Index with Buffers 779
I/O port resource descriptor format 328	Index with Packages 778
I/O resource flag 348	Index with Strings 780
I/O SAPIC	IndexField (Declare Index/Data Fields) 780
definition 21	indicators, system 447
mixed addresses, preventing 142, 364	initialization
Platform Interrupt Source structure 143,	BIOS 639
145	boot-up 638
structure 142	OS 644
I/O space 102	initialization object (_INI) 363
IA (Intel Architecture) specifications 15	Input Buffer Full (IBF) flag 578, 583
IA-32 systems 104	input devices, power management 871, 882
IA-PC	Input/Output See I/O
boot architecture flags 126	insertion and removal objects 312
definition 20	insertion and removal, batteries 511
interrupt models 139	INT 15 mapping 622
memory map system 622	Integer data type, ASL 720, 725
RSDP location 107	Integers 717
ID, Compatible (_CID object) 263	Intel Architecture specifications 15
IDE	Intel Architecture-Personal Computer See IA-
controller device 459	PC
drives 58	interdependent resources 327
IDE devices See storage devices	interfaces
identification objects, device 261	ACPI 4
idle loops, CPU 43	battery 45
idle timers, legacy 64	BIOS, legacy 31
IDs, Plug and Play 240, 262	Control Method Battery 512
If (Conditional Execution) 777	design guides 6
ignored bits	EC-SMB-HC 583
definition 20, 65	embedded controller 19
PM1 Status register 85	extensible firmware (EFI) 19
implementation requirements	fixed hardware 104
OEM 3	hardware 6
OS 11	sharing protocols 576
OSPM 10	SMBus 23, 599
In Rush Current (_IRC) object 382	interference, device 65

Interrupt (Extended Interrupt Descriptor Mac-	keyboard controllers 573
ro) 781	keyboards See input devices
interrupt events	L
logic 62	LAnd (Logical And) 784
SCI 82	large resource resource descriptor format 223,
shareable 82	226, 331
SMI 82	latency
Interrupt Source Overrides 139	acceptable 33, 267, 268, 272, 901
interrupt sources, non-maskable (NMIs) 141	global power states 25
interrupt status bits 64	processor power states 397
interrupts	LCD panels
Extended Interrupt resource descriptor for-	brightness control 895
mat 349	power management 875
models 136, 139, 151, 162, 192	legacy BIOS interfaces 31
Platform Interrupt Source structure 143	legacy hardware
PMIs 143	BIOS specification 15
invocation, control methods 206	boot flags 126
IO (I/O Port Resource Descriptor Macro) 782	converting to fixed 56
IPMI	definition 21
data buffers 210	interrupt handlers 82
fields, declaring 209	support 3
operation regions 208	legacy OS, definition 21
IRQ (Interrupt Resource Descriptor Macro 783	legacy systems
IRQNoFlags (Interrupt Resource Descriptor	definition 21
Macro) 784	power button functions 34
IRQs	power management 64
mapping 139, 141	power state transitions 60
PCI routing 305	switching devices out of 364
resource descriptor format 325	transitioning to ACPI 82
ISA	LEqual (Logical Equal) 784
bus device 241, 254, 457	LGreater (Logical Greater) 785
Device Objects code 752	LGreaterEqual (Logical Greater Than Or
interrupt sources 140	Equal) 785
old cards 328	lid device 241
ISDN Terminal Adapters See modems	lid status notification values 238, 239
isolation logic 41	lid switch 96
italics, ASL notation 690	life, battery 46
J	link status events 887
joysticks See input devices	LINT 141
K	LLess (Logical Less) 785
Kelvin scale 537	LLessEqual (Logical Less Than Or Equal) 786
kernel 5	LNot (Logical Not) 786
key, logic diagrams 59	LNotEqual (Logical Not Equal) 786

Load (Load Definition Block) 787	QWordSpace Resource Descriptor 807
loading Definition Blocks 101, 133, 787	Register Resource Descriptor 809
LoadTable (Load Definition Block From XS-	ResourceTemplate 811
DT) 787	Start Dependent Function NoPri Resource
local APIC, definition 21	Descriptor 817
Local Objects encoding, AML 847	Start Dependent Function Resource De-
Localx (Method Local Data Objects) 788	scriptor 816
Lock (LCK) object 317	Unicode Conversion 825
Lock, Global 131	UUID Conversion 823
logic	VendorLong Resource Descriptor 826
fixed power button 75	VendorShort Resource Descriptor 826
lid switch 97	WordBusNumber Resource Descriptor 828
sleep button 77	WordIO Resource Descripto 829
sleeping/wake control 79	WordSpace Resource Descriptor 831
LOr (Logical Or) 789	MADT
low-level warnings, battery 47	_MAT object 294
LPT ports 42	definition 21
\mathbf{M}	flags 137
macros, ASL	interrupt models 136, 162, 192
24-bit Memory Resource Descriptor 790	table fields 136, 162, 187
32-bit Fixed Memory Resource Descriptor	Magic Packet wake 887
792	management See power management
32-bit Memory Resource Descriptor 791	mapping
coding 720	E820 622
DMA Resource Descriptor 754, 771	EFI GetMemoryMap 624
DWordIO Resource Descriptor 754	INT 15 622
DWordMemory Resource Descriptor 756	IRQs 139, 141
DWordSpace Resource Descriptor 758	Query System Address Map function 627
EISAID Conversion 759	samples 626
End Dependent Functions Resource De-	Match (Find Object Match) 789
scriptor 761	Mechanical Off
Extended Interrupt Resource Descriptor	definition 24
781	properties 26
ExtendedIO Resource Descriptor 762	transitioning from 60
ExtendedMemory Resource Descriptor 764	transitioning to 34
ExtendedSpace Resource Descriptor 765	memory
FixedIO Resource Descriptor 772	BIOS initialization 641
I/O Port Resource Descriptor 782	controller configuration 640
IRQ Interrupt Resource Descriptor 783	descriptor macros 792
IRQNoFlags Interrupt Resource Descriptor	devices 471
784	map sample 626
QWordIO Resource Descriptor 803	NVS 642
QWordMemory Resource Descriptor 805	resource flag 348

memory device 241	Multiply (Integer Multiply) 795
memory range descriptors	multiprocessor PCs
24-Bit 332	performance control 419
32-Bit 333	power management for 35
32-Bit Fixed Location 335	mutex
purpose 333	acquiring 741
Memory24 (Memory Resource Descriptor	Global Lock 254
Macro) 790	release synchronization objects 811
Memory32 (Memory Resource Descriptor Macro) 791	Mutex (Declare Synchronization/Mutex Object) 795
Memory32Fixed (Memory Resource Descrip-	Mutex data type, ASL 721, 725
tor Macro) 792	N
Message (MSG) control method 447, 448	Name (Declare Named Object) 796
Method (Declare Control Method) 792	Name Objects encoding, AML 836, 837
Method data type, ASL 721, 725	name terms, ASL 691
methods, control See control methods	Named Objects encoding, AML 839
mice See input devices	names, object 21
Microsoft Device Class Power Management	Namespace See ACPI Namespace
specifications 37	naming conventions 197
Mid (Extract Portion of Buffer or String) 794	NAnd (Integer Bitwise Nand) 796
mobile PCs	nested packages 778
lid switch 96	network devices, power management 871, 886
power management 34	NMIs 141
profile system type 125	noise, active cooling 50
Mod (Integer Modulo) 794	non-linear address spaces 208, 599
modems	Non-Maskable Interrupt Sources (NMIs) 141
configuration example 44	non-visible states, device power 26
power management 871, 884	Non-Volatile Sleeping memory (NVS) 642
power management example 39	NoOp Code (No Operation) 796
modifiers	NOr (Integer Bitwise Nor) 797
ASL names 716	Not (Integer Bitwise Not) 797
Module Device 242, 468	notation
MON-ALRM 81	AML 835
monitors See display devices	ASL 690
month alarm 81	numeric constants 690
motherboard device configurations	register bits 59
ACPI goals 1	Nothing 690
controlled by OSPM 31	notification
modems 885	battery removal 511
MPS INTI flags 140	power button control 75
Multiple APIC Description Table See MADT	Smart Battery status 506
Multiple APIC Table Entry (_MAT) object 294	temperature changes 537
multiple Smart Battery Subsystem 509	Notification Temperature Threshold (_NTT)

object 553	_IRC (In Rush Current) 382
Notify (Notify Object of Event) 797	LCK (Lock) 317
numeric constants, notation 690	MAT (Multiple APIC Table Entry) 294
NVS files	NTT (Notification Temperature Thresh-
checking validity 644	old) 553
NVS memory 642	PCL (Power Consumer List) 525
0	PCT (Performance Control) 420
object name, definition 21	PPC (Performance Present Capabilities)
Object Reference data type, ASL 721, 725	422
objects	PR0 (Power Resources for D0) 377
BMC (Battery Maintenance Control) 523	PR1 (Power Resources for D1) 378
ACx (Active Cooling) 535, 548	PR2 (Power Resources for D2) 378, 379
ADR (Address) 262	PRS (Possible Resource Settings) 304
BBN (Base Bus Number) 367	PRW (Power Resources for Wake) 232,
BCT (Battery Charge Time) 521	380
_BIF (Battery Information) 512	PSL (Passive List) 553
BIX (Battery Information Extended) 514	PSR (Power Source) 524
BMA (Battery Measurement Averaging	PSS (Performance Supported States) 409.
Interval) 517	415, 420, 424
BMD (Battery Maintenance Data) 521	PSV (Passive) 535, 553
BMS (Battery Measurement Sampling	PTC (Processor Throttling Control) 412
Time) 518	RMV (Remove) 323
BST (Battery Status) 518	S1D 382
BTM (Battery Time) 520	
BTP (Battery Trip Point) 520	
_CID (Compatible ID) 263	
CRS (Current Resource Settings) 278, 480	_SBS (Smart Battery Subsystem) 507, 508
_CRT (Critical Temperature) 540, 552	SEG (Segment) 367
CST (C States) 407	SRS (Set Resource Settings) 310
DDN (Device Name 264	STA (Status) 373
DIS (Disable) 278	_STR (String) 275
DMA (Direct Memory Access) 278	SUN (Slot User Number) 275
EDL (Eject Device List) 314	TC1 (Thermal Constant 1) 557
EJD (Ejection Dependent Device) 315	TC2 (Thermal Constant 2) 557
EJx (Eject) 316	TSP (Thermal Sampling Period) 559
_FDE (Floppy Disk Enumerate) 464	TZD (Thermal Zone Devices) 560
FIX (Fixed Register Resource Provider)	TZP (Thermal Zone Polling) 455, 486,
284	495, 560
GLK (Global Lock) 368	UID (Unique ID) 276
_HID (hardware ID) 264, 265, 507	ASL encoding 716
HOT (Hot Temperature) 552	ASL statements 689
_HPP (Hot Plug Parameters) 287, 291, 292	ASL, declaring 203
INI (Init) 363	control methods 204

definition 21	OperationRegion (Declare Operation Region)
device identification 261	206, 799
device insertion and removal 312	operator reference, ASL 740
device power resource 377	operator summary by type, ASL 736
dynamic 205	operator summary, ASL 732
EC-SMB-HC 596	operators, ASL 720
embedded controller interface 594	Or (Integer Bitwise Or) 801
floppy controller 464	organization, document 12
global scope 200	original equipment manufacturer See OEM
initialization 363	OS
Module Device 468	AML support, required 689
names, reserved 716	boot flags 126
Notify operator 235	compatibility requirements 11
OS-defined 253	defined object names 253
Power Resource 371	device power management 37
processor 405	drivers, embedded controller interface 573
reserved and predefined 242	functional fixed hardware implementation
revision data 257	104
Smart Battery 507	independent generic hardware 57
SMBus host controller 601	legacy hardware interaction 3
static 205	loading 643
thermal management 547	name object 257
unnamed 201	policy owner, device power management
objects See also control methods	869
ObjectType 689	power management 2
ObjectType (Get Object Type) 798	S4 Sleeping state transition 636
OEM implementation 3	transparent events 63
OEM-supplied control methods 386	OSPM
OFF 372	caches, flushing 638
off See Mechanical Off	cooling policy changes 535
ON 373	cooling preferences 51
One (Constant One Object) 799	device insertion and removal 313
Ones (Constant Ones Object) 799	event handlers 64
opcodes	exclusive controls 33
Type 1, AML 842	fixed hardware access 57
Type 2, AML 843	fixed hardware registers 83
Operating System See OS	functions 31
Operation Region data type, ASL 721, 725	general-event register access 95
Operation Region Field Unit data type, ASL	generic hardware model 58
720	Get Power Status 38
operation regions	goals 1
IPMI 208	hardware model 60
SMBus 599	implementation requirements 10

passive cooling 539	threshold values 541
performance states 43	Passive List (_PSL) object 553
PlaceNameplaceSet PlaceNamePower Pla-	PC Card controllers, power management 871,
ceTypeState operation 38	888
power management vs. performance 371	PC keyboard controllers 573
power state control 33	PCCARD 870
Real Time Clock Alarm (RTC) 80	PCI
resetting system 90, 91	BAR target operations 207
SMBus registration 602	bus number 367
thermal management 533	buses, address space translation 102
transitioning to sleeping states 632	Device Objects code 752
transitioning working to sleeping states 637	device power management 870
transitioning working to soft-off state 638	interrupt pins 304
Output Buffer Full (OBF) flag 577, 583	IRQ routing 305
output devices	power management 870
control methods 907	PCI configuration space 57
definition 896	PCI Interrupt Link device 241
switching 910	PCISIG 870
types of 899	PCMCIA 870
override, power button 76	PEC (packet error checking) 585, 600
P	Performance Control (_PCT) object 420
P_BLK 89	Performance Present Capabilities (_PPC) ob-
P_LVL2 89	ject 422
P_LVL3 90	performance states
P0 performance state, definition 29	definitions 29
P1 performance state, definition 29	device 43
Package (Declare Package Object) 801	Performance Supported States (_PSS) object
Package data type, ASL 721, 725	409, 415, 420, 424
packages	performance, energy conservation vs. 51, 371
definition 21	Persistent System Description Table (PSDT)
length 200	135
length encoding, AML 838	phones, answering
nested 778	modem example 40
packet error checking (PEC) 600	waking computer 42
parameters, ASL 723	PIC method 259
parent bits 64, 92	pins
parent objects, ASL statements 689	general event model 45
parentheses, AML notation 836	GPE 95
Passive (_PSV) object 535, 553	PlaceNameAddress PlaceTypeRange types
passive cooling	621
definition 50, 534	PlaceNameDevice PlaceNameSet PlaceTypeS-
preferences 51, 541	tate (_DSS) 908
processor clock throttling 539	PlaceNameGraphics PlaceTypeState, Query

(DGS) 908	port descriptors, I/O 328
PlaceNameSet PlaceNamePower PlaceTypeS-	Possible Resource Settings (_PRS) object 304
tate 38	POST Device control methods 902, 903
placeSOHO servers 126	power button
platform	ASL code example 75
implementation 6	control methods 75, 457
Platform Interrupt Source structure 143, 145	definition 22
Platform Management Interrupts (PMIs) 143	device ID 241
Plug and Play devices	dual-button model 74
ACPI control 43	fixed hardware 75
IDs 240, 262	functions 34
large resource items 331	object notification values 237
resource control method 276	override 76, 79
small resource items 325	single-button model 74
specifications 15	Power Consumer List (PCL) object 525
PM timer	power consumption
bits 88	device and processor performance states 29
function 64	global power states 25
idle time, determining 43	power loss
operations 73	Mechanical Off 60
register address 71	power management
register blocks 72	audio devices 872
PM1 Control registers	buses 870
addresses 70	COM port devices 874
bits 87	cooling, relationship to 51
blocks 72	definition 22
grouping 70, 86	desktop PCs 35
PM1 Enable registers 84	device 36, 872
PM1 Event registers	device objects 373
addresses 70	display devices 875
blocks 71	display standards 870
grouping 70, 83	goals 2
PM1 Status registers 83	input devices 882
PM2 Control registers	legacy 64
addresses 71	mobile PCs 34
bits 88	modem devices 884
blocks 72	modem example 39
PM2 Controller register grouping 70	multiprocessor PCs 35
PMIs 143	network devices 886
Pn performance state, definition 29	PC Card controllers 888
PNPBIOS 31	PCI 870
Polarity flags 140	PCMCIA 870
policy owner 869	performance states 43

performance vs. energy conservation 51,	power button 34
371	preferred PM profile system 125
preferred system types 125	Prepare to Sleep (_PTS) control method 387
servers 35	Process Call (SMBProcessCall) protocol 222,
setting device power states 38	611
storage devices 890	Processor (Declare Processor) 803
power management (PM) timer	processor and device performance states 29
function 64	processor control block 72
idle time, determining 43	processor control registers
operations 73	addresses 71
register address 71	bits 89
register blocks 72	Processor data type, ASL 721, 725
Power Resource data type, ASL 721, 725	processor device notification values 238
power resources	Processor devices 242
battery management 503	Processor Local APIC 138, 141, 163
child objects 372	Processor Local SAPIC 142
definition 22	processor LVL2 register 89, 398
device objects 377	processor LVL3 register 89, 398
devices, turning off 38	processor objects 405
isolation logic 41	processor See CPU
objects 371	Processor Throttling Control (_PTC) object
shared 42	412
wake system object 380	programming models
Power Source (_PSR) object 524	events 226
power sources	feature summary 66
AC adapter 524	fixed 56
definition 22	generic 57
object notification values 237, 239	protocol register (SMB_PRTCL) 585
power states	protocols
control methods 376, 377	BARs (Base Address Registers) 207
controlled by OSPM 33	CMOS 206
device 26	SMBus 588, 600, 607
global 24	Proximity (_PXM) object 277, 306
non-symmetric processor 399	PSDT 135
objects 376, 377	pseudocode language See AML
processor 397	pulsed interrupts 581
sleeping 27	PWRBTN_EN 86
transitioning 60	PWRBTN_STS 84
PowerResource (Declare Power Resource) 802	Q
predefined ACPI names 242	Query Embedded Controller (QR_EC) 580
preferences, user	query events 93
performance vs. energy conservation 51,	query value, definition 59
541	quotes

AML notation 835	Release terms 795
ASL notation 691	Remaining Battery Percentage 46, 519
QWord IO Resource Descriptor Macro 803	removal objects 312
QWord Memory Resource Descriptor Macro	removal, batteries 511
805	Remove (RMV) object 323
QWORD resource descriptor format 336, 805,	requirements, implementation
807, 808	OS 11
QWord Space Resource Descriptor Macro 807	OSPM 10
Ř	reserved ACPI names 242
Read Embedded Controller (RD_EC) 579	reserved bits
Read/Write Block (SMBBlock) protocol 610	definition 22
Read/Write Byte (SMBByte) protocol 220, 609	hardware 65
Read/Write Quick (SMBQuick) protocol 218,	PM1 Control registers 87
607	PM1 Enable registers 86
Read/Write Word (SMBWord) protocol 220,	PM1 Status register 84, 85
610	software requirements 103
reclaim memory 641	reserved object names 716
RefOf (Create Object Reference) 809	reserved SMBus protocol values 600
Region (_REG) control method 365	Reset (Reset an Event Synchronization Object)
register bits, notation 59	811
register blocks 69	reset register 90
register definitions, hardware 105	resource data types
Register Generic Register Descriptor Macro)	Address Space Resource Descriptors 336
809	control methods 324
register groupings	DMA 326, 330
definition 22, 68	End Dependent Functions 328
list of 69	end tag 331
registers	IRQ 325
BARs (Base Address Registers) 207	large 223, 226, 331
control 68	large vendor defined 333
EC-SMB-HC 584	memory range descriptors 332
embedded controller interface 577	small 324
enable 44	small vendor defined 330
fixed feature 20	Start Dependent Functions 327
fixed hardware 83	vendor defined 333
general-purpose event 20	resources
reset 90	allocation 310
SMB-HC 592	control method 276
status 44	interdependencies 327
virtual 210, 213, 214, 601, 606	resources, power See power resources
related device interference 65	ResourceTemplate Resource To Buffer Con-
Release (Release a Mutex Synchronization Ob-	version Macro) 811
ject) 810	restoring system context 635

results, storing 723	S4D object 384
Return (Return from Method Execution) 811	behavior during 392
Revision (Constant Revision Object) 812	definition 28
revision data object 257	implementation 635
RISC processors 336	low-level battery 48
RISC systems 34	waking using RTC 80
ROM control methods 902	S5 Soft-Off
Root System Description Pointer See RSDP	behavior during 636
Root System Description Table See RSDT	definition 24, 28
RSDP	properties 26
definition 22	transitioning to 638
location 107	SAPIC
table structure 107	definition 23
RSDT	I/O 21, 142
definition 22	local 21
table fields 112	NMI 141
RTC EN 86	Processor Local 142
RTC STS 85	SATA
RTC/CMOS protocols 206	controller device 463
S	saving system context
S0 State (Working) 390	during emergency shutdown 49
S1 Sleeping state	S4 Non-Volatile Sleep state 635
_S1D object 382	SBST 152
behavior during 390	SCI
definition 28	battery status information 38
implementation 633	definition 23
transitioning 388	embedded controller events 582
waking using RTC 80	enable bits 39
S2 Sleeping state	interrupt handlers 62, 82
_S2D object 383	SCI_EN 82, 83, 87
behavior during 391	Scope (Open Named Scope) 812
definition 28	SCSI, power management 870
implementation 634	Secondary System Description Table Sec
transitioning 388	SSDT
waking using RTC 80	Segment (_SEG) object 367
S3 Sleeping state	Send/Receive Byte (SMBSendReceive) proto-
_S3D object 383	col 219, 608
behavior during 391	separators, ASL 689
definition 28	Serialized methods 773, 793
implementation 634	server machines, power management 35
transitioning 388	Set Cooling Policy (SCP) control method 554
waking using RTC 80	Set POST Device (_SPD) 903
S4 Sleeping state	Set Resource Settings (_SRS) object 310

Set the Brightness Level (_BCM) 906	transitioning 33, 267, 268, 272, 388, 901
Set Timing Mode (_STM) control method 462	user settings 34
settings, user	waking using RTC 80
performance vs. energy conservation 51,	Slot User Number (_SUN) object 275
541	SLP_EN 87, 632
power button 34	SLP EN field 79
shareable interrupts 82	SLP_TYPx 87, 632
shared interface, embedded controller 574, 576	SLP TYPx field 68, 79
ShiftLeft (Integer Shift Left) 813	SLPBTN EN 86
ShiftRight (Integer Shift Right) 813	SLPBTN_STS 84
Short Vendor-Defined Resource Descriptor	small resource data type 324
macro 826	Smart Batteries
shutdown, emergency 48, 540	(SBS object 508
shutting down See Mechanical Off	definition 23
Signal (Signal a Synchronization Event) 814	device ID 241
signatures	multiple battery subsystem 509
collisions, avoiding 109, 110	single battery subsystem 509
interpreting 101, 112	SMBus data buffers 217, 606
values, storing 103	SMBus devices 603
single quotes	specifications 15
AML notation 835	status notification 506
ASL notation 691	subsystem 45, 503
SizeOf (Get Data Object Size) 814	supported 39
slave addresses, SMBus 505, 599	table 23
Sleep (Milliseconds Sleep) 814	table formats 152
sleep button	Smart Battery Charger
ASL code example 78	functions 506
control methods 77, 457	status notification 506
definition 23	Smart Battery Selector 507
device ID 241	Smart Battery System Manager
fixed hardware 77	functions 505
object notification values 238	status notification 507
support 77	SMB-HC 505, 510, 592
Sleeping states	SMBus
behavior during 390	address register (SMB_ADDR) 586
button logic 77	alarm address register
definitions 24, 27	(SMB_ALRM_ADDR) 587
entering 632	block count register (SMB_BCNT) 587
logic controlling 79	Block Write-Read Block Process Cal
objects 383	(SMBBlockProcessCall) protoco
packages, system state 387	223, 612
power consumption 25	commands, restricted 594
properties 25	data buffers 217, 606

data register array (SMB_DATA) 587	transitioning to 61, 638
definition 23	sources, power See power sources
device enumeration, enabling 602	SSDT 22, 135
device ID 241	Stall (Stall for a Short Time) 816
embedded controller interface 583	standards
encoding, bit 600	device power states 37
fields, declaring 212, 215, 604	Start Dependent functions resource descriptor
host controller notification header	format 327
(OS SMB EVT) 580	StartDependentFn Start Dependent Function
host controller objects, declaring 601	Resource Descriptor Macro) 816
interface 23	StartDependentFnNoPri Start Dependent
operation regions 599, 602	Function Resource Descriptor Macro) 817
PEC (packet error checking) 600	statements
Process Call (SMBProcessCall) protocol	ElseIf 760
222, 611	If 760
protocol register (SMB_PRTCL) 585	Power Resource 371
protocols 588, 600, 607	Processor 405
Read/Write Block (SMBBlock) protocol	statements, ASL 689
610	states See power states
Read/Write Byte (SMBByte) protocol 220,	static objects 205
609	Status (_STA) 373
Read/Write Quick (SMBQuick) 218, 607	Status (_STA) object 323
Read/Write Word (SMBWord) protocol	status bits
220, 610	corresponding enable bits 94
Send/Receive Byte (SMBSendReceive)	functions 92
protocol 219, 608	symbol 59
slave addresses 505, 599	status codes, SMBus 601
specifications 15	status notification, Smart Battery 506
status codes 601	status register 44
status register (SMB_STS) 584	status register (SMB_STS) 584
transactions 601	status, battery 38
virtual registers 601	sticky status bit, definition 59
SMBus devices 242	storage devices, power management 871, 890
SMI	Store (Store an Object) 817
definition 23	storing results, ASL operators 723
embedded controller firmware 581	Streamlined Advanced Programmable Inter-
interrupt events 62, 82	rupt Controller See SAPIC
SMM firmware 104	String (_STR) object 275
Soft-Off	String data type, ASL 721, 725
behavior during 393, 636	strings, ASL 717
definition 24, 28	Subtract (Integer Subtract) 818
properties 26	supplemental documentation 15
transitioning crashed systems to 75	surprise-style removal 313, 323

Switch (Select Code To Execute Based On Ex-	terminology
pression) 818	design guides 6, 8
switching, output devices 910	device power states 26
Sx states See Sleeping states	general 17
syntax	performance states 29
OperationRegion 208, 603	sleeping states 27
Power Resource statements 371	terms
syntax, ASL 689	AML 835
system context	ASL notation 690
definition 23	Thermal Constant 1 (_TC1) object 557
during emergency shutdown 49	Thermal Constant 2 (TC2) object 557
S4 Sleeping state 635	thermal management
sleep states lost in 28	control methods 547
System Control Interrupt See SCI	energy conservation, optimizing 51
system description tables See tables	notification of temperature changes 537
system events, general model 44	objects 547
system indicators 447	OSPM controlled 533
System Management Bus See SMBus	performance, optimizing 51
System Management Interrupt See SMI	polling 536, 538
System Management Mode See SMM	temperature changes, detecting 536
System Status (_SST) control method 447	threshold settings, dynamically changing
System Wake (_WAK) control method 394	535
T	trip points 537
tables	Thermal Sampling Period (_TSP) object 559
address format 104	thermal states, definition 24
compatibility 104	Thermal Zone data type, ASL 721, 725
DSDT 134	Thermal Zone Devices (_TZD) object 560
embedded controller boot resources 153	Thermal Zone Polling (_TZP) object 455, 486,
encoding format 103	495, 560
FACS 128	thermal zones
headers 100, 108	basic configuration 562, 566
MADT 136, 162, 187	examples 562, 566
overview 99	mobile PC example 49
RSDP 107	multiple-speed fan example 564
RSDT 112	object notification values 237
SBST (Smart Battery Description) 152	object requirements 562
signatures 109, 110	ThermalZone (Declare Thermal Zone) 820
SSDT 135	thirty-two bit fixed location memory range re-
Temperature (_TMP) control method 535, 558	source descriptor format 335
temperature changes, detecting 536	thirty-two bit memory range resource descrip-
temperature management See thermal manage-	tor format 333
ment	throttling 399, 412
Term Objects encoding, AML 839	THT_EN 89

Timer (Get 64-Bit Timer Value) 820	Unicode (String To Unicode Conversion Mac-
timers	ro) 825
global standby 64	Uninitialzed data type, ASL 720, 724
idle 64	Unique ID (_UID) object 276
power management (PM) 64, 73	Unload (Unload Definition Block) 826
TMR- field 74	unnamed objects 201
TMR_EN 86	unrelated device interference 65
TMR_STS 84, 438	upper case, ASL names 716
TMR_VAL 88	USB, power management 870, 871
ToBCD (Convert Integer to BCD) 821	user preferences
ToBuffer (Convert Data to Buffer) 821	performance vs. energy conservation 51,
ToDecimalString (Convert Data to Decimal	541
String) 822	power button 34
ToHexString (Convert Data to Hexadecimal	user-visible power states 33
String) 822	UUID (Convert String to UUID Macro) 823
ToInteger (Convert Data to Integer) 822	\mathbf{V}
token ring adapters See network devices	value-added hardware
top of memory 642	enabling OSPM 57
ToString (Convert Buffer To String) 823	registers 91
transactions, SMBus	Variable List 689
data buffers 217, 606	VCR-style ejection mechanism 313
status codes 601	vendor defined large resource descriptor for-
transitioning	mat 333
crashed systems 74, 75	vendor defined resource data types 333
device power states 870	vendor defined small resource descriptor for-
Legacy mode to ACPI 82	mat 330
power states 33, 60, 267, 268, 272, 901	VendorLong Long Vendor-Defined Descriptor
working to sleeping states 637	macro) 826
working to soft-off states 638	VendorShort Vendor Defined Resource De-
transparent events 63	scriptor Macro) 826
transparent switching, device power states 27,	VESA specifications 870
435	VGA 899, 902
trap monitors 64	video controllers, power management 875
Trigger Mode flags 140	Video Electronics Standards Associations (VE-
trip points, thermal 537	SA) 870
turning off See Mechanical Off	Video POST Options (_VPO) 903
TVs 899	virtual data objects 750
twenty-four bit memory range resource de-	virtual registers 210, 213, 214, 601, 606
scriptor format 332	visible states
Type 1 Opcodes, AML encoding 842	global system 24 W
Type 2 Opcodes, AML encoding 843 U	
	Walt (Wait for a Synchronization Event) 827
UARTs, power management 874	WAK_STS (Wake Status) 79, 85

wake frame events 888	definition 25
waking	properties 25
_WAK control method 394	transitioning to 60
audio devices 874	transitioning to Sleeping state 637
COM ports 875	transitioning to Soft-Off 638
device power resource object (_PRW) 380	workstations 125
devices 872	Write Embedded Controller (WR_EC) 579
disabling system-waking devices 381	write-only bits
display devices 880	control 59
initialization 638	definition 65
input devices 883	X
latency time 33, 267, 268, 272, 901	XOr (Integer Bitwise Xor) 832
lid switch 96	XSDT
logic controlling 79	definition 24
modem devices 886	loading Definition Block 787
modem example 42	location 100
network devices 887	${f Z}$
OS operations 39	Zero (Constant Zero Object) 832
PC Card controllers 890	Zero, One, Ones data type, ASL 721, 725
Real Time Clock Alarm (RTC) 80	zones, thermal See thermal zones
resetting lost enable bits 94	
storage devices 892	
warm insertion and removal 316	
warnings, battery 47	
WBINVD 638	
web sites	
Intel Architecture 15	
Microsoft 15	
PCISIG 870	
PCMCIA 870	
Smart Battery System 15	
SMBus specification 599	
USB-IF 871	
While (Conditional Loop) 827	
WORD resource descriptor format 342	
WordBusNumber (Word Bus Number Re-	
source Descriptor Macro) 828	
WordIO (Word IO Resource Descriptor Mac-	
ro) 829	
WordSpace (Word Space Resource Descriptor	
Macro) 831	
Working state	
behavior during 631	